

Description

Present invention is concerned with the decoding of a binary symbol sequence $\{a_n\}$ which appears at the output of a channel in modified form. In particular the invention is concerned with maximum-likelihood sequence estimation (MLSE) decoding of such a sequence which is received from communication channel or recording device whose intersymbol interference is of a partial-response class described by one of three polynomials $1+d$, $1-d$, or $1-d^2$. Major application areas are PCM transmission and magnetic recording.

Partial-response signaling allows a better handling of intersymbol interference and allows a more efficient utilization of the bandwidth of a given channel. In partial-response (PR) systems a controlled amount of intersymbol interference can be allowed. As the intersymbol interference then is known, the receiver can take it into account. PR signaling in communications allows transmissions at the Nyquist rate, and provides an attractive trade-off between error probability and the available spectrum. The partial-response systems described by the polynomials $1+d$, $1-d$, and $1-d^2$ are also called duobinary, dicode, and class-IV, respectively.

Maximum-likelihood sequence estimation, in particular the Viterbi algorithm, is an effective tool in receivers for improving the detection of symbol sequences in the presence of intersymbol interference. It was described e.g. in the articles by G.D. Forney "The Viterbi Algorithm", Proceedings of the IEEE, Vol. 61, No. 3, March 1973, pp. 268-278, and by G. Ungerböck "Adaptive maximum-likelihood receiver for carrier-modulated data-transmission systems", IEEE Transactions on Communications, Vol. COM-22, No. 5, May 1974, pp. 624-636. These articles also show some basic form of MLSE receivers or portions thereof.

The utilization of MLSE or Viterbi Algorithm in connection with partial-response signaling systems was already suggested by a publication of H. Kobayashi "Application of probabilistic decoding to digital magnetic recording systems", IBM Journal of Research and Development, Vol. 15, No. 1, January 1971, pp. 64-74.

The problem of maximum-likelihood sequence estimation can be stated as follows. Given a received sequence (z_n) , where n is an integer time index, choose from among all possible transmitted sequences (x_n) the one which is most likely to cause (z_n) to be received, i.e. choose (x_n) to maximize $p((z_n)|(x_n))$. The symbols of (x_n) are not detected independently of one another, rather they are detected "in context". Maximum likelihood sequence estimation can be done efficiently using the Viterbi algorithm, a form of dynamic programming. The Viterbi algorithm maintains a set of "survivor" sequences and a metric for each indicating the likelihood of that sequence. One property of these metrics is that their absolute values can grow without bound.

It is assumed that the channel synchronously transmits or records a sequence of binary symbols $a_n = +1$ or $a_n = -1$, with n being an integer symbol time index. The output signal is filtered and sampled so as to obtain values (y_n) with intersymbol interference of a partial-response class described by one of the three polynomials $1+d$, $1-d$, and $1-d^2$. A general description of partial-response signaling is given by P. Kabal et al. in "Partial Response Signaling", IEEE Transactions on Communications, Vol. COM-23, No. 9, September 1975, pp. 921-934. The meaning of the above polynomials is that the output sample y_n is obtained by multiplying the input sample a_n by the polynomial and adding noise. The symbol d is the delay operator: $da_n = a_{(n-1)}$. For example, $1-d$: $y_n = (1-d)a_n + r_n = a_n - a_{(n-1)} + r_n$, where r_n is the noise sample.

It is an object of present invention to devise a method and apparatus for reliably decoding a signal representing a sequence of time-discrete binary symbols received from a transmission channel or read in a recording device, which allow to reduce the necessary circuitry to a minimum and enable operation at high speed. It is a further object to generate tentative decisions with a minimum delay with respect to the time at which the signal representing the symbol is presented to the receiver.

The invention for achieving the desired improvements is defined in the claims.

The foregoing objects are satisfied in that the invention uses only two survivor sequences, and only the difference between the two metrics associated with these survivor sequences is computed and stored. Simplicity and efficiency results because less computing and storage resources are required to process the one difference metric that would have been required to process the two path metrics, and the difference metric cannot grow without bound as the path metrics can. Reliability results from the fact that the detected sequence is chosen by maximum-likelihood sequence estimation. It is the one most likely to cause the observed sequence of sampled values at the receiver. In the case of $1-d^2$ channel, interleaving and pipelining contribute to simplicity and speed of operation. The difference metric provides a convenient means of generating tentative decisions with very little delay. A limiter decision circuit can be used to facilitate the calculation of the difference metric and the survivor sequences.

The method steps include (a) partitioning the sample values y_n into two separate sequences having even and odd time indices n , respectively, if class-IV partial-response ($1-d^2$) is being used. In this case, the

remaining steps are applied to the even and odd sequences independently of each other. As each sample y_n is received, the operations performed include (b) recursively determining the new pair of survivor sequences and the new difference metric, and (c) producing tentative decisions and final decisions based on the stored survivor sequences and the sign of the difference metric.

5 Embodiments of the invention are described in the following with reference to the drawings.

The drawings show:

- Fig. 1 schematic survey of a transmission/recording system which is the environment for present invention,
- Fig. 2 impulse responses and transmission spectra of channels and filters in the system of Fig. 1,
- 10 Fig. 3 a schematic representation of the separate handling of interleaved sequences in the decoder,
- Fig. 4 trellis diagrams for consecutive states of the survivor sequences in the decoder,
- Fig. 5 block diagram of a first embodiment comprising circuitry for determining pairs of survivor metrics for two interleaved dicode sequences,
- Fig. 6 block diagram of a second embodiment comprising circuitry for determining survivor metric differences in a whitened matched filter receiver,
- 15 Fig. 7 block diagram of a third embodiment comprising circuitry for determining survivor metric differences in a matched filter receiver,
- Fig. 8 block diagram of a limiter-decision unit for the circuitry of Figs. 6 and 7,
- Fig. 9 block diagram of the shift register and selection circuitry for storage and updating of survivor sequences.
- 20

GENERAL FACTS AND THEORETICAL BACKGROUND

Partial-response signaling is a technique which enforces spectral properties by allowing a controlled amount of intersymbol interference. A survey of partial-response signaling is given in the above mentioned article by P. Kabal et al. With maximum-likelihood sequence estimation (MLSE), most partial-response schemes perform practically as well as a system without intersymbol interference, cf. the above-mentioned article by H. Kobayashi: "Application of probabilistic decoding to digital magnetic recording systems". Hence, no penalty has to be paid for the benefit of spectrum shaping, except for the higher complexity of the MLSE decoding hardware which performs the Viterbi decoding process.

30 Partial-response "class-IV" (PR-IV) signaling leads to spectral nulls at DC and at half of the signaling rate. PR-IV is therefore well suited for channels with baseband-like characteristics, which do not transmit DC. Magnetic recording channels are of this type and PR-IV is therefore regarded as a promising technique to achieve higher storage density in digital magnetic recording systems.

35 In the following, first the theory of MLSE for PR-IV signaling is reviewed.

In the next section, two types of MLSE receivers with identical performance are discussed, called the whitened-matched filter (WMF) version and the matched filter (MF) version. They differ in the receiver filters used before sampling the received signal at signaling rate, and in the computation of survivor metrics in the Viterbi decoding process.

40 In another section explaining basic invention features, it is shown that PR-IV sequences can be viewed as two "dicode" sequences which are interleaved, and that each dicode sequence can be decoded independently. For binary systems, as in saturation recording, the state-transition diagram of each dicode scheme exhibits then only two states. Instead of two survivor metrics it is possible to compute only one difference survivor metric.

45 In a further section, embodiments are disclosed which are digital implementations of Viterbi decoders utilizing pipelined handling of interleaved PR-IV sequences, some of them using difference survivor metrics. Simplicity and capability for operation at high speed is achieved by decoding the two dicode sequences in an interleaved and pipelined fashion. A dicode decoder is the same as the partial-response class-IV decoder with the interleaving and pipelining removed. A duobinary decoder is similar to a dicode decoder with the signs of certain quantities changed. The discussion focuses on the partial-response class-IV decoder. The changes necessary for the dicode and duobinary cases are given at the end of each section.

Survey of Transmission System:

55 Fig. 1 is a schematic representation of a transmission system in which present invention finds application.

A sequence of binary values $a_n = +1$ and $a_n = -1$ is transmitted at rate $1/T$ through a channel h . White noise $w(t)$ is added during transmission. $x(t)$ is the resulting continuous input signal of the receiver.

It should be noted that channel 11 can also be a magnetic recording device, that the white noise $w(t)$ is added during recording and reading, and that $x(t)$ is the output signal of a magnetic reading transducer. Signal $x(t)$ is applied to a receiver filter 13. For the present case, this may be either a Whitened Matched Filter WMF, or a Matched Filter MF, as will be explained later.

5 The filter output is a continuous signal $y(t)$ or $z(t)$, depending on the type of filter.

The filter output signal is sampled at regular intervals T by sampling means 15. The result is a sequence of time-discrete samples y_n or z_n , respectively.

These samples are furnished to a Viterbi decoder 17 in which they are used in a maximum likelihood sequence estimation (MLSE) process to obtain binary output values b_n with a given delay. Viterbi decoder 17 essentially comprises a section 19 for survivor metric determination and tentative selection of binary output values, and a section 20 for storage and updating of survivor sequences which allows final selection of the binary output values.

Present invention is concerned with the means for MLSE decoding contained in Viterbi decoder 17.

15 In the sequel, some theoretical explanations will be given prior to the detailed description of the invention and the selected embodiments.

PR-IV Signaling:

As shown in Fig. 1, PR-IV signaling results from sending a data sequence a_n at the rate $1/T$ through a channel whose response to an isolated input $a_n = +1$ is given by

$$25 \quad h(t) = \frac{\sin(\pi t/T)}{\pi t/T} - \frac{\sin[\pi(t-2T)/T]}{\pi(t-2T)/T} \quad (1)$$

30 In the frequency domain, this corresponds to the channel transfer characteristics

$$35 \quad H(f) = \begin{cases} T [1 - \exp(-j4\pi fT)] & , |f| < 1/2T, \\ 0 & \text{otherwise.} \end{cases} \quad (2)$$

At the output of the channel the received signal becomes

$$40 \quad x(t) = \sum_k a_k h(t-kT) + w(t) \quad (3)$$

45 where $w(t)$ is assumed to be additive wide-band white noise. The above description of a PR-IV transmission system applies as well to a magnetic recording system where in the case of saturation recording the data amplitudes are binary: $a_n = \pm 1$. Only a modest amount of equalization is required to shape the actual read signal into the form described by (1) and (3). In practice this equalization can be regarded as being combined with the further filtering required prior to signal sampling and detection.

50 The function $h(t)$ is shown in Fig. 2(a). The transmission characteristic of the channel is depicted in Fig. 2(c).

TWO MLSE RECEIVER VERSIONS

55 Two receiver versions for PR-IV signals are described. They are equivalent in that both perform true maximum-likelihood sequence estimation (MLSE). As mentioned above already, they differ in the receiver filters used.

The whitened-matched-filter (WMF) version is more commonly known. In the particular case of the

signal being given by (3), the WMF to be used as a receiver filter is just an ideal low-pass filter with cut-off frequency $1/2T$. Its transmission characteristic is shown in Fig. 2(d). The output of this filter is given by

$$y(t) = \sum_k a_k h(t-kT) + r(t) \quad (4)$$

where $h(t)$ was defined by (1) and has a shape as shown in Fig. 2(a), and $r(t)$ denotes white noise band-limited to $1/2T$.

For the matched-filter (MF) version, the receiver filter is matched to the channel characteristic given by (2) i.e., it has a characteristic as shown in Fig. 2(c). Thus, if causality is ignored, the receiver filter exhibits the transfer function

$$P(f) = \frac{1}{T} H(f) = \begin{cases} [1 - \exp(+j4\pi fT)], & |f| < 1/2T \\ 0 & \text{otherwise.} \end{cases} \quad (5)$$

The overall response of the channel and MF to an isolated input $a_0 = +1$ is then given by

$$s(t) = \frac{8T^3}{\pi t} \frac{\sin(\pi t/T)}{4T^2 - t^2} \quad (6)$$

and the signal observed at the output of the MF becomes

$$z(t) = \frac{1}{T} h(-t) * y(t) = \sum_k a_k s(t-kT) + p(t) \quad (7)$$

The noise $p(t)$ is band-limited to $1/2T$ and correlated. The function $s(t)$ is shown in Fig. 2(b). Sampling the outputs of the WMF and the MF at times nT , leads, respectively, to the sampled signals

$$y_n = a_n - a_{n-2} + r_n \quad (8)$$

$$z_n = -a_{n-2} + 2a_n - a_{n-2} + q_n = -y_{n-2} + y_n \quad (9)$$

The last equality in (9) expresses the fact that the MF output samples could also be obtained by digital filtering of the WMF output signals.

In the WMF case, the noise samples (r_n) are uncorrelated. The most-likely transmitted sequence ($\hat{a}_n$) is the binary sequence $a_n = \pm 1$ which minimizes

$$\sum_k \{y_k - (a_k' - a_{k-2}')\}^2 = \sum_k y_k^2 + a_k'^2 + a_{k-2}'^2 - 2[y_k(a_k' - a_{k-2}') + a_k' a_{k-2}'] \quad (10)$$

a_k' designates here an undetermined value. It may be either $+1$ or -1 . The most likely sequence ($\hat{a}_k$) for a

given sequence of received samples (y_k) is the one which when substituted for the a_k 's in equation (10) yields the minimum sum

$$y_k + a_k' + a_{k-2}'.$$

The squared terms of the right-hand side of (10) are identical for all sequences (a_n). Hence, minimization of (10) is equivalent to maximizing the cost function

$$J = \sum_k y_k a_k' - y_k a_{k-2}' + a_k' a_{k-2}'. \quad (11)$$

For the MF case an equivalent cost function is obtained by replacing in the term $y_k a_{k-2}'$ of (11) the index k by $k+2$, which does not change the result of the summation. Replacing then from (9) $y_k y_{k+2}$ by z_k leads to

$$J = \sum_k a_k' (z_k + a_{k-2}') \quad (12)$$

In the sequel, the following notation is used for the cost function:

$$J = \sum_k v_k(a_k', a_{k-2}') \quad (13)$$

where the auxiliary function v_k is defined as

$$v_k(a_k', a_{k-2}') = \begin{cases} y_k(a_k' - a_{k-2}') + a_k' a_{k-2}' & \text{WMF case,} \\ z_k a_k' + a_k' a_{k-2}' & \text{MF case.} \end{cases} \quad (14)$$

The sequence which maximizes J is determined by the Viterbi decoding algorithm.

BASIS OF INVENTION

Interleaving of Sub-Sequences (Dicode Sequences):

The cost function J can be rewritten as

$$J = J_E + J_O = \sum_{k \text{ even}} v_k(a_k', a_{k-2}') + \sum_{k \text{ odd}} v_k(a_k', a_{k-2}') \quad (16)$$

Hence its maximization can be carried out separately for J_E with respect to (a_k' , k even), and for J_O

with respect to $(a'_k, k \text{ odd})$.

As illustrated in Fig. 3, this point of view corresponds to treating PR-IV sequences characterized by the polynomial $1-d^2$, where d refers to a delay T , as two independent interleaved "dicode" partial-response sequences with polynomial $1-d$, where d refers to a delay of $2T$. (For an explanation of dicode sequences cf. above-mentioned article by P. Kabal et al.: "Partial-response signaling"). A Viterbi decoder operating in an interleaved fashion on the two dicode schemes requires for each scheme only two states.

Viterbi Decoding of Interleaved Dicode Sequences:

The Viterbi algorithm is now developed as it applies to one of the two interleaved dicode systems. Hence, in the following derivation indices are either even or odd. A general description of the Viterbi algorithm is given in the above-mentioned article by G. Forney: "The Viterbi algorithm", and in a publication by J.F. Hayes: "The Viterbi algorithm applied to digital data transmission", Communication Society Magazine, Vol. 13, March 1975, pp. 15-20.

The Viterbi algorithm for one dicode system is illustrated in Fig. 4. It determines in a two-state trellis diagram the sequence $\dots, \hat{a}_{n-2}, \hat{a}_n, \hat{a}_{n+2}, \dots$ which maximizes JE or JO as given by (13). This is accomplished by recursively computing for each time n two "survivor metrics"

$$J_n(a'_n) = \max_{(\dots, a'_{n-4}, a'_{n-2})} \sum_{k \leq n} v_k(a'_k, a'_{k-2}), \quad a'_n = +1, -1, \quad (17)$$

which represent the maximum cost up to time n , for an hypothesized last symbol $a'_n = +1$ and -1 , respectively. The optimum sequences resulting from (17) are called the "survivor sequences", denoted by

$$q_n(a'_n) = [\dots, \hat{a}_{n-4}(a'_n), \hat{a}_{n-2}(a'_n)], \quad a'_n = +1, -1 \quad (18)$$

The survivor metrics and associated survivor sequences are extended by the recursion

$$J_n(a'_n) = \max_{a'_{n-2} = +1, -1} \{J_{n-2}(a'_{n-2}) + v_n(a'_n, a'_{n-2})\}, \quad (19)$$

$$q_n(a'_n) = \{q_{n-2}[\hat{a}_{n-2}(a'_n)], \hat{a}_{n-2}(a'_n)\}, \quad a'_n = +1, -1, \quad (20)$$

where $\hat{a}_{n-2}(a'_n)$ is the value of a'_{n-2} which maximizes the right-hand side of (19). The recursion of survivor metrics for the WMF and MF version are explicitly given below.

WMF version:

$$J_n(+1) = \max[J_{n-2}(+1) + 1; J_{n-2}(-1) + 2y_{n-1}] \quad (21)$$

$$J_n(-1) = \max[J_{n-2}(+1) - 2y_{n-1}; J_{n-2}(-1) + 1] \quad (22)$$

MF version:

$$J_n(+1) = \max[J_{n-2}(+1) + z_n + 1; J_{n-2}(-1) + z_n - 1] \quad (23)$$

$$J_n(-1) = \max[J_{n-2}(+1) - z_{n-1}; J_{n-2}(-1) - z_n + 1] \quad (24)$$

Using Difference of Survivor Metrics:

5 The Viterbi decoding process for binary dicode sequences can be significantly simplified by considering not the pairs of explicit survivor metrics but only the difference between the survivor metrics, i.e.,

$$DJ_n = [J_n(+1) - J_n(-1)]/2. \quad (25)$$

10

From Fig. 4, it can be seen that four possible extensions of the survivor sequences are to be considered:

$$\begin{aligned}
 15 \quad (a) \quad \hat{a}_{n-2}(a'_n=+1) &= +1, \hat{a}_{n-2}(a'_n=-1) = +1 \Leftrightarrow \begin{array}{c} \circ \rightarrow \circ \\ \circ \rightarrow \circ \end{array} \\
 (b) \quad \hat{a}_{n-2}(a'_n=+1) &= +1, \hat{a}_{n-2}(a'_n=-1) = -1 \Leftrightarrow \begin{array}{c} \circ \rightarrow \circ \\ \circ \rightarrow \circ \end{array} \\
 20 \quad (c) \quad \hat{a}_{n-2}(a'_n=+1) &= -1, \hat{a}_{n-2}(a'_n=-1) = -1 \Leftrightarrow \begin{array}{c} \circ \rightarrow \circ \\ \circ \rightarrow \circ \end{array} \\
 (d) \quad \hat{a}_{n-2}(a'_n=+1) &= -1, \hat{a}_{n-2}(a'_n=-1) = +1 \Leftrightarrow \begin{array}{c} \circ \rightarrow \circ \\ \circ \rightarrow \circ \end{array}
 \end{aligned} \quad (26)$$

25

The corresponding path selections are indicated on the right.

30 Considering the above four cases, and observing (21) - (25), allows the determination of the following recursions for the difference survivor metrics:

WMF Version:

$$35 \quad DJ_n = \begin{cases} y_n + 1 & \text{if } +1 \leq (DJ_{n-2} - y_n) \\ DJ_{n-2} & \text{if } -1 < (DJ_{n-2} - y_n) < +1 \\ y_n - 1 & \text{if } (DJ_{n-2} - y_n) \leq -1 \end{cases} \quad \begin{array}{l} (a) \Leftrightarrow \\ (b) \Leftrightarrow \\ (c) \Leftrightarrow \end{array} \begin{array}{c} \circ \rightarrow \circ \\ \circ \rightarrow \circ \\ \circ \rightarrow \circ \end{array} \quad (27)$$

40

MF version:

45

$$50 \quad DJ_n = \begin{cases} z_n + 1 & \text{if } +1 \leq DJ_{n-2} \\ z_n + DJ_{n-2} & \text{if } -1 < DJ_{n-2} < +1 \\ z_n - 1 & \text{if } DJ_{n-2} \leq -1 \end{cases} \quad \begin{array}{l} (a) \Leftrightarrow \\ (b) \Leftrightarrow \\ (c) \Leftrightarrow \end{array} \begin{array}{c} \circ \rightarrow \circ \\ \circ \rightarrow \circ \\ \circ \rightarrow \circ \end{array} \quad (28)$$

55

The conditions in the above recursions reveal that extension (d) can never occur. The non-occurrence of this extension can be seen in Fig. 4. The theoretical background for the dicode (1-d) and the duobinary (1+d) systems is similar to that given in equations (1)-(28). The following summarizes the differences and gives the final results. The equations corresponding to (27) and (28) are directed to the dicode and

duobinary cases.

The processing of samples from a dicode channel is the same as the processing of the even (or odd) subsequence described for partial-response class-IV. The dicode versions of equations (8) through (28) are obtained by changing all occurrences of time indices $n+2$, $k+2$, $n-2$, and $k-2$, $n+1$, $k+1$, $n-1$, and $k-1$, respectively. Splitting into even and odd subsequences as described by equation (16) is omitted. The recursions for the survivor metrics corresponding to equations (27) and (28) are:

WMF Dicode Version:

$$DJ_n = \begin{cases} y_n + 1 & \text{if } -1 \leq (DJ_{n-1} - y_n) \\ DJ_{n-1} & \text{if } -1 < (DJ_{n-1} - y_n) < +1 \\ y_n - 1 & \text{if } (DJ_{n-1} - y_n) \leq -1 \end{cases} \quad \begin{matrix} (a) \Leftrightarrow \\ (b) \Leftrightarrow \\ (c) \Leftrightarrow \end{matrix} \quad \begin{matrix} \text{Diagram (a)} \\ \text{Diagram (b)} \\ \text{Diagram (c)} \end{matrix} \quad (27a)$$

MF Dicode Version:

$$DJ_n = \begin{cases} z_n + 1 & \text{if } +1 \leq DJ_{n-1} \\ z_n + DJ_{n-1} & \text{if } -1 < DJ_{n-1} < +1 \\ z_n - 1 & \text{if } DJ_{n-1} \leq -1 \end{cases} \quad \begin{matrix} (a) \Leftrightarrow \\ (b) \Leftrightarrow \\ (c) \Leftrightarrow \end{matrix} \quad \begin{matrix} \text{Diagram (a)} \\ \text{Diagram (b)} \\ \text{Diagram (c)} \end{matrix} \quad (28a)$$

The duobinary versions of equations (8) through (28) can be obtained from the dicode versions by changing the signs of certain terms. For example, (8) and (9) become:

$$y_n = a_n + a_{n-1} + r_n$$

$$z_n = a_{n+1} + 2a_n + a_{n-1} + p_n = y_{n+1} + y_n$$

The recursions for the difference survivor metrics for duobinary are:

WMF Duobinary Version:

$$DJ_n = \begin{cases} y_n + 1 & \text{if } -1 \geq (DJ_{n-1} - y_n) \\ -DJ_{n-1} & \text{if } +1 > (DJ_{n-1} - y_n) > -1 \\ y_n - 1 & \text{if } (DJ_{n-1} - y_n) \geq +1 \end{cases} \quad \begin{matrix} (a) \Leftrightarrow \\ (b) \Leftrightarrow \\ (c) \Leftrightarrow \end{matrix} \quad \begin{matrix} \text{Diagram (a)} \\ \text{Diagram (b)} \\ \text{Diagram (c)} \end{matrix} \quad (27b)$$

MF Duobinary Version:

$$DJ_n = \begin{cases} z_n + 1 & \text{if } -1 \geq DJ_{n-1} \\ z_n - DJ_{n-1} & \text{if } +1 > DJ_{n-1} > -1 \\ z_n - 1 & \text{if } DJ_{n-1} \geq +1 \end{cases} \quad \begin{matrix} (a) \Leftrightarrow \\ (b) \Leftrightarrow \\ (c) \Leftrightarrow \end{matrix} \quad \begin{matrix} \text{Diagram (a)} \\ \text{Diagram (b)} \\ \text{Diagram (c)} \end{matrix} \quad (28b)$$

EMBODIMENTS OF MLSE DECODERS

In the following section, embodiments of the Viterbi decoder or MLSE decoder 17 which incorporate the invention are described. As shown generally in Fig. 1, the Viterbi decoder consists of a first section 19 for determining survivor metrics and for obtaining intermediate and tentative values for the receiver output

signal, and a second section 21 for storing and updating the survivor sequences furnished by section 19, and for making the final selection of output values.

Three embodiments are disclosed for Section 19, in connection with Figs. 5, 6, and 7. A suitable implementation of a limiter-decision circuit used in the second and third embodiment will be disclosed with reference to Fig. 8. Finally, one implementation of section 21 is explained and shown in Fig. 9. Each of these embodiments is described first for the partial-response class-IV channel. The modifications necessary to convert them to dicode and duobinary are described at the end.

It should be noted that the digital circuitry discussed in the following generates binary output quantities which assume either value 0 or 1, and are therefore designated as " b_n " or " $\hat{b}_n$ ". In the previous discussion, the signal elements were amplitudes which assume either value +1 or -1, and they were designated as " a_n " or " $\hat{a}_n$ ".

The transition from one form to the other is formally given below in equations (29) and (30).

First Embodiment - Circuitry for Determining Two Survivor Metrics:

In Fig. 5, an embodiment of section 19 of the Viterbi decoder is shown which determines two survivor metrics for the two states of the decoder, and which furnishes intermediate values b_{n-5}^+ , b_{n-5}^- and a tentative output value $\hat{b}_{n-4}$ for further handling in section 21. This circuitry is suited for both, the WMF case and the MF case and implements the function given in equation (19).

It comprises V unit 25 which computes for an applied input value y_n or z_n , the value of auxiliary function v_n (a'_n , a'_{n-2}) according to either equation (14) or (15). Values a'_n and a'_{n-2} , which are assumed received amplitude values, can both be +1 as well as -1 so that V unit 25 for each input value furnishes four output values which are stored in clocked registers 27, 29, 31, and 33. These v_n values can be considered metric increments because they have to be added to the survivor metrics previously accumulated.

Four adders 35, 37, 39, and 41 are provided for adding the contents of registers 27...33, i.e. the four previously stored values of v_{n-1} , and two previously determined metric values J_{n-3} , as required by equation (19). The results are stored in clocked registers 43, 45, 47, and 49 respectively. For determining the maximum value for each pair of register contents, two subtractors 51 and 53 are provided. They determine the sign bit of the difference of the respective pair of values, and furnish these as binary values b_{n-4}^+ and b_{n-4}^- to two flipflop circuits 55 and 57. Previously stored contents of these two flipflops represent the two intermediate values b_{n-5}^+ and b_{n-5}^- , which are furnished on lines 59 and 61 as output values of section 19.

The formal relationship between decoded values $\hat{a}_{n-5}$ and the actual binary output values $\hat{b}_{n-5}$ is as follows:

$$b_{n-5}^{\pm} = \begin{cases} 1 & \text{for } \hat{a}_{n-5}(\pm 1) = +1 \\ 0 & \text{for } \hat{a}_{n-5}(\pm 1) = -1 \end{cases} \quad (29)$$

With the aid of multiplexers or gating circuits 63 and 65, the sign bits available at the outputs of subtractors 51 and 53 select the maximum of each pair of values stored in registers 43/45 and 47/49, respectively and furnish the resulting two values as metric values $J_{n-2}(+1)$ and $J_{n-2}(1)$ to clocked registers 67 and 69. The previously stored values in these registers, $J_{n-3}(+1)$ and $J_{n-3}(1)$, are on one hand furnished to adders 35...41 as was previously mentioned. On the other hand, they are furnished to a subtractor 71 which on its output delivers the sign bit of the difference DJ_{n-3} . This sign bit is complemented in inverter circuit 73 and the result is transferred as binary value $\hat{b}_{n-3}$ to flipflop circuit 75. The previously stored contents of this flipflop represents the tentative decoder output value $\hat{b}_{n-4}$ which is furnished on line 79 as the third output value of section 19.

The formal relationship between survivor metrics J_{n-4} and the tentative binary output values $\hat{b}_{n-4}$ is as follows:

$$\hat{b}_{n-4} = \begin{cases} 1 & \text{for } J_{n-4}(+1) \geq J_{n-4}(-1) \\ 0 & \text{otherwise.} \end{cases} \quad (30)$$

It should be noted that the survivor metrics are not normalized but are allowed to wrap around the maximum values in their two's complement representation. With a sufficient word length, the add and subtract operations will still produce correct results.

At the bottom of Fig. 5, boxes with indices are shown which illustrate the fact that the circuitry has separate stages. Each of the double vertical lines indicates where the circuitry comprises storage units that separate stages. At any time, each section contains only values either with even indices or with odd indices. At each clock time, the whole contents is shifted from one stage to the next for further processing, but no mixing between odd and even indexed values occurs.

This shows that in the whole circuitry, two sub-sequences with odd and even indices, respectively, are handled completely separately as indicated in Fig. 3, but in an interleaved and pipelined manner. Nevertheless, the sequence of input values and the sequence of output values are continuous, i.e. they need not be expressly separated into two sub-sequences because this splitting occurs automatically within the circuit of Fig. 4 due to the separation of stages by clocked storage units, and due to suitable feedback between stages.

Second Embodiment - Circuitry Determining Difference Survivor Metric for WMF Version:

Fig. 6 shows an embodiment of section 19 of the Viterbi decoder which does not explicitly determine the two survivor metrics but only their difference. This second embodiment is suited for the WMF (whitened matched filter) version of the receiver, i.e. the version producing receiver samples y_n (equation 8). The circuitry implements equation (27).

The quantity shown next to each line in Fig. 6 indicates the number of bits transferred on that line in parallel. In the absence of noise, the samples y_n can assume three possible values, i.e. levels -2, 0, +2 (see equation 8). Thus, if the range $-4 \leq y_n < +4$ should be covered, and intervals between adjacent levels are divided into 2^L sublevels, $L + 2$ bits are required to represent y_n in a two's complement representation.

For soft decoding, the value for L should be chosen between 2 and 4.

An important portion of the circuitry of Fig. 6 is the limiter-decision unit 81. With the aid of this unit, intermediate values b_k^+ and b_k^- (as defined in equation 29) are obtained with shorter processing delay. Limiter-decision unit 81 generates from an input sample P_k an output sample Q_k and intermediate values b_k^+ and b_k^- in accordance with the following rule:

- (a) $(Q_k = +1, b_k^+ = 1, b_k^- = 1)$ if $+1 \leq P_k$
 (b) $(Q_k = P_k, b_k^+ = 1, b_k^- = 0)$ if $-1 < P_k < +1$
 (c) $(Q_k = -1, b_k^+ = 0, b_k^- = 0)$ if $P_k \leq -1$ (31)

Limiter-decision unit 81 can be implemented either as a read-only store (ROS), as a programmable logic array (PLA), or by discrete logic. An example is shown in Fig. 8 and will be explained later.

Referring again to Fig. 6, an input value y_n is stored in clocked register 83 and also furnished to one input of subtractor 85. The other input of subtractor 85 receives a previously obtained survivor metric difference value DJ_{n-2} which is stored in clocked register 87. The output of subtractor 85 is sample P_{n-2} which indicates in which of three regions the difference falls, i.e. whether the first, second, or third condition of equations (27) and (31) applies. The output value Q_{n-2} of limiter-decision unit 81 is stored in a clocked register 89. Contents of registers 83 and 89 are added in adder 91 to obtain a new survivor metric difference value DJ_{n-1} in accordance with equation (27), which is then stored in register 87.

Limiter-decision unit 81 also furnishes the two binary intermediate values b_{n-2}^+ and b_{n-2}^- which are stored in flipflop 93 and 95, respectively. Previously stored binary intermediate values b_{n-3}^+ and b_{n-3}^- are available on output lines 59a and 61a, which also constitute two of the outputs of the whole circuitry of Fig. 6.

One output line of adder 91, i.e. the one carrying the sign bit, is connected to an inverter 97 which complements the sign of DJ_{n-1} . This complement is the tentative output value $\hat{b}_{n-1}$ which is stored in flipflop

99. The previously stored tentative output value $\hat{b}_{n-2}$ is available on line 79a which constitutes the third output of the whole circuitry.

Similar as for Fig. 5, also at the bottom of Fig. 6 boxes with indices are shown. These boxes indicating separate stages and intermediate clocked storage units also illustrate the interleaved and pipelined handling of two sequences of alternating samples. A comparison between Fig. 5 and Fig. 6 reveals that less stages are required for the circuitry of Fig. 6, thus it has less delay and needs less hardware.

Third Embodiment - Circuitry Determining Difference Survivor Metrics for MF Version:

10 A third embodiment of section 19 of the Viterbi decoder is illustrated in Fig. 7. It also directly determines the survivor metric difference value DJ_k . The third embodiment is suited for the MF (matched filter) version of the receiver, i.e. it operates with receiver samples z_n as defined in equation (9), and it implements equation (28).

15 In the MF case, sample values z_n assume (without noise) the five levels -4, -2, 0, +2, +4 in accordance with equation (9). Thus, assuming again 2^L sublevels, $L+3$ bits are needed to represent z_n in the range $-8 \leq z_n < +8$.

The circuitry of Fig. 7 comprises the same limiter-decision unit as the circuitry of Fig. 6. Here, this unit has reference number 81a (detailed embodiment shown in Fig. 8). The output sample Q_{n-1} of unit 81a is stored in clocked register 101. Adder 103 is provided to combine the previous sample Q_{n-2} from register 20 101 and the input value z_n to obtain a new survivor metric difference value DJ_n which is to be stored in clocked register 105. The previous survivor metric difference DJ_{n-1} is furnished from register 105 directly to the input of limiter-decision unit 81 as sample P_{n-1} .

Two outputs of limiter-decision unit 81 furnish the binary intermediate values b_{n-1}^+ and b_{n-1}^- which are stored in flipflop 107 and 109, respectively.

25 Contents of these flipflops are furnished as intermediate values b_{n-2}^+ and b_{n-2}^- on output lines 59b and 61b, respectively. The sign bit output line of adder 103 is connected to inverter 111 which complements the sign of DJ_n and furnishes tentative output value $\hat{b}_n$. The latter is stored in flipflop 113. The previously stored binary value $\hat{b}_{n-1}$ is furnished from flipflop 113 to output line 79b. The output lines 59b, 61b, and 79b are connected to the inputs of the survivor sequence storage and updating section 21 shown in Fig. 9, as will be explained later.

30 The blocks at the bottom of Fig. 7 with indices inserted illustrate also for this case the different stages of the circuitry separated by clocked storage units, which enable the pipelined and interleaved processing of the two dicode sub-sequences.

A comparison of Figs. 5, 6, and 7 immediately reveals that among the three metric-computation schemes presented, the MF version with difference metric calculation (Fig. 7) offers the lowest circuit complexity, capability of operation at highest signaling rate (from a circuit delay consideration), and shortest delay in producing binary decision values.

Another advantage of the second and third embodiments over the first is that the difference metric is automatically normalized. Equations (27) and (28) show that it does not accumulate as the individual survivor metrics do. There is no need to provide extra word length to allow for wrap around.

Limiter-Decision Unit:

45 Fig. 8 shows an embodiment of limiter-decision unit 81/81a for the case $L=4$ comprising discrete logic circuits. As mentioned previously, this unit implements equation (31).

It has eight inputs for the eight bits of a sample P_k which is presented in binary two's complement notation (most significant bit $P_{k,4}$ in the position having value 2^4 , least significant bit $P_{k,3}$ in the position having value 2^{-3}). Similarly, five outputs are provided for the five bits of a sample Q_k in binary two's complement notation ($Q_{k,1}$ is most significant bit in position having value 2^1 , $Q_{k,3}$ is least significant bit in position having value 2^{-3}). Furthermore, two outputs for binary intermediate values b_k^+ and b_k^- are provided.

50 The five input lines for the most significant bits of P_k (integer portion) are connected to the inputs of a first NOR circuit 115 and also through a group of inverters 117 to the inputs of a second NOR circuit 119. The three input lines for the least significant digits of P_k (fractional portion) are connected through a group of inverters 121 to the inputs of a NAND circuit 123 and to the inputs of a group of three NOR circuits 125. The outputs of NOR circuits 115 and 119 are combined in a NOR circuit 127, and the outputs of NOR circuit 119 and NAND circuit 123 are combined in a NAND circuit 129.

The two output lines for the most significant digits of Q_k (integer portion) are connected directly to the

most significant input line of P_k and through an inverter 131 to the output of NOR circuit 115, respectively. The three output lines for the least significant bits of Q_k (fractional portion) are connected to the outputs of the three NOR circuits 125 whose second inputs are connected to the output of NOR gate 127.

The output line for the first binary intermediate value b_k^+ is connected through a NAND circuit 133 directly to the output of NAND circuit 129 and to the input line of the most significant P_k bit, and the output line for the second binary intermediate value b_k^- is connected through a NOR circuit 135 directly to the output of NOR circuit 115 and also to the input line of the most significant P_k bit.

Circuitry for Storage and Updating of Survivor Sequences:

10

Details of section 21 of the Viterbi decoder 17, for the storage and updating of survivor sequences are shown in Fig. 9. It consists essentially of two shift registers 137 and 139 each comprising $2m-1$ flipflop stages arranged in sequence. Every second flipflop is connected to its successor through a multiplexer or gating circuit that allows to selectively transfer to the successor flipflop either the bit from the preceding flipflop stage of the same shift register or the bit from the corresponding flipflop stage of the other shift register. The control inputs of all multiplexers/gating circuits of one shift register are commonly connected to the input of the respective shift register, i.e. the binary value of the bit just inserted into the first stage of a shift register also determines the selections made by all multiplexers/gating circuits of the respective shift register.

The output flipflop stages of both shift registers are connected to an additional multiplexer/gating circuit 141 which is controlled by a binary signal on selection control line 143. The output value of multiplexer/gating circuit 141 is stored in a final flipflop stage 145 having output line 147 for finally selected output bits $\hat{b}_{j-2m-1}$.

As shown in Fig. 9, inputs of the two shift registers 137 and 139 are connected to the two intermediate value outputs (b_{j-1}^+) and (b_{j-1}^-) of section 19, i.e. output lines 59/59a/59b and 61/61a/61b of Figs. 5 or 6 or 7, respectively. Selection control line 143 is connected to the tentative output value line ($\hat{b}_j$) of section 19, i.e. output line 79/79a/79b of Figs. 5 or 6 or 7, respectively.

Operation is as follows: The two shift registers store the two binary sequences which have the highest probability of being similar to the transmitted sequence a_n . Each sampling time two new intermediate values b_{j-1}^+ and b_{j-1}^- appear which are inserted into the two shift register inputs and control the multiplexer selections during shifting of the two shift registers, thereby updating the stored survivor sequences and thus improving their likelihood with respect to the actually transmitted sequence of binary values a_n . Of the two oldest bits leaving the shift registers, only one is selected each sampling time by the newest tentative output value $\hat{b}_j$ appearing at the output of section 19 and thus on selection control line 143.

The finally selected bits are furnished sequentially on line 147 which is the output line of the whole Viterbi decoder 17.

Section 21 shown in Fig. 9 has an additional portion 149 for providing a sequence of tentative output values which are required for timing recovery and gain control in the receiver. This section comprises an additional group of $2m-1$ flipflops, each corresponding to one flipflop stage in the two shift registers 137 and 139 (except the last stage). The flipflops are arranged in pairs as shown, and the input of each pair (except the first one) is connected to a multiplexer/gating circuit whose two inputs are connected to the output of an associated flipflop stage in the first (137) and second (139) shift register, respectively.

The control inputs of all multiplexers in portion 149 as well as the input to the first pair of flipflops are connected to control line 149, i.e. to output line 79 (or 79a, 79b) of survivor metric section 19. Thus, the outputs of all flipflops in portion 149 together with the output of flipflop 145 deliver, at each sampling time, a sequence of tentative output values $\hat{b}_j, \hat{b}_{j-1}, \dots, \hat{b}_{j-2m-1}$ which is not equal but already very similar to the final output sequence appearing sequentially on line 147. It is available, however, much earlier than the final output sequence and thus much more useful for timing and gain control required at the input of the receiver.

As was mentioned earlier, indices j and $j-1$ at the inputs of Fig. 9 correspond to indices $n-4$ and $n-5$ at the outputs of Fig. 5, to indices $n-2$ and $n-3$ at the outputs of Fig. 6, and to indices $n-1$ and $n-2$ at the outputs of Fig. 7, respectively. Thus, in Fig. 9, the index j can be replaced by $n-4$, $n-2$, or $n-1$, depending on whether the binary decision values b_{j-1}^+ , b_{j-1}^- , and $\hat{b}_j$ originate from the circuitry of Fig. 5, Fig. 6, or Fig. 7, respectively.

If circuit delay permits, the single-bit registers (flipflops) 55/57/75, 93/95/99, and 107, 109, 113 which in Figs. 5, 6 and 7 buffer the output values can be omitted, thus reducing processing delay by one signaling period. Similar simplifications are also possible in connection with deriving tentative decisions from portion 149 and the final decision, if circuit delay is not critical in the further operations performed with these

signals.

Embodiments for Dicode and Duobinary Channels

- 5 The partial-response class-IV embodiments described above can be converted to dicode embodiments by removing the registers and flipflops used for interleaving and pipelining. Removing a register or flipflop means deleting it from the circuit and connecting its inputs directly to their corresponding outputs. The elements to be removed are 43, 45, 47, and 49 in FIG. 5 with elements 83, 89 in FIG. 6, 101 in FIG. 7 and 151, 153, 155, 157, 159, 161, 163, and 165 in FIG. 9. The dicode embodiments can be converted to
 10 duobinary embodiments by the following modifications. The "V unit" 25 in FIG. 5 should generate an output according to the duobinary versions of equations (14) and (15):

$$16 \quad V_k(a'_k, a'_{k-1}) = \begin{cases} y_k(a'_k + a'_{k-1}) - a'_k a'_{k-1} & \text{WME (14b)} \\ z_k a'_k - a'_k a'_{k-1} & \text{MF (15b)} \end{cases}$$

- 20 Subtractor 85 in FIG. 6 should be changed to an adder, and adder 91 should be changed to a subtractor. The designations of 61a and 59a should be interchanged. Further, the adder in FIG. 7 should be changed to a subtractor. The designation 61b and 59b should also be interchanged.

25

30

35

40

45

50

55

TABLE OF SYMBOLS USED

		<u>Value Range</u>	<u>Time Relation</u>
5		a= discrete amplitude	
		b= binary	
		c= continuous	
10		s= sampled	
	a_n	transmitted value	a
	$x(t)$	received signal	c
15	$y(t)$	filtered receiver signal (WMF)	c
	$z(t)$	filtered receiver signal (MF)	c
20	y_n	receiver sample value	c
	z_n	receiver sample value	c
	$\hat{a}'_n$	assumed receiver value	a
25	$\hat{a}_n$	final decided receiver output value	a
	b_n^+	intermediate output value (for $\hat{a}'_n = +1$ or $\hat{a}'_n = -1$)	b
30	$\hat{b}_n$	final decided receiver output value	b
	J_n	survivor metric, cost factor	c
35	DJ_n	difference of two sur- vivor metrics	c
	P_k	auxiliary quantity	c
40	Q_k	auxiliary quantity	c
	V_k	auxiliary quantity	c
45	$h(t)$	transmission characteristic (channel or filter)	
	$s(t)$	transmission characteristic (filter)	
	T	signaling/sampling period	
50	L	defines the number 2^L of sublevels between receive signal levels	

Claims

55

1. A method of maximum-likelihood sequence decoding of the output signal of a communication or recording device channel, said channel synchronously transmitting or recording a sequence of binary symbols $a_n = +1$ or -1 , n being an integer symbol time index, said output signal being filtered and

sampled to obtain samples y_n with intersymbol interference of the partial-response classes described by the polynomials $1 + d$, $1 - d$, or $1 - d^2$, the method determining from the samples y_n the most likely transmitted or recorded sequence of binary symbols, said method being executable on a decoder of the type having a memory for storing binary valued indicia of state transitions underlying said decoding method, characterized by the steps of:

recursively computing a difference metric at each sampling instant, which metric represents the difference between implicit survivor metrics, each implicit survivor metric indicating the probability of occurrence of the binary survivor sequence obtained and stored in the decoder memory; and

generating two binary symbol decisions and using these to extend the binary survivor sequences stored in the path memory, the sign of the difference metric determining at each sampling instant which one of the survivor sequences currently stored in the path memory is the more probable sequence from which the output of the decoder is to be selected.

2. A method according to claim 1, for maximum-likelihood sequence decoding of sample signals with intersymbol interference of the partial-response class-IV type being described by polynomial $1-d^2$, characterized in that the two sequences of even and odd indexed samples y_n are independently decoded based upon independent state transition diagrams with two states at each sampling instant.

3. Apparatus for maximum-likelihood sequence decoding of sample sequences with intersymbol interference of the partial-response class-IV type described by polynomial $1-d^2$, said apparatus having a whitened match filter (13), sampling means (15), and survivor sequence storage and updating means (21), characterized by metric value determining circuitry (19; Fig. 6) which comprises:

means (91) for adding a recent sample value (y_{n-1}) and the range limited difference of said recent sample value (y_{n-1}) and a previous difference survivor metric (DJ_{n-3}), and for delivering a new difference survivor metric (DJ_{n-1});

means (85) for subtracting a new sample (y_n) from a recent difference survivor metric (DJ_{n-2});

means (81) for limiting the output of the subtracting means (85) to a range between +1 and -1 and for generating two intermediate binary decision values (b_{n-2}^+ and b_{n-2}^-);

means (97) connected to the output of said adding means (91) for generating a binary output value ($\hat{b}_{n-1}$) representing the sign of the new difference survivor metric (DJ_{n-1}).

4. Apparatus according to claim 3, characterized in that the inputs of said adding means (91) are connected through clocked registers (83, 89) to a sample input (y_n) and to the output of the limiting means (81), respectively, the inputs of said subtracting means (85) are connected to said sample input (y_n) and, through a clocked register (87), to the output of said adding means, respectively, so that output values can be generated for even and odd indexed sample values independently in a pipelined process.

5. Apparatus for maximum-likelihood sequence decoding of sample sequences with intersymbol interference of the partial-response class-IV type described by polynomial $1-d^2$, said apparatus having a matched filter (13), sampling means (15), and survivor sequence storage and updating means (21), characterized by metric value determining means (19; Fig. 7) which comprises:

means (103) for adding a new sample value (z_n) and a range limited previous difference survivor metric (DJ_{n-2}), and for delivering a new difference survivor metric (DJ_n);

means (81a) for limiting the value of a recent difference survivor metric (DJ_{n-1}) to a range between +1 and -1 and for generating two intermediate binary decision values (b_{n-1}^+ and b_{n-1}^-); and

means (111) connected to the output of said adding means (103) for generating a binary output value ($\hat{b}_n$) representing the sign of the new difference survivor metric (DJ_n).

6. Apparatus according to claim 5, characterized in that the inputs of said adding means (103) are connected to a sample input (z_n) and, through a clock register (101), to the output of said limiting means (81a), respectively, and said the output of said adding means (103) is connected through a clock register (105) to the input of said limiting means (81a), so that output values can be generated for even and odd indexed sample values independently in a pipelined process.

Revendications

1. Procédé de décodage de la séquence à probabilité maximale du signal sortant d'un canal de communication ou d'un dispositif d'enregistrement, ledit canal transmettant ou enregistrant de façon synchrone une séquence de symboles binaires $a_n = +1$ ou -1 , n étant un indice de temps de symbole entier, ledit signal de sortie étant filtré et échantillonné pour obtenir des échantillons y_n ayant une interférence entre symboles des classes à réponse partielle décrite par les polynômes $1 + d$, $1 - d$, ou $1 - d^2$, le procédé déterminant à partir des échantillons y_n la séquence de symboles binaires la plus probablement transmise ou enregistrée, ledit procédé pouvant être exécuté dans un décodeur du type ayant une mémoire pour emmagasiner des indices à valeur binaire de transitions d'états fondamentales dans ledit procédé de décodage, caractérisé par les étapes de:
 - calcul par récurrence d'une métrique de différence à chaque instant d'échantillonnage, laquelle métrique représente la différence existant entre des métriques survivantes implicites, chaque métrique survivante implicite indiquant la probabilité d'apparition de la séquence survivante binaire obtenue et emmagasinée dans la mémoire du décodeur; et
 - génération de deux décisions de symboles binaires et utilisation de celles-ci pour étendre les séquences survivantes binaires emmagasinées dans la mémoire d'acheminement, le signe de la métrique de différence déterminant à chaque instant d'échantillonnage quelle est, parmi les séquences survivantes alors emmagasinées dans la mémoire d'acheminement, la séquence la plus probable à partir de laquelle doit être sélectionnée la sortie du décodeur.
2. Procédé selon la revendication 1, pour le décodage de la séquence à probabilité maximale de signaux échantillons ayant une interférence entre symboles du type de classe IV décrite par le polynôme $1 - d^2$, caractérisé en ce que les deux séquences d'échantillons indexés pairs et impairs y_n sont décodées de façon indépendante sur la base des diagrammes de transitions d'états indépendants avec deux états à chaque instant d'échantillonnage.
3. Dispositif pour le décodage de la séquence à probabilité maximale de séquences d'échantillons avec une interférence entre symboles du type de classe IV à réponse partielle décrite par le polynôme $1 - d^2$, ledit dispositif ayant un filtre d'adaptation "blanc" (13), des moyens d'échantillonnage (15), et des moyens d'emmagasinage et de mise à jour des séquences de métriques survivantes (21), caractérisé par des circuits de détermination des valeurs des métriques (19, Fig.8) qui comprennent:
 - des moyens (91) pour additionner une valeur d'échantillon récente (y_{n-1}) et la différence de gamme limitée entre ladite valeur d'échantillon récente (y_{n-1}) et une métrique survivante de différence précédente (DJ_{n-3}), et pour produire une nouvelle métrique survivante de différence (DJ_{n-1});
 - des moyens (85) pour soustraire un nouvel échantillon (y_n) d'une métrique survivante de différence récente (DJ_{n-2});
 - des moyens (81) pour limiter la sortie des moyens de soustraction (85) à une gamme allant de $+1$ à -1 et pour engendrer deux valeurs de décisions binaires intermédiaires (b_{n-2}^+ et b_{n-2}^-);
 - des moyens (97) connectés à la sortie desdits moyens d'addition (91) pour engendrer une valeur de sortie binaire ($\hat{a}_{n-1}$) représentant le signe de la nouvelle métrique survivante de différence (DJ_{n-1}).
4. Dispositif selon la revendication 3, caractérisé en ce que les entrées desdits moyens d'addition (91) sont respectivement connectées, par des registres synchronisés (83, 89) à une entrée d'échantillons (y_n) et à la sortie des moyens de limitation (81), les entrées desdits moyens de soustraction (85) sont respectivement connectées à ladite entrée d'échantillons (y_n) et, par un registre synchronisé (87), à la sortie desdits moyens d'addition, de sorte que les valeurs de sortie puissent être engendrées indépendamment comme valeurs d'échantillons indexés paires et impaires, dans un procédé à enchevêtrements.
5. Dispositif de décodage de la séquence à probabilité maximale des séquences d'échantillons ayant une interférence entre symboles du type de classe IV à réponse partielle décrite par le polynôme $1 - d^2$ ledit dispositif ayant un filtre d'adaptation (13), des moyens d'échantillonnage (15), et des moyens d'emmagasinage et de mise à jour de séquence survivante (21), caractérisé par des moyens de détermination de valeurs métriques (19; fig.7) qui comprennent:
 - des moyens (103) pour additionner une valeur d'échantillon nouvelle (z_n) et une métrique survivante de différence précédente, à gamme limitée (DJ_{n-2}), et pour produire une nouvelle métrique survivante de différence (DJ_n);
 - des moyens (81a) pour limiter la valeur d'une métrique survivante de différence récente (DJ_{n-1}) à

une gamme allant de $+1$ à -1 et pour engendrer deux valeurs de décisions binaires intermédiaires (b_{n-1}^+ et b_{n-1}^-); et

des moyens (111) connectés à la sortie desdits moyens d'addition (103) pour engendrer une valeur de sortie binaire ($\hat{b}_n$) représentant le signe de la nouvelle métrique survivante de différence (DJ_n).

5

6. Dispositif selon la revendication 5, caractérisé en ce que les entrées desdits moyens d'addition (103) sont respectivement connectées à une entrée d'échantillon (Z_n) et, par un registre synchronisé (101), à la sortie desdits moyens de limitation (81a), et ladite sortie desdits moyens d'addition (103) est connectée par un registre synchronisé (105) à l'entrée desdits moyens de limitation (81a) de sorte que les valeurs de sortie puissent être engendrées indépendamment comme valeurs d'échantillon indexées paires et impaires, dans un procédé à enchevêtrements.

10

Patentansprüche

1. Verfahren zum Decodieren des Ausgangssignals eines Kommunikations- oder Aufzeichnungsgerätekannals nach der Methode der Folge mit höchster Wahrscheinlichkeit, wobei der Kanal synchron eine Folge binärer Symbole $a_n = +1$ oder -1 überträgt oder aufzeichnet, wo n ein ganzzahliger Symbol-Zeitindex ist, das Ausgangssignal gefiltert und abgetastet wird, um Abtastungen y_n mit einer Zwischensymbol-Interferenz der Teilantwort-Klassen zu erhalten, die durch die Polynome $1+d$, $1-d$ oder $1-d^2$ beschrieben sind, das Verfahren aus den Abtastungen y_n die am wahrscheinlichsten übertragene oder aufgezeichnete Folge binärer Symbole bestimmt, wobei das Verfahren auf einem Decodierer der Art durchgeführt werden kann, die einen Speicher zum Speichern binärwertiger Zeichen von Zustandsübergängen aufweist, welche dem Decodierverfahren zugrundeliegen, gekennzeichnet durch die folgenden Schritte:

25

rekursives Berechnen einer Differenzmetrik zu jedem Abtastmoment, wobei diese Metrik die Differenz zwischen impliziten überbleibenden Metriken repräsentiert, jede implizite überbleibende Metrik die Auftretenswahrscheinlichkeit der binären überbleibenden Folge anzeigt, die in dem Decodierspeicher erhalten und gespeichert ist und

30

Erzeugen zweier binärer Symbolentscheidungen und Verwenden derselben, um die in dem Pfad-Speicher gespeicherten binären überbleibenden Folgen zu erweitern, wobei das Vorzeichen der Differenzmetrik zu jedem Abtastmoment bestimmt, welche der überbleibenden, augenblicklich in dem Pfad-Speicher gespeicherten Folgen, die wahrscheinlichere Folge ist, aus welcher der Ausgang des Decodierers ausgewählt werden soll.

35

2. Verfahren nach Anspruch 1 zum Decodieren von Probe-Signalen mit einer Zwischensymbol-Interferenz der Teilantwort-Klasse-IV-Art, die durch ein Polynom $1-d^2$ beschrieben ist, nach der Methode der Folge mit höchster Wahrscheinlichkeit, dadurch gekennzeichnet, daß die zwei Folgen gerade und ungerade indizierter Proben y_n unabhängig, auf der Basis unabhängiger Zustandsübergangsdiagramme mit zwei Zuständen, zu jedem Abtastmoment decodiert werden.

40

3. Einrichtung zum Decodieren von Probe-Folgen mit einer Zwischensymbol-Interferenz der Teilantwort-Klasse-IV-Art, die durch ein Polynom $1-d^2$ beschrieben ist, nach der Methode der Folge mit höchster Wahrscheinlichkeit, wobei die Einrichtung ein weiß ausgelegtes angepaßtes Filter (13), Abtastmittel (15) und Überbleibende-Folge-Speicher- und Aktualisierungsmittel (21) aufweist, gekennzeichnet durch eine metrikwertbestimmende Schaltung (19; Fig.6), die aufweist:

45

Mittel (91) zum Addieren eines neueren Probe-Wertes (y_{n-1}) und der bereichbegrenzten Differenz des neueren Probe-Wertes (y_{n-1}) und einer vorangehenden Überbleibende-Differenz-Metrik (DJ_{n-3}) und zum Liefern einer neuen Überbleibende-Differenz-Metrik (DJ_{n-1}),

50

Mittel (85) zum Subtrahieren einer neuen Probe (y_n) von einer neueren Überbleibende-Differenz-Metrik (DJ_{n-2}),

55

Mittel (81) zum Begrenzen des Ausgangs der Subtrahiermittel (85) auf einen Bereich zwischen $+1$ und -1 und zum Erzeugen zweier zwischenliegender binärer Entscheidungswerte (b_{n-2}^+ und b_{n-2}^-),



une gamme allant de $+1$ à -1 et pour engendrer deux valeurs de décisions binaires intermédiaires (b_{n-1}^+ et b_{n-1}^-); et

des moyens (111) connectés à la sortie desdits moyens d'addition (103) pour engendrer une valeur de sortie binaire ($\hat{b}_n$) représentant le signe de la nouvelle métrique survivante de différence (DJ_n).

5

6. Dispositif selon la revendication 5, caractérisé en ce que les entrées desdits moyens d'addition (103) sont respectivement connectées à une entrée d'échantillon (Z_n) et, par un registre synchronisé (101), à la sortie desdits moyens de limitation (81a), et ladite sortie desdits moyens d'addition (103) est connectée par un registre synchronisé (105) à l'entrée desdits moyens de limitation (81a) de sorte que les valeurs de sortie puissent être engendrées indépendamment comme valeurs d'échantillon indexées paires et impaires, dans un procédé à enchevêtrements.

10

Patentansprüche

1. Verfahren zum Decodieren des Ausgangssignals eines Kommunikations- oder Aufzeichnungsgerätekansals nach der Methode der Folge mit höchster Wahrscheinlichkeit, wobei der Kanal synchron eine Folge binärer Symbole $a_n = +1$ oder -1 überträgt oder aufzeichnet, wo n ein ganzzahliger Symbol-Zeitindex ist, das Ausgangssignal gefiltert und abgetastet wird, um Abtastungen Y_n mit einer Zwischensymbol-Interferenz der Teilantwort-Klassen zu erhalten, die durch die Polynome $1+d$, $1-d$ oder $1-d^2$ beschrieben sind, das Verfahren aus den Abtastungen y_n die am wahrscheinlichsten übertragene oder aufgezeichnete Folge binärer Symbole bestimmt, wobei das Verfahren auf einem Decodierer der Art durchgeführt werden kann, die einen Speicher zum Speichern binärwertiger Zeichen von Zustandsübergängen aufweist, welche dem Decodierverfahren zugrundeliegen, gekennzeichnet durch die folgenden Schritte:

20

25

rekursives Berechnen einer Differenzmetrik zu jedem Abtastmoment, wobei diese Metrik die Differenz zwischen impliziten überbleibenden Metriken repräsentiert, jede implizite überbleibende Metrik die Auftrittswahrscheinlichkeit der binären überbleibenden Folge anzeigt, die in dem Decodierspeicher erhalten und gespeichert ist und

30

Erzeugen zweier binärer Symbolentscheidungen und Verwenden derselben, um die in dem Pfad-Speicher gespeicherten binären überbleibenden Folgen zu erweitern, wobei das Vorzeichen der Differenzmetrik zu jedem Abtastmoment bestimmt, welche der überbleibenden, augenblicklich in dem Pfad-Speicher gespeicherten Folgen, die wahrscheinlichere Folge ist, aus welcher der Ausgang des Decodierers ausgewählt werden soll.

35

2. Verfahren nach Anspruch 1 zum Decodieren von Probe-Signalen mit einer Zwischensymbol-Interferenz der Teilantwort-Klasse-IV-Art, die durch ein Polynom $1-d^2$ beschrieben ist, nach der Methode der Folge mit höchster Wahrscheinlichkeit, dadurch gekennzeichnet, daß die zwei Folgen gerade und ungerade indizierter Proben y_n unabhängig, auf der Basis unabhängiger Zustandsübergangsdiagramme mit zwei Zuständen, zu jedem Abtastmoment decodiert werden.

40

3. Einrichtung zum Decodieren von Probe-Folgen mit einer Zwischensymbol-Interferenz der Teilantwort-Klasse-IV-Art, die durch ein Polynom $1-d^2$ beschrieben ist, nach der Methode der Folge mit höchster Wahrscheinlichkeit, wobei die Einrichtung ein weiß ausgelegtes angepaßtes Filter (13), Abtastmittel (15) und Überbleibende-Folge-Speicher- und Aktualisierungsmittel (21) aufweist, gekennzeichnet durch eine metrikwertbestimmende Schaltung (19; Fig.6), die aufweist:

45

Mittel (91) zum Addieren eines neueren Probe-Wertes (y_{n-1}) und der bereichbegrenzten Differenz des neueren Probe-Wertes (y_{n-1}) und einer vorangehenden Überbleibende-Differenz-Metrik (DJ_{n-3}) und zum Liefern einer neuen Überbleibende-Differenz-Metrik (DJ_{n-1}),

50

Mittel (85) zum Subtrahieren einer neuen Probe (y_n) von einer neueren Überbleibende-Differenz-Metrik (DJ_{n-2}),

55

Mittel (81) zum Begrenzen des Ausgangs der Subtrahierungsmittel (85) auf einen Bereich zwischen $+1$ und -1 und zum Erzeugen zweier zwischenliegender binärer Entscheidungswerte (b_{n-2}^+ und b_{n-2}^-),



Mittel (97), die mit dem Ausgang der Addiermittel (91) zum Erzeugen eines binären Ausgangswertes ($\hat{b}_{n-1}$) verbunden sind, welcher das Vorzeichen der neuen Überbleibende-Differenz-Metrik (DJ_{n-1}) repräsentiert.

- 5 4. Einrichtung nach Anspruch 3, dadurch gekennzeichnet, daß die Eingänge der Addiermittel (91) durch getaktete Register (83, 89) mit einem Probe-Eingang (y_n) bzw. mit dem Ausgang der Begrenzermittel (81) verbunden sind, die Eingänge der Subtrahiermittel (85) mit dem Probe-Eingang (y_n) bzw. durch ein getaktetes Register (87) mit dem Ausgang der Addiermittel verbunden sind, sodaß Ausgangswerte für gerade und ungerade indizierte Probe-Werte unabhängig in einem Pipeline-Prozeß erzeugt werden können.

- 10 5. Einrichtung zum Decodieren von Probe-Folgen mit einer Zwischensymbol-Interferenz der Tellantwort-Klasse-IV-Art, die durch ein Polynom $1-d^2$ beschrieben ist, nach der Methode der Folge mit höchster Wahrscheinlichkeit, wobei die Einrichtung ein angepaßtes Filter (13), Abtastmittel (15) und Überbleibende-Folge-Speicher- und Aktiviermittel (21) aufweist, gekennzeichnet durch ein metrikwertbestimmendes Mittel (19; Fig.7), das aufweist:

20 Mittel (103) zum Addieren eines neuen Probe-Wertes (z_n) und einer bereichsbeschränkten vorangehenden Überbleibende-Differenz-Metrik (DJ_{n-2}) und zum Liefern einer neuen Überbleibende-Differenz-Metrik (DJ_n),

25 Mittel (81a) zum Begrenzen des Wertes einer neueren Überbleibende-Differenz-Metrik (DJ_{n-1}) auf einen Bereich zwischen +1 und -1 und zum Erzeugen zweier zwischenliegender binärer Entscheidungswerte (b_{n-1}^+ und b_{n-1}^-) und

30 Mittel (111), die mit dem Ausgang der Addiermittel (103) zum Erzeugen eines binären Ausgangswertes ($\hat{b}_n$) verbunden sind, welcher das Vorzeichen der neuen Überbleibende-Differenz-Metrik (DJ_n) repräsentiert.

- 35 6. Einrichtung nach Anspruch 5, dadurch gekennzeichnet, daß die Eingänge der Addiermittel (103) mit einem Probe-Eingang (z_n) bzw. durch ein getaktetes Register (101) mit dem Ausgang der Begrenzermittel (81a) und der Ausgang der Addiermittel (103) durch ein getaktetes Register (105) mit dem Eingang der Begrenzermittel (81a) verbunden sind, sodaß Ausgangswerte für gerade und ungerade indizierte Probe-Werte unabhängig in einem Pipeline-Prozeß erzeugt werden können.

40

45

50

55