

METHOD AND SYSTEM FOR THE CONTROL OF DISCONTINUOUS RECEPTION IN A WIRELESS NETWORK

FIELD OF THE DISCLOSURE

[0001] The present disclosure relates to the long term evolution (E-UTRA) of Third Generation Partnership Project (3GPP), and in particular to discontinuous reception (DRX) for user equipment (UE) in the E-UTRA infrastructure.

BACKGROUND

[0002] In the long term evolution infrastructure, a UE can be in one of two radio resource control (RRC) states. These are LTE_IDLE and LTE_ACTIVE.

[0003] The UE can be configured for discontinuous reception (DRX) in both the LTE_IDLE and the LTE_ACTIVE states. DRX allows the UE to synchronize its listening period to a known paging cycle of the network. By synchronizing the listening period with acceptable transmission times from the network, the UE can turn off its radio transceiver when the network will not schedule transmissions, thereby significantly saving battery resources. As will be appreciated by those skilled in the art, unless a UE is used extensively, a large drain on its battery comes from the standby cycle in which it monitors the paging channel (or control channels) and measures serving and neighboring cells. DRX parameters allow the mobile to synchronize with the network and to know that it will not receive another signal until a specified time has elapsed.

[0004] Utilizing DRX in an IDLE state is performed in present UMTS systems and is done by the network signaling to the UE a DRX parameter and synchronizing the UE and the network.

[0005] In an ACTIVE state however, various issues exist for turning off the receiver based on a DRX parameter. This includes the fact that only network controlled handover is allowed in the LTE_ACTIVE state. Also, other issues include efficient signaling of activation and deactivation of DRX, measurement requirements of network signals during the DRX, handling of missed handover opportunities, and issues dealing with the length of the DRX value in which entity in the network can request DRX activation and reconfiguring the DRX period.

[0006] Further issues involve configuration and control of various timers for long DRX.

SUMMARY

[0007] The present disclosure provides various methods and systems for addressing the deficiencies in the prior art regarding DRX in an LTE_ACTIVE state.

[0008] The present disclosure provides a method to control a short discontinuous reception 'DRX' timer comprising: receiving a medium access control control element; checking whether a short DRX cycle is configured; stopping the short DRX timer responsive to the checking; and utilizing a long DRX cycle.

[0009] The present disclosure further provides a method to control a short discontinuous reception 'DRX' timer comprising: receiving a medium access control control element; checking whether a short DRX cycle is configured; and restarting the short DRX timer responsive to the checking.

[0010] The present disclosure still further provides a method to control a short discontinuous reception 'DRX' timer comprising: receiving a medium access control control element; checking whether a short DRX cycle is running; and maintaining the short DRX timer responsive to the checking.

[0011] The present disclosure further provides a user equipment adapted to control a short discontinuous reception 'DRX' timer comprising: a communications subsystem adapted to communicate with a network element and to further receive a medium access control control element; and a processor, said processor adapted to check whether a short DRX cycle is configured and responsive to the checking to stop the short DRX timer and transition the user equipment to a long DRX cycle.

[0012] The present disclosure further provides a user equipment adapted to control a short discontinuous reception 'DRX' timer comprising: a communications subsystem adapted to communicate with a network element and to further receive a medium access control control element; and a processor, said processor adapted to check whether a short DRX timer is running and responsive to the checking to restart the short DRX timer.

[0013] The present disclosure further provides a user equipment adapted to control a short discontinuous reception 'DRX' timer comprising: a communications subsystem adapted to communicate with a network element and to further receive a medium access control control element; and a processor, said processor adapted to check whether a short DRX cycle is configured and responsive to the checking to maintain the short DRX timer.

[0014] The present disclosure further provides a method to prevent a retransmission timer from starting, comprising: receiving a value for a maximum number of downlink transmissions for a hybrid acknowledgement request process; checking whether the number of downlink transmissions for the hybrid acknowledgement request process equals or exceeds the value; and responsive to the checking, preventing the retransmission timer from starting.

[0015] The present disclosure further provides a method to prevent a retransmission timer from starting, comprising: receiving a value for a specific redundant version; checking whether the redundant version for the hybrid acknowledgement request process equals the value; and responsive to the checking, preventing the retransmission timer from starting.

[0016] The present disclosure further provides a method to prevent a retransmission timer from starting, comprising: receiving an expiration value for a number of downlink transmissions for a hybrid acknowledgement request process; checking whether the number of downlink transmissions for the hybrid acknowledgement request process equals or exceeds the expiration value; and responsive to the checking, preventing the retransmission timer from starting.

[0017] The present disclosure further provides a method to limit a duration of a retransmission timer or to prevent the start of the retransmission timer comprising: receiving a discontinuous reception medium access control control element; identifying a hybrid acknowledgement request process corresponding to the discontinuous reception medium access control control element; and preventing the start of, or stopping, the retransmission timer for the hybrid acknowledgement request process.

[0018] The present disclosure further provides a user equipment adapted to prevent a retransmission timer from starting, comprising: a communication

subsystem adapted to receive a value for a maximum number of downlink transmissions for a hybrid acknowledgement request process; and a processor adapted to check whether the number of downlink transmissions for the hybrid acknowledgement request process equals or exceeds the value and responsive to the check the processor adapted to prevent the retransmission timer from starting.

[0019] The present disclosure further provides a user equipment adapted to prevent a retransmission timer from starting, comprising: a communications subsystem adapted to receive a value for a specific redundant version; and a processor adapted to check whether the redundant version for the hybrid acknowledgement request process equals to the value and responsive to the checking, the processor adapted to prevent the retransmission timer from starting.

[0020] The present disclosure further provides a user equipment adapted to prevent a retransmission timer from starting, comprising: a communication subsystem adapted to receive an expiration value for a number of downlink transmissions for a hybrid acknowledgement request process; and a processor adapted to check whether the number of downlink transmissions for the hybrid acknowledgement request process equals or exceeds the expiration value and responsive to the check the processor is adapted to prevent the retransmission timer from starting.

[0021] The present disclosure further provides a user equipment adapted to limit a duration of a retransmission timer or to prevent the start of the retransmission timer comprising: a communications subsystem adapted to receive a discontinuous reception medium access control control element; and a processor adapted to identify a hybrid acknowledgement request process corresponding to the discontinuous reception medium access control control element, the processor further adapted to prevent the start of, or to stop, the retransmission timer for the hybrid acknowledgement request process.

BRIEF DESCRIPTION OF THE DRAWINGS

[0022] The present application will be better understood with reference to the drawings, in which:

Figure 1 is a block diagram showing a long term evolution user plane protocol stack;

Figure 2 is a block diagram showing a long term evolution control plane protocol architecture;

Figure 3a is a flow chart showing a method to activate deactivate and reconfigure DRX period using a MAC-PDU header from the eNB side;

Figure 3b is a flow chart showing a method to acknowledge the activation, deactivation or reconfiguration of the DRX period from the UE side;

Figure 4a is a flow chart showing a method to transition directly to long DRX period using a MAC-PDU header from the eNB side;

Figure 4b is a flow chart showing a method to transition directly to a long DRX period from the UE side and stopping the short DRX timer if running;

Figure 4c is a flow chart showing a method to transition directly to a long DRX period from the UE side and resetting the short DRX timer if running;

Figure 4d is a flow chart showing a method to transition directly to a long DRX period from the UE side and maintaining the short DRX timer if running;

Figure 5a is a flow chart showing a network side method for signaling that a maximum number of retries has occurred;

Figure 5b is a flow chart showing a UE side method for determining whether to start a retransmission timer;

Figure 6a is a flow chart showing a network side method for signaling that a maximum number of retries has occurred;

Figure 6b is a flow chart showing a UE side method for determining whether to start a retransmission timer;

Figure 7a is a flow chart showing a network side method for signaling that an expiration value for a number of retries;

Figure 7b is a flow chart showing a UE side method for determining whether to start a retransmission timer;

Figure 8a is a flow chart showing a network side method for signaling a maximum redundant version number;

Figure 8b is a flow chart showing a UE side method for determining whether to start a retransmission timer;

Figure 9 is a block diagram of an exemplary mobile device apt to be used with the present disclosure; and...

Figure 10 is a block diagram of a simplified network element apt to be used with the present disclosure.

DETAILED DESCRIPTION OF THE DRAWINGS

[0023] Reference is now made to the drawings. **Figure 1** shows a block diagram illustrating the long-term evolution (LTE) user plane protocol stack.

[0024] A UE **110** communicates with an evolved Node B (eNB) **120**.

[0025] Various layers are illustrated in the protocol stack. The packet data convergence protocol (PDCP) layer **140** is illustrated both on the UE **110** and on eNB **120**. The PDCP layer **140** performs Internet protocol (IP) header compression and decompression, encryption of user data, transfer of user data and maintenance of PDCP sequence numbers (SN) for radio bearers.

[0026] Below the PDCP layer **140** is the radio link control protocol layer **142**, which communicates with the radio link control protocol layer **142** on the eNB **120**. As will be appreciated, communication occurs through the physical layer in protocol stacks such as those illustrated in **Figures 1** and **2**. However, RLC-PDUs from the RLC layer **142** of the UE are interpreted by the RLC layer **142** on the eNB **120**.

[0027] Below RLC layer **142** is the medium access control (MAC) data communication protocol layer **146**. As will be appreciated by those skilled in the art, the RLC and MAC protocols form the data link sublayers of the LTE radio interface and reside on the eNB in LTE and user equipment.

[0028] The layer 1 (L1) LTE (physical layer **148**) is below the RLC/MAC layers **142** and **146**. This layer is the physical layer for communications.

[0029] Referring to **Figure 2**, **Figure 2** illustrates the LTE control plane protocol architecture. Similar reference numerals to those used in **Figure 1** will be used in **Figure 2**. Specifically, UE **110** communicates with eNB **120**

and an access gateway (aGW) **130**. Further, physical layer **148**, MAC layer **146**, RLC layer **142** and PDCP layer **140** exist within **Figure 2**.

[0030] **Figure 2** also shows the non-access stratum (NAS) layer **210**. As will be appreciated, NAS layer **210** could include mobility management and session management.

[0031] The radio resource control protocol layer (RRC) **220**, is the part of the protocol stack that is responsible for the assignment, configuration and release of radio resources between the UE and the E-UTRAN (Evolved universal terrestrial radio access network). The basic functionalities of RRC protocol for LTE is described in 3GPP TS 36.331.

[0032] As will be appreciated by those skilled in the art, in UMTS, automatic repeat request (ARQ) functionality is carried out within the RLC layer which resides in the radio network controller (RNC). Long Term Evolution (LTE) moves the ARQ functionality from the RNC to eNB where a tighter interaction may exist between the ARQ and the HARQ (within the MAC layer, also located in the eNB).

[0033] Various issues regarding DRX in an LTE-ACTIVE state are considered herein.

DRX signaling procedure

[0034] Very efficient signaling procedures for activating and de-activating DRX and specifying the duration of DRX periods are required in order to support a large population of UEs in a cell that are utilizing DRX in an LTE_ACTIVE state.

[0035] As will be appreciated by those skilled in the art, if the evolved node B (eNB) transmits data to the UE during its receiver off period due to a DRX operation, the UE cannot receive the data. Therefore, an indication is required to ensure the UE and the eNB are synchronized regarding when DRX is activated and deactivated.

[0036] The indication between the UE and the eNB can be explicit signaling by the radio resource control (RRC) or layer 1/layer 2 (L1/L2) signaling. As will be appreciated, however, explicit signaling may not be as efficient as desired.

[0037] A more efficient solution is to include an optional field in the MAC header of a MAC-PDU (MAC Protocol Data Unit) to indicate DRX activation

and deactivation. The field preferably indicates the DRX value and timing margin for activation and deactivation. A value of zero, for example, could mean DRX deactivation in the DRX value field in one embodiment. Conversely, if data that is to be transmitted in the next MAC-PDU is the last one in the buffer for the UE, the eNB may extend the MAC header field to include a DRX length initial value. For example, this could be 320 milliseconds. The timing margin is explained below, and is utilized to reduce the consequences of a NACK to ACK or ACK to NACK misinterpretation, for the reception status of the MAC-PDU between the UE and the eNB.

[0038] For example, three bits may be added to the MAC header to indicate eight values of the DRX period. Thus, rather than a specific time value being sent, a bit value from 000 to 111 could indicate one of eight discrete values.

[0039] In an alternative embodiment, a smaller field in the MAC header could be used (for example two bits) to indicate increment or decrement. The RRC could indicate default values, and if the MAC header indicates increment or decrement then the UE could change to the prespecified value.

[0040] For example, a Logical Channel ID field (LCID) for a downlink shared channel (DL-SCH) could be:

Index	LCID values
00000	CCCH
00001-xxxxx	Identity of the logical channel
xxxxx-11011	Reserved
11100	[UE Contention Resolution Identity]
11101	[Timing Advance]
11110	DRX Command
11111	Padding

Values of LCID for DL-SCH

[0041] As indicated above, a DRX Control Element could be 11110 in the Index.

[0042] Once the UE receives the DRX value, it acknowledges it to the eNB by transmitting HARQ ACK and starts the DRX at the system frame time considering propagation delay and processing delay at the eNB. When the

eNB receives the ACK from the UE, it also starts the DRX at the next system frame time. As will be appreciated, the eNB does not turn off its transceiver, but simply knows not to transmit messages to the individual UE.

[0043] During a DRX period, if new data arrives at the eNB, the eNB can send a MAC-PDU with a header extension set to DRX deactivation or a shorter DRX length depending on the amount of data in the buffer or the quality of service requirements. The UE reconfigures the DRX accordingly and acknowledges the MAC-PDU. When the eNB receives the ACK, it reconfigures the DRX. As indicated above, the deactivation could be accomplished by merely setting the length value to zero.

[0044] Reference is now made to **Figure 3a** and **3b**. **Figure 3a** shows an exemplary method for controlling DRX activation in an LTE_ACTIVE state. The process starts at block **300** and proceeds to block **310** in which data is transmitted to the UE. As will be appreciated by those skilled in the art, data transmission in an LTE_ACTIVE state utilizes the MAC-PDU at the data link layer to transmit the data.

[0045] The process next proceeds to block **312** in which a check is made to see whether the buffer of data to be sent to the UE will be empty after the next transmit. If no, the process proceeds back to block **310** in which data is transmitted to the UE. Alternatively, if the buffer will be empty after the next transmit and the data arrival rate is lower than a threshold value, the process proceeds to block **314**.

[0046] In block **314**, the eNB sets DRX activation in the MAC-PDU header. As indicated above, this includes a DRX activation value indicating the length of the DRX period. In another embodiment the eNB may simply indicate an increase in the DRX interval. The UE reconfigures the existing DRX interval to a predetermined interval. The predetermined interval may be either known to both eNB and UE or pre-signaled to the UE from the eNB via explicit signaling; either by system broadcast or RRC signaling.

[0047] The process then proceeds to block **316** in which the data including the modified MAC-PDU header is sent to the UE.

[0048] Reference is now made to **Figure 3b**. In block **318**, the UE receives the data and sees that DRX activation is specified in the MAC-PDU header. The process proceeds to block **320** in which the UE sends an

acknowledgement (ACK) to the eNB and starts the DRX at the system frame time considering propagation delay and processing delay at the eNB.

[0049] In block **330** of **Figure 3a**, the eNB receives the ACK from the UE and starts the DRX at the next system frame time.

[0050] As will be appreciated, the DRX can continue until various events occur which may require the DRX to be adjusted. One event is the reception of data from aGW by the eNB for the UE. Depending on the amount of data received, the DRX can either be deactivated or the period of the DRX can be reduced. Other events that may require the adjustment of the DRX include a change of signal power level between the eNB and the UE or possibly a gradual increase in the DRX cycle due to continued data inactivity, among others. These other events are discussed in more detail below.

[0051] In block **332** the eNB checks to see whether the DRX needs to be adjusted. As indicated above, this could be the situation where data is received to be sent to the UE. Here the DRX can either be deactivated or the period adjusted.

[0052] From block **332**, if the DRX does not need to be adjusted, the process proceeds back to block **332** and continues to check whether or not the DRX needs to be adjusted.

[0053] Once the process in block **332** finds that the DRX does need to be adjusted, the process proceeds to block **334** in which it adjusts the DRX. This could be deactivating the DRX by transmitting a zero value for the DRX or a shorter DRX or a longer DRX as required.

[0054] The MAC-PDU with the modified header is sent to the UE in block **336**. The MAC-PDU in block **336** could also include any data that has been received by the eNB that needs to be transmitted to the UE.

[0055] Referring to **Figure 3b**, the process then proceeds to block **318** in which the MAC-PDU with modified header is received at the UE. This MAC-PDU with the modified header is referred to herein as the MAC Control Element (CE). The UE recognizes the DRX period is to be adjusted and in block **320** it sends an acknowledgement to the eNB and it adjusts its DRX period at the same system frame time considering propagation delay and processing delay as at the eNB.

[0056] Referring to **Figure 3a**, in block **342** the eNB receives the ACK and starts the modified DRX period at the appropriate system frame time. The process then proceeds back to block **332** to see whether the DRX needs to be adjusted again.

[0057] In one embodiment, a DRX command MAC control element could indicate to a UE to transition to a DRX period. In this case, if the eNB wants the UE to transition to a long DRX period due to lack of uplink and downlink traffic and based on low traffic rates for non real time DRX, under current E-UTRA specifications this requires a change in the DRX configuration to be made with an RRC configuration message. This may be a 'go-to-sleep' CE. An issue with this is that if the eNB later receives traffic patterns that require a shorter DRX period, the RRC configuration message will need to be sent again to reconfigure the DRX configuration on the UE.

[0058] Instead, a MAC CE could include a "go-to-long-sleep" possibility. Thus, the eNB could provide the UE with an option to go directly to a long DRX period or cycle without a reconfiguration message explicitly being sent.

[0059] Reference is now made to **Figure 4a**. In **Figure 4a**, the process starts at block **410** and proceeds to block **412** in which a check is made to determine whether a precondition for a long DRX cycle exists. As will be appreciated by those skilled in the art, such a precondition could include one or more of: the DRX being configured, a lack of uplink and downlink traffic for the UE, low data transmission to the UE, the position of the UE within a cell and the likelihood of a transition occurring, among others.

[0060] If, in block **412**, a determination is made that the precondition exists the process proceeds to block **420** in which a long DRX MAC CE is sent to the UE.

[0061] Conversely, if the precondition in block **412** does not exist, the process proceeds to block **430** in which the short DRX period is maintained and the process proceeds back to block **412**.

Stopping the Short DRX Timer

[0062] From the UE perspective, reference is now made to **Figure 4b**. The process in **Figure 4b** starts at block **450** and proceeds to block **452** in which a

check is made to determine whether short DRX cycle is configured. If not, the process proceeds to block **460** in which a long DRX cycle is used.

[0063] Conversely, if it is determined in block **452** that short DRX cycle is configured, the process proceeds to block **470** in which a check is made to determine whether a DRX MAC CE command has been received.

[0064] From block **470**, if a DRX MAC CE command has been received, the process proceeds to block **472** in which a check is made to see whether the short DRX timer is started. If yes, the process proceeds to block **473** in which the short DRX timer is stopped. As will be appreciated, this avoids having a short DRX cycle start on the expiry of the timer.

[0065] The process then proceeds to block **476** in which a long DRX cycle is used.

[0066] Conversely, if it is determined that the short DRX timer has not been started in block **472**, the process proceeds directly to block **476** and uses a long DRX cycle.

Restarting the Short DRX Timer

[0067] Alternatively, instead of stopping the short DRX cycle timer at block **473**, other options are available. A first is to restart the DRX short cycle timer.

[0068] Reference is now made to **Figure 4c**. In **Figure 4c** the same blocks as in **Figure 4b** are performed, except block **473** from **Figure 4b** is replaced with block **474** in **Figure 4c**. Block **474** restarts the short DRX timer. As will be appreciated by those in the art, this provides the situation that, if the DRX short cycle timer is already started when receiving the DRX MAC CE, the duration of short DRX is extended. In this case a long DRX cycle is not transitioned to until the expiry of the short DRX timer.

[0069] From block **474** the process proceeds to block **480** and ends.

Maintaining the Short DRX Timer

[0070] A further alternative option is to keep the current DRX short cycle timer. In this case, the duration of the short DRX cycle is unchanged regardless of the reception of the DRX MAC CE.

[0071] Reference is now made to **Figure 4d**, which replaces block **473** of **Figure 4b** with block **475**. In block **475** the process maintains the current

short DRX timer. This keeps the current DRX transition time from a short DRX cycle to a long DRX cycle. From block **475** the process proceeds to block **480** and ends.

[0072] Under this embodiment, once the DRX short cycle timer expires the UE transitions to a long DRX cycle.

[0073] The three embodiments above thus present the options of extending the short DRX cycle period by restarting the DRX short cycle timer, maintaining the current DRX short cycle period by maintaining the current short cycle timer, or transitioning immediately to long DRX by stopping the DRX short cycle timer. From a battery perspective and a network signaling perspective, the maintaining of the current DRX short cycle timer or the transitioning directly to long DRX are preferable. Restarting the DRX short cycle timer extends the short DRX period which utilizes more battery and network resources than a UE in long DRX.

[0074] From block **476** the process proceeds to block **480** and ends.

[0075] From block **470**, if a DRX MAC CE has not been received the process proceeds to block **490** in which a short DRX timer is started. The process then proceeds to block **492** in which the UE uses a short DRX period or cycle. The use of the short DRX timer allows the UE to transition to a long DRX cycle after the timer has expired if no data is received or sent during the timer period.

[0076] From block **492** the process proceeds to block **480** and ends.

[0077] The above saves battery consumption and network resources when very low traffic is observed by the eNB. The solution provides a more efficient way to transition to a long DRX cycle than by sending RRC level reconfiguration messages.

DRX RETRANSMISSION TIMER

[0078] A further issue for control of DRX is with regard to the retransmission timer. As indicated in 3GPP TS 36.321 a DRX retransmission timer specifies the maximum number of consecutive downlink subframes the UE is to monitor the packet data control channel (PDCCH) for when a downlink retransmission is expected by the UE. It is utilized in situations where a packet has

unsuccessfully been received and a retransmission of the packet has been requested.

[0079] While waiting for retransmission, an HARQ round trip time (RTT) timer is utilized to allow the UE the ability to turn its radio off during this time. The HARQ RTT timer is a parameter which specifies the minimum amount of subframes before a downlink HARQ retransmission is expected by the UE.

[0080] In one embodiment, a counter, referred to herein as a retransmission counter, will count the number of times the retransmission timer is started or stopped by the UE.

[0081] Current functionality for discontinuous reception in 3GPP standards includes the following:

When a DRX cycle has been configured, the UE shall for each downlink subframe,

if a HARQ RTT timer expires in this downlink subframe and the data in the soft buffer of the corresponding HARQ process was not successfully decoded;

UE shall start the DRX retransmission for the corresponding HARQ process.

[0082] The standards further specify that DRX retransmission timers are stopped:

if the PDCCH indicates a DL transmission;

start the HARQ RTT timer for the corresponding HARQ process;

stop the DRX retransmission timer for the corresponding HARQ process.

One problem with the above is in the situation that the MAC PDU is not successfully decoded when the maximum number of transmission or retransmissions is reached. Since the maximum number of retransmissions is reached, the eNB will not send another retransmission; however, the UE will still expect to receive a retransmission. In this case, the DRX retransmission timer will be started, but since the maximum number of transmissions is reached, no retransmission will be sent, and the retransmission timer of the corresponding HARQ process will not be stopped until other new transmission using the same HARQ process is indicated over the PDCCH or the timer is

expired. The UE may wake up an additional retransmission window without receiving anything. The consequence of this is that in certain cases the DRX retransmission timer for certain HARQ processes may be running unnecessarily which causes the UE to continue to monitor the PDCCH unnecessarily and the UE to transmit the sounding reference signal (SRS) and channel quality indicator (CQI) and other feedbacks that facilitate more efficient downlink transmissions unnecessarily in the uplink.

Send DRX MAC CE to UE

[0083] Various solutions to the above are possible. In a first solution the network may send a DRX MAC control element to the UE.

[0084] The reception of DRX MAC CE results in the on-duration timer and inactivity timer being stopped. This could be extended to also stop the retransmission timer.

[0085] As will be appreciated by those skilled in the art, stopping the retransmission timer requires identification of the HARQ process. In one embodiment this can be done by including an optional field within the DRX MAC CE. For example, a three bit HARQ process identifier field could be included in the DRX MAC CE.

[0086] In an alternative embodiment the UE could stop the retransmission timer with the maximum value or the HARQ process that has the largest number of transmissions.

[0087] Reference is now made to **Figure 5a**. **Figure 5a** shows a flow diagram of the network side blocks used to send the DRX MAC CE. The process starts at block **510** in which a precondition exists that the maximum number of retries has occurred.

[0088] The process then proceeds to block **512** in which a DRX MAC CE is sent to the UE.

[0089] Optionally, the process proceeds to block **514** in which the DRX MAC CE sent at block **512** is modified to include an HARQ process identifier.

[0090] The process then proceeds to block **520** and ends.

[0091] Referring to **Figure 5b**, this figure shows the UE side functionality for stopping the retransmission timer. The process starts at block **530** and proceeds to block **532** in which a DRX MAC CE is received at the UE.

[0092] If the DRX MAC CE includes the optional extension having the HARQ process identifier, the process proceeds from block 532 to block 534 in which the HARQ process identifier is read from the DRX MAC CE.

[0093] Conversely, if the optional field for the process identifier does not exist in the DRX MAC CE, the process proceeds to block 536 in which the process identifies the HARQ process having the maximum number of transmissions or the retransmission timer having the maximum value. Blocks 534 or 536 thus identify the retransmission timer to be stopped or prevented from starting.

[0094] From block 534 or 536 the process proceeds to block 540 in which the retransmission timer for the process identified in blocks 534 or 536 is stopped or prevented from starting.

[0095] The process then proceeds to block 550 and ends.

[0096] As will be appreciated by those in the art, the above prevents a retransmission timer from running after the maximum number of retries has occurred by providing a DRX MAC CE to the UE to indicate that the retransmission timer should not be started or should be stopped.

Providing the Maximum Downlink Retry Value

[0097] As a further option, the network could signal the maximum number of downlink transmissions to the UE. In this case, the UE is therefore aware of when to stop or prevent starting the retransmission timer.

[0098] Reference is now made to **Figure 6a**. **Figure 6a**, the network side flow diagram is shown for signaling the maximum number of downlink transmissions to the UE.

[0099] The process of **Figure 6a** starts at block 610 and proceeds to block 612 in which the maximum number of downlink transmissions is signaled to the UE. As will be appreciated by those skilled in the art, the maximum number of retransmissions can vary based on factors such as the quality of service (QoS) for semi-persistent or "configured" cases. The process then proceeds to block 614 and ends.

[00100] Referring to **Figure 6b**, this figure shows the UE side process. The process starts at block 620 and proceeds to block 622 in which the UE receives and stores the maximum number of downlink transmissions possible from the network.

[00101] Communication proceeds as normal and eventually reaches block **624** in which a check is made to determine whether a HARQ process has been successfully decoded. If yes, the process proceeds to block **630** and ends. Alternatively, the process could continue to receive and decode HARQ processes.

[00102] If it is determined in block **624** that the HARQ process has not been successfully decoded the process proceeds to block **640** and checks whether the maximum number of downlink transmissions for that process has been reached. This could be done by utilizing a retransmission counter as described above to determine the number of retransmissions that have occurred. If yes, the process proceeds to block **630** and ends.

[00103] Conversely, if the maximum number of downlink transmissions has not been reached as determined in block **640** the process proceeds to block **642** and the retransmission timer is started pursuant to the current standards.

[00104] The above therefore prevents the starting of the retransmission timer when no further retransmissions will occur.

Providing an Expiration Retry Value

[00105] As a further option, the network could signal an expiration value to the UE, signaling the number of times a UE should start the retransmission timer for a given HARQ process. The expiration value relates to the retransmission counter, which counts the number of times the retransmission timer is started. In this case, the UE is therefore aware of when to stop or prevent starting the retransmission timer.

[00106] As will be appreciated by those in the art, the expiration value can be set by the network. Thus a network operator can determine that for certain services such as voice over internet protocol, the starting of a retransmission timer more than a certain number of times will lead to a bad user experience, and thus can set the expiration value to limit the number of times the retransmission timer starts.

[00107] In one embodiment the expiration retry value is less than the maximum downlink retry value.

[00108] Reference is now made to **Figure 7a**. **Figure 7a**, the network side flow diagram is shown for signaling the expiration value to the UE. In one embodiment a different expiration value can be set for different types of HARQ processes.

[00109] The process of **Figure 7a** starts at block **710** and proceeds to block **712** in which the expiration value or values are signaled to the UE. The process then proceeds to block **714** and ends.

[00110] Referring to **Figure 7b**, this figure shows the UE side process. The process starts at block **720** and proceeds to block **722** in which the UE receives and stores the expiration value or values from the network.

[00111] Communication proceeds as normal and eventually reaches block **724** in which a check is made to determine whether a HARQ process has been successfully decoded. If yes, the process proceeds to block **730** and ends. Alternatively, the process could continue to receive and decode HARQ processes.

[00112] If it is determined in block **724** that the HARQ process has not been successfully decoded, the process proceeds to block **740** and checks whether the number of retransmissions matches or exceeds the expiration value for the HARQ process. This could be done by utilizing a retransmission counter as described above to determine the number of retransmissions that have occurred. If yes, the process proceeds to block **730** and ends.

[00113] Conversely, if the number of retransmissions does not match or exceed the expiration value for the HARQ process, as determined in block **740** the process proceeds to block **742** and the retransmission timer is started pursuant to the current standards.

[00114] The above therefore prevents the starting of the retransmission timer when an expiration value has been reached.

Providing the a Specific Redundant Version Number

[00115] As a further option, instead of signaling a maximum number of downlink transmissions, the UE could instead be signaled a specific redundant version number associated with the last retransmission so the UE is aware when it is the last retransmission from the network.

[00116] Reference is now made to **Figure 8a**. **Figure 8a** shows a process from a network perspective for signaling a specific redundant version number associated with the last retransmission. The process starts at block **810** and proceeds to block **812** in which the specific redundant version number is signaled to the UE. The process then proceeds to block **814** and ends.

[00117] From the UE perspective reference is now made to **Figure 8b**. On the UE side **Figure 8b** starts at block **820** and proceeds to block **822** in which the UE receives and stores the redundant version number.

[00118] The process then proceeds and starts to decode HARQ processes. At block **824** a check is made to determine whether the particular HARQ process was successfully decoded. If yes, the process proceeds to block **830** and ends.

[00119] Conversely, from block **824** if the HARQ process was not successfully decoded the process proceeds to block **840** in which a check is made to determine whether the last HARQ process has a redundant version number that matches the specific redundancy version number received at block **822**. If yes, the process proceeds to block **850** and ends. Conversely, the process proceeds to block **842** and starts the retransmission timer. Again, this prevents the starting of the retransmission timer if further retransmissions are not expected.

[00120] The various options above each present advantages with regard to the other options. The setting of a expiration value for the retransmission timer is easy to implement and requires minimal signaling.

[00121] Conversely, the sending of a DRX MAC CE prevents the start of the retransmission timer but requires further signaling. Similarly, the storing of the maximum number of downlink retransmissions or specific redundant version number prevents the retransmission timer from starting unnecessarily.

[00122] The above can be implemented on any UE. Such UEs include, but are not limited to, personal digital assistants, cellular telephones, wireless data devices, among others. Reference is now made to **Figure 9**.

[00123] UE **900** is preferably a two-way wireless communication device having at least voice and data communication capabilities. UE **900** preferably

has the capability to communicate with other computer systems on the Internet. Depending on the exact functionality provided, the wireless device may be referred to as a data messaging device, a two-way pager, a wireless e-mail device, a cellular telephone with data messaging capabilities, a wireless Internet appliance, or a data communication device, as examples.

[00124] Where UE **900** is enabled for two-way communication, it will incorporate a communication subsystem **911**, including both a receiver **912** and a transmitter **914**, as well as associated components such as one or more, preferably embedded or internal, antenna elements **916** and **918**, local oscillators (LOs) **913**, and a processing module such as a digital signal processor (DSP) **920**. As will be apparent to those skilled in the field of communications, the particular design of the communication subsystem **911** will be dependent upon the communication network in which the device is intended to operate. For example, UE **900** may include a communication subsystem **911** designed to operate within the LTE Network.

[00125] Network access requirements will also vary depending upon the type of network **919**. For example, In UMTS and GPRS networks, network access is associated with a subscriber or user of UE **900**. For example, a GPRS mobile device therefore requires a subscriber identity module (SIM) card in order to operate on a GPRS network. In UMTS and LTE a USIM or SIM module is required. In CDMA a RUIM card or module is required. These will be referred to as a UIM interface herein. Without a valid UIM interface, a mobile device may not be fully functional. Local or non-network communication functions, as well as legally required functions (if any) such as emergency calling, may be available, but mobile device **900** will be unable to carry out any other functions involving communications over the network **900**. The UIM interface **944** is normally similar to a card-slot into which a card can be inserted and ejected like a diskette or PCMCIA card. The UIM card can have approximately 64K of memory and hold many key configuration **951**, and other information **953** such as identification, and subscriber related information.

[00126] When required network registration or activation procedures have been completed, UE **900** may send and receive communication signals

over the network **919**. Signals received by antenna **916** through communication network **919** are input to receiver **912**, which may perform such common receiver functions as signal amplification, frequency down conversion, filtering, channel selection and the like, and in the example system shown in **Figure 9**, analog to digital (A/D) conversion. A/D conversion of a received signal allows more complex communication functions such as demodulation and decoding to be performed in the DSP **920**. In a similar manner, signals to be transmitted are processed, including modulation and encoding for example, by DSP **920** and input to transmitter **914** for digital to analog conversion, frequency up conversion, filtering, amplification and transmission over the communication network **919** via antenna **918**. DSP **920** not only processes communication signals, but also provides for receiver and transmitter control. For example, the gains applied to communication signals in receiver **912** and transmitter **914** may be adaptively controlled through automatic gain control algorithms implemented in DSP **920**.

[00127] Network **919** may further communicate with multiple systems, including a server **960** and other elements (not shown). For example, network **919** may communicate with both an enterprise system and a web client system in order to accommodate various clients with various service levels.

[00128] UE **900** preferably includes a microprocessor **938** which controls the overall operation of the device. Communication functions, including at least data communications, are performed through communication subsystem **911**. Microprocessor **938** also interacts with further device subsystems such as the display **922**, flash memory **924**, random access memory (RAM) **926**, auxiliary input/output (I/O) subsystems **928**, serial port **930**, keyboard **932**, speaker **934**, microphone **936**, a short-range communications subsystem **940** and any other device subsystems generally designated as **942**.

[00129] Some of the subsystems shown in **Figure 9** perform communication-related functions, whereas other subsystems may provide "resident" or on-device functions. Notably, some subsystems, such as keyboard **932** and display **922**, for example, may be used for both communication-related functions, such as entering a text message for transmission over a communication network, and device-resident functions such as a calculator or task list.

[00130] Operating system software used by the microprocessor **938** is preferably stored in a persistent store such as flash memory **924**, which may instead be a read-only memory (ROM) or similar storage element (not shown). Those skilled in the art will appreciate that the operating system, specific device applications, or parts thereof, may be temporarily loaded into a volatile memory such as RAM **926**. Received communication signals may also be stored in RAM **926**. Further, a unique identifier is also preferably stored in read-only memory.

[00131] As shown, flash memory **924** can be segregated into different areas for both computer programs **958** and program data storage **950**, **952**, **954** and **956**. These different storage types indicate that each program can allocate a portion of flash memory **924** for their own data storage requirements. Microprocessor **938**, in addition to its operating system functions, preferably enables execution of software applications on the mobile device. A predetermined set of applications that control basic operations, including at least data and voice communication applications for example, will normally be installed on UE **900** during manufacturing. A preferred software application may be a personal information manager (PIM) application having the ability to organize and manage data items relating to the user of the mobile device such as, but not limited to, e-mail, calendar events, voice mails, appointments, and task items. Naturally, one or more memory stores would be available on the mobile device to facilitate storage of PIM data items. Such PIM application would preferably have the ability to send and receive data items, via the wireless network **919**. In a preferred embodiment, the PIM data items are seamlessly integrated, synchronized and updated, via the wireless network **919**, with the mobile device user's corresponding data items stored or associated with a host computer system. Further applications may also be loaded onto the mobile device **900** through the network **919**, an auxiliary I/O subsystem **928**, serial port **930**, short-range communications subsystem **940** or any other suitable subsystem **942**, and installed by a user in the RAM **926** or preferably a non-volatile store (not shown) for execution by the microprocessor **938**. Such flexibility in application installation increases the functionality of the device and may provide enhanced on-device functions, communication-related functions, or both. For example, secure

communication applications may enable electronic commerce functions and other such financial transactions to be performed using the UE 900. These applications will however, according to the above, in many cases need to be approved by a carrier.

[00132] In a data communication mode, a received signal such as a text message or web page download will be processed by the communication subsystem 911 and input to the microprocessor 938, which preferably further processes the received signal for output to the display 922, or alternatively to an auxiliary I/O device 928. A user of UE 900 may also compose data items such as email messages for example, using the keyboard 932, which is preferably a complete alphanumeric keyboard or telephone-type keypad, in conjunction with the display 922 and possibly an auxiliary I/O device 928. Such composed items may then be transmitted over a communication network through the communication subsystem 911.

[00133] For voice communications, overall operation of UE 900 is similar, except that received signals would preferably be output to a speaker 934 and signals for transmission would be generated by a microphone 936. Alternative voice or audio I/O subsystems, such as a voice message recording subsystem, may also be implemented on UE 900. Although voice or audio signal output is preferably accomplished primarily through the speaker 934, display 922 may also be used to provide an indication of the identity of a calling party, the duration of a voice call, or other voice call related information for example.

[00134] Serial port 930 in **Figure 9** would normally be implemented in a personal digital assistant (PDA)-type mobile device for which synchronization with a user's desktop computer (not shown) may be desirable. Such a port 930 would enable a user to set preferences through an external device or software application and would extend the capabilities of mobile device 900 by providing for information or software downloads to UE 900 other than through a wireless communication network. The alternate download path may for example be used to load an encryption key onto the device through a direct and thus reliable and trusted connection to thereby enable secure device communication.

[00135] Alternatively, serial port **930** could be used for other communications, and could include as a universal serial bus (USB) port. An interface is associated with serial port **930**.

[00136] Other communications subsystems **940**, such as a short-range communications subsystem, is a further optional component which may provide for communication between UE **900** and different systems or devices, which need not necessarily be similar devices. For example, the subsystem **940** may include an infrared device and associated circuits and components or a Bluetooth™ communication module to provide for communication with similarly enabled systems and devices.

[00137] Reference is now made to **Figure 10**. **Figure 10** illustrates the simplified network element adapted to make the decisions shown in **Figures 3a, 4a, 5a, 6a, 7a and 8a** above. Network element **1010** includes a communications subsystem **1020** adapted to communicate with user equipment. As will be appreciated by those skilled in the art communications subsystem **1020** does not need to directly communicate with user equipment, but could be part of a communications path for communications to and from the user equipment.

[00138] Network element **1010** further includes a processor **1030** and a storage **1040**. Storage **1040** is adapted to store information for each user equipment being serviced by network element **1010**. Processor **1030** is adapted to, provide information such as maximum number of retries, maximum redundant versions, DRX MAC CE, or expiration values by communications subsystem **1920**.

[00139] The embodiments described herein are examples of structures, systems or methods having elements corresponding to elements of the techniques of this application. This written description may enable those skilled in the art to make and use embodiments having alternative elements that likewise correspond to the elements of the techniques of this application. The intended scope of the techniques of this application thus includes other structures, systems or methods that do not differ from the techniques of this

application as described herein, and further includes other structures, systems or methods with insubstantial differences from the techniques of this application as described herein.

CLAIMS

We claim:

1. A method to control a short discontinuous reception 'DRX' timer comprising:
 - checking whether a medium access control control element is received and whether a short DRX cycle is configured;
 - stopping the short DRX timer responsive to the checking; and
 - utilizing a long DRX cycle.
2. A method to control a short discontinuous reception 'DRX' timer comprising:
 - checking whether a medium access control control element is received and whether a short DRX cycle is configured; and
 - restarting the short DRX timer responsive to the checking.
3. A method to control a short discontinuous reception 'DRX' timer comprising:
 - checking whether a medium access control control element is received and whether a short DRX cycle is configured; and
 - maintaining the short DRX timer responsive to the checking.
4. A user equipment for controlling a short discontinuous reception 'DRX' timer comprising:
 - a communications subsystem adapted to communicate with a network element and to further receive a medium access control control element; and
 - a processor, said processor adapted to check whether the medium access control control element is received and whether a short DRX cycle is configured and responsive to the checking to stop the short DRX timer and transition the user equipment to a long DRX cycle.

5. A user equipment for controlling a short discontinuous reception 'DRX' timer comprising:
 - a communications subsystem adapted to communicate with a network element and to further receive a medium access control control element; and
 - a processor, said processor adapted to check whether the medium access control control element is received and whether a short DRX cycle is configured and responsive to the checking to restart the short DRX timer.
6. A user equipment for controlling a short discontinuous reception 'DRX' timer comprising:
 - a communications subsystem adapted to communicate with a network element and to further receive a medium access control control element; and
 - a processor, said processor adapted to check whether the medium access control control element is received and whether a short DRX cycle is configured and responsive to the checking to maintain the short DRX timer.
7. A method to prevent a retransmission timer from starting, comprising:
 - receiving a value for a maximum number of downlink transmissions for a hybrid acknowledgement request process;
 - checking whether the number of downlink transmissions for the hybrid acknowledgement request process equals or exceeds the value; and
 - responsive to the checking, preventing the retransmission timer from starting.
8. A method to prevent a retransmission timer from starting, comprising:
 - receiving a value for a specific redundant version;
 - checking whether the redundant version for the hybrid acknowledgement request process equals the value; and
 - responsive to the checking, preventing the retransmission timer from starting.
9. A method to prevent a retransmission timer from starting, comprising:
 - receiving an expiration value for a number of downlink transmissions for a hybrid acknowledgement request process;

checking whether the number of downlink transmissions for the hybrid acknowledgement request process equals or exceeds the expiration value;
and

responsive to the checking, preventing the retransmission timer from starting.

10. A method to limit a duration of a retransmission timer or to prevent the start of the retransmission timer comprising:

receiving a discontinuous reception medium access control control element;

identifying a hybrid acknowledgement request process corresponding to the discontinuous reception medium access control control element; and

preventing the start of, or stopping, the retransmission timer for the hybrid acknowledgement request process.

11. The method of claim 10, wherein the identifying utilizes a process identifier within the discontinuous reception medium access control control element.

12. The method of claim 10, wherein the identifying chooses the hybrid acknowledgement request process having a maximum number of transmissions or the retransmission timer having a maximum value.

13. A user equipment adapted to prevent a retransmission timer from starting, comprising:

a communication subsystem adapted to receive a value for a maximum number of downlink transmissions for a hybrid acknowledgement request process; and

a processor adapted to check whether the number of downlink transmissions for the hybrid acknowledgement request process equals or exceeds the value and responsive to the check the processor adapted to prevent the retransmission timer from starting.

14. A user equipment adapted to prevent a retransmission timer from starting, comprising:

- a communications subsystem adapted to receive a value for a specific redundant version; and

- a processor adapted to check whether the redundant version for the hybrid acknowledgement request process equals to the value and responsive to the checking, the processor adapted to prevent the retransmission timer from starting.

15. A user equipment adapted to prevent a retransmission timer from starting, comprising:

- a communication subsystem adapted to receive an expiration value for a number of downlink transmissions for a hybrid acknowledgement request process; and

- a processor adapted to check whether the number of downlink transmissions for the hybrid acknowledgement request process equals or exceeds the expiration value and responsive to the check the processor is adapted to prevent the retransmission timer from starting.

16. A user equipment adapted to limit a duration of a retransmission timer or to prevent the start of the retransmission timer comprising:

- a communications subsystem adapted to receive a discontinuous reception medium access control control element; and

- a processor adapted to identify a hybrid acknowledgement request process corresponding to the discontinuous reception medium access control control element, the processor further adapted to prevent the start of, or to stop, the retransmission timer for the hybrid acknowledgement request process.

17. The user equipment of claim 16, wherein the processor utilizes a process identifier within the discontinuous reception medium access control control element to identify the hybrid acknowledgement request process.

18. The user equipment of claim 16, wherein the processor chooses the hybrid acknowledgement request process having a maximum number of transmissions or the retransmission timer having a maximum value to identify the hybrid acknowledgement request process.