

APPARATUS AND METHODS USING AN EFFICIENT GOLAY CORRELATOR RUNNING AT 1.5 THE SAMPLING RATE IN WIRELESS COMMUNICATION SYSTEMS

BACKGROUND

5 Golay (complementary) sequences are starting to play an important role in wireless communications. These sequences have the property that if $G_a(n)$ and $G_b(n)$ are a complementary pair, the sum of correlation of G_a with itself and G_b with itself is equal to the delta function. This property makes these sequences very useful for channel estimation. Some of these sequences also have the property that there is a large zero auto
10 correlation zone around the peak of the correlation when correlating the sequence G_a with itself (or G_b with itself). However, improvements to the implementation of complementary sequences are needed to further improve wireless communications.

 Thus, a strong need exists for improved apparatus and methods which may provide for significant improvements in the implementation of Golay sequences in wireless
15 communication systems.

BRIEF DESCRIPTION OF THE DRAWINGS

 The subject matter regarded as the invention is particularly pointed out and distinctly claimed in the concluding portion of the specification. The invention, however, both as to organization and method of operation, together with objects, features, and
20 advantages thereof, may best be understood by reference to the following detailed description when read with the accompanying drawings in which:

 FIG. 1 depicts a correlator performing $M=2m$ additions per input samples so as to perform only m additions per input sample according to embodiments of the present invention.

25 It will be appreciated that for simplicity and clarity of illustration, elements illustrated in the figures have not necessarily been drawn to scale. For example, the dimensions of some of the elements are exaggerated relative to other elements for clarity. Further, where considered appropriate, reference numerals have been repeated among the figures to indicate corresponding or analogous elements.

30

DETAILED DESCRIPTION

In the following detailed description, numerous specific details are set forth in order to provide a thorough understanding of the invention. However, it will be understood by those skilled in the art that the present invention may be practiced without
5 these specific details. In other instances, well-known methods, procedures, components and circuits have not been described in detail so as not to obscure the present invention.

Although embodiments of the invention are not limited in this regard, discussions utilizing terms such as, for example, “processing,” “computing,” “calculating,” “determining,” “establishing,” “analyzing,” “checking,” or the like, may refer to
10 operation(s) and/or process(es) of a computer, a computing platform, a computing system, or other electronic computing device, that manipulate and/or transform data represented as physical (e.g., electronic) quantities within the computer’s registers and/or memories into other data similarly represented as physical quantities within the computer’s registers and/or memories or other information storage medium that may store instructions to perform
15 operations and/or processes.

Although embodiments of the invention are not limited in this regard, the terms “plurality” and “a plurality” as used herein may include, for example, “multiple” or “two or more”. The terms “plurality” or “a plurality” may be used throughout the specification to describe two or more components, devices, elements, units, parameters, or the like. For
20 example, “a plurality of stations” may include two or more stations.

As mentioned above, Golay (complementary) sequences are starting to play an important part in wireless communications. These sequences have the property that if $G_a(n)$ and $G_b(n)$ are a complementary pair, the sum of correlation of G_a with itself and G_b with itself is equal to the delta function. This property makes these sequences very useful
25 for channel estimation. Some of these sequences also have the property that there is a large zero auto correlation zone around the peak of the correlation when correlating the sequence G_a with itself (or G_b with itself).

Another very important property of Golay sequences is that there is an efficient implementation of a correlator with a Golay sequence. In this implementation, rather than
30 performing $M=2^m$ additions per input samples it is possible to perform only m additions per input sample. This implementation is shown in FIG. 1, shown generally as 100, with multipliers W 110, $W(2)$ 120, $W(3)$ 130 and $W(4)$ 140.

Embodiments of the present invention provide a transmitter operable to communicate in a wireless network and adapted to use an efficient Golay correlator running at 1.5 times a sampling rate. Further, embodiments of the present invention provide the signal is passing through delays ($D(n)$) and multiplied by weights $W(n)$ and then additions are performed. $D(n)$ may be a permutation of (1,2,4, 2^m) and in most cases without any permutation. In embodiments of the present invention, $W(n)$ may be any modulus one complex multiplier but in most cases it would be ± 1 or $\pm j$ – although the present invention is not limited in this respect. It is noted that if $w(1)$ is j and $w(2)$ is -1 this correlator will give the correlation with a sequence whose correlator has $w(1)=1$ and $w(2)=1$ and was modulated by a $\exp(-j\pi n/2)$, which is important for GMSK and BPSK transmitters. The output of the upper branch is a correlation with G_a and that of the lower branch is a correlation with G_b .

An embodiment of the present invention provides an implementation for this correlator for a situation where the transmitter generates the signal at chip frequency F_c and the receiver samples the signal at $F_s=1\frac{1}{2} F_c$. This happens when the transmitter is transmitting possibly a single carrier packet and the receiver is expecting either an SC or an OFDM packet. It may also be useful when the receiver samples at this rate to facilitate digital filtering instead of analog. In an embodiment of the present invention, an implementation all the delays $D(n)$ are replaced with $1.5D(n)$ (i.e a delay by 2 is replaced by a delay by 3, etc.) except to the first delay which remains 1. Everything else remains the same, except to the multiplier $W(1)$ which is converted to $\exp(j2\pi/3)$ if $w(1)$ had equaled to j . This implementation gives an impulse response very close to correlating with the original sequences. It is close enough to be useful in any implementation of the sequence. If not for embodiments set forth herein in the present invention, the sequence would have had to be resampled to the chip sampling rate, where some information may have been lost; or the correlation may have had to be done with a resampled sequence, which means 1.5×2^m multipliers per sample rather than the 1 multiplier plus m adders provided in embodiments of the present invention. Further, embodiments of the present invention can be extended to other rational sampling rate conversions (2, 5/4 etc.).

While certain features of the invention have been illustrated and described herein, many modifications, substitutions, changes, and equivalents may occur to those skilled in the art. It is, therefore, to be understood that the appended claims are intended to cover all such modifications and changes as fall within the true spirit of the invention.

We Claim:

1. An apparatus, comprising:
a transmitter operable to communicate in a wireless network and adapted to use an efficient Golay correlator running at 1.5 times a sampling rate.
- 5 2. The apparatus of claim 1, wherein said transmitter generates a signal at chip frequency F_c and a receiver in communication with said transmitter samples said signal at $F_s = 1\frac{1}{2} F_c$.
3. The apparatus of claim 2, wherein all delays $D(n)$ transmitted by said transmitter are replaced with $1.5D(n)$ except a first delay which remains 1.
- 10 4. The apparatus of claim 3, wherein a multiplier $W(1)$ associated with transmissions from said transmitter is converted to $\exp(j2\pi/3)$ if $w(1)$ is equal to j thereby producing an impulse response very close to correlating with original sequences.
5. A method, comprising:
using an efficient Golay correlator running at 1.5 times a sampling rate in a
15 transmitter operating to communicate in a wireless network.
6. The method of claim 1, further comprising generating by said transmitter a signal at chip frequency F_c and a receiver in communication with said transmitter samples said signal at $F_s = 1\frac{1}{2} F_c$.
7. The method of claim 6, further comprising replacing all delays $D(n)$
20 transmitted by said transmitter with $1.5D(n)$, except a first delay which remains 1.
8. The method of claim 7, wherein a multiplier $W(1)$ associated with transmissions from said transmitter is converted to $\exp(j2\pi/3)$ if $w(1)$ is equal to j thereby producing an impulse response very close to correlating with original sequences.
9. A computer readable medium encoded with computer executable
25 instructions, which when accessed, cause a machine to perform operations comprising:
using an efficient Golay correlator running at 1.5 times a sampling rate in a transmitter operating to communicate in a wireless network.
10. The computer readable medium encoded with computer executable instructions of claim 9, further comprising additional instructions that provide generating
30 by said transmitter a signal at chip frequency F_c and a receiver in communication with said transmitter samples said signal at $F_s = 1\frac{1}{2} F_c$.

11. The computer readable medium encoded with computer executable instructions of claim 10, further comprising additional instructions that provide replacing all delays $D(n)$ transmitted by said transmitter with $1.5D(n)$, except a first delay which remains 1.

5 12. The computer readable medium encoded with computer executable instructions of claim 11, wherein a multiplier $W(1)$ associated with transmissions from said transmitter is converted to $\exp(j2\pi/3)$ if $w(1)$ is equal to j thereby producing an impulse response very close to correlating with original sequences.

10 13. A system, comprising:
a first transceiver operable as a base station (BS) in a wireless network; and
a second transceiver operable as a mobile station (MS) in said wireless network and operable to communicate with said BS;

wherein said BS or said MS are adapted to use an efficient Golay correlator running at 1.5 times a sampling rate

15 14. The system of claim 13, wherein said transmitter generates a signal at chip frequency F_c and a receiver in communication with said transmitter samples said signal at $F_s = 1\frac{1}{2} F_c$.

15. The system of claim 14, wherein all delays $D(n)$ transmitted by said transmitter are replaced with $1.5D(n)$ except a first delay which remains 1.

20 16. The system of claim 15, wherein a multiplier $w(1)$ associated with transmissions from said transmitter is converted to $\exp(j2\pi/3)$ if $w(1)$ is equal to j thereby producing an impulse response very close to correlating with original sequences.