



166166

- 1 -

TITLE OF THE INVENTION
METHOD AND APPARATUS FOR TESTING MAGNETIC HEAD WITH
TMR ELEMENT

BACKGROUND OF THE INVENTION

5 The present invention relates to a magnetic
head testing apparatus for testing generally a
magnetic head using a tunneling magnetoresistive
effect element. In particular, it relates to a
technique for non destructive inspection of a tunnel
10 barrier layer of the element.

In general, a magnetic head comprising separately
a reading head and a writing head, mounted on the same
slider is used in a disk drive. The reading head is a
head dedicated for reading a data signal recorded
15 magnetically on a disk medium.

Recently, a GMR (giant magnetoresistive effect)
element (referred also as a GMR sensor) suited for
achieving a high recording density of a disk medium
is used for the reading head. However, as recent
20 magnetic heads and the like are very a problem of
sensitivity deterioration of the GMR element has grown
in importance.

As a countermeasure for the problem, use of a
novel tunneling magnetoresistive effect (TMR) element
25 (referred to also as a TMR sensor) as the reading head
has been proposed.

Unlike the GMR element, in a TMR element, the



G00002

conducting direction of the sense electric current
is in the vertical direction with respect to the film
surface, such that the tunneling electric current
flows in the tunnel barrier layer (for example, see
5 U. S. Patent No. 5,729,410 and the U. S. Patent
No. 5,898,547).

The characteristics of the TMR element depend
largely on the quality of the tunnel barrier layer of
the extremely thin film. Particularly in the case a
10 pin hole is present in the tunnel barrier layer, the
decline of the breakdown voltage is observed (for
example, see Journal of Applied Physics, Vol. 91,
No. 7, 2002; P. 4348-4352, "Dielectric breakdown in
magnetic tunnel junctions having an ultrathin barrier"
15 Bryan Oliver, Qing He, Xuefei Tang, and J. Nowark
(Seagate Technology LLC)).

The "breakdown voltage" refers to the critical
voltage of causing an element destruction at the time
of applying the electric current stress to the TMR
20 element stepwise. Moreover, the "pin hole" refers to
a part with a free layer and a pinned layer present on
the both sides of the tunnel barrier layer, contacted
locally with a metal due to the interface disturbance
by the film formation irregularity of the tunnel
25 barrier layer, the stress in the process and the like.

In the case a pin hole is present in the tunnel
barrier layer, since the pin hole part has a low

resistance, the electric current flowing in the tunnel barrier layer is concentrated. It is confirmed that the destructive damage to the tunnel barrier layer is accelerated by the local heat generating effect resulting from the electric current concentration. Therefore, for an improvement of the reliability of the reading head using the TMR element, it is essential to test for the presence of pin holes in the tunnel barrier layer.

In general, the presence of pin holes can be confirmed by the breakdown test. However, since the test is a destructive test, it cannot be used for the screening test for the reading head (magnetic head).

BRIEF SUMMARY OF THE INVENTION

In accordance with one embodiment of the present invention, there is provided an apparatus for testing a magnetic head, capable of testing non destructively the pin hole state in a tunnel barrier layer of a TMR element.

The apparatus comprises a measuring unit which measures the resistance value of the TMR element, a calculating unit which calculates the temperature coefficient with respect to the resistance value of the TMR element based on a relationship between the resistance value and a circumferential temperature of the TMR element, and a determining unit which determines a pin hole state in a tunnel barrier layer

included in the TMR element based on the temperature coefficient.

BRIEF DESCRIPTION OF THE SEVERAL VIEWS OF THE DRAWING

The accompanying drawings, which are incorporated
5 in and constitute a part of the specification, illustrate embodiments of the invention, and together with the general description given above and the detailed description of the embodiments given below, serve to explain the principles of the invention.

10 FIG. 1 is a block diagram showing a configuration of a magnetic head testing apparatus of an embodiment of the present invention;

FIG. 2 is a diagram for explaining a structure of the TMR element of the embodiment;

15 FIG. 3 is a diagram for explaining a quality testing method for the TMR element of the embodiment;

FIG. 4 is a diagram for explaining a quality testing method for the TMR element of the embodiment;

20 FIG. 5 is a graph showing a temperature dependency of a resistance value of a GMR element of the embodiment;

FIG. 6 is a graph showing an example of a result of measuring the resistance value change with respect to the temperature of the TMR element of the
25 embodiment;

FIG. 7 is a graph showing an example of a calculation result of a temperature coefficient TC

with respect to an initial resistance value of the embodiment;

FIG. 8 is a graph showing an example of a result of a breakdown test of the TMR element of the
5 embodiment;

FIG. 9 is a graph showing an example of a breakdown voltage with respect to the initial resistance value of the TMR element of the embodiment;

FIG. 10 is a graph showing the relationship
10 between the temperature coefficient TC and the breakdown voltage BDV of the embodiment;

FIG. 11 is a flow chart for explaining a procedure of a test process of the TMR element of the embodiment; and

15 FIG. 12 is a block diagram showing an essential part of a disk drive of the embodiment.

DETAILED DESCRIPTION OF THE INVENTION

Hereinafter, with reference to the drawings, an embodiment of the present invention will be explained.

20 FIG. 1 is a block diagram showing the configuration of a magnetic head testing apparatus of this embodiment. FIG. 2 is a diagram for explaining the structure of the TMR element (TMR sensor) of this embodiment.

25 (Structure of the TMR element)

This embodiment relates to a magnetic head testing apparatus to be used for a magnetic head

(numeral 2 in FIG. 1) comprising separately a reading head and a writing head using a TMR element, mounted on the same slider as the testing subject. The testing apparatus has the function of determining (evaluating) the pin hole state (specifically, the ratio of the presence thereof) in the tunnel barrier layer of the TMR element.

As shown in FIG. 2, the TMR element which is the testing subject of this embodiment is a sensor comprising as the basic structure a tunnel multi layer film having a first ferromagnetic layer 16 and a second ferromagnetic layer 14 laminated with a tunnel barrier layer 15 provided as the intermediate layer. FIG. 2 shows the surface facing the surface of a disk medium.

The TMR element has a first shield layer 11, a first electrode layer 12, a pinned layer 13, a pinned layer 14 as the second ferromagnetic layer, a tunnel barrier layer 15, a free layer 16 as the first ferromagnetic layer, a second electrode layer 17 and a second shield layer 18 laminated in this order.

In the case bias electric current is supplied to the second electrode layer 17, so-called tunnel electric current 19 flows from the free layer 16 as the first ferromagnetic layer to the pinned layer 14 as the second ferromagnetic layer. The TMR element is advantageous in that the sensitivity is not dependent

on the element size. Moreover, owing to the presence of the extremely thin tunnel barrier layer 15 between the pinned layer 14 and the free layer 16, a high MR change ratio can be obtained.

5 As to the operation principle of the TMR element, in the case the bias electric current is provided in the vertical direction with respect to the film surface, the magnetization orientation of the free layer 16 is changed in the film surface according to
10 the external magnetic field so that the conductance of the tunnel electric current 19 is changed, depending on the relative angle with respect to the magnetization orientation of the pinned layer 14 (principle of generation of the magnetic resistance effect).

15 Moreover, for a TMR element, the MR change ratio can be calculated theoretically from the polarizability of each ferromagnetic layer of the free layer 16 and the pinned layer 14.

(Configuration of the testing apparatus)

20 As shown in FIG. 1, the magnetic head testing apparatus of this embodiment comprises a mechanism for setting a head assembly 1 including a slider (magnetic head) 2 with a TMR element test subject as a reading head at the testing position. Here, the test subject
25 is not limited to the slider 2, it may be provided for example in a wafer state during the production process of the TMR element. The head assembly 1 comprises

the slider 2 mounted on a suspension 3 and a flexible printed circuit board (FPC) 4 connected with the TMR element.

Furthermore, the testing apparatus has a bias electric current control unit 5, an element resistance measuring unit 6, a temperature control unit 7, a memory 8, a micro processor (CPU) 9, and a main control unit (hereinafter it is referred to as a controller) 10.

The bias electric current control unit 5 is a circuit for controlling the supply of the bias electric current (electric current 19 FIG. 2) for the measurement with respect to the TMR element via the FPC 4. The element resistance measuring unit 6 is a circuit for measuring the resistance of the TMR element being supplied via the FPC 4. Specifically, the element resistance measuring unit 6 measures the resistance value of the TMR element (i.e., the resistance value of the tunnel barrier layer 15) based on the bias electric current value applied to the TMR element and the potential difference between the first electrode layer 12 and the second electrode layer 17.

The temperature control unit 7 is a device for controlling the circumferential temperature of the head assembly 1 including the TMR element as the test subject. Specifically, the temperature control unit 7 comprises specifically heating devices and controlling

devices such as a heater, a laser and a constant temperature vessel.

The CPU 9 executes the testing process of the TMR element (such as the calculation process of the temperature coefficient TC to be described later).
5 The memory stores the electric current value of the bias electric current obtained from the bias electric current control unit 5, the resistance value measured by the element resistance measuring unit 6, and the
10 temperature value of the circumferential temperature controlled by the temperature control unit 7, or the like according to the control by the CPU 9.

The controller 10 is an apparatus for executing the control of the entire testing apparatus, which
15 provides the final evaluation of the TMR element based on the testing result outputted from the CPU 9. Moreover, the controller 10 executes the testing processes automatically according to a predetermined sequence, utilizing a ρ -H tester, a spin stand, or the
20 like, used as the existing magnetic sensor testing apparatus. Furthermore, the controller 10 stores in the internal memory the evaluation conditions of the temperature coefficient TC such as the bias electric current value and the setting temperature inputted by
25 an operator before a test.

(Procedure of the testing process)

Hereinafter, the procedure of the testing

process of the TMR element of this embodiment will be explained with reference to the flow chart of FIG. 11.

First, the controller 10 sets an initial electric current value I_0 with respect to the bias electric current control unit 5 (step S1). It is preferable for the initial electric current value I_0 to be 300 mV or less based on the voltage ($V_0 = I_0 \times R_0$) for avoiding destruction of the TMR element (for example, 1 mA in the case of a 300 ohm element resistance value).

Moreover, the controller 10 sets an initial temperature value T_0 to the temperature control unit 7 (step S2). The definition of the temperature here is a temperature applied from the outside to the TMR element (circumferential temperature), using a heater, a laser, a constant temperature vessel, or the like. Since the initial temperature value T_0 is the reference temperature, it is preferable to be set up near room temperature (for example, 30°C) in order to restrain the load on the TMR element to a minimum level without an error with respect to the setting temperature. It is maintained until the difference of the setting temperature and the actual temperature is stabilized within the range of " $\pm 1^\circ\text{C}$ ".

After the stabilization of the circumferential temperature with respect to the TMR element, the controller 10 measures the initial resistance value

R0 by controlling the element resistance measuring unit 6 (step S3). The CPU 9 stores the initial resistance value R0 in the memory 8. The element resistance measuring unit 6 measures the initial resistance value R0 of the TMR element according to the initial electric current value I0 applied by the bias electric current control unit 5. Here, the measurement accuracy of the resistance is preferably 1% or less.

10 Next, the controller 10 sets a temperature value T_n ($n = 1$) different from the initial temperature value T_0 in the temperature control unit 7 (step S5). The setting temperature value T_1 may either be higher or lower than the initial temperature value T_0 .
15 However, since the higher temperature side involves the risk of the element deterioration, it is preferable to be 200°C or less.

 After the stabilization of the temperature by the temperature control unit 7, the element resistance measuring unit 6 measures the resistance value R_1 of the TMR element according to the initial electric current value I0 applied by the bias electric current control unit 5 (step S6).
20

 Hereafter, by repeating the processes of the steps S5 to S8, the controller 10 finally executes the temperature setting of the n th time and the measuring of the resistance value R_n (YES of step S8). The
25

CPU 9 calculates the temperature coefficient TC with respect to the resistance of the TMR element, using the measurement values (R0 to Rn) and the temperature values (T0 to Tn) stored in the memory 8 by the measuring processes (step S9).

(Temperature coefficient TC)

Specifically, the CPU 9 calculates the temperature coefficient TCn using the below-mentioned formula (1). The below-mentioned formula (1) is a formula for calculating the gradient of the regression line.

$$TCn(\% / ^\circ C) = \sum_{i=1}^n (T_i - \bar{T}) (R_i - \bar{R}) / R_0 \sum_{i=1}^n (T_i - \bar{T})^2 \quad \dots (1)$$

Here, $\bar{T}$ and $\bar{R}$ each represent the average value of the setting temperature and the average value of the resistance.

The number of times n of the temperature setting and the resistance measurement is preferably large, since this improves the reliability of the measurement data. The setting range of the temperatures T0 to Tn is preferably wide, and within a range that does not cause deterioration of the TMR element.

As shown in FIG. 2, the CPU 9 determines the quality of the tunnel barrier layer 15 of the TMR element (pin hole state) (step S10). The specific determining criteria and the principle of the quality determination (evaluation) method for the tunnel barrier layer 15 will be explained with reference

to FIGS. 3 to 10.

FIGS. 3 and 4 are conceptual diagrams for explaining the state of the quality change of the TMR element.

5 As shown in FIG. 3, the TMR element having a multiple layer structure comprising the free layer 32, the tunnel barrier layer 33 and the pinned layer 34 has the resistance value R reduced according to the circumferential temperature rise. The reference
10 numeral 31 denotes the tunnel electric current.

 According to the reduction of the resistance value R , the temperature coefficient TC becomes " $TC < 0$ ". In this state, as shown in FIG. 4, the interface of the tunnel barrier layer 33 is disturbed so as to
15 cause the metal contact of the free layer 32 and the pinned layer 34 provided above and below. The local metal contact part is referred to as the pin hole.

 In the case such a pin hole is formed in the tunnel barrier layer 33, since a parallel circuit
20 of the tunnel electric current 31 and the pin hole electric current 41 is formed, the resistance value tends to be lower as a whole. Moreover, since the pin hole part is a metal, the resistance value is increased according to the temperature rise.
25 Therefore, the temperature coefficient TC becomes " $TC > 0$ ".

 FIG. 5 is a characteristic figure showing the

temperature dependency of the resistance value of the GMR element having the same metal characteristic as that of the pin hole part. As shown in FIG. 4, in the case the pin holes are increased in the tunnel barrier layer 33, the positive temperature coefficient TC characteristic of the pin hole parts offset the negative TC characteristic of the tunnel barrier layer 33. The temperature coefficient TC shifts from a negative value to a positive value. Therefore, the presence ratio of the pin holes generated in the tunnel barrier layer 33 can be presumed from the tendency of the temperature coefficient TC.

FIG. 6 shows an example of the result of measurement of the resistance value change with respect to the TMR element temperature (temperature dependency of the resistance) in the testing method of this embodiment. In FIG. 6, the abscissa axis represents the temperature T , and the ordinate axis represents the resistance value standardized with respect to the initial resistance value R_0 at 30°C .

In FIG. 6, each of the temperature dependency characteristics of a sample 60 in the case of a 345 ohm initial resistance value R_0 , a sample 61 in the case of a 251 ohm initial resistance value R_0 , and a sample 62 in the case of a 123 ohm initial resistance value R_0 are specific examples. The measurement conditions here are a 0.2 mA initial

electric current I_0 , a 30°C initial temperature T_0 and setting temperatures of 60, 90, 120 and 150°C.

As shown in FIG. 6, the gradients of the straight lines of the graph corresponding to the temperature coefficient TC become steeper with a smaller initial resistance value R_0 in the order of the samples 60 to 62. Therefore, the sample 60 is close to the complete tunnel barrier layer 33 as shown in FIG. 3. In contrast, in the case of the samples 61, 62, the pin hole ratio in the tunnel barrier layer is increased relatively so as to be close to the state as shown in FIG. 4.

FIG. 7 shows an example of the result of the temperature coefficient TC calculated by the above-mentioned formula (1) with respect to the initial resistance value R_0 . As shown in FIG. 7, with a smaller initial resistance value, the temperature coefficient becomes closer from the negative value to the positive value. From this result, it is confirmed that the temperature coefficient TC is an indicator accurately representing the pin hole ratio in the tunnel barrier layer.

(Breakdown voltage BDV)

Next, a method of testing the durability of the TMR element non destructively according to the breakdown voltage BDV will be explained.

The CPU 9 calculates (presumes) the breakdown

voltage from the calculated temperature coefficient TC. As mentioned above, the breakdown voltage denotes the critical voltage of causing the element destruction at the time of applying the stress electric current I_b to the TMR element stepwisely.

It is confirmed that the breakdown voltage BDV becomes lower in the case a pin hole is present in the tunnel barrier layer.

FIG. 8 shows an example of the testing result of the breakdown test of the TMR element. In FIG. 8, the abscissa axis represents the stress electric current I_b , and the ordinate axis represents the resistance value standardized with respect to the initial resistance value. The resistance value shown here is a value measured after the application of the stress electric current I_b with the measurement conditions of a 30°C setting temperature and a 0.2 mA initial electric current I_0 .

As shown in FIG. 8, as to a sample 80, the resistance value R is reduced moderately according to the increase of the stress electric current I_b and it is reduced drastically in the vicinity of the 3.3 mA stress electric current I_b . As to a sample 81, the resistance value starts to be reduced from the 1.3 mA stress electric current I_b and it is reduced stepwisely according to the increase of the stress electric current I_b .

In FIG. 8, the characteristics of the samples 80, 81 are determined by the pin hole presence ratio in the tunnel barrier layer. That is, in the case pin holes are not present or the presence ratio is small in the tunnel barrier layer, the barrier type destruction behavior deteriorates drastically beyond a certain critical voltage (the vicinity of 3.3 mA stress electric current I_b), as in the case of the sample 80.

In contrast, in the case the pin hole ratio in the tunnel barrier layer is large, since the electric current is concentrated in the pin hole parts, the electric current density is increased so as to cause the destruction by Joule heat. Moreover, as the deterioration behavior, the pin holes are enlarged and propagated successively according to the increase of the stress electric current so as to show the tendency of the stepwise TMR element deterioration (resistance reduction) as in the case of the sample 81. Therefore, it is confirmed that the voltage resistance of the tunnel barrier layer (BDV) becomes extremely low in the case the pin hole ratio is large in the tunnel barrier layer.

FIG. 9 shows an example of the breakdown voltage (BDV) with respect to the initial resistance value of the TMR element. In FIG. 9, the abscissa axis represents the initial resistance value, and the

ordinate axis represents the breakdown voltage (BDV). It is preferable that the breakdown voltage (BDV) is defined to be a value at the time when the resistance value deteriorates by 15% or more with respect to the initial resistance value.

As mentioned above, if pin holes are not present in the tunnel barrier layer or the presence ratio is small, the barrier type destruction behavior deteriorates drastically beyond a certain critical voltage, as in the case of the sample 80 of FIG. 8 (reference numeral 91). The barrier type destruction 91 denotes the behavior with 50% or more of the maximum deterioration ratio of the resistance value per 0.1 mA at the time of the breakdown. In contrast, since the destruction derived from the pin holes (reference numeral 90) is promoted with a smaller initial resistance, the BDV becomes lower. Here, the sample showing the barrier type destruction indicates a 500 mV or more BDV and a high voltage resistance, thus is excellent in terms of reliability.

FIG. 10 is a characteristic graph showing the relationship between the temperature coefficient TC and the breakdown voltage BDV (barrier type characteristic 100 and pin hole type characteristic 101).

As shown in FIG. 10, the TC and the BDV have an extremely good correlation. Therefore, merely

by measuring the temperature coefficient TC, not only the presence of pin holes can be determined but also the BDV can be predicted (evaluated) without the risk of breaking the TMR element.

5 In this case, the criterion for determining the quality control "pass" level for the tunnel barrier layer is " $TC > -0.03\%/^{\circ}C$ ". Moreover, in the case of " $TC > -0.03\%/^{\circ}C$ ", the tunnel barrier layer can have the durability of " $BDV > 500 \text{ mV}$ ".

10 (Configuration of the disk drive)

FIG. 12 is a block diagram showing the essential part of the magnetic head 2 with the TMR element of this embodiment mounted as the reading head 20A, and the disk drive storing the micro processor (CPU) 127
15 having the TMR element testing function.

The disk drive of this embodiment comprises a disk 120 fixed to a spindle motor (SPM) 121, to be rotated at a high speed, and an actuator 122 with the head 2 mounted. The head 2 has the reading head 20A
20 and the writing head 20B mounted.

The actuator 122 is driven rotatably by the driving force of a voice coil motor (VCM) 123 so as to move the head 2 in the disk 120 radius direction. The driving electric current for VCM 123 is supplied
25 from a VCM driver 129A included in a motor driver IC 129. The motor driver 129 including a SPM driver 129B together with the VCM driver 129A is controlled by the

CPU 127.

Furthermore, the disk drive comprises a preamplifier circuit 124, a R/W channel 125, a disk controller (HDC) 126, a CPU 127 and a memory 128.

5 The preamplifier circuit 124 comprises a writing amplifier 124A for supplying the recording electric current to be provided to a coil of the writing head 20B in addition to the reading amplifier for amplifying a reading signal outputted from the reading
10 head 20A.

 The R/W channel 125 is a signal processing IC for processing a reading/writing data signal. The HDC 9 has an interface function for a drive and a host system 140 (such as a personal computer or a digital
15 device).

 The CPU 127 as the main control device for the drive has the testing function of the TMR element (reading head 20A) of this embodiment. The memory 128 includes a RAM, a ROM, and the like in addition to a
20 flash memory (EEPROM) 110 as a nonvolatile memory for storing the program and data necessary for the control and the testing process of the CPU 127. Furthermore, the drive has a temperature sensor 130 for sensing the temperature in the drive. The CPU 127 monitors the
25 circumferential temperature of the head 2 according to the temperature detection from the temperature sensor 130.

The CPU 127 basically executes the determination (evaluation) of the temperature coefficient TC and the breakdown voltage BDV of the TMR element of the reading head 20A according to the testing process procedure shown in FIG. 11. As the element resistance measuring unit 6, the CPU 127 utilizes a reading signal outputted from a reading amplifier included in the preamplifier circuit 124.

Moreover, as the bias electric current control unit 5, the CPU 127 utilizes a bias electric current control circuit included in the preamplifier 124. That is, according to the control by the CPU 127, the preamplifier 124 supplies a bias electric current for the measurement (electric current 19 in FIG. 2) to the TMR element. The CPU 127 measures the resistance value of the TMR element (in the narrower meaning, the resistance value of the tunnel barrier layer 15) utilizing the reading signal outputted from the reading amplifier.

Moreover, as the temperature control unit 7, the CPU 127 controls the circumferential temperature of the reading head 20A (TMR element) by providing the recording electric current to the coil of the writing head 20B by controlling the writing amplifier 124A.

The disk drive need not store all the configurations for realizing the testing function, and the CPU may execute only the testing process. In this

case, the configuration for providing the device corresponding to the element resistance measuring unit 6 and the temperature control unit 7 outside the disk drive and executing the resistance measurement and the temperature setting of the TMR element outside the disk drive may be adopted. The device corresponding to the temperature control unit 7 refers to a heater, a laser, a constant temperature vessel, or the like. In the case of a testing method by such a disk drive, the special testing device as shown in FIG. 1 may be omitted.

As heretofore mentioned, according to the head testing method of this embodiment, presence of pin holes (defect part) in the tunnel barrier layer can be tested by a non destructive inspection by calculating or measuring the temperature coefficient TC and the breakdown voltage BDV of the TMR element comprising the reading head.

In other words, the state of the pin holes (pin hole ratio, or the like) generated in the tunnel barrier layer included in the TMR element can be tested by a non destructive test method.

Therefore, the quality of the TMR element can be tested efficiently and accurately so that a TMR element with a quality defect can be screened preliminarily. Furthermore, the testing method of this embodiment can be introduced to a shipping

testing process of a TMR element as a product or a disk drive with the TMR element mounted.

Additional advantages and modifications will readily occur to those skilled in the art. Therefore,
5 the invention in its broader aspects is not limited to the specific details and representative embodiments shown and described herein. Accordingly, various modifications may be made without departing from the spirit or scope of the general inventive concept as
10 defined by the appended claims and their equivalents.

WHAT IS CLAIMED IS:

1. An apparatus for testing a magnetic head that includes a tunneling magnetoresistive effect element (TMR element), comprising:

5 a measuring unit which measures the resistance value of the TMR element;

 a calculating unit which calculates the temperature coefficient with respect to the resistance value of the TMR element based on a relationship between the
10 resistance value and a circumferential temperature of the TMR element;

 a unit which calculates the breakdown voltage of the TMR element according to the temperature coefficient; and

15 a determining unit which determines a pin hole state in a tunnel barrier layer included in the TMR element based on the temperature coefficient and evaluates the characteristics of the tunnel barrier based on the breakdown voltage.

20 2. The apparatus according to claim 1, further comprising:

 a temperature control unit which controls the circumferential temperature of the TMR element.

 3. The apparatus according to claim 1, further
25 comprising:

 an electric current control unit to provide a bias electric current to the tunnel barrier layer by

using an electrode layer included in the TMR element,
wherein

the measuring unit measures the resistance value
of the tunnel barrier layer based on the bias electric
5 current provided by the electric current control unit.

4. The apparatus according to claim 1, wherein
the TMR element has a tunnel multi layer film with
a structure having the tunnel barrier layer provided
between a first ferromagnetic layer and a second
10 ferromagnetic layer as the intermediate layer.

5. A disk drive comprising:
a magnetic head which has a reading head using
a tunneling magnetoresistive effect element (TMR
element), and a writing head for generating a
15 recording magnetic field according to a recording
electric current provided in a coil, and which
executes a data reading operation or writing operation
to a disc medium; and

a controller to control a circumferential
20 temperature of the TMR element by controlling the
electric current to be supplied to the coil of the
writing head at the time of a testing process for
calculating a temperature coefficient with respect
to a resistance value of the TMR element;

25 a measuring unit which measures the resistance
value of the TMR element by providing an electric
current to the TMR element;

a unit which calculates the temperature coefficient with respect to the resistance value of the TMR element based on a relationship between the resistance value of the circumferential temperature
5 of the TMR element;

a unit which calculates the breakdown voltage of the TMR element according to the temperature coefficient; and

a determining unit which determines a pin hole
10 state of a tunnel barrier layer included in the TMR element based on the temperature coefficient and evaluates the characteristics of the tunnel barrier layer based on the breakdown voltage.

6. A method of testing a magnetic head that
15 includes a tunneling magnetoresistive effect element (TMR element), the method comprising:

setting a circumferential temperature of the TMR element;

measuring a resistance value of the TMR element
20 by providing an electric current to the TMR element;

calculating a temperature coefficient with respect to the resistance value of the TMR element based on a relationship between the resistance value and the circumferential temperature of the TMR
25 element;

determining a pin hole state of a tunnel barrier layer included in the TMR element based on the

temperature coefficient;
calculating the breakdown voltage of the TMR element
according to the temperature coefficient for
evaluating the characteristics of the tunnel barrier
5 layer based on the breakdown voltage.

7. The method according to claim 6, wherein
the calculating the temperature coefficient calculates
the temperature coefficient using a setting value
and a measurement value after executing each for a
10 plurality of times the setting of the circumferential
temperature of the TMR element and the measurement of
the resistance value.