

REDUCTION OF POWER CONSUMPTION IN INTEGRAL ULTRA-WIDEBAND POWER AMPLIFIERS

BACKGROUND OF THE INVENTION

5 1. TECHNICAL FIELD

The present invention relates to the field of power amplifiers, and more particularly, to reducing power consumption in integral ultra-wideband power amplifiers.

2. DISCUSSION OF RELATED ART

10 Low power consumption is important for mobile operation such as communication and radar equipment. These types of equipment may be operated in a wideband frequency range, for which multi octave Power Amplifiers are often used. The power consumption of the Power Amplifier (PA) is usually a major part of the total power consumption. Ultra-Wideband (multi octave) PA has a low power added efficiency (PAE). Generally, distributed amplifier architectures are used
15 for this type of amplifiers. For RF (radiofrequency) pulses operation with duty cycle less than 50%, the power consumption of the amplifier during the quiet time slots between the pulses still continues, although no RF power exists at the amplifier input. Conventional methods for reducing power consumption during the quiet slots between pulses are based on PA bias voltage control (via gate and drain amplifier ports). For example, U.S. Patent Publication Nos. 2003011433,
20 2006039449, 2010220774 and 2010226411, as well as Chinese Patent Publication Nos. 102098064 and 102891691 which are incorporated herein by reference in their entirety, disclose various ways of reducing the power consumption of power amplifiers.

SUMMARY OF THE INVENTION

25 The following is a simplified summary providing an initial understanding of the invention. The summary does not necessarily identify key elements nor limit the scope of the invention, but merely serves as an introduction to the following description.

One aspect of the present invention provides a power amplification unit comprising an integral ultra-wideband (UWB) power amplifier (PA) having a RF (radio frequency) input for receiving a
30 RF input signal, a PA output for providing an amplified output, the UWB PA operated by control and power supply voltages; a combiner configured to receive a RF signal and an auxiliary signal and to generate therefrom, the RF input signal to the UWB PA; a signal generator configured to

generate the auxiliary signal to have a pulse-shaped component derived from the RF signal and a quiet period component, the auxiliary signal having a frequency spectrum lower than a cutoff RF frequency; and an output matching circuit connected to the PA output and having signal filtering parameters selected to pass the amplified output above the cutoff RF frequency which is lower than a frequency of the RF signal.

These, additional, and/or other aspects and/or advantages of the present invention are set forth in the detailed description which follows; possibly inferable from the detailed description; and/or learnable by practice of the present invention.

BRIEF DESCRIPTION OF THE DRAWINGS

For a better understanding of embodiments of the invention and to show how the same may be carried into effect, reference will now be made, purely by way of example, to the accompanying drawings in which like numerals designate corresponding elements or sections throughout.

In the accompanying drawings:

Figure 1 is a high level schematic block diagram of a power amplification unit, according to some embodiments of the invention.

Figure 2 schematically illustrates of exemplary signals in the power amplification unit, according to some embodiments of the invention.

Figure 3 is a high level flowchart illustrating a method, according to some embodiments of the invention.

DETAILED DESCRIPTION OF THE INVENTION

In the following description, various aspects of the present invention are described. For purposes of explanation, specific configurations and details are set forth in order to provide a thorough understanding of the present invention. However, it will also be apparent to one skilled in the art that the present invention may be practiced without the specific details presented herein. Furthermore, well known features may have been omitted or simplified in order not to obscure the present invention. With specific reference to the drawings, it is stressed that the particulars shown are by way of example and for purposes of illustrative discussion of the present invention only, and are presented in the cause of providing what is believed to be the most useful and readily understood description of the principles and conceptual aspects of the invention. In this regard, no attempt is made to show structural details of the invention in more detail than is

necessary for a fundamental understanding of the invention, the description taken with the drawings making apparent to those skilled in the art how the several forms of the invention may be embodied in practice.

Before at least one embodiment of the invention is explained in detail, it is to be understood that the invention is not limited in its application to the details of construction and the arrangement of the components set forth in the following description or illustrated in the drawings. The invention is applicable to other embodiments that may be practiced or carried out in various ways as well as to combinations of the disclosed embodiments. Also, it is to be understood that the phraseology and terminology employed herein is for the purpose of description and should not be regarded as limiting.

Unless specifically stated otherwise, as apparent from the following discussions, it is appreciated that throughout the specification discussions utilizing terms such as "processing", "computing", "calculating", "determining", "enhancing" or the like, refer to the action and/or processes of a computer or computing system, or similar electronic computing device, that manipulates and/or transforms data represented as physical, such as electronic, quantities within the computing system's registers and/or memories into other data similarly represented as physical quantities within the computing system's memories, registers or other such information storage, transmission or display devices. Any of the disclosed modules or units may be at least partially implemented by a computer processor.

In the prior art, the implementation of fast bias control (duration less than 100ns) is very difficult and power consuming due to high capacitance of the bias circuits. For cases in which very short RF pulses are used (e.g., ultra-wideband waveform, where pulse duration is less than 5ns and duty cycle less than 50%), the mentioned conventional methods of power reduction can't be used. Embodiments of the present invention provide efficient and economical method and mechanism for operating ultra-wideband PA's, particularly with RF signals having a low duty cycle (less than 50%).

Power amplification units and methods are provided, which use a combiner and an auxiliary signal to feed the power amplifier (PA) with a signal that prevents or reduces operation of higher amplification stages during off periods of the received RF signal. The disclosed invention provides ultra-wideband (UWB) power amplifiers (PA) for use e.g., in communications, in radars and radar imaging systems, etc.

The combiner combines the RF signal and the auxiliary signal through respective filters to generate the RF input signal to the PA and an output matching circuit is connected to the PA output and has signal filtering parameters selected to pass the amplified output above a cutoff RF frequency which is lower than a frequency of the RF signal. An auxiliary signal generator may be configured to generate the auxiliary signal with relation to the RF signal as having a frequency spectrum lower than the cutoff RF frequency. Resulting lower power consumption, particularly in case of low duty cycle RF signals, reduces heating, enables longer battery use and increases reliability performance.

Figure 1 is a high level schematic block diagram of a power amplification unit **100**, according to some embodiments of the invention. Power amplification unit **100** comprises an ultra-wideband (UWB) power amplifier (PA) **80** with control and supply voltages **82** and having a PA RF (radio frequency) input **81** for receiving an RF input signal. UWB PA **80** may comprise an integral UWB PA, a multi-octave PA (MOPA), a monolithic microwaves integrated circuit (MMIC) PA etc. PA **80** is controlled by PA control and supply voltages **82** ensuring PA DC (direct current) bias.

Power amplification unit **100** further comprises a combiner **120** (e.g., a duplexer, a multiplexer or any other unit for combining signals) configured to receive a RF signal **90** and an auxiliary signal **110** and to generate therefrom the RF input signal (**81**) to PA **80**. Combiner **120** may comprise no, one two or more filters; optionally filters may be connected at one or more inputs to the combiner. In a non-limiting example, combiner **120** may comprise a high pass filter (HPF) **121** and a low pass filter (LPF) **122** configured to pass RF signal **90** and auxiliary signal **110**, respectively, preventing interference and mutual disturbances between RF signal **90** and auxiliary signal **110**. Alternatively or complementarily, combiner **120** may comprise two or more bandpass filters at respective frequency ranges. Auxiliary signal **110** comprises a signal at a lower frequency than RF signal **90**, generally having its spectrum width according to the PRF (pulse repetition frequency), e.g., up to $1/\tau$, where τ is the pulse duration of RF signal **90**. One or more filters **121**, **122** may be part of combiner **120** or be set at one or more inputs to combiner **120**. Auxiliary signal **110** is configured to significantly reduce or prevent amplification and power consumption by PA **80** during periods between pulses of RF signal **90**.

Power amplification unit **100** further comprises an output matching circuit **86** connected to a PA output **78** of PA **80** and having signal filtering parameters selected to pass the amplified output above a cutoff RF frequency which is lower than a frequency of RF signal **90**. Output matching

circuit **86** may be configured to receive and pass with minimum loss only (or mainly) the amplified output from PA **80** and attenuate auxiliary signal **110**. For example, output matching circuit **86** may comprise LC components (capacitor(s) and/or coil(s)) such as an RF choke coil (L), a DC block, capacitors (C), etc.

5 Power amplification unit **100** further comprises signal generator **130** having for example an RF signal generator **132** configured to generate RF signal **90**, e.g., from digital data input **71**, and an auxiliary signal generator **134** configured to generate auxiliary signal **110** to have a pulse-shaped component **111** derived from RF signal **90** (e.g., an envelope or a modified envelope thereof) and a quiet period component **112** (e.g., a DC level in a non-limiting manner) selected to be
10 attenuated or removed by output matching circuit **86**. In certain embodiments, auxiliary signal generator **134** may be in communication with RF generator **132**, be integrated therein and/or receive same digital data input **71** and signal generator **130** may be configured to generate both RF signal **90** and auxiliary signal **110** simultaneously to maintain synchronicity between them and avoid delay.

15 Alternatively or complementarily, auxiliary signal generator **134** may be configured to receive RF signal **90** and generate pulse-shaped component **111** of auxiliary signal **110** as an envelope of RF signal **90** and/or as a modified envelope of RF signal **90**, based on its envelope, and further comprising adjustments of various envelope features (e.g., start, end, shape, etc.) to prevent or reduce high frequency components of auxiliary signal **110**. Pulse-shaped component **111** may be
20 optimized for spectrum mask quality and Error Vector Magnitude (EVM) quality of the amplified output with respect to a PA power consumption.

In certain embodiments, auxiliary signal generator **134** may comprise an envelope detector **134A** configured to detect an envelope **91** of RF signal **90** and generate corresponding pulse-shaped component **111** of auxiliary signal **110** therefrom. Alternatively or complementarily, the shape of
25 envelope **91** may be selected to avoid changing RF signal **90** as well as to avoid introduction of noise upon changes from quiet period component **112** (e.g., a DC or other low frequency signal) to pulse-shaped component **111**. The configuration of combiner **120** with filters **121**, **122** may be designed to prevent interaction between RF signal **90** and auxiliary signal **110**.

UWB PA **80** (e.g., an integral UWB PA) may be configured to amplify RF pulsed signal **91**.
30 Output matching circuit **86** may be configured to pass with minimum loss only RF signal **90** from UWB PA **80** and to reduce significantly auxiliary signal **110** and prevent it from loading the amplification stages of UWB PA **80**.

The cutoff RF frequency of output matching circuit **86** may be selected to pass RF signal **90** and attenuate auxiliary signal components such as pulse-shaped component **111** and quiet period component **112**. For example, the cutoff RF frequency may be set according to any specifications of PA **80**, RF signal **90** and auxiliary signal **110**, e.g., anywhere between 300MHz and 2GHz, 3GHz or beyond. For example, in a non-limiting case, if the $1/\tau$ is around 500MHz (corresponding to a pulse duration of 2ns) and RF signal **90** is at 4GHz, the cutoff RF frequency may be set between these frequencies. For example, output matching circuit **86** may comprise a high-pass filter at 3GHz (e.g., a corresponding passive LC circuit) to minimize loss to the RF signal while attenuating the auxiliary signal. It is noted that PA **80** should be selected to operate in both frequency ranges, that of RF signal **90** and auxiliary signal **110**, and may be implemented, e.g., as a multi-octave PA.

In certain embodiments, combiner **120** may be configured to offset RF signal **90** by adding a DC level to it (as quiet period components **112** of auxiliary signal **110**), which is selected according to levels of the PA control and supply voltages **82**. The signal filtering parameters of output matching circuit **86** ensure a low gain of late amplification stages of PA **80** for the auxiliary signal **110**.

Power amplification unit **100** may thus be configured to provide a significant reduction of power consumption by an off-the-shelf integral PA, not requiring performing any internal modifications of the PA (e.g., PA **80** may be operated without changing control voltages **82**). Combiner **120** and auxiliary signal **110** are configured to reduce PA power consumption when idle (i.e., no RF amplification needed), by shifting the PA's internal working point to a non-amplifying state (inactive final amplification stage(s) of the PA) due to the parameters of auxiliary signal **110**. During active periods (RF amplification), auxiliary signal **110** is configured to shift the PA's internal working point for amplification of the RF signal **90** (when the PA is open).

Quiet period component **112** (e.g., a DC level) of auxiliary signal **110** may be selected according to levels of the PA control and supply voltages **82** to set the PA's internal working point in the non-amplification state (when the PA is closed) to a point that reduces a power consumption of PA **80** with respect to a power consumption thereof when receiving a zero RF input signal.

In certain embodiments, power amplification unit **100** may thus be configured to be switchable into an operation mode of direct RF input signal amplification, i.e., to operate without auxiliary signal **110** as a regular PA. For example, power amplification unit **100** may have a regular mode

of operation according to the prior art and an operation mode according to the disclosed invention, which are switchable according to user preferences.

Figure 2 schematically illustrates exemplary signals in power amplification unit **100**, according to some embodiments of the invention. **Figure 2** illustrates non-limiting examples of RF signal **90**, auxiliary signal **110**, PA RF input **81** combined by combiner **120** from RF signal **90** and auxiliary signal **110**, and RF output **79** (using the MMIC distributed PA HMC797L5 with DC-22GHz operation frequency range as the PA **80** and an L-C output matching circuit **86**). RF signal **90** is depicted as having pulses **90A** and quiet periods **90B** (alternating at PRF) and auxiliary signal **110** is depicted as having corresponding pulse-shaped component **111** (e.g., RF signal envelope) and quiet period component **112** (e.g., approximately DC, due to implementation factors). Combiner **120** generates PA RF input **81** from RF signal **90** and auxiliary signal **110** with corresponding signal periods **81A** and quiet periods **81B**. Due to this configuration of PA RF input **81**, PA **80** amplifies only input signal periods **81A** to yield output signal periods **79A** and not amplifying input quiet periods **81B** to yield output quiet periods **79B**. As illustrated in **Figure 2**, the power consumption of PA **80** is reduced and RF output **79** is cleaner than RF signal **90**.

In certain embodiments, power amplification unit **100** may be configured as an UWB transmitter comprising an UWB power amplifier which includes UWB integrated PA **80** having control and supply voltages **82** ensuring PA DC biasing, as well as a PA RF input **81** for receiving of RF signal **90** and output matching circuit **86** configured to pass with minimum loss only an amplified RF signal (from PA output **78**) from UWB integrated PA **80** to a RF output **79**. Power amplification unit **100** may further comprise combiner **120** (e.g., a duplexer or a multiplexer) configured to combine RF signal **90** and auxiliary signal **110**, through respective high frequency filter **121** and low frequency filter **122** and to deliver the combined signal to PA RF input **81**. Power amplification unit **100** may further comprise signal generator **130**, which comprises RF signal generator **132** having digital data input **71** and auxiliary signal generator **134** interfaced with RF signal generator **132**. RF signal generator **132** may be configured to deliver desired RF pulses as RF signal **90** and auxiliary generator **134** may be configured to generate auxiliary pulses as auxiliary signal **110**, which is synchronized with envelope **91** of RF pulses signal **90**. The amplitude and the duration of the auxiliary pulses may be selected to switch UWB PA **80** on during the RF pulses and to switch UWB PA **80** off during the quiet time slot between the RF pulses.

In certain embodiments, power amplification unit **100** may be configured as an UWB transmitter comprising signal generator **130**, which includes RF signal generator **132** having digital data input **71** and auxiliary signal generator **134** interfaced with RF signal generator **132**. RF signal generator **132** may be configured to deliver RF signal **90** and auxiliary generator **134** may be configured to generate auxiliary signal **110**, which is synchronized with envelope **91** of desired RF pulses signal **90**, as explained above. Output matching circuit **86** may be configured to pass with minimum loss only the output RF signal from UWB integrated PA **80** to RF output **79**. Auxiliary generator **134** may be configured to receive RF input signal **90** and generate auxiliary signal **110** therefrom using envelope detector **134A**.

Figure 3 is a high level flowchart illustrating a method **200**, according to some embodiments of the invention. These method stages are described in more detail with respect to power amplification unit **100** described above and optionally configured to implement method **200**. Method **200** comprises combining (e.g., duplexing) an RF signal with an auxiliary signal to provide an RF input signal to an ultra-wideband power amplifier (stage **210**), wherein the auxiliary signal is generated to have a pulse-shaped component derived from the RF signal and a quiet period component. Method **200** further comprises delivering an amplified output from the integral ultra-wideband PA through an output matching circuit having signal filtering parameters selected to pass the amplified output above a cutoff RF frequency (stage **215**). The cutoff RF frequency is set to be lower than the frequency of the RF signal and higher than the frequency spectrum of the auxiliary signal. Method **200** further comprises generating the auxiliary signal to have a pulse-shaped component derived from the RF signal (e.g., its envelope or modified envelope) and a quiet period component (e.g., a DC level) selected according to the PA control and supply level and/or the output matching circuit parameters (stage **220**).

Method **200** may further comprise selecting the signal filtering parameters to attenuate the auxiliary signal in the amplified output (stage **215**). The cutoff RF frequency may be set according to any specifications of the PA, the RF signal and the auxiliary signal, e.g., anywhere between 300MHz, 500MHz and 2GHz, 3GHz or beyond. For example, if the $1/\tau$ is around 500MHz (corresponding pulse duration of 2ns) and the RF signal is at 4GHz, the cutoff RF frequency may be set between these frequencies.

Method **200** may further comprise operating the PA without changing control and power supply voltages thereof (stage **250**), with the quiet period component (e.g., a DC or a low frequency level) of the auxiliary signal selected to reduce a power consumption of the PA with respect to a

power consumption thereof when receiving a zero RF input signal (stage **230**). The pulse-shaped component may be optimized for spectrum mask quality and EVM quality of the amplified output with respect to a PA power consumption.

Method **200** may further comprise generating the auxiliary signal from digital data input that is used to generate the RF signal as well (stage **240**) and/or generating the auxiliary signal according to a detected envelope of the RF signal (stage **250**).

Auxiliary signal **110** which is fed into PA **80** may be synchronized with envelope **91** of desired RF pulses signal **90**. Auxiliary signal **110** may be configured to open PA **80** during the RF pulses, and close PA **80** during the quiet time slot between the RF pulses by providing quiet period component **112** which removes PA **80** from its amplification working point and/or is not amplified by PA **80** due to the configuration of the output matching circuit. When PA **80** is closed or inoperative, its power consumption is significantly decreased. Power saving is enhanced as the RF signal's duty cycle is decreased, and further contributed to enhanced reliability of PA **80**. Moreover, the PA may be operated at a higher gain than in the prior art, as heating is avoided between actual RF pulses.

Auxiliary signal generator **130** may be configured to avoid providing auxiliary signal **110** and/or to modify parameters of auxiliary signal **110** according to different operation schemes.

Power amplification unit **100** and method **200** were tested experimentally using a distributed PA (HMC797L5) operating in the frequency range of DC to 22GHz and RF pulses having a center frequency of 4.02GHz, pulse rate of 125MHz, pulse duration of about 2ns, peak to average power ratio (PAPR) of about 6 dB, a RMS (root mean square) channel power at 500M BW of RF signal was varied from 11.3dBm to 13.5dBm. A simple combiner (IL- insertion loss $\leq$ 1dB) was used for simultaneous feeding of RF and auxiliary signal to PA RF input **81**. Power amplification unit **100** and method **200** achieved total power consumption reduction (including power needed for production of the auxiliary signal) by 30-40%. The total power consumption was reduced by 1.15W for 23.8dBm RMS channel power, and by 1.35W for 22.4dBm RMS channel power. The influence of the auxiliary signal on signal parameters was minimal - PAPR increased by 0.3-1dB, weak improvement of Error Vector Magnitude (EVM) ($\sim$ 1dB) and weak adjacent channel power ratio (ACPR) degradation ($\sim$ 1-3dB) were measured.

Advantageously, power amplification unit **100** and method **200** provide significant PA improvement that reduces PA power consumption; provide fast control of PA power consumption while not or weakly influencing the PA output signal quality; and can be implemented by simple

means and at low cost. In particular, in battery operated PA applications, power amplification unit **100** and method **200** may enable significant increases in battery utilization time, particularly when the RF signal's duty cycle is low.

In the above description, an embodiment is an example or implementation of the invention. The
5 various appearances of "one embodiment", "an embodiment", "certain embodiments" or "some
embodiments" do not necessarily all refer to the same embodiments. Although various features of
the invention may be described in the context of a single embodiment, the features may also be
provided separately or in any suitable combination. Conversely, although the invention may be
described herein in the context of separate embodiments for clarity, the invention may also be
10 implemented in a single embodiment. Certain embodiments of the invention may
include features from different embodiments disclosed above, and certain embodiments may
incorporate elements from other embodiments disclosed above. The disclosure of elements of the
invention in the context of a specific embodiment is not to be taken as limiting their use in the
specific embodiment alone. Furthermore, it is to be understood that the invention can be carried
15 out or practiced in various ways and that the invention can be implemented in certain
embodiments other than the ones outlined in the description above.

The invention is not limited to those diagrams or to the corresponding descriptions. For example,
flow need not move through each illustrated box or state, or in exactly the same order as
illustrated and described. Meanings of technical and scientific terms used herein are to be
20 commonly understood as by one of ordinary skill in the art to which the invention belongs, unless
otherwise defined. While the invention has been described with respect to a limited number of
embodiments, these should not be construed as limitations on the scope of the invention, but
rather as exemplifications of some of the preferred embodiments. Other possible variations,
modifications, and applications are also within the scope of the invention. Accordingly, the scope
25 of the invention should not be limited by what has thus far been described, but by the appended
claims and their legal equivalents.

CLAIMS

What is claimed is:

1. A power amplification unit comprising:
 - an integral ultra-wideband (UWB) power amplifier (PA) having a RF (radio frequency) input for receiving a RF input signal, a PA output for providing an amplified output, the UWB PA operated by control and power supply voltages,
 - a combiner configured to receive a RF signal and an auxiliary signal and to generate therefrom, the RF input signal to the UWB PA,
 - a signal generator configured to generate the auxiliary signal to have a pulse-shaped component derived from the RF signal and a quiet period component, the auxiliary signal having a frequency spectrum lower than a cutoff RF frequency, and
 - an output matching circuit connected to the PA output and having signal filtering parameters selected to pass the amplified output above the cutoff RF frequency which is lower than a frequency of the RF signal.
2. The power amplification unit of claim 1, wherein the combiner is configured to generate the RF input signal to the UWB PA through at least one filter thereof.
3. The power amplification unit of claim 1, wherein the combiner is configured to generate the RF input signal to the UWB PA through at least two filters thereof, which correspond to frequency ranges of the RF signal and the auxiliary signal, respectively.
4. The power amplification unit of claim 1, further comprising at least one filter connected at one or more inputs of the combiner.
5. The power amplification unit of claim 1, further comprising at least two filters connected at one or more inputs of the combiner and corresponding to frequency ranges of the RF signal and the auxiliary signal, respectively.
6. The power amplification unit of claim 1, further configured to be switchable into an operation mode of direct RF input signal amplification.
7. The power amplification unit of claim 1, wherein the UWB PA is operated without changing the control and power supply voltages.
8. The power amplification unit of claim 1, wherein the pulse-shaped component is related to an envelope of the RF signal.

9. The power amplification unit of claim 1, wherein the pulse-shaped component is optimized for spectrum mask quality and Error Vector Magnitude (EVM) quality of the amplified output with respect to a PA power consumption.
10. The power amplification unit of claim 1, wherein the quiet period component of the auxiliary signal is selected to reduce a power consumption of the UWB PA with respect to a power consumption thereof when receiving a zero RF input signal.
11. The power amplification unit of claim 1, wherein the signal generator is configured to receive digital data input and to generate therefrom the RF signal and the auxiliary signal.
12. The power amplification unit of claim 1, wherein the signal generator comprises an envelope detector configured to detect an envelope of the RF signal and generate the corresponding pulse-shaped component of the auxiliary signal therefrom.
13. The power amplification unit of claim 1, wherein the combiner comprises a duplexer having a high pass filter and a low pass filter.
14. The power amplification unit of claim 1, wherein the at least two filters of the combiner comprise at least one band pass filter.
15. The power amplification unit of claim 1, wherein the output matching circuit comprises a band-stop filter configured to attenuate the auxiliary signal in the amplified output signal.
16. The power amplification unit of claim 1, wherein the cutoff RF frequency is set between 300MHz and 3GHz.
17. A method comprising:
 - combining an RF signal with an auxiliary signal to provide an RF input signal to an integral UWB PA, wherein the auxiliary signal is generated to have a pulse-shaped component derived from the RF signal and a quiet period component, and
 - delivering an amplified output from the UWB PA through an output matching circuit having signal filtering parameters selected to pass the amplified output above a cutoff RF frequency, wherein the cutoff RF frequency is lower than a frequency of the RF signal and the auxiliary signal is configured to have a frequency spectrum lower than the cutoff RF frequency.
18. The method of claim 17, further comprising operating the UWB PA without changing control and power supply voltages thereof, with the quiet period component of the auxiliary signal selected to reduce a power consumption of the UWB PA with respect to a power consumption thereof when receiving a zero RF input signal.

19. The method of claim 17, wherein the pulse-shaped component is related to an envelope of the RF signal.
20. The power amplification unit of claim 1, further comprising optimizing the pulse-shaped component for spectrum mask quality and EVM quality of the amplified output with respect to a PA power consumption.