

Description

The present invention relates to a pager decoding system for use in a paging system employing a standard code such as the CCIR Radiopaging Code No. 1, otherwise known as POCSAG (British Post Office Code Standardisation Advisory Group).

Although the POCSAG code is becoming widely known, in order to understand the present invention it is worth mentioning the signal and code word formats of POCSAG and in this respect reference is made to Figures 1 and 2 of the accompanying drawings. Figure 1 shows the signal format which comprises a preamble 10 of at least 576 bits, which comprises alternate ones and zeroes, and a series of batches 12, 14 each of 544 bits. The preamble 10 at its shortest has a duration of a number of bits corresponding to one of the batches plus a thirty-two bit code word. A batch 12 or 14 comprises a thirty-two bit synchronisation code word 16 and eight frames 18, each of which frames comprises two code words 20 each of thirty-two bits length. Thus each batch 12, 14 is formed by seventeen code words 20 each of 32 bits.

There are two types of code word 20, i.e. address code words 22 and message code words 24. The first bit of a code word determines whether it is an address code word because its value is then zero, or whether it is a message code word because its value is then one. In the case of an address code word, bits 2 to 19 are address bits corresponding to the eighteen most significant bits of a twenty-one bit identity assigned to the paging receiver. The three least significant bits are not transmitted but serve to define the frame within a batch in which the address code word must be transmitted. Four discrete addresses are assigned to each paging receiver having a given twenty-one bit identity, selection of a particular one of the four addresses is according to the values assigned to the bits 20 and 21. Bits twenty-two to thirty-one are cyclic redundancy check bits and the final bit, bit 32, is chosen to give even parity on the complete code word.

In the case of a message code word 24 the bits 2 to 21 are assigned as message bits which do not follow the allocations of the address code word 22, however bits 22 to 32 do.

A batch is formed by a synchronisation code word which precedes in time sixteen other code words. Since the identity of a paging receiver is defined by an address code word 22 transmitted in a given time frame 18 within a batch 12, 14, then it is unnecessary for the paging receiver to receive any address code words other than those in its allocated frame. Thus the paging receiver may switch off when other frames are being transmitted thus providing a battery saving capability. In any transmission of a batch, an idle (unallocated) address code word is transmitted in the event that a particular code word location within that batch is not required for the transmission of a paging call.

A paging call requiring transmission of message code words 24 is formatted such that an appropriate number of message code words 24 related to the length of the message are concatenated onto one

of the address code words 22 assigned to the particular paging receiver. Although message code words 24 (Figure 2) may continue into a subsequent batch due to the length of the messages, the normal batch structure, that is sixteen code words 20 preceded by a synchronisation code word 16, is maintained.

With the POCSAG signalling structure, a paging decoder has to synchronize itself first with the preamble 10 and second with the synchronisation code word 16. Unless the paging decoder is synchronised to the synchronisation code word, it will be unable to decode successfully address code words in their assigned frame.

In operation, a paging receiver in its carrier-off mode when there are no transmissions from its base station is usually switched on once every seventeen code words for a duration of a thirty-two code word in order to detect the preamble bit pattern which may be transmitted. As the preamble for POCSAG is at least eighteen code words in duration it will quickly be detected. Thereafter the paging receiver is continuously energised for a duration of eighteen code words in order to detect the synchronisation code word 16 which is concatenated onto the preamble 10. Thereafter the paging receiver assumes its data receive mode and switches its receiver section off until its assigned time frame and then switches it on for that time frame in order to decode address code words. Then the decoder will be switched off until the time slot allocated to the synchronisation code word in a subsequent concatenated batch, the decoder is then switched on in order to decode that synchronisation code word and subsequently the address code word in the following allocated frame. If the synchronisation code word is not detected then the paging decoder may not decode address code words in the allocated subsequent time frame. Thus it is essential to achieve and maintain word synchronisation. It is important that synchronisation and address code words are decoded acceptably in order to keep a sufficiently low falsing rate.

British Patent Specification 2 086 106A discloses a pager decoding circuit with an intelligent synchronisation circuit. This known circuit employs a synchronisation strategy which tolerates at least some degree of error in an attempt to achieve batch synchronisation. The decoding circuit includes means for examining the received bit pattern in order to search initially for the presence of preamble. When a match or near match to the preamble bit pattern is detected, the decoding circuit examines the received bit pattern for the synchronisation code word. When a match or a near match to the synchronisation code word is achieved the decoding circuit is deemed to be in batch synchronisation in which case it is then able to examine the address code words in its assigned frame in order to detect the receipt of a paging call.

The decoding circuit then examines each synchronisation time slot in subsequent batches in order to detect the synchronisation code word in those batches and thereafter detect address code words in the allocated time frame within those batches. If a match between the received bit pattern and the stored reference synchronisation code word is not achieved nor a near match to a certain number of bits

in error is obtained then the address frame is not examined for address code words. If the synchronisation code word is again not detected in the time slot allocated for the synchronisation code word in the next following batch, assuming that a batch has been transmitted, then the decoding circuit deems that batch synchronisation has been lost and thence reverts to its carrier-off mode in which it examines the received bit pattern for the preamble bit pattern or a near match to it.

When examining the received bit pattern for preamble the known circuit switches on for one code word slot in each batch, as before, thus guaranteeing detection of preamble if it is being transmitted. Once preamble has been detected the receiver then examines the bit pattern for the synchronisation code word. When this has been detected the known circuit assumes a data receive mode as described previously.

This known decoding circuit has two drawbacks. Firstly it cannot resume correct batch synchronisation should a long fade, greater than eighteen code word (worst case) occur, causing irrecoverable errors in the received bit pattern because the circuit will have reverted to preamble detection operation in a carrier-off mode whilst coded data is still being transmitted. Consequently the probability of detecting preamble in coded data is very low causing batches of data (e.g. addresses) to be overlooked. The second drawback in the operation of this known decoding circuit may occur if the paging receiver is used in a heavily loaded, zoned, transmission system. A zoned transmission system as specified within the POCSAG description would allow for the transmission of a preamble immediately concatenated to the end of a batch of code words should the paging receiver be in an overlap region of two transmission zones and the data transmission period in the former zone be continuous for the complete zone time period. Under such circumstances the known circuit would not detect the transmitted preamble (assuming that the received bit pattern is decodable as preamble) since immediately following failure to detect a synchronisation code word, as would occur at the end of transmission on one zone or in an unzoned system, the known decoder will be only examining the received bit pattern for the following synchronisation code word which will not be present because preamble is being transmitted.

It is the object of this present invention to recover and maintain batch synchronisation more effectively than is possible in the prior art system.

According to the present invention there is provided a pager decoding system suitable for use with a signal format in which code words of m bits are sent in batches of n code words, each batch containing a synchronisation code word and $(n-1)$ address/message code words, the system being characterised by timing means for switching-on a receiver section of the pager for a duration corresponding to m bits at intervals corresponding to $(n+1)$ code words, shift register means for storing data received during the m bit period, the shift register having m stages and the data being concatenated onto the data received in the previous interval, and preamble

and synchronisation code word detecting means coupled to the shift register means, the detecting means producing output signals in response to a preamble bit pattern being detected or a synchronisation code word being detected, one of said output signals, produced in response to the detection of the preamble, being used to set the timing means to wait for synchronisation code word detection, another of said output signals, produced in response to the detection of the synchronisation code word, being used to reset the timing means so that the pager operates in a data receive mode.

The pager decoding system in accordance with the present invention enables a transmitted signal to be detected and properly synchronised if there has been a loss of signal due to a deep fade as well as due to the termination of a previous transmission and the commencement of a new one. Additionally the system is inherently capable of greater battery economy in the carrier-off mode because it is turned-on every $(n+1)$ code words rather than every n code words as is done in known POCSAG pagers.

The pager decoding system in accordance with the present invention may further comprise means for detecting the absence of a synchronisation code word when the pager is operating in its data receive mode, said means producing an output signal in response to detecting the absence of the synchronisation code word such that the pager operates in a fade recovery mode, which output signal is applied to the timing means, said timing means in response to the output signal enabling data input to the shift register for at least $(m+2)$ bit periods and activating the preamble and synchronisation code word detecting means for the $(m-1)$ th, m th and $(m+1)$ th bit periods in every n th code word, whereby in response to detecting preamble or a synchronisation code word the timing means is reset so that the pager operates in a data receive mode but if no synchronising code word is detected after a predetermined number of batches then the pager adopts a carrier-off mode in which data is switched into the shift register every $(n+1)$ code words.

By being able to examine the input signal in the fade recovery mode for a predetermined number of batches, the pager decoding system is capable of recovering synchronisation in the event of a fade lasting several batches whereas the cited known system reverts to a carrier-off mode very quickly which means that batch synchronisation is not achieved until a new transmission is made, i.e. preamble transmitted.

The present invention will now be described, by way of example, with reference to Figures 3 to 5 of the accompanying drawings, wherein:

Figure 3 is a block schematic circuit diagram of a paging receiver and shows those parts which are necessary for the understanding of the pager decoding system in accordance with the invention,

Figure 4 comprises waveform diagrams 4A to 4D which illustrate the change from the data receive mode to the fade recovery mode, and

Figure 5 comprises waveform diagrams 5A to 5E which illustrate the operation of the decoding system in its carrier-off mode.

The paging receiver 100 comprises a receiver section 102 which is turned-on and -off by a receiver power control circuit 104 which is controlled by a timer control circuit 106. A thirty-two stage shift register 108 is coupled to the receiver section 102. Output of each of the stages of the shift register 108 are coupled to an address detector 110 and to a preamble and synchronisation detector 112. In the interests of clarity not all 32 outputs have been shown. The detector 112 has two outputs 114, 116 on which appear respectively output signals indicating that the preamble bit pattern and synchronisation bit pattern have been detected. These outputs 114, 116 are connected to a preamble and synchronisation pulse generator 118. In response to an output signal on the output 114, the generator 118 produces a pulse on a line 120 and in a similar manner an output signal on the output 116 causes a pulse to be produced on the line 122. The lines 120 and 122 are coupled to the timer control circuit 106. A frame number store 124 which holds the number of the frame in which the address code word is transmitted is also coupled to the timer control circuit 106.

An address store 128 which stores the addresses allocated to the paging receiver 100 is coupled to the address detector 110. An output of the detector 110 is connected to an alert control circuit 130 which controls the energisation of an acoustic transducer 132. The timing control circuit has an output connected to the address detector 110.

Assuming that the paging receiver 100 is already in bit and batch synchronisation then the timing control circuit 106 causes the power control circuit 104 to energise the receiver section 102 at the synchronisation code word interval and the allocated frame interval in each batch. If an address allocated to the paging receiver 100 is detected then the alert control circuit 130 causes the transducer 132 to be energised.

The operation of the decoding system in the fade recovery and carrier-off modes will now be described with reference to Figures 4 and 5 of the accompanying drawings.

In Figure 4 the left-hand part refers to the data receive mode and the right-hand part refers to the fade recovery mode wherein the data is lost to the receiver, this is shown in broken lines in waveform diagram 4A.

In the data receive mode the preamble 10 (not shown in Figure 4) and the synchronisation code word 16 have been detected, the receiver is both bit synchronised and batch synchronised. This is shown in waveform diagram 4B wherein the receiver section 102 (Figure 3) is switched-on or powered-up at the intervals 40 to receive the synchronising code word 16.

The pulse generator 118 produces synchronising pulses 42, waveform diagram 4C, at times corresponding to the end of the parity bit, bit 32, of the synchronisation code words 16. These pulses, when generated, are used by the timing control circuit 106 to control the switching of the receiver 102 by means of signals to the receiver power control circuit 104 for the detection of address code words and to predict the time occurrence of the synchronisation

code word at the start of the subsequent batch by means of a counter within the timing control circuit 106 which produces an output every seventeenth code word in anticipation of the receipt of the subsequent synchronisation code word.

Once the synchronisation code word has been detected, the timing control circuit 106 switches off or powers down the receiver section 102 by means of the receiver power control circuit 104 until the frame 18 (Figure 1) in which its address code words are assigned, at which time the timing control circuit 106 switches on the receiver section 102 for the duration of that particular frame; this is denoted by the pulses 44 in diagram 4B. At the end of the address frame, the timing control circuit 106 switches off the receiver section 102 again until the start of the subsequent synchronisation code word time slot, at which time the receiver section 102 is again switched on in order to repeat the process.

When data is lost or corrupted beyond detection, say due to a fade in the received signal, as shown in broken lines in waveform 4A, the synchronisation code word cannot be detected when the receiver section 102 is switched on for the duration of the synchronisation code word time slot and no synchronising pulse is produced by the pulse generator 118. On failing to detect the first of these synchronisation pulses, denoted by an arrow 46 in timing diagram 4D, the timing control circuit 106 switches the pager from the data receive mode 48 to the fade recovery mode 50. As no synchronising pulse 42 is generated, the timing control circuit 106 inhibits the receiver power control circuit 104 so that the receiver section 102 is not switched on at the assigned address frame time slot. The timing control circuit 106 continues running and causes the receiver section 102 to be switched on every seventeenth code word time slot in order to attempt to retain synchronisation should the pager be in a deep fade such that data reception would be maintained when the fade ends. In the fade recovery mode it is not possible to determine whether true data is being received and hence whether bit synchronisation is being maintained. Thus in order to account for any timing errors introduced, the decoding system inspects the incoming data for preamble as well as for synchronisation code word just in case the loss of data is due to a cessation of transmission of data, at the 31st, 32nd and 33rd bit positions every seventeenth code word. The fade recovery mode is maintained for a predetermined number of batches, for example 30 batches, whereupon the timer control circuit 106 switches the decoding system to the carrier-off mode. The exact number of batches during which the fade recovery mode is maintained is a function of the stabilities of the transmitter and receiver data frequency crystal oscillators and of the characteristics of the bit synchronisation technique employed. In order to detect the synchronisation code word at the 31st bit position, the receiver section 102 is turned-on one bit earlier than is customary. In addition, to detect the synchronisation code word at the 33rd bit position the receiver section 102 is turned-off one bit later than is customary.

In the carrier-off mode the paging receiver section

102 is switched-on and the input signal is clocked into the 32-stage shift register 108 for 32 bit periods and then the receiver section 102 is switched-off. Outputs of the shift register stages are coupled in parallel to the preamble and synchronisation signal detector 112. Assuming that the preamble bit pattern or the synchronisation code word is not stored in the shift register 108 then precisely eighteen code words later the receiver section 102 is switched-on and another thirty-two bits are stored by being concatenated onto the already stored data. As each bit is clocked in a check is made by the synchronisation and preamble detector 112 to determine whether 32 bits of preamble or the synchronisation code word is present in the shift register 108. If preamble is detected which is indicative that a new transmission is being made then the synchronisation pulse generator 118 produces an output on the line 122 coupled to the timing control circuit 106 which maintains the receiver section 102 on until synchronisation code word is detected up to a maximum of eighteen code words duration should a synchronisation code word not be detected. If the synchronisation code word is detected, the pulse generator 118 produces a synchronising pulse which causes the timer control circuit 106 to switch the decoding circuit into the data receive mode.

If the loss of signal is due to a long fade then the first thing detected will be the synchronisation code word. Thus by switching-on the receiver section 102 every eighteen code words, the decoder is able to comb through all the relative bit positions in a batch in seventeen batch durations. By using the shift register 108 in the manner described it is possible to pick-up the synchronisation code word in spite of the fact that the switching-on and switching-off of the receiver section 102 is not synchronised to the incoming data. How this is done will be described with reference to Figure 5.

Waveform diagram 5A illustrates the incoming data with a synchronisation code word 16 every seventeen code words as is usual with the POCSAG code structure. Diagram 5B illustrates the switching-on of the receiver 102 every eighteen code words. Diagram 5C illustrates the blocks of 32 bits of data being read into the shift register 114. The left-hand block received first comprises 32 bits of which some are the first part X of a synchronisation code word. The next time the receiver section 102 is turned on the first data to be read-in is the second part Y of the subsequent synchronisation code word. At the instant that the concatenated parts X and Y are configured in the shift register to form a complete synchronisation code word, see diagram 5D, the synchronisation signal detector 112 recognises that the shift register 108 contains the synchronisation code word and causes the synchronising pulse generator 118 to produce a synchronisation pulse, diagram 5E, which is used by the timing control circuit 106 to reset the receiver power control circuit 104 so that the pager operates in a data receive mode as before.

Although the decoding system in accordance with the present invention has been described with particular reference to the POCSAG format, it is capable

of adaptation to other formats having a fixed length regular batch structure, each batch comprising a synchronisation code word whose position in a batch is fixed relative to address and/or message code words, and multiples of such batches being concatenated with the preceding preamble to form a transmitted signal.

Claims

1. A pager decoding system suitable for use with a signal format in which code words of m bits are sent in batches of n code words, each batch containing a synchronisation code word and $(n-1)$ address/message code words, the system being characterised by timing means for switching-on a receiver section of the pager for a duration corresponding to m bits at intervals corresponding to $(n+1)$ code words, shift register means for storing data received during the m bit periods, the shift register having m stages and the data being concatenated onto the data received in the previous interval, and preamble and synchronisation code word detecting means coupled to the shift register means, the detecting means producing output signals in response to a preamble bit pattern being detected or a synchronisation code word being detected, one of said output signals, produced in response to the detection of the preamble, being used to set the timing means to wait for synchronisation code word detection, another of said output signals, produced in response to the detection of the synchronisation code word, being used to reset the timing means so that the pager operates in a data receive mode.

2. A pager decoding system as claimed in Claim 1, characterised in that there is provided means for detecting the absence of a synchronisation code word when the pager is operating in its data receive mode, said means producing an output signal in response to detecting the absence of the synchronisation code word such that the pager operates in a fade recovery mode, which output signal is applied to the timing means, said timing means in response to the output signal enabling data input to the shift register for at least $(m+2)$ bit periods and activating the preamble and synchronisation code word detecting means for the $(m-1)$ th, m th and $(m+1)$ th bit periods in every n th code word, whereby in response to detecting preamble or a synchronisation code word the timing means is reset so that the pager operates in a data receive mode but if no synchronisation code word is detected after a predetermined number of batches then the pager adopts a carrier-off mode in which data is switched into the shift register means every $(n+1)$ code words.

3. A paging receiver including a decoding system as claimed in Claim 1 or 2.

Patentansprüche

1. Decodersystem für Personenrufempfänger zur Verwendung mit einem SignalfORMAT, in dem Codewörter von m Bits in Stapeln von n Codewörtern

102 is switched-on and the input signal is clocked into the 32-stage shift register 108 for 32 bit periods and then the receiver section 102 is switched-off. Outputs of the shift register stages are coupled in parallel to the preamble and synchronisation signal detector 112. Assuming that the preamble bit pattern or the synchronisation code word is not stored in the shift register 108 then precisely eighteen code words later the receiver section 102 is switched-on and another thirty-two bits are stored by being concatenated onto the already stored data. As each bit is clocked in a check is made by the synchronisation and preamble detector 112 to determine whether 32 bits of preamble or the synchronisation code word is present in the shift register 108. If preamble is detected which is indicative that a new transmission is being made then the synchronisation pulse generator 118 produces an output on the line 122 coupled to the timing control circuit 106 which maintains the receiver section 102 on until synchronisation code word is detected up to a maximum of eighteen code words duration should a synchronisation code word not be detected. If the synchronisation code word is detected, the pulse generator 118 produces a synchronising pulse which causes the timer control circuit 106 to switch the decoding circuit into the data receive mode.

If the loss of signal is due to a long fade then the first thing detected will be the synchronisation word. Thus by switching-on the receiver section 102 every eighteen code words, the decoder is able to comb through all the relative bit positions in a batch in seventeen batch durations. By using the shift register 108 in the manner described it is possible to pick-up the synchronisation code word in spite of the fact that the switching-on and switching-off of the receiver section 102 is not synchronised to the incoming data. How this is done will be described with reference to Figure 5.

Waveform diagram 5A illustrates the incoming data with a synchronisation code word 16 every seventeen code words as is usual with the POCSAG code structure. Diagram 5B illustrates the switching-on of the receiver 102 every eighteen code words. Diagram 5C illustrates the blocks of 32 bits of data being read into the shift register 114. The left-hand block received first comprises 32 bits of which some are the first part X of a synchronisation code word. The next time the receiver section 102 is turned on the first data to be read-in is the second part Y of the subsequent synchronisation code word. At the instant that the concatenated parts X and Y are configured in the shift register to form a complete synchronisation code word, see diagram 5D, the synchronisation signal detector 112 recognises that the shift register 108 contains the synchronisation code word and causes the synchronising pulse generator 118 to produce a synchronisation pulse, diagram 5E, which is used by the timing control circuit 106 to reset the receiver power control circuit 104 so that the pager operates in a data receive mode as before.

Although the decoding system in accordance with the present invention has been described with particular reference to the POCSAG format, it is capable

of adaptation to other formats having a fixed length regular batch structure, each batch comprising a synchronisation code word whose position in a batch is fixed relative to address and/or message code words, and multiples of such batches being concatenated with the preceding preamble to form a transmitted signal.

Claims

1. A pager decoding system suitable for use with a signal format in which code words of m bits are sent in batches of n code words, each batch containing a synchronisation code word and $(n-1)$ address/message code words, the system being characterised by timing means for switching-on a receiver section of the pager for a duration corresponding to m bits at intervals corresponding to $(n+1)$ code words, shift register means for storing data received during the m bit periods, the shift register having m stages and the data being concatenated onto the data received in the previous interval, and preamble and synchronisation code word detecting means coupled to the shift register means, the detecting means producing output signals in response to a preamble bit pattern being detected or a synchronisation code word being detected, one of said output signals, produced in response to the detection of the preamble, being used to set the timing means to wait for synchronisation code word detection, another of said output signals, produced in response to the detection of the synchronisation code word, being used to reset the timing means so that the pager operates in a data receive mode.

2. A pager decoding system as claimed in Claim 1, characterised in that there is provided means for detecting the absence of a synchronisation code word when the pager is operating in its data receive mode, said means producing an output signal in response to detecting the absence of the synchronisation code word such that the pager operates in a fade recovery mode, which output signal is applied to the timing means, said timing means in response to the output signal enabling data input to the shift register for at least $(m+2)$ bit periods and activating the preamble and synchronisation code word detecting means for the $(m-1)$ th, m th and $(m+1)$ th bit periods in every n th code word, whereby in response to detecting preamble or a synchronisation code word the timing means is reset so that the pager operates in a data receive mode but if no synchronisation code word is detected after a predetermined number of batches then the pager adopts a carrier-off mode in which data is switched into the shift register means every $(n+1)$ code words.

3. A paging receiver including a decoding system as claimed in Claim 1 or 2.

Patentansprüche

1. Decodersystem für Personenrufempfänger zur Verwendung mit einem SignalfORMAT, in dem Codewörter von m Bits in Stapeln von n Codewörtern



übertragen werden, wobei jeder Stapel ein Synchronisations-Codewort und $(n-1)$ Adress-/Nachricht-Codewörter enthält, wobei das System gekennzeichnet ist durch Zeitgebermittel zum Einschalten eines Empfängerabschnitts des Personenrufempfängers für eine Dauer entsprechend m Bits in Intervallen entsprechend $(n+1)$ Codewörtern, durch Schieberegistermittel zur Speicherung von in den m Bitperioden empfangenen Daten, wobei das Schieberegister aus m Stufen besteht und die Daten zu den im vorangehenden Intervall empfangenen Daten verkettet werden, und durch Vorlauf- und Synchronisationscodewort-Detektormittel, die mit den Schieberegistermitteln verbunden sind und in Beantwortung eines zu detektierenden Vorlauf-Bitmusters oder eines zu detektierenden Synchronisationscodewortes Ausgangssignale erzeugt, von denen eines nach der Erzeugung in Beantwortung der Vorlaufdetektierung zum Einstellen der Zeitgebermittel in einen Wartezustand in Erwartung der Detektierung eines Synchronisationscodewortes und ein anderes dieser Ausgangssignale nach der Erzeugung in Beantwortung der Detektierung des Synchronisationscodewortes zum Rückstellen der Zeitgebermittel benutzt wird, so dass der Personenrufempfänger in einem Datenempfangsbetrieb arbeitet.

2. Decodersystem für Personenrufempfänger nach Anspruch 1, dadurch gekennzeichnet, dass Mittel zum Detektieren der Abwesenheit eines Synchronisationscodewortes vorgesehen sind, wenn der Personenrufempfänger in seinem Datenempfangsbetrieb arbeitet, wobei diese Mittel ein Ausgangssignal in Beantwortung der Detektierung der Abwesenheit des Synchronisationscodewortes erzeugen, so dass der Personenrufempfänger in einem Schwundwiederherstellungsbetrieb arbeitet, wobei dieses Ausgangssignal den Zeitgebermitteln zugeführt wird, die in Beantwortung des Ausgangssignals ermöglichen, dass wenigstens $(m+2)$ Bitperioden Daten in das Schieberegister eingegeben werden, und in den $(m-1)$., m . und $(m+1)$. Bitperioden in jedem n . Codewort die Vorlauf- und Synchronisationscodewort-Detektormittel aktivieren, wobei in Antwort auf das Detektieren des Vorlauf- und Synchronisationscodewortes die Zeitgebermittel derart rückgestellt werden, dass der Personenrufempfänger in einem Datenempfangsbetrieb arbeitet, wenn aber nach einer vorbestimmten Anzahl Durchgänge kein Synchronisationscodewort detektiert wird, nimmt der Personenrufempfänger einen Betriebszustand an, in dem es keinen Träger gibt, wobei Daten alle $(n+1)$ Codeworte in das Schieberegister geschaltet werden.

3. Personenrufempfänger mit einem Decodersystem nach Anspruch 1 oder 2.

Revendications

1. Système de décodage pour un dispositif de recherche de personnes pouvant être utilisé avec un

format de signal dans lequel des mots de code de m bits sont émis en groupes de n mots de code, chaque groupe contenant un mot de code de synchronisation et $(n-1)$ mots de code d'adresse/message, le système étant caractérisé par un dispositif à temps pour allumer une section de récepteur du dispositif de recherche de personnes pendant une durée correspondant à m bits à des intervalles correspondant à $(n+1)$ mots de code, un dispositif à registre à décalage pour stocker des données reçues pendant les m périodes de bits, le registre à décalage comportant m étages et les données étant enchaînées aux données reçues dans l'intervalle précédent et un dispositif détecteur de préambule et de mots de code de synchronisation connecté au dispositif à registre de décalage, le dispositif détecteur produisant des signaux de sortie en réaction à la détection d'une configuration de bits de préambule ou d'un mot de code de synchronisation, un de ces signaux de sortie, produit en réaction à la détection du préambule, étant utilisé pour régler le dispositif à temps pour attendre la détection d'un mot de code de synchronisation, un autre de ces signaux de sortie, produit en réaction à la détection du mot de code de synchronisation, étant utilisé pour ramener à zéro le dispositif à temps de telle sorte que le dispositif de recherche de personnes fonctionne dans un mode de réception de données.

2. Système de décodage pour un dispositif de recherche de personnes suivant la revendication 1, caractérisé en ce qu'un dispositif est prévu pour détecter l'absence d'un mot de code de synchronisation lorsque le dispositif de recherche de personnes fonctionne dans son mode de réception de données, ce dispositif produisant un signal de sortie en réaction à la détection de l'absence du mot de code de synchronisation de sorte que le dispositif de recherche de personnes fonctionne dans un mode de récupération de fading, le signal de sortie étant appliqué au dispositif à temps, ce dispositif à temps, en réaction au signal de sortie, validant l'entrée de données du registre à décalage pendant au moins $(m+2)$ périodes de bits et activant le dispositif détecteur de préambule et de mots de code de synchronisation pendant la $(m-1)$ ème, la m ème et la $(m+1)$ ème période de bits dans chaque n ème mot de code, de sorte que, en réponse à la détection du préambule ou d'un mot de code de synchronisation, le dispositif à temps est ramené dans son état initial de sorte que le dispositif de recherche de personnes fonctionne dans un mode de réception de données, mais si aucun mot de code de synchronisation n'est détecté après un nombre prédéterminé de groupes, le dispositif de recherche de personnes adopte un mode à porteuse coupée dans lequel les données sont commutées dans le dispositif à registre à décalage tous les $(n+1)$ mots de code.

3. Récepteur pour la recherche de personnes comprenant un système de décodage suivant la revendication 1 ou 2.

