

GENERATION OF MBSFN-DOB SYNCHRONIZATION CODES

TECHNICAL FIELD

The present invention relates generally to MBSFN (Multicast Broadcast Single Frequency Network) DOB (Downlink Optimized Broadcast) cell search and generation of primary synchronization codes.

BACKGROUND

MBMS (Multimedia Broadcast Multicast Service) over single frequency networks (MBSFN) has recently been specified in 3GPP for Rel-7 UMTS Terrestrial Radio Access (UTRA) systems. The MBSFN feature provides significantly higher spectral efficiency compared to Rel-6 MBMS and is primarily intended for broadcasting high bit rate demanding Mobile TV services on dedicated MBMS carriers. Since it is broadcast only, MBSFN inherently targets transmissions in unpaired frequency bands.

In SFN (Single Frequency Network) transmission, multiple base stations transmit the same waveform at the same time such that a terminal receives signals from all base stations, resulting in a behavior similar to one large cell. For UTRA systems, SFN transmission implies that a cluster of time synchronized NodeBs transmit the same content using the same channelization and scrambling codes.

SFN transmission is illustrated in Fig. 1, where a terminal, or mobile station MS, receives signals from two base stations BS1 and BS2. When using cell-specific scrambling, transmissions from the right hand side base station BS2 would represent inter-cell interference for the terminal in the adjacent cell. In a single frequency network, on the other hand, inter-cell interference shows up as additional multi-path transmission, which can be accounted for

by the terminal receiver as a desired signal, resulting in considerably improved coverage.

MBSFN enhances the Rel-6 MBMS physical layers by supporting SFN operations for MBMS point-to-multipoint (ptm) transmissions on a dedicated MBMS carrier. It also supports higher service bit rates and efficient time division multiplexing of services for reducing terminal battery consumption by allowing discontinuous reception (DRX) of services. MBSFN uses the same type of channels as used for Rel-6 MBMS ptm transmissions.

In order to provide smooth integration of the MBSFN feature to any existing UTRA system, MBSFN has been specified for both FDD (Frequency Division Duplex) and TDD (Time Division Duplex) based physical layer downlink (DL) channel structures:

- MBSFN based on WCDMA (Wideband Code Division Multiple Access) (FDD based)
- MBSFN based on TD-SCDMA (Time Division-Synchronous Code Division Multiple Access) (TDD based)
- MBSFN based on TD-CDMA (Time Division-Code Division Multiple Access) (TDD based)

The FDD related MBSFN uses the WCDMA downlink common physical layer channels for transmission of data, and no paired uplink transmissions occur. For the TDD related MBSFN, all slots are used for downlink transmissions when networks are optimized for broadcast. Hence, no duplex occurs in MBSFN and the differences between FDD and TDD based MBSFN then mainly refer to the physical layer slot formats, the way Mobile TV services are time multiplexed and the chip rates in the case of the TDD options TD-SCDMA and 7.68 Mcps TD-CDMA. (The chip rate for the third TDD option, 3.84 Mcps TD-CDMA, is the same as used in FDD.)

When transmitting downlink in all slots, the meaning of TDD and FDD becomes blurred in the sense that no duplex occurs in broadcast. As mentioned above, the difference then basically refers to the construction of the common downlink physical channels. Therefore, in an ongoing 3GPP work item [1] the objective is to specify the WCDMA based MBSFN approach as an additional TDD option, in which all slots are dedicated for broadcast. This additional TDD option has been referred to as MBSFN Downlink Optimized Broadcast (DOB). The MBSFN DOB fulfils relevant TDD RF requirements.

In cell search, the SCH (Synchronization CHannel) is used by a terminal to determine slot and radio frame synchronization as well as to identify the group code of a cell. Given the group code of the cell, the terminal can detect the cell-specific scrambling code (and midamble code in case of TDD). The cell search procedure is normally divided into three steps:

1. Slot synchronization
2. Frame synchronization and code group identification
3. Cell-specific scrambling code detection

The synchronization channel consists of two sub-channels, the Primary SCH and the Secondary SCH, see [2],[3]:

- The Primary SCH is formed by a modulated code, the Primary Synchronization Code (PSC). This code is the same for all cells in the system. With e.g. a receive filter matched to the PSC, the terminal can locate the slot timing of the cell by detecting peaks in the matched filter output.
- The Secondary SCH is formed by a repeatedly transmitted sequence of modulated codes, the Secondary Synchronization Codes (SSC), and is transmitted in parallel with the Primary SCH. The SSC indicates which of the code groups the cell-specific scrambling code belongs to and the SSC also provides the possibility to obtain frame synchronization.

In WCDMA, and 3.84Mcps TD-CDMA systems, the 10 ms radio frames of the synchronization channels are divided into 15 slots, each of length 2560 chips. The PSC and SSC have a length of 256 chips and the mechanism to generate these synchronization codes is the same for WCDMA and 3.84 Mcps TD-CDMA, but the allocation of the codes within the frame differs.

In the case of WCDMA, the synchronization codes are allocated in each slot as illustrated by Fig. 2, whereas in TD-CDMA there are two possible allocations of the SCH codes within the frame:

1. In slot #k, where $k = 0 \dots 14$
2. In two slots, #k and #k+8, where $k = 0 \dots 6$

In WCDMA, the PSC and SSC are always allocated in the beginning of the slots, as illustrated in Fig. 2, whereas in TD-CDMA a time offset can be applied to the PSC. Furthermore, in WCDMA the Secondary SCH is formed by one sequence of SSC, whereas in TD-CDMA three SSC sequences are transmitted in parallel.

When deploying MBSFN based on WCDMA common downlink channels in UMTS unpaired frequency bands (i.e. MBSFN DOB in TDD bands), there might be some impact on roaming legacy (older) TD-CDMA terminals with respect to cell search at power-on. A legacy TD-CDMA terminal that expects to find synchronization codes in at most two slots per frame could experience longer cell search times (depending on the particular implementation), due to the deployment of the WCDMA based synchronization channel structure in the unpaired spectrum. It may have to evaluate 15 positions within a frame in order to find out that it actually cannot access the MBSFN DOB carrier.

A WCDMA (and non-MBSFN capable) terminal trying to access an MBSFN DOB carrier performs the cell search steps and then reads system information on the broadcast channel (BCH) to find out that this carrier is barred. In this case, however, the WCDMA terminal may not try to perform the cell

search in unpaired frequency bands, due to pre-knowledge of their spectrum locations. On the other hand, reading a barred cell may delay the cell search at power on for a roaming WCDMA and non-MBSFN capable terminal trying to access unpaired bands.

SUMMARY

An object of the present invention is to improve cell search for non-MBSFN capable terminals in an MBSFN DOB system.

This object is achieved in accordance with the attached claims.

Briefly, the present invention is based on a new PSC, denoted $C_{psc,new}$, for MBSFN having the following properties:

- $C_{psc,new}$ is a hierarchical Golay sequence constructed by a plurality of constituent sequences with at least one of the constituent sequences being the Golay sequence.
- $C_{psc,new}$ is orthogonal to the PSC and SSC used in non-MBSFN capable WCDMA.

The new PSC may be used to generate a new synchronization channel structure for MBSFN, in which the new PSC is allocated to predetermined time slots of frames and PSCs used in non-MBSFN capable WCDMA are allocated to any remaining time slots of the frames.

An MBSFN capable base station includes means adapted to generate such a synchronization channel frame that includes the new primary synchronization code.

BRIEF DESCRIPTION OF THE DRAWINGS

The invention, together with further objects and advantages thereof, may best be understood by making reference to the following description taken together with the accompanying drawings, in which:

Fig. 1 is a diagram illustrating the SFN principle;

Fig. 2 is a diagram illustrating the structure of the WCDMA synchronization channel;

Fig. 3 is a diagram illustrating the structure of an embodiment of the primary synchronization channel in accordance with the present invention;

Fig. 4 is a diagram illustrating the structure of an example of another embodiment of the primary synchronization channel in accordance with the present invention;

Fig. 5 is a diagram illustrating the structure of an example of still another embodiment of the primary synchronization channel in accordance with the present invention;

Fig. 6 is a flow chart of an embodiment of a method of generating an MBSFN primary synchronization channel frame in accordance with the present invention;

Fig. 7 is a flow chart of another embodiment of a method of generating an MBSFN primary synchronization channel frame in accordance with the present invention;

Fig. 8 is a flow chart of still another embodiment of a method of generating an MBSFN primary synchronization channel frame in accordance with the present invention; and

Fig. 9 is a block diagram of part of a base station configured in accordance with an embodiment of the present invention.

DETAILED DESCRIPTION

In a first embodiment, illustrated in Fig. 3, the Primary SCH sent on the MBSFN DOB carrier is modulated by a new PSC. The new PSC is orthogonal

to the PSC and SSC specified for WCDMA and TD-CDMA. Due to the orthogonality and low cross-correlation properties, MBSFN DOB carriers (cells) are not observable for any non-MBSFN DOB capable terminals. The Secondary SCH sent on the MBSFN DOB carrier is the same as specified for WCDMA and no time offsets are applied to the synchronization codes.

In further embodiments, illustrated in Fig. 4 and 5, the Primary SCH sent on the MBSFN DOB carrier is in one slot, or possibly in two slots, of a frame modulated by the PSC specified for WCDMA (PSC_{WCDMA}) and in the remaining slots of the frame modulated by the new PSC (PSC_{NEW}), i.e.

1. If PSC_{WCDMA} is allocated in slot #k, where $k = 0 \dots 14$, then PSC_{NEW} is allocated in slots not equal to #k of the frame (Fig. 4).
2. If PSC_{WCDMA} is allocated in slots #k and #k+8, where $k = 0 \dots 6$, then PSC_{NEW} is allocated in slots not equal to #k and #k+8 of the frame (Fig. 5).

No time offset is applied to PSC_{WCDMA} and PSC_{NEW} , and thus they always start at the beginning of slots associated with the Primary SCH.

In another embodiment, the Secondary SCHs sent on the MBSFN DOB carrier is constructed as in FDD and TDD 3.84 Mcps option, but with the constituent sequence a defined in [2], [3] replaced with the corresponding constituent sequence used to construct the new PSC (procedure described below).

With the above slot arrangement of the primary synchronization codes PSC_{WCDMA} and PSC_{NEW} , a legacy TD-CDMA terminal trying to access an MBSFN DOB carrier will find at most two peaks within a frame when correlating receive signals (matched filter output) with its primary synchronization code. In this case, the cell search time will not be longer than for a legacy TD-CDMA terminal trying to access an MBSFN TD-CDMA carrier.

The new PSC, denoted $C_{psc,new}$ in the mathematical description below, of length 256 chips is constructed as follows: The new sequence can be constructed from two constituent sequences $x_{1,new}$ and $x_{2,new}$, each of length 16 chips, in accordance with:

$$\begin{aligned} y(i) &= x_{2,new}(i \bmod 16) * x_{1,new}(i \div 16), \quad i = 0 \dots 255 \\ C_{psc,new} &= p * \langle y(0), y(1), \dots, y(255) \rangle \end{aligned} \quad (1)$$

where p denotes a phase rotation represented by a complex number, for example $p = (1 + j)$.

The constituent sequence $x_{1,new}$ is chosen as a Golay complementary sequence to the corresponding constituent sequence x_1 associated with the PSC defined in [2] for WCDMA. With $R_{x_{1,new}}(k)$ and $R_{x_1}(k)$ denoting the aperiodic autocorrelation functions of the sequences $x_{1,new}$ and x_1 , respectively, the constituent sequence $x_{1,new}$ shall thus be chosen such that:

$$R_{x_{1,new}}(k) + R_{x_1}(k) = C \times \delta(k), \quad k = -15, -14, \dots, 15 \quad (2)$$

In (2) C is a constant integer and $\delta(k)$ represents the Kronecker delta function, i.e. $\delta(0) = 1$, otherwise $\delta(k) = 0$. The constituent sequence x_1 follows from Appendix A1 in [2] as:

$$x_1 = \langle 1, 1, 1, -1, -1, 1, -1, -1, 1, 1, 1, -1, 1, -1, 1, 1 \rangle \quad (3)$$

The complementary sequence to x_1 is:

$$x_{1,new} = \langle 1, 1, -1, 1, -1, 1, 1, 1, 1, 1, -1, 1, 1, -1, -1, -1 \rangle \quad (4)$$

The constituent sequence $x_{2,new}$ in (1) is orthogonal to the constituent sequence x_2 used to generate the hierarchical sequence used as the PSC for WCDMA and follows from [2]

$$x_2 = \langle 1, 1, 1, 1, 1, 1, -1, -1, 1, -1, 1, -1, 1, -1, -1, 1 \rangle \quad (5)$$

Furthermore, the constituent sequence $x_{2,new}$ in (1) is also orthogonal to the constituent sequence b used to generate the hierarchical sequence used as the SSC's for WCDMA, and follows from [2] as:

$$b = \langle 1, 1, 1, 1, 1, 1, -1, -1, -1, 1, -1, 1, -1, 1, -1 \rangle \quad (6)$$

A list of sequences for $x_{2,new}$ satisfying the above two orthogonality properties is given Table 1 below.

Table 1 Candidate sequences for $x_{2,new}$

	$x_{2,new}$
1	$\langle 1, -1, 1, -1, 1, -1, -1, 1, 1, 1, 1, 1, 1, -1, -1 \rangle$
2	$\langle 1, 1, -1, -1, 1, 1, 1, 1, 1, -1, -1, 1, 1, -1, -1 \rangle$
3	$\langle 1, -1, -1, 1, 1, -1, 1, -1, 1, 1, -1, -1, 1, 1, 1 \rangle$
4	$\langle 1, 1, 1, 1, -1, -1, 1, 1, 1, -1, 1, -1, -1, 1, -1 \rangle$
5	$\langle 1, -1, 1, -1, -1, 1, 1, -1, 1, 1, 1, 1, -1, -1, 1 \rangle$
6	$\langle 1, 1, -1, -1, -1, -1, -1, -1, 1, -1, -1, 1, -1, 1, -1 \rangle$
7	$\langle 1, -1, -1, 1, -1, 1, -1, 1, 1, 1, -1, -1, -1, -1, -1 \rangle$
8	$\langle 1, -1, 1, -1, 1, -1, -1, 1, -1, -1, -1, -1, -1, -1, 1 \rangle$
9	$\langle 1, 1, -1, -1, 1, 1, 1, 1, -1, 1, 1, -1, -1, 1, -1 \rangle$
10	$\langle 1, -1, -1, 1, 1, -1, 1, -1, -1, -1, 1, 1, -1, -1, -1 \rangle$

11	<1, 1, 1, 1, -1, -1, 1, 1, -1, 1, -1, 1, 1, -1, -1, 1>
12	<1, -1, 1, -1, -1, 1, 1, -1, -1, -1, -1, -1, 1, 1, -1, -1>
13	<1, 1, -1, -1, -1, -1, -1, -1, -1, 1, 1, -1, 1, -1, 1, -1>
14	<1, -1, -1, 1, -1, 1, -1, 1, -1, -1, 1, 1, 1, 1, 1, 1>

Any of these sequences can be used to construct the new PSC. The preferred one however is

$$x_{2,new} = \langle 1, -1, -1, 1, 1, -1, 1, -1, 1, 1, -1, -1, 1, 1, 1, 1 \rangle \quad (7)$$

as this sequence will have the smallest sidelobes in its cross-correlations with the existing PSC.

Using the two constituent sequences $x_{1,new}$ and $x_{2,new}$ in (1) to generate the PSC code $C_{psc,new}$, we obtain:

$$C_{psc,new} = p * \langle a, a, -a, a, -a, a, a, a, a, a, -a, a, a, -a, -a, -a \rangle \quad (8)$$

where

$$a = x_{2,new} = \langle 1, -1, -1, 1, 1, -1, 1, -1, 1, 1, -1, -1, 1, 1, 1, 1 \rangle \quad (9)$$

The leftmost chip in $C_{psc,new}$ corresponds to the chip transmitted first in time.

In the preferred embodiment, the Secondary Synchronization Codes, SSCs, are generated as in the FDD and TDD 3.84 Mcps option. This means that the sequence b above is constructed from the elements of the constituent sequence x_2 as described in [2] and [3], in which $a = x_2$. In the third embodiment mentioned above, the SSCs are generated as in the FDD and TDD 3.84 Mcps option, but in this case the sequence b is constructed from the elements of the constituent sequence $x_{2,new}$ used to construct the new PSC.

The procedure described above may be summarized as:

1. Send a new primary synchronization code for MBSFN DOB to facilitate cell search.
2. The new primary synchronization code is orthogonal to existing PSC and SSC of the FDD and TDD option TD-CDMA.
3. The constituent sequence $x_{1,new}$ of the new PSC sequence and that of the PSC of FDD (and 3.84 Mcps TD-CDMA) x_1 form a Golay complementary sequence pair.
4. The constituent sequence $x_{2,new}$ of the new PSC is selected to have good aperiodic autocorrelation properties and low aperiodic cross-correlations with existing PSC.

An alternative method of constructing the new PSC, $C_{psc,new}$, of length 256 chips is as follows: The new sequence $C_{psc,new}$ may be constructed from two constituent sequences $x_{1,new}$ and x_2 , each of length 16 chips, in accordance with:

$$\begin{aligned} y(i) &= x_2(i \bmod 16) * x_{1,new}(i \div 16), \quad i = 0 \dots 255 \\ C_{psc,new} &= p * \langle y(0), y(1), \dots, y(255) \rangle \end{aligned} \quad (10)$$

where p is a complex number providing an arbitrary phase rotation, for example $p = (1 + j)$.

The constituent sequence $x_{1,new}$ is chosen as a Golay complementary sequence to the corresponding constituent sequence x_1 associated with the PSC defined in [2] for WCDMA. With $R_{x_{1,new}}(k)$ and $R_{x_1}(k)$ denoting the auto-

correlation functions of the sequences $x_{1,new}$ and x_1 , respectively, the constituent sequence $x_{1,new}$ shall thus be chosen such that:

$$R_{x_{1,new}}(k) + R_{x_1}(k) = C \times \delta(k), \quad k = -15, -14, \dots, 15 \quad (11)$$

In (11) C is a constant integer and $\delta(k)$ represents the Kronecker delta function, i.e. $\delta(0) = 1$, otherwise $\delta(k) = 0$. The constituent sequence x_1 follows from Appendix A1 in [2] as:

$$x_1 = \langle 1, 1, 1, -1, -1, 1, -1, -1, 1, 1, 1, -1, 1, -1, 1, 1 \rangle \quad (12)$$

The complementary sequence to x_1 is:

$$x_{1,new} = \langle 1, 1, -1, 1, -1, 1, 1, 1, 1, -1, 1, 1, -1, -1, -1 \rangle \quad (13)$$

The constituent sequence x_2 in (10) is the same generalized hierarchical sequence used to generate the PSC for WCDMA and follows from [2] as:

$$x_2 = a = \langle 1, 1, 1, 1, 1, 1, -1, -1, 1, -1, 1, -1, 1, -1, -1, 1 \rangle \quad (14)$$

Using the two constituent sequences $x_{1,new}$ and x_2 in (10) to generate the PSC code $C_{psc,new}$, we obtain:

$$C_{psc,new} = p * \langle a, a, -a, a, -a, a, a, a, a, a, -a, a, a, -a, -a, -a \rangle \quad (15)$$

where the leftmost chip in $C_{psc,new}$ corresponds to the chip transmitted first in time.

This procedure may be summarized as:

1. Send a new generalized hierarchical Golay sequence $C_{psc,new}$ for MBSFN DOB to facilitate cell search.
2. The new generalized hierarchical Golay sequence $C_{psc,new}$ is orthogonal to PSC and SSC of FDD and the TDD option TD-CDMA.
3. The constituent sequence of the new generalized hierarchical Golay sequence $C_{psc,new}$ and that of the PSC of FDD (and 3.84 Mcps TD-CDMA) form a Golay complementary sequence pair.

Fig. 6 is a flow chart of an embodiment of a method of generating an MBSFN primary synchronization channel frame in accordance with the present invention. In step S1 the new PSC $C_{psc,new}$ is allocated to predetermined time slots of a primary synchronization channel frame. In step S2 a primary synchronization code PSC_{WCDMA} used in non-MBSFN capable WCDMA is allocated to any remaining time slots of the frame.

Fig. 7 is a flow chart of another embodiment of a method of generating an MBSFN primary synchronization channel frame in accordance with the present invention. In step S1 the new PSC $C_{psc,new}$ is allocated to all time slots of a primary synchronization channel frame, except time slot #k, where k is one of the integers 0...14. In step S2 a primary synchronization code PSC_{WCDMA} used in non-MBSFN capable WCDMA is allocated to time slot #k of the frame.

Fig. 8 is a flow chart of still another embodiment of a method of generating an MBSFN primary synchronization channel frame in accordance with the present invention. In step S1 the new PSC $C_{psc,new}$ is allocated to all time slots of a primary synchronization channel frame, except time slots #k and #k+8,

where k is one of the integers $0 \dots 6$. In step S2 a primary synchronization code PSC_{WCDMA} used in non-MBSFN capable WCDMA is allocated to time slots $\#k$ and $\#k+8$ of the frame.

Fig. 9 is a block diagram of part of a base station configured in accordance with an embodiment of the present invention. In Fig. 9 only elements necessary to explain the present invention are included. Physical downlink channels PPHY1, PHY2 are summed (after weighting by factors G_1 and G_2 , respectively) in a summation unit 10. The output of summation unit 10 is forwarded to another summation unit 12, where it is combined with the primary and secondary synchronization channels P-SCH, S-SCH (weighted by factors G_P and G_S , respectively). The secondary synchronization channel S-SCH is formed as in WCDMA. The primary synchronization channel P-SCH is formed by connecting a switch SW either to a code generator 14 generating the conventional code PSC_{WCDMA} or a code generator 16 generating the code PSC_{NEW} . The selection is controlled by a PSC controller 18. This controller can be adapted to produce a P-SCH in accordance with one of the formats above. The output of unit 12 is forwarded to a modulator 20, and the resulting bandpass signal is amplified and transmitted.

As an alternative a single code generator may be dynamically reconfigured to produce the appropriate code, PSC_{WCDMA} or PSC_{NEW} .

The functionality of the various blocks is typically implemented by one or several micro processors or micro/signal processor combinations and corresponding software.

It will be understood by those skilled in the art that various modifications and changes may be made to the present invention without departure from the scope thereof, which is defined by the appended claims.

REFERENCES

- [1] RP-070493, Work item description of MBSFN Downlink Optimized Broadcast (DOB)
- [2] 3GPP TS 25.213, "Spreading and modulation (FDD)" Release 7
- [3] 3GPP TS 25.223, "Spreading and modulation (TDD)" Release 7

ABBREVIATIONS

BCH:	Broadcast channel
DOB:	Downlink Optimized Broadcast
FDD	Frequency Division Duplex
MBMS:	Multimedia Broadcast Multicast Service
MBSFN:	Multicast Broadcast Single Frequency Network
PSC:	Primary Synchronization Code
SCH:	Synchronization channel
SSC:	Secondary Synchronization Codes
TD-CDMA	Time Division-Code Division Multiple Access
TD-SCDMA	Time Division-Synchronous Code Division Multiple Access
TDD	Time Division Duplex
UMTS:	Universal Mobile Telecommunications System
UTRA:	UMTS Terrestrial Radio Access
WCDMA	Wideband Code Division Multiple Access

CLAIMS

1. A primary synchronization code, denoted $C_{psc,new}$, for MBSFN, said code having the following properties:

$C_{psc,new}$ is a hierarchical Golay sequence constructed by a plurality of constituent sequences with at least one of the constituent sequences being the Golay sequence;

$C_{psc,new}$ is orthogonal to the primary and secondary synchronization codes used in non-MBSFN capable WCDMA.

2. The primary synchronization code $C_{psc,new}$ of claim 1, wherein

$$C_{psc,new} = p * \langle a, a, -a, a, -a, a, a, a, a, a, -a, a, a, -a, -a, -a \rangle,$$

where p is a phase rotating complex number and a is selected from one of the following 14 sequences:

1	<1, -1, 1, -1, 1, -1, -1, 1, 1, 1, 1, 1, 1, -1, -1>
2	<1, 1, -1, -1, 1, 1, 1, 1, 1, -1, -1, 1, 1, -1, 1, -1>
3	<1, -1, -1, 1, 1, -1, 1, -1, 1, 1, -1, -1, 1, 1, 1, 1>
4	<1, 1, 1, 1, -1, -1, 1, 1, 1, -1, 1, -1, -1, 1, 1, -1>
5	<1, -1, 1, -1, -1, 1, 1, -1, 1, 1, 1, 1, -1, -1, 1, 1>
6	<1, 1, -1, -1, -1, -1, -1, -1, 1, -1, -1, 1, -1, 1, -1, 1>
7	<1, -1, -1, 1, -1, 1, -1, 1, 1, 1, -1, -1, -1, -1, -1, -1>
8	<1, -1, 1, -1, 1, -1, -1, 1, -1, -1, -1, -1, -1, -1, 1, 1>
9	<1, 1, -1, -1, 1, 1, 1, 1, -1, 1, 1, -1, -1, 1, -1, 1>
10	<1, -1, -1, 1, 1, -1, 1, -1, -1, -1, 1, 1, -1, -1, -1, -1>
11	<1, 1, 1, 1, -1, -1, 1, 1, -1, 1, -1, 1, 1, -1, -1, 1>
12	<1, -1, 1, -1, -1, 1, 1, -1, -1, -1, -1, -1, 1, 1, -1, -1>

13	<1, 1, -1, -1, -1, -1, -1, -1, -1, 1, 1, -1, 1, -1, 1, -1>
14	<1, -1, -1, 1, -1, 1, -1, 1, -1, -1, 1, 1, 1, 1, 1, 1>

3. The primary synchronization code $C_{psc,new}$ of claim 2, wherein

$$a = \langle 1, -1, -1, 1, 1, -1, 1, -1, 1, 1, -1, -1, 1, 1, 1, 1 \rangle.$$

4. A synchronization channel structure for MBSFN including a primary synchronization code, denoted $C_{psc,new}$, having the following properties:

$C_{psc,new}$ is a hierarchical Golay sequence constructed by a plurality of constituent sequences with at least one of the constituent sequences being the Golay sequence;

$C_{psc,new}$ is orthogonal to the primary and synchronization codes used in non-MBSFN capable WCDMA.

5. The synchronization channel structure of claim 4, wherein

$$C_{psc,new} = p * \langle a, a, -a, a, -a, a, a, a, a, a, -a, a, a, -a, -a, -a \rangle,$$

where p is a phase rotating complex number and a is selected from one of the following 14 sequences:

1	<1, -1, 1, -1, 1, -1, -1, 1, 1, 1, 1, 1, 1, -1, -1>
2	<1, 1, -1, -1, 1, 1, 1, 1, 1, -1, -1, 1, 1, -1, -1>
3	<1, -1, -1, 1, 1, -1, 1, -1, 1, 1, -1, -1, 1, 1, 1>
4	<1, 1, 1, 1, -1, -1, 1, 1, 1, -1, 1, -1, -1, 1, 1>
5	<1, -1, 1, -1, -1, 1, 1, -1, 1, 1, 1, 1, -1, -1, 1>
6	<1, 1, -1, -1, -1, -1, -1, -1, 1, -1, -1, 1, -1, 1, -1>
7	<1, -1, -1, 1, -1, 1, -1, 1, 1, 1, -1, -1, -1, -1, -1>
8	<1, -1, 1, -1, 1, -1, -1, 1, -1, -1, -1, -1, -1, 1, 1>

9	<1, 1, -1, -1, 1, 1, 1, 1, -1, 1, 1, -1, -1, 1, -1, 1>
10	<1, -1, -1, 1, 1, -1, 1, -1, -1, -1, 1, 1, -1, -1, -1, -1>
11	<1, 1, 1, 1, -1, -1, 1, 1, -1, 1, -1, 1, 1, -1, -1, 1>
12	<1, -1, 1, -1, -1, 1, 1, -1, -1, -1, -1, -1, 1, 1, -1, -1>
13	<1, 1, -1, -1, -1, -1, -1, -1, -1, 1, 1, -1, 1, -1, 1, -1>
14	<1, -1, -1, 1, -1, 1, -1, 1, -1, -1, 1, 1, 1, 1, 1, 1>

6. The synchronization channel structure of claim 5, wherein

$$a = \langle 1, -1, -1, 1, 1, -1, 1, -1, 1, 1, -1, -1, 1, 1, 1, 1 \rangle.$$

7. The synchronization channel structure of claim 4, 5 or 6, wherein $C_{psc,new}$ is allocated to every time slot of a frame.

8. The synchronization channel structure of claim 4, 5 or 6, wherein the primary synchronization code used in non-MBSFN capable WCDMA is allocated to time slot #k of a frame, where k is set to one of the integers 0....14, and $C_{psc,new}$ is allocated to the remaining time slots of the frame.

9. The synchronization channel structure of claim 4, 5 or 6, wherein the primary synchronization code used in non-MBSFN capable WCDMA is allocated to time slot #k and #k+8 of a frame, where k is set to one of the integers 0...6, and $C_{psc,new}$ is allocated to the remaining time slots of the frame.

10. A method of generating an MBSFN primary synchronization channel frame, including the steps of

allocating (S1) a primary synchronization code $C_{psc,new}$ to predetermined time slots of a primary synchronization channel frame, where $C_{psc,new}$ has the following properties:

- $C_{psc,new}$ is a hierarchical Golay sequence constructed by a plurality of constituent sequences with at least one of the constituent sequences being the Golay sequence;
- $C_{psc,new}$ is orthogonal to the primary and secondary synchronization codes used in non-MBSFN capable WCDMA;

allocating (S2) a primary synchronization code used in non-MBSFN capable WCDMA to any remaining time slots of the frame.

11. The method of claim 10, wherein

$$C_{psc,new} = p * \langle a, a, -a, a, -a, a, a, a, a, a, -a, a, a, -a, -a, -a \rangle$$

where p is a phase rotating complex number and a is selected from one of the following 14 sequences:

1	<1, -1, 1, -1, 1, -1, -1, 1, 1, 1, 1, 1, 1, -1, -1>
2	<1, 1, -1, -1, 1, 1, 1, 1, 1, -1, -1, 1, 1, -1, 1, -1>
3	<1, -1, -1, 1, 1, -1, 1, -1, 1, 1, -1, -1, 1, 1, 1, 1>
4	<1, 1, 1, 1, -1, -1, 1, 1, 1, -1, 1, -1, -1, 1, 1, -1>
5	<1, -1, 1, -1, -1, 1, 1, -1, 1, 1, 1, 1, -1, -1, 1, 1>
6	<1, 1, -1, -1, -1, -1, -1, -1, 1, -1, -1, 1, -1, 1, -1, 1>
7	<1, -1, -1, 1, -1, 1, -1, 1, 1, 1, -1, -1, -1, -1, -1, -1>
8	<1, -1, 1, -1, 1, -1, -1, 1, -1, -1, -1, -1, -1, 1, 1, 1>
9	<1, 1, -1, -1, 1, 1, 1, 1, -1, 1, 1, -1, -1, 1, -1, 1>
10	<1, -1, -1, 1, 1, -1, 1, -1, -1, -1, 1, 1, -1, -1, -1, -1>
11	<1, 1, 1, 1, -1, -1, 1, 1, -1, 1, -1, 1, 1, -1, -1, 1>
12	<1, -1, 1, -1, -1, 1, 1, -1, -1, -1, -1, -1, 1, 1, -1, -1>
13	<1, 1, -1, -1, -1, -1, -1, -1, -1, 1, 1, -1, 1, -1, 1, -1>
14	<1, -1, -1, 1, -1, 1, -1, 1, -1, -1, 1, 1, 1, 1, 1, 1>

12. The method of claim 8 or 9, wherein

$$a = \langle 1, -1, -1, 1, 1, -1, 1, -1, 1, 1, -1, -1, 1, 1, 1, 1 \rangle.$$

13. The method of claim 10, 11 or 12, wherein $C_{psc,new}$ is allocated to every time slot of the frame.

14. The method of claim 10, 11 or 12, wherein the primary synchronization code used in non-MBSFN capable WCDMA is allocated to time slot #k of the frame, where k is set to one of the integers 0...14, and $C_{psc,new}$ is allocated to the remaining time slots of the frame.

15. The method of claim 10, 11 or 12, wherein the primary synchronization code used in non-MBSFN capable WCDMA is allocated to time slot #k and #k+8 of the frame, where k is set to one of the integers 0...6, and $C_{psc,new}$ is allocated to the remaining time slots of the frame.

16. An MBSFN capable base station including means (16, 18, SW) adapted to generate a synchronization channel frame that includes a primary synchronization code, denoted $C_{psc,new}$, having the following properties:

$C_{psc,new}$ is a hierarchical Golay sequence constructed by a plurality of constituent sequences with at least one of the constituent sequences being the Golay sequence;

$C_{psc,new}$ is orthogonal to the PSC and SSC used in non-MBSFN capable WCDMA.

17. The base station of claim 16, wherein

$$C_{psc,new} = p * \langle a, a, -a, a, -a, a, a, a, a, a, -a, a, a, -a, -a, -a \rangle,$$

where p is a phase rotating complex number and a is selected from one of the following 14 sequences:

1	<1, -1, 1, -1, 1, -1, -1, 1, 1, 1, 1, 1, 1, 1, -1, -1>
2	<1, 1, -1, -1, 1, 1, 1, 1, 1, -1, -1, 1, 1, -1, 1, -1>
3	<1, -1, -1, 1, 1, -1, 1, -1, 1, 1, -1, -1, 1, 1, 1, 1>
4	<1, 1, 1, 1, -1, -1, 1, 1, 1, -1, 1, -1, -1, 1, 1, -1>
5	<1, -1, 1, -1, -1, 1, 1, -1, 1, 1, 1, 1, -1, -1, 1, 1>
6	<1, 1, -1, -1, -1, -1, -1, -1, 1, -1, -1, 1, -1, 1, -1, 1>
7	<1, -1, -1, 1, -1, 1, -1, 1, 1, 1, -1, -1, -1, -1, -1, -1>
8	<1, -1, 1, -1, 1, -1, -1, 1, -1, -1, -1, -1, -1, -1, 1, 1>
9	<1, 1, -1, -1, 1, 1, 1, 1, -1, 1, 1, -1, -1, 1, -1, 1>
10	<1, -1, -1, 1, 1, -1, 1, -1, -1, -1, 1, 1, -1, -1, -1, -1>
11	<1, 1, 1, 1, -1, -1, 1, 1, -1, 1, -1, 1, 1, -1, -1, 1>
12	<1, -1, 1, -1, -1, 1, 1, -1, -1, -1, -1, -1, 1, 1, -1, -1>
13	<1, 1, -1, -1, -1, -1, -1, -1, -1, 1, 1, -1, 1, -1, 1, -1>
14	<1, -1, -1, 1, -1, 1, -1, 1, -1, -1, 1, 1, 1, 1, 1, 1>

18. The base station of claim 17, wherein

$$a = \langle 1, -1, -1, 1, 1, -1, 1, -1, 1, 1, -1, -1, 1, 1, 1, 1 \rangle.$$

19. The base station of claim 16, 17 or 18, wherein said means (16, 18, SW) are adapted to allocate $C_{psc,new}$ to every time slot of the frame.

20. The base station of claim 16, 17 or 18, wherein said means (14, 16, 18, SW) are adapted to allocate the primary synchronization code used in non-MBSFN capable WCDMA to time slot #k of the frame, where k is set to one of the integers 0....14, and $C_{psc,new}$ to the remaining time slots of the frame.

21. The base station of claim 16, 17 or 18, wherein said means (14, 16, 18, SW) are adapted to allocate the primary synchronization code used in non-

MBSFN capable WCDMA to time slot #k and #k+8 of the frame, where k is set to one of the integers 0...6, and $C_{psc,new}$ to the remaining time slots of the frame.
