

METHOD FOR COMMUNICATING DOWNLINK CONTROL SIGNAL, BASE STATION, AND USER EQUIPMENT

CROSS-REFERENCE TO RELATED APPLICATION

[0001] This application claims priority to Chinese Patent Application No.
5 201210070953.6, filed with the Chinese Patent Office on March 16, 2012, and entitled
"METHOD FOR COMMUNICATING DOWNLINK CONTROL SIGNAL, BASE
STATION, AND USER EQUIPMENT", which is incorporated herein by reference in its
entirety.

TECHNICAL FIELD

10 **[0002]** Embodiments of the present invention relate to the field of communications
technologies, and in particular, to a method for communicating a downlink control signal, a
base station, and a user equipment.

BACKGROUND

[0003] In a 3GPP (3rd Generation Partnership Project, 3rd Generation Partnership Project)
15 LTE (Long Term Evolution, Long Term Evolution)/LTE-A (LTE-advanced, LTE-advanced)
system, a downlink multiple access mode generally used is an OFDMA (Orthogonal
Frequency Division Multiple Access, Orthogonal Frequency Division Multiple Access)
mode. In terms of time, downlink resources of the system are divided into OFDM
(Orthogonal Frequency Division Multiple, Orthogonal Frequency Division Multiple)
20 symbols, and in terms of frequency, the downlink resources of the system are divided into
subcarriers.

[0004] In LTE release 8, LTE release 9 and LTE release 10, one downlink subframe
includes two timeslots (slots), and each timeslot includes 7 or 6 OFDM symbols, so that a

downlink subframe includes 14 or 12 OFDM symbols; one PRB (Physical Resource Block, PRB, physical resource block) includes 12 subcarriers in a frequency domain, and one timeslot in a time domain, which means that one PRB includes 7 or 6 OFDM symbols. A subcarrier in an OFDM symbol is called a RE (Resource Element, resource element), and therefore one PRB includes 84 or 72 REs. In one subframe, two PRBs of two timeslots at a same frequency position are called a physical resource block pair; and in LTE, a resource granularity of downlink transmission is a physical resource block pair (PRB pair, physical resource block pair, physical resource block pair), that is, a PRB pair.

[0005] In LTE release 10 and earlier LTE systems, a physical downlink control channel (Physical Downlink Control Channel, PDCCH) and a physical downlink shared channel (Physical Downlink Shared Channel, PDSCH) are time-division multiplexed in one subframe. The PDCCH is borne on the first n symbols of a subframe, and downlink data that the PDCCH schedules is mapped from the $(n+1)^{\text{th}}$ symbol of the subframe. In one subframe, all PDCCHs scheduling user equipments UEs (User Equipments, user equipments) are multiplexed together, and are then sent in a PDCCH area. One PDCCH may be formed by 1, 2, 4 or 8 control channel elements (Control Channel Element, CCE); one CCE is formed by 9 resource element groups (Resource Element Group, REGs); and one REG occupies 4 REs.

[0006] In LTE release 10 and earlier LTE systems, according to an index of the first CCE of a downlink_grant (Downlink_grant, DL_grant) for scheduling a UE, that is, a start position of an enhanced physical downlink control channel E-PDCCH (Enhanced PDCCH), a physical uplink control channel PUCCH (Physical Uplink Control Channel) format 1a/1b channel may be determined in an implicit manner to bear ACK/NACK (Acknowledgement/Negative-acknowledgement) feedback information for downlink data transmission.

[0007] As control information in a PDCCH is obtained by means of convolutional encoding with master code being 1/3 and circular buffering based rate matching, when an encoding rate is less than 1/3, it may occur that different CCEs include a same modulation symbol. For example, when the PDCCH is formed by 4 CCEs, each including 72 bits, the PDCCH can carry totally 288 encoded bits. Assuming that the PDCCH originally has 48 bits, the bit number becomes 144 after the 1/3 encoding, and becomes 288 after the circular

buffering based rate matching, which is equivalent to a repetition encoding; and the 288 bits are finally mapped to the four CCEs of the PDCCH. Therefore, modulation symbols in the third CCE and the fourth CCE are completely the same as modulation symbols in the first CCE and the second CCE.

5 **[0008]** Under the foregoing situation, a base station sends a PDCCH at aggregation level (Aggregation Level, AL, aggregation level) 4, but when performing blind detection, a UE may possibly detect information in the third CCE and the fourth CCE as a PDCCH at aggregation level 2. Therefore, the UE may determine a PUCCH format 1a/1b channel in an implicit manner according to an index of the first CCE of the PDCCH at aggregation level 2,
10 that is, an index of the third CCE. However, the base station may regard that the PUCCH format 1a/1b channel allocated to the UE is determined by the first CCE, so that feedback information cannot be correctly transmitted. It can be seen that unclarity of the CCE detection (that is, incorrect judgment on the start position of the E-PDCCH) will lead to unclarity of the PUCCH format 1a/1b channel determined by the UE.

15 **[0009]** In a LTE system later than release 10, with introduction of a multi-user multi-input multi-output antenna system (Multi-Input Multi-Output, MIMO, multi-input multi-output antenna system) and coordinated multi-point (Coordinated Multi-Point, CoMP) transmission and like technologies, a control channel capacity is restricted. Therefore, a PDCCH, which is transmitted based on a MIMO pre-coding mode is introduced and the PDCCH can be
20 demodulated based on a UE-specific reference signal, that is, a demodulation reference signal DMRS (Demodulation Reference Signal, DMRS), and the PDCCH here is also called an E-PDCCH. An E-PDCCH is not in a control area of the first n symbols of a subframe, but is in a downlink data transmission area of the subframe, and is frequency-division multiplexed with a PDSCH, and may occupy a different PRB pair from that occupied by the PDSCH, or
25 an E-PDCCH and a PDSCH may be multiplexed in a same PRB pair. In addition, a group of PRB pairs for E-PDCCH(s) may be configured for a cell, so that each UE in the cell knows all the PRB pairs for E-PDCCH(s) that are configured by a base station; or, a PRB pair for E-PDCCH transmission may be configured for each UE, which means that PRB pairs for E-PDCCHs that different UEs need to detect may be different.

30 **[0010]** Using LTE release 11 as an example, a reference signal of an E-PDCCH is a

UE-specific reference signal, and can support 4 ports (that is, DMRS ports 7, 8, 9 and 10 for PDSCH demodulation in LTE release 10). A data part of an E-PDCCH is used to bear modulation symbols of control information after coding and modulation.

[0011] An E-PDCCH CCE, hereinafter called an eCCE, is also defined in LTE release 11.

5 Using a localized E-PDCCH as an example, there are many REs that can be used to transmit an E-PDCCH in a PRB pair, and these REs may further be divided into several eCCEs. An E-PDCCH is formed by one or more eCCEs by means of aggregation, and needs to be blindly detected by a UE. As control information in the E-PDCCH is also obtained by means of convolutional encoding with master code being 1/3 and circular buffering based rate
10 matching, a problem also exists that a UE judges a start position of the E-PDCCH incorrectly.

SUMMARY

[0012] Embodiments of the present invention provide a method for communicating a downlink control signal, a base station, and a user equipment, which can avoid that a UE judges a start position of an E-PDCCH incorrectly.

15 **[0013]** According to one aspect, a method for communicating a downlink control signal is provided, including: mapping, by a base station according to an order of OFDM symbols used by a physical downlink control channel E-PDCCH of a user equipment UE, the E-PDCCH sequentially to resource elements used to transmit the E-PDCCH in each OFDM symbol; and sending, by the base station, the E-PDCCH to the UE by using the resource
20 elements.

[0014] According to another aspect, a method for communicating a downlink control signal is provided, including: receiving, by a user equipment UE, a downlink subframe from a base station; and extracting, by the UE in a blind detection process according to an order of OFDM symbols used by a candidate E-PDCCH in the downlink subframe, modulation
25 symbols of the candidate E-PDCCH sequentially from resource elements used to transmit the candidate E-PDCCH in each OFDM symbol, and performing decoding and cyclic redundancy check CRC on the candidate E-PDCCH.

[0015] According to another aspect, a method for communicating a downlink control

signal is provided, including: determining, by a base station, a reference signal port according to an aggregation level of a physical downlink control channel E-PDCCH of a user equipment UE, where E-PDCCHs at different aggregation levels correspond to different reference signal ports, and the aggregation level indicates the quantity of control channel elements included in the E-PDCCH; and sending, by the base station, the E-PDCCH to the UE in a subframe, and sending a reference signal of the E-PDCCH to the UE by using the determined reference signal port.

[0016] According to another aspect, a method for communicating a downlink control signal is provided, including: receiving, by a user equipment UE from a reference signal port in a subframe, a reference signal of a candidate E-PDCCH sent by a base station, where candidate E-PDCCHs at different aggregation levels correspond to different reference signal ports, and the aggregation level indicates the quantity of control channel elements included in the candidate E-PDCCH; and performing, by the UE, channel estimation according to the reference signal, so as to demodulate the candidate E-PDCCH.

[0017] According to another aspect, a method for communicating a downlink control signal is provided, including: sending, by a base station, a reference signal of the E-PDCCH by using a first reference signal port v ; sending, by the base station, a reference signal of the PDSCH by using at least one second reference signal port; and determining, by the base station, not to use a second reference signal port $p(v)$ to send the reference signal of the PDSCH, so that a reference signal port of the E-PDCCH and a reference signal port of the PDSCH are processed based on orthogonal time extensions with different lengths, where the first reference signal port is one of the at least one second reference signal port, and v and $p(v)$ are serial numbers of the reference signal ports.

[0018] According to another aspect, a method for communicating a signal is provided, including: receiving, by a user equipment UE, a reference signal of a physical downlink control channel E-PDCCH which is sent by a base station by using a first reference signal port v and a reference signal of a physical downlink shared channel PDSCH which is sent by the base station by using at least one second reference signal port, where the PDSCH is invoked by the E-PDCCH; performing, by the UE, channel estimation by using the reference

signal of the E-PDCCH, so as to demodulate the E-PDCCH, and performing channel estimation by using the reference signal of the PDSCH, so as to demodulate the PDSCH; and determining, by the UE, not to use a reference signal of the PDSCH sent by a second reference signal port $p(v)$ to perform channel estimation, so that a reference signal port of the E-PDCCH and a reference signal port of the PDSCH are processed based on orthogonal time extensions with different lengths, where the first reference signal port is one of the at least one second reference signal port, and v and $p(v)$ are serial numbers of the reference signal ports.

[0019] According to another aspect, a base station is provided, including: a mapping unit, configured to map, according to an order of OFDM symbols used by a physical downlink control channel E-PDCCH of a user equipment UE, the E-PDCCH sequentially to resource elements used to transmit the E-PDCCH in each OFDM symbol; and a sending unit, configured to send the E-PDCCH to the UE by using the resource elements.

[0020] According to another aspect, a user equipment is provided, including: a receiving unit, configured to receive a downlink subframe from a base station; and an extracting unit, configured to extract, in a blind detection process according to an order of OFDM symbols used by a candidate E-PDCCH in the downlink subframe, modulation symbols of the candidate E-PDCCH sequentially from resource elements used to transmit the candidate E-PDCCH in each OFDM symbol, and perform decoding and CRC check on the candidate E-PDCCH.

[0021] According to another aspect, a base station is provided, including: a determining unit, configured to determine a reference signal port according to an aggregation level of a physical downlink control channel E-PDCCH of a user equipment UE, where E-PDCCHs at different aggregation levels correspond to different reference signal ports, and the aggregation level indicates the quantity of control channel elements included in the E-PDCCH; and a sending unit, configured to send the E-PDCCH to the UE in a subframe, and send a reference signal of the E-PDCCH to the UE by using the determined reference signal port.

[0022] According to another aspect, a user equipment is provided, including: a sending unit, configured to receive a reference signal of a candidate E-PDCCH from a reference

signal port in a subframe, where candidate E-PDCCHs at different aggregation levels correspond to different reference signal ports, and the aggregation level indicates the quantity of control channel elements included in the candidate E-PDCCH; and a demodulating unit, configured to perform channel estimation according to the reference signal, so as to demodulate the candidate E-PDCCH.

[0023] According to another aspect, a base station is provided, including: a sending unit, configured to send a reference signal of the E-PDCCH by using a first reference signal port v , and send a reference signal of the PDSCH by using at least one second reference signal port; and a determining unit, configured to determine not to use a second reference signal port $p(v)$ to send the reference signal of the PDSCH, so that a reference signal port of the E-PDCCH and a reference signal port of the PDSCH are processed based on orthogonal time extensions with different lengths, where the first reference signal port is one of the at least one second reference signal port, and v and $p(v)$ are serial numbers of the reference signal ports.

[0024] According to another aspect, a user equipment is provided, including: a receiving unit, configured to receive a reference signal of a physical downlink control channel E-PDCCH which is sent by a base station by using a first reference signal port v and a reference signal of a physical downlink shared channel PDSCH which is sent by the base station by using at least one second reference signal port, where the PDSCH is invoked by the E-PDCCH; a demodulating unit, configured to perform channel estimation by using the reference signal of the E-PDCCH, so as to demodulate the E-PDCCH, and perform channel estimation by using the reference signal of the PDSCH, so as to demodulate the PDSCH; and a determining unit, configured to determine not to use a reference signal of the PDSCH sent by a second reference signal port $p(v)$ to perform channel estimation, so that a reference signal port of the E-PDCCH and a reference signal port of the PDSCH are processed based on orthogonal time extensions with different lengths, where the first reference signal port is one of the at least one second reference signal port, and v and $p(v)$ are serial numbers of the reference signal ports.

[0025] In the technical solutions, the E-PDCCH can be mapped, according to an order of OFDM symbols used by an E-PDCCH of a UE, sequentially to resource elements used to transmit the E-PDCCH in each OFDM symbol, so that different control channel elements will not include a same E-PDCCH modulation symbol, thereby avoiding that the UE incorrectly
5 judges a start position of the E-PDCCH.

BRIEF DESCRIPTION OF DRAWINGS

[0026] To describe the technical solutions in the embodiments of the present invention more clearly, the following briefly introduces the accompanying drawings required for describing the embodiments or the prior art. Apparently, the accompanying drawings in the
10 following description show merely some embodiments of the present invention, and a person of ordinary skill in the art may still derive other drawings from these accompanying drawings without creative efforts.

[0027] FIG. 1 is a schematic diagram of an eCCE division according to an embodiment of the present invention;

[0028] FIG. 2 is a schematic flowchart of a method for communicating downlink control
15 information according to Embodiment 1 of the present invention;

[0029] FIG. 3 is a schematic flowchart of a method for communicating downlink control information according to Embodiment 2 of the present invention;

[0030] FIG. 4 is a schematic flowchart of a method for communicating downlink control
20 information according to Embodiment 3 of the present invention;

[0031] FIG. 5 is a schematic flowchart of a method for communicating downlink control information according to Embodiment 4 of the present invention;

[0032] FIG. 6 is a schematic flowchart of a method for communicating downlink control information according to Embodiment 5 of the present invention;

[0033] FIG. 7 is a schematic flowchart of a method for communicating downlink control
25 information according to Embodiment 6 of the present invention;

[0034] FIG. 8A is a schematic flowchart of a process for communicating downlink control information according to Embodiment 7 of the present invention;

[0035] FIG. 8B is a schematic diagram showing physical resource mapping on a PDCCH according to an embodiment of the present invention;

[0036] FIG. 9A is a schematic flowchart of a process for communicating downlink control information according to Embodiment 8 of the present invention;

5 **[0037]** FIG. 9B and FIG. 9C are examples of allocating a DMRS port to a candidate E-PDCCH;

[0038] FIG. 10 is a schematic flowchart of a process for communicating downlink control information according to Embodiment 9 of the present invention;

[0039] FIG. 11 is a schematic structural diagram of a base station according to
10 Embodiment 10 of the present invention;

[0040] FIG. 12 is a schematic structural diagram of a user equipment according to Embodiment 11 of the present invention;

[0041] FIG. 13 is a schematic structural diagram of a base station according to Embodiment 12 of the present invention;

15 **[0042]** FIG. 14 is a schematic structural diagram of a user equipment according to Embodiment 13 of the present invention;

[0043] FIG. 15 is a schematic structural diagram of a base station according to Embodiment 14 of the present invention;

[0044] FIG. 16 is a schematic structural diagram of a user equipment according to
20 Embodiment 15 of the present invention;

[0045] FIG. 17 is a schematic diagram of physical resources according to Embodiment 16 of the present invention;

[0046] FIG. 18 is a first schematic diagram of an aggregation level and reference signal port correspondence according to Embodiment 16 of the present invention;

25 **[0047]** FIG. 19 is a second schematic diagram of an aggregation level and reference signal port correspondence according to Embodiment 16 of the present invention;

[0048] FIG. 20 is a third schematic diagram of an aggregation level and reference signal port correspondence according to Embodiment 16 of the present invention; and

[0049] FIG. 21 is a schematic diagram describing a start position according to
30 Embodiment 16 of the present invention.

DESCRIPTION OF EMBODIMENTS

[0050] The following clearly and completely describes the technical solutions in the embodiments of the present invention with reference to the accompanying drawings in the embodiments of the present invention. Apparently, the described embodiments are a part
5 rather than all of the embodiments of the present invention. All other embodiments obtained by a person of ordinary skill in the art based on the embodiments of the present invention without creative efforts shall fall within the protection scope of the present invention.

[0051] It should be understood that technical solutions of the present invention may be applied to various communications systems, for example, a GSM (Global System of Mobile
10 communication, Global System of Mobile communication) system, a CDMA (Code Division Multiple Access, Code Division Multiple Access) system, a WCDMA (Wideband Code Division Multiple Access, Wideband Code Division Multiple Access) system, a GPRS (General Packet Radio Service, General Packet Radio Service) system, an LTE (Long Term Evolution, Long Term Evolution) system, an LTE-A (Advanced long term evolution,
15 Advanced Long Term Evolution) system, a UMTS (Universal Mobile Telecommunication System, Universal Mobile Telecommunication System), and the like, which are not limited in the embodiments of the present invention, but for convenience of description, the embodiments of the present invention will be described by using an LTE system network as an example.

[0052] The embodiments of the present invention may be applied to wireless networks under different standards. A radio access network may include different network elements in different systems. For example, network elements of a radio access network in LTE and LTE-A include an eNB (Evolved Node B, that is, eNodeB, evolved base station), while network elements of a radio access network in WCDMA includes an RNC (Radio Network
25 Controller, radio network controller) and a base station Node B. Similarly, a WiMax (Worldwide Interoperability for Microwave Access, Worldwide Interoperability for Microwave Access) and other wireless networks may also use solutions similar to those in the embodiments of the present invention, but a relevant module in a base station system may be different, which is not limited in the embodiments of the present invention, but for

convenience of description, the following embodiments will be described by using an eNodeB as an example.

[0053] It should be further understood that, in the embodiments of the present invention, a user equipment (UE, user equipment) includes but is not limited to a mobile station (MS, Mobile Station), a mobile terminal (Mobile Terminal), a mobile telephone (Mobile Telephone), a handset (handset), portable equipment (portable equipment), or the like; the user equipment may communicate with one or more core networks through a radio access network (RAN, Radio Access Network); for example, the user equipment may be a mobile phone (or called a "cellular" phone), a computer with a radio communication function, or the like; and the user equipment may also be a portable, pocket-sized, handheld, computer-embedded, or vehicle-mounted mobile device.

[0054] FIG. 1 is a schematic diagram of an eCCE division according to an embodiment of the present invention. Referring to FIG. 1, after REs occupied by Cell-specific reference signals (CRS, cell-specific reference signal), REs occupied by a legacy compatible control channel (for example, a legacy (Legacy) PDCCH) and REs occupied by a reference signal of an E-PDCCH are excluded, each PRB pair may be divided into 4 eCCEs. FIG. 1 shows a possible division method. The embodiment according to the present invention is not limited to this eCCE division method, and does not limit that all eCCEs should have the same number of REs. An E-PDCCH and a PDSCH are multiplexed in an FDM mode in a data area of a subframe. Transmission of an E-PDCCH is formed by two parts, that is, a reference signal part and a data symbol part.

[0055] According to an E-PDCCH mapping mode, E-PDCCHs may be classified into localized E-PDCCHs and distributed E-PDCCHs. A localized E-PDCCH is mapped in one PRB pair or adjacent PRB pairs in a centralized way, so that a base station can select, according to a channel state report of a UE, a PRB pair in a better channel condition to send the E-PDCCH, so as to obtain a frequency scheduling gain. A distributed E-PDCCH is dispersed and mapped to multiple PRB pairs, so as to obtain a frequency diversity benefit. The embodiment according to the present invention is described by using a localized E-PDCCH as an example.

[0056] The foregoing problem that a UE judges a start position of an E-PDCCH

incorrectly may be solved by adding a filling bit, for example, by finding, according to sizes of different E-PDCCH formats and numbers of CCEs of different CCE aggregations, sizes of all E-PDCCHs that are possible to cause unclearness of a feedback information resource, and making a list. If a base station detects that the quantity of original bits of an E-PDCCH that
5 needs to be sent meets any one in the above list, the base station will add a zero behind the original bits of the E-PDCCH. The E-PDCCH corrected by adding a zero prevents the mentioned problem that different eCCEs transmit same encoded E-PDCCH information. However, this method increases feedback overhead.

[0057] In addition, although the method of adding a filling bit solves the problem that a
10 UE judges a start position of an E-PDCCH incorrectly, a problem cannot be avoided that the UE identifies an aggregation level of the E-PDCCH incorrectly. An E-PDCCH formed by 4 eCCEs is still used as an example. As a filling bit is added, it is impossible for the UE to detect an E-PDCCH at aggregation level 2 on the third eCCE and the fourth eCCE, but still possible that the UE detect an E-PDCCH at aggregation level 2 on the first eCCE and the
15 second eCCE. As the E-PDCCH is sent in a data area of a subframe, and is multiplexed with a PDSCH based on FDM, if the aggregation level detection is incorrect, transmission of the PDSCH will possibly be affected. For example, it is assumed that one RBG has 3 PRB pairs, and one PRB pair has two eCCEs; that the base station sends an E-PDCCH at aggregation level 4 to a UE, which occupies 4 eCCEs of PRB pairs numbered 0 and 1 in RBG0; and that
20 resources allocated to the PDSCH are RBG0 and RBG1, where resources in RBG0 other than those for the E-PDCCH, can be used to transmit the PDSCH, which is to say, PDSCH resources that the base station allocates are PRB pairs numbered 2, 3, 4 and 5. During E-PDCCH blind detection at a UE end, if the UE detects an E-PDCCH at aggregation level 2 on a PRB pair numbered 0, the UE regards that the PDSCH occupies PRB pairs numbered 1, 2, 3, 4 and 5, thereby causing an incorrect PDSCH reception. In addition, a similar problem
25 will also occur when an E-PDCCH and a PDSCH are multiplexed in a same PRB pair.

Embodiment 1

[0058] FIG. 2 is a schematic flowchart of a method for communicating downlink control

information according to Embodiment 1 of the present invention. The method in FIG. 2 may be executed by a base station.

[0059] 210: A base station maps, according to an order of OFDM symbols used by an E-PDCCH of a UE, the E-PDCCH sequentially to REs used to transmit the E-PDCCH in each OFDM symbol.

[0060] For example, each E-PDCCH may include L (L=1, 2, 4 or 8) eCCEs; that is to say, REs used by the E-PDCCH may be divided into L eCCEs. Assuming that OFDM symbols used by the E-PDCCH of the UE are symbols from the n^{th} symbol to the m^{th} symbol, when physical resource mapping is performed, according to an ascending order of indexes the OFDM symbols, a first part of modulation symbols of the E-PDCCH may be firstly mapped to REs used to transmit the E-PDCCH in the n^{th} symbol, and then a second part of symbols may be mapped to REs used to transmit the E-PDCCH in the $(n+1)^{\text{th}}$ symbol, and so on, till a last part of modulation symbols are finally mapped to REs used to transmit the E-PDCCH in the m^{th} symbol. Certainly, the embodiment of the present invention is not limited thereto; for example, another order (for example, a descending order of indexes of the OFDM symbols or other specific orders) may also be used to perform physical resource mapping.

[0061] 220: The base station sends the E-PDCCH to the UE by using the REs, where the E-PDCCH and a PDSCH invoked by the E-PDCCH are frequency-division multiplexed.

[0062] For example, that the E-PDCCH and a PDSCH invoked by the E-PDCCH are frequency-division multiplexed means that an E-PDCCH and a PDSCH in LTE11 are frequency-division multiplexed on REs of data part.

[0063] In the embodiment of the present invention, the E-PDCCH can be mapped, according to the order of OFDM symbols used by the E-PDCCH of the UE, sequentially to the REs used to transmit the E-PDCCH in each OFDM symbol, so that, for candidate E-PDCCHs at a same start eCCE but different aggregation levels, different eCCEs will not include E-PDCCH modulation symbols of a same index, thereby avoiding that the UE judges a start position of the E-PDCCH incorrectly. In addition, a problem that E-PDCCHs at a same start position but different aggregation levels are mixed up is also solved.

[0064] In 210, when the E-PDCCH is mapped sequentially to the REs used to transmit the E-PDCCH in each OFDM symbol, in each OFDM symbol, the E-PDCCH may be

sequentially mapped, according to an order of L eCCEs allocated to the E-PDCCH, to REs occupied by the L eCCEs in the OFDM symbol, where L is an integer.

[0065] For example, before physical resource mapping is performed, REs that can be used to transmit the E-PDCCH in a PRB pair may be firstly divided into multiple eCCEs.

5 Another division method is to disperse REs of each eCCE to all OFDM symbols of a data part with limitation to a part of subcarriers of the PRB pair, or disperse the REs of each eCCE to all OFDM symbols of the data part and subcarriers of the PRB pair. Under this situation, if the E-PDCCH is sequentially mapped, according to the order of L eCCEs allocated to the E-PDCCH, to REs occupied by the L eCCEs in the OFDM symbol, it can be ensured that, for
10 candidate E-PDCCHs at a same start eCCE but different aggregation levels, different eCCEs will not have E-PDCCH modulation symbols of a same index.

[0066] In 210, when the E-PDCCH is mapped sequentially to the REs used to transmit the E-PDCCH in each OFDM symbol, in each OFDM symbol, modulation symbols of the

e-PDCCH with index numbers of $j_0 + \sum_{q=0}^{l-1} N_q + [0, \dots, N_l - 1]$ may be mapped, according to

15 the order of the L eCCEs allocated to the E-PDCCH, sequentially to REs of a set R_l , where the set R_l is a set of REs occupied by the l^{th} eCCE among the L eCCEs included in the E-PDCCH, j_0 is a start position of the modulation symbols of the e-PDCCH mapped in the OFDM symbol, N_l is the quantity of the REs in the set R_l , and N_l , j_0 , l and q are integers.

20 **[0067]** For example, an E-PDCCH at aggregation level L may include L eCCEs, and have a modulation symbol sequence S_j , where $j = 0, \dots, J - 1$, where J is the total number of REs of the L eCCEs included in the E-PDCCH, and j is an index number of an E-PDCCH modulation symbol. According to the embodiment of the present invention, an E-PDCCH sequence S_j may be mapped sequentially to the REs used to transmit the E-PDCCH in each
25 OFDM symbol.

[0068] In 210, when the E-PDCCH is mapped sequentially to the REs used to transmit

the E-PDCCH in each OFDM symbol, in each OFDM symbol, the base station maps, according to an order of subcarriers, the E-PDCCH sequentially to REs occupied by L eCCEs allocated to the E-PDCCH.

[0069] In 210, when the E-PDCCH is mapped sequentially to the REs used to transmit the E-PDCCH in each OFDM symbol, in each OFDM symbol, modulation symbols of the e-PDCCH with index numbers of $j_0 + [0, \dots, N - 1]$ may be mapped sequentially to REs of a set R, where j_0 is a start position of modulation symbols of the E-PDCCH mapped in the OFDM symbol, the set R is a set of REs occupied by L eCCEs included in the E-PDCCH in the OFDM symbol, N is the quantity of the REs in set R, and N and j_0 are integers.

10

Embodiment 2

[0070] FIG. 3 is a schematic flowchart of a method for communicating downlink control information according to Embodiment 2 of the present invention. The method in FIG. 3 is executed by a UE. The method in FIG. 3 corresponds to the method in FIG. 2, and detailed descriptions here are omitted appropriately.

15 **[0071]** 310: The UE receives a downlink subframe from a base station.

[0072] 320: The UE extracts, in a blind detection process according to an order of OFDM symbols used by a candidate E-PDCCH in the downlink subframe, modulation symbols of the candidate E-PDCCH sequentially from REs used to transmit the candidate E-PDCCH in each OFDM symbol, and performs decoding and CRC check on the candidate E-PDCCH, where the E-PDCCH of the UE and a PDSCH invoked by the E-PDCCH of the UE are frequency-division multiplexed.

[0073] In the embodiment of the present invention, modulation symbols of the candidate E-PDCCH can be obtained, according to an order of OFDM symbols used by a candidate E-PDCCH of the UE, sequentially from REs used to transmit the E-PDCCH in each OFDM symbol, so that, for candidate E-PDCCHs at a same start eCCE but different aggregation levels, different eCCEs will not include a same E-PDCCH modulation symbol, thereby avoiding a problem that the UE judges a start position of the E-PDCCH incorrectly, and

25

solves a problem that E-PDCCHs at a same start position but different aggregation levels are mixed up.

[0074] In 320, when the UE uses, in the blind detection process, the order of OFDM symbols used by the candidate E-PDCCH, in each OFDM symbol, the UE may extract, according to an order of L eCCEs allocated to the candidate E-PDCCH, the modulation symbols of the candidate E-PDCCH sequentially from REs occupied by the L eCCEs in the OFDM symbol, where L is an integer.

[0075] In 320, when the UE uses, in the blind detection process, the order of OFDM symbols used by the candidate E-PDCCH, in each OFDM symbol, the UE may extract modulation symbols of the candidate E-PDCCH and with index numbers of

$j_0 + \sum_{q=0}^{l-1} N_q + [0, \dots, N_l - 1]$ from REs of a set R_l , where the set R_l is a set of REs occupied by the l^{th} eCCE among the L eCCEs included in the candidate E-PDCCH in the OFDM symbol, j_0 is a start position of the modulation symbols of the candidate E-PDCCH mapped in the OFDM symbol, N_l is the quantity of the REs in the set R_l , and N_l, j_0, l and q are integers.

[0076] In 320, when the UE uses, in the blind detection process, the order of OFDM symbols used by the candidate E-PDCCH, in each OFDM symbol, the UE may extract, according to an order of subcarriers, modulation symbols of the candidate E-PDCCH from REs occupied by the L eCCEs allocated to the candidate E-PDCCH.

[0077] In 320, when the UE uses, in the blind detection process, the order of OFDM symbols used by the candidate E-PDCCH, in each OFDM symbol, the UE may extract modulation symbols of the candidate E-PDCCH and with index numbers of $j_0 + [0, \dots, N - 1]$ from REs of a set R , where j_0 is a start position of the modulation symbols of the candidate E-PDCCH mapped in the OFDM symbol, the set R is a set of REs occupied by L eCCEs and included in the candidate E-PDCCH in the OFDM symbol, N is the quantity of the REs in the set R, and N and j_0 are integers.

Embodiment 3

[0078] FIG. 4 is a schematic flowchart of a method for communicating downlink control information according to Embodiment 3 of the present invention. The method in FIG. 4 is executed by a base station.

5 **[0079]** 410: The base station determines a reference signal port according to an aggregation level of an E-PDCCH of a UE, where E-PDCCHs at different aggregation levels correspond to different reference signal ports, and the aggregation level indicates the quantity of eCCEs included in the E-PDCCH.

[0080] 420: The base station sends the E-PDCCH to the UE in a subframe, and sends a
10 reference signal of the E-PDCCH to the UE by using the determined reference signal port, where the E-PDCCH and a PDSCH invoked by the E-PDCCH are frequency-division multiplexed.

[0081] For example, the reference signal may be a DMRS, and the reference signal port may be a DMRS port. Correspondence between E-PDCCHs at different eCCE aggregation
15 levels and DMRS ports that the E-PDCCHs use may be notified by using signaling, or may be determined by using an implicit method, which means that a signaling notification is not needed, but some parameters, such as a cell identity, a UE identity and an aggregation level and the like are used to determine the correspondence. Different PRB pairs may have same
20 correspondence, or different correspondence may be defined for each PRB pair. The correspondence may be cell-specific; for example, the base station may notify all UEs in a cell by using broadcast signaling, which means that all the UEs in the cell run according to same correspondence. The correspondence may also be UE-specific; for example, the base station may notify a specific UE by using RRC signaling, which means that different UEs may have different correspondence.

25 **[0082]** For example, in LTE11, corresponding to candidate E-PDCCHs at aggregation levels 1, 2, 4 and 8, the reference signal is sent by sequentially using DMRS ports 7, 8, 9 and 10.

[0083] According to the embodiment of the present invention, reference signals of E-PDCCHs at different eCCE aggregation levels can be sent by using different DMRS ports,

so that the UE can demodulate an E-PDCCH at each aggregation level correctly according to a special DMRS reference signal of the E-PDCCH, thereby avoiding a problem that the UE judges a start position of the E-PDCCH incorrectly, and solving a problem that E-PDCCHs at a same start position but different aggregation levels are mixed up.

5 **[0084]** According to the embodiment of the present invention, an E-PDCCH at aggregation level $L = 2^{m-1}$ corresponds to a reference signal port with a port number $7 + (m + \sigma) \bmod P$, where $m = 1, 2, 3, 4$, σ is 0 or a UE-specific parameter or a cell-specific parameter, and P is the quantity of available reference signal ports for the E-PDCCH, and $P=4$.

10 **[0085]** Optionally, that E-PDCCHs at different aggregation levels correspond to different reference signal ports may include that, E-PDCCHs at different aggregation levels, among a part or all of aggregation levels corresponding to E-PDCCHs of the UE, correspond to different reference signal ports.

15 **[0086]** Optionally, the determining, by the base station, a reference signal port according to the aggregation level of the physical downlink control channel E-PDCCH of the user equipment UE, where E-PDCCHs at different aggregation levels correspond to different reference signal ports may specifically be: selecting, by the base station according to the aggregation level of the physical downlink control channel E-PDCCH of the user equipment UE, one or more reference signal ports from a reference signal port set corresponding to the
20 aggregation level as a reference signal port corresponding to the aggregation level, where reference signal ports selected for E-PDCCHs at different aggregation levels are different.

25 **[0087]** According to the embodiment of the present invention, in 410, it is acceptable that only E-PDCCHs at a same start position in the subframe but different aggregation levels correspond to different reference signal ports. In other words, without depending on the aggregation level, E-PDCCHs with different start positions may correspond to a same reference signal port.

[0088] Optionally, as another embodiment, the method in FIG. 4 further includes: configuring, by the base station, correspondence between eCCEs in the subframe and the reference signal ports, so that, according to the correspondence between eCCEs in the

subframe and the reference signal ports, enabling E-PDCCHs at a same start position but different aggregation levels in the subframe correspond to different reference signal ports.

[0089] Further, the at a same start position in the subframe may include: at a same start position in a same physical resource block pair or different physical resource block pairs.

5 **[0090]** Further, E-PDCCHs, corresponding to different user equipments UEs, at a same aggregation level, and occupying a same physical resource, correspond to different reference signal ports.

[0091] The correspondence between eCCEs in the subframe and the reference signal ports includes: the i^{th} eCCE in the subframe corresponds to a reference signal port $7 + (i + \sigma) \bmod P$, where i is an index of the eCCE in the subframe, σ is 0 or a UE-specific parameter or a cell-specific parameter, and P is the quantity of available reference signal ports, and $P = 4$, and i is an integer; in 410, the base station sends a reference signal of the E-PDCCH at aggregation level $L = 2^{m-1}$ by using a reference signal port corresponding to the m^{th} eCCE in the E-PDCCH at aggregation level $L = 2^{m-1}$, where $m = 1, 2, 3, 4$.

10

15 **Embodiment 4**

[0092] FIG. 5 is a schematic flowchart of a method for communicating downlink control information according to Embodiment 4 of the present invention. The method in FIG. 5 is executed by a UE. The method in FIG. 5 corresponds to the method in FIG. 4, and detailed descriptions here are omitted appropriately.

20 **[0093]** 510: The UE receives a reference signal of a candidate E-PDCCH from a reference signal port in a subframe, where candidate E-PDCCHs at different aggregation levels correspond to different reference signal ports, and the aggregation level indicates the quantity of eCCEs included in the candidate E-PDCCH.

[0094] The user equipment UE receives, from a reference signal port in a subframe, a reference signal of a candidate physical downlink control channel E-PDCCH sent by a base station, where candidate E-PDCCHs at different aggregation levels correspond to different reference signal ports, and the aggregation level indicates the quantity of control channel elements included in the candidate E-PDCCH.

25

[0095] 520: The UE performs channel estimation according to the reference signal, so as to demodulate the candidate E-PDCCH.

[0096] Further, optionally, the E-PDCCH of the UE and a PDSCH invoked by the E-PDCCH of the UE are frequency-division multiplexed.

5 **[0097]** The UE performs channel estimation according to the reference signal, so as to demodulate the candidate E-PDCCH, where the candidate E-PDCCH and a physical downlink shared channel PDSCH invoked by the candidate E-PDCCH are frequency-division multiplexed.

[0098] For example, assuming that the base station sends an E-PDCCH at aggregation level 2 and sends a reference signal by using DMRS port 8, when blindly detecting each candidate E-PDCCH at aggregation level 1, the UE tries to perform channel estimation based on DMRS port 7 and demodulate the E-PDCCH; however, in fact, the base station does not send the reference signal to the UE by using DMRS port 7; it is quite clear that the demodulated output is some random noise, so that CRC check is not possible to be
10 successful, thereby avoiding that the UE mixes up candidate E-PDCCHs at different aggregation levels.
15

[0099] According to the embodiment of the present invention, reference signals of E-PDCCHs at different eCCE aggregation levels can be sent by using different DMRS ports, thereby avoiding a problem that the UE judges a start position of the E-PDCCH incorrectly,
20 and solving a problem that E-PDCCHs at a same start position but different aggregation levels are mixed up.

[00100] According to the embodiment of the present invention, an E-PDCCH at aggregation level $L = 2^{m-1}$ corresponds to a reference signal port with a port number $7 + (m + \sigma) \bmod P$, where $m = 1, 2, 3, 4$, σ is 0 or a UE-specific parameter or a cell-specific
25 parameter, and P is the quantity of available reference signal ports for the E-PDCCH, and $P=4$.

[0100] Optionally, as another embodiment, in 510, it is acceptable that only E-PDCCHs at a same start position but different aggregation levels correspond to different reference signal ports. In other words, without depending on the aggregation level, E-PDCCHs with

different start positions may correspond to a same reference signal port.

[0101] The method in FIG. 5 further includes: configuring, by the UE, correspondence between eCCEs in the subframe and the reference signal ports, so that, according to the correspondence between eCCEs in the subframe and the reference signal ports, enabling
5 E-PDCCHs at a same start position but different aggregation levels in the subframe correspond to different reference signal ports.

[0102] The correspondence between the eCCEs in the subframe and the different reference signal ports includes: the i^{th} eCCE in the subframe corresponds to a reference signal port $7 + (i + \sigma) \bmod P$, where i is an index of the eCCE in the subframe, σ is 0 or a
10 UE-specific parameter or a cell-specific parameter, and P is the quantity of available reference signal ports, and $P = 4$, and i is an integer; in 510, the UE may receive a reference signal of an E-PDCCH at aggregation level $L = 2^{m-1}$ from a reference signal port corresponding to the m^{th} eCCE in the E-PDCCH at aggregation level $L = 2^{m-1}$, where $m = 1, 2, 3, 4$.

[0103] Optionally, that candidate E-PDCCHs at different aggregation levels correspond to different reference signal ports may specifically be: selecting, by the UE, according to the aggregation level of the candidate E-PDCCH of the UE, one or more reference signal ports from a reference signal port set corresponding to the aggregation level as a reference signal port corresponding to the aggregation level, where candidate E-PDCCHs at different
20 aggregation levels correspond to different reference signal ports.

[0104] Further, that candidate E-PDCCHs at different aggregation levels correspond to different reference signal ports may include: that candidate E-PDCCHs at a same start position but different aggregation levels in the subframe correspond to different reference signal ports.

[0105] Optionally, that candidate E-PDCCHs at different aggregation levels correspond to different reference signal ports may include:

that candidate E-PDCCHs at different aggregation levels, among a part or all of aggregation levels corresponding to candidate E-PDCCHs of the UE, correspond to different reference signal ports.

Embodiment 5

[0106] FIG. 6 is a schematic flowchart of a method for communicating downlink control information according to Embodiment 5 of the present invention. The method in FIG. 6 is executed by a base station.

5 **[0107]** 610: The base station sends a reference signal of the E-PDCCH by using a first reference signal port v .

[0108] 620: The base station sends a reference signal of the PDSCH by using at least one second reference signal port.

[0109] 630: The base station determines not to use a second reference signal port $p(v)$ to send the reference signal of the PDSCH, so that a reference signal port of the E-PDCCH and a reference signal port of the PDSCH are processed based on orthogonal time extensions with different lengths, where the E-PDCCH and the PDSCH are frequency-division multiplexed, the first reference signal port may be one of the at least one second reference signal port, and v and $p(v)$ are serial numbers of the reference signal ports.

15 **[0110]** For example, LTE release 11 supports multiplexing of an E-PDCCH and a PDSCH; in order that a DMRS port with respect to an E-PDCCH is processed based on an orthogonal time extension with a length of 2, and also that, when a PDSCH with a rank of 5, 6 or 7 is scheduled by the E-PDCCH, a DMRS port with respect to a PDSCH is processed based on an orthogonal time extension with a length of 4, the present invention proposes the following limitation on the DMRS ports for the PDSCH; that is to say, when a DMRS port occupied by the E-PDCCH of the UE is v , a DMRS port $p(v)$ is defined not to be used to demodulate the PDSCH, or, another DMRS port is needed to replace the $p(v)$, so that a reference signal port of the E-PDCCH and a reference signal port of the PDSCH are processed based on orthogonal time extensions with different lengths, and that the E-PDCCH and the PDSCH can be multiplexed normally.

25 **[0111]** According to the embodiment of the present invention, when sending the reference signal of the PDSCH by using a reference signal port results that the reference signal ports of the E-PDCCH and the PDSCH cannot be processed based on orthogonal time

extensions with different lengths, the reference signal port may be not used to send the reference signal of the PDSCH, so that the reference signal of the PDSCH and the reference signal of the E-PDCCH are multiplexed normally.

[0112] According to the embodiment of the present invention, the at least one second reference signal port includes at least one of PDSCH reference signal ports 7, 8, 9, 10, 11, 12, 13 and 14 defined in LTE release 10, the first reference signal port includes an E-PDCCH

reference signal port 7, 8, 9, or 10 defined in LTE release 10, and $p(v) = \begin{cases} 11, v = 7 \\ 13, v = 8 \\ 12, v = 9 \\ 14, v = 10 \end{cases}$.

[0113] In 620, when a rank R of the PDSCH is less than or equal to 4, the base station may send the reference signal of the PDSCH by using a PDSCH reference signal port defined in LTE release 10.

[0114] Optionally, as another embodiment, when the rank of the PDSCH is one of 5, 6 and 7, the base station sends the reference signal of the PDSCH by using a PDSCH reference signal port defined in LTE release 10, and when needing to send the reference signal of the PDSCH by using the second reference signal port $p(v)$, replaces the reference signal port

$p(v)$ with another available reference signal port among the PDSCH reference signal ports, where R is an integer.

[0115] According to the embodiment of the present invention, when a rank R of the PDSCH is less than or equal to 4, the base station sends the reference signal of the PDSCH by using R reference signal ports $7 + (v - 7 + r) \bmod 4$ starting from the reference signal port v , where $r = 0, \dots, R - 1$, and R is an integer.

[0116] Optionally, as another embodiment, when the rank R of the PDSCH is equal to one of 5, 6 and 7, the base station sends the reference signal of the PDSCH by using R reference signal ports $7 + (v - 7 + r) \bmod 8$ starting from the reference signal port v , and when the R reference signal ports include the reference signal port $p(v)$, replaces the

reference signal port $p(v)$ with another reference signal port among the PDSCH reference

signal ports, where $r = 0, \dots, R-1$.

[0117] Optionally, as another embodiment, when a rank R of the PDSCH is equal to 3 or 4, the base station may send the reference signal of the PDSCH by using R reference signal ports $7 + (v - 7 + r) \bmod 4$ starting from the reference signal port v , where R is an integer, $r = 0, \dots, R-1$; and when the rank R of the PDSCH is equal to 2, the base station sends the reference signal of the PDSCH by using reference signal ports v and $v + (-1)^{(v-7) \bmod 2}$.

Embodiment 6

[0118] FIG. 7 is a schematic flowchart of a method for communicating downlink control information according to Embodiment 6 of the present invention. The method in FIG. 7 is executed by a UE. The method in FIG. 7 corresponds to the method in FIG. 6, and detailed descriptions here are omitted appropriately.

[0119] 710: The UE receives a reference signal of an E-PDCCH which is sent by a base station by using a first reference signal port v and a reference signal of a PDSCH which is sent by the base station by using at least one second reference signal port, where the PDSCH is invoked by the E-PDCCH.

[0120] 720: The UE performs channel estimation by using the reference signal of the E-PDCCH, so as to demodulate the E-PDCCH, and performs channel estimation by using the reference signal of the PDSCH, so as to demodulate the PDSCH.

[0121] 730: The base station determines not to use the reference signal of the PDSCH sent by a second reference signal port $p(v)$ to perform channel estimation, so that a reference signal port of the E-PDCCH and a reference signal port of the PDSCH are processed based on orthogonal time extensions with different lengths, where the E-PDCCH and the PDSCH are frequency-division multiplexed, the first reference signal port may be one of the at least one second reference signal port, and v and $p(v)$ are serial numbers of the reference signal ports.

[0122] According to the embodiment of the present invention, when sending the reference signal of the PDSCH by using a reference signal port results that the reference signal ports of the E-PDCCH and the PDSCH cannot be processed according to orthogonal time extensions with different lengths, the reference signal port may be not used to send the reference signal of the PDSCH, so that the reference signal of the PDSCH and the reference signal of the E-PDCCH are multiplexed normally.

[0123] According to the embodiment of the present invention, the at least one second reference signal port includes at least one of PDSCH reference signal ports 7, 8, 9, 10, 11, 12, 13 and 14 defined in LTE release 10; that is to say, the second reference signal port includes the PDSCH reference signal ports 7, 8, 9, 10, 11, 12, 13 or 14 defined in LTE release 10, the first reference signal port includes an E-PDCCH reference signal port 7, 8, 9, or 10 defined in

$$\text{LTE release 10, and } p(v) = \begin{cases} 11, v = 7 \\ 13, v = 8 \\ 12, v = 9 \\ 14, v = 10 \end{cases}.$$

[0124] According to the embodiment of the present invention, when a rank R of the PDSCH is less than or equal to 4, the UE performs channel estimation by using a reference signal of the PDSCH sent by a PDSCH reference signal port defined in LTE release 10.

[0125] According to the embodiment of the present invention, when the rank R of the PDSCH is one of 5, 6 and 7, the UE may perform channel estimation by using a reference signal of the PDSCH sent by a PDSCH reference signal port defined in LTE release 10, and when needing to perform channel estimation by using the reference signal of the PDSCH sent by the second reference signal port $p(v)$, replaces the reference signal port $p(v)$ with another available reference signal port among the PDSCH reference signal ports to perform channel estimation.

[0126] Optionally, as another embodiment, when a rank R of the PDSCH is less than or equal to 4, the UE performs channel estimation by using reference signals of the PDSCH sent by R reference signal ports $7 + (v - 7 + r) \bmod 4$ starting from the reference signal port v , where $r = 0, \dots, R - 1$, and R is an integer; or, when the rank R of the PDSCH is equal to one

of 5, 6 and 7, the UE performs channel estimation by using reference signals of the PDSCH sent by R reference signal ports $7 + (v - 7 + r) \bmod 8$ starting from the reference signal port v , and when the R reference signal ports include the reference signal port $p(v)$, replaces the reference signal port $p(v)$ with another reference signal port among the PDSCH reference signal ports to perform channel estimation, where $r = 0, \dots, R - 1$.

[0127] According to the embodiment of the present invention, when a rank R of the PDSCH is equal to 3 or 4, the UE performs channel estimation by using reference signals of the PDSCH sent by R reference signal ports $7 + (v - 7 + r) \bmod 4$ starting from the reference signal port v , where $r = 0, \dots, R - 1$; and when the rank of the PDSCH is equal to 2, the UE performs channel estimation by using reference signals of the PDSCH sent by reference signal ports v and $v + (-1)^{(v-7) \bmod 2}$.

[0128] With reference to a specific example, the following describes the embodiments of the present invention in more detail.

Embodiment 7

[0129] FIG. 8A is a schematic flowchart of a process for communicating downlink control information according to Embodiment 7 of the present invention. FIG. 8B is a schematic diagram showing physical resource mapping on a PDCCH according to an embodiment of the present invention. Embodiment 7 elaborates one or more steps of the methods in Embodiment 1 and Embodiment 2.

[0130] 810: A base station performs CRC check code addition, scrambling, encoding and rate matching on downlink control information of a UE, so as to obtain modulation symbols of a PDCCH.

[0131] For example, scrambling may be performed on the downlink control information of the UE by using 16-bit cyclic redundancy check (cyclic redundancy check, CRC) and a radio network temporary identity (Radio Network Temporary Identity, RNTI), and encoding and rate matching is performed on the downlink control information of the UE by using

convolutional encoding with master code being 1/3 and a circular buffering based rate, so as to obtain modulation symbols of a PDCCH.

[0132] 820: The base station maps, according to an order of OFDM symbols used by a PDCCH, the PDCCH sequentially to REs used to transmit the E-PDCCH in each OFDM symbol.

[0133] Before physical resource mapping is performed, REs that can be used to transmit the E-PDCCH in a PRB pair may be divided into several eCCEs. Here, a specific eCCE division method is not limited.

[0134] Specifically, for a localized E-PDCCH, a simple eCCE division method is to limit an eCCE to a part of subcarriers, for example, a division method in FIG. 1. Another method is to disperse REs of each eCCE to all subcarriers and all OFDM symbols of a data part of the PRB pair, for example, assuming that the quantity of REs available for the E-PDCCH in the PRB pair is N, and the REs are divided into K eCCEs. Particularly, the K eCCEs may have an equal size, that is, $\lfloor N/K \rfloor$; under this situation, the quantity of REs that are not used is

$N \bmod K$. In order to fully utilize all REs, and ensure that sizes of eCCEs divided in a PRB pair are as close as possible, a simple method is to allocate a size of $\lceil N/K \rceil$ to the first $N \bmod K$ eCCEs, and allocate a size of $\lfloor N/K \rfloor$ to other eCCEs. However, this method may cause uneven sizes of candidate E-PDCCHs at aggregation level 2; for example, assuming that K is equal to 4, and $N \bmod K = 2$, and assuming that the first two eCCEs form a candidate E-PDCCH at aggregation level 2, while the last two eCCEs form another candidate E-PDCCH at aggregation level 2, a difference in the numbers of REs between the two candidate E-PDCCHs is 2, but in fact, the two candidate E-PDCCHs may possibly have an equal number of REs. Therefore, another method to allocate eCCE sizes is to map eCCEs with a size of $\lceil N/K \rceil$ in the PRB pair to discontinuous eCCE indexes, for example, to define a size of an eCCE with an index of $\lfloor k \cdot K / (N \bmod K) \rfloor$ as $\lceil N/K \rceil$, where $k = 0, \dots, N \bmod K - 1$, and define a size of other eCCEs as $\lfloor N/K \rfloor$.

[0135] Similarly, for a distributed E-PDCCH, assuming that a total number of available REs in a PRB pair of the distributed E-PDCCH is N, and the REs are divided into K eCCEs.

Particularly, the K eCCEs may have an equal size, that is, $\lfloor N/K \rfloor$; under this situation, the quantity of REs that are not used is $N \bmod K$. In order to fully utilize all REs, and ensure that sizes of eCCEs divided in a PRB pair are as close as possible, a simple method is to allocate a size of $\lceil N/K \rceil$ to the first $N \bmod K$ eCCEs, and allocate a size of $\lfloor N/K \rfloor$ to other eCCEs. Optionally, as another embodiment, eCCEs with a size of $\lceil N/K \rceil$ may be mapped to discontinuous eCCE indexes, for example, to define a size of an eCCE with an index of $\lfloor k \cdot K / (N \bmod K) \rfloor$ as $\lceil N/K \rceil$, where $k = 0, \dots, N \bmod K - 1$, and define a size of another eCCE as $\lfloor N/K \rfloor$.

[0136] According to the embodiment of the present invention, an E-PDCCH at aggregation level L may include L eCCEs, and have a modulation symbol sequence S_j , where $j = 0, \dots, J-1$, where J is a total number of REs of the L eCCEs included in the E-PDCCH. The base station performs physical resource mapping on each E-PDCCH. The base station may, according to a frequency priority method, firstly map the E-PDCCH to REs occupied by L eCCEs allocated to the E-PDCCH on an OFDM symbol of the E-PDCCH, and then map the E-PDCCH to REs occupied by the L eCCEs allocated to the E-PDCCH on a next OFDM symbol of the E-PDCCH.

[0137] Specifically, in an OFDM symbol, the E-PDCCH may be firstly mapped to REs occupied by an eCCE among the L eCCEs included in the E-PDCCH, and then mapped to REs occupied by a next eCCE. Assuming that in an OFDM symbol, a RE set occupied by the l^{th} eCCE among the L eCCEs included in the E-PDCCH is R_l , and the quantity of REs included in the set is N_l , modulation symbols of the e-PDCCH with an index j within a range $j_0 + \sum_{q=0}^{l-1} N_q + [0, \dots, N_l - 1]$ are mapped sequentially to the REs of the set R_l according to an order of eCCEs, where j_0 is a start position of the modulation symbols of the E-PDCCH mapped in the OFDM symbol.

[0138] Optionally, as another embodiment, in an OFDM symbol, for REs of L eCCEs

allocated to the E-PDCCH, eCCEs are not differentiated and mapping is performed according to an order of subcarriers. Assuming that, in an OFDM symbol, a RE set occupied by L eCCEs included in an E-PDCCH is R , and a total number of REs included in the set is N , modulation symbols of the e-PDCCH with an index j within a range $j_0 + [0, \dots, N-1]$ are mapped sequentially to the REs of the set R , where j_0 is a start position of the modulation symbols of the E-PDCCH mapped in the OFDM symbol.

[0139] Referring to FIG. 8B, FIG. 8B shows physical resource mapping of an E-PDCCH at aggregation level 1 and physical resource mapping of an E-PDCCH at aggregation level 2. It can be seen from FIG. 8B that, a modulation symbol of an E-PDCCH at aggregation level 2 mapped in eCCE0 is almost completely different with a modulation symbol of an E-PDCCH at aggregation level 1 mapped in eCCE0 or eCCE1.

[0140] 830: The base station sends the E-PDCCH to the UE by using a RE, and sends the PDSCH scheduled by the E-PDCCH to the UE.

[0141] 840: After receiving a downlink subframe from the base station, the UE extracts, in a blind detection process according to an order of OFDM symbols used by a candidate E-PDCCH, modulation symbols of the candidate E-PDCCH sequentially from REs used to transmit the candidate E-PDCCH in each OFDM symbol.

[0142] For a PDSCH and an E-PDCCH transmitted in a subframe, the UE firstly needs to blindly detect the E-PDCCH, that is, to detect, from all candidate E-PDCCHs in a search space of the UE, the E-PDCCH that the base station sends to the UE. For example, the UE performs channel estimation based on a reference signal part, and performs demodulation, decoding and CRC check and like operations on a data symbol part, so as to obtain downlink control information (Downlink Control Information, DCI) of the UE transmitted on the E-PDCCH.

[0143] Referring to FIG. 8B again, assuming that the base station actually sends an E-PDCCH at aggregation level 2 by using eCCE0 and eCCE1, it is impossible that the UE detect an E-PDCCH at aggregation level 1 on eCCE0 and eCCE1. Therefore, according to the method in the embodiment of the present invention, the foregoing problem that a start position of the E-PDCCH is judged incorrectly and the problem that E-PDCCHs at a same

start position but different aggregation levels are mixed up are both solved.

[0144] 850: If detecting its own E-PDCCH, the UE demodulates a corresponding PDSCH according to the downlink control information in the E-PDCCH, and feeds back in the uplink according to whether the PDSCH demodulation is correct.

5 **[0145]** For example, if the PDSCH is demodulated correctly, the UE feeds back an acknowledgement (ACK) message to the eNodeB, indicating that the UE has already correctly received data sent by the eNodeB, and the eNodeB may transmit new data. Otherwise, the UE feeds back a negative-acknowledgement (NACK) message to the eNodeB, indicating that the data has not been received correctly, and the eNodeB needs to retransmit
10 the data. Another situation is that the E-PDCCH has not been detected correctly, so that the UE assumes that no data is scheduled to the UE, and does not feed back anything in an uplink, which means discontinuous transmission (Discontinuous Transmission, DTX).

Embodiment 8

[0146] FIG. 9A is a schematic flowchart of a process for communicating downlink control information according to Embodiment 8 of the present invention. Embodiment 8 elaborates
15 one or more steps of the methods in Embodiment 3 and Embodiment 4.

[0147] According to the embodiment of the present invention, a localized E-PDCCH is used as an example for description. As a reference signal of an E-PDCCH is dedicated to one UE, a reference signal port (that is a DMRS port) and eCCEs occupied by the E-PDCCH both
20 need to be defined in a design of an E-PDCCH search space. According to the embodiment of the present invention, reference signals of E-PDCCHs at different eCCE aggregation levels can be sent by using different DMRS ports, so as to prevent the UE from mixing up the E-PDCCHs at different eCCE aggregation levels.

[0148] 910: A base station performs CRC check code addition, scrambling, encoding and
25 rate matching on downlink control information of a UE, so as to obtain modulation symbols of a PDCCH. 910 in FIG. 9 is similar to 810 in FIG. 8, and is not described here any further.

[0149] 920: The base station maps an E-PDCCH to a physical source, and determines a reference signal port according to an aggregation level of the E-PDCCH of the UE, where

E-PDCCHs at different aggregation levels correspond to different reference signal ports.

[0150] Correspondence between E-PDCCHs at different eCCE aggregation levels and DMRS ports that the E-PDCCHs use may be notified by using signaling, or may be determined by using an implicit method, which means that a signaling notification is not needed, but some parameters, such as a cell identity, a UE identity and an aggregation level and the like are used to determine the correspondence. Different PRB pairs may have same correspondence, or different correspondence may be defined for each PRB pair. The correspondence may be cell-specific; for example, the base station may notify all UEs in a cell by using broadcast signaling, which means that all the UEs in the cell run according to same correspondence. The correspondence may also be UE-specific; for example, the base station may notify a specific UE by using RRC signaling, which means that different UEs may have different correspondence.

[0151] For example, the quantity of DMRS ports available for an E-PDCCH is P ; in LTE release 11, P may be equal to 4; that is to say, DMRS ports 7, 8, 9 and 10 may be used as E-PDCCH reference signal ports. Therefore, for a UE, a DMRS port used by a candidate E-PDCCH at aggregation level $L = 2^m$ may be defined as $7 + (m + \sigma) \bmod P$, where σ is a fixed value, for example, σ is equal to 0; or σ is a cell-specific parameter; or σ is a specific parameter for each transmission point in a cell in coordinated multi-point transmission; or σ is a UE-specific parameter. For example, for a UE, corresponding to candidate E-PDCCHs at aggregation levels 1, 2, 4 and 8, the reference signal is sent sequentially by using DMRS ports 7, 8, 9 and 10.

[0152] Optionally, as another embodiment, assuming that a problem that a start position of an E-PDCCH is judged incorrectly has already been solved by using another method, for example, by using a method of adding a filling bit in LTE release 8, only a problem needs to be solved that E-PDCCHs at a same start position but different aggregation levels is mixed. Here, it is only necessary to allocate different DMRS ports to candidate E-PDCCHs at a same start eCCE but different aggregation levels to send reference signals; that is to say, for candidate E-PDCCHs with different start eCCEs, a same DMRS port may be allocated to send reference signals. Assuming that correspondence between each eCCE and a DMRS port

is defined by using a method, the correspondence may be notified by using signaling, but with a high overhead; or the correspondence may be determined by using an implicit method, which means that no signaling notification is needed, but some parameters (such as a cell identity, a UE identity and an aggregation level and the like) are used to determine the correspondence. Different PRB pairs may have same correspondence, or different correspondence may be defined for each PRB pair. The correspondence may be cell-specific; for example, the base station may notify all UEs in a cell by using broadcast signaling, which means that all the UEs in the cell run according to same correspondence. The correspondence may also be UE-specific; for example, the base station may notify a specific UE by using RRC signaling, which means that different UEs may have different correspondence.

[0153] According to the embodiment of the present invention, in order to allocate different DMRS ports to candidate E-PDCCHs at a same start position but different aggregation levels, eCCEs may be sorted firstly; for example, eCCEs in a PRB pair may be numbered firstly, and eCCEs in a next PRB pair may be numbered subsequently; that is to say, an eCCE with an index i corresponds to the $(i \bmod K)^{\text{th}}$ eCCE in the $\lfloor i/K \rfloor^{\text{th}}$ E-PDCCH PRB pair, where K is the quantity of eCCEs divided in each PRB pair. The embodiment of the present invention is not limited to this numbering method.

[0154] Then, based on the eCCE numbering, a DMRS port corresponding to each eCCE is defined sequentially; for example, when the quantity of available DMRS ports is P , eCCEs may be defined to use reference signals at the P DMRS ports sequentially and circularly. In LTE release 11, P is equal to 4; that is to say, DMRS ports 7, 8, 9 and 10 may be used as E-PDCCH reference signal ports. Therefore, for a UE, a DMRS port corresponding to the i^{th} eCCE may be defined as $7 + (i + \sigma) \bmod P$, where σ is a fixed value, for example, 0; optionally, σ is a cell-specific parameter; optionally, σ is a specific parameter specific to each transmission point in a cell in coordinated multi-point transmission; and optionally, σ is a UE-specific parameter.

[0155] Finally, based on the correspondence between eCCEs and DMRS ports, a DMRS port that an E-PDCCH at each aggregation level uses is defined, and it is ensured that candidate E-PDCCHs at a same start position but different aggregation levels use different

DMRS ports. For example, when the aggregation level is $L = 2^{m-1}$ ($m = 1, 2, 3, 4$), each candidate E-PDCCH may be defined to use a DMRS port mapped to the m^{th} eCCE to send a reference signal.

[0156] FIG. 9B and FIG. 9C are examples of allocating a DMRS port to a candidate E-PDCCH.

[0157] Referring to FIG. 9B, assuming that one RBG includes two PRB pairs, and each PRB pair is divided into 4 eCCEs, according to the foregoing method, for a UE, eCCEs use DMRS ports 7, 8, 9 and 10 sequentially and circularly. For aggregation level 1, a DMRS port mapped to an eCCE included in a candidate E-PDCCH is used; for aggregation level 2, a DMRS port mapped to a second eCCE included in a candidate E-PDCCH is used, which means that DMRS ports 8 and 10 may be used; for aggregation level 4, a DMRS port mapped to a third eCCE included in a candidate E-PDCCH is used, which means port 9 is always used; and for aggregation level 8, a DMRS port mapped to a fourth eCCE included in a candidate E-PDCCH is used, which means port 10 is always used. When a candidate E-PDCCH crosses more than one PRB pair, a DMRS port determined according to the foregoing method is also configured to bear a reference signal on multiple PRB pairs mapped to the candidate E-PDCCH, for example, when the aggregation level is 8.

[0158] Referring to FIG. 9C, assuming that one RBG includes three PRB pairs, and each PRB pair is divided into 3 eCCEs, according to the foregoing method, for a UE, it is still assumed that eCCEs use DMRS ports 7, 8, 9 and 10 sequentially and circularly. For aggregation level 1, a DMRS port mapped to an eCCE included in a candidate E-PDCCH is used; for aggregation level 2, a DMRS port mapped to a second eCCE included in a candidate E-PDCCH is used, which means that DMRS ports 8 and 10 may be used; for aggregation level 4, a DMRS port mapped to a third eCCE included in a candidate E-PDCCH is used, which means port 9 is always used; and for aggregation level 8, a DMRS port mapped to a fourth eCCE included in a candidate E-PDCCH is used, which means port 10 is always used. When a candidate E-PDCCH crosses more than one PRB pair, a DMRS port determined according to the foregoing method is further configured to bear a reference signal on multiple PRB pairs mapped to the candidate E-PDCCH, for example, when the aggregation level is 2,

4 and 8.

[0159] 930: The base station sends the E-PDCCH to the UE in a subframe, and sends a PDSCH scheduled by the PDCCH to the UE.

[0160] When sending the E-PDCCH, the base station sends a reference signal of the E-PDCCH to the UE by using the determined reference signal port, where the E-PDCCH and the PDSCH invoked by the E-PDCCH are frequency-division multiplexed; and E-PDCCHs at a same start position but different aggregation levels correspond to different reference signal ports.

[0161] 940: In a blind detection process, the UE performs channel estimation according to the reference signal, so as to demodulate the candidate E-PDCCH.

[0162] Assuming that the base station sends an E-PDCCH at aggregation level 2 and sends a reference signal by using DMRS port 8, when blindly detecting each candidate E-PDCCH at aggregation level 1, the UE tries to perform channel estimation based on DMRS port 7 and demodulate the E-PDCCH; however, in fact, the base station does not send the reference signal to the UE by using DMRS port 7; it is quite clear that the demodulated output is some random noise, so that CRC check is not possible to be successful, thereby avoiding that the UE mixes up candidate E-PDCCHs at different aggregation levels. This method also solves the foregoing problem that a start position of an E-PDCCH is judged incorrectly and the problem that E-PDCCHs at a same start position but different aggregation levels are mixed up.

[0163] 950: If detecting its own E-PDCCH, the UE demodulates a corresponding PDSCH according to the downlink control information in the E-PDCCH, and feeds back in the uplink according to whether the PDSCH demodulation is correct. 950 in FIG. 9 is similar to 850 in FIG. 8, and is not described here any further.

Embodiment 9

[0164] FIG. 10 is a schematic flowchart of a process for communicating downlink control information according to Embodiment 9 of the present invention. Embodiment 9 elaborates one or more steps of the methods in Embodiment 5 and Embodiment 6.

[0165] In order to support multiplexing of an E-PDCCH and a PDSCH, another problem to be solved is how to configure reference signals of the E-PDCCH and the PDSCH. One situation is that the E-PDCCH and the PDSCH are multiplexed in one PRB pair, where because the reference signal of the E-PDCCH and the PDSCH are sent on a same PRB pair, the reference signal of the E-PDCCH may possibly be used to demodulate the PDSCH. Another situation is that the E-PDCCH and the PDSCH are multiplexed in different PRB pairs of a same RBG; here, although a PRB pair where the E-PDCCH is located does not transmit the PDSCH, it is possible that channel estimation of the reference signal of the E-PDCCH is used to enhance, by means of interpolation, channel estimation accuracy of a PRB pair where the PDSCH is located. Under both the two situations, a method for multiplexing the reference signals of the E-PDCCH and the PDSCH needs to be defined.

[0166] Specifically, when a rank of the PDSCH is one of 5, 6 and 7, a DMRS port of at least a part of data flows of the PDSCH is expanded in time by using a walsh code with a length of 4. However, in order to ensure channel estimation performance of an E-PDCCH, a reference signal of the E-PDCCH uses DMRS ports 7, 8, 9 and 10, where the four DMRS ports may be processed based on a time extension of walsh codes with a length of 2. Therefore, when the reference signals of the E-PDCCH and the PDSCH are multiplexed, a problem needs to be solved that walsh codes used by the E-PDCCH and the PDSCH have different lengths.

[0167] In release 10, a maximum rank available for PDSCH transmission is 8; a PDSCH DMRS port is mapped to two RE sets bearing a reference signal, and these two sets are multiplexed based on FDM/TDM, and may multiplex at most four DMRS ports on each RE set. DMRS ports 7, 8, 11 and 13 are multiplexed in a CDM multiplexing mode on a first RE set, while DMRS ports 9, 10, 12 and 14 are multiplexed in a CDM multiplexing mode on a second RE set.

[0168] Referring to Table 1, Table 1 shows walsh codes used by the foregoing 8 DMRS ports respectively. Walsh codes of the four DMRS ports in the first RE set are used as an example, the first two elements and the last two elements of walsh codes of DMRS ports 7 and 8 are orthogonal respectively, so that DMRS ports 7 and 8 can be processed based on an orthogonal time extension with a length of 2; the first two elements and the last two elements

of walsh codes of DMRS ports 7 and 13 are also orthogonal respectively, so that DMRS ports 7 and 13 can also be processed based on an orthogonal time extension with a length of 2. However, neither the first two elements nor the last two elements of walsh codes of DMRS ports 7 and 11 are orthogonal, but only an entirety of the four elements is orthogonal; and therefore, the two ports can only be processed based on an orthogonal time extension with a length of 4; if the UE still processes the ports according to an orthogonal time extension with a length of 2, great interference will be caused. Similarly, DMRS ports 8 and 11 can be processed based on an orthogonal time extension with a length of 2, while DMRS ports 8 and 13 can only be processed according to an orthogonal time extension with a length of 4.

10

Table 1

Antenna port p	$[\bar{w}_p(0) \ \bar{w}_p(1) \ \bar{w}_p(2) \ \bar{w}_p(3)]$
7	$[+1 \ +1 \ +1 \ +1]$
8	$[+1 \ -1 \ +1 \ -1]$
9	$[+1 \ +1 \ +1 \ +1]$
10	$[+1 \ -1 \ +1 \ -1]$
11	$[+1 \ +1 \ -1 \ -1]$
12	$[-1 \ -1 \ +1 \ +1]$
13	$[+1 \ -1 \ -1 \ +1]$
14	$[-1 \ +1 \ +1 \ -1]$

[0169] In order that a DMRS port with respect to an E-PDCCH is processed based on an orthogonal time extension with a length of 2, and also that, when a PDSCH with a rank of 5, 6 or 7 is scheduled by the E-PDCCH, a DMRS port with respect to a PDSCH is processed based on an orthogonal time extension with a length of 4, the present invention proposes the following limitation on the DMRS ports of the PDSCH; that is to say, when a DMRS port occupied by the E-PDCCH of the UE is v , a DMRS port $p(v)$ is defined not to be used to demodulate the PDSCH, or another DMRS port is needed to replace the $p(v)$, so that a

15

reference signal port of the E-PDCCH and a reference signal port of the PDSCH are processed based on orthogonal time extensions with different lengths, and that the E-PDCCH and the PDSCH can be multiplexed normally. Particularly, $p(v)$ is defined as follows:

$$p(v) = \begin{cases} 11, v = 7 \\ 13, v = 8 \\ 12, v = 9 \\ 14, v = 10 \end{cases}.$$

5 **[0170]** When the rank of the PDSCH is equal to 8, it may be considered not to support multiplexing of the reference signals of the E-PDCCH and the PDSCH. When the rank of the PDSCH is less than or equal to 4, the E-PDCCH and the PDSCH both use DMRS ports 7, 8, 9 and 10; as the four DMRS ports are all based on an orthogonal time extension with a length of 2, a problem that a DMRS port is not available as a result of another DMRS port does not exist.

[0171] 1010: A base station performs CRC check code addition, scrambling, encoding and rate matching on downlink control information of a UE, so as to obtain modulation symbols of a PDCCH. 1010 of FIG. 10 is similar to 810 of FIG. 8, and is not described here any further.

15 **[0172]** 1020: The base station performs physical resource mapping on an E-PDCCH and a PDSCH, and allocates reference signal ports of the E-PDCCH and the PDSCH, where the E-PDCCH and the PDSCH are frequency-division multiplexed in a same PRB pair or in different PRB pairs of a same RBG. According to the embodiment of the present invention, two methods for allocating reference signal ports of an E-PDCCH and a PDSCH are provided.

[0173] A first method is to adjust, according to a DMRS port occupied by the E-PDCCH, a DMRS port of the PDSCH defined in LTE release 10. A principle of the method is to maximally multiplex PDSCH DMRS ports already defined in release 10; in other words, only a port that affects a DMRS port occupied by the E-PDCCH is not used; for example, when
25 the E-PDCCH uses DMRS port 7, the PDSCH will not use DMRS port 11.

[0174] When the rank is less than or equal to 4, for transmission of a PDSCH, the definition of PDSCH DMRS ports in release 10 can be completely reused. Specifically, if a

DMRS port used by an E-PDCCH is included in DMRS ports of a currently scheduled PDSCH, the DMRS port may also be configured to demodulate the E-PDCCH and the PDSCH; if the DMRS port used by the E-PDCCH is not included in the DMRS ports of the currently scheduled PDSCH, the DMRS port is only configured to demodulate the E-PDCCH.

5 Optionally, if the definition of the PDSCH DMRS port in release 10 is followed, for the currently allocated PDSCH, the DMRS port used by the E-PDCCH is not included in the DMRS port of the currently scheduled PDSCH, but on a time-frequency resource where the DMRS port used by the E-PDCCH is located, another DMRS port based on CDM multiplexing is occupied by a reference signal of the PDSCH; here, the DMRS port used by
10 the E-PDCCH may be used to replace another DMRS port on a same time-frequency resource to demodulate the PDSCH.

[0175] When the rank is 5, 6 or 7, and a DMRS port that the base station uses to send the E-PDCCH to the UE is v , according to the definition of the PDSCH DMRS port in release 10, if a DMRS port needed by the currently scheduled PDSCH is $p(v)$, the $p(v)$ is replaced
15 with another DMRS port. Three preferred methods are described as follows, but the present invention is not limited to the three methods. When the rank is 5 or 6, the $p(v)$ is replaced with another DMRS port using a same RE set as the $p(v)$, that is, DMRS port $p(v)+2$; when the rank is 7, the $p(v)$ is replaced with DMRS port 14. Optionally, when the rank is 5, 6 or 7, the $p(v)$ is uniformly replaced with DMRS port 14. Optionally, when the rank R is 5,
20 6 or 7, the $p(v)$ is uniformly replaced with DMRS port $7+R$.

[0176] A second method is to use, according to the DMRS port v occupied by the E-PDCCH and the rank R of the currently scheduled PDSCH, R continuous DMRS ports starting from port v as PDSCH reference signal ports.

[0177] When the rank is less than or equal to 4, DMRS port $7+(v-7+r)\bmod 4$
25 $(r=0,...,R-1)$, may be used as a PDSCH reference signal port; that is to say, port $7+(v-7+r)\bmod 4$ replaces PDSCH DMRS port $7+r$ defined in release 10. This method ensures that all E-PDCCH DMRS ports can be multiplexed for PDSCH demodulation.

Optionally, when the rank is 2, in order to avoid extra resource overhead which results from that two DMRS ports are respectively mapped to two RE sets bearing a reference signal, an improved method may be used that, when the rank is 3 or 4, the foregoing method is still used; in other words, DMRS port $7 + (v - 7 + r) \bmod 4$ ($r = 0, \dots, R - 1$) may be used as the PDSCH reference signal port; however, when the rank is 2, two PDSCH DMRS ports are limited to be mapped to a same RE set; that is to say, DMRS ports v and $v + (-1)^{(v-7) \bmod 2}$ are used to transmit the PDSCH.

[0178] When the rank R is 5, 6 and 7, if the DMRS port that the base station uses to send the E-PDCCH to the UE is v , R continuous ports starting from DMRS port v are used; that is to say, DMRS port $7 + (v - 7 + r) \bmod 8$ ($r = 0, \dots, R - 1$) are used as PDSCH reference signal ports; and if the R DMRS ports include $p(v)$, $p(v)$ is replaced with another DMRS port. Two preferred methods are described as follows, but the present invention is not limited to the two methods. For example, when the rank is 5, 6 or 7, $p(v)$ is uniformly replaced with DMRS port $7 + v \bmod 8$. Optionally, when the rank R is 5, 6 and 7, $p(v)$ is uniformly replaced with DMRS port $7 + (v - 7 + R) \bmod 8$.

[0179] 1030: The base station sends the mapped PDCCH and PDSCH to the UE.

[0180] The base station sends the reference signal of the E-PDCCH by using a first reference signal port v . The base station sends a reference signal of the PDSCH by using at least one second reference signal port, and determines, according to the foregoing reference signal port allocation method, not to use a second reference signal port $p(v)$ but to select another reference signal port to send the reference signal of the PDSCH, so that a reference signal port of the E-PDCCH and a reference signal port of the PDSCH are processed based on orthogonal time extensions with different lengths, where the first reference signal port is one of the at least one second reference signal port.

[0181] 1040: The UE demodulates the E-PDCCH based on a channel estimation result.

[0182] The UE receives the reference signal of the E-PDCCH which is sent by the base station by using the first reference signal port v and the reference signal of the PDSCH

which is sent by the base station by using at least one second reference signal port, where the PDSCH is invoked by the E-PDCCH. The UE performs channel estimation by using the reference signal of the E-PDCCH, so as to demodulate the E-PDCCH, and performs channel estimation by using the reference signal of the PDSCH, so as to demodulate the PDSCH. The UE determines, according to the foregoing reference signal port allocation method, not to use the reference signal of the PDSCH sent by the second reference signal port $p(v)$ but to select another reference signal port to perform channel estimation, so that a reference signal port of the E-PDCCH and a reference signal port of the PDSCH are processed based on orthogonal time extensions with different lengths, where the first reference signal port is one of the at least one second reference signal port.

[0183] Similarly, the foregoing method for allocating reference signal ports of the E-PDCCH and the PDSCH may be configured in the UE; a specific method is similar to the method for allocating reference signal ports of the E-PDCCH and the PDSCH at a base station end, and is not described here any further.

[0184] 1050: If detecting its own E-PDCCH, the UE demodulates a corresponding PDSCH according to the downlink control information in the E-PDCCH, and feeds back in the uplink according to whether the PDSCH demodulation is correct. 1050 in FIG. 10 is similar to 850 in FIG. 8, and is not described here any further.

[0185] The method for communicating downlink control information according to the embodiment of the present invention is described above; with reference to FIG. 11 to FIG. 16, the following respectively describes a base station, a UE, and a system, as well as a corresponding storable medium and a corresponding computer program product, according to embodiments of the present invention.

Embodiment 10

[0186] FIG. 11 is a schematic structural diagram of a base station 1100 according to Embodiment 10 of the present invention. The base station 1100 includes a mapping unit 1110 and a sending unit 1120. The embodiment in FIG. 11 elaborates one or more steps of the method in the embodiment in FIG. 2.

[0187] The mapping unit 1110 maps, according to an order of OFDM symbols used by an E-PDCCH of a UE, the E-PDCCH sequentially to REs used to transmit the E-PDCCH in each OFDM symbol. The sending unit 1120 sends the E-PDCCH to the UE by using the REs, where the E-PDCCH and a PDSCH invoked by the E-PDCCH are frequency-division multiplexed.

[0188] In the embodiment of the present invention, the E-PDCCH can be mapped, according to the order of OFDM symbols used by the E-PDCCH of the UE, sequentially to the REs used to transmit the E-PDCCH in each OFDM symbol, so that different eCCEs will not include a same E-PDCCH modulation symbol, thereby avoiding that the UE judges a start position of the E-PDCCH incorrectly. In addition, a problem that E-PDCCHs at a same start position but different aggregation levels are mixed up is also solved.

[0189] According to the embodiment of the present invention, the mapping unit 1110 maps, according to an order of L eCCEs allocated to the E-PDCCH in each OFDM symbol, the E-PDCCH sequentially to REs occupied by the L eCCEs in the OFDM symbol, where L is an integer.

[0190] Optionally, as another embodiment, the mapping unit 1110 maps, according to an order of subcarriers in each OFDM symbol, the E-PDCCH sequentially to REs occupied by L eCCEs allocated to the E-PDCCH.

[0191] For operations executed by means of hardware of the base station 1100 or cooperation of hardware and corresponding software of the base station 1100, reference may be made to the corresponding method in Embodiment 1, for example, 210 and 220 of the method in the foregoing Embodiment 1. However, to avoid repetition, the steps are not described here any further.

[0192] In addition, a computer readable media (or medium) is further provided, including a computer readable instruction that performs the following operation when executed, that is, an operation of executing 210 and 220 of the method the foregoing Embodiment 1.

[0193] In addition, a computer program product is further provided, including the foregoing computer readable medium.

Embodiment 11

[0194] FIG. 12 is a schematic structural diagram of a UE 1200 according to Embodiment 11 of the present invention. The UE 1200 includes a receiving unit 1210 and an extracting unit 1220. The embodiment in FIG. 12 elaborates one or more steps of the method in the
5 embodiment in FIG. 3.

[0195] The receiving unit 1210 receives a downlink subframe from a base station. The extracting unit 1220 extracts, in a blind detection process according to an order of OFDM symbols used by a candidate E-PDCCH in the downlink subframe, modulation symbols of the candidate E-PDCCH sequentially from REs used to transmit the candidate E-PDCCH in
10 each OFDM symbol, and performs decoding and CRC check on the candidate E-PDCCH, where the E-PDCCH of the UE and a PDSCH invoked by the E-PDCCH of the UE are frequency-division multiplexed.

[0196] In the embodiment of the present invention, the E-PDCCH can be mapped, according to the order of OFDM symbols used by the E-PDCCH of the UE, sequentially to
15 the REs used to transmit the E-PDCCH in each OFDM symbol, so that different eCCEs will not include a same E-PDCCH modulation symbol, thereby avoiding that the UE judges a start position of the E-PDCCH incorrectly. In addition, a problem that E-PDCCHs at a same start position but different aggregation levels are mixed up is also solved.

[0197] According to the embodiment of the present invention, the extracting unit 1220
20 sequentially extracts, according to an order of L eCCEs allocated to the candidate E-PDCCH in each OFDM symbol, modulation symbols of the candidate E-PDCCH from REs occupied by the L eCCEs in the OFDM symbol, where L is an integer.

[0198] Optionally, as another embodiment, the extracting unit 1220 sequentially extracts, according to an order of subcarriers in each OFDM symbol, the E-PDCCH from REs
25 occupied by L eCCEs allocated to the E-PDCCH.

[0199] For operations executed by means of hardware of the UE 1200 or cooperation of hardware and corresponding software of the UE 1200, reference may be made to the corresponding method in Embodiment 2, for example, 310 and 320 of the method in the foregoing Embodiment 2. However, to avoid repetition, the steps are not described here any

further.

[0200] In addition, a computer readable media (or medium) is further provided, including a computer readable instruction that performs the following operation when executed, that is, an operation of executing 310 and 320 of the method in the foregoing Embodiment 2.

5 **[0201]** Further, a computer program product is further provided, including the foregoing computer readable medium.

Embodiment 12

[0202] FIG. 13 is a schematic structural diagram of a base station 1300 according to Embodiment 12 of the present invention. The base station 1300 includes a determining unit
10 1310 and a sending unit 1320. The embodiment in FIG. 13 elaborates one or more steps of the method in the embodiment in FIG. 4.

[0203] The determining unit 1310 is configured to determine a reference signal port according to an aggregation level of an E-PDCCH of a UE, where E-PDCCHs at different aggregation levels correspond to different reference signal ports, and the aggregation level
15 indicates the quantity of eCCEs included in the E-PDCCH. The sending unit 1320 is configured to send the E-PDCCH to the UE in a subframe, and send a reference signal of the E-PDCCH to the UE by using the determined reference signal port, where the E-PDCCH and a PDSCH invoked by the E-PDCCH are frequency-division multiplexed.

[0204] According to the embodiment of the present invention, reference signals of
20 E-PDCCHs at different eCCE aggregation levels can be sent by using different DMRS ports, so that the UE can demodulate, according to a dedicated DMRS reference signal of an E-PDCCH at each aggregation level, the E-PDCCH correctly, thereby avoiding a problem that the UE judges a start position of the E-PDCCH incorrectly. In addition, a problem that E-PDCCHs at a same start position but different aggregation levels are mixed up is also
25 solved.

[0205] According to the embodiment of the present invention, E-PDCCHs at a same start position but different aggregation levels in the subframe correspond to different reference signal ports.

[0206] Further, the determining unit 1310 may be specifically configured to select, according to the aggregation level of the physical downlink control channel E-PDCCH of the user equipment UE, one or more reference signal ports from a reference signal port set corresponding to the aggregation level as a reference signal port corresponding to the aggregation level, where reference signal ports selected for E-PDCCHs at different aggregation levels are different.

[0207] Further, the at a same start position in the subframe may include: at a same start position in a same physical resource block pair or different physical resource block pairs.

[0208] Further, E-PDCCHs, corresponding to different user equipments UEs, at a same aggregation level, and occupying a same physical resource, correspond to different reference signal ports.

[0209] For operations executed by means of hardware of the base station 1300 or cooperation of hardware and corresponding software of the base station 1300, reference may be made to the corresponding method in Embodiment 3, for example, 410 and 420 of the method in the foregoing Embodiment 3. However, to avoid repetition, the steps are not described here any further.

[0210] In addition, a computer readable media (or medium) is further provided, including a computer readable instruction that performs the following operation when executed, that is, an operation of executing 410 and 420 of the method in the foregoing Embodiment 3.

[0211] In addition, a computer program product is further provided, including the foregoing computer readable medium.

Embodiment 13

[0212] FIG. 14 is a schematic structural diagram of a UE 1400 according to Embodiment 13 of the present invention. The UE 1400 includes a receiving unit 1410 and a demodulating unit 1420. The embodiment in FIG. 14 elaborates one or more steps of the method in the embodiment in FIG. 5.

[0213] The receiving unit 1410 receives, from a reference signal port in a subframe, a reference signal of a candidate E-PDCCH sent by a base station, where candidate E-PDCCHs

at different aggregation levels correspond to different reference signal ports, and the aggregation level indicates the quantity of eCCEs included in the candidate E-PDCCH. The demodulating unit 1420 performs channel estimation according to the reference signal, so as to demodulate the E-PDCCH, where the candidate E-PDCCH and a PDSCH invoked by the candidate E-PDCCH are frequency-division multiplexed.

[0214] According to the embodiment of the present invention, reference signals of E-PDCCHs at different eCCE aggregation levels can be sent by using different DMRS ports, so that the UE can demodulate, according to a dedicated DMRS reference signal of an E-PDCCH at each aggregation level, the E-PDCCH correctly, thereby avoiding a problem that the UE judges a start position of the E-PDCCH incorrectly. In addition, a problem that E-PDCCHs at a same start position but different aggregation levels are mixed up is also solved.

[0215] According to the embodiment of the present invention, candidate E-PDCCHs at a same start position but different aggregation levels in the subframe correspond to different reference signal ports.

[0216] For operations executed by means of hardware of the UE 1400 or cooperation of hardware and corresponding software of the UE 1400, reference may be made to the corresponding method in Embodiment 4, for example, 510 and 520 of the method in the foregoing Embodiment 4. However, to avoid repetition, the steps are not described here any further.

[0217] In addition, a computer readable media (or medium) is further provided, including a computer readable instruction that performs the following operation when executed, that is, an operation of executing 510 and 520 of the method in the foregoing Embodiment 4.

[0218] In addition, a computer program product is further provided, including the foregoing computer readable medium.

Embodiment 14

[0219] FIG. 15 is a schematic structural diagram of a base station 1500 according to Embodiment 14 of the present invention. The base station 1500 includes a sending unit 1510

and a determining unit 1520. The embodiment in FIG. 15 elaborates one or more steps of the method in the embodiment in FIG. 6.

[0220] The sending unit 1510 sends a reference signal of the E-PDCCH by using a first reference signal port v , and send a reference signal of the PDSCH by using at least one second reference signal port. The determining unit 1520 determines not to use a second reference signal port $p(v)$ to send the reference signal of the PDSCH, so that a reference signal port of the E-PDCCH and a reference signal port of the PDSCH are processed based on orthogonal time extensions with different lengths, where the E-PDCCH and the PDSCH are frequency-division multiplexed, the first reference signal port is one of the at least one second reference signal port, and v and $p(v)$ are serial numbers of the reference signal ports.

[0221] According to the embodiment of the present invention, when using a reference signal port to send a reference signal of a PDSCH results that a reference signal port of an E-PDCCH and the reference signal port of the PDSCH cannot be processed based on orthogonal time extensions with different lengths, the reference signal port may be not used to send the reference signal of the PDSCH, so that the reference signal of the PDSCH and a reference signal of the E-PDCCH are multiplexed normally.

[0222] According to the embodiment of the present invention, the at least one second reference signal port includes at least one of PDSCH reference signal ports 7, 8, 9, 10, 11, 12, 13 and 14 defined in LTE release 10, the first reference signal port includes an E-PDCCH

reference signal port 7, 8, 9, or 10 defined in LTE release 10, and $p(v) = \begin{cases} 11, v = 7 \\ 13, v = 8 \\ 12, v = 9 \\ 14, v = 10 \end{cases}$.

[0223] According to the embodiment of the present invention, when a rank R of the PDSCH is less than or equal to 4, the sending unit 1510 sends the reference signal of the PDSCH by using a PDSCH reference signal port defined in LTE release 10; or when the rank R of the PDSCH is one of 5, 6 and 7, the sending unit 1510 sends the reference signal of the PDSCH by using a PDSCH reference signal port defined in LTE release 1, and when needing

to send the reference signal of the PDSCH by using the second reference signal port $p(v)$ to, the sending unit 1510 replaces the reference signal port $p(v)$ with another available reference signal port among the PDSCH reference signal ports, where R is an integer.

[0224] Optionally, as another embodiment, when a rank R of the PDSCH is less than or equal to 4, the sending unit 1510 may send the reference signal of the PDSCH by using R reference signal ports $7 + (v - 7 + r) \bmod 4$ starting from the reference signal port v , where $r = 0, \dots, R - 1$, and R is an integer; or, when the rank R of the PDSCH is equal to one of 5, 6 and 7, the sending unit 1510 may send the reference signal of the PDSCH by using R reference signal ports $7 + (v - 7 + r) \bmod 8$ starting from the reference signal port v , and when the R reference signal ports include the reference signal port $p(v)$, replace the reference signal port $p(v)$ with another reference signal port among the PDSCH reference signal ports, where $r = 0, \dots, R - 1$.

[0225] For operations executed by means of hardware of the base station 1500 or cooperation of hardware and corresponding software of the base station 1500, reference may be made to the corresponding method in Embodiment 5, for example, 610 and 620 of the method in the foregoing Embodiment 5. However, to avoid repetition, the steps are not described here any further.

[0226] In addition, a computer readable media (or medium) is further provided, including a computer readable instruction that performs the following operation when executed, that is, an operation of executing 610 and 620 of the method in the foregoing Embodiment 5.

[0227] In addition, a computer program product is further provided, including the foregoing computer readable medium.

Embodiment 15

[0228] FIG. 16 is a schematic structural diagram of a UE 1600 according to Embodiment 15 of the present invention. The UE 1600 includes a receiving unit 1610, a demodulating unit 1620, and a determining unit 1630. The embodiment in FIG. 16 elaborates one or more steps

of the method in the embodiment in FIG. 7.

[0229] The receiving unit 1610 is configured to receive a reference signal of an E-PDCCH which is sent by a base station by using a first reference signal port v and a reference signal of a PDSCH which is sent by the base station by using at least one second reference signal port, where the PDSCH is invoked by the E-PDCCH. The demodulating unit 1620 is configured to perform channel estimation by using the reference signal of the E-PDCCH, so as to demodulate the E-PDCCH, and perform channel estimation by using the reference signal of the PDSCH, so as to demodulate the PDSCH. The determining unit 1630 is configured to determine not to use the reference signal of the PDSCH sent by the second reference signal port $p(v)$ to perform channel estimation, so that a reference signal port of the E-PDCCH and a reference signal port of the PDSCH are processed based on orthogonal time extensions with different lengths, where the E-PDCCH and the PDSCH are frequency-division multiplexed, the first reference signal port is one of the at least one second reference signal port, and v and $p(v)$ are serial numbers of the reference signal ports.

[0230] According to the embodiment of the present invention, the at least one second reference signal port includes at least one of PDSCH reference signal ports 7, 8, 9, 10, 11, 12, 13 and 14 defined in LTE release 10, the first reference signal port includes an E-PDCCH

reference signal port 7, 8, 9, or 10 defined in LTE release 10, and $p(v) = \begin{cases} 11, v = 7 \\ 13, v = 8 \\ 12, v = 9 \\ 14, v = 10 \end{cases}$.

[0231] According to the embodiment of the present invention, when a rank R of the PDSCH is less than or equal to 4, the demodulating unit 1620 performs channel estimation by using a reference signal of the PDSCH sent by a PDSCH reference signal port defined in LTE release 10; or when the rank R of the PDSCH is one of 5, 6 and 7, the demodulating unit 1620 performs channel estimation by using a reference signal of the PDSCH sent by a PDSCH reference signal port defined in LTE release 10, and when the UE needs to perform channel estimation by using the reference signal of the PDSCH sent by the second reference signal port $p(v)$, replaces the reference signal port $p(v)$ with another available reference

signal port among the PDSCH reference signal ports to perform channel estimation, where R is an integer.

[0232] Optionally, as another embodiment, when a rank R of the PDSCH is less than or equal to 4, the demodulating unit 1620 may perform channel estimation by using reference signals of the PDSCH sent by R reference signal ports $7 + (v - 7 + r) \bmod 4$ starting from the reference signal port v , where $r = 0, \dots, R - 1$, and R is an integer; or, when the rank R of the PDSCH is equal to one of 5, 6 and 7, the demodulating unit 1620 may to perform channel estimation by using reference signals of the PDSCH sent by R reference signal ports $7 + (v - 7 + r) \bmod 8$ starting from the reference signal port v , and when the R reference signal ports include the reference signal port $p(v)$, replace the reference signal port $p(v)$ with another reference signal port among the PDSCH reference signal ports to perform channel estimation, where $r = 0, \dots, R - 1$.

[0233] For operations executed by means of hardware of the UE 1600 or cooperation of hardware and corresponding software of the UE 1600, reference may be made to the corresponding method in Embodiment 6, for example, 710, 720 and 730 of the method in the foregoing Embodiment 6. However, to avoid repetition, the steps are not described here any further.

[0234] In addition, a computer readable media (or medium) is further provided, including a computer readable instruction that performs the following operation when executed, that is, an operation of executing 710 and 720 of the method in the foregoing Embodiment 6.

[0235] In addition, a computer program product is further provided, including the foregoing computer readable medium.

[0236] A person of ordinary skill in the art may recognize that units and algorithmic steps of examples described with reference to the embodiments disclosed herein may be implemented by means of electronic hardware or combination of computer software and electronic hardware. Whether the functions are executed by hardware or software depends on particular applications and design constraint conditions of the technical solutions. A person skilled in the art may use different methods to implement the described functions for each

particular application, but it should not be considered that the implementation goes beyond the scope of the present invention.

[0237] A person skilled in the art can clearly understand that, for convenience and conciseness of description, for specific working processes of the described systems, apparatuses and units, reference may be made to corresponding processes in the foregoing method embodiments, which will not be described here any further.

[0238] In the several embodiments provided in the present application, it should be understood that the disclosed system, apparatus, and method may be implemented in other manners. For example, the described apparatus embodiment is merely exemplary. For example, the unit division is merely logical function division and may be other division in actual implementation. For example, a plurality of units or components may be combined or integrated into another system, or some features may be ignored or not performed. In addition, the displayed or discussed mutual couplings or direct couplings or communication connections may be implemented through some interfaces. The indirect couplings or communication connections between the apparatuses or units may be implemented in electronic, mechanical, or other forms.

[0239] The units described as separated parts may be or may not be physically separate, and the parts displayed as units may or may not be physical units, may be located in one position, or may be distributed on a plurality of network units. A part of or all of the units may be selected according to actual needs to achieve the objectives of the solutions of the embodiments.

[0240] In addition, the functional units of each embodiment in the present invention may be integrated in a physical unit, or each of the units may exist alone physically, or two or more units may be integrated into one unit.

[0241] When the functions are implemented in a form of a software functional unit and sold or used as an independent product, the functions may be stored in a computer-readable storage medium. Based on such an understanding, the technical solutions of the present invention essentially, or the part contributing to the prior art, or a part of the technical solutions may be implemented in a form of a software product. The computer software product is stored in a storage medium and includes several instructions for instructing a

computer device (which may be a personal computer, a server, a network device, or the like) to perform all or a part of the steps of the methods described in the embodiments of the present invention. The foregoing storage medium includes: any mediums that can store program code, such as a USB flash drive, a removable hard disk, a read-only memory (ROM, 5 Read-Only Memory), a random access memory (RAM, Random Access Memory), a magnetic disk, or an optical disc.

Embodiment 16

[0242] In LTE R-11, the quantity of aggregation levels corresponding to a UE is M ; if E-PDCCHs at N aggregation levels among the M aggregation levels are mixed up, correct 10 reception of an E-PDCCH or a PDSCH by the UE will be affected, where M is not less than N , and M and N are integers.

[0243] Downlink control channels E-PDCCHs have M aggregation levels, where each aggregation level of N aggregation levels thereof corresponds to a reference signal port set. With respect to a user equipment UE, for each aggregation level of the N aggregation levels, 15 a base station selects a reference signal port from a reference signal port set corresponding to the aggregation level as a reference signal port corresponding to the aggregation level; reference signal ports selected for the N aggregation levels of the UE are different from each other; and the reference signal port set at least includes one reference signal port.

[0244] The base station sends the E-PDCCH to the UE in a subframe, and sends a 20 reference signal of the E-PDCCH to the UE by using a determined reference signal port, where N is less than or equal to M .

[0245] For E-PDCCH transmission, each physical resource block pair may include 2 or 4 physical eCCEs, where each physical eCCE bears eCCEs of one ePDCCH, as shown in FIG. 17. An E-PDCCH at aggregation level L includes L logical eCCEs; the L logical eCCEs are 25 mapped to L physical eCCEs; and control information of the E-PDCCH is transmitted on the L physical eCCEs.

[0246] If each PRB pair includes 4 eCCEs, according to a size of control signaling, the numbers of PRB pairs occupied by an ePDCCH corresponding to aggregation levels 2, 4, 8,

12, 16 and above 16 are respectively 1, 1, 2, 3, 4 and above 4. For example, when a UE detects an E-PDCCH at aggregation level 8, if the first 4 eCCEs are detected successfully, the UE regards the aggregation level of the E-PDCCH as 4 and the quantity of PRB pairs occupied as 1. In fact, the quantity of PRB pairs occupied by the E-PDCCH is 2. In this case, the UE may possibly regard the rest 4 eCCEs as resources to transmit a PDSCH, and receive the PDSCH on the rest 4 eCCEs, which may cause incorrect reception of the PDSCH. Similarly, if each PRB pair includes two eCCEs, according to a size of control signaling, the numbers of PRB pairs occupied by an ePDCCH corresponding to aggregation levels 2, 4, 8, 12, 16 and above 16 are respectively 1, 2, 4, 6, 8 and above 8. When the E-PDCCH is received, the foregoing problem that aggregation levels are mixed up will also occur. Aggregation levels that are possible to be mixed up for a UE are possibly N of the aggregation levels 2, 4, 8, 12, 16 and above 16, and each aggregation level of the N aggregation levels corresponds to a reference signal port set. A reference signal port corresponding to aggregation level L among the N aggregation levels of the UE is one or more reference signal ports selected from a reference signal port set corresponding to the aggregation level L. Reference signal ports selected for the N aggregation levels of the UE are different from each other.

[0247] To be specific, for example:

[0248] If each physical resource block includes four physical eCCEs, a reference signal port set corresponding to aggregation level 2 may be set 1, a reference signal port set corresponding to aggregation level 4 may be set 2, and a reference signal port set corresponding to aggregation level 8 may be set 3. Reference signal ports included in each set may be completely different, partially the same or the completely same. The quantity of reference signal ports respectively included in set 1, set 2 and set 3 is at least 1. For any UE, a reference signal port selected from set 1 is r, a reference signal port selected from set 2 is s, and a reference signal port selected from set 3 is t. A reference signal port corresponding to aggregation level 2 of the UE is r, a reference signal port corresponding to aggregation level 4 of the UE is s, and a reference signal port corresponding to aggregation level 8 of the UE is t, where r, s and t are different from each other. For example, set 1 is {reference signal port 7, reference signal port 8, reference signal port 9, reference signal port 10}, set 2 is {reference

signal port 8, reference signal port 9}, and set 3 is {reference signal port 7, reference signal port 10}. As shown in FIG. 18, for UE1 (or all UEs in cell 1, aggregation level 2 corresponds to reference signal port 7 or 9, aggregation level 4 corresponds to reference signal port 8, and aggregation level 8 corresponds to reference signal port 10; for UE2 (or all UEs in cell 2, aggregation level 2 corresponds to reference signal port 8 or 10, aggregation level 4 corresponds to reference signal port 9, and aggregation level 8 corresponds to reference signal port 7. It can be seen that, if reference signal ports are configured in such a manner, for a same UE, aggregation levels 2, 4 and 8 correspond to different reference signal ports, which can avoid the problem that the aggregation levels are mixed up. Further, E-PDCCHs, corresponding to different user equipments UEs, at a same aggregation level, and occupying a same physical resource, correspond to different reference signal ports, and can support multi-user transmission. For example, for aggregation level 2, physical resources that the first E-PDCCHs of UE1 and UE2 occupy are eCCE0 and eCCE1, while physical resources that the second E-PDCCHs of UE1 and UE2 occupy are eCCE2 and eCCE3. For aggregation level 2, the first E-PDCCHs of UE1 and UE2 correspond to different reference signal ports, so as to support simultaneous transmission of UE1 and UE2 on eCCE0 and eCCE1; and the second E-PDCCHs of UE1 and UE2 correspond to different reference signal ports, so as to support simultaneous transmission of UE1 and UE2 on eCCE2 and eCCE3.

[0249] If each physical resource block includes two physical eCCEs, a reference signal port set corresponding to aggregation level 2 is set 1, a reference signal port set corresponding to aggregation level 4 is set 2, and a reference signal port set corresponding to aggregation level 8 is set 3. Reference signal ports included in each set may be completely different, partially the same or completely the same. The quantity of reference signal ports respectively included in set 1, set 2 and set 3 is at least 1. For any UE, a reference signal port selected from set 1 is r , a reference signal port selected from set 2 is s , and a reference signal port selected from set 3 is t . A reference signal port corresponding to aggregation level 2 of the UE is r , a reference signal port corresponding to aggregation level 4 of the UE is s , and a reference signal port corresponding to aggregation level 8 of the UE is t , where r , s and t are different from each other. For example, set 1 is {reference signal port 7, reference signal port 10}, set 2 is {reference signal port 8, reference signal port 9}, and set 3 is {reference signal

port 7, reference signal port 10}. As shown in FIG. 19, for UE1 (or all UEs in cell 1, aggregation level 2 corresponds to reference signal port 7, aggregation level 4 corresponds to reference signal port 9, and aggregation level 8 corresponds to a reference signal port 10; for UE2 (or all UEs in cell 2, aggregation level 2 corresponds to reference signal port 10, aggregation level 4 corresponds to reference signal port 8, and aggregation level 8 corresponds to reference signal port 7. It can be seen that, if reference signal ports are configured in such a manner, for a same UE, aggregation levels 2, 4 and 8 correspond to different reference signal ports, which can avoid the problem that the aggregation levels are mixed up. Further, E-PDCCHs, corresponding to different user equipments UEs, at a same aggregation level, and occupying a same physical resource, correspond to different reference signal ports, and can support multi-user transmission.

[0250] Further, that reference signal ports selected for the N aggregation levels of the UE are different from each other may specifically be: reference signal ports selected for E-PDCCHs at the N aggregation levels of the UE, which are mapped to a same physical resource start position are different from each other, which may also be understood that, E-PDCCHs at a same start position but different aggregation levels in the subframe correspond to different reference signal ports.

[0251] Further, the at a same start position in the subframe may include: at a same start position in a same physical resource block pair or different physical resource block pairs. The "at a same start position in the subframe" herein may all be understood as above, and is not described any further.

[0252] As shown in FIG. 20, for UE1 and UE2, in a same PRB pair, two E-PDCCHs are at aggregation level 2, where a first E-PDCCH is mapped to eCCE0 and eCCE1, where eCCE0 is a start position; and a second E-PDCCH is mapped to eCCE2 and eCCE3, where eCCE2 is a start position. One E-PDCCH is at aggregation level 4, which is mapped to eCCE0, eCCE1, eCCE2 and eCCE3, where eCCE0 is a start position. One E-PDCCH is at aggregation level 8, which is mapped to eCCE0, eCCE1, eCCE2 and eCCE3, as well as eCCE0, eCCE1, eCCE2 and eCCE3 of another PRB pair, where eCCE0 is a start position.

[0253] Then, for UE1, reference signal ports selected for the two E-PDCCHs at aggregation level 2 are reference signal ports 7 and 10 respectively, a reference signal port

selected for the E-PDCCH at aggregation level 4 is reference signal port 8, and a reference signal port selected for the E-PDCCH at aggregation level 8 is reference signal port 10. It can be seen that reference signal ports selected for E-PDCCHs at aggregation levels 2, 4 and 8 and mapped to a same physical resource start position (that is eCCE0 in this embodiment) are respectively reference signal ports 7, 8 and 10, which are different from each other. For UE2, reference signal ports selected for the two E-PDCCHs at aggregation level 2 are reference signal ports 8 and 9 respectively, a reference signal port selected for the E-PDCCH at aggregation level 4 is reference signal port 9, and a reference signal port selected for the E-PDCCH at aggregation level 8 is reference signal port 7. It can be seen that reference signal ports selected for E-PDCCHs at aggregation levels 2, 4 and 8 and mapped to a same physical resource start position (that is eCCE0 in this embodiment) are respectively reference signal ports 8, 9 and 7, which are different from each other. The at a same physical resource start position may be understood as at a same start position in the subframe. Further, the at a same start position in the subframe includes: at a same start position in a same physical resource block pair or different physical resource block pairs. That is to say, the at a same start position in the subframe may be at a same start position in different PRB pairs or at a same start position in identical PRB pairs. As shown in FIG. 21, physical resource position 1 is eCCE0 of PRB pair 1, physical resource position 2 is eCCE0 of PRB pair 2, and physical resource position 3 is eCCE0 of PRB pair 3. A same start position in different PRB pairs means that positions of the PRB pairs are different, but start positions in the PRB pairs are the same; for example, if one start position is physical resource position 1, and another start position is physical resource position 3, and it may be called at a same start position in different PRB pairs. A same start position in identical PRB pairs means that positions of PRB pairs are the same and start positions in the PRB pairs are also the same; for example, if the two start positions both are physical resource position 1 or the two start positions both are physical resource position 3, it may be called at a same start position in identical PRB pairs.

[0254] The methods of configuring a reference signal port set and selecting a reference signal port from the reference signal port set are shared by the base station and the UE, and may be defined and configured by the system previously, or notified to the UE by the base station, or obtained according to a parameter of the UE, or the like.

[0255] Understandably, the selected reference signal ports are only used for description; a person skilled in the art may deduce another reference signal port set or an example of selecting a reference signal port from the set, which is not limited in the present invention.

[0256] It should be noted that, due to limited space, mutual reference may be made to corresponding embodiments of the present invention, and same content will not be described repetitively.

[0257] The foregoing descriptions are merely specific embodiments of the present invention, but are not intended to limit the protection scope of the present invention. Any variation or replacement readily figured out by a person skilled in the art within the technical scope disclosed in the present invention shall fall within the protection scope of the present invention. Therefore, the protection scope of the present invention shall be subject to the protection scope of the claims.

CLAIMS

What is claimed is:

1. A method for communicating a downlink control signal, comprising:

mapping, by a base station according to an order of orthogonal frequency division
5 multiplexing OFDM symbols used by a physical downlink control channel E-PDCCH of a
user equipment UE, the E-PDCCH sequentially to resource elements used to transmit the
E-PDCCH in each OFDM symbol; and

sending, by the base station, the E-PDCCH to the UE by using the resource elements.

2. The method according to claim 1, wherein:

10 the E-PDCCH and a physical downlink shared channel PDSCH invoked by the
E-PDCCH are frequency-division multiplexed.

3. The method according to claim 1 or 2, wherein

the mapping the E-PDCCH sequentially to resource elements used to transmit the
E-PDCCH in each OFDM symbol comprises:

15 mapping, according to an order of L control channel elements allocated to the E-PDCCH
in each OFDM symbol, the E-PDCCH sequentially to resource elements occupied by the L
control channel elements in the OFDM symbol, wherein L is an integer.

4. The method according to claim 3, wherein the mapping the E-PDCCH sequentially to
resource elements occupied by the L control channel elements in the OFDM symbol
20 comprises:

mapping modulation symbols of the e-PDCCH with index numbers of
 $j_0 + \sum_{q=0}^{l-1} N_q + [0, \dots, N_l - 1]$ sequentially to resource elements of a set R_l , wherein the set R_l
is a set of resource elements occupied by the l^{th} control channel element among the L
control channel elements comprised in the E-PDCCH in the OFDM symbol; j_0 is a start
25 position of the modulation symbols of the E-PDCCH mapped in the OFDM symbol; N_l is
the quantity of the resource elements in the set R_l ; and N_l , j_0 , l and q are integers.

5. The method according to claim 1 or 2, wherein the mapping the E-PDCCH sequentially to resource elements used to transmit the E-PDCCH in each OFDM symbol comprises:

mapping, by the base station according to an order of subcarriers in each OFDM symbol, the E-PDCCH sequentially to resource elements occupied by L control channel elements allocated to the E-PDCCH, wherein L is an integer.

6. The method according to claim 5, wherein the mapping the E-PDCCH sequentially to resource elements occupied by L control channel elements allocated to the E-PDCCH comprises:

mapping modulation symbols of the E-PDCCH with index numbers of $j_0 + [0, \dots, N - 1]$ sequentially to resource elements of a set R, wherein j_0 is a start position of the modulation symbols of the E-PDCCH mapped in the OFDM symbol; the set R is a set of resource elements occupied by the L control channel elements comprised in the E-PDCCH in the OFDM symbol; N is the quantity of the resource elements in the set R; and N and j_0 are integers.

7. A method for communicating a downlink control signal, comprising:

receiving, by a user equipment UE, a downlink subframe from a base station; and

extracting, by the UE in a blind detection process according to an order of orthogonal frequency division multiplexing OFDM symbols used by a candidate physical downlink control channel E-PDCCH in the downlink subframe, modulation symbols of the candidate E-PDCCH sequentially from resource elements used to transmit the candidate E-PDCCH in each OFDM symbol, and performing decoding and cyclic redundancy check CRC on the candidate E-PDCCH.

8. The method according to claim 6, wherein:

the E-PDCCH of the UE and a physical downlink shared channel PDSCH invoked by the E-PDCCH of the UE are frequency-division multiplexed.

9. The method according to claim 7 or 8, wherein the extracting modulation symbols of the candidate E-PDCCH sequentially from resource elements used to transmit the candidate E-PDCCH in each OFDM symbol comprises:

extracting, according to an order of L control channel elements allocated to the E-PDCCH in each OFDM symbol, the modulation symbols of the candidate E-PDCCH sequentially from resource elements occupied by the L control channel elements in the OFDM symbol, wherein L is an integer.

5 10. The method according to claim 9, wherein the extracting the modulation symbols of the candidate E-PDCCH sequentially from resource elements occupied by the L control channel elements in the OFDM symbol comprises:

extracting modulation symbols of the candidate E-PDCCH and with index numbers of

$j_0 + \sum_{q=0}^{l-1} N_q + [0, \dots, N_l - 1]$ from resource elements of a set R_l , wherein the set R_l is a set

10 of resource elements occupied by the l^{th} control channel element among the L control channel elements comprised in the modulation symbols of the candidate E-PDCCH in the OFDM symbol; j_0 is a start position of the modulation symbols of the candidate E-PDCCH mapped in the OFDM symbol; N_l is the quantity of the resource elements in the set R_l ; and N_l , j_0 , l and q are integers.

15 11. The method according to claim 7 or 8, wherein the extracting modulation symbols of the candidate E-PDCCH sequentially from resource elements used to transmit the candidate E-PDCCH in each OFDM symbol comprises:

extracting, by the UE according to an order of subcarriers in each OFDM symbol, the modulation symbols of the candidate E-PDCCH from resource elements occupied by L
20 control channel elements allocated to the candidate E-PDCCH.

12. The method according to claim 11, wherein the extracting the modulation symbols of the candidate E-PDCCH from resource elements occupied by L control channel elements allocated to the candidate E-PDCCH comprises:

extracting modulation symbols of the candidate E-PDCCH and with index numbers of

25 $j_0 + [0, \dots, N - 1]$ from resource elements of a set R, wherein j_0 is a start position of the modulation symbols of the candidate E-PDCCH mapped in the OFDM symbol; the set R is a set of resource elements occupied by the L control channel elements comprised in the

modulation symbols of the candidate E-PDCCH in the OFDM symbol; N is the quantity of the resource elements in the set R ; and N and j_0 are integers

13. A method for transmitting a downlink control signal, comprising:

determining, by a base station, a reference signal port according to an aggregation level
5 of a physical downlink control channel E-PDCCH of a user equipment UE, wherein E-PDCCHs at different aggregation levels correspond to different reference signal ports, and the aggregation level indicates the quantity of control channel elements comprised in the E-PDCCH; and

10 sending, by the base station, the E-PDCCH to the UE in a subframe, and sending a reference signal of the E-PDCCH to the UE by using the determined reference signal port.

14. The method according to claim 13, wherein:

the E-PDCCH and a physical downlink shared channel PDSCH invoked by the E-PDCCH are frequency-division multiplexed.

15 15. The method according to claim 13 or 14, wherein an E-PDCCH at aggregation level $L = 2^{m-1}$ corresponds to a reference signal port with a port number $7 + (m + \sigma) \bmod P$, wherein σ is 0 or a UE-specific parameter or a cell-specific parameter; P is the quantity of available reference signal ports for the E-PDCCH, and $P = 4$; and $m = 1, 2, 3, 4$.

16. The method according to claim 13 or 14, wherein that E-PDCCHs at different aggregation levels correspond to different reference signal ports comprises:

20 that E-PDCCHs at a same start position but different aggregation levels in the subframe correspond to different reference signal ports.

17. The method according to claim 16, further comprising: configuring, by the base station, correspondence between control channel elements in the subframe and the reference signal ports, so that, according to the correspondence between control channel elements in the
25 subframe and the reference signal ports, enabling E-PDCCHs at a same start position but different aggregation levels in the subframe correspond to different reference signal ports.

18. The method according to claim 16 or 17, wherein the at a same start position in the subframe comprises:

at a same start position in a same physical resource block pair or different physical

resource block pairs.

19. The method according to claim 17, wherein the correspondence between control channel elements in the subframe and the reference signal ports comprises: the i^{th} control channel element in the subframe corresponds to a reference signal port $7 + (i + \sigma) \bmod P$,

5 wherein i is an index of the control channel element in the subframe, σ is 0 or a UE-specific parameter or a cell-specific parameter, and P is the quantity of available reference signal ports, and $P = 4$, and i is an integer; and

the sending a reference signal of the E-PDCCH to the UE by using the determined reference signal port comprises:

10 sending, by the base station, a reference signal of the E-PDCCH at aggregation level $L = 2^{m-1}$ by using a reference signal port corresponding to the m^{th} control channel element in the E-PDCCH at aggregation level $L = 2^{m-1}$, wherein $m = 1, 2, 3, 4$.

20. The method according to any one of claims 13 to 19, wherein that E-PDCCHs at different aggregation levels correspond to different reference signal ports comprises:

15 that E-PDCCHs at different aggregation levels, among a part or all of aggregation levels corresponding to E-PDCCHs of the UE, correspond to different reference signal ports.

21. The method according to any one of claims 13 to 20, wherein the determining, by a base station, a reference signal port according to an aggregation level of a physical downlink control channel E-PDCCH of a user equipment UE, wherein E-PDCCHs at different aggregation levels correspond to different reference signal ports, is specifically:

20 selecting, by the base station according to the aggregation level of the physical downlink control channel E-PDCCH of the user equipment UE, one or more reference signal ports from a reference signal port set corresponding to the aggregation level as a reference signal port corresponding to the aggregation level, wherein reference signal ports selected for
25 E-PDCCHs at different aggregation levels are different.

22. The method according to any one of claims 13 to 21, wherein E-PDCCHs, corresponding to different user equipments UEs, at a same aggregation level, and occupying a same physical resource, correspond to different reference signal ports.

23. A method for transmitting a downlink control signal, comprising:

receiving, by a user equipment UE from a reference signal port in a subframe, a reference signal sent by a base station of a candidate physical downlink control channel E-PDCCH, wherein candidate E-PDCCHs at different aggregation levels correspond to different reference signal ports, and the aggregation level indicates the quantity of control channel elements comprised in the candidate E-PDCCH; and

performing, by the UE, channel estimation according to the reference signal, so as to demodulate the candidate E-PDCCH.

24. The method according to claim 23, wherein:

the candidate E-PDCCH and a physical downlink shared channel PDSCH invoked by the candidate E-PDCCH are frequency-division multiplexed.

25. The method according to claim 23 or 24, wherein an E-PDCCH at aggregation level $L = 2^{m-1}$ corresponds to a reference signal port with a port number $7 + (m + \sigma) \bmod P$, wherein $m = 1, 2, 3, 4$; σ is 0 or a UE-specific parameter or a cell-specific parameter; and P is the quantity of available reference signal ports for the E-PDCCH, and $P = 4$.

26. The method according to claim 23 or 24, further comprising: configuring, by the UE, correspondence between control channel elements in the subframe and the reference signal ports.

27. The method according to any one of claims 23, 24 and 26, wherein that candidate E-PDCCHs at different aggregation levels correspond to different reference signal ports is specifically: selecting, by the UE, according to the aggregation level of the candidate E-PDCCH of the UE, one or more reference signal ports from a reference signal port set corresponding to the aggregation level as a reference signal port corresponding to the aggregation level, wherein candidate E-PDCCHs at different aggregation levels correspond to different reference signal ports.

28. The method according to any one of claims 23 to 27, wherein that candidate E-PDCCHs at different aggregation levels correspond to different reference signal ports comprises:

that candidate E-PDCCHs at a same start position but different aggregation levels in the subframe correspond to different reference signal ports.

29. The method according to claim 26, wherein the correspondence between control channel elements in the subframe and the reference signal ports comprises: the i^{th} control channel element in the subframe corresponds to a reference signal port, $7 + (i + \sigma) \bmod P$, wherein i is an index of the control channel element in the subframe, σ is 0 or a
5 UE-specific parameter or a cell-specific parameter, and P is the quantity of available reference signal ports, and $P = 4$, and i is an integer; and

the receiving, by the user equipment UE from a reference signal port in a subframe, a reference signal of a candidate E-PDCCH sent by a base station comprises:

receiving, by the UE, a reference signal of a candidate E-PDCCH at aggregation level
10 $L = 2^{m-1}$ from a reference signal port corresponding to the m^{th} control channel element in the candidate E-PDCCH at aggregation level $L = 2^{m-1}$, wherein $m = 1, 2, 3, 4$.

30. The method according to any one of claims 23 to 29, wherein that candidate E-PDCCHs at different aggregation levels correspond to different reference signal ports comprises:

15 that candidate E-PDCCHs at different aggregation levels, among a part or all of aggregation levels corresponding to candidate E-PDCCHs of the UE, correspond to different reference signal ports.

31. A method for transmitting a downlink control signal, comprising:

sending, by a base station, a reference signal of a physical downlink control channel
20 E-PDCCH by using a first reference signal port v ;

sending, by the base station, a reference signal of a physical downlink shared channel PDSCH by using at least one second reference signal port; and

determining, by the base station, not to use a second reference signal port $p(v)$ to send
the reference signal of the PDSCH, so that a reference signal port of the E-PDCCH and a
25 reference signal port of the PDSCH are processed based on orthogonal time extensions with different lengths, wherein the first reference signal port is one of the at least one second reference signal port, and v and $p(v)$ are serial numbers of the reference signal ports.

32. The method according to claim 31, wherein:

the E-PDCCH and the PDSCH are frequency-division multiplexed.

33. The method according to claim 31 or 32, wherein the at least one second reference signal port comprises at least one of PDSCH reference signal ports 7, 8, 9, 10, 11, 12, 13 and 14 defined in LTE release 10, the first reference signal port v comprises an E-PDCCH

5 reference signal port 7, 8, 9, or 10 defined in LTE release 10, and
$$p(v) = \begin{cases} 11, v = 7 \\ 13, v = 8 \\ 12, v = 9 \\ 14, v = 10 \end{cases}.$$

34. The method according to claim 33, wherein, when a rank R of the PDSCH is less than or equal to 4, the base station sends the reference signal of the PDSCH by using R reference signal ports starting from the reference signal port v ; and

10 when the rank of the PDSCH is one of 5, 6 and 7, the base station sends the reference signal of the PDSCH by using R reference signal ports starting from the reference signal port v , and when needing to send the reference signal of the PDSCH by using the second reference signal port $p(v)$, replaces the reference signal port $p(v)$ with another available reference signal port among the PDSCH reference signal ports, wherein R is an integer.

15 35. The method according to claim 33, wherein, when a rank R of the PDSCH is less than or equal to 4, the base station sends the reference signal of the PDSCH by using R reference signal ports $7 + (v - 7 + r) \bmod 4$ starting from the reference signal port v , wherein $r = 0, \dots, R - 1$, and R is an integer; and

20 when the rank R of the PDSCH is equal to one of 5, 6 and 7, the base station sends the reference signal of the PDSCH by using R reference signal ports $7 + (v - 7 + r) \bmod 8$ starting from the reference signal port v , and when the R reference signal ports comprise the reference signal port $p(v)$, replaces the reference signal port $p(v)$ with another reference signal port among the PDSCH reference signal ports, wherein $r = 0, \dots, R - 1$.

36. The method according to claim 33, wherein:

25 when a rank R of the PDSCH is equal to 3 or 4, the base station sends the reference signal of the PDSCH by using R reference signal ports $7 + (v - 7 + r) \bmod 4$ starting from

the reference signal port v ; and when the rank R of the PDSCH is equal to 2, the base station sends the reference signal of the PDSCH by using reference signal ports v and $v + (-1)^{(v-7) \bmod 2}$, wherein R is an integer.

37. A method for transmitting a signal, comprising:

5 receiving, by a UE, a reference signal of a physical downlink control channel E-PDCCH which is sent by a base station by using a first reference signal port v and a reference signal of a physical downlink shared channel PDSCH which is sent by the base station by using at least one second reference signal port, wherein the PDSCH is invoked by the E-PDCCH;

performing, by the UE, channel estimation by using the reference signal, so as to
10 demodulate the E-PDCCH, and performing channel estimation by using the reference signal of the PDSCH, so as to demodulate the PDSCH; and

determining, by the UE, not to use a reference signal of the PDSCH sent by a second reference signal port $p(v)$ to perform channel estimation, so that a reference signal port of the E-PDCCH and a reference signal port of the PDSCH are processed based on orthogonal
15 time extensions with different lengths, wherein the first reference signal port is one of the at least one second reference signal port, and v and $p(v)$ are serial numbers of the reference signal ports.

38. The method according to claim 37, wherein:

the E-PDCCH and the PDSCH are frequency-division multiplexed.

20 39. The method according to claim 37 or 38, wherein the at least one second reference signal port comprises at least one of PDSCH reference signal ports 7, 8, 9, 10, 11, 12, 13 and 14 defined in LTE release 10, the first reference signal port comprises an E-PDCCH reference

signal port 7, 8, 9, or 10 defined in LTE release 10, and $p(v) = \begin{cases} 11, v = 7 \\ 13, v = 8 \\ 12, v = 9 \\ 14, v = 10 \end{cases}$.

40. The method according to claim 39, wherein, when a rank R of the PDSCH is less
25 than or equal to 4, the UE performs channel estimation by using a reference signal of the PDSCH sent by a PDSCH reference signal port defined in LTE release 10; and

when the rank of the PDSCH is one of 5, 6 and 7, the UE performs channel estimation by using a reference signal of the PDSCH sent by a PDSCH reference signal port defined in LTE release 10, and when needing to perform channel estimation by using the reference signal of the PDSCH sent by the second reference signal port $p(v)$, replaces the reference signal port $p(v)$ with another available reference signal port among the PDSCH reference signal ports to perform channel estimation.

41. The method according to claim 39, wherein, when a rank R of the PDSCH is less than or equal to 4, the UE performs channel estimation by using a reference signal of the PDSCH sent by a PDSCH reference signal port $7 + (v - 7 + r) \bmod 4$ defined in LTE release

10, wherein $r = 0, \dots, R - 1$, and R is an integer; and

when the rank R of the PDSCH is equal to one of 5, 6 and 7, the UE performs channel estimation by using reference signals of the PDSCH sent by R reference signal ports $7 + (v - 7 + r) \bmod 8$ starting from the reference signal port, and when the R reference signal ports comprise the reference signal port $p(v)$, replaces the reference signal port $p(v)$ with another reference signal port among the PDSCH reference signal ports to perform channel estimation, wherein $r = 0, \dots, R - 1$.

42. The method according to claim 39, wherein:

when a rank R of the PDSCH is equal to 3 or 4, UE performs channel estimation by using reference signals of the PDSCH sent by R reference signal ports $7 + (v - 7 + r) \bmod 4$

starting from the reference signal port v , wherein $r = 0, \dots, R - 1$; and

when the rank of the PDSCH is equal to 2, the UE performs channel estimation by using reference signals of the PDSCH sent by reference signal ports v and $v + (-1)^{(v-7) \bmod 2}$.

43. A base station, comprising:

a mapping unit, configured to map, according to an order of orthogonal frequency division multiplexing OFDM symbols used by a physical downlink control channel E-PDCCH of a user equipment UE, the E-PDCCH sequentially to resource elements used to

transmit the E-PDCCH in each OFDM symbol; and

a sending unit, configured to send the E-PDCCH to the UE by using the resource elements.

44. The base station according to claim 43, wherein:

5 the E-PDCCH and a physical downlink shared channel PDSCH invoked by the E-PDCCH are frequency-division multiplexed.

45. The base station according to claim 43 or 44, wherein the mapping unit maps, according to an order of L control channel elements allocated to the E-PDCCH in each OFDM symbol, the E-PDCCH sequentially to resource elements occupied by the L control
10 channel elements in the OFDM symbol, wherein L is an integer.

46. The base station according to claim 43 or 44, wherein the mapping unit maps, according to an order of subcarriers in each OFDM symbol, the E-PDCCH sequentially to resource elements occupied by L control channel elements allocated to the E-PDCCH.

47. A user equipment, comprising:

15 a receiving unit, configured to receive a downlink subframe from a base station; and
an extracting unit, configured to sequentially extract, in a blind detection process according to an order of orthogonal frequency division multiplexing OFDM symbols used by a candidate physical downlink control channel E-PDCCH in the downlink subframe, modulation symbols of the candidate E-PDCCH from resource elements used to transmit the
20 candidate E-PDCCH in each OFDM symbol, and perform decoding and cyclic redundancy check CRC on the candidate E-PDCCH.

48. The user equipment according to claim 47, wherein the E-PDCCH of the user equipment and a physical downlink shared channel PDSCH invoked by the E-PDCCH of the user equipment are frequency-division multiplexed.

25 49. The user equipment according to claim 47 or 48, wherein the extracting unit extracts, according to an order of L control channel elements allocated to the candidate E-PDCCH in each OFDM symbol, the candidate E-PDCCH sequentially to resource elements occupied by the L control channel elements in the OFDM symbol, wherein L is an integer.

50. The user equipment according to claim 47 or 48, wherein the extracting unit extracts,
30 according to an order of subcarriers in each OFDM symbol, the modulation symbols of the

candidate E-PDCCH from resource elements occupied by L control channel elements allocated to the candidate E-PDCCH.

51. A base station, comprising:

a determining unit, configured to determine a reference signal port according to an aggregation level of a physical downlink control channel E-PDCCH of a user equipment UE, wherein E-PDCCHs at different aggregation levels correspond to different reference signal ports, and the aggregation level indicates the quantity of control channel elements comprised in the E-PDCCH; and

a sending unit, configured to send the E-PDCCH to the UE in a subframe, and send a reference signal of the E-PDCCH to the UE by using the determined reference signal port.

52. The base station according to claim 51, wherein the E-PDCCH and a physical downlink shared channel PDSCH invoked by the E-PDCCH are frequency-division multiplexed.

53. The base station according to claim 51 or 52, wherein E-PDCCHs at a same start position but different aggregation levels in the subframe correspond to different reference signal ports.

54. The base station according to any one of claims 51 to 53, wherein the determining unit is specifically configured to select, according to the aggregation level of the physical downlink control channel E-PDCCH of the user equipment UE, one or more reference signal ports from a reference signal port set corresponding to the aggregation level as a reference signal port corresponding to the aggregation level, wherein reference signal ports selected for E-PDCCHs at different aggregation levels are different.

55. The base station according to any one of claims 51 to 54, wherein E-PDCCHs, corresponding to different user equipments UEs, at a same aggregation level, and occupying a same physical resource, correspond to different reference signal ports.

56. A user equipment, comprising:

a receiving unit, configured to receive, from a reference signal port in a subframe, a reference signal of a candidate physical downlink control channel E-PDCCH sent by a base station, wherein candidate E-PDCCHs at different aggregation levels correspond to different reference signal ports, and the aggregation level indicates the quantity of control channel

elements comprised in the candidate E-PDCCH; and

a demodulating unit, configured to perform channel estimation according to the reference signal, so as to demodulate the candidate E-PDCCH.

57. The user equipment according to claim 56, wherein the candidate E-PDCCH and a physical downlink shared channel PDSCH invoked by the candidate E-PDCCH are frequency-division multiplexed.

58. The user equipment according to claim 56 or 57, wherein candidate E-PDCCHs at a same start position but different aggregation levels in the subframe correspond to different reference signal ports.

59. A base station, comprising:

a sending unit, configured to send a reference signal of a physical downlink control channel E-PDCCH by using a first reference signal port v , and send a reference signal of a physical downlink shared channel PDSCH by using at least one second reference signal port; and

a determining unit, configured to determine not to use a second reference signal port $p(v)$ to send the reference signal of the PDSCH, so that a reference signal port of the E-PDCCH and a reference signal port of the PDSCH are processed based on orthogonal time extensions with different lengths, wherein the first reference signal port is one of the at least one second reference signal port, and v and $p(v)$ are serial numbers of the reference signal ports.

60. The base station according to claim 59, wherein the E-PDCCH and the PDSCH are frequency-division multiplexed.

61. The base station according to claim 59 or 60, wherein the at least one second reference signal port comprises at least one of PDSCH reference signal ports 7, 8, 9, 10, 11, 12, 13 and 14 defined in LTE release 10, the first reference signal port comprises an E-PDCCH reference signal port 7, 8, 9, or 10 defined in LTE release 10, and

$$p(v) = \begin{cases} 11, v = 7 \\ 13, v = 8 \\ 12, v = 9 \\ 14, v = 10 \end{cases}.$$

62. The base station according to claim 61, wherein the sending unit is specifically configured to: when a rank R of the PDSCH is less than or equal to 4, send the reference signal of the PDSCH by using a PDSCH reference signal port defined in LTE release 10; and

the sending unit is further configured to: when the rank R of the PDSCH is one of 5, 6 and 7, send the reference signal of the PDSCH by using a PDSCH reference signal port defined in LTE release 10, and when needing to send the reference signal of the PDSCH by using the second reference signal port $p(v)$, the sending unit replaces the reference signal port $p(v)$ with another available reference signal port among the PDSCH reference signal ports, wherein R is an integer.

63. The base station according to claim 61, wherein the sending unit is specifically configured to: when a rank R of the PDSCH is less than or equal to 4, send the reference signal of the PDSCH by using R reference signal ports $7 + (v - 7 + r) \bmod 4$ starting from the reference signal port v , wherein $r = 0, \dots, R - 1$, and R is an integer; and

the sending unit is further configured to: when the rank R of the PDSCH is equal to one of 5, 6 and 7, send the reference signal of the PDSCH by using R reference signal ports $7 + (v - 7 + r) \bmod 8$ starting from the reference signal port v , and when the R reference signal ports comprise the reference signal port $p(v)$, replace the reference signal port $p(v)$ with another reference signal port among the PDSCH reference signal ports, wherein $r = 0, \dots, R - 1$.

64. A user equipment, comprising:

a receiving unit, configured to receive a reference signal of a physical downlink control channel E-PDCCH which is sent by a base station by using a first reference signal port v and a reference signal of a physical downlink shared channel PDSCH which is sent by the base station by using at least one second reference signal port, wherein the PDSCH is invoked by the E-PDCCH;

a demodulating unit, configured to perform channel estimation by using the reference signal of the E-PDCCH, so as to demodulate the E-PDCCH, and perform channel estimation

by using the reference signal of the PDSCH, so as to demodulate the PDSCH; and

a determining unit, configured to determine not to use a reference signal of the PDSCH sent by a second reference signal port $p(v)$ to perform channel estimation, so that a reference signal port of the E-PDCCH and a reference signal port of the PDSCH are processed based on orthogonal time extensions with different lengths, wherein the first reference signal port is one of the at least one second reference signal port, and v and $p(v)$ are serial numbers of the reference signal ports.

65. The user equipment according to claim 64, wherein the E-PDCCH and the PDSCH are frequency-division multiplexed.

66. The user equipment according to claim 64 or 65, wherein the at least one second reference signal port comprises at least one of PDSCH reference signal ports 7, 8, 9, 10, 11, 12, 13 and 14 defined in LTE release 10, the first reference signal port comprises an E-PDCCH reference signal port 7, 8, 9, or 10 defined in LTE release 10, and

$$p(v) = \begin{cases} 11, v = 7 \\ 13, v = 8 \\ 12, v = 9 \\ 14, v = 10 \end{cases}.$$

67. The user equipment according to claim 66, wherein the demodulating unit is specifically configured to: when a rank R of the PDSCH is less than or equal to 4, perform channel estimation by using a reference signal of the PDSCH sent by a PDSCH reference signal port defined in LTE release 10; and

the demodulating unit is further configured to: when the rank R of the PDSCH is one of 5, 6 and 7, perform channel estimation by using a reference signal of the PDSCH sent by a PDSCH reference signal port defined in LTE release 10, and when the UE needs to perform channel estimation by using a reference signal of the PDSCH sent by the second reference signal port $p(v)$, replace the reference signal port $p(v)$ with another available reference signal port among the PDSCH reference signal ports to perform channel estimation,

wherein R is an integer.

68. The user equipment according to claim 66, wherein the demodulating unit is

specifically configured to: when a rank R of the PDSCH is less than or equal to 4, perform channel estimation by using reference signals of the PDSCH sent by R reference signal ports $7 + (v - 7 + r) \bmod 4$ starting from the reference signal port v , wherein $r = 0, \dots, R - 1$, and R is an integer; and

- 5 the demodulating unit is further configured to: when the rank R of the PDSCH is equal to one of 5, 6 and 7, perform channel estimation by using reference signals of the PDSCH sent by R reference signal ports $7 + (v - 7 + r) \bmod 8$ starting from the reference signal port v , and when the R reference signal ports comprise the reference signal port $p(v)$, replace the reference signal port $p(v)$ with another reference signal port among the PDSCH
- 10 reference signal ports to perform channel estimation, wherein $r = 0, \dots, R - 1$.