

[0001] HYBRID ORTHOGONAL FREQUENCY DIVISION
MULTIPLE ACCESS SYSTEM AND METHOD

[0002] FIELD OF INVENTION

[0003] The present invention is related to wireless communication systems. More particularly, the present invention is related to a hybrid orthogonal frequency division multiple access (OFDMA) system and method.

[0004] BACKGROUND

[0005] It is expected that future wireless communication systems will provide broadband services such as wireless Internet access to subscribers. Such broadband services require reliable and high throughput transmissions over a wireless channel which is time dispersive and frequency selective. The wireless channel is subject to limited spectrum and inter-symbol interference (ISI) caused by multipath fading. Orthogonal frequency division multiplexing (OFDM) and OFDMA are some of the most promising solutions for the next generation wireless communication systems.

[0006] OFDM has a high spectral efficiency since the subcarriers used in the OFDM system overlap in frequency and an adaptive modulation and coding scheme (MCS) may be employed across subcarriers. In addition, implementation of the OFDM is very simple because the baseband modulation and demodulation are performed by simple inverse fast Fourier transform (IFFT) and fast Fourier transform (FFT) operations. Other advantages of the OFDM system include a simplified receiver structure and excellent robustness in a multipath environment.

[0007] OFDM and OFDMA have been adopted by several wireless/wired communication standards, such as digital audio broadcast (DAB), digital audio broadcast terrestrial (DAB-T), IEEE 802.11a/g, IEEE 802.16, asymmetric digital subscriber line (ADSL) and is being considered for adoption in third generation partnership project (3GPP) long term evolution (LTE), cdma2000 evolution, a fourth generation (4G) wireless communication system, IEEE 802.11n, or the like.

[0008] One key problem with OFDM and OFDMA is that it is difficult to mitigate or control inter-cell interference to achieve a frequency reuse factor of one. Frequency hopping and subcarrier allocation cooperation between cells have been proposed to mitigate inter-cell interference. However, the effectiveness of both methods is limited.

[0009] SUMMARY

[0010] The present invention is related to a hybrid OFDMA system and method. The system includes a transmitter and a receiver. The transmitter includes a first spread OFDMA subassembly, a first non-spread OFDMA subassembly and a first common subassembly. The first spread OFDMA subassembly spreads input data and maps the spread data to a first group of subcarriers. The first non-spread OFDMA subassembly maps input data to a second group of subcarriers. The first common subassembly transmits the input data mapped to the first group of subcarriers and the second group of subcarriers using OFDMA. The receiver includes a second spread OFDMA subassembly, a second non-spread OFDMA subassembly and a second common subassembly. The second common subassembly of the receiver processes received data to recover data mapped to the subcarriers using OFDMA. The second spread OFDMA subassembly recovers the first input data by separating user data in a code domain and the second non-spread OFDMA subassembly recovers the second input data.

[0011] BRIEF DESCRIPTION OF THE DRAWINGS

[0012] Figure 1 is a block diagram of an exemplary hybrid OFDMA system configured in accordance with the present invention.

[0013] Figure 2 shows an example of frequency domain spreading and subcarrier mapping in accordance with the present invention.

[0014] Figure 3 shows another example of spreading and subcarrier mapping in accordance with the present invention.

[0015] Figure 4 shows an example of time-frequency hopping of subcarriers in accordance with the present invention.

[0016] Figure 5 is a block diagram of an exemplary time-frequency Rake combiner configured in accordance with the present invention.

[0017] DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

[0018] Hereafter, the terminology "transmitter" and "receiver" includes but are not limited to a user equipment (UE), a wireless transmit/receive unit (WTRU), a mobile station, a fixed or mobile subscriber unit, a pager, a Node-B, a base station, a site controller, an access point or any other type of device capable of operating in a wireless environment.

[0019] The features of the present invention may be incorporated into an integrated circuit (IC) or be configured in a circuit comprising a multitude of interconnecting components.

[0020] The present invention is applicable to any wireless communication system that utilizes OFDMA (or OFDM) and/or code division multiple access (CDMA), such as IEEE 802.11, IEEE 802.16, third generation (3G) cellular systems, 4G systems, satellite communication systems, or the like.

[0021] Figure 1 is a block diagram of an exemplary hybrid OFDMA system 10 including a transmitter 100 and a receiver 200 in accordance with the present invention. The transmitter 100 includes a spread OFDMA subassembly 130, a non-spread OFDMA subassembly 140 and a common subassembly 150. In the spread OFDMA subassembly 130, input data 101 (for one or more users) is spread with a spreading code to generate a plurality of chips 103 and the chips 103 are then mapped to subcarriers. In the non-spread OFDMA subassembly 140, input bit 111 (for one or more different users) is mapped to subcarriers without spreading.

[0022] The spread OFDMA subassembly 130 includes a spreader 102 and a first subcarrier mapping unit 104. The non-spread OFDMA subassembly 140 includes a serial-to-parallel (S/P) converter 112 and a second subcarrier mapping unit 114. The common subassembly 150 includes an N-point inverse discrete

Fourier transform (IDFT) processor 122, a parallel-to-serial (P/S) converter 124 and a cyclic prefix (CP) insertion unit 126.

[0023] Assuming that there are N subcarriers in the system and that K different users communicate at the same time in the system, among K users, data to K_s users is transmitted via the spread OFDMA subassembly 130. The number of subcarriers used in the spread OFDMA subassembly 130 and the non-spread OFDMA subassembly 140 are N_s and N_o , respectively. The values of N_s and N_o satisfy the conditions that $0 \leq N_s \leq N$, $0 \leq N_o \leq N$, and $N_s + N_o \leq N$.

[0024] The input data 101 is spread by the spreader 102 to a plurality of chips 103. The chips 103 are mapped to the N_s subcarriers by the subcarrier mapping unit 104. The spreading may be performed in the time domain, in the frequency domain, or both. For a particular user, spreading factors in the time domain and the frequency domain are denoted by SF_t and SF_f , respectively. A joint spreading factor for the user is denoted by SF_{joint} , which equals to $SF_t \times SF_f$. When $SF_t=1$, the spreading is performed only in the frequency domain, and when $SF_f=1$, the spreading is performed one in the time domain. A frequency domain spreading for user i is limited to the number of subcarriers allocated to the user i , $N_s(i)$. The allocation of subcarriers can be static or dynamic. In the case where $N_s(i) = N_s$ for every user i , the spread OFDMA becomes spread OFDM.

[0025] One subcarrier may be mapped to more than one user in the spread OFDMA subassembly 130. In such case input data 101 of two or more users mapped to the same subcarrier are code multiplexed, and therefore, should be spread using different spreading codes. If spreading is performed both in the time and frequency domain, spreading codes assigned to users may be different in the time domain, in the frequency domain, or both.

[0026] Figure 2 shows an example of frequency domain spreading and subcarrier mapping in accordance with the present invention. The input data 101 is multiplied with a spreading code 204 by a multiplier 202 to generate a

plurality of chips 103'. The chips 103' are converted to parallel chips 103 by an S/P converter 206. Each of the parallel chips 103 is then mapped to one of the subcarriers by the subcarrier mapping unit 104 before being sent to the IDFT processor 122.

[0027] Figure 3 shows another example of frequency domain spreading and subcarrier mapping in accordance with the present invention. Instead of multiplying a spreading code by a spreader, a repeater 302 may be used to repeat each input data 101 multiple times at the chip rate to generate chips 103'. The chips 103' are then converted to parallel chips 103 by an S/P converter 304. Each of the parallel chips 103 is mapped to one of the subcarriers by the subcarrier mapping unit 104 before being sent to the IDFT processor 122.

[0028] Alternatively, when input data is spread in the time domain, each input data is spread by a spreader to generate a plurality of chip streams and the chip streams are mapped to subcarriers. In such case, the time domain spreading may also be performed by simple repetition of the input data without using a spreading code.

[0029] Common pilots may be transmitted on the subcarriers used in the spread OFDMA subassembly 130. In order to distinguish from other user data, common pilots are also spread.

[0030] Referring again to Figure 1, in the non-spread OFDMA subassembly 140, input bits 111 of different users are converted to parallel bits 113 by the S/P converter 112. The subcarrier mapping unit 114 allocates users to one or more subcarriers, such that each subcarrier is used by at most one user and bits from each user are mapped to the allocated subcarriers for the user by the subcarrier mapping unit. In this way, users are multiplexed in the frequency domain. The number of subcarriers allocated to user i is denoted by $N_o(i)$, $0 \leq N_o(i) \leq N_o$. The allocation of subcarriers can be static or dynamic.

[0031] In accordance with the present invention, time-frequency hopping may be performed for the non-spread OFDMA subassembly 140 in a pseudo-random way in each cell. With time domain hopping, the users that transmit in a cell change from time to time, (i.e., over one or several OFDM symbols or

frames). With frequency domain hopping, subcarriers allocated to users that transmit in a cell are hopping per one or several OFDM symbols or frames. In this way, the inter-cell interference can be mitigated and averaged among the users and cells.

[0032] Figure 4 illustrates an example of time-frequency hopping where ten (10) subcarriers, s0-s9, are used for time periods of T0-T6 in accordance with the present invention. As an example, in Figure 2, subcarriers s3, s5, s8 are used for spread OFDMA and the remaining subcarriers are used for non-spread OFDMA. For the subcarriers allocated for non-spread OFDMA, subcarriers and time periods allocated to users are hopping in a pseudo-random way. For example, data for user 1 is transmitted via s9 at T0, s7 at T1, s7 at T3, and s1 and s9 at T4, and data for user 2 is transmitted via s4 at T0, s7 at T1, s3 at T2, s 0 and s4 at T5. Therefore, data to different users is transmitted over different OFDM symbols or frames and inter-cell interference is mitigated.

[0033] Referring again to Figure 1, both the chips 105 and the data 115 are fed into the IDFT processor 122. The IDFT processor 122 converts the chips 105 and data 115 to time domain data 123. The IDFT may be implemented by IFFT or an equivalent operation. The time domain data 123 is then converted to a serial data 125 by the P/S converter 124. A CP, (also known as a guard period (GP)), is then added to the serial data 125 by the CP insertion unit 126. Data 127 is then transmitted via the wireless channel 160.

[0034] The receiver 200 includes a spread OFDMA subassembly 230, a non-spread OFDMA subassembly 240 and a common subassembly 250 for hybrid OFDMA. The common subassembly 250 includes a CP removal unit 202, a P/S converter 204, an N-point discrete Fourier transform (DFT) processor 206, an equalizer 208 and a subcarrier demapping unit 210. The spread OFDMA subassembly 230 includes a code domain user separation unit 214 and the non-spread OFDMA subassembly 240 includes a P/S converter 216.

[0035] The receiver 200 receives data 201 transmitted via the channel. A CP is removed from received data 201 by the CP removal unit 202. Data 203 after the CP is removed, which is time domain data, is converted to parallel data

205 by the S/P converter 204. The parallel data 205 is fed to the DFT processor 206 and converted to frequency domain data 207, which means N parallel data on N subcarriers. The DFT may be implemented by FFT or equivalent operation. The frequency domain data 207 is fed to the equalizer 208 and equalization is performed to data at each subcarrier. As in a conventional OFDM system, a simple one-tap equalizer may be used.

[0036] After equalization at each subcarrier, data corresponding to a particular user is separated by the subcarrier demapping unit 210, which is an opposite operation performed by the subcarrier mapping units 104, 114 at the transmitter 100. In the non-spread OFDMA subassembly 240, each user data 211 is simply converted to a serial data 217 by the S/P converter 216. In the spread OFDMA subassembly 230, data 212 on the separated subcarriers are further processed by the code domain user separation unit 214. Depending on the way spreading is performed at the transmitter 100 corresponding user separation is performed in the code domain user separation unit 214. For example, if the spreading is performed only in the time domain at the transmitter 100, a conventional Rake combiner may be used as the code domain user separation unit 214. If the spreading is performed only in the frequency domain at the transmitter 100, a conventional (frequency domain) despreader may be used as the code domain user separation unit 214. If the spreading is performed in both the time domain and the frequency domain at the transmitter 100, a time-frequency Rake combiner may be used as the code domain user separation unit 214.

[0037] Figure 5 is a block diagram of an exemplary time-frequency Rake combiner 500 configured in accordance with the present invention. The time-frequency Rake combiner 500 performs processing at both time and frequency domains in order to recover data that is spread in both time and frequency domains at the transmitter 100. It should be noted that the time-frequency Rake combiners 500 may be implemented in many different ways and the configuration shown in Figure 5 is provided as an example, not as a limitation, and the scope of the present invention is not limited to the structure shown in

Figure 5.

[0038] The time-frequency Rake combiner 500 comprises a despreader 502 and a Rake combiner 504. Data 212 separated and collected for a particular user by the subcarrier demapping unit 210 in Figure 1 for the spread OFDMA subassembly 230 is forwarded to the despreader 502. The despreader 502 performs frequency-domain despreading to the data 212 on the subcarriers. The despreader 502 includes a plurality of multipliers 506 for multiplying conjugate 508 of the spreading codes to the data 212, a summer 512 for summing the multiplication outputs 510, and a normalizer 516 for normalizing the summed output 514. The despreader output 518 is then processed by the Rake combiner 504 to recover the data of the user by time domain combining.

[0039] The transmitter 100, the receiver 200, or both may include multiple antennas and may implement hybrid OFDMA in accordance with the present invention with multiple antennas either at transmitter side, the receiver side, or both.

[0040] Embodiments.

[0041] 1. A hybrid orthogonal frequency division multiple access (OFDMA) system comprising a transmitter and a receiver. The transmitter comprises a first spread OFDMA subassembly for spreading first input data for a first group of users and mapping spread data to a first group of subcarriers; a first non-spread OFDMA subassembly for mapping second input data to a second group of subcarriers; and a first common subassembly for transmitting the first input data and the second input data mapped to the first group of subcarriers and the second group of subcarriers using OFDMA. The receiver comprises a second common subassembly for processing received data to recover data mapped to the subcarriers using OFDMA; a second spread OFDMA subassembly for recovering the first input data; and a second non-spread OFDMA subassembly for recovering the second input data.

[0042] 2. The system of embodiment 1 wherein the first spread OFDMA subassembly spreads the first input data in at least one of a time-domain and a frequency domain.

- [0043] 3. The system of embodiment 2 wherein the first spread OFDMA subassembly spreads the first input data by repeating the first input data at a chip rate.
- [0044] 4. The system as in any embodiments of 1-3, wherein the first spread OFDMA subassembly and the first non-spread OFDMA subassembly map the subcarriers dynamically.
- [0045] 5. The system as in any embodiments of 1-4, wherein the first spread OFDMA subassembly transmits common pilots on the first group of subcarriers.
- [0046] 6. The system as in any embodiments of 1-5, wherein the first non-spread OFDMA subassembly implements at least one of time-domain hopping and frequency-domain hopping in mapping the second input data to the second group of subcarriers.
- [0047] 7. The system as in any embodiments of 1-6, wherein the second OFDMA subassembly of the receiver comprises a Rake combiner.
- [0048] 8. The system as in any embodiments of 1-7, wherein the second OFDMA subassembly of the receiver comprises a time-frequency Rake combiner.
- [0049] 9. The system as in any embodiments of 1-8, wherein at least one of the transmitter and the receiver comprises multiple antennas.
- [0050] 10. A hybrid orthogonal frequency division multiple access (OFDMA) system comprising a transmitter and a receiver. The transmitter comprises a spreader for spreading first input data for a first group of users to generate chips; a first subcarrier mapping unit for mapping the chips to a first group of subcarriers; a first serial-to-parallel (S/P) converter for converting second input data for a second group of users to first parallel data; a second subcarrier mapping unit for mapping the first parallel data to a second group of subcarriers; an inverse discrete Fourier transform (IDFT) processor for performing IDFT on outputs of the first subcarrier mapping unit and the second subcarrier mapping unit to generate a time domain data; a first parallel-to-serial (P/S) converter for converting the time domain data to serial data; and a cyclic

prefix (CP) insertion unit for inserting a CP to the serial data for transmission. The receiver comprises a CP removal unit for removing a CP from received data; a second S/P converter for converting output of the CP removal unit to second parallel data; a discrete Fourier transform (DFT) processor for performing DFT on the second parallel data to generate frequency domain data; an equalizer for performing equalization on the frequency domain data; a subcarrier demapping unit for separating the frequency domain data after equalization for the first group of users and the second group of users; a code domain user separation unit for separating the frequency domain data after equalization for the first group of users in a code domain to recover the first data; and a second P/S converter for converting the frequency domain data after equalization for the second group of users to serial data to recover the second input data.

[0051] 11. The system of embodiment 10 wherein the spreader spreads the first input data in at least one of a time-domain and a frequency domain.

[0052] 12. The system of embodiment 11 wherein the spreader spreads the first input data by repeating the first input data at a chip rate.

[0053] 13. The system as in any embodiments of 10-12, wherein the first subcarrier mapping unit and the second subcarrier mapping unit map the subcarriers dynamically.

[0054] 14. The system as in any embodiments of 10-13, wherein the transmitter transmits common pilots on the first group of subcarriers.

[0055] 15. The system as in any embodiments of 10-14, wherein the second subcarrier mapping unit implements at least one of time-domain hopping and frequency-domain hopping in mapping the first parallel data to the second group of subcarriers.

[0056] 16. The system as in any embodiments of 10-15, wherein the code domain user separation unit comprises a Rake combiner.

[0057] 17. The system as in any embodiments of 10-16, wherein the code domain user separation unit comprises a time-frequency Rake combiner.

[0058] 18. The system as in any embodiments of 10-17, wherein at least one of the transmitter and the receiver comprises multiple antennas.

[0059] 19. A method for transmitting data using hybrid orthogonal frequency division multiple access (OFDMA), wherein, at a transmitter, first input data for a first group of users is spread to generate chips; the chips are mapped to a first group of subcarriers; second input data for a second group of users is converted to first parallel data; the first parallel data is mapped to a second group of subcarriers; an inverse discrete Fourier transform (IDFT) is performed on outputs of data mapped to the first group of subcarriers and the second group of subcarriers a time domain data; the time domain data is converted to serial data; a cyclic prefix (CP) is inserted to the serial data; and the CP inserted data is transmitted; and, at a receiver, data transmitted by the transmitter is received; a CP is removed from received data; the CP removed data is converted to second parallel data; a discrete Fourier transform (DFT) is performed on the second parallel data to generate frequency domain data; equalization is performed on the frequency domain data; the frequency domain data after equalization for the first group of users and the second group of users are separated; the data for the first group of users is separated in a code domain to recover the first data; and the data for the second group of users is converted to serial data to recover the second input data.

[0060] 20. The method of embodiment 19 wherein the spreading of the first input data is performed in at least one of a time-domain and a frequency domain.

[0061] 21. The method of embodiment 20 wherein the spreading of the first input data is performed by repeating the first input data at a chip rate.

[0062] 22. The method as in any embodiments of 19-21, wherein the first group of subcarriers and the second group of subcarriers are mapped dynamically.

[0063] 23. The method as in any embodiments of 19-22, wherein the transmitter transmits common pilots on the first group of subcarriers.

[0064] 24. The method as in any embodiments of 19-23, wherein at least one of time-domain hopping and frequency-domain hopping is performed in mapping the first parallel data to the second group of subcarriers.

[0065] 25. The method as in any embodiments of 19-24, wherein separating the data for the first group of users in a code domain is performed by a Rake combiner.

[0066] 26. The method as in any embodiments of 19-25, wherein separating the data for the first group of users in a code domain is performed by a time-frequency Rake combiner.

[0067] Although the features and elements of the present invention are described in the preferred embodiments in particular combinations, each feature or element can be used alone without the other features and elements of the preferred embodiments or in various combinations with or without other features and elements of the present invention.

CLAIMS:

1. A wireless transmit/receive unit (WTRU) comprising:
a receiver configured to receive in a first single symbol time interval a plurality of subcarriers;
wherein a first group of subcarriers from the plurality of subcarriers includes information for the WTRU combined with an orthogonal sequence; wherein the first group of subcarriers includes information for a plurality of WTRUs; wherein the information for each of the plurality of WTRUs is combined with an orthogonal sequence and the orthogonal sequence for each of the plurality of WTRUs is different; wherein a second group of subcarriers from the plurality of subcarriers includes information for the WTRU not combined with an orthogonal sequence;
wherein the receiver is further configured to recover the information for the WTRU from the first group of subcarriers and the receiver is further configured to recover the information for the WTRU from the second group of subcarriers; and
wherein a third group of subcarriers from the plurality of subcarriers in the first single symbol time interval includes information for another WTRU that is not combined with an orthogonal sequence.
2. The WTRU of claim 1 wherein the first group of subcarriers are not contiguous subcarriers.
3. The WTRU of claim 1 wherein the receiver is configured to recover the information from the first group of subcarriers using despreading.
4. The WTRU of claim 1 wherein the information in the first group of subcarriers is time repeated in a second single symbol time interval and the orthogonal sequence in the first single symbol time interval and the second single symbol time interval frequency spreads the information; wherein the receiver is further configured to recover the information using the time repeated information.
5. The WTRU of claim 1 wherein the first single symbol time interval includes pilot signals.
6. The WTRU of claim 5 wherein the WTRU uses the pilot signals to aid in recovering the information from the first and second groups of subcarriers.
7. A method comprising:
receiving by a wireless transmit/receive unit (WTRU) in a first single symbol time interval a plurality of subcarriers; wherein a first group of subcarriers from the plurality of subcarriers includes information for the WTRU combined with an orthogonal sequence; wherein the first group of subcarriers includes information for a plurality of WTRUs; wherein the information for each of the

plurality of WTRUs is combined with an orthogonal sequence and the orthogonal sequence for each of the plurality of WTRUs is different; wherein a second group of subcarriers from the plurality of subcarriers includes information for the WTRU not combined with an orthogonal sequence;

recovering by the WTRU the information for the WTRU from the first group of subcarriers;
recovering by the WTRU the information for the WTRU from the second group of subcarriers; and
wherein a third group of subcarriers from the plurality of subcarriers in the first single symbol time interval includes information for another WTRU that is not combined with an orthogonal sequence.

8. The method of claim 7 wherein the first group of subcarriers are not contiguous subcarriers.

9. The method of claim 7 wherein the information recovered from the first group of subcarriers is performed using despreading.

10. The method of claim 7 wherein the information in the first group of subcarriers is time repeated in a second single symbol time interval and the orthogonal sequence in the first single symbol time interval and the second single symbol time interval frequency spreads the information; wherein the recovering the information includes using the time repeated information.

11. The method of claim 7 wherein the first single symbol time interval includes pilot signals.

12. The method of claim 11 wherein the WTRU uses the pilot signals to aid in recovering the information from the first and second groups of subcarriers.

13. A wireless network device comprising:

a transmitter configured to transmit in a first single symbol time interval a plurality of subcarriers;
wherein a first group of subcarriers from the plurality of subcarriers includes information for a first wireless transmit/receive unit (WTRU) combined with an orthogonal sequence; wherein the first group of subcarriers includes information for a plurality of WTRUs; wherein the information for each of the plurality of WTRUs is combined with an orthogonal sequence and the orthogonal sequence for each of the plurality of WTRUs is different; wherein a second group of subcarriers from the plurality of subcarriers includes information for the first WTRU not combined with an orthogonal sequence; wherein a third group of subcarriers from the plurality of subcarriers in the first single symbol time interval includes information for a second WTRU that is not combined with an orthogonal sequence; wherein the first WTRU and the second WTRU are different.

14. The wireless network device of claim 13 wherein the first group of subcarriers are not contiguous subcarriers.

15. The wireless network device of claim 13 wherein the information in the first group of subcarriers is time repeated in a second single symbol time interval and the orthogonal sequence in the first single symbol time interval and the second single symbol time interval frequency spreads the information.

16. The wireless network device of claim 13 further comprising transmitting pilot signals in the first single symbol time interval.