

Description

This invention relates to circuit arrangements for providing electromagnetic deflection of a cathode ray tube beam to develop a scanning raster with reduced distortion occurring in the development of the raster.

In a television apparatus having means for electromagnetically deflecting an electron beam in a cathode ray tube (CRT), a deflection yoke is positioned about a neck of the CRT. Circuit means cause cyclically varying currents to flow in deflection windings of the yoke. A varying electromagnetic field, which is thereby generated, deflects the electron beam and forms a raster on a target of the cathode ray tube. In general, the raster which is formed is desirably rectangular shaped. However, various types of electron beam scanning distortions can occur and cause the generated raster configuration to deviate from the desired rectangle.

One well-known form of raster distortion with which the present invention is concerned is so-called "pincushion" distortion, and, particularly, the "top and bottom" aspect of such distortion. This type of distortion is characterized by a central bowing of the raster scanning lines, the character of the bowing varying from a maximum downward bowing at the raster top through a minimum near the raster middle to a maximum upward bowing at the raster bottom. The bowing is approximately hyperbolically or parabolically shaped. FIGURE 1 illustrates the effect of pincushion distortion, when left uncorrected, on a crosshatch pattern. This distortion results from the physical geometry of the deflection system as determined by such factors as the size and configuration of the target area and the relative position of an electron beam deflection center with respect to the target.

A well known solution to the top-bottom pincushion distortion problem is to modulate the vertical scanning current with a horizontal rate f_H correction current. Thus, during the scanning of a horizontal scan line at the top of the screen of the CRT, for example, the horizontal rate correction current causes a varying change in the vertical scanning current. The varying change is such that at the center of such horizontal line, the vertical scanning current is larger than at the edges. Thus, the vertical deflection at the center portion of such horizontal scan line is greater than at the edge portions of the horizontal scan line. Consequently, the bow-shaped horizontal scan line is modified to appear closer to a horizontal straight line.

Another form of raster distortion with which the present invention is concerned is so-called "gullwing" distortion. This type of distortion is characterized by a multiple bowing or humps of raster scanning lines that are already substantially cor-

rected for pincushion distortion, as illustrated in FIGURE 2. The size of the humps varies in accordance with the type of the CRT used. In one example of a CRT, the size of the humps is at a maximum at an intermediate zone between the center of the screen and the top or between the center of the screen and the bottom. The origin of gullwing distortion is the difference between the beam scanning radius of curvature and the tube faceplate radius of curvature. New, flatter faceplate picture tubes having aspherical faceplate curvatures require correction of such gullwing distortion.

A tube of the type having a complex curvature faceplate is described in the following four UK patent applications.

1. GB-A-2136200, published 12 September 1984, in the name of F.R. Ragland, Jr. and entitled, CATHODE-RAY TUBE HAVING AN IMPROVED SHADOW MASK CONTOUR.

2. GB-A-2136198, published 12 September 1984, in the name of F.R. Ragland, Jr. and entitled, CATHODE-RAY TUBE HAVING A FACEPLATE PANEL WITH A SUBSTANTIALLY PLANAR PERIPHERY.

3. GB-A-2136199, published 12 September 1984, in the names of R.J. D'Amato et al., and entitled, CATHODE-RAY TUBE HAVING A NOVEL FACEPLATE CONTOUR.

4. GB-A-2147142, published 1 May 1985, in the names of R.J. D'Amato et al., and entitled, CATHODE-RAY TUBE HAVING A FACEPLATE PANEL WITH AN APPARENTLY PLANAR SCREEN PERIPHERY.

In one form of flatter faceplate picture tube, as typified by the RCA 110° COTY-SP, square-planar, 27V, color television picture tube, A68ACC10X, the formula for the tube faceplate sagittal height, z , in millimeters, with reference to the center of the faceplate is given by:

$$Z = A_1 X^2 + A_2 X^4 + A_3 Y^2 + A_4 X^2 Y^2 + A_5 X^4 Y^2 + A_6 Y^4 + A_7 X^2 Y^4 + A_8 X^4 Y^4,$$

where X and Y are the distance coordinates, in millimeters, from the faceplate center along the major and minor axes, respectively, and where:

$$A_1 = -0.236424229 \times 10^{-4}$$

$$A_2 = -0.363538575 \times 10^{-8}$$

$$A_3 = -0.422441063 \times 10^{-3}$$

$$A_4 = -0.213537355 \times 10^{-8}$$

$$A_5 = +0.883912220 \times 10^{-13}$$

$$A_6 = -0.100020398 \times 10^{-9}$$

$$A_7 = +0.117915353 \times 10^{-14}$$

$$A_8 = +0.527722295 \times 10^{-21}$$

The picture tube faceplate defined by this formula has a relatively shallow curvature near the center of the faceplate, which increases near the edges along paths parallel to both the major and

minor axes of the tube. The overall result is a faceplate of relatively flat appearance and with planar edges, namely, with points along the top, bottom, right and left edges located substantially in a common plane.

The gullwing distortion occurs because of the geometry of the faceplate of the CRT. When a flat face CRT is used, gullwing distortion is noticeable. In flat face picture tubes, the face of the tube is flat near the center and has an increasing radius of curvature near the edges. Multiple radiuses of curvatures cause the corresponding humps that characterize the gullwing distortion.

There is disclosed in Philips Application Note 1972, page 162, Electronic Components and Materials Division; L. Valkenstijn: "110° Colour Television - Phase 2, passive north-south raster correction", a cathode-ray tube scanning system in which a horizontal scanning current and a vertical scanning current are provided, with raster distortion correction means being arranged to modulate the vertical scanning current with a component having a frequency equal to the horizontal scanning frequency for reducing pincushion distortion, and a component having a frequency equal to the second harmonic of the horizontal scanning frequency for reducing "moustache" distortion.

An equivalent arrangement is disclosed in Telefunken Sprecher, No. 68, February 1976, pages 3-32; "Total-Modulbauweise für bewährte Technik: Farbfernsehchassis 712".

The problem with such arrangements is that the control of the desired corrections is not sufficiently accurate.

With a view to providing more control over raster correction, the present invention provides a cathode ray tube scanning system including a deflection yoke having respective horizontal and vertical deflection windings, a source of horizontal scanning current, a source of vertical scanning current, and means for coupling said yoke to said first and second sources in such manner that said horizontal scanning current is caused to traverse said horizontal deflection winding and said vertical scanning current is caused to traverse said vertical deflection winding, and a raster distortion correction apparatus for modulating the vertical scanning currents with components having frequencies of the horizontal scanning frequency and a harmonic thereof, characterized by: a body of ferromagnetic material arranged in a magnetic circuit configuration having first and second outside body segments and a center segment; first and second series coupled primary windings positioned respectively about said first and second outside body segments and coupled in the current path of said horizontal scanning current; first and second, output windings positioned about said center segment, and coupled

in the current path of said vertical scanning current for developing in each of said first and second output windings a corresponding current in accordance with said horizontal scanning current having an amplitude that varies in accordance with said vertical scanning current; a first tuned circuit that is tuned to a harmonic of the horizontal scanning frequency and that is responsive to said corresponding current in said first output winding for producing a first modulating current at the frequency of said harmonic; and means for developing from said first modulating current at said harmonic of the horizontal scanning frequency a vertical scanning current modulating voltage.

In accordance with a preferred embodiment of the invention, a gullwing distortion correction current at a frequency that is an harmonic of the horizontal frequency f_H , is used for modulating the vertical scanning current during each horizontal scan line time. The gullwing distortion may be corrected by modulating the vertical deflection current by an appropriate gullwing correction waveform, so as to straighten the horizontal scan lines that would otherwise have had multiple humps. In one example, the harmonic that is used is the second harmonic. A nonlinear, saturable reactor is used for introducing the appropriately modulated harmonic of the horizontal frequency component into the vertical scanning current paths to correct gullwing distortion. This nonlinear reactor may then advantageously provide the additional function of top-bottom pincushion correction.

In carrying out the invention, the reactor may comprise, for example, a two-window three-leg core, with an output winding wound on the center core leg, and with respective halves of an input winding wound on respective different outside core legs. The input winding halves are energized by the same horizontal scanning current but due to their respective poling they tend to drive horizontal rate flux through the center core leg in mutually opposing directions. Thus when their respective flux contributions are matched in amplitude there is complete cancellation of flux variations at the horizontal frequency or its harmonic, in the center core leg, with the result that no energy at the horizontal frequency or its harmonics is transferred to the output winding. However, should their respective flux contributions differ, cancellation in the central core leg will not be complete, with the result that there is effective flux linkage between the output winding and one of the input winding halves. Thus, variations at the horizontal frequency or its harmonics will be transferred to the output winding circuit by simple transformer action, the amplitude of the transferred variations depending upon the degree of difference in flux contributions, and the polarity depending upon which flux contribution is

predominant.

Dynamic control of the relative horizontal and harmonic flux contributions is afforded by the vertical scanning current itself, which flows through the output winding on the center core leg. During a first portion of the vertical scan cycle, when vertical scanning current is in a first direction, it includes a flux that, in one embodiment: (1) opposes a bias flux in a core segment linking the center leg to one outside leg (thereby increasing the permeability of this core segment); and (2) adds to a bias flux in a core segment linking the central leg to the other outside leg, thereby lowering the permeability of this core segment. The reverse is true during a succeeding portion of the vertical scan cycle when the scanning current reverses direction.

Thus, variations of one polarity at the horizontal frequency or its harmonic are transferred to the output winding from one input winding segment with maximum amplitude at a first peak of vertical scanning current. Maximum amplitude transfer of opposite polarity variation at the horizontal frequency or its harmonics, from the other input winding segment, occurs at the succeeding opposite direction peak of vertical scanning current. A polarity crossover occurs intermediate these peaks. A steady decrease in amplitude of the first polarity transfer occurs during approach of the crossover from the first peak, and a steady increase in amplitude of the opposite polarity transfer occurs subsequent to the crossover.

The modulated component at the horizontal frequency or its harmonic, thus transferred to the output winding, is of the form appropriate for top and bottom pincushion correction or gullwing correction, respectively. This modulated component is then coupled to the vertical deflection winding. This modulated component is provided for resonating a first resonant circuit that includes the output winding. In an embodiment of the invention, the first resonant circuit is tuned to a harmonic of the fundamental horizontal frequency.

Advantageously, a second resonant circuit may be tuned to the horizontal scanning frequency to provide top and bottom pincushion distortion correction. With the first resonant circuit tuned to the harmonic, a readily attainable level of control winding voltage will develop sufficient voltage at the horizontal frequency and its harmonic from the second and first resonant circuits, respectively, to add the requisite horizontal frequency current component and harmonic current component, respectively, to the vertical scanning current in the vertical deflection winding.

The horizontal frequency variations introduced by the second resonant circuit will be essentially sinusoidal in shape. Such a shape sufficiently approximates the ideal waveshape to produce an

acceptable pincushion correction. Similarly, it should be recognized that the amplitude and waveshape of the variations at the harmonic, introduced by the first resonant circuit, only approximate the ideal amplitude and waveshape that is required for providing gullwing distortion correction.

In accordance with an aspect of the invention, a source of vertical scanning current is coupled to a vertical deflection winding and to a control winding of a nonlinear reactor device. A source of horizontal scanning current is coupled to a horizontal deflection winding and to an input winding of the nonlinear reactor device. The nonlinear reactor device includes an output winding. A voltage is produced at the output winding from the horizontal scanning current at the input winding. Such voltage at the output winding is in an amplitude or phase that is in accordance with the vertical scanning current. A current that substantially contains a harmonic of the horizontal scanning frequency is produced from the voltage at the output winding. The vertical scanning current traversing the vertical deflection winding is modulated in accordance with the current that substantially contains the harmonic of the horizontal scanning frequency.

In the Drawing:

FIGURE 1 illustrates pincushion distortion of a raster;

FIGURE 2 illustrates gullwing distortion of a raster;

FIGURE 3 illustrates a gullwing and top-bottom pincushion distortion correction circuit, embodying an aspect of the invention;

FIGURE 4 illustrates a nonlinear reactor device that is used in the circuit of FIGURE 3;

FIGURE 5a illustrates the waveform of a second harmonic of the horizontal scanning current that is used for modulating the vertical rate scanning current for correcting gullwing distortion;

FIGURE 5b illustrates a horizontal retrace voltage that is produced simultaneously with the waveform of FIGURE 5a;

FIGURE 6 illustrates the waveform of a pincushion and gullwing correction voltage, applied to vertical deflection to winding of FIGURE 3, that causes the modulation of the vertical scanning current during an entire vertical scanning interval;

FIGURE 7 illustrates the waveform of the voltage of FIGURE 6 during a single horizontal scanning period; and

FIGURE 8 illustrates a second embodiment of a gullwing and a top-bottom pincushion correction circuit in accordance with an aspect of the invention, that includes first and second resonant circuits tuned to f_H and $2f_H$, respectively, that are mutually coupled by a transformer action.

In a horizontal deflection circuit 200, illustrated in FIGURE 3, a filtered DC voltage V_B from a power supply 45 is developed at a terminal 48. Voltage V_B is coupled through a primary winding 53a of a horizontal output or flyback transformer 53 to a terminal 90 of a horizontal deflection generator 86.

A horizontal deflection winding L_y is coupled to horizontal deflection generator 86. Generator 86 comprises the series arrangement of a linearity inductor 83, a trace capacitor 62, series coupled primary windings W3 and W4 of a nonlinear transformer T1, a dynamic "S" correction circuit 150 and a parallel arrangement of a retrace capacitor 80 and a trace switch 87. Switch 87 comprises the parallel arrangement of a horizontal output transistor 88 and a damper diode 89. Deflection generator 86 is capable of generating scanning current i_y in deflection winding L_y each horizontal deflection cycle. A conventional synchronized horizontal oscillator and driver circuit 85 provides switching control signals to the control base electrode of horizontal output transistor 88 to turn on the transistor during the horizontal trace interval and to turn off the transistor for initiating the horizontal retrace interval. A high voltage winding 53b of flyback transformer 53 is coupled to a conventional high voltage circuit 63 for developing an ultor accelerating potential for beam current.

Dynamic "S" correction circuit 150 includes an inductance L_{150} coupled in parallel with a capacitor C_{150} . Inductance L_{150} has an intermediate tap that is coupled to conduct deflection current i_y . Circuit 150 interposes a voltage waveform in series with deflection winding L_y that includes, together with the normal linearity waveform, a second harmonic of the horizontal frequency for reducing residual "S" errors that are associated with a flat face CRT.

In operation, trace switch 87 is conductive during the trace interval. When trace switch 87 is conductive, it isolates transformer 53 from deflection winding L_y . An upramping primary current i_2 in primary winding 53a increases the energy stored in flyback transformer 53 during the trace interval. This stored energy replenishes losses in deflection generator 86 and energizes high voltage circuit 63 during the retrace interval, when switch 87 is non-conductive. Deflection generator 86 forms with transformer 53 and retrace capacitor 80 a retrace resonant circuit. The energy stored in transformer 53 and deflection winding L_y , at the end of the trace interval, is transferred into retrace capacitor 80 to produce a retrace voltage V_R across capacitor 80 during the retrace interval. Horizontal deflection generator 86 generates horizontal rate deflection current i_y in each of windings W3 and W4 of transformer T1 that are series coupled with deflection winding L_y . It should be understood that deflection current i_y includes, in addition to current at the

fundamental frequency f_H , current at a harmonic or multiple, in this case $2f_H$, of the fundamental frequency f_H .

A vertical deflection output stage 57 that generates a vertical rate driving voltage V_v is coupled to a terminal 82 of a vertical winding L_v . A distortion correction voltage generating circuit 84 is coupled between a terminal 81a that is coupled to the other end terminal of deflection winding L_v and a terminal 81b. Terminal 81b is coupled to ground through a current sampling resistor 59 in series with a coupling capacitor 58. Distortion correction voltage generating circuit 84 develops voltage V_{DIC} between terminals 81a and 81b that modulates vertical current i_v through deflection winding L_v . A capacitor 64 is connected between terminals 81a and 81b.

FIGURE 6 illustrates the waveform of voltage V_{81a} at terminal 81a of FIGURE 3 that is representative of correction voltage V_{DIC} across capacitor 64. Voltage V_{DIC} has an amplitude that varies at the vertical rate. FIGURE 7 illustrates the waveform of voltage V_{81a} of FIGURE 3 in an expanded scale. Note the $2f_H$ rate component included in voltage V_{81a} , as illustrated by undulating waveform 120 of FIGURE 7.

Voltage V_{DIC} of FIGURE 3 modulates vertical scanning current i_v , and therefore varies the vertical position of the electron beam in the CRT, that is not shown in the figures. Voltage V_{DIC} compensates for the humps of the gullwing distortion shown in FIGURE 2, by modulating the vertical deflection current with a harmonic of the horizontal rate frequency so as to cause vertical deviation that is opposite in direction to that of the humps. Thus, the gullwing distortion is corrected by introducing vertical deflection current that follows the distortion and, thereby, "straightens" the horizontal scan lines.

Distortion correction voltage generating circuit 84 includes transformer T1 that is, illustratively, a saturable-core transformer having output windings W1 and W2 coupled in series. Distortion correction voltage generating circuit 84 includes a series resonant circuit 84_r that is tuned to the horizontal frequency f_H . The output or secondary winding W2 of transformer T1, between terminals 12 and 15, energizes capacitor 64 between terminals 81a and 81b and an inductor L4 between terminals 12 and 81b. Capacitor 64, inductor L4 and winding W2 form series resonant circuit 84_r. As explained later on, a horizontal rate f_H current i_r that flows in inductor L4 and capacitor 64 generates the horizontal rate f_H component of voltage V_{DIC} of circuit 84 that corrects pincushion distortion.

In accordance with an aspect of the invention, distortion voltage generating circuit 84 also includes a resonant circuit 84_{2r}, that is tuned to,

illustratively, the second harmonic $2f_H$ of the fundamental frequency f_H of scanning current i_y . Resonant circuit 84_{2f} includes windings W1 and W2 of transformer T1 coupled in series between end terminals 16 and 12 that energize a series arrangement of a gullwing distortion correcting tuning inductor L3, a capacitor C4 and the inductive impedance of that part of inductor L4 between a terminal L4C of inductor L4 and terminal 12 of transformer T1. Thus, inductor L3, inductor L4, windings W1 and W2 and capacitor C4 form series resonant circuit 84_{2f}. As explained later on, a current i_{2f} that flows in inductor L3 and capacitor C4, provides the second harmonic rate component of voltage V_{DIC} of circuit 84 that corrects gullwing distortion. It should be understood that inductor L4 combines currents i_{2f} and i_f at the harmonic $2f_H$ and fundamental frequency f_H , respectively, for generating the respective components of gullwing and pincushion correction voltage V_{DIC} .

Saturable transformer T1 of FIGURE 3 is illustrated in FIGURE 4. Similar numbers and symbols in FIGURES 3 and 4 indicate similar items or functions. Output windings W1 and W2 are wound on center segment or leg TCC of a core TC. Primary windings W3 and W4 are wound on the outside segments or legs TCB and TCA, respectively, of core TC. A permanent magnet 40 introduces a bias magnetic flux ϕ_1 in the direction shown in FIGURE 4. Substantially all of the vertical deflection current i_v of FIGURE 3 flows through terminal 15, at the junction of windings W1 and W2, to produce a flux ϕ_2 which divides, as fluxes ϕ_{2A} and ϕ_{2B} , into the magnetic circuits through legs TCA and TCB respectively and which is related in magnitude and polarity to vertical deflection current i_v of FIGURE 3. Horizontal scanning current i_y in windings W3 and W4 of FIGURE 3 produces a flux ϕ_{3A} and a flux ϕ_{3B} , respectively. Flux ϕ_{3A} is opposed to flux ϕ_{3B} in center leg TCC because of the way windings W3 and W4 of FIGURE 3 are coupled to conduct current i_y .

When vertical deflection current i_v is zero, as it is when the electron beam is at the center of the raster, the flux in each of the outer legs TCB and TCA of core TC is balanced and flux $\phi_{3A} = \text{flux } \phi_{3B}$. Therefore, there will be no induced voltage in windings W1 and W2.

At one extreme, for example, when the beam is at the top of the raster and vertical deflection current i_v is at its maximum positive value, flux ϕ_{2B} is, illustratively, polarized to add to flux ϕ_1 in core TC and flux ϕ_{2A} to subtract from flux ϕ_1 . The permeability of core TC may be illustratively characterized by an S-shaped curve of permeability versus flux that is typical for ferromagnetic material. Thus, flux ϕ_{2B} tends to decrease and flux ϕ_{2A} to increase the permeability of core TC in the

magnetic circuits including legs TCB and TCA respectively. Because of this magnetic differential, flux ϕ_{3A} and flux ϕ_{3B} are no longer equal at center leg TCC. Consequently, a voltage V_{W2} and a voltage V_{W1} are induced across windings W1 and W2, respectively. Each of voltages V_{W1} and V_{W2} is, in this case, illustratively, directly related to the value of flux ϕ_{3A} less flux ϕ_{3B} .

In contrast, at the extreme bottom of the raster, when vertical deflection current i_v of FIGURE 3 is at its maximum negative value, the induced voltage V_{W1} and V_{W2} are proportional to the value of flux ϕ_{3B} less flux ϕ_{3A} . Thus each of induced voltages V_{W1} and V_{W2} is of the opposite phase at the bottom of the raster relative to its respective phase at the top.

At points between these extremes, the difference between flux ϕ_{3A} and flux ϕ_{3B} is directly dependent on the magnitude and phase of flux ϕ_2 that is caused by vertical deflection current i_v . Therefore, a decreasing correction is achieved toward the center of the raster. A reversal of phase of correction is achieved near the center, and an increasing correction is achieved toward the bottom of the raster.

It should be understood that magnet 40 is not essential for creating the nonlinearity of the flux in core TC. Such nonlinearity or differential may be obtained by a judicious selection of core material for core TC.

Voltage V_{W2} of FIGURE 3 produces horizontal rate current i_f in resonant circuit 84_f. Current i_f produces a corresponding horizontal rate component of voltage V_{DIC} across capacitor 64. The phase of the horizontal rate component and that of the harmonic component of voltage V_{DIC} is controlled by phase adjusting inductor L4 to provide, for example, maximum amplitude of the horizontal rate modulation at the center of each line scan for properly phased N-S correction.

In carrying out an aspect of the invention, the sum voltage of voltages V_{W1} and V_{W2} , between terminals 12 and 16 of transformer T1 of FIGURE 3, produces current i_{2f} in resonant circuit 84_{2f} that is predominantly at the second harmonic of the fundamental horizontal frequency. FIGURE 5a illustrates the waveform of current i_{2f} of FIGURE 3. FIGURE 5b illustrates the simultaneous retrace waveform of voltage V_R across retrace capacitor 80.

Filtering action by capacitor C4 and inductor L3 produces current i_{2f} that has a substantial cosine waveform as illustrated in FIGURE 5a. The amplitude of current i_{2f} varies at a vertical rate, as in FIGURE 6, in accordance with the vertical rate amplitude variations of current i_v in winding W2. Current i_{2f} reverses its phase at the center of vertical trace. This vertical rate envelope of current

i_{2f} provides to an approximate degree, the level of gullwing correction vertical displacement, since such gullwing distortion varies in magnitude in a vertical manner, as illustrated in FIGURE 2.

Alignment of distortion correction voltage generating circuit 84 is done, illustratively, by adjusting inductor L4 to obtain maximum amplitude of voltage V_{81a} , adjusting inductor L3 for obtaining maximum current i_{2f} , readjusting inductor L4 for obtaining symmetrical right and left distortion correction on the CRT screen, and then adjusting resistor 61 for obtaining straight lines at the top and bottom of the CRT screen.

FIGURE 8 illustrates another embodiment of the invention. Similar numbers and symbols in FIGURES 3 and 8 indicate similar items or functions. The circuit of FIGURE 8 is similar to that of FIGURE 3 but with the difference that is noted below. In the circuit of FIGURE 8 resonant circuit 84_{2f} is coupled to capacitor 64 by transformer action of a transformer L4' which also provides, like inductor L4 in FIGURE 3, the inductive components of resonant circuits 84_f and 84_{2f} . Unlike the circuit of FIGURE 3, the resonant circuit 84_{2f} of FIGURE 8 is not conductively or D.C. coupled to capacitor 64.

Transformer T1 windings W1 and W2 of FIGURE 4 have a combined resistance of 3.3 ohms between terminals 12 and 16. Each of windings W3 and W4 has 0.08 ohm resistance. The inductance, at 15750 Hz, between terminals 12 and 16 is 320 microHenry. The inductance between terminals 14 and 17, when terminals 13 and 11 are shorted, is 26 microHenry. The core material of core TC is H3TEI25 made by TDK Co., Japan.

Claims

1. A cathode ray tube scanning system including a deflection yoke having respective horizontal (L_y) and vertical (L_v) deflection windings, a source (200) of horizontal scanning current (i_y), a source (57) of vertical scanning current (i_v), and means for coupling said yoke to said first and second sources in such manner that said horizontal scanning current is caused to traverse said horizontal deflection winding and said vertical scanning current is caused to traverse said vertical deflection winding, and a raster distortion correction apparatus for modulating the vertical scanning currents with components having frequencies of the horizontal scanning frequency and a harmonic thereof, said apparatus being characterized by:

a body (TC) of ferromagnetic material arranged in a magnetic circuit configuration having first (TCA) and second (TCB) outside body segments and a center segment (TCC);

first (W4) and second (W3) series coupled

primary windings positioned respectively about said first (TCA) and second (TCB) outside body segments and coupled in the current path of said horizontal scanning current (i_y);

first (W1) and second (W2) output windings positioned about said center segment (TCC), and coupled in the current path of said vertical scanning current (i_v) for developing in each of said first and second output windings a corresponding current in accordance with said horizontal scanning current (i_y) having an amplitude that varies in accordance with said vertical scanning current (i_v);

a first tuned circuit (L3,C4) that is tuned to a harmonic of the horizontal scanning frequency and that is responsive to said corresponding current in said first output winding (W1) for producing a first modulating current (i_{2f}) at the frequency of said harmonic; and

means (64) for developing from said first modulating current (i_{2f}) at said harmonic of the horizontal scanning frequency a vertical scanning current modulating voltage (V_{DIC}).

2. The raster distortion correction apparatus as recited in claim 1, characterized in that said first primary winding (W4) induces in said center segment (TCC) oppositely poled flux, relative to the flux that is induced by said second primary winding (W3).
3. The raster distortion correction apparatus as recited in claim 1, characterized by a second tuned circuit (L4,64) that is tuned to the horizontal scanning frequency and that is responsive to said corresponding current in said second output winding (W2) for producing a second modulating current (i_f) at the horizontal scanning frequency having an amplitude that varies at the vertical scanning frequency, and wherein said vertical scanning current modulating voltage developing means (64) develops said vertical scanning current modulating voltage (V_{DIC}) in accordance with said second modulating current (i_f).
4. The apparatus as recited in claim 3 characterized, in that said second modulating current (i_f) is coupled to said vertical scanning current modulating voltage developing means (64) by only magnetic coupling.

Patentansprüche

1. Kathodenstrahlröhren-Abtastsystem mit einem Ablenkjoch, welches Horizontal- (L_y) bzw. Vertikal- (L_v) Ablenkwindungen, eine Quelle (200) von Horizontal-Abtaststrom (i_y), eine



i_{2t} provides to an approximate degree, the level of gullwing correction vertical displacement, since such gullwing distortion varies in magnitude in a vertical manner, as illustrated in FIGURE 2.

Alignment of distortion correction voltage generating circuit 84 is done, illustratively, by adjusting inductor L4 to obtain maximum amplitude of voltage V_{81a} , adjusting inductor L3 for obtaining maximum current i_{2t} , readjusting inductor L4 for obtaining symmetrical right and left distortion correction on the CRT screen, and then adjusting resistor 61 for obtaining straight lines at the top and bottom of the CRT screen.

FIGURE 8 illustrates another embodiment of the invention. Similar numbers and symbols in FIGURES 3 and 8 indicate similar items or functions. The circuit of FIGURE 8 is similar to that of FIGURE 3 but with the difference that is noted below. In the circuit of FIGURE 8 resonant circuit 84_{2t} is coupled to capacitor 64 by transformer action of a transformer L4' which also provides, like inductor L4 in FIGURE 3, the inductive components of resonant circuits 84_t and 84_{2t}. Unlike the circuit of FIGURE 3, the resonant circuit 84_{2t} of FIGURE 8 is not conductively or D.C. coupled to capacitor 64.

Transformer T1 windings W1 and W2 of FIGURE 4 have a combined resistance of 3.3 ohms between terminals 12 and 16. Each of windings W3 and W4 has 0.08 ohm resistance. The inductance, at 15750 Hz, between terminals 12 and 16 is 320 microHenry. The inductance between terminals 14 and 17, when terminals 13 and 11 are shorted, is 26 microHenry. The core material of core TC is H3TEi25 made by TDK Co., Japan.

Claims

1. A cathode ray tube scanning system including a deflection yoke having respective horizontal (L_y) and vertical (L_v) deflection windings, a source (200) of horizontal scanning current (i_y), a source (57) of vertical scanning current (i_v), and means for coupling said yoke to said first and second sources in such manner that said horizontal scanning current is caused to traverse said horizontal deflection winding and said vertical scanning current is caused to traverse said vertical deflection winding, and a raster distortion correction apparatus for modulating the vertical scanning currents with components having frequencies of the horizontal scanning frequency and a harmonic thereof, said apparatus being characterized by:

a body (TC) of ferromagnetic material arranged in a magnetic circuit configuration having first (TCA) and second (TCB) outside body segments and a center segment (TCC);

first (W4) and second (W3) series coupled

primary windings positioned respectively about said first (TCA) and second (TCB) outside body segments and coupled in the current path of said horizontal scanning current (i_y);

first (W1) and second (W2) output windings positioned about said center segment (TCC), and coupled in the current path of said vertical scanning current (i_v) for developing in each of said first and second output windings a corresponding current in accordance with said horizontal scanning current (i_y) having an amplitude that varies in accordance with said vertical scanning current (i_v);

a first tuned circuit (L3,C4) that is tuned to a harmonic of the horizontal scanning frequency and that is responsive to said corresponding current in said first output winding (W1) for producing a first modulating current (i_{2t}) at the frequency of said harmonic; and

means (64) for developing from said first modulating current (i_{2t}) at said harmonic of the horizontal scanning frequency a vertical scanning current modulating voltage (V_{dic}).

2. The raster distortion correction apparatus as recited in claim 1, characterized in that said first primary winding (W4) induces in said center segment (TCC) oppositely poled flux, relative to the flux that is induced by said second primary winding (W3).
3. The raster distortion correction apparatus as recited in claim 1, characterized by a second tuned circuit (L4,64) that is tuned to the horizontal scanning frequency and that is responsive to said corresponding current in said second output winding (W2) for producing a second modulating current (i_t) at the horizontal frequency having an amplitude that varies at the vertical scanning frequency, and wherein said vertical scanning current modulating voltage developing means (64) develops said vertical scanning current modulating voltage (V_{dic}) in accordance with said second modulating current (i_t).
4. The apparatus as recited in claim 3 characterized, in that said second modulating current (i_t) is coupled to said vertical scanning current modulating voltage developing means (64) by only magnetic coupling.

Patentansprüche

1. Kathodenstrahlröhren-Abtastsystem mit einem Ablenkjoch, welches Horizontal-(L_y) bzw. Vertikal-(L_v) Ablenkwicklungen, eine Quelle (200) von Horizontal-Abtaststrom (i_y), eine



Quelle (57) von Vertikal-Abtaststrom (i_v) und Mittel aufweist zum Koppeln des Joches mit den ersten und zweiten Quellen so, daß der Horizontal-Abtaststrom die Horizontal-Ablenkwicklung durchfließt und der Vertikal-Abtaststrom die Vertikal-Ablenkwicklung durchfließt, und mit einer Rasterverzerrungs-Korrekturereinrichtung zum Modulieren der Vertikal-Abtastströme mit Komponenten, die Frequenzen der Horizontal-Abtastfrequenz und einer Harmonischen davon aufweisen, welche Einrichtung gekennzeichnet ist durch:

- einen Rumpf (TC) aus ferromagnetischem Werkstoff, der in einer Magnetkreis-Konfiguration angeordnet ist mit erstem (TCA) und zweitem (TCB) Rumpfaußen-Segment und einem Mittensegment (TCC);
- erste (W4) und zweite (W3) - in Reihe gekoppelte - Primärwicklung, die um das erste (TCA) bzw. zweite (TCB) Rumpfaußen-Segment angeordnet und in den Strompfad des Horizontal-Abtaststromes (i_h) gekoppelt sind;
- erste (W1) und zweite (W2) Ausgangswicklung, die um das Mittensegment (TCC) angeordnet sind und in den Strompfad des Vertikal-Abtaststromes (i_v) gekoppelt sind, zum Bilden eines korrespondierenden Stromes in jeder der ersten und zweiten Ausgangswicklung in Übereinstimmung mit dem Horizontal-Abtaststrom (i_h) mit einer Amplitude, die in Übereinstimmung mit dem Vertikal-Abtaststrom (i_v) variiert;
- einen ersten abgestimmten Kreis (L3, C4), der abgestimmt ist auf eine Harmonische der Horizontal-Abtastfrequenz und der abhängig ist von dem korrespondierenden Strom in der ersten Ausgangswicklung (W1), zum Erzeugen eines ersten Modulationsstromes (i_{21}) mit der Frequenz der Harmonischen;
- Mittel (64) zum Bilden - aus dem ersten Modulationsstrom (i_{21}) mit der Harmonischen der Horizontal-Abtastfrequenz - einer Vertikalabtast-Strommodulations-Spannung (V_{DIC}).

2. Rasterverzerrungs-Korrekturereinrichtung nach Anspruch 1, dadurch gekennzeichnet, daß die erste Primärwicklung (W4) in dem Mittensegment (TCC) entgegengesetzt gepolten Fluß induziert, relativ zu dem Fluß, der von der zweiten Primärwicklung (W3) induziert wird.

3. Rasterverzerrungs-Korrekturereinrichtung nach Anspruch 1, gekennzeichnet durch einen zweiten abgestimmten Kreis (L4, 64), der auf die Horizontal-Abtastfrequenz abgestimmt ist und der abhängig ist von dem korrespondierenden Strom in der zweiten Ausgangswicklung (W2), zum Erzeugen eines zweiten Modulationsstromes (i_{12}) mit der Horizontalfrequenz, der eine Amplitude aufweist, die mit der Vertikal-Abtastfrequenz variiert, und wobei die Mittel (64) zum Bilden der Vertikalabtast-Strommodulations-Spannung die Vertikalabtast-Strommodulations-Spannung (V_{DIC}) in Übereinstimmung mit dem zweiten Modulationsstrom (i_{12}) bilden.
4. Einrichtung nach Anspruch 3, dadurch gekennzeichnet, daß der zweite Modulationsstrom (i_{12}) zu den Mitteln (64) zum Bilden der Vertikalabtast-Strommodulations-Spannung nur durch Magnetkopplung gekoppelt wird.

Revendications

1. Système de balayage d'un tube à rayons cathodiques incluant un collier de déviation comportant des enroulements respectifs de déviation horizontale (L_h) et verticale (L_v), une source (200) de courant de balayage horizontal (i_h), une source (57) de courant de balayage vertical (i_v) et un moyen pour coupler ledit collier auxdites première et seconde sources d'une manière telle que ledit courant de balayage horizontal est entraîné à traverser ledit enroulement de déviation horizontale et ledit courant de balayage vertical est entraîné à traverser ledit enroulement de déviation verticale et un dispositif de correction de la distorsion d'image pour moduler les courants de balayage vertical avec des composantes ayant des fréquences de la fréquence de balayage horizontal et un harmonique de celle-ci, ledit dispositif étant caractérisé par :

un corps (TC) de matériau ferromagnétique disposé dans une configuration de circuit magnétique comportant des premier (TCA) et second (TCB) segments de corps extérieurs et un segment central (TCC) ;

des premier (W4) et second (W3) enroulements primaires couplés en série, placés respectivement autour desdits premier (TCA) et second (TCB) segments de corps extérieurs et couplés dans le parcours de courant dudit courant de balayage horizontal (i_h) ;

des premier (W1) et second (W2) enroulements de sortie placés autour dudit segment



central (TCC) et couplés dans le parcours de courant dudit courant de balayage vertical (i_v) pour développer dans chacun desdits premier et second enroulements de sortie un courant correspondant en conformité avec ledit courant de balayage horizontal (i_h) ayant une intensité qui varie en conformité avec ledit courant de balayage vertical (i_v) ;

un premier circuit accordé (L3, C4) qui est accordé à un harmonique de la fréquence de balayage horizontal et qui est sensible audit courant correspondant dudit premier enroulement de sortie (W1) pour produire un premier courant de modulation (i_{21}) à la fréquence dudit harmonique ; et

un moyen (64) pour développer , à partir dudit premier courant de modulation (i_{21}) audit harmonique de la fréquence de balayage horizontal, une tension de modulation du courant de balayage vertical (V_{DC}).

2. Dispositif de correction de la distorsion d'image selon la revendication 1 caractérisé en ce que ledit premier enroulement primaire (W4) induit dans ledit segment central (TCC) un flux de polarité contraire relativement au flux qui est induit par ledit second enroulement primaire (W3).
3. Dispositif de correction de la distorsion d'image selon la revendication 1, caractérisé par un second circuit accordé (L4, C4) qui est accordé à la fréquence de balayage horizontal et qui est sensible audit courant correspondant dudit second enroulement de sortie (W2) pour produire un second courant de modulation (i_1) à la fréquence horizontale ayant une intensité qui varie à la fréquence de balayage vertical et dans lequel ledit moyen de développement de la tension de modulation du courant de balayage vertical (64) développe ladite tension de modulation du courant de balayage vertical (V_{DC}) en conformité avec ledit second courant de modulation (i_1).
4. Dispositif selon la revendication 3, caractérisé en ce que ledit second courant de modulation (i_1) est couplé audit moyen de développement de la tension de modulation du courant de balayage vertical (64) par couplage magnétique seulement.