

Claims

1. Comparison device for a multi-channel audio signal configured to:
 - 5 derive, for an inter-channel time difference (ITD) between audio signals for at least one pair of channels, at least one ITD parameter (ITD_t) of the audio signals of the at least one pair of channels in an analysis window ($w(\tau)$),
 - 10 compensate the ITD for the at least one pair of channels in the frequency domain by circular shift using the at least one ITD parameter to generate at least one pair of ITD compensated frequency transforms ($L_{t,k,comp}; R_{t,k,comp}$),
 - 15 compute, based on the at least one ITD parameter and the at least one pair of ITD compensated frequency transforms, at least one comparison parameter ($\hat{r}_t, I\hat{C}_t$).
2. The comparison device according to claim 1, further configured to use frequency transforms ($L_{t,k}; R_{t,k}$) of the audio signals of the at least one pair of channels in the analysis window ($w(\tau)$) for deriving the at least one ITD parameter (ITD_t).
- 20 3. The comparison device according to claim 1 or 2, further configured to:
 - 25 compute the at least one comparison parameter using a function equaling or approximating an autocorrelation function ($W_X(n) = \sum_{\tau} w(\tau) w(\tau + n)$) of the analysis window and the at least one ITD parameter.
4. The comparison device according to claim 3, wherein
 - 30 the function equals or approximates a normalized version of the autocorrelation function ($\hat{W}_X(n) = W_X(n) / W_X(0)$) of the analysis window.
5. The comparison device according to claim 4, further configured to:
 - 35 obtain the function by interpolation of the normalized version of the autocorrelation function of the analysis window stored in a look-up table.

6. The comparison device according to any one of claims 1 to 5, wherein
- the at least one comparison parameter comprises at least one side gain ($g_{t,b}$) of at least one pair of mid/side transforms ($M_{t,k}; S_{t,k}$) of the at least one pair of *ITD* compensated frequency transforms ($L_{t,k,comp}; R_{t,k,comp}$), the at least one side gain being a prediction gain ($S_{t,k} = g_{t,b} M_{t,k} + \rho_{t,k}$) of a side transform ($S_{t,k}$) from a mid transform ($M_{t,k}$) of the at least one pair of mid/side transforms.
7. The comparison device according to claim 6, wherein
- the at least one comparison parameter comprises at least one corrected residual gain ($r_{t,b,corr}$) corresponding to at least one residual gain ($r_{t,b}$) corrected by a residual gain correction parameter ($\hat{r}_t$), the at least one residual gain ($r_{t,b}$) being a function of an energy of a residual ($\rho_{t,k}$) in a prediction of the side transform ($S_{t,k}$) from the mid transform ($M_{t,k}$) relative to an energy of the mid transform
- $$\left(r_{t,b} = \left(\frac{\sum_{k \in I_b} |\rho_{t,k}|^2}{\sum_{k \in I_b} |M_{t,k}|^2} \right)^{1/2} \right).$$
8. The comparison device according to claim 7, further configured to:
- compute the at least one side gain and the at least one residual gain using the energies and the inner product of the at least one pair of *ITD* compensated frequency transforms ($L_{t,k,comp}; R_{t,k,comp}$).
9. The comparison device according to any one of claims 7 to 8, further configured to:
- correct the at least one residual gain by an offset corresponding to the residual gain correction parameter $\hat{r}_t$ computed as $\hat{r}_t = \frac{2c}{c+1} \sqrt{2 \frac{1 - \widehat{W}_X(ITD_t)}{1 + c^2 + 2c\widehat{W}_X(ITD_t)}}$, wherein c is a scaling gain between the audio signals of the at least one pair of channels and $\widehat{W}_X(n)$ is a function approximating a normalized version of the autocorrelation function of the analysis window.
10. The comparison device according to any one of claims 1 to 9, wherein

the at least one comparison parameter comprises at least one inter-channel coherence (ICC) correction parameter ($\hat{ICC}_t$) for correcting an estimate ($ICC_{b,t}$) of the ICC - determined in the frequency domain - of the at least one pair of audio signals based on the at least one ITD parameter.

11. The comparison device according to any one of claims 1 to 10, further configured to:

10 generate at least one downmix signal for the audio signals of the at least one pair of channels, wherein the at least one comparison parameter ($\hat{r}_t, \hat{ICC}_t$) is computed for restoring the audio signals of the at least one pair of channels from the at least one downmix signal.

12. The comparison device according to any one of claims 1 to 11, further configured to:

generate the at least one downmix signal based on the at least one pair of ITD compensated frequency transforms.

13. Multi-channel encoder comprising the comparison device according to claim 11 or 12, further configured to:

25 encode the at least one downmix signal, the at least one ITD parameter and the at least one comparison parameter for transmission to a decoder.

14. Decoder for multi-channel audio signals configured to:

30 decode at least one downmix signal, at least one inter-channel time difference (ITD) parameter and at least one comparison parameter ($\hat{r}_t, \hat{ICC}_t$) received from an encoder,

upmix the at least one downmix signal for restoring the audio signals of at least one pair of channels from the at least one downmix signal using the at least one

comparison parameter to generate at least one pair of decoded *ITD* compensated frequency transforms $(\hat{L}_{t,k}; \hat{R}_{t,k})$,

5 decompensate the *ITD* for the at least one pair of decoded *ITD* compensated frequency transforms $(\hat{L}_{t,k}; \hat{R}_{t,k})$ of the at least one pair of channels in the frequency domain by circular shift using the at least one *ITD* parameter to generate at least one pair of *ITD* decompensated decoded frequency transforms for reconstructing the *ITD* of the audio signals of the at least one pair of channels in the time domain,

10

inverse frequency transform the at least one pair of *ITD* decompensated decoded frequency transforms to generate at least one pair of decoded audio signals of the at least one pair of channels.

15 15. Comparison method for a multi-channel audio signal comprising:

deriving, for an inter-channel time difference (*ITD*) between audio signals for at least one pair of channels, at least one *ITD* parameter (ITD_t) of the audio signals of the at least one pair of channels in an analysis window $(w(\tau))$,

20

compensating the *ITD* for the at least one pair of channels in the frequency domain by circular shift using the at least one *ITD* parameter to generate at least one pair of *ITD* compensated frequency transforms $(L_{t,k,comp}; R_{t,k,comp})$,

25

computing, based on the at least one *ITD* parameter and the at least one pair of *ITD* compensated frequency transforms, at least one comparison parameter $(\hat{r}_t, IC_t)$.