Description

The invention concerns a video signal processing apparatus including the means recited in the preamble of claim 1.

From US-A-4,725,960 a method of sizing an image on a graphic display for a numerical controller is known whereby a microcomputer obtains a magnification for image drawing and center coordinates of an image drawing space such that maximum and minimum coordinate values entered through a key input means will be put in the display screen. Based upon such a magnification and center coordinates, the locus of a tool or the like is drawn on the display screen. In parallel with the above drawing process, the microcomputer obtains maximum and minimum coordinate values of the NC command program. When a predetermined command is entered through the key input means after completion of the above drawing process, the microcomputer obtains such a magnification for image drawing and center coordinates of the image drawing space that the maximum and minimum coordinate values of the NC command program obtained in parallel with the above drawing process will be contained in the display screen. Based upon the thus obtained magnification and center coordinates, the locus of a tool or the like is drawn on the display screen.

Further, from US-A-4,774,581 a television picture Zoom system is known relating to a circuitry that produces a magnificant image representing a portion of a video frame from a conventional television signal. The portion of the field which is magnified, hereinafter referred to as the source portion, is determined by signals provided via viewer controls. These controls define the upper left corner of the image, in terms of horizontal and vertical pixel positions in the unmagnified field, and a magnification factor to be used to produce the magnified display.

In this referenced patent, the upper left corner of the source portion is used as a reference point when the magnification factor is changed or when the source portion is panned around the unmagnified field. However, this may not be the best reference point. Intuitively, a viewer manipulating the controls would expect the center of the image to be the reference point since this is the reference used by mechanical zoom apparatus such as photographic zoom lenses. If, for example, the upper left corner of a source portion were used as the reference point, an object of interest in the center of the picture may be moved out of the display when the magnification factor is increased.

From the point of view of the circuit designer, it is more convenient to provide the pixel positions of the upper left corner of the portion of the image to be magnified to the zoom and pan system. If, for example, the portion of the image being magnified were near an edge of the frame and the magnification factor were reduced, maintaining a constant center position would cause portions of the video signal outside of the active video region (i.e. the horizontal or vertical blanking intervals) to be included in the magnified display. Moreover, it is easier to determine the allowable limits of the source portion during a pan operation when the upper left corner is used as the reference point than when the image center is used as the reference point.

The object of the invention is to provide for means allowing a viewer of a television apparatus to more convenient make use of the magnification feature thereof.

Starting from the above mentioned US-A-4,774,581 to which the preamble of claim 1 refers, this object is being solved by the characterizing features of that claim. Particular improvements and embodiments of the invention are being characterized in the subclaims.

The present invention is embodied in apparatus and a method for selecting a part of a field of an input video signal to be used to produce a magnified image. This apparatus includes control circuitry which allows a viewer to select the center position of the selected part, and the magnification factor to be used to produce the magnified image. Monitoring circuitry is included in the apparatus to limit the boundaries of the selected part to be within the active video portion of the input signal. This monitoring circuitry is responsive to the horizontal and vertical coordinates of the selected center position as well as to the selected magnification factor.

FIGURE 1 is a block diagram of a television receiver which includes an image zoom feature.

FIGURE 1a is a diagram of a zoom system control suitable for use with the television receiver shown in FIGURE 1.

FIGURE 2 is a block diagram of an output controller suitable for use in the television receiver shown in FIGURE 1.

FIGURE 3 is a block diagram of a portion of an alternative output controller which limits the magnification factor selected by the viewer.

FIGURES 4, 5A and 5B are block diagrams of other portions of the alternative controller which limit the horizontal and vertical starting positions selected by the viewer.

FIGURE 6 is a block diagram of circuitry which augments the controller shown in FIGURES 3, 4, 5A and 5B.

FIGURE 7 is a block diagram of a second alternative output controller which limits the magnification factor and vertical and horizontal starting positions selected by the viewer.

FIGURES 8, 9 and 10 are flow chart diagrams useful for explaining the operation of the controller shown in FIGURE 7.

The following is a brief description of the zoom system described in the above referenced U.S. Patent US-A-4,774,581 which provides a context for the present invention. In FIGURE 1, a composite video signal, provided by a source 10 which, may include a conventional television tuner, provides a composite video signal to an analog to digital converter (ADC) 14. The ADC 14 digitizes this signal and applies it to a field memory 16. The memory 16 is responsive to signals provided by a memory sequencer 18 and by a write address generator 20 to write samples representing image pixels into the field memory 16. These samples are read from the memory 16, after a suitable delay, responsive to address values provided by a read address generator 22.

The sampled data composite video signal provided by the memory 16 is separated into luminance (Y) and chrominance (C) signal components by Y/C separation circuitry 27. The luminance and chrominance components are applied to respective vertical interpolator circuits 28 and 32. The interpolators 28 and 32 insert additional lines between the lines of the respective video signals provided by the circuitry 27 to effect the requested vertical magnification. The chrominance vertical interpolator 32 also separates the chrominance signal into in-phase (I') and quadrature-phase (Q') color difference signal components.

The vertically interpolated luminance signal is applied to hanging dot correction circuitry 29 which removes distorting signal artifacts, introduced in the Y/C separation process, to produce an output signal Y'. The signal Y' is applied to a luminance signal horizontal interpolator 30 and the signals I' and Q' are applied to a color difference signal horizontal interpolator 34. The interpolators 30 and 34 insert interpolated samples between the samples of the respective signals Y' and I', Q' to effect the horizontal magnification requested by the viewer.

In the above-referenced patent, the portion of the video signal provided by the source 10 which is to be used to produce the magnified image is defined by three signals provided via viewer controls 24, indicated in phantom. These signals are a vertical position value, VPOS, a horizontal position value, HPOS and a zoom ratio value, ZR. The signals VPOS and HPOS respectively define a line interval of the video field held in the memory 16 and a sample in that line interval which are at the upper left corner of the image to be magnified. The signal ZR defines the magnification factor to be used. This value is not, itself a magnification factor but the denominator of a fraction 256/ZR which is the magnification factor. The signal VPOS and ZR are used by the read address generator 22 while the signals HPOS and ZR are used by the horizontal interpolators 30 and 34 to produce the magnified image.

Those persons skilled in the art of digital video signal processing will readily appreciate that in the more general case both starting addresses HPOS and VPOS will be applied to the read address circuitry. In addition a signal ZR or a signal representing the desired magnification will be coupled to the read address circuitry to establish the rate at which read addresses are generated. Nominally only the signal ZR or signals representing ZR will be coupled to the vertical and horizontal interpolators. Note signals representing ZR may be, for example, interpolator coefficients which may be provided by preprogrammed read only memories addressed by the values ZR.

In the present embodiments of the invention, the viewer controls 24 are replaced by an output controller 25. The controller 25 is responsive to viewer controls 23 which allow a user to specify the center of the source portion of an image and a magnification factor to be used to produce an output image. The controller 25 converts signals provided by these controls into the signals HPOS, VPOS and ZR. The controller 25 ensures that the magnified image includes only active video information, and the signals it produces properly track viewer commands to change the center of the source portion as the source portion is panned around the input field.

FIGURE 1A is a diagram of an exemplary viewer control 23. These controls include vertical up and down center position controls, 51 and 52, respectively, horizontal left and right center position controls, 55 and 56, respectively, and zoom-in and zoom-out step controls 58 and 59, respectively. A reset button 57 may also be provided. By pressing one of the control buttons 51, 52, 55, and 56, the viewer incrementally changes the horizontal and vertical center positions of the target image. By pressing one of the control buttons 58 and 59, the viewer incrementally increases and decreases the applied magnification factor. A constant center position is maintained while the magnification factor is changed. However, this center position may be adjusted if a decrease in magnification would cause a portion of the image beyond the raster boundaries to be displayed. By pressing the reset button, 57, the viewer may return the displayed

image to a preset center position and magnification factor, for example, one to one magnification and centered in the center of the input field.

Two different hardware implementations and one combined hardware and software implementation of the output controller 25 are described below. To understand the operation of these controllers, it is helpful to first understand some mathematics used by the controllers. The zoom system shown in FIGURE 1 is designed for an exemplary video image having 768 active pixels per horizontal line interval, and 256 active line intervals per field. It is understood that the methodology employed may be used for displays with different numbers of pixels per line interval and different numbers of line intervals per field.

Ten-bit data values are used to identify a horizontal pixel position. Similarly, eight-bit data values are used to identify the line interval in which a pixel resides.

During the zooming process, when the magnification factor is changing, it is desirable to maintain the appearance of a smooth, continuous transition, although the displayed image is changing in discrete steps. As the number of intermediate steps grows larger, the change appears smoother. Moreover, it is desirable to create a relatively large number of virtual positions located between the actual pixels, in order to identify a unique value for each pixel in the magnified display. To these ends, 256 virtual positions are defined between each pair of pixels in a scan line and between each pair of scan lines. These virtual positions are used to define the relative positions of the pixels and lines which constitute the magnified display. However, these virtual positions are grouped into a smaller number of interstitial positions for interpolation. In the embodiments of the invention described below, 15 interstitial pixel values may be interpolated between each pair of contiguous pixels, with a sixteenth position located at the pixel center. Likewise, each pair of horizontal scan lines has 16 interstitial line positions. Four additional bits are used to specify the interstitial pixel or line location with the required precision. Output controller 25, therefore, specifies HPOS as a 14-bit signal and VPOS as a 12-bit signal.

The maximum magnification is attained when each virtual pixel position in the zoom region is mapped to one pixel in the displayed image. This corresponds to 1/65,536th [i.e. 1/(256 * 256)] of the original picture being displayed. The magnification factor is an eight-bit value, thus, 256 different magnification steps are allowed. Since the most of the steps correspond to non-integer magnification levels, it is convenient to define a zoom ratio signal, ZR, related to the magnification in which each value of the signal ZR corresponds to a unique magnification value and the values of ZR are integers ranging from one to 256. To determine the unique zoom ratio value for any magnification level, it is only necessary to determine the fraction of the image, along a linear dimension, which is displayed and multiply by the maximum magnification value (in this case 256). In order to store the information in eight bits, rather than nine, one is subtracted from each value of the signal ZR as per the above computation, making the range of the signal ZR between zero and 255. The magnification factor, MF, is defined in terms of the signal ZR by equation (1).

$$MF = 256 / (ZR + 1) \quad (1)$$

Since this magnification factor is applied uniformly across the displayed region, a pair of center point coordinates and a ZR value will uniquely define the horizontal and vertical pixel positions, HPOS and VPOS, of the upper left corner of the image. The general relationship is defined by equations (2) and (3), and the specific relationship for a 768 x 256 display is defined by equations (4) and (5).

$$HPOS = HC - (NHP * NIP) / (2 * MF) \quad (2)$$

$$VPOS = VC - (NVL * NIP) / (2 * MF) \quad (3)$$

$$HPOS = HC - (24)(ZR + 1) \quad (4)$$

$$VPOS = VC - (8)(ZR + 1) \quad (5)$$

In these equations, HPOS is the starting horizontal position, VPOS is the starting vertical position HC is the horizontal center, VC is the vertical center, ZR is the selected zoom ratio, NHP is the number of pixels in a horizontal scan line. NVL is the number of vertical lines in the display and NIP is the number of interstitial positions between any two lines or any two pixels, plus one.

In addition to allowing the user to specify a center point and a zoom factor, the output controller 25 includes circuitry which automatically corrects the center point of the viewed region so that raster boundaries are not crossed and only active video is displayed. If the magnification factor, MF, is increased

while the center point of the magnified image is held at the center of the source image, only active video information will be displayed. However, once the center point of the generated image is moved away from the center of the source image, demagnification may eventually result in the display of non-active video information, i.e. the horizontal and vertical blanking intervals.

The general relationship defining the valid horizontal and vertical center positions is given by the inequalities (6) and (7) while the specific relationship for a 768 pixel by 256 line display is given by the inequalities (8) and (9).

$$(NHP*NIP)/(2*MF) \leq HC \leq NHP*NIP*(1 - 1/(2*MF)) \quad (6)$$

$$(NVL*NIP)/(2*MF) \leq VC \leq NVL*NIP*(1 - 1/(2*MF)) \quad (7)$$

$$24 * (ZR+1) \leq HC \leq 12288 - 24 * (ZR+1) \quad (8)$$

$$8 * (ZR+1) \leq VC \leq 4096 - 8 * (ZR+1) \quad (9)$$

FIGURE 2 is a block diagram showing components of an output controller 25 suitable for use in a first embodiment of the invention. This controller accepts the incremental signals provided by the viewer controls 23 and produces signals ZR, HPOS and VPOS for application to the zoom system as shown in FIGURE 1.

To change the magnification factor, the output controller 25 accepts up and down incremental zoom control signals from the viewer controls 58 and 59, respectively. These control signals are applied to a zoom controller 212 which converts the signals into pulses that respectively decrement and increment the value held in an 8 bit up-down counter 213. The output signal of the counter 213 is the signal ZR.

The horizontal center controller 216 accepts left and right control signals provided by the viewer controls 55 and 56. These signals are converted into pulse signals which respectively decrement and increment a horizontal center counter 217. The output signal provided by the counter 217 is the horizontal center signal, HC.

In the same way, a vertical center controller 221 receives up and down control signals from the viewer controls 51 and 52. The controller 221 converts these signals into pulse signals which respectively decrement and increment a vertical center counter 222. The output signal of the counter 222 is the vertical center signal, VC.

Circuitry which includes an adder 241, multipliers 242 and 243, digital value sources 241a, 242a and 243a and a subtracter 244 produce the signal HPOS at the output port of the subtracter 244 according to the equation (4) set forth above. Similarly, the adder 241, the multiplier 242, digital value sources 241a and 242a and a subtracter 248 produce the signal VPOS at the output port of the subtracter 248 according to the equation (5) set forth above.

The signal HPOS is compared, in a comparator 218, to a signal HL which is defined by equation (10).

$$HL = 48 * (255 - ZR) \quad (10)$$

The signal HL is generated by a subtracter 245, multipliers 246 and 247 and digital value sources 245a, 246a, and 247a. The signal HL defines the right pixel limiting value for the image. If HPOS is greater than HL, a portion of the horizontal blanking interval will be displayed on the right side of the reproduced image. The left pixel limiting value for the image is zero. The comparator 218 performs the validity check set forth above in reference to equation (8) when equation (2) is used to convert the signal HC to the signal HPOS.

When the comparator 218 detects that the signal HPOS is greater than HL or less than zero, it applies a logic-one signal to the horizontal center controller 216. The controller 216 is also coupled to receive a signal, 225, provided by the counter 217. The signal 225 indicates whether the value of the signal HC is on the left or right of horizontal center of the source image, that is to say, whether the value of the signal HC is respectively less than or not less than 6144 (1800 hexadecimal). There are 12288 (768 * 16) pixels and interstitial pixels on each line of the source image. The signal 225 may be generated as the logical OR of the most significant bit (MSB) of the 14-bit signal HC with the logical AND of the next two less significant bits of the signal HC.

Responsive to these two signals, the horizontal center controller 216 conditions the counter 217 to increment its value if HPOS is invalid and HC is in the left half of the source image and to decrement its value if HPOS is invalid and HC is in the if the right half of the source image. Otherwise, the controller 216 increments or decrements the counter 217 as requested by the viewer.

The subtracter 245, multiplier 246 and digital value sources 245a and 246a are used to generate a vertical limiting signal, VL, which is defined by equation (11).

$$VL = 16 * (255 - ZR) \quad (11)$$

The signal VL represents the largest line number or interpolated line number which can be at the top of an image for a given zoom ratio. The vertical position signal VPOS is compared to the signal VL by a comparator 223.

The comparator 223 provides a logic-one output signal when the signal VPOS is greater than VL or when it is less than zero. the output signal of the comparator 223 is a logic-zero otherwise. The output signal of the comparator 223 is coupled to the vertical center controller 221. The controller 221 is also coupled to receive a signal 226 from the counter 222 which indicates that the signal VC represents a line in the upper or lower half of the source image. This signal has a logic-one value, for example, when the signal VC is greater than 2048 (800 hexadecimal) and a logic-zero value when the signal VC is less than or equal to 2048. There are 4096 (256 * 16) lines and interstitial lines in a field of the source image. The signal 226 may be, for example, the most MSB of the signal VC.

When the comparator 223 indicates that VPOS is invalid and the signal 226 indicates that the current vertical center is in the upper half or the lower half of the source image, the vertical center controller 221 conditions the counter 222 to respectively increment or decrement its value. When the comparator 223 indicates that VPOS is valid, the controller 221 conditions the counter 222 to increment or decrement its value as requested by the viewer.

FIGURE 3 shows the details of a portion of an alternative output controller 23 which may be used to replace step control 212 and 8-bit counter 213, shown in FIGURE 2. In the discussion of the previous embodiment of the invention, the only zoom control option for the viewer was to request an increase or a decrease in the value of ZR. FIGURE 3 shows a circuit which will allow a user to change ZR or to reset ZR to a predetermined value. Switching to an absolute ZR value allows an instantaneous transition from one magnification factor to another without stepping through the intermediate magnification factors. A typical use for such a feature would be to implement a reset feature as discussed above in reference to the reset button 57 of the viewer controls 23. In these embodiments of the invention, a reset may be achieved by setting the signal ZR to 255. This reset button may also be coupled to condition the horizontal and vertical control circuitry to set HPOS and VPOS to zero, as shown below in reference to FIGURES 5A and 5B.

FIGURE 3 shows a circuit which receives a signal DZ indicating a requested change in the magnification factor. This signal is generated, for example, by viewer manipulation of the magnification step controls 58 and 59. A value of -1 is provided when the control button 58 is pressed to increase the magnification factor and a value of +1 is provided when the control button 59 is pressed to decrease the magnification factor. The signal DZ is added to the zoom ratio signal ZR by an adder 310. The sum provided by the adder 310 is a user requested zoom ratio, Z2. The signal Z2 is applied to a Limiter 311 which ensures that the requested value of ZR is within range and corrects the value as necessary. For the range of the signal ZR set forth above (0 to 255), the limiter may be eliminated since the signal ZR is kept within these limits by virtue of it being an eight-bit signal. It may be desirable to limit the lower value of the signal ZR to a value such as 51, to limit the maximum magnification factor to five. In this instance, the limiter 311 would establish a lower limit of 51 for the signal provided by the adder 310.

The signal Z3, provided by the limiter 311, is applied to one input port of a multiplexor 312. An absolute value, A1, for the signal ZR is applied to another input port of the multiplexor 312. The control input terminal of the multiplexor is coupled to receive an absolute/differential mode signal ADM1. The signal ADM1 may be provided, for example, by the reset control button 57 of the viewer controls 23, shown in FIGURE 1A. Responsive to the signal ADM1, the multiplexor 312 passes either the signal Z3 or the value A1. The multiplexor 312 applies its output signal Z4 to a synchronizing latch 313. The latch 313 synchronizes the signal Z4 to the system clock signal (not shown). The output signal of the latch 313 is the zoom ratio signal, ZR, which is provided by the output controller 25 as shown in FIGURE 1.

The signal ZR is also applied to the adder 310, for use in processing further zoom changes, and it is passed on to latch 314 and to one input port of a subtractor 315. In this embodiment of the invention, the latch 314 is a delay element which provides a delay of one cycle of the viewer control update clock. Typically, this clock is relatively slow, having a period on the order of a centisecond to allow the viewer to stop the zoom at any level. By subtracting the signal Z5 from the signal ZR, the zoom differential, Z6, between the current and previous values of the signal ZR may be determined. The signal Z6 may differ from the user requested zoom differential signal Z1 if the limiter 311 has made adjustments or if the system has been reset. The zoom differential signal, Z6, is used in the circuit shown in FIGURE 4 to adjust the

values of the signals HPOS and VPOS.

FIGURE 4 shows a circuit which corrects user requested changes to the signals HPOS and VPOS to account for changes in the zoom ratio signal ZR. The signal Z6 is stored in a synchronizing latch 415. The output signal, Z7, of latch 415 is applied to two parallel circuits which determine the adjustments to the signals HPOS and VPOS, respectively. This circuitry maintains a substantially constant image center position when the magnification factor is changed. The signal Z7 is multiplied by 24 by a shift-and-add circuitry which includes bit-shifters 416 and 418 and an adder 417. The signal provided by the shifter 418 is subtracted, by a subtractor 419, from a requested horizontal differential signal, DX, to produce a corrected horizontal differential value DX'. In the same manner, a subtractor 421 subtracts a signal representing eight times the signal Z7 from a requested vertical differential circuit DY to produce a corrected differential circuit DY'. The resulting differential horizontal and vertical signals are applied to circuitry such as that shown in FIGURES 5A and 5B which generates the respective signals HPOS and VPOS for the zoom system shown in FIGURE 1.

FIGURE 5A shows the details of a viewer control interface which may be used to replace the horizontal center controller 216 and the horizontal center counter 217, described above in reference to FIGURE 2. This circuit allows a user either to increment or decrement the signal HC or to substitute an absolute HC value for the current HC signal. FIGURE 5B shows circuitry of the same type which performs the same functions for the vertical center signal VC.

In the circuitry shown in FIGURE 5A, the signal DX', provided by the adder 419 of FIGURE 4 is applied to one input port of an adder 512. Another input port of the adder 512 is coupled to receive the signal HPOS. The output signal of the adder 512 is a user requested horizontal position signal, X3. The signal X3 is range checked in a limiter 513. The limiter 513 ensures that the new sum is non-negative and no greater than the total number of pixels and interstitial pixels in a scan line (i.e. 12288). The output signal, X4, of limiter 513 is applied to one input port of a multiplexor 514. Another input port of the multiplexor 514 is coupled to receive an absolute horizontal position value, A2. The multiplexor 514 is conditioned by a control signal ADM2, which may be the same as the signal ADM1, to pass either the signal X4 or a preset absolute value, A2. The output signal, X5, of the multiplexor 514 is stored in a synchronizing latch 515. The output signal of the latch 515 is the signal HPOS which is applied to the zoom circuitry by the output controller 25 as shown in FIGURE 1. The signal HPOS is also applied to the adder 512, as set forth above. The circuit in FIGURE 5B is substantially the same as the circuit shown in FIGURE 5A. The two circuits differ only in the maximum values used by respective limiters 513 and 517. The limiter 517 will allow VPOS values as large as the total number of scan lines and interstitial scan lines (i.e. 4096).

FIGURE 6 shows the details of circuitry which will limit the user requested HPOS and VPOS values, provided by the circuitry shown in FIGURES 5A and 5B, to prevent the display of video information outside of the active video region. This circuitry receives, as inputs, the signals ZR, HPOS and VPOS provided by the circuitry shown in FIGURES 3, 4, 5A and 5B. The output signals provided by the circuitry shown in FIGURE 6 are corrected signals HPOS' and VPOS'. These signals are applied to the zoom system shown in FIGURE 1 as the starting horizontal and vertical position signals. This circuitry uses substantially the same algorithm as is used by the circuitry shown in FIGURE 2: it limits HPOS to be greater than zero and less than 48 * (256 - ZR). It also limits VPOS to be greater than zero and less than 16 * (256 - ZR).

In FIGURE 6, a zero is concatenated onto the signal ZR in the MSB position to add a ninth bit. This new MSB is inverted in inverter 611, and then concatenated to the eight least significant bits (LSB's) of the signal ZR, which have not been inverted. This operation is equivalent to a twos complement subtraction of 256 from ZR. The difference value produced by this operation is applied to a conventional shift and add multiplier 612 which multiplies the difference value by three. The multiplier 612 includes a synchronizing latch (not shown). The output signal of the multiplier 612 is a ten-bit signal. Four zero bits are concatenated to this value in the LSB positions to provide a 14 bit value, P5, which represents the signal provided by the multiplier 612 multiplied by 16.

The signal P5 is extended to 15 bits by sign extending circuitry 613 which adds a fifteenth most significant bit with the same value as the fourteenth (previously the most significant) bit. This 15-bit signal, P6, is applied to an input port of an adder 614. Another input port of the adder 614 is coupled to receive a signal S5 which is the signal HPOS extended to 15 bits and delayed by a synchronizing latch 619 to be properly timed with respect to the signal P6.

The signals S5 and P6 are summed by adder 614, yielding a signal, S6. The signal S6 has a value of [HPOS + 48 * (ZR - 256)] which is equivalent to -[48 * (256 - ZR) - HPOS]. The product in the square brackets is essentially the same limiting signal that is applied to the comparator 218 in FIGURE 2. The 15 bits of the signal S6 are applied to respective first input terminals of a 15 two-input NAND gates 615. An inverted version of the MSB of the signal S6 is applied to the second input terminal of each of the gates

615. If the MSB is logic-zero (a positive S6), each of the 15 bits will be inverted so that the signal S7 provided by the NAND gates 615 is the ones complement representation of the signal S6. If, however, the MSB of the signal S6 is logic-one (a negative S6), the NAND gates 615 are all disabled and provide an output value having 15 ones (the ones complement of zero).

The signal S7 is applied, through a synchronizing latch 619, to one input port of an adder 616. The other input port of the adder 616 is coupled to receive the signal S5 via a synchronizing latch 620. The adder 616 has a carry-in input terminal, CI, which is coupled to receive a logic-one value. In this configuration, the adder 616 effectively converts the ones complement values provided by the latch 619 into twos complement negative values which are added to the twos complement positive values provided by the latch 620.

This operation subtracts the signal S6 from the signal S5. If S6 is negative or zero then the signal HPOS is within its valid range and a value of zero is subtracted from HPOS by the adder 616. If S6 is positive, its value is the amount by which the signal HPOS exceeds its upper limit. This value is subtracted by the adder 616 to produce a signal HPOS that is within its upper limit. However, the signal HPOS may still be less than the lower limit of zero. HPOS is limited to be within its lower limit (i.e. to be greater than or equal to zero) by a bank of 14 AND gates, 617. First input terminals of the gates 617 are coupled to receive the 14 LSB's, respectively, of the signal provided by the adder 616. Second input terminals of each of the AND gates 617 are coupled to receive an inverted version of the MSB (i.e. the sign bit) of the signal provided by the adder 616. When the signal provided by the adder 616 is negative, the AND gates 617 are disabled and provide a zero value. Otherwise, the gates 617 pass the value applied to their first input terminals.

The output signal provided by the AND gates 617 is passed through a synchronizing latch 618 to produce a signal HPOS'. This signal is the horizontal position signal that is provided to the zoom circuitry shown in FIGURE 1.

A similar correction is applied to the signal VPOS. The signal S4 (i.e.the signal (ZR - 256) is multiplied by 16 by the concatenation of four logic-zero valued LSBs from a digital value source 630a. This product, the signal P7, is applied to a synchronizing latch 630. The user requested vertical center value, VPOS, is applied to a synchronizing latch 641. The 12-bit output signal of the latch 641 is extended to 13 bits by concatenating a logic-zero in the thirteenth most significant bit position. This 13 bit version of the signal VPOS is designated S10. The signal S10 is added to the signal provided by the latch 630 by an adder 632.

The output signal, S11, of the adder 632 has a value represented by the expression [VPOS + 16 * (ZR - 256)]. If S11 is positive, its value represents an error in the upper bound of the signal VPOS. If S11 is negative or zero there is no error. Accordingly, the signal S11 is limited to be zero or positive by a bank of 13 NAND gates 633 and subtracted from the signal VPOS by an adder 635. The adder 635 is configured in the same way as the adder 616 described above. The output signal S13 provided by the adder 635 is a VPOS signal that is limited to be within its upper bound. The signal VPOS is limited to be within its lower bound (i.e. greater than zero) by a bank of 12 AND gates 636. The output signal provided by the AND gates 636 is applied to a synchronizing latch 637 which provides the fully limited signal VPOS'. This signal is the vertical position signal that is applied to the zoom system shown in FIGURE 1.

The signals HPOS' and VPOS', provided by the circuitry shown in FIGURE 6, are limited to produce a magnified image that is always entirely within the active video region.

FIGURES 7 through 10 illustrate a third embodiment of the present invention. In this system, the horizontal and vertical center positions are adjusted by a microprocessor 712 as incremental changes are requested using the viewer controls 23. The horizontal and vertical center positions are stored and manipulated as eight-bit values. These values are converted into respective 14 and 12 bit starting pixel values, HPOS and VPOS, respectively, which are applied to the zoom system shown in FIGURE 1. Using this method, the value of HPOS is adjusted in increments of three pixels of the source image and the value of VPOS is adjusted in increments of one scan line of the source image. The microprocessor 712 also adjusts the magnification factor by incrementing or decrementing the zoom ratio signal, ZR. The magnification factor is limited to a range between one-to-one and five-to-one. When the signal ZR is adjusted, the horizontal and vertical center positions are reevaluated to determine if further adjustment of these signals is desirable to prevent the display of the blanking intervals.

An assembly language listing of the program which controls the microprocessor 712 is included as an appendix to this specification. The program is written in assembly language for a HD63B01Y0 microprocessor manufactured by Hitachi, Inc.

In FIGURE 7, the viewer control buttons, 51, 52, 55, 56, 58 and 59 are coupled to interface circuitry 710. This circuitry translates the action of the viewer pressing one or more of the buttons into a sequence of commands for a microprocessor 712. In the present embodiment of the invention, the operator control 23 is

a remote control transmitter and The interface 710 is circuitry internal to the remote control transmitter, which generates a sequence of infra-red signals, and circuitry internal to the television receiver, which translates these signals into commands for the microprocessor 712.

The microprocessor 712 interprets these incremental commands to produce signals ZR, HPOS and VPOS for application to the zoom system shown in FIGURE 1. The signals ZR, HPOS and VPOS are stored, by the microprocessor 712, in respective latches 714, 716 and 718 as they are calculated.

FIGURE 8 is a flow-chart diagram of an exemplary main program which is executed by the microprocessor 712 to generate the signals ZR, HPOS and VPOS. In FIGURE 8, commands are received from the interface 710 at step 810. Step 812 determines if the command is an adjustment of the signal ZR. If so, it invokes a zoom routine at step 818. If the command is not a zoom adjustment, step 812 transfers control to step 814 which invokes a horizontal position routine, at step 820, if the command is for a horizontal center position adjustment. If so, the command is neither a zoom change nor a horizontal position change step, control passes to step 816 which determines if the command is a vertical center adjustment. If so, the command 816 invokes a vertical position routine at step 822. If the command was not a vertical center adjustment command, control is transferred to the step 810 to await the next command. After the routines invoked at the steps 818, 820 and 822 have returned control to the main program, the step 810 is executed to await the next command.

FIGURE 9 is a flow-chart diagram of an exemplary horizontal position routine. This routine begins at step 900 which receives the command from the main program. Step 910 tests the type of the received command to determine if it is an increment command or a decrement command. If it is an increment command, step 912 is executed which adds a value of one to an eight-bit horizontal center position variable HC. If the command is a decrement command, step 914 is executed which subtracts a value of one from the variable HC. The steps 912 and 914 both transfer control to a step 916.

The step 916 determines if the value held by the variable HC is less than the quantity ZR/2. If it is, then the left side of the magnified image may include portions of the horizontal blanking interval. To prevent this, step 918 is executed which assigns the value ZR/2 to the variable HC. The next step executed, 920, determines if the value held in the variable HC is greater than 256- ZR/2. If so, the right side of the image may include portions of the horizontal blanking interval. To prevent this, the step 922 is executed which assigns the value 256 - ZR/2 to the variable HC.

The next step, 924, multiplies the value held in HC by 64 and stores the result in a variable HC1. This operation converts the eight-bit HC value into an equivalent 14-bit value. Step 924 also generates a horizontal starting position value from the value HC1 and stores the generated value in a variable HPOS. The algorithm for this conversion is given in the equation (4) set forth above. At step 926, the value HPOS is applied by the microprocessor 712 to the latch 716. The final step, 928, of the routine returns control to the program which invoked the horizontal position routine.

The vertical position routine is the same as the horizontal position routine shown in FIGURE 9 except that the variables VC, VC1 and VPOS replace the variables HC, HC1 and HPOS, the step 924 multiplies VC by 16 instead of 64, and equation (5) is used instead of equation (4) to convert the value held in VC1 to a value to be stored in VPOS.

FIGURE 10 is a flow-chart diagram of a zoom routine suitable for use in this embodiment of the invention. The zoom routine starts at step 1000 which accepts the command from the interface 710. Step 1010 determines if the command requests that the signal ZR be incremented (to reduce the magnification factor) or be decremented (to increase the magnification factor). If ZR is to be incremented, step 1012 is executed, otherwise step 1014 is executed. The next step in the routine, 1016 determines if the value held in the variable ZR is less than 51. This value corresponds to a magnification factor of five-to-one, an arbitrarily established maximum for this embodiment of the invention. If ZR is less than 51, a step 1018 sets ZR to 51. Step 1020 determines if the incremented value held in the variable ZR is greater than 256. This value corresponds to the minimum magnification factor, one-to-one. Step 1022 limits the value held in ZR to 256. After the value held in ZR has been updated, the horizontal position routine is invoked at step 1024 and the vertical position routine is invoked at step 1026 to recalculate the current values of HC and VC using the new value of ZR. These recalculated values for HC and VC ensure that image blanking intervals are not displayed as part of the magnified image. Step 1028 writes the calculated values of ZR, HPOS and VPOS into the registers 714, 716 and 718 and step 1030 returns control to the main program.

```
        CAV SOFTWARE FOR 1989 V2.0 COPYRIGHT THOMSON CONSUMER ELECTRONICS 1989
        PIP CODE SECTION

                        CODE     SECTION

            D4BA        PIPPOS_INIT     EQU     (256*HORRGHT)+VERBOT

                        ;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;
                        ;        HORCHK AND VERCHK ENTER WITH VALUE IN A, IT IS LIMITED, AND THEN
                        ;        STORED IN THE CORRECT PIP POSITION
                        ;
E4FA    7B 40 D0        VERCHK: TIM      ZOOMED,PIPFLG2
E4FD    27 10                   BEQ      ?NOZOOM
E4FF    D6 CC                   LDAB     ZOOM
E501    54                      LSRB
E502    10                      SBA
E503    24 01                   BCC      ?ZOK1
E505    4F                      CLRA
E506    1B              ?ZOK1:  ABA
E507    1B                      ABA
E508    24 02                   BCC      ?ZOK2
E50A    86 FF                   LDAA     #0FFH
E50C    10              ?ZOK2:  SBA
E50D    20 0C                   BRA      ?OK2
                        ;
E50F    81 06           ?NOZOOM:CMPA     #06H
E511    22 02                   BHI      ?OK1
E513    86 06                   LDAA     #06H
E515    81 A0           ?OK1:   CMPA     #0A0H
E517    25 02                   BLO      ?OK2
E519    86 A0                   LDAA     #0A0H
E51B    97 C5           ?OK2:   STAA     VERPOS
E51D    39                      RTS
```

If vertical position is less than $\frac{Zoom}{2}$ then set it to $\frac{Zoom}{2}$.

If vertical position is more than $256 - \frac{Zoom}{2}$ then set to $256 - \frac{Zoom}{2}$

```
                        ;
E51E    7B 40 D0        HORCHK: TIM      ZOOMED,PIPFLG2
E521    27 10                   BEQ      ?NOZOOM
E523    D6 CC                   LDAB     ZOOM
E525    54                      LSRB
E526    10                      SBA
E527    24 01                   BCC      ?ZOK1
E529    4F                      CLRA
E52A    1B              ?ZOK1:  ABA
E52B    1B                      ABA
E52C    24 02                   BCC      ?ZOK2
E52E    86 FF                   LDAA     #0FFH
E530    10              ?ZOK2:  SBA
E531    20 0C                   BRA      ?OK2
                        ;
E533    81 E4           ?NOZOOM:CMPA     #0E4H
E535    25 02                   BLO      ?OK1
E537    86 E4                   LDAA     #0E4H
E539    81 0C           ?OK1:   CMPA     #0CH
E53B    22 02                   BHI      ?OK2
E53D    86 0C                   LDAA     #0CH
E53F    97 C4           ?OK2:   STAA     HORPOS
E541    39                      RTS
                        ;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;
E541                    RIGHT_ARROW:
E542    96 C4                   LDAA     HORPOS
E544    C6 02                   LDAB     #2
```

Same thing for horizontal position

Mon Mar 6 1989 11:11

```
                CAV SOFTWARE FOR 1989 V2.0 COPYRIGHT THOMSON CONSUMER ELECTRONICS 1988
                PIP CODE SECTION

 303  E546  7B 80 5B            TIM     PIPON,PIPFLG            ;IF PIP IS ON
 304  E549  26 41               BNE     HARROW_END              ;THEN GO EXECUTE A MOVE
 305  E54B  7B 10 5D            TIM     KEYRLS,PARSFLG
 306  E54E  27 1E               BEQ     PIP_CON_ENDO
 307  E550  7B 06 DD            TIM     MULTION,PIPFLG2
 308  E553  27 07               BEQ     ?NOMULT                 ;IF IN MULTIPIX MODE
 309  E555  86 0A               LDAA    #CPIPHGRAB
 310  E557  BD E9 C7            JSR     CPIPCON                 ;THEN REPEAT CURRENT COMMAND
 311  E55A  20 12               BRA     PIP_CON_ENDO
 312                         ;                                       (GRAB A FRAME)
 313  E55C  7B 10 DD         ?NOMULT:TIM     DVEON,PIPFLG2
 314  E55F  27 0D               BEQ     PIP_CON_ENDO            ;IF WE ARE IN DVE MODE
 315  E561  96 CB               LDAA    SOLAR
 316  E563  16                  TAB
 317  E564  48                  ASLA                            ;INCREASE LEVEL OF SOLARIZE
 318  E564                    SOLAREND:
 319  E565  C4 40               ANDB    #40H                    ;GET STATE OF VIDEO INVERT IN B
 320  E567  8A 20               ORAA    #20H                    ;ALWAYS LET ONE BIT OF VIDEO THROUGH
 321  E569  84 8F               ANDA    #80FFH-40H
 322  E56B  1B                  ABA
 323  E56C  97 CB               STAA    SOLAR                   ;STORE NEW SOLARIZE MASK
 324  E56C                    PIP_CON_ENDO:
 325  E56E  7E E7 77            JMP     PIP_CON_END
 326                         ;
 327  E571                    LEFT_ARROW:
 328  E571  96 C4               LDAA    HORPOS
 329  E573  C6 FE               LDAB    #-2
 330  E575  7B 80 5B            TIM     PIPON,PIPFLG
 331  E578  26 12               BNE     HARROW_END
 332  E57A  7B 10 5D            TIM     KEYRLS,PARSFLG
 333  E57D  27 EF               BEQ     PIP_CON_ENDO
 334  E57F  7B 10 DD            TIM     DVEON,PIPFLG2
 335  E582  27 EA               BEQ     PIP_CON_ENDO
 336  E584  96 CB               LDAA    SOLAR
 337  E586  16                  TAB
 338  E587  44                  LSRA
 339  E588  8A 40               ORAA    #40H
 340  E58A  20 D9               BRA     SOLAREND
 341                         ;
 342  E58A                    HARROW_END:
 343  E58C  BD 40               BSR     ARROSUB
 344  E58E  BD BE               BSR     HORCHK
 345  E590  20 79               BRA     ARROW_END
 346                         ;
 347  E590                    UP_ARROW:
 348  E592  96 C5               LDAA    VERPOS
 349  E594  C6 FE               LDAB    #-2
 350  E596  20 04               BRA     VARROW_END
 351                         ;
 352  E598                    DOWN_ARROW:
 353  E598  96 C5               LDAA    VERPOS
 354  E59A  C6 02               LDAB    #2
 355  E59A                    VARROW_END:
 356  E59C  7B 18 DD            TIM     DVEON+MULTION,PIPFLG2
 357  E59F  26 07               BNE     ?STROBE
 358  E5A1  BD 2B               BSR     ARROSUB
 359  E5A3  BD E4 FA            JSR     VERCHK
```

Arrow keys change horpos and verpos, then go to limiting routines

CAV SOFTWARE FOR 1989 V2.0 COPYRIGHT THOMSON CONSUMER ELECTRONICS 1989
PIP CODE SECTION

```
E5A6  20 63              BRA   ARROW_END
                 ;
E5A8  7B 10 50  ?STROBE:TIM    KEYRLS,PARSFLG
E5AB  27 1E              BEQ   ?STROB9
E5AD  86 52              LDAA  #SPEEDOSD
E5AF  BD C6 07           JSR   SENDOSD ;SEND COMMAND TO DISPLAY STROBE SPEED
E5B2  50                 NEGB
E5B3  57                 ASRB          ;CHANGE B TO +-1
E5B4  DB CA              ADDB  PIPSPEED
E5B6  2A 01              BPL   ?OK1
E5B8  5F                 CLRB
E5B9  C1 09     ?OK1:    CMPB  #PIPSPEED_TABLEEND-PIPSPEED_TABLE
E5BB  2F 02              BLE   ?OK2
E5BD  C6 09              LDAB  #PIPSPEED_TABLEEND-PIPSPEED_TABLE
E5BF  96 CA     ?OK2:    LDAA  PIPSPEED
E5C1  D7 CA              STAB  PIPSPEED
E5C3  4D                 TSTA
E5C4  26 05              BNE   ?STROB9        ;IF STROBE WAS FROZEN
E5C6  96 C6              LDAA  CPIPSTAT
E5C8  BD E9 C7           JSR   CPIPCON        ;THEN START CPIP UP AGAIN
E5CB  7E CE AA  ?STROB9:JMP    PARSEND
                 ;
E5CE  7B 40 D0  ARROWUB:TIM    ZOOMED,PIPFLG2
E5D1  26 05              BNE   ?ZOOM
E5D3  7B 84 58           TIM   PIPON+FROZEN,PIPFLG
E5D6  27 11              BEQ   ?SKIP          ;IF PIP PIX IS DISPLAYED, OR ZOOM IS ON
E5D8  7B 10 50  ?ZOOM:   TIM   KEYRLS,PARSFLG ;| IF THIS IS NOT THE FIRST ARROW COMMAND
E5DB  26 08              BNE   ?DOIT
E5DD  58                 ASLB                 ;| | DOUBLE THE AMOUNT TO MOVE
E5DE  7D 00 50           TST   PARSFLG        ;| | IF THIS IS NOT THE 5TH ARROW CMD
E5E1  2B 06              BMI   ?SKIP          ;| | THEN SKIP THE MOVE
E5E3  7B 20 57           TIM   CPIPSYS,STAMD1 ;| | IF THIS IS A CPIP SET
E5E6  26 01              BNE   ?SKIP          ;| | THEN SKIP THE MOVE
E5E8  1B        ?DOIT:   ABA                  ;| ENDIF(CHANGE POSITION FOR THIS ARROW)
E5E9  39        ?SKIP:   RTS                  ;ENDIF
                 ;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;
E5E9            MOVE_KEY:
E5EA  7B 84 58           TIM   PIPON+FROZEN,PIPFLG    ;IF PIP IS ON
E5ED  27 26              BEQ   PIP_COM_END1
E5EF  96 C5              LDAA  VERPOS
E5F1  D6 C4              LDAB  HORPOS         ;| GET CURRENT PIX POSITION
E5F3  81 52              CMPA  #52H
E5F5  22 04              BHI   ?RIGHT
E5F7  86 1C              LDAA  #HORLEFT       ;| IF WE WERE IN TOP HALF OF SCREEN
E5F9  20 02              BRA   ?HOREND        ;| THEN SET TO LEFT DEFAULT POSITION
                 ;
E5FB  86 D4     ?RIGHT:  LDAA  #HORRGHT       ;| ELSE SET TO RIGHT DEFAULT
E5FD  97 C4     ?HOREND:STAA   HORPOS         ;| STORE NEW HOR. POSITION
E5FF  C1 5A              CMPB  #5AH           ;| IF WE WERE IN LEFT HALF OF SCREEN
E601  22 04              BHI   ?TOP
E603  86 8A              LDAA  #VERBOT        ;| THEN SET TO BOTTOM DEFAULT POSITION
E605  20 02              BRA   ?VEREND
                 ;
E607  86 1A     ?TOP:    LDAA  #VERTOP        ;| ELSE SET TO TOP DEFUALT POSITION
E609  97 C5     ?VEREND:STAA   VERPOS         ;| STORE NEW VERT. POSITION
E60B            ARROW_END:
E60B  7B 80 58           TIM   PIPON,PIPFLG
```

```
                CAV SOFTWARE FOR 1989 V2.0 COPYRIGHT THOMSON CONSUMER ELECTRONICS 1989
                PIP CODE SECTION

 417  E60E  27 05            BEQ     ?NOPIP
 418  E610  86 02            LDAA    #CPIPMOVST      ;RESET CPIP'S READ ADDR
 419  E612  BD E9 C7         JSR     CPIPCON         ;START UP TASK TO SEND IT
 420  E612                 ?NOPIP:
 421  E612                 PIP_CON_END1:
 422  E615  20 56            BRA     PIP_CON_END2    ;ENDIF
 423                       ;*******************************************************************************
 424  E615                 FREEZE_KEY:
 425  E617  7B 80 47          TIM     DEVON,STATUS
 426  E61A  27 51             BEQ     PIP_CON_END2
 427  E61C  7B 04 58          EIM     FROZEN,PIPFLG   ;CHANGE FROZEN STATUS OF MODULE
 428  E61F  7B 40 57          TIM     CPIPSYS,STAND1
 429  E622  26 34             BNE     ?CPIP           ;IF THIS IS A CPIP SET
 430  E624  7B 10 D0          TIM     DVEON,PIPFLG2
 431  E627  26 44             BNE     PIP_CON_END2    ;| IF MODULE IS IN TVGUIDE OR DVE
 432  E629  7B 40 58          TIM     TVEON,PIPFLG    ;| THEN EXIT
 433  E62C  26 3F             BNE     PIP_CON_END2
 434  E62E  7B 04 58          TIM     FROZEN,PIPFLG
 435  E631  27 13             BEQ     ?MOVE           ;| IF VIDEO IS NOW FROZEN
 436  E633  7B 08 D0          TIM     MULTICH,PIPFLG2
 437  E636  26 35             BNE     PIP_CON_END2    ;| | IF IN MULTIPIX, THEN EXIT
 438  E638  86 12             LDAA    #CPIPSMFRZ      ;| | SET UP TO FREEZE SMALL PIX
 439  E63A  7B 80 58          TIM     PIPON,PIPFLG
 440  E63D  26 02             BNE     ?PIPFRZ         ;| | IF PIP IS NOT ON
 441  E63F  86 14             LDAA    #CPIPBIGFRZ     ;| | THEN FREEZE BIG PIX
 442  E641  BD E9 C7       ?PIPFRZ:JSR     CPIPCON
 443  E644  20 27             BRA     PIP_CON_END2
 444                       ;                       ;| ELSE (VIDEO IS NOW MOVING)
 445  E646  86 03          ?MOVE:  LDAA    #CPIP_SM_UNFRZ
 446  E648  7B 80 58          TIM     PIPON,PIPFLG    ;| | IF PIP IS ON, THEN UNFREEZE THE SMALL PIX
 447  E64B  26 F4             BNE     ?PIPFRZ
 448  E64D  96 C6             LDAA    CPIPSTAT
 449  E64F  7B 08 D0          TIM     MULTICH,PIPFLG2 ;| | IF MULTIPIX IS ON, THEN UNFREEZE MPIX
 450  E652  26 BD             BNE     ?PIPFRZ         ;|
 451  E654  86 01             LDAA    #CPIPRES        ;| | ELSE RESET THE WHOLE MODULE
 452  E656  20 B9             BRA     ?PIPFRZ         ;| ENDIF
 453                       ;                       ;ELSE
 454  E658  7B 80 58       ?CPIP:  TIM     PIPON,PIPFLG
 455  E65B  26 10             BNE     PIP_CON_END2    ;| IF PIP IS NOT ON
 456  E65D  7B 00 84          TST     CURDEV
 457  E660  26 05             BNE     ?NOTTV          ;| | IF TV IS CURDEV
 458  E662  BD D6 64          JSR     TVSWIT          ;| | | SWITCH TO TV
 459  E665  20 03             BRA     ?TV
 460                       ;                       ;| | ELSE
 461  E667  BD B7 0C       ?NOTTV: JSR     DEVSWIT         ;| | | SWITCH THIS DEVICE
 462                       ?TV:                    ;| | ENDIF
 463  E66A  72 06 18          OIM     SELBITS,PORT7   ;| | MAKE SURE MODULE FREEZES THE BIG PIX
 464                       PIP_CON_END2:           ;| ENDIF
 465  E66D  20 2C             BRA     PIP_CON_END3    ;ENDIF
 466                       ;*******************************************************************************
 467  E66F  86 FF          IN_KEY: LDAA    #-1             ;SET UP TO DECREMENT SIZE
 468  E671  20 02             BRA     ZOOMIT          ;CHANGE SIZE
 469                       ;*******************************************************************************
 470  E673  86 01          OUT_KEY:LDAA    #1              ;SET UP TO INCREMENT SIZE
 471                       ;       BRA     ZOOMIT          ;CHANGE SIZE IF WE SHOULD
 472                       ;*********************************
 473                       ;
```

CAV SOFTWARE FOR 1989 V2.0 COPYRIGHT THOMSON CONSUMER ELECTRONICS 1989
PIP CODE SECTION

```
                        ;       ZOOMIT ADDS A TO PIPMULTI IF MPIX OR PIP MODE
                        ;               ADDS A TO ZOOM IF IN NORMAL OR ZOOM MODE
                        ;       ALSO CHECKS FOR LIMITS
                        ;       Z-FLAG SET IF WE DID ON DO ANYTHING
                        ;
E675    7B 10 50        ZOOMIT: TIM     KEYRLS,PARSFLG
E678    27 21                   BEQ     PIP_COM_END3    ;IF THIS IS THE FIRST COMMAND
E67A    7B 08 D0                TIM     MULTION,PIPFLG2
E67D    26 05                   BNE     ?SMSIZE
E67F    7B 80 58                TIM     PIPON,PIPFLG
E682    27 19                   BEQ     ZOOMPIX         ;| IF PIP OR MPIX IS ON
E684    9B C8           ?SMSIZE:ADDA    PIPMULTI
E686    2A 01                   BPL     ?OK1
E688    4F                      CLRA
E689    81 05           ?OK1:   CMPA    #5
E68B    2D 02                   BLT     ?OK2
E68D    86 04                   LDAA    #4
E68F    97 C8           ?OK2:   STAA    PIPMULTI        ;| | SET PIP MULTI TO NEW SIZE VALUE
E691    7B 80 58                TIM     PIPON,PIPFLG
E694    27 61                   BEQ     MPIXEND         ;| | IF WE SET MPIX SIZE, THEN RESTART MPIX
E696    86 07                   LDAA    #PIPZOOMST      ;| | ELSE RESTART PIP
E698    BD E9 C7                JSR     CPIPCOM
E69B                    PIP_COM_END3:
E69B    20 6B                   BRA     PIP_COM_END4
                        ;                               ;| ELSE
E69D    8D 18           ZOOMPIX:BSR     ZOOMSET
E69F    4C                      INCA
E6A0    26 08                   BNE     ?ZOOM           ;| | IF ZOOM IS 1:1
E6A2    71 BF D0                AIM     OFFH.XOR.ZOOMED,PIPFLG2
E6A5    BD E9 80                JSR     PIPSTART        ;| | | RESTART MODULE
E6A8    20 5E                   BRA     PIP_COM_END4
                        ;                               ;| | ELSE
E6AA    72 40 D0        ?ZOOM:  OIM     ZOOMED,PIPFLG2
E6AD    86 16                   LDAA    #CPIPZOOM       ;| | | SHOW ZOOMED VIDEO
E6AF    BD E9 C7                JSR     CPIPCOM
E6B2    86 53                   LDAA    #ZOOMOSD
E6B4    BD C6 07                JSR     SENDOSD         ;| | | SEND ZOOM OSD
E6B7    7E CE AA                JMP     PARSEND         ;| | | SEND KEY RELEASE TO TV
                                                        ;ENDIF ENDIF ENDIF
                        ;
E6BA    D6 CC           ZOOMSET:LDAB    ZOOM
E6BC    7B 40 D0                TIM     ZOOMED,PIPFLG2  ;| | IF ZOOM IS NEW
E6BF    26 08                   BNE     ?NEWZM
E6C1    C6 80                   LDAB    #80H
E6C3    D7 C5                   STAB    VERPOS
E6C5    D7 C4                   STAB    HORPOS          ;| | THEN SET POSITION TO CENTER
E6C7    C6 FF                   LDAB    #OFFH           ;| | AND START AT 1:1
E6C9    1B              ?NEWZM: ABA
E6CA    26 01                   BNE     ?OK3        LIMIT ZOOM TO 10:1
E6CC    4A                      DECA
E6CD    81 19           ?OK3:   CMPA    #25
E6CF    22 02                   BHI     ?OK4
E6D1    86 19                   LDAA    #25
E6D3    97 CC           ?OK4:   STAA    ZOOM            ;| | STORE NEW VALUE OF ZOOM
E6D5    39                      RTS

                        ;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;
E6D5                    MULTI_KEY:
```

```
CAV SOFTWARE FOR 1989 V2.0 COPYRIGHT THOMSON CONSUMER ELECTRONICS 1988
TABLES FOR CPIP

                        ;;
                        ;WRT_OFFSET:
                        ;       DB      0,0,0,0
                        ;       DB      0,0,0,0
                        ;       DB      0,0,0,0
                        ;       DB      0,0,0,0
                        ;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;
                        ;
                        ;       DVEOUTMOD:      ROUTINE TO SET VIDEO MASKS FOR DVE
                        ;
                        ;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;
EBE2                    DVEOUTMOD:
EBE3    FC EB 58                LDD     FFF_OUTMOD
EBE6    DD BC                   STD     DATA_BUFFER
EBE8    FC EB 5A                LDD     FFF_OUTMOD+2
EBEB    DD BE                   STD     DATA_BUFFER+2   ;COPY DEFAULT FULL FIELD EFFECTS
EBED    96 CB                   LDAA    SOLAR
EBEF    16                      TAB
EBF0    94 BD                   ANDA    DATA_BUFFER+1
EBF2    97 BD                   STAA    DATA_BUFFER+1           ;SET C MASK AND INVERT
EBF4    D4 BF                   ANDB    DATA_BUFFER+3
EBF6    D7 BF                   STAB    DATA_BUFFER+3           ;SET Y MASK AND INVERT
EBF8    85 40                   BITA    #40H
EBFA    26 03                   BNE     ?POSVID         ;IF VIDEO IS INVERTED
EBFC    75 3F BE                EIM     #3FH,DATA_BUFFER+2
EBFF    BD ED 6D        ?POSVID:JSR     GETSPEED
EC02    86 0A                   LDAA    #CPIPOVE+1      ;DEFUALT TO LOOP FOR DVE
EC04    5A                      DECB
EC05    27 11                   BEQ     ?FLYING         ;IF STROBE IS ON
EC07    36                      PSHA
EC08    37                      PSHB
EC09    CE EB 84                LDX     #FRZ_INPTIN
EC0C    BD E9 41                JSR     SET_INP_TIN     ;THEN STOP THE WRITES
EC0F    33                      PULB
EC10    32                      PULA
EC11    C1 FE                   CMPB    #OFEH
EC13    26 03                   BNE     ?FLYING         ;IF DVE IS FROZEN
EC15    86 09                   LDAA    #CPIPOVE        ;THEN DON'T GRAB ANY MORE FRAMES
EC17    5F                      CLRB
EC18    D7 C2           ?FLYING:STAB    NEXT_FIELD      ;SET SPEED FOR STROBE
EC1A    97 C6                   STAA    CPIPSTAT
EC1C    39                      RTS
                        ;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;
                        ;
                        ;       ZOOMADR:        SET READ ADDR FOR ZOOM
                        ;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;
EC1D                    ZOOMADR:
EC1D    CE EC 73                LDX     #ZOOM_TABLE
EC20    8D 46                   BSR     PIPKEYS         ;EXECUTE ZOOM OR PAN COMMANDS
EC22    96 C4                   LDAA    HORPOS
EC24    D6 CC                   LDAB    ZOOM
EC26    54                      LSRB
EC27    10                      SBA                     ;CLACULATE LEFT EDGE POSITION
EC28    36                      PSHA
EC29    96 C5                   LDAA    VERPOS
EC2B    10                      SBA                     ;CALCULATE TOP POSITION
EC2C    33                      PULB
```

Mon Mar 6 1989 11:11

```
                CAV SOFTWARE FOR 1989 V2.0 COPYRIGHT THOMSON CONSUMER ELECTRONICS 1988
                TABLES FOR CPIP

 1764  EC2D  54                  LSRB
 1765  EC2E  54                  LSRB
 1766  EC2F  54                  LSRB                    ;CHANGE HORIZONTAL POSITION TO BLOCK COUNT
 1767  EC30  BD BB 7F            JSR     VRAM_ADDR_CALC
 1768  EC33  D6 CC               LDAB    ZOOM
 1769  EC35  E7 C0               STAB    DATA_BUFFER+4   ;PUT ZOOM VALUE IN BUFFER
 1770  EC37  7C 00 C6            INC     CPIPSTAT        ;EXECUTE THIS COMMAND NEXT TIME TOO
 1771  EC3A  39                  RTS
 1772                    ;
 1773  EC3B  FC EB 48    ZOOMTIN:LDD     FILL_OUTTIN
 1774  EC3E  DD BC               STD     DATA_BUFFER
 1775  EC40  FC EB 4A            LDD     FILL_OUTTIN+2
 1776  EC43  DD BE               STD     DATA_BUFFER+2
 1777  EC45  FC EB 4C            LDD     FILL_OUTTIN+4
 1778  EC48  97 C0               STAA    DATA_BUFFER+4
 1779  EC4A  96 C4               LDAA    HORPOS
 1780  EC4C  84 07               ANDA    #07H            ;GET LSB'S OF HORIZONTAL POSITION
 1781  EC4E  48                  ASLA
 1782  EC4F  48                  ASLA                    ;CONVERT FROM 200nS TO 50nS STEPS
 1783  EC50  1B                  ABA                     ;ADD IN DEFAULT VALUE
 1784  EC51  D6 CC               LDAB    ZOOM
 1785  EC53  58                  ASLB
 1786  EC54  1B                  ABA                     ;ADD IN SIZE FOR ZOOM VALUE
 1787  EC55  97 C1               STAA    DATA_BUFFER+5
 1788  EC57  39                  RTS
 1789                    ;
 1790  EC57              ZOOMING_IN:
 1791  EC58  86 FF               LDAA    #-1
 1792  EC5A  20 02               BRA     ZOOMING_END
 1793                    ;
 1794  EC5A              ZOOMING_OUT:
 1795  EC5C  86 01               LDAA    #1
 1796  EC5E              ZOOMING_END:
 1797  EC5E  BD E6 8A            JSR     ZOOMSET
 1798  EC61  86 53               LDAA    #ZOOMCMD
 1799  EC63  BD C6 07            JSR     SENDCMD
 1800  EC66  20 36               BRA     PIPKEYS_END
 1801                    ;
 1802  EC68  7D 00 5D    PIPKEYS:TST     PARSFLG         ;IF WE HAVE GOTTEN FIVE OF THE SAME CHR
 1803  EC6B  2B 05               BMI     ?SKIP
 1804  EC6D  96 85               LDAA    LASTCOM
 1805  EC6F  BD 02 9D            JSR     GENPARSE        ;THEN EXECUTE AN ARROW COMMAND IF NEEDED
 1806  EC72  39          ?SKIP:  RTS
 1807                    ;
 1808  EC73              ZOOM_TABLE:
 1809  EC73  AA                  DB      CZOOMIN
 1810  EC74  EC58                DW      ZOOMING_IN
 1811  EC76  AB                  DB      CZOOMOUT
 1812  EC77  EC5A                DW      ZOOMING_OUT
 1813  EC79              CPIPMOVTAB:
 1814  EC79  A6                  DB      CPIPUP
 1815  EC7A  EC80                DW      ?UP
 1816  EC7C  A7                  DB      CPIPDN
 1817  EC7D  EC8A                DW      ?DOWN
 1818  EC7F  A8                  DB      CPIPRT
 1819  EC80  EC97                DW      ?RIGHT
 1820  EC82  A9                  DB      CPIPLF
```

APPENDIX
Page 29

Mon Mar 6 1989 11:11

```
CAV SOFTWARE FOR 1989 V2.0 COPYRIGHT THOMSON CONSUMER ELECTRONICS 1988
TABLES FOR CPIP

EC83   EC93                DW      ?LEFT
EC85   00                  DB      0
                   ;
EC86   86 FF       ?UP:    LDAA    #-1
EC88   20 02               BRA     ?VEREND
                   ;
EC8A   86 01       ?DOWN:  LDAA    #1
EC8C   9B C5       ?VEREND:ADDA    VERPOS
EC8E   BD E4 FA            JSR     VERCHK
EC91   20 08               BRA     PIPKEYS_END
                   ;
EC93   86 FF       ?LEFT:  LDAA    #-1
EC95   20 02               BRA     ?HOREND
                   ;
EC97   86 01       ?RIGHT: LDAA    #1
EC99   9B C4       ?HOREND:ADDA    HORPOS
EC9B   BD E5 1E            JSR     HORCHK
EC9E               PIPKEYS_END:
EC9E   C6 00               LDAB    #0                     ;SET TO UPDATE LOCATION NEXT FIELD
ECA0   D7 C2               STAB    NEXT_FIELD
ECA2   39                  RTS
                   ;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;
                   ;
                   ;       CPIPLOC:        ROUTINE TO SET READ ADDR FOR CPIP
                   ;                       THIS DETERMINES THE LOCATION OF THE SMALL PIX
                   ;       PRESERVE:
                   ;
                   ;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;
                   ;HORIZONTAL POSITION OF 12 --> READ START =31
                   ;                      228 -->            =12 APPROX.
                   ; H READ = 1.5*(356-HORPOS)/16   11-31
                   ;VERTICAL POSITION OF     6 --> READ START =254
                   ;                       160 -->            =54 APPROX.
                   ; V READ = 1.25*(209-VERPOS) 61-254
ECA2               CPIPLOC:
ECA3   7C 00 C6            INC     CPIPSTAT        ;SET TO EXECUTE PIP POSITION NEXT TIME TOO
ECA6   86 09               LDAA    #9
ECA8   97 C2               STAA    NEXT_FIELD       ;SET TO CHECK POSITION AGAIN IN 9 FIELDS
ECAA   CE EC 79            LDX     #CPIPMOVTAB
ECAD   8D B9               BSR     PIPKEYS         ;EXECUTE MOVE COMMAND IF WE SHOULD
ECAF   BD ED 63            JSR     PIXDATA_GET     ;GET POINTER TO CURRENT PIX SIZE INFO
ECB2   FC EB 48            LDD     PIP_CUTTIN
ECB5   DD BC               STD     DATA_BUFFER
ECB7   FC EB 4A            LDD     PIP_CUTTIN+2
ECBA   DD BE               STD     DATA_BUFFER+2
ECBC   FC EB 4C            LDD     PIP_CUTTIN+4
ECBF   DD C0               STD     DATA_BUFFER+4
                   ; CALCULATE READ POSITION START IN 50nS COUNTS
                   ; 228-HORPOS IS TO MAKE A HIGH HORPOS INTO THE RIGHT SIDE OF SCREEN
                   ; 19(32) IS AN OFFSET TO START WITH FOR A 3x3 PIX
                   ; HORSIZ-HORSIZ 3x3 IS IN PIXELS (100nS) AND CENTERS TO ZOOM COMMANDS
ECC1   96 C4               LDAA    HORPOS
ECC3   40                  NEGA                    ;A= -HORPOS
ECC4   C6 03               LDAB    #3
ECC6   3D                  MUL                     ;D= -3*HORPOS
ECC7   C3 04 6C            ADDD    #(3*228)+(19*32)-160  ;D= 3(228-HORPOS)-19(32)-HOR SIZ OF 3x3
ECCA   36                  PSHA                ;SAVE HIGH ORDER BYTE
```

Claims

1. A video signal processing apparatus having means for producing a magnified image representing a portion of an active video part of a source image, and including means for selecting the portion of the

APPENDIX
Page 29

```
Mon Mar  6 1989 11:11

      CAV SOFTWARE FOR 1989 V2.0 COPYRIGHT THOMSON CONSUMER ELECTRONICS 1988
      TABLES FOR CPIF

EC83  EC93                    DW      ?LEFT
EC85  00                      DB      0
                        ;
EC86  86 FF             ?UP:  LDAA    #-1
EC88  20 02                   BRA     ?VEREND
                        ;
EC8A  86 01             ?DOWN: LDAA   #1
EC8C  9B C3             ?VEREND:ADDA  VERPOS
EC8E  BD E4 FA                JSR     VERCHK
EC91  20 08                   BRA     PIPKEYS_END
                        ;
EC93  86 FF             ?LEFT: LDAA   #-1
EC95  20 02                   BRA     ?HOREND
                        ;
EC97  86 01             ?RIGHT: LDAA  #1
EC99  9B C4             ?HOREND:ADDA  HORPOS
EC9B  BD E5 1E                JSR     HORCHK
EC9E                    PIPKEYS_END:
EC9E  C6 00                   LDAB    #0                  ;SET TO UPDATE LOCATION NEXT FIELD
ECA0  D7 C2                   STAB    NEXT_FIELD
ECA2  39                      RTS
                        ;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;
                        ;
                        ;     CPIPLOC:      ROUTINE TO SET READ ADDR FOR CPIP
                        ;                   THIS DETERMINES THE LOCATION OF THE SMALL PIX
                        ;     PRESERVE:
                        ;
                        ;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;;
                        ;HORIZONTAL POSITION OF 12 --> READ START =31
                        ;                      228 -->           =12 APPROX.
                        ; H READ = 1.5*(356-HORPOS)/16   11-31
                        ;VERTICAL POSITION OF    6 --> READ START =254
                        ;                      160 -->           =54 APPROX.
                        ; V READ = 1.25*(209-VERPOS) 61-254
ECA2                    CPIPLOC:
ECA3  7C 00 CA                INC     CPIPSTAT        ;SET TO EXECUTE PIP POSITION NEXT TIME TOO
ECA6  86 09                   LDAA    #9
ECA8  97 C2                   STAA    NEXT_FIELD      ;SET TO CHECK POSITION AGAIN IN 9 FIELDS
ECAA  CE EC 79                LDX     #CPIPMOVTAB
ECAD  8D B9                   BSR     PIPKEYS         ;EXECUTE MOVE COMMAND IF WE SHOULD
ECAF  BD BD 63                JSR     PIXDATA_GET     ;GET POINTER TO CURRENT PIX SIZE INFO
ECB2  FC EB 48                LDD     PIP_CUTTIN
ECB5  DD BC                   STD     DATA_BUFFER
ECB7  FC EB 4A                LDD     PIP_CUTTIN+2
ECBA  DD BE                   STD     DATA_BUFFER+2
ECBC  FC EB 4C                LDD     PIP_CUTTIN+4
ECBF  DD C0                   STD     DATA_BUFFER+4
                        ; CALCULATE READ POSITION START IN 50nS COUNTS
                        ; 228-HORPOS IS TO MAKE A HIGH HORPOS INTO THE RIGHT SIDE OF SCREEN
                        ; 19(32) IS AN OFFSET TO START WITH FOR A 3x3 PIX
                        ; HORSIZ-HORSIZ 3x3 IS IN PIXELS (100nS) AND CENTERS TO ZOOM COMMANDS
ECC1  96 C4                   LDAA    HORPOS
ECC3  40                      NEGA                    ;A= -HORPOS
ECC4  C6 03                   LDAB    #3
ECC6  3D                      MUL                     ;D= -3*HORPOS
ECC7  C3 04 6C                ADDD    #(3*228)+(19*32)-160  ;D= 3(228-HORPOS)-19(32)-HOR SIZ OF 3x3
ECCA  36                      PSHA            ;SAVE HIGH ORDER BYTE
```

Claims

1. A video signal processing apparatus having means for producing a magnified image representing a portion of an active video part of a source image, and including means for selecting the portion of the

source image to be magnified comprising:

first viewer control means (51-56) for establishing a center point of the selected portion in at least a first coordinate direction;

second viewer control means (58,59) for adjusting a magnification factor for scaling the selected portion to produce said magnified images, characterized by;

means responsive to adjusted magnification factors for generating limit values; and

means (218,223,241-248) responsive to said limit values for adjusting the position of said center point in response to an adjustment of said magnification factor to prevent display of portions of said source image outside of said active video part.

2. The video signal processing apparatus set forth in Claim 1, characterized by, memory means for storing the image from which the magnified portion is selected, memory address means responsive to starting addresses for providing memory addresses for reading the portion of the stored image to be magnified from said memory means, and means for generating horizontal starting addresses comprising;

first means responsive to a user control, for generating a first value representing a magnification factor;

second means responsive to a user control, for generating a second value representing a center coordinate of the selected portion;

means responsive to said first and second values, for generating a third value corresponding to an adjusted center coordinate;

means responsive to said third value, for generating a fourth value corresponding to said horizontal starting address;

means responsive to said first value for generating a horizontal limit value representing maximum horizontal address that may be utilized for the generated magnification factor; and

means responsive to the horizontal limit value and said fourth value, for decreasing said fourth value when said fourth value exceeds said horizontal limit value.

3. The apparatus set forth in Claim 2, characterized in that said second means includes means responsive to the user control for incrementing or decrementing a count value and responsive to a further signal for decrementing said count value, and wherein said means for decreasing said fourth value includes a comparing means, responsive to said fourth value and said horizontal limit value for generating said further signal when said fourth value exceeds said horizontal limit value.

4. The apparatus set forth in Claim 2, characterized in that the means for decreasing the fourth value includes means for adjusting the second and third values.

5. The apparatus set forth in Claim 2, characterized in that the means for decreasing the fourth value includes:

means for generating the difference between the first value and a predetermined constant;

means for generating a product equal to said difference multiplied by a second predetermined constant;

means for combining said product with said fourth value to form a combined value;

means for subtracting said combined value from said fourth value to produce a further difference; and

means for providing as said horizontal starting address a zero value if said further difference has a first predetermined polarity and providing said further difference if said further difference has a polarity opposite said first predetermined polarity.

Patentansprüche

1. Videosignalverarbeitungsgerät mit einer Einrichtung zur Erzeugung eines vergrößerten Bildes als Ausschnitt aus einem aktiven Bildbereich eines Ausgangsbildes und mit einer Einrichtung zur Auswahl des zu vergrößernden Ausschnittes des Ausgangsbildes mit

einem ersten Einstellorgan (51-56) zur Festlegung eines Mittelpunktes des gewählten Ausschnittes in mindestens einer ersten Koordinatenrichtung, und

einem zweiten Einstellorgan (58,59) für einen Vergrößerungsfaktor zur Maßstabsbestimmung des gewählten Ausschnittes für die Erzeugung der vergrößerten Bilder,

* C L M S *

gekennzeichnet durch

eine Grenzwertschaltung, die in Abhängigkeit von den eingestellten Vergrößerungsfaktoren Grenzwerte erzeugt und

eine Mittelpunkteinstellschaltung (218,223,241-248), die in Abhängigkeit von den Grenzwerten die Position des Mittelpunktes auch in Abhängigkeit von einer Vergrößerungsfaktoreinstellung so einstellt, daß außerhalb des aktiven Bildbereichs liegende Teile des Ausgangsbildes nicht dargestellt werden.

2. Videosignalverarbeitungsgerät nach Anspruch 1, **gekennzeichnet durch** einen Speicher für das Bild, aus dem der vergrößerte Ausschnitt ausgewählt wird, eine Speicheradressenschaltung, die unter Steuerung durch Start-Adressen Speicheradressen zum Auslesen des zu vergrößernden Teils des gespeicherten Bildes aus dem Speicher liefert, und durch eine Horizontal-Start-Adressen liefernde Schaltung mit

einer ersten Einrichtung, die unter Benutzersteuerung einen einen Vergrößerungsfaktor darstellenden ersten Wert erzeugt,

einer zweiten Einrichtung, die unter Benutzersteuerung einen eine Mittenkoordinate des ausgewählten Ausschnittes darstellenden zweiten Wert erzeugt,

einer Einrichtung, die in Abhängigkeit vom ersten und zweiten Wert einen einer eingestellten Mittenkoordinate entsprechenden dritten Wert erzeugt,

einer Einrichtung, die in Abhängigkeit von dem dritten Wert einen der Horizontal-Start-Adresse entsprechenden vierten Wert erzeugt,

einer Einrichtung, die in Abhängigkeit von dem ersten Wert einen Horizontalgrenzwert erzeugt, welcher die maximale Horizontaladresse darstellt, die bei dem erzeugten Vergrößerungsfaktor benutzt werden kann, und

einer Einrichtung, die in Abhängigkeit von dem Horizontalgrenzwert und dem vierten Wert den letzteren herabsetzt, wenn er den Horizontalgrenzwert übersteigt.

3. Gerät nach Anspruch 2, **dadurch gekennzeichnet**, daß die zweite Einrichtung eine Einrichtung enthält, die unter Benutzersteuerung einen Zählwert vergrößert oder verkleinert und in Abhängigkeit von einem weiteren Signal den Zählwert verkleinert, und daß die den vierten Wert verkleinernde Einrichtung eine Vergleichsschaltung enthält, die in Abhängigkeit von dem vierten Wert und dem Horizontalgrenzwert das weitere Signal dann erzeugt, wenn der vierte Wert den Horizontalgrenzwert übersteigt.

4. Gerät nach Anspruch 2, **dadurch gekennzeichnet**, daß die den vierten Wert verkleinernde Einrichtung eine Einstelleinrichtung für den zweiten und dritten Wert enthält.

5. Gerät nach Anspruch 2, **dadurch gekennzeichnet**, daß die den vierten Wert verkleinernde Einrichtung enthält:

eine Einrichtung zur Bildung der Differenz zwischen dem ersten Wert und einer vorbestimmten Konstante,

eine Einrichtung zur Erzeugung eines Produktes, das gleich dem Produkt aus der Differenz und einer zweiten vorbestimmten Konstante ist,

eine Einrichtung zur Kombinierung des Produktes mit dem vierten Wert zu einem Kombinationswert,

eine Einrichtung zur Subtrahierung des Kombinationswertes von dem vierten Wert zur Bildung einer weiteren Differenz und

eine Einrichtung zur Lieferung eines Null-Wertes als Horizontal-Start-Adresse, wenn die weitere Differenz eine erste vorbestimmte Polarität hat, und zur Lieferung der weiteren Differenz, wenn diese eine der ersten vorbestimmten Polarität entgegengesetzte Polarität hat.

Revendications

1. Dispositif de traitement de signaux vidéo comportant un moyen pour produire une image agrandie représentant une zone d'une partie vidéo active d'une image source, et comprenant un moyen pour choisir la zone de l'image source à agrandir, comprenant :

un premier moyen de commande de l'observateur (51-56) pour établir un point central de la zone choisie au moins dans une première direction de coordonnée ;

un second moyen de commande de l'observateur (58-59) pour régler le facteur d'agrandissement

* C L M S *

afin de convertir à échelle la zone choisie pour produire lesdites images agrandies, caractérisé par :

un moyen sensible aux facteurs réglés d'agrandissement pour produire des valeurs limites ; et

des moyens (218, 223, 241-248) sensibles auxdites valeurs limites pour régler la position dudit point central en réponse à un ajustement dudit facteur d'agrandissement pour éviter un affichage des zones de ladite image source extérieur à ladite partie vidéo active.

2. Dispositif de traitement de signaux vidéo selon la revendication 1, caractérisé par un moyen de mémoire pour enregistrer l'image à partir de laquelle la zone agrandie est choisie, un moyen d'adresse de mémoire sensible aux adresses de départ afin de fournir des adresses de mémoire pour lire à partir dudit moyen de mémoire la zone à agrandir de l'image enregistrée et un moyen pour produire les adresses de départ horizontales comprenant :

un premier moyen sensible à une commande de l'utilisateur, pour produire une première valeur représentant un facteur d'agrandissement ;

un second moyen sensible à une commande de l'utilisateur pour produire une seconde valeur représentant une coordonnée centrale de la zone sélectionnée ;

un moyen sensible auxdites première et seconde valeurs pour produire une troisième valeur correspondant à une coordonnée centrale ajustée ;

un moyen sensible à ladite troisième valeur pour produire une quatrième valeur correspondant à ladite adresse de départ horizontale ;

un moyen sensible à ladite première valeur pour produire une valeur limite horizontale représentant une adresse horizontale qui peut être utilisée pour le facteur d'agrandissement produit ; et

un moyen sensible à la valeur limite horizontale et à ladite quatrième valeur pour diminuer ladite quatrième valeur lorsque ladite quatrième valeur dépasse ladite valeur limite horizontale.

3. Dispositif selon la revendication 2 caractérisé en ce que ledit second moyen comprend un moyen sensible à la commande de l'utilisateur pour incrémenter ou décrémenter une valeur de comptage et sensible à un autre signal pour décrémenter ladite valeur de comptage et dans lequel le moyen pour diminuer ladite quatrième valeur comprend un moyen de comparaison sensible à ladite quatrième valeur et à ladite valeur limite horizontale pour produire ledit signal supplémentaire lorsque ladite quatrième valeur dépasse ladite valeur limite horizontale.

4. Dispositif selon la revendication 2, caractérisé en ce que le moyen pour diminuer la quatrième valeur comprend un moyen pour ajuster les seconde et troisième valeurs.

5. Dispositif selon la revendication 2, caractérisé en ce que le moyen pour diminuer la quatrième valeur comprend :

un moyen pour générer la différence entre la première valeur et une constante prédéterminée ;

un moyen pour générer un produit égal à ladite différence multipliée par une seconde constante prédéterminée ;

un moyen pour combiner ledit produit avec ladite quatrième valeur pour former une valeur combinée ;

un moyen pour soustraire ladite valeur combinée de ladite quatrième valeur pour produire une différence supplémentaire ; et

un moyen pour fournir comme dite adresse de départ horizontale une valeur de zéro si ladite différence supplémentaire a une première polarité prédéterminée et fournir ladite différence supplémentaire si ladite différence supplémentaire a une polarité opposée à ladite première polarité prédéterminée.