

METHOD AND DEVICE FOR INDICATING TRANSMISSION FRAME STRUCTURE, AND SYSTEM

TECHNICAL FIELD

[0001] The present invention relates to the field of communications technologies,
5 and specifically, to a method and device for indicating a transmission frame structure,
and a system.

BACKGROUND

[0002] With evolution of a wireless local area network (Wireless Local Area
Network, WLAN) standard, a current IEEE (Institute of Electrical and Electronics
10 Engineers, Institute of Electrical and Electronics Engineers) 802.11 working group
starts to research and formulate a next-generation WiFi (Wireless Fidelity, Wireless
Fidelity) standard. The next-generation WiFi standard is referred to as a HEW (High
Efficiency WLAN, high efficiency wireless local area network) for short, and a
project code name is 802.11ax. The next-generation WiFi standard aims to increase a
15 system capacity to more than 10Gbps, and specially concerns an outdoor deployment
scenario of WiFi devices and a high-density deployment scenario of WiFi devices.

[0003] For a high-density distribution scenario, a competitive access mechanism
of conventional WiFi cannot work well due to low efficiency of the competitive
access mechanism, and a new media access mechanism is in urgent need of
20 introduction. Therefore, a multiuser transmission technology with an advantage of
relatively high performance is very likely to be introduced into 11ax. OFDMA
(Orthogonal Frequency Division Multiple Access, orthogonal frequency division
multiplexing) that includes UL (Uplink, uplink) OFMDA and DL (downlink,
downlink) OFMDA may be introduced into 11ax. In addition, UL MU (Multiple User,
25 multi-user) MIMO (Multiple Input Multiple Output, multiple-input multiple-output)
may also be introduced (DL MU MIMO has been introduced into 11ac). The 11ax
should support all transmission modes supported by an existing standard. Actually,
evolution of the WiFi standard always adheres to this idea, which is shown in Table 1.

Table 1

Standard	Supported transmission mode
11a/g	SU
11n	SU, SU MIMO
11ac	SU, SU MIMO, DL MU MIMO
11ax	SU, SU MIMO, DL MU MIMO, UL MU MIMO, UL/DL OFDMA

[0004] It may be seen from Table 1 that, an 11a/g standard supports an SU (Single User, single user) transmission mode, an 11n standard supports the SU transmission mode and an SU MIMO transmission mode, and an 11ac standard supports the SU transmission mode, the SU MIMO transmission mode, and a DL MU MIMO transmission mode. In the prior art, each standard has a particular transmission frame structure. A field in a physical header of a transmission frame is used to indicate a frame structure of the transmission frame.

[0005] It may be seen from Table 1 that, a frame structure of the 11ax standard not only should support the newly-introduced UL/DL OFDMA and UL MU MIMO, but also should support the existing three transmission modes. In addition, the frame structure of the 11ax should also be identified by a HEW device and an existing device as early as possible. That is, the HEW device can identify the frame as an 11ax transmission frame according to a physical header of a transmission frame; or the existing device can determine, according to a physical header of a transmission frame, that the transmission frame is a transmission frame that cannot be understood by the existing device. Therefore, a frame structure of a transmission frame needs to be indicated in a physical header of the transmission frame.

[0006] It is found in practice that, in the prior art, a particular frame structure is used in each standard, and a physical header of the frame structure can indicate only this frame structure. However, with development of a WLAN, more transmission modes need to be supported, and multiple frame structures may be designed in one standard. As a result, the prior art cannot satisfy application. For example, the 11ax standard needs to support more than five transmission modes. It is difficult for one frame structure to satisfy this requirement, that is, at least two frame structures may

need to be designed to separately support different transmission modes. Therefore, a method for indicating multiple different frame structures is in urgent need.

SUMMARY

[0007] Embodiments of the present invention provide a method and device for indicating a transmission frame structure, and a system, which may be used to indicate multiple different transmission frame structures, and may be applied to a HEW into which any one or more of transmission modes in a UL OFMDA transmission mode, a DL OFDMA transmission mode, and a UL MU MIMO transmission mode are introduced.

[0008] A first aspect of the present invention provides a method for indicating a transmission frame structure, where the method is applied to a wireless local area network WLAN, and includes: generating, by a sending device, a transmission frame, where a physical header of the transmission frame includes a frame structure indication field, a subcarrier polarity of the frame structure indication field is used to indicate a frame structure of the transmission frame, where when the subcarrier polarity of the frame structure indication field is a first subcarrier polarity, the transmission frame has a first frame structure, or when the subcarrier polarity of the frame structure indication field is a second subcarrier polarity, the transmission frame has a second frame structure; and sending the transmission frame, so that a receiving device determines the frame structure of the transmission frame according to the subcarrier polarity of the frame structure indication field.

[0009] With reference to the first aspect, in a first possible implementation manner, the frame structure indication field closely follows a legacy signaling field L-SIG, and the generating, by a sending device, a transmission frame includes: generating, by the sending device, a first transmission frame that has the first frame structure, or generating a second transmission frame that has the second frame structure, where in a physical header of the first transmission frame, there is a high efficiency wireless local area network first signaling field HE-SIG-A after an L-SIG and before a high efficiency wireless local area network short training field HE-STF, where the HE-SIG-A includes control indication information, the control indication information is used to instruct the receiving device how to decode all or a part of fields in a part that is of the first transmission frame and after the HE-SIG-A, and the

first transmission frame is used to support a single user SU transmission mode, a single user multiple-input multiple-output SU MIMO transmission mode, and a downlink multi-user multiple-input multiple-output DL MU MIMO transmission mode; in a physical header of the second transmission frame, there is no HE-SIG-A after an L-SIG and before an HE-STF, or there is an HE-SIG-A, but the HE-SIG-A includes only common information, so that decoding can still be performed after HE-SIG-As in second transmission frames sent by multiple sending devices that include the sending device superpose, where the second transmission frame is used to support an uplink orthogonal frequency division multiple access UL OFDMA transmission mode, and the common information includes at least one of the following information: a network identifier, an identifier of the receiving device, or remaining transmission duration.

[0010] With reference to the first possible implementation manner of the first aspect, in a second possible implementation manner, the first transmission frame is further used to support a downlink orthogonal frequency division multiple access DL OFDMA transmission mode, or the second transmission frame is further used to support a DL OFDMA transmission mode.

[0011] With reference to the first or the second possible implementation manner of the first aspect, in a third possible implementation manner, the first transmission frame is further used to support an uplink multi-user multiple-input multiple-output UL MU MIMO transmission mode, or the second transmission frame is further used to support a UL MU MIMO transmission mode.

[0012] With reference to any one of the first to the third possible implementation manners of the first aspect, in a fourth possible implementation manner, a high efficiency wireless local area network second signaling field HE-SIG-B is further included after the HE-SIG-A of the first transmission frame and before the HE-STF of the first transmission frame, where the HE-SIG-B includes control indication information, and the control indication information included in the HE-SIG-B is used to instruct the receiving device how to decode a part that is of the first transmission frame and after the HE-SIG-B.

[0013] With reference to the fourth possible implementation manner of the first aspect, in a fifth possible implementation manner, the HE-SIG-A or the HE-SIG-B of the first transmission frame further includes mode indication information, where the mode indication information is used to indicate a transmission mode specifically

supported by the first transmission frame.

[0014] With reference to the first aspect or any one of the first to the fifth possible implementation manners of the first aspect, in a sixth possible implementation manner, the generating, by a sending device, a transmission frame includes:

- 5 generating, by the sending device, a first transmission frame that has the first frame structure, or generating a second transmission frame that has the second frame structure, where after a frame structure indication field, a physical header of the first transmission frame includes a time domain repetition of a particular field; and a physical header of the second transmission frame includes the particular field, but
10 does not include the time domain repetition of the particular field.

[0015] With reference to the sixth possible implementation manner of the first aspect, in a seventh possible implementation manner, the particular field is an HE-SIG-A.

- [0016]** With reference to any one of the first aspect or the first to the seventh
15 possible implementation manners of the first aspect, in an eighth possible implementation manner, the frame structure indication field closely follows a legacy signaling field L-SIG; and the frame structure indication field in the first frame structure and that in the second frame structure both are RL-SIGs, where the RL-SIG is a time domain repetition of the L-SIG; or the frame structure indication field in the
20 first frame structure is all or a part of OFDM symbols of the HE-SIG-A, and the frame structure indication field in the second frame structure is an RL-SIG, where the RL-SIG is a time domain repetition of the L-SIG; or the frame structure indication field in the first frame structure is all or a part of OFDM symbols of the HE-SIG-A, and the frame structure indication field in the second frame structure is all or a part of
25 OFDM symbols of the HE-SIG-A; or the frame structure indication field in the first frame structure is an RL-SIG, and the frame structure indication field in the second frame structure is all or a part of OFDM symbols of the HE-SIG-A, where the RL-SIG is a time domain repetition of the L-SIG.

- [0017]** With reference to any one of the first aspect or the first to the eighth
30 possible implementation manners of the first aspect, in a ninth possible implementation manner, the first subcarrier polarity means that phases of a first group of subcarriers in multiple subcarriers included in the frame structure indication field are rotated by a first angle, and phases of a second group of subcarriers are rotated by a second angle; and the second subcarrier polarity means that the phases of the first

group of subcarriers in the multiple subcarriers included in the frame structure indication field are rotated by the second angle, and the phases of the second group of subcarriers are rotated by the first angle, where the second angle is greater than the first angle, and the first angle is greater than or equal to 0 degree; or the first subcarrier polarity means that a first group of subcarriers in multiple subcarriers included in the frame structure indication field are filled, and a second group of subcarriers are vacant; and the second subcarrier polarity means that the first group of subcarriers in the multiple subcarriers included in the frame structure indication field are vacant, and the second group of subcarriers are filled; or the first subcarrier polarity means that phases of all subcarriers included in the frame structure indication field are rotated by a third angle, and the second subcarrier polarity means that the phases of all the subcarriers included in the frame structure indication field are rotated by a fourth angle, where the fourth angle is greater than the third angle, and the third angle is greater than 0 degree.

[0018] A second aspect of the present invention provides a method for indicating a transmission frame structure, where the method is applied to a wireless local area network WLAN, and includes: receiving, by a receiving device, a physical header of a transmission frame sent by a sending device, where the physical header of the transmission frame includes a frame structure indication field, and a subcarrier polarity of the frame structure indication field is used to indicate a frame structure of the transmission frame; and determining the frame structure of the transmission frame according to the subcarrier polarity of the frame structure indication field, where when the subcarrier polarity of the frame structure indication field is a first subcarrier polarity, the transmission frame has a first frame structure, or when the subcarrier polarity of the frame structure indication field is a second subcarrier polarity, the transmission frame has a second frame structure.

[0019] With reference to the second aspect, in a first possible implementation manner, the frame structure indication field closely follows a legacy signaling field L-SIG, and the receiving, by a receiving device, a physical header of a transmission frame sent by a sending device includes: receiving, by the receiving device, a physical header of a first transmission frame that is sent by the sending device and has the first frame structure or a physical header of a second transmission frame that is sent by the sending device and has the second frame structure, where in the physical header of the first transmission frame, there is a high efficiency wireless local area network first

signaling field HE-SIG-A after an L-SIG and before a high efficiency wireless local area network short training field HE-STF, where the HE-SIG-A includes control indication information, the control indication information is used to instruct the receiving device how to decode all or a part of fields in a part that is of the first transmission frame and after the HE-SIG-A, and the first transmission frame is used to support a single user SU transmission mode, a single user multiple-input multiple-output SU MIMO transmission mode, and downlink multi-user multiple-input multiple-output DL MU MIMO; in the physical header of the second transmission frame, there is no HE-SIG-A after an L-SIG and before an HE-STF, or there is an HE-SIG-A, but the HE-SIG-A includes only common information, so that decoding can still be performed after HE-SIG-As in second transmission frames sent by multiple sending devices superpose, where the second transmission frame is used to support an uplink orthogonal frequency division multiple access UL OFDMA transmission mode, and the common information includes at least one of the following information: a network identifier, an identifier of the receiving device, or remaining transmission duration.

[0020] With reference to the first possible implementation manner of the second aspect, in a second possible implementation manner, the first transmission frame is further used to support a downlink orthogonal frequency division multiple access DL OFDMA transmission mode, or the second transmission frame is further used to support a DL OFDMA transmission mode.

[0021] With reference to the first or the second possible implementation manner of the second aspect, in a third possible implementation manner, the first transmission frame is further used to support an uplink multi-user multiple-input multiple-output UL MU MIMO transmission mode, or the second transmission frame is further used to support a UL MU MIMO transmission mode.

[0022] With reference to any one of the first to the third possible implementation manners of the second aspect, in a fourth possible implementation manner, a high efficiency wireless local area network second signaling field HE-SIG-B is further included after the HE-SIG-A of the first transmission frame and before the HE-STF of the first transmission frame, where the HE-SIG-B includes control indication information, and the control indication information included in the HE-SIG-B is used to instruct the receiving device how to decode a part that is of the first transmission frame and after the HE-SIG-B.

[0023] With reference to the fourth possible implementation manner of the second aspect, in a fifth possible implementation manner, the HE-SIG-A or the HE-SIG-B of the first transmission frame further includes mode indication information, and the method further includes: determining, according to the mode indication information, a transmission mode specifically supported by the frame structure of the first transmission frame.

[0024] With reference to the second aspect or any one of the first to the fifth possible implementation manners of the second aspect, in a sixth possible implementation manner, the receiving, by a receiving device, a physical header of a transmission frame sent by a sending device includes: receiving, by the receiving device, a physical header of a first transmission frame that is sent by the sending device and has the first frame structure or a physical header of a second transmission frame that is sent by the sending device and has the second frame structure, where after a frame structure indication field, the physical header of the first transmission frame includes a time domain repetition of a particular field; and the physical header of the second transmission frame includes the particular field, but does not include the time domain repetition of the particular field.

[0025] With reference to the sixth possible implementation manner of the second aspect, in a seventh possible implementation manner, the particular field is an HE-SIG-A.

[0026] With reference to any one of the second aspect or the first to the seventh possible implementation manners of the second aspect, in an eighth possible implementation manner, the frame structure indication field closely follows a legacy signaling field L-SIG; and the frame structure indication field in the first frame structure and that in the second frame structure both are RL-SIGs, where the RL-SIG is a time domain repetition of the L-SIG; or the frame structure indication field in the first frame structure is all or a part of OFDM symbols of the HE-SIG-A, and the frame structure indication field in the second frame structure is an RL-SIG, where the RL-SIG is a time domain repetition of the L-SIG; or the frame structure indication field in the first frame structure is all or a part of OFDM symbols of the HE-SIG-A, and the frame structure indication field in the second frame structure is all or a part of OFDM symbols of the HE-SIG-A; or the frame structure indication field in the first frame structure is an RL-SIG, and the frame structure indication field in the second frame structure is all or a part of OFDM symbols of the HE-SIG-A, where the

RL-SIG is a time domain repetition of the L-SIG.

[0027] With reference to any one of the second aspect or the first to the eighth possible implementation manners of the second aspect, in a ninth possible implementation manner, the first subcarrier polarity means that phases of a first group of subcarriers in multiple subcarriers included in the frame structure indication field are rotated by a first angle, and phases of a second group of subcarriers are rotated by a second angle; and the second subcarrier polarity means that the phases of the first group of subcarriers in the multiple subcarriers included in the frame structure indication field are rotated by the second angle, and the phases of the second group of subcarriers are rotated by the first angle, where the second angle is greater than the first angle, and the first angle is greater than or equal to 0 degree; or the first subcarrier polarity means that a first group of subcarriers in multiple subcarriers included in the frame structure indication field are filled, and a second group of subcarriers are vacant; and the second subcarrier polarity means that the first group of subcarriers in the multiple subcarriers included in the frame structure indication field are vacant, and the second group of subcarriers are filled; or the first subcarrier polarity means that phases of all subcarriers included in the frame structure indication field are rotated by a third angle, and the second subcarrier polarity means that phases of all the subcarriers included in the frame structure indication field are rotated by a fourth angle, where the fourth angle is greater than the third angle, and the third angle is greater than 0 degree.

[0028] A third aspect of the present invention provides a sending device for indicating a transmission frame structure, where the sending device is applied to a wireless local area network WLAN, and includes: a generation module, configured to generate a transmission frame, where a physical header of the transmission frame includes a frame structure indication field, and a subcarrier polarity of the frame structure indication field is used to indicate a frame structure of the transmission frame, where when the subcarrier polarity of the frame structure indication field is a first subcarrier polarity, the transmission frame has a first frame structure, or when the subcarrier polarity of the frame structure indication field is a second subcarrier polarity, the transmission frame has a second frame structure; and a sending module, configured to send the transmission frame, so that a receiving device determines the frame structure of the transmission frame according to the subcarrier polarity of the frame structure indication field.

[0029] With reference to the third aspect, in a first possible implementation manner, the frame structure indication field closely follows a legacy signaling field L-SIG, and the generation module is specifically configured to generate a first transmission frame that has the first frame structure, or generate a second transmission frame that has the second frame structure, where in a physical header of the first transmission frame, there is a high efficiency wireless local area network first signaling field HE-SIG-A after an L-SIG and before a high efficiency wireless local area network short training field HE-STF, where the HE-SIG-A includes control indication information, the control indication information is used to instruct the receiving device how to decode all or a part of fields in a part that is of the first transmission frame and after the HE-SIG-A, and the first transmission frame is used to support a single user SU transmission mode, a single user multiple-input multiple-output SU MIMO transmission mode, and a downlink multi-user multiple-input multiple-output DL MU MIMO transmission mode; in a physical header of the second transmission frame, there is no HE-SIG-A after an L-SIG and before an HE-STF, or there is an HE-SIG-A, but the HE-SIG-A includes only common information, so that decoding can still be performed after HE-SIG-As in second transmission frames sent by multiple sending devices that include the sending device superpose, where the second transmission frame is used to support an uplink orthogonal frequency division multiple access UL OFDMA transmission mode, and the common information includes at least one of the following information: a network identifier, an identifier of the receiving device, or remaining transmission duration.

[0030] With reference to the first possible implementation manner of the third aspect, in a second possible implementation manner, the first transmission frame is further used to support a downlink orthogonal frequency division multiple access DL OFDMA transmission mode, or the second transmission frame is further used to support a DL OFDMA transmission mode.

[0031] With reference to the first or the second possible implementation manner of the third aspect, in a third possible implementation manner, the first transmission frame is further used to support an uplink multi-user multiple-input multiple-output UL MU MIMO transmission mode, or the second transmission frame is further used to support a UL MU MIMO transmission mode.

[0032] With reference to any one of the first to the third possible implementation manners of the third aspect, in a fourth possible implementation manner, a high

efficiency wireless local area network second signaling field HE-SIG-B is further included after the HE-SIG-A of the first transmission frame and before the HE-STF of the first transmission frame, where the HE-SIG-B includes control indication information, and the control indication information included in the HE-SIG-B is used to instruct the receiving device how to decode a part that is of the first transmission frame and after the HE-SIG-B.

[0033] With reference to the fourth possible implementation manner of the third aspect, in a fifth possible implementation manner, the HE-SIG-A or the HE-SIG-B of the first transmission frame further includes mode indication information, where the mode indication information is used to indicate a transmission mode specifically supported by the first transmission frame.

[0034] With reference to the third aspect or any one of the first to the fifth possible implementation manners of the third aspect, in a sixth possible implementation manner, the generation module is specifically configured to generate a first transmission frame that has the first frame structure, or generate a second transmission frame that has the second frame structure, where after a frame structure indication field, a physical header of the first transmission frame includes a time domain repetition of a particular field; and a physical header of the second transmission frame includes the particular field, but does not include the time domain repetition of the particular field.

[0035] With reference to the sixth possible implementation manner of the third aspect, in a seventh possible implementation manner, the particular field is an HE-SIG-A.

[0036] With reference to any one of the third aspect or the first to the seventh possible implementation manners of the third aspect, in an eighth possible implementation manner, the frame structure indication field closely follows a legacy signaling field L-SIG; and the frame structure indication field in the first frame structure and that in the second frame structure both are RL-SIGs, where the RL-SIG is a time domain repetition of the L-SIG; or the frame structure indication field in the first frame structure is all or a part of OFDM symbols of the HE-SIG-A, and the frame structure indication field in the second frame structure is an RL-SIG, where the RL-SIG is a time domain repetition of the L-SIG; or the frame structure indication field in the first frame structure is all or a part of OFDM symbols of the HE-SIG-A, and the frame structure indication field in the second frame structure is all or a part of

OFDM symbols of the HE-SIG-A; or the frame structure indication field in the first frame structure is an RL-SIG, and the frame structure indication field in the second frame structure is all or a part of OFDM symbols of the HE-SIG-A, where the RL-SIG is a time domain repetition of the L-SIG.

- 5 **[0037]** With reference to any one of the third aspect or the first to the eighth possible implementation manners of the third aspect, in a ninth possible implementation manner, the first subcarrier polarity means that phases of a first group of subcarriers in multiple subcarriers included in the frame structure indication field are rotated by a first angle, and phases of a second group of subcarriers are rotated by
10 a second angle; and the second subcarrier polarity means that the phases of the first group of subcarriers in the multiple subcarriers included in the frame structure indication field are rotated by the second angle, and the phases of the second group of subcarriers are rotated by the first angle, where the second angle is greater than the first angle, and the first angle is greater than or equal to 0 degree; or the first
15 subcarrier polarity means that a first group of subcarriers in multiple subcarriers included in the frame structure indication field are filled, and a second group of subcarriers are vacant; and the second subcarrier polarity means that the first group of subcarriers in the multiple subcarriers included in the frame structure indication field are vacant, and the second group of subcarriers are filled; or the first subcarrier
20 polarity means that phases of all subcarriers included in the frame structure indication field are rotated by a third angle, and the second subcarrier polarity means that the phases of all the subcarriers included in the frame structure indication field are rotated by a fourth angle, where the fourth angle is greater than the third angle, and the third angle is greater than 0 degree.
- 25 **[0038]** A fourth aspect of the present invention provides a receiving device for indicating a transmission frame structure, where the receiving device is applied to a wireless local area network WLAN, and includes: a receiving module, configured to receive a physical header of a transmission frame sent by a sending device, where the physical header of the transmission frame includes a frame structure indication field,
30 and a subcarrier polarity of the frame structure indication field is used to indicate a frame structure of the transmission frame; and a determining module, configured to determine the frame structure of the transmission frame according to the subcarrier polarity of the frame structure indication field, where when the subcarrier polarity of the frame structure indication field is a first subcarrier polarity, the transmission frame

has a first frame structure, or when the subcarrier polarity of the frame structure indication field is a second subcarrier polarity, the transmission frame has a second frame structure.

[0039] With reference to the fourth aspect, in a first possible implementation manner, the frame structure indication field closely follows a legacy signaling field L-SIG, and the receiving module is specifically configured to receive a physical header of a first transmission frame that is sent by the sending device and has the first frame structure or a physical header of a second transmission frame that is sent by the sending device and has the second frame structure, where in the physical header of the first transmission frame, there is a high efficiency wireless local area network first signaling field HE-SIG-A after an L-SIG and before a high efficiency wireless local area network short training field HE-STF, where the HE-SIG-A includes control indication information, the control indication information is used to instruct the receiving device how to decode all or a part of fields in a part that is of the first transmission frame and after the HE-SIG-A, and the first transmission frame is used to support a single user SU transmission mode, a single user multiple-input multiple-output SU MIMO transmission mode, and downlink multi-user multiple-input multiple-output DL MU MIMO; in the physical header of the second transmission frame, there is no HE-SIG-A after an L-SIG and before an HE-STF, or there is an HE-SIG-A, but the HE-SIG-A includes only common information, so that decoding can still be performed after HE-SIG-As in second transmission frames sent by multiple sending devices superpose, where the second transmission frame is used to support an uplink orthogonal frequency division multiple access UL OFDMA transmission mode, and the common information includes at least one of the following information: a network identifier, an identifier of the receiving device, or remaining transmission duration.

[0040] With reference to the first possible implementation manner of the fourth aspect, in a second possible implementation manner, the first transmission frame is further used to support a downlink orthogonal frequency division multiple access DL OFDMA transmission mode, or the second transmission frame is further used to support a DL OFDMA transmission mode.

[0041] With reference to the first or the second possible implementation manner of the fourth aspect, in a third possible implementation manner, the first transmission frame is further used to support an uplink multi-user multiple-input multiple-output

UL MU MIMO transmission mode, or the second transmission frame is further used to support a UL MU MIMO transmission mode.

[0042] With reference to any one of the first to the third possible implementation manners of the fourth aspect, in a fourth possible implementation manner, a high efficiency wireless local area network second signaling field HE-SIG-B is further included after the HE-SIG-A of the first transmission frame and before the HE-STF of the first transmission frame, where the HE-SIG-B includes control indication information, and the control indication information included in the HE-SIG-B is used to instruct the receiving device how to decode a part that is of the first transmission frame and after the HE-SIG-B.

[0043] With reference to the fourth possible implementation manner of the fourth aspect, in a fifth possible implementation manner, the HE-SIG-A or the HE-SIG-B of the first transmission frame further includes mode indication information, and the determining module is further configured to determine, according to the mode indication information, a transmission mode specifically supported by the frame structure of the first transmission frame.

[0044] With reference to the fourth aspect or any one of the first to the fifth possible implementation manners of the fourth aspect, in a sixth possible implementation manner, the receiving module is specifically configured to receive a physical header of a first transmission frame that is sent by the sending device and has the first frame structure or a physical header of a second transmission frame that is sent by the sending device and has the second frame structure, where after a frame structure indication field, the physical header of the first transmission frame includes a time domain repetition of a particular field; and the physical header of the second transmission frame includes the particular field, but does not include the time domain repetition of the particular field.

[0045] With reference to the sixth possible implementation manner of the fourth aspect, in a seventh possible implementation manner, the particular field is an HE-SIG-A.

[0046] With reference to any one of the fourth aspect or the first to the seventh possible implementation manners of the fourth aspect, in an eighth possible implementation manner, the frame structure indication field closely follows a legacy signaling field L-SIG; and the frame structure indication field in the first frame structure and that in the second frame structure both are RL-SIGs, where the RL-SIG

is a time domain repetition of the L-SIG; or the frame structure indication field in the first frame structure is all or a part of OFDM symbols of the HE-SIG-A, and the frame structure indication field in the second frame structure is an RL-SIG, where the RL-SIG is a time domain repetition of the L-SIG; or the frame structure indication field in the first frame structure is all or a part of OFDM symbols of the HE-SIG-A, and the frame structure indication field in the second frame structure is all or a part of OFDM symbols of the HE-SIG-A; or the frame structure indication field in the first frame structure is an RL-SIG, and the frame structure indication field in the second frame structure is all or a part of OFDM symbols of the HE-SIG-A, where the RL-SIG is a time domain repetition of the L-SIG.

[0047] With reference to any one of the fourth aspect or the first to the eighth possible implementation manners of the fourth aspect, in a ninth possible implementation manner, the first subcarrier polarity means that phases of a first group of subcarriers in multiple subcarriers included in the frame structure indication field are rotated by a first angle, and phases of a second group of subcarriers are rotated by a second angle; and the second subcarrier polarity means that the phases of the first group of subcarriers in the multiple subcarriers included in the frame structure indication field are rotated by the second angle, and the phases of the second group of subcarriers are rotated by the first angle, where the second angle is greater than the first angle, and the first angle is greater than or equal to 0 degree; or the first subcarrier polarity means that a first group of subcarriers in multiple subcarriers included in the frame structure indication field are filled, and a second group of subcarriers are vacant; and the second subcarrier polarity means that the first group of subcarriers in the multiple subcarriers included in the frame structure indication field are vacant, and the second group of subcarriers are filled; or the first subcarrier polarity means that phases of all subcarriers included in the frame structure indication field are rotated by a third angle, and the second subcarrier polarity means that the phases of all the subcarriers included in the frame structure indication field are rotated by a fourth angle, where the fourth angle is greater than the third angle, and the third angle is greater than 0 degree.

[0048] A fifth aspect of the present invention provides a communications system, where the communications system includes: the sending device according to the third aspect of the present invention or the first to the fifth possible implementation manners of the third aspect, and the receiving device according to the fourth aspect of

the present invention or the first to the fifth possible implementation manners of the fourth aspect; or the communications system includes: the sending device according to the sixth or the seventh possible implementation manner of the third aspect of the present invention, and the receiving device according to the sixth or the seventh possible implementation manner of the fourth aspect of the present invention.

[0049] It may be seen from the foregoing that, according to the embodiments of the present invention, in a technical solution, a subcarrier polarity of a frame structure indication field in a physical header of a transmission frame is used to indicate different frame structures, so as to obtain the following technical effects:

[0050] Because a subcarrier polarity may have more expression manners, and may be used to indicate more frame structures, design of multiple frame structures in a WLAN standard is supported, so as to satisfy a requirement that a HEW needs to support more transmission modes, support more frame structures, and indicate more frame structures.

BRIEF DESCRIPTION OF DRAWINGS

[0051] To describe the technical solutions in the embodiments of the present invention more clearly, the following briefly introduces the accompanying drawings required for describing the embodiments and the prior art. Apparently, the accompanying drawings in the following description show merely some embodiments of the present invention, and a person of ordinary skill in the art may still derive other drawings from these accompanying drawings without creative efforts.

[0052] FIG. 1(a) to FIG. 1(c) are schematic diagrams of transmission frame structures in existing standards 11a/g, 11n, and 11ac;

[0053] FIG. 2 is a schematic diagram of a BPSK constellation and a QBPSK constellation;

[0054] FIG. 3 is a schematic diagram of a method for indicating a transmission frame structure according to an embodiment of the present invention;

[0055] FIG. 4(a) and FIG. 4(b) are schematic diagrams of two frame structures according to some embodiments of the present invention;

[0056] FIG. 4(c) is a schematic structural diagram of a first transmission frame according to some other embodiments of the present invention;

[0057] FIG. 5(a) and FIG. 5(b) are schematic diagrams of two implementation

manners of DL OFDMA;

[0058] FIG. 6 is a schematic diagram of another method for indicating a transmission frame structure according to an embodiment of the present invention;

5 **[0059]** FIG. 7 is a schematic structural diagram of a sending device according to an embodiment of the present invention;

[0060] FIG. 8 is a schematic structural diagram of a receiving device according to an embodiment of the present invention;

[0061] FIG. 9 is a schematic architectural diagram of a communications system according to an embodiment of the present invention;

10 **[0062]** FIG. 10 is a schematic diagram of a subcarrier polarity expression method according to an embodiment of the present invention;

[0063] FIG. 11 is a schematic structural diagram of another sending device according to an embodiment of the present invention; and

[0064] FIG. 12 is a schematic structural diagram of another receiving device
15 according to an embodiment of the present invention.

DESCRIPTION OF EMBODIMENTS

[0065] Embodiments of the present invention provide a method and device for indicating a transmission frame structure, and a system, which may be used to indicate multiple different transmission frame structures, and may be applied to a
20 HEW into which any one or more of transmission modes in a UL OFMDA transmission mode, a DL OFDMA transmission mode, and a UL MU MIMO transmission mode are introduced.

[0066] To make a person skilled in the art understand the technical solutions in the present invention better, the following clearly and completely describes the technical
25 solutions in the embodiments of the present invention with reference to the accompanying drawings in the embodiments of the present invention. Apparently, the described embodiments are merely some rather than all of the embodiments of the present invention. All other embodiments obtained by a person of ordinary skill in the art based on the embodiments of the present invention without creative efforts shall
30 fall within the protection scope of the present invention.

[0067] First, a method for indicating a transmission frame structure in the prior art is briefly described.

[0068] In the prior art, each standard has a particular transmission frame structure. For example, transmission frame structures in existing standards 11a/g, 11n, and 11ac are respectively shown in FIG. 1(a), FIG. 1(b), and FIG. 1(c). In 11n and 11ac frame structures, an L (Legacy, legacy)-STF (Short Training Field, short training field), an L-LTF (Long Training Field, long training field), and an L-SIG (Signal, signaling field) are collectively referred to as an L-preamble (legacy pilot), and the L-preamble is for backward compatibility. That is, when an 11a/g third-party STA (Station, station) receives an 11n/11ac transmission frame, even though the third-party STA cannot understand subsequent transmission content, the third-party STA can still obtain transmission duration of the entire transmission frame by calculating according to content of the L-SIG, and then can choose to enter a sleep state, thereby reaching a power saving objective. Certainly, when an 11n device receives an 11ac transmission frame, the L-preamble can provide a same function. It should be noted that, Data (data field) in the 11n/11ac frame structure has a same structure as a data field in the 11a/g frame structure. All SIG fields in a frame structure are modulated by using BPSK (Binary Phase Shift Keying, binary phase shift keying) or QPSK (Quadrature Binary Phase Shift Keying, quadrature binary phase shift keying).

[0069] A length of an OFDM (Orthogonal Frequency Division Multiplexing, orthogonal frequency division multiplexing) symbol in an existing standard is 4 us. Therefore, an HT (High Throughput, high throughput)-SIG in FIG. 1 actually includes two symbols: an HT-SIG1 and an HT-SIG2. Likewise, a VHT (Very High Throughput, very high throughput)-SIG-A includes a VHT-SIG-A1 and a VHT-SIG-A2.

[0070] In the existing standard, different transmission frame structures are indicated by means of different subcarrier phase rotation of the first and the second OFDM symbols that closely follow an L-SIG.

[0071] In the 11a/g standard, the first and the second OFDM symbols that closely follow the L-SIG are first two symbols of the data field. In the 11n standard, the first and the second OFDM symbols that closely follow the L-SIG are the HT-SIG1 and the HT-SIG2. In the 11ac standard, the first and the second OFDM symbols that closely follow the L-SIG are the VHT-SIG-A1 and the VHT-SIG-A2.

Table 2

	First OFDM symbol	Second OFDM symbol
11a/g	BPSK, QPSK, 16QAM, 64QAM	BPSK, QPSK, 16QAM, 64QAM
11n	QBPSK	BPSK
11ac	BPSK	QBPSK

[0072] According to the existing standard, in a bandwidth of 20 MHz, the first and the second symbols after the L-SIG each include 48 data subcarriers and four pilot subcarriers. In a current 802.11 standard, subcarrier phase rotation generally means that a phase of a data subcarrier is rotated in a counterclockwise direction. In other words, a modulation constellation diagram is rotated in a counterclockwise direction. If the phase is rotated by 90 degrees, a BPSK constellation changes into a QBPSK constellation, which is shown in FIG. 2. A horizontal axis is an I (Inphase, inphase) component, and a vertical axis is a Q (Quadrature, quadrature) component.

[0073] Referring to Table 2, when an 11n device receives a transmission frame, if QBPSK is used in the first OFDM symbol of the frame, the 11n device decodes a subsequent part according to the 11n frame structure; or if any modulation manner except QBPSK is used in the first OFDM symbol of the frame, the 11n device performs decoding according to the 11a/g frame structure (all existing standards are backward-compatible). Likewise, when an 11ac device receives a transmission frame, if QBPSK is used in the first symbol of the frame, the 11ac device decodes a subsequent part according to the 11n frame structure; or if BPSK is used in the first symbol, and QBPSK is used in the second symbol, the 11ac device decodes a subsequent part according to the 11ac frame structure; or in any case except the foregoing two cases, the 11ac device performs decoding according to the 11a/g frame structure. Optionally, the device may directly discard a frame structure that cannot be identified by the device.

[0074] It may be seen from the foregoing that, in a successive standard of 802.11n, the first and the second symbols for indicating a frame structure, for example, an HT-SIG1 and an HT-SIG2, or a VHT-SIG-A1 and a VHT-SIG-A2, both include control information used to decode a data field, for example, an MCS (Modulation and Coding Scheme, modulation and coding scheme). A receive end may

determine, according to the control information, how to decode a subsequent part of a frame. Control information in 802.11a/g is in an L-SIG. An 802.11n or 802.11ac device performs detection on two symbols after an L-SIG in a received transmission frame, that is, first two symbols of a data field, to identify whether the transmission frame is a legacy transmission frame. Therefore, the foregoing solution is applicable to only a scenario in which one device performs sending, and one or more devices perform receiving. If multiple devices perform sending, and one device performs receiving, content of the first symbols and the second symbols of transmission frames sent by the multiple devices randomly superpose, and therefore, the receiving device cannot correctly receive and parse the transmission frames. Therefore, the existing foregoing solution is not applicable to a case in which multiple devices perform sending, and one device performs receiving, that is, not applicable to UL MU transmission that is to be introduced into a HEW, such as UL OFMDA/UL MU MIMO.

[0075] In addition, in the prior art, a particular frame structure is used in each standard, and a physical header of the frame structure can indicate only this frame structure. However, with development of a WLAN, more transmission modes need to be supported, and multiple frame structures may be designed in one standard. As a result, the prior art cannot satisfy application. For example, the 11ax standard needs to support more than five transmission modes. It is difficult for one frame structure to satisfy this requirement, that is, at least two frame structures may need to be designed to separately support different transmission modes. However, in the prior art, a physical header of a transmission frame can indicate only one frame structure, which cannot satisfy a requirement for indicating multiple frame structures.

[0076] In conclusion, an existing frame structure indication technology is not applicable to a HEW into which any one or more of transmission modes in a UL OFMDA transmission mode, a DL OFDMA transmission mode, a UL MU MIMO transmission mode, and the like are introduced.

[0077] For the foregoing problem, embodiments of the present invention provide a method and a corresponding device for indicating a transmission frame structure, and a system that are applicable to a HEW. The following provides detailed descriptions separately by using specific embodiments.

Embodiment 1

[0078] Referring to FIG. 3, this embodiment of the present invention provides a method for indicating a transmission frame structure. The method is applied to a WLAN, and is particularly applied to a HEW. The method may include the following steps:

[0079] 301. A sending device generates a transmission frame.

[0080] In this embodiment of the present invention, the sending device generates the transmission frame, where a physical header of the transmission frame includes a frame structure indication field, and a subcarrier polarity of the frame structure indication field is used to indicate a frame structure of the transmission frame.

[0081] Optionally, the frame structure indication field may include at least one OFDM (orthogonal frequency division multiplexing) symbol, and may closely follow an L-SIG in the physical header.

[0082] In this specification, various frames and various fields in a frame, such as a transmission frame or a frame structure indication field in a transmission frame, is merely under exemplary names, and may also be given other names, provided that a frame or field under other names has a same or similar function.

[0083] 302. Send the transmission frame, so that a receiving device determines a frame structure of the transmission frame according to the subcarrier polarity of the frame structure indication field.

[0084] In this embodiment of the present invention, the transmission frame is sent to the receiving device. Therefore, after receiving the physical header of the transmission frame, the receiving device may determine the frame structure of the transmission frame according to the subcarrier polarity of the frame structure indication field in the physical header, and then determine how to process a remaining part after the frame structure indication field of the transmission frame, for example, determine whether to receive the remaining part.

[0085] As described in the foregoing, for an OFDM-based 802.11 standard, a subcarrier in an OFDM symbol includes a data subcarrier and a pilot subcarrier, and a subcarrier herein generally refers to a data subcarrier. Unless otherwise stated, all subcarriers involved in descriptions of this specification refer to data subcarriers.

[0086] In this embodiment of the present invention, the sending device may generate transmission frames with at least two frame structures. When the subcarrier

polarity of the frame structure indication field is a first subcarrier polarity, the transmission frame has a first frame structure. When the subcarrier polarity of the frame structure indication field is a second subcarrier polarity, the transmission frame has a second frame structure.

5 **[0087]** Optionally, a frame structure indication field in the second frame structure may include only common information, but not include control information used to decode a data field, so that decoding can be performed after signals superpose. Therefore, a scenario in which multiple devices perform sending, and a single device performs receiving is supported. The common information may help a third-party
10 HEW device understand the transmission frame, but is meaningless to a target receiving device. That is, the control information used to decode a data field of the transmission frame is not included. The common information includes at least one of the following information: a network identifier, an identifier of the receiving device, or remaining transmission duration.

15 **[0088]** It may be seen from the foregoing that, according to this embodiment of the present invention, in a technical solution, a subcarrier polarity of a frame structure indication field in a physical header of a transmission frame is used to indicate different transmission frame structures, so as to obtain the following technical effects:

20 **[0089]** 1. Because a subcarrier polarity may have more expression manners, and may be used to indicate more frame structures, design of multiple frame structures in a WLAN standard is supported, so as to satisfy a requirement that a HEW needs to support more transmission modes, support more frame structures, and indicate more frame structures.

25 **[0090]** 2. A legacy (legacy) device may determine, according to a subcarrier polarity of a frame structure indication field in a physical header of a transmission frame, that the transmission frame is a transmission frame that cannot be parsed by the legacy device. A HEW device may determine a structure of the transmission frame according to the subcarrier polarity of the frame structure indication field in the physical header of the transmission frame, and then determine how to receive and
30 parse a remaining part of the transmission frame.

[0091] The following further describes in detail the method in this embodiment of the present invention.

[0092] First

[0093] In some embodiments of the present invention, a transmission frame

structure applied to a HEW is provided.

[0094] To support both an existing transmission mode (that is, transmission modes such as SU, SU MIMO, and DL MU MIMO that are supported by standards such as 11a/g, 11n, and 11ac) and a newly-added transmission mode (that is, transmission modes such as UL MU MIMO and UL/DL OFDMA that may be introduced into the 11ax standard), two transmission frame structures applied to the HEW are proposed, and are respectively shown in FIG. 4(a) and FIG. 4(b).

[0095] Referring to FIG. 4(a), FIG. 4(a) is a schematic diagram of a first frame structure. In this specification, a transmission frame that has the first frame structure is referred to as a first transmission frame. The first transmission frame is used to support the SU transmission mode, the SU MIMO transmission mode, and the DL MU MIMO transmission mode, and may be further used to support the DL OFDMA transmission mode.

[0096] An L-preamble part in a physical header of the first transmission frame includes fields such as an L-STF, an L-LTF, and an L-SIG. The L-preamble part is the same as L-preamble parts in existing standards such as 11n and 11ac, and details are not described herein. An HE (High Efficiency WLAN, high efficiency wireless local area network)-STF and an HE-LTF field are further included between the L-preamble part of the first transmission frame and a Data part of the first transmission frame. The HE-STF and the HE-LTF provide same functions as an HT-STF and an HT-LTF in the 11n standard, or a VHT-STF and a VHT-LTF in the 11ac standard, and details are not described herein.

[0097] Specially, in the physical header of the first transmission frame, there is an HE-SIG-A after the L-SIG and before the HE-STF. The HE-SIG-A includes control indication information. The control indication information is used to instruct a receiving device how to decode all or a part of fields in a part that is of the first transmission frame and after the HE-SIG-A. The control indication information includes, for example, bandwidth of the data field, and an MCS.

[0098] It should be noted that, according to step 301, a frame structure indication field closely follows an L-SIG in a physical header. Therefore, that in the physical header of the foregoing first transmission frame, there is an HE-SIG-A after the L-SIG and before the HE-STF includes two specific cases: The HE-SIG-A is after a frame structure indication field and before the HE-STF; or all or a part of symbols of the HE-SIG-A are a frame structure indication field.

[0099] Optionally, an HE-SIG-B is further included after the HE-SIG-A of the first transmission frame and before the HE-STF of the first transmission frame. The HE-SIG-B includes control indication information. The control indication information in the HE-SIG-B is used to instruct the receiving device how to decode a part that is
5 of the first transmission frame and after the HE-SIG-B. The HE-SIG-B described herein is a newly-added field in this embodiment, and is different from an HT-SIG2 in an original standard such as 11ac.

[0100] The HE-SIG-B and the HE-SIG-A are coded/decoded independently. The HE-SIG-A indicates information about the HE-SIG-B, such as an MCS and a length.
10 That is, a higher order MCS may be used for the HE-SIG-B, and the HE-SIG-B is changeable in length, which enables the HE-SIG-B to carry more bits. Because the HE-SIG-B can carry more bits, for example, control information used to decode the data field, an HE-SIG-C may not exist.

[0101] Optionally, the control indication information in the HE-SIG-A is used to
15 decode the HE-SIG-B, and the control indication information in the HE-SIG-B is used to decode the data field.

[0102] Optionally, the HE-SIG-A or the HE-SIG-B of the first transmission frame further includes mode indication information. The mode indication information is used to indicate a transmission mode specifically supported by the first transmission
20 frame, for example, indicate a specifically supported transmission mode in SU, SU MIMO, DL MU MIMO, and DL OFDMA.

[0103] Optionally, an HE-SIG-C may be further included or an HE-SIG-C may be not included after the HE-LTF of the first transmission frame and before the Date of the first transmission frame. The HE-SIG-C described herein is similar to an HT-SIG2
25 in an original standard such as 11ac. The HE-SIG-C is used in a DL MU MIMO or DL OFDMA scenario, and carries control indication information for a particular receiving device. Actually, the control information may also be carried by the HE-SIG-A or the HE-SIG-B. However, the HE-SIG-A can be transmitted by using only 20 MHz. Instead, the HE-SIG-C after the HE-STF and the HE-LTF may be
30 transmitted in parallel by using larger bandwidth or multiple spatial flows, which has higher transmission efficiency and can effectively reduce transmission overheads.

[0104] In comparison with a frame structure in an existing standard, the 11ax standard is applicable to an outdoor scenario in which a multipath effect is relatively severe. Therefore, a long symbol (that is, an OFDM symbol with a longer GI (Guard

Interval, guard interval)) is preferable to be used in the data field of the first transmission frame, so as to offset a relatively large delay extension. A length of the GI may be indicated in the HE-SIG-A.

[0105] Referring to FIG. 4(b), FIG. 4(b) is a schematic diagram of a second frame structure. In this specification, a transmission frame that has the second frame structure is referred to as a second transmission frame. The second transmission frame is used to support the UL MU MIMO transmission mode, and may be further used to support the UL OFDMA transmission mode, or may be further used to support the DL OFDMA transmission mode. The second transmission frame can closely follow only a trigger (trigger) frame sent by a device, for example, an AP (Access Point, access point).

[0106] An L-preamble part in a physical header of the second transmission frame includes fields such as an L-STF, an L-LTF, and an L-SIG. The L-preamble part is the same as L-preamble parts in existing standards such as 11n and 11ac, and details are not described herein. An HE (High Efficiency WLAN, high efficiency wireless local area network)-STF and an HE-LTF field are further included between the L-preamble part of the second transmission frame and a Data part of the second transmission frame. The HE-STF and the HE-LTF are similar to HT-STFs and HT-LTFs in the standards such as 11n and 11ac, and details are not described herein.

[0107] Optionally, an HE-SIG-C may be included or an HE-SIG-C may be not included after the HE-LTF of the second transmission frame and before the Data of the second transmission frame. The HE-SIG-C is used to carry control indication information. The control indication information is used to instruct a receiving device how to decode the data field that is of the second transmission frame and after the HE-SIG-C. However, because the second transmission frame is always sent just after the AP sends a trigger frame, the control indication information may be specified in the trigger frame by the AP. In this case, the second transmission frame does not need to carry the control indication information. That is, the second transmission frame does not need to include the HE-SIG-C.

[0108] Specially, in the physical header of the second transmission frame, there may be no HE-SIG-A after the L-SIG and before the HE-STF, or there is an HE-SIG-A, but the HE-SIG-A includes only common information, and does not carry control information used to decode the data field, so that decoding can still be performed after HE-SIG-As in second transmission frames sent by multiple sending

devices that include the sending device superpose. The common information includes at least one of the following information: a network identifier, an identifier of the receiving device (such as an AP), or remaining transmission duration (Duration). The network identifier is a color (Color) or the like. An AP identifier is a basic service set identifier (Basic Service Set Identifier, BSSID) or the like.

[0109] It should be noted that, according to step 301, a frame structure indication field closely follows an L-SIG in a physical header. Therefore, that in the physical header of the foregoing first transmission frame, there is an HE-SIG-A after the L-SIG and before the HE-STF includes two specific cases: The HE-SIG-A is after a frame structure indication field and before the HE-STF; or all or a part of symbols of the HE-SIG-A are a frame structure indication field.

[0110] Optionally, if the second transmission frame includes the HE-SIG-A, the HE-SIG-A can carry only common information such as an AP identifier and Duration, but cannot carry any control information that may be used to decode the data field, such as bandwidth of the data field and an MCS. In this case, the common information in the HE-SIG-A may help a third-party HEW device understand the transmission frame. For example, the third-party device may set a NAV (Network Allocation Vector, network allocation vector) according to the Duration. However, the common information is meaningless to a target receiving device. That is, the control information used to decode a data field of the transmission frame is not included. Preferably, the second transmission frame does not include the HE-SIG-A, which is a simplest design that is shown in FIG. 4 (b).

[0111] It should be specially noted that whether the first transmission frame or the second transmission frame is used in DL OFDMA depends on an implementation manner of the DL OFDMA. For the DL OFDMA, there are two possible implementation manners. One manner is shown in 5(a). An AP concatenates a trigger frame and DL OFDMA Data together for sending. In this case, resource scheduling information is in a physical header of a concatenation transmission frame, and the trigger is actually the physical header of the entire concatenation transmission frame. The other manner is shown in FIG. 5(b). An AP first sends a trigger frame, and then sends DL OFDMA Data after an interval of a predetermined time length, where the trigger frame includes the resource scheduling information. In this case, the resource scheduling information is in a physical header of the trigger frame or MAC (Media Access Control, media access control) layer data. If the implementation manner of the

DL OFDMA shown in FIG. 5(a) is used, the first transmission frame shown in FIG. 4(a) is used. If the implementation manner of the DL OFDMA shown in FIG. 5(b) is used, the second transmission frame shown in FIG. 4(b) is used.

[0112] If the UL MU MIMO transmission mode is introduced into the HEW, either the first transmission frame or the second transmission frame may be selected, according to an actual requirement, to be used in the UL MU MIMO.

[0113] Second

[0114] Some embodiments of the present invention provide multiple expression manners of a subcarrier polarity.

[0115] In some embodiments of the present invention, a transmission frame generated by a sending device of a transmission frame may be a first transmission frame that has a first frame structure, or may be a second transmission frame that has a second frame structure. Subcarrier polarities of frame structure indication fields in physical headers of the first transmission frame and the second transmission frame are different, so as to indicate different frame structures. The frame structure indication field in the first transmission frame has a first subcarrier polarity, and the frame structure indication field in the second transmission frame has a second subcarrier polarity.

[0116] A subcarrier polarity of a frame structure indication field may have the following multiple expression manners, but is not limited to the following manners:

[0117] A. In some implementation manners of the present invention, the first subcarrier polarity means that phases of a first group of subcarriers in multiple subcarriers included in the frame structure indication field are rotated by a first angle, and phases of a second group of subcarriers are rotated by a second angle; and

the second subcarrier polarity means that the phases of the first group of subcarriers in the multiple subcarriers included in the frame structure indication field are rotated by the second angle, and the phases of the second group of subcarriers are rotated by the first angle.

[0118] The second angle is greater than the first angle, and the first angle is greater than or equal to 0 degree.

[0119] The multiple subcarriers included in the frame structure indication field may be divided into two groups in any manner. Preferably, the first group of subcarriers may be odd-numbered subcarriers, and a second subcarrier may be an

even-numbered subcarrier; or the first group of subcarriers may be even-numbered subcarriers, and a second subcarrier may be an odd-numbered subcarrier.

[0120] Phase rotation may be phase rotation relative to an L-SIG. The rotated first angle and second angle may be any value, for example, may be respectively 0 degree and 90 degrees. That is, the first subcarrier polarity is that the phases of the first group of subcarriers are rotated by 90 degrees, and the phases of the second group of subcarriers are not rotated; the second subcarrier polarity is that the phases of the first group of subcarriers are not rotated, and the phases of the second group of subcarriers are rotated by 90 degrees.

[0121] B. In some other implementation manners of the present invention, the first subcarrier polarity means that a first group of subcarriers in multiple subcarriers included in the frame structure indication field are filled, and a second group of subcarriers are vacant; and

the second subcarrier polarity means that the first group of subcarriers in the multiple subcarriers included in the frame structure indication field are vacant, and the second group of subcarriers are filled.

[0122] The filling means filling information into a subcarrier, and the vacancy means not filling any information into a subcarrier. A vacant subcarrier does not carry information about the sending device.

[0123] The multiple subcarriers included in the frame structure indication field may be divided into two groups in any manner. Preferably, the first group of subcarriers may be odd-numbered subcarriers, and a second subcarrier may be an even-numbered subcarrier; or the first group of subcarriers may be even-numbered subcarriers, and a second subcarrier may be an odd-numbered subcarrier.

[0124] C. In still some implementation manners of the present invention, the first subcarrier polarity means that phases of all subcarriers included in the frame structure indication field are rotated by a third angle; and

the second subcarrier polarity means that the phases of all the subcarriers included in the frame structure indication field are rotated by a fourth angle.

[0125] The fourth angle is greater than the third angle, and the third angle is greater than 0 degree.

[0126] Phase rotation may be phase rotation relative to an L-SIG. For example, the third angle is 45 degrees, and the fourth angle is 135 degrees. That is, the first subcarrier polarity is that the phases of all the subcarriers included in the frame

structure indication field are rotated by 45 degrees, and the second subcarrier polarity is that the phases of all the subcarriers included in the frame structure indication field are rotated by 135 degrees. It should be specially noted that, in an existing standard, phase rotation generally refers to rotation in a counterclockwise direction.

5 **[0127]** The multiple subcarriers included in the frame structure indication field may be divided into two groups in any manner. Preferably, a first group of subcarriers may be odd-numbered subcarriers, and a second subcarrier may be an even-numbered subcarrier; or a first group of subcarriers may be an even-numbered subcarrier, and a second subcarrier may be an odd-numbered subcarrier.

10 **[0128]** It should be noted that, because repetition transmission is performed on all parts before an HE-STF on a basis of 20 MHz, the foregoing descriptions are for a bandwidth of 20 MHz. In 20 MHz, all the parts before the HE-STF each include 52 effective subcarriers that are numbered $\pm 1, \pm 2, \dots, \pm 26$. Subcarriers numbered ± 7 and ± 21 are pilot subcarriers, and the other 48 subcarriers are data subcarriers. In the
15 foregoing description, the subcarriers on which a phase rotation operation is performed preferably refer to the 48 data subcarriers. That is, preferably, the subcarriers described in the foregoing specifically refer to data subcarriers.

[0129] Third

[0130] Some embodiments of the present invention provide multiple expression
20 manners of a frame structure indication field.

[0131] The following further describes the frame structure indication field.

[0132] Referring to FIG. 4(a) and FIG. 4(b), the frame structure indication field is indicated by X in the figures, and X may have the following several possible kinds of content.

25 **[0133]** In some implementation manners, a frame structure indication field in a first frame structure and that in a second frame structure both are RL-SIGs. The RL-SIG is a time domain repetition of an L-SIG. The time domain repetition is repetition in terms of time, and may be understood as addition of a field after a particular field, for example, an L-SIG. Content of the added field is the same as that
30 of the particular field, for example, the L-SIG. However, the added field and the particular field may be different in physical waveform. For example, the added field is a result obtained after phase rotation is performed on the particular field.

[0134] In this case, in the first frame structure, the RL-SIG is inevitably followed by an HE-SIG-A. This design is a preferred solution. Optionally, a HEW device may

have a higher probability of correctly obtaining, by means of parsing by using the RL-SIG with reference to the foregoing L-SIG, content included in the L-SIG. According to a standard, the L-SIG includes only the following information: a rate (RATE) that is generally set to 6 Mps, a length (LENGTH) that is in units of bytes and
5 indicates a time domain length of a current frame with reference to the rate, a parity bit used to check a rate and a length, and a tail (Tail) bit used to decode convolutional code. The L-SIG aims to be compatible with a legacy device, but cannot provide, for a receiving device, information required for decoding a data field. In the second frame structure, because the second frame structure is mainly used for UL MU transmission,
10 transmission frames sent by multiple devices need to be equal in length (even if original data is not equal in length, an equal length needs to be implemented in a filling manner and the like) in terms of a time domain, that is, LENGTHs of all users are the same. Therefore, L-SIGs sent by all devices are the same, so that decoding can still be correctly performed after L-SIGs sent by different devices superpose. In a
15 word, the L-SIG actually does not include any information that is helpful for a receive end to perform decoding.

[0135] Alternatively, in some implementation manners, a frame structure indication field in a first frame structure is all or a part of OFDM symbols of an HE-SIG-A, and a frame structure indication field in a second frame structure is an
20 RL-SIG. The RL-SIG is a time domain repetition of an L-SIG. In this case, the first transmission frame does not include an RL-SIG, and overheads may be much lower. The HE-SIG-A may include multiple OFDM symbols, and X may be a part of the symbols (for example, only the first symbol) of the multiple OFDM symbols, or may include all symbols of the multiple OFDM symbols. The L-SIG does not include any
25 information that is helpful for a receive end to perform decoding.

[0136] Alternatively, in some implementation manners, a frame structure indication field in the first frame structure is all or a part of OFDM symbols of an HE-SIG-A, and a frame structure indication field in the second frame structure is all or a part of OFDM symbols of an HE-SIG-A. In this case, an HE-SIG-A in the first
30 transmission frame may carry control indication information that is helpful for a receive end to perform decoding, and an HE-SIG-A in the second transmission frame can carry only common information. The common information may include at least one of the following information: a network identifier, an identifier of a receiving device (such as an AP), or remaining transmission duration (Duration).

[0137] Alternatively, in some implementation manners, a frame structure indication field in the first frame structure is an RL-SIG, a frame structure indication field in the second frame structure is all or a part of OFDM symbols of an HE-SIG-A, where the RL-SIG is a time domain repetition of an L-SIG. In this case, in the first transmission frame, an RL-SIG is inevitably followed by an HE-SIG-A. An HE-SIG-A in the second transmission frame can carry only common information. The common information may include at least one of the following information: a network identifier, an identifier of a receiving device (such as an AP), or remaining transmission duration (Duration).

10 **[0138]** Fourth

[0139] Some embodiments of the present invention provide a method for enhancing and indicating a particular field in a frame structure.

[0140] In some embodiments of the present invention, that the sending device generates the transmission frame in 201 may include: The sending device generates a first transmission frame that has a first frame structure, or generates a second transmission frame that has a second frame structure.

[0141] In the first frame structure in this embodiment of the present invention, there is an HE-SIG-A after an L-SIG and before an HE-STF. The HE-SIG-A includes control indication information, such as bandwidth and an MCS. A receiving device may determine, according to the information, how to decode all or a part of fields in a part after the HE-SIG-A. Apparently, reliability of the HE-SIG-A is very important. Once the HE-SIG-A is incorrectly received, a data field cannot be decoded. Therefore, in some cases, the reliability of the HE-SIG-A needs to be enhanced. However, enhancement of the HE-SIG-A is not always needed. For example, when a channel is in a good condition and with small interference surrounded, it is unnecessary to perform enhancement on the HE-SIG-A. It may be understood that, in addition to the HE-SIG-A, there may be another particular field that needs enhancement.

[0142] Therefore, in this embodiment of the present invention, a time domain repetition of a particular field may be included after a frame structure indication field in the first transmission frame, so as to implement enhancement of the particular field. The particular field may be an HE-SIG-A or another field. An HE-SIG-A is used as example herein. A time domain repetition of the HE-SIG-A may be included after the HE-SIG-A in the first transmission frame. In addition, a subcarrier polarity of the HE-SIG-A may be used to indicate whether the time domain repetition of the

HE-SIG-A is further included after the HE-SIG-A. For example, as shown in FIG. 4(c), the time domain repetition of the HE-SIG-A is further included after the HE-SIG-A in the first transmission frame. In FIG. 4(c), X is an RL-SIG, and after the RL-SIG, there is the HE-SIG-A and the time domain repetition of the HE-SIG-A. It should be noted
5 that a physical header of the second transmission frame includes the particular field, for example, the HE-SIG-A, but does not include the time domain repetition of the particular field.

[0143] In an implementation manner, a subcarrier polarity of the HE-SIG-A in the first transmission frame may be used to indicate that the time domain repetition of the
10 HE-SIG-A is further included after the HE-SIG-A. For an expression form of the subcarrier polarity of the HE-SIG-A, reference may be made to any one of the foregoing manners A, B, and C, and simplest implementation is: When a phase of a subcarrier of the HE-SIG-A is not rotated, there is no repetition of the HE-SIG-A after the HE-SIG-A, or when phases of all subcarriers of the HE-SIG-A are rotated by 90
15 degrees, there is a repetition of the HE-SIG-A after the HE-SIG-A. In this case, the HE-SIG-A is the frame structure indication field.

[0144] In another implementation manner, a subcarrier polarity of the frame structure indication field X may be used to indicate whether there is the time domain repetition of the HE-SIG-A. In this case, X should have three polarities:

20 **[0145]** Polarity 1: indicates that a transmission frame (that is, the first transmission frame) has the first frame structure, and there is no time domain repetition of the HE-SIG-A.

[0146] Polarity 2: indicates that a transmission frame (that is, the first transmission frame) has the first frame structure, and there is the time domain
25 repetition of the HE-SIG-A.

[0147] Polarity 3: indicates that a transmission frame (that is, the second transmission frame) has the second frame structure.

[0148] How does X express the three polarities? The polarity of X may be extended by using a method for increasing subcarrier groups. For example, multiple
30 subcarriers included in X are divided into three groups (for example, subcarrier numbers are separately $3n$, $3n+1$, and $3n+2$), and filling/phase rotation is performed on different groups, so as to present different polarities.

[0149] A subcarrier polarity of the foregoing OFDM symbol is used to dynamically indicate whether there is a repetition of an HE-SIG-A. If necessary,

transmission reliability of the HE-SIG-A may be enhanced. However, in a scenario in which it is unnecessary to enhance reliability, the HE-SIG-A is not repeated, which helps reduce transmission overheads.

5 **[0150]** In the second frame structure in this embodiment of the present invention, the HE-SIG-A includes only common information, and does not carry control indication information, so that the HE-SIG-A does not need enhancement. Therefore, the second transmission frame that has the second frame structure may include the particular field, but does not include the time domain repetition of the particular field.

10 **[0151]** It should be noted that, the foregoing first, second, third, and fourth parts are separately further refinement or supplement to the method shown in FIG. 3 of the present invention, and the four parts are independent of each other in terms of content, and certainly may be combined with each other in terms of content.

15 **[0152]** It may be understood that, the foregoing solution in this embodiment of the present invention may be specifically implemented by a device, for example, a STA or an AP.

20 **[0153]** It may be seen from the foregoing that, this embodiment of the present invention discloses a method for indicating a transmission frame structure. According to the method, in a technical solution, a subcarrier polarity of a frame structure indication field in a physical header of a transmission frame is used to indicate different frame structures, so as to obtain the following technical effects:

25 **[0154]** First, because a subcarrier polarity may have more expression manners, and may be used to indicate more frame structures, design of multiple frame structures in a WLAN standard is supported, so as to satisfy a requirement that a HEW needs to support more transmission modes, support more frame structures, and indicate more frame structures.

30 **[0155]** Second, in some implementation manners, a frame structure indication field in a second frame structure includes only common information. In a scenario in which multiple devices perform sending, and one device performs receiving, frame structure indication fields in transmission frames sent by the multiple devices are the same, and may still be properly received and parsed after the frame structure indication fields superpose. Therefore, the second frame structure supports a scenario in which multiple devices perform sending, and one device performs receiving, and may be applied to a HEW into which any one or more of transmission modes in transmission modes of UL OFMDA, DL OFDMA, and UL MU MIMO are

introduced.

5 **[0156]** Third, in some implementation manners, whether to perform time domain repetition on a particular field, for example, an HE-SIG-A, may be indicated by using a subcarrier polarity of a frame structure indication field. In some scenarios, the particular field is repeated to enhance reliability of the particular field, and in some other scenarios, the particular field is not repeated to reduce overheads.

10 **[0157]** Fourth, in some implementation manners, an expression manner of a subcarrier polarity is that a group of subcarriers are filled/phases of a group of subcarriers are rotated, and another group of subcarriers are vacant/phases of another group of subcarriers are not rotated. Because the expression manner has a higher identification degree, in comparison with an indication method in the prior art, in this embodiment of the present invention, a receiving device can more easily identify a structure of a transmission frame.

Embodiment 2

15 **[0158]** Referring to FIG. 6, this embodiment of the present invention further provides a method for indicating a transmission frame structure. The method is applied to a WLAN, and may include:

20 **[0159]** 601. A receiving device receives a physical header of a transmission frame sent by a sending device, where the physical header of the transmission frame includes a frame structure indication field, and a subcarrier polarity of the frame structure indication field is used to indicate a frame structure of the transmission frame.

[0160] 602. Determine the frame structure of the transmission frame according to the subcarrier polarity of the frame structure indication field.

25 **[0161]** When the subcarrier polarity of the frame structure indication field is a first subcarrier polarity, the transmission frame has a first frame structure. When the subcarrier polarity of the frame structure indication field is a second subcarrier polarity, the transmission frame has a second frame structure.

30 **[0162]** In some embodiments of the present invention, the frame structure indication field closely follows a legacy signaling field L-SIG. That the receiving device receives the physical header of the transmission frame sent by the sending device may include: The receiving device receives a physical header of a first

transmission frame that is sent by the sending device and has the first frame structure or a physical header of a second transmission frame that is sent by the sending device and has the second frame structure.

[0163] In the physical header of the first transmission frame, there is a high efficiency wireless local area network first signaling field HE-SIG-A after an L-SIG and before a high efficiency wireless local area network short training field HE-STF. The HE-SIG-A includes control indication information, and the control indication information is used to instruct the receiving device how to decode all or a part of fields in a part that is of the first transmission frame and after the HE-SIG-A. The first transmission frame is used to support a single user SU transmission mode, a single user multiple-input multiple-output SU MIMO transmission mode, and a downlink multi-user multiple-input multiple-output DL MU MIMO transmission mode.

[0164] In the physical header of the second transmission frame, there is no HE-SIG-A after an L-SIG and before an HE-STF, or there is an HE-SIG-A, but the HE-SIG-A includes only common information, so that decoding can still be performed after HE-SIG-As in second transmission frames sent by multiple sending devices superpose. The second transmission frame is used to support an uplink orthogonal frequency division multiple access UL OFDMA transmission mode.

[0165] The common information includes at least one of the following information: a network identifier, an identifier of the receiving device, or remaining transmission duration.

[0166] In some embodiments of the present invention, the first transmission frame is further used to support a downlink orthogonal frequency division multiple access DL OFDMA transmission mode, or the second transmission frame is further used to support a DL OFDMA transmission mode.

[0167] In some embodiments of the present invention, the first transmission frame is further used to support an uplink multi-user multiple-input multiple-output UL MU MIMO transmission mode, or the second transmission frame is further used to support a UL MU MIMO transmission mode.

[0168] After determining the frame structure of the transmission frame according to the subcarrier polarity of the frame structure indication field, the receiving device may process a remaining part of the transmission frame by using a corresponding method. For example, when a HEW STA that does not receive a trigger frame sent in advance by an AP or an AP that does not send a trigger frame before a predetermined

time length detects a second transmission frame, the HEW STA or the AP directly discards the frame because the second transmission frame is certainly not sent to the HEW STA or the AP. The STA or the AP may enter a sleep state during a transmission time (obtained by calculating according to the L-SIG) of the transmission frame, so as to reach a power saving objective.

[0169] In some embodiments of the present invention, a high efficiency wireless local area network second signaling field HE-SIG-B is further included after the HE-SIG-A of the first transmission frame and before the HE-STF of the first transmission frame. The HE-SIG-B includes control indication information, and the control indication information included in the HE-SIG-B is used to instruct the receiving device how to decode a part that is of the first transmission frame and after the HE-SIG-B.

[0170] In some embodiments of the present invention, the HE-SIG-A or the HE-SIG-B of the first transmission frame further includes mode indication information. The method further includes: determining, according to the mode indication information, a transmission mode specifically supported by the frame structure of the first transmission frame.

[0171] In some embodiments of the present invention,

the first subcarrier polarity means that phases of a first group of subcarriers in multiple subcarriers included in the frame structure indication field are rotated by a first angle, and phases of a second group of subcarriers are rotated by a second angle; and the second subcarrier polarity means that the phases of the first group of subcarriers in the multiple subcarriers included in the frame structure indication field are rotated by the second angle, and the phases of the second group of subcarriers are rotated by the first angle, where the second angle is greater than the first angle, and the first angle is greater than or equal to 0 degree; or

the first subcarrier polarity means that a first group of subcarriers in multiple subcarriers included in the frame structure indication field are filled, and a second group of subcarriers are vacant; and the second subcarrier polarity means that the first group of subcarriers in the multiple subcarriers included in the frame structure indication field are vacant, and the second group of subcarriers are filled; or

the first subcarrier polarity means that phases of all subcarriers included in the frame structure indication field are rotated by a third angle, and the second subcarrier polarity means that the phases of all the subcarriers included in the frame

structure indication field are rotated by a fourth angle, where the fourth angle is greater than the third angle, and the third angle is greater than 0 degree.

[0172] In some embodiments of the present invention, that the receiving device receives the physical header of the transmission frame sent by the sending device includes: The receiving device receives a physical header of a first transmission frame that is sent by the sending device and has the first frame structure or a physical header of a second transmission frame that is sent by the sending device and has the second frame structure. After a frame structure indication field, the physical header of the first transmission frame includes a time domain repetition of a particular field. The physical header of the second transmission frame includes the particular field, but does not include the time domain repetition of the particular field.

[0173] In some embodiments of the present invention, the particular field is an HE-SIG-A.

[0174] In some embodiments of the present invention, the frame structure indication field closely follows a legacy signaling field L-SIG; and

the frame structure indication field in the first frame structure and that in the second frame structure both are RL-SIGs, where the RL-SIG is a time domain repetition of the L-SIG; or

the frame structure indication field in the first frame structure is all or a part of OFDM symbols of the HE-SIG-A, and the frame structure indication field in the second frame structure is an RL-SIG, where the RL-SIG is a time domain repetition of the L-SIG; or

the frame structure indication field in the first frame structure is all or a part of OFDM symbols of the HE-SIG-A, and the frame structure indication field in the second frame structure is all or a part of OFDM symbols of the HE-SIG-A; or

the frame structure indication field in the first frame structure is an RL-SIG, and the frame structure indication field in the second frame structure is all or a part of OFDM symbols of the HE-SIG-A, where the RL-SIG is a time domain repetition of the L-SIG.

[0175] In the foregoing embodiment shown in FIG. 6, that the receiving device is an execution body is used as an example to describe the method in this embodiment of the present invention. For detailed descriptions, reference may be made to Embodiment 1 shown in FIG. 3 to FIG. 5. All content described in Embodiment 1 may be correspondingly referenced to Embodiment 2, and details are not described herein.

[0176] It may be understood that, the foregoing solution in this embodiment of the present invention may be specifically implemented by a device, for example, a STA or an AP.

[0177] It may be seen from the foregoing that, this embodiment of the present invention discloses a method for indicating a transmission frame structure. According to the method, in a technical solution, a subcarrier polarity of a frame structure indication field in a physical header of a transmission frame is used to indicate different frame structures, so as to obtain the following technical effects:

[0178] First, because a subcarrier polarity may have more expression manners, and may be used to indicate more frame structures, design of multiple frame structures in a WLAN standard is supported, so as to satisfy a requirement that a HEW needs to support more transmission modes, support more frame structures, and indicate more frame structures.

[0179] Second, in some implementation manners, a frame structure indication field includes only common information. In a scenario in which multiple devices perform sending, and one device performs receiving, frame structure indication fields in transmission frames sent by the multiple devices are the same, and may still be properly received and parsed after the frame structure indication fields superpose. Therefore, the frame structure supports a scenario in which multiple devices perform sending, and one device performs receiving, and may be applied to a HEW into which any one or more of transmission modes in transmission modes of UL OFMDA, DL OFDMA, and UL MU MIMO are introduced.

[0180] Third, in some implementation manners, whether to perform time domain repetition on a particular field, for example, an HE-SIG-A, may be indicated by using a subcarrier polarity of a frame structure indication field. In some scenarios, the particular field is repeated to enhance reliability of the particular field, and in some other scenarios, the particular field is not repeated to reduce overheads.

[0181] Fourth, in some implementation manners, an expression manner of a subcarrier polarity is that a group of subcarriers are filled/phases of a group of subcarriers are rotated, and another group of subcarriers are vacant/phases of another group of subcarriers are not rotated. Because the expression manner has a higher identification degree, in comparison with an indication method in the prior art, in this embodiment of the present invention, a receiving device can more easily identify a structure of a transmission frame.

[0182] To better implement the foregoing solutions in the embodiments of the present invention, the following further provides a related apparatus that is configured to implement the foregoing solutions in a cooperation manner.

Embodiment 3

5 **[0183]** Referring to FIG. 7, this embodiment of the present invention provides a sending device 700 for indicating a transmission frame structure. The sending device 700 is applied to a WLAN, and is particularly applied to a HEW. The sending device 700 may include a generation module 701 and a sending module 702.

[0184] The generation module 701 is configured to generate a transmission frame.
10 A physical header of the transmission frame includes a frame structure indication field, and a subcarrier polarity of the frame structure indication field is used to indicate a frame structure of the transmission frame.

[0185] When the subcarrier polarity of the frame structure indication field is a first subcarrier polarity, the transmission frame has a first frame structure. When the
15 subcarrier polarity of the frame structure indication field is a second subcarrier polarity, the transmission frame has a second frame structure.

[0186] The sending module 702 is configured to send the transmission frame, so that a receiving device determines the frame structure of the transmission frame according to the subcarrier polarity of the frame structure indication field.

20 **[0187]** In some embodiments of the present invention, the frame structure indication field closely follows a legacy signaling field L-SIG, and the generation module 701 may be specifically configured to generate a first transmission frame that has the first frame structure, or generate a second transmission frame that has the second frame structure.

25 **[0188]** In a physical header of the first transmission frame, there is a high efficiency wireless local area network first signaling field HE-SIG-A after an L-SIG and before a high efficiency wireless local area network short training field HE-STF. The HE-SIG-A includes control indication information, and the control indication information is used to instruct the receiving device how to decode all or a part of
30 fields in a part that is of the first transmission frame and after the HE-SIG-A. The first transmission frame is used to support a single user SU transmission mode, a single user multiple-input multiple-output SU MIMO transmission mode, and a downlink

multi-user multiple-input multiple-output DL MU MIMO transmission mode.

5 **[0189]** In a physical header of the second transmission frame, there is no HE-SIG-A after an L-SIG and before an HE-STF, or there is an HE-SIG-A, but the HE-SIG-A includes only common information, so that decoding can still be performed after HE-SIG-As in second transmission frames sent by multiple sending devices superpose. The second transmission frame is used to support an uplink orthogonal frequency division multiple access UL OFDMA transmission mode.

10 **[0190]** The common information includes at least one of the following information: a network identifier, an identifier of the receiving device, or remaining transmission duration.

[0191] In some embodiments of the present invention, the first transmission frame is further used to support a downlink orthogonal frequency division multiple access DL OFDMA transmission mode, or the second transmission frame is further used to support a DL OFDMA transmission mode.

15 **[0192]** In some embodiments of the present invention, the first transmission frame is further used to support an uplink multi-user multiple-input multiple-output UL MU MIMO transmission mode, or the second transmission frame is further used to support a UL MU MIMO transmission mode.

20 **[0193]** In some embodiments of the present invention, a high efficiency wireless local area network second signaling field HE-SIG-B is further included after the HE-SIG-A of the first transmission frame and before the HE-STF of the first transmission frame. The HE-SIG-B includes control indication information, and the control indication information included in the HE-SIG-B is used to instruct the receiving device how to decode a part that is of the first transmission frame and after
25 the HE-SIG-B.

[0194] In some embodiments of the present invention, the HE-SIG-A or the HE-SIG-B of the first transmission frame further includes mode indication information, and the mode indication information is used to indicate a transmission mode specifically supported by the first transmission frame.

30 **[0195]** In some embodiments of the present invention, the first subcarrier polarity means that phases of a first group of subcarriers in multiple subcarriers included in the frame structure indication field are rotated by a first angle, and phases of a second group of subcarriers are rotated by a second angle; and the second subcarrier polarity means that the phases of the first group of subcarriers in the multiple subcarriers

included in the frame structure indication field are rotated by the second angle, and the phases of the second group of subcarriers are rotated by the first angle, where the second angle is greater than the first angle, and the first angle is greater than or equal to 0 degree; or

5 the first subcarrier polarity means that a first group of subcarriers in multiple subcarriers included in the frame structure indication field are filled, and a second group of subcarriers are vacant; and the second subcarrier polarity means that the first group of subcarriers in the multiple subcarriers included in the frame structure indication field are vacant, and the second group of subcarriers are filled; or

10 the first subcarrier polarity means that phases of all subcarriers included in the frame structure indication field are rotated by a third angle, and the second subcarrier polarity means that the phases of all the subcarriers included in the frame structure indication field are rotated by a fourth angle, where the fourth angle is greater than the third angle, and the third angle is greater than 0 degree.

15 **[0196]** In some embodiments of the present invention, the generation module 701 is specifically configured to generate a first transmission frame that has the first frame structure, or generate a second transmission frame that has the second frame structure. After a frame structure indication field, the physical header of the first transmission frame includes a time domain repetition of a particular field. The physical header of
20 the second transmission frame includes the particular field, but does not include the time domain repetition of the particular field.

[0197] In some embodiments of the present invention, the particular field is an HE-SIG-A.

[0198] In some embodiments of the present invention, the frame structure
25 indication field closely follows a legacy signaling field L-SIG; and

the frame structure indication field in the first frame structure and that in the second frame structure both are RL-SIGs, where the RL-SIG is a time domain repetition of the L-SIG; or

30 the frame structure indication field in the first frame structure is all or a part of OFDM symbols of the HE-SIG-A, and the frame structure indication field in the second frame structure is an RL-SIG, where the RL-SIG is a time domain repetition of the L-SIG; or

the frame structure indication field in the first frame structure is all or a part of OFDM symbols of the HE-SIG-A, and the frame structure indication field in

the second frame structure is all or a part of OFDM symbols of the HE-SIG-A; or

the frame structure indication field in the first frame structure is an RL-SIG, and the frame structure indication field in the second frame structure is all or a part of OFDM symbols of the HE-SIG-A, where the RL-SIG is a time domain repetition of the L-SIG.

[0199] The sending device in this embodiment of the present invention may be a device, for example, a STA or an AP, and may be specifically a mobile phone, a tablet computer, a router, or the like.

[0200] It may be understood that, functions of function modules of the sending device in this embodiment of the present invention may be specifically implemented according to the methods in the foregoing method embodiments. For a specific implementation process, reference may be made to related descriptions in the foregoing method embodiments, and details are not described herein.

[0201] It may be seen from the foregoing that, in some feasible implementation manners of the present invention, in a technical solution, a subcarrier polarity of a frame structure indication field in a physical header of a transmission frame is used to indicate different frame structures, so as to obtain the following technical effects:

[0202] First, because a subcarrier polarity may have more expression manners, and may be used to indicate more frame structures, design of multiple frame structures in a WLAN standard is supported, so as to satisfy a requirement that a HEW needs to support more transmission modes, support more frame structures, and indicate more frame structures.

[0203] Second, in some implementation manners, a frame structure indication field in a second frame structure includes only common information. In a scenario in which multiple devices perform sending, and one device performs receiving, frame structure indication fields in transmission frames sent by the multiple devices are the same, and may still be properly received and parsed after the frame structure indication fields superpose. Therefore, the second frame structure supports a scenario in which multiple devices perform sending, and one device performs receiving, and may be applied to a HEW into which any one or more of transmission modes in transmission modes of UL OFMDA, DL OFDMA, and UL MU MIMO are introduced.

[0204] Third, in some implementation manners, whether to perform time domain repetition on a particular field, for example, an HE-SIG-A, may be indicated by using

a subcarrier polarity of a frame structure indication field. In some scenarios, the particular field is repeated to enhance reliability of the particular field, and in some other scenarios, the particular field is not repeated to reduce overheads.

5 [0205] Fourth, in some implementation manners, an expression manner of a subcarrier polarity is that a group of subcarriers are filled/phases of a group of subcarriers are rotated, and another group of subcarriers are vacant/phases of another group of subcarriers are not rotated. Because the expression manner has a higher identification degree, in comparison with an indication method in the prior art, in this embodiment of the present invention, a receiving device can more easily identify a
10 structure of a transmission frame.

Embodiment 4

[0206] Referring to FIG. 8, this embodiment of the present invention provides a receiving device 800 for indicating a transmission frame structure. The receiving device 800 is applied to a WLAN, and is particularly applied to a HEW. The receiving
15 device 800 may include:

a receiving module 801, configured to receive a physical header of a transmission frame sent by a sending device, where the physical header of the transmission frame includes a frame structure indication field, and a subcarrier polarity of the frame structure indication field is used to indicate a frame structure of
20 the transmission frame; and

a determining module 802, configured to determine the frame structure of the transmission frame according to the subcarrier polarity of the frame structure indication field, where when the subcarrier polarity of the frame structure indication field is a first subcarrier polarity, the transmission frame has a first frame structure, or
25 when the subcarrier polarity of the frame structure indication field is a second subcarrier polarity, the transmission frame has a second frame structure.

[0207] In some embodiments of the present invention, the frame structure indication field closely follows a legacy signaling field L-SIG, and the receiving module 801 may be specifically configured to:

30 receive a physical header of a first transmission frame that is sent by the sending device and has the first frame structure or a physical header of a second transmission frame that is sent by the sending device and has the second frame

structure.

[0208] In the physical header of the first transmission frame, there is a high efficiency wireless local area network first signaling field HE-SIG-A after an L-SIG and before a high efficiency wireless local area network short training field HE-STF.

5 The HE-SIG-A includes control indication information, and the control indication information is used to instruct the receiving device how to decode all or a part of fields in a part that is of the first transmission frame and after the HE-SIG-A. The first transmission frame is used to support a single user SU transmission mode, a single user multiple-input multiple-output SU MIMO transmission mode, and downlink
10 multi-user multiple-input multiple-output DL MU MIMO.

[0209] In the physical header of the second transmission frame, there is no HE-SIG-A after an L-SIG and before an HE-STF, or there is an HE-SIG-A, but the HE-SIG-A includes only common information, so that decoding can still be performed after HE-SIG-As in second transmission frames sent by multiple sending
15 devices superpose. The second transmission frame is used to support an uplink orthogonal frequency division multiple access UL OFDMA transmission mode.

[0210] The common information includes at least one of the following information: a network identifier, an identifier of the receiving device, or remaining transmission duration.

20 **[0211]** In some embodiments of the present invention, the first transmission frame is further used to support a downlink orthogonal frequency division multiple access DL OFDMA transmission mode, or the second transmission frame is further used to support a DL OFDMA transmission mode.

[0212] In some embodiments of the present invention, the first transmission frame
25 is further used to support an uplink multi-user multiple-input multiple-output UL MU MIMO transmission mode, or the second transmission frame is further used to support a UL MU MIMO transmission mode.

[0213] In some embodiments of the present invention, a high efficiency wireless local area network second signaling field HE-SIG-B is further included after the
30 HE-SIG-A of the first transmission frame and before the HE-STF of the first transmission frame. The HE-SIG-B includes control indication information, and the control indication information included in the HE-SIG-B is used to instruct the receiving device how to decode a part that is of the first transmission frame and after the HE-SIG-B.

[0214] In some embodiments of the present invention, the HE-SIG-A or the HE-SIG-B of the first transmission frame further includes mode indication information, and the determining module 802 is further configured to determine, according to the mode indication information, a transmission mode specifically supported by the frame structure of the first transmission frame.

[0215] In some embodiments of the present invention, the first subcarrier polarity means that phases of a first group of subcarriers in multiple subcarriers included in the frame structure indication field are rotated by a first angle, and phases of a second group of subcarriers are rotated by a second angle; and the second subcarrier polarity means that the phases of the first group of subcarriers in the multiple subcarriers included in the frame structure indication field are rotated by the second angle, and the phases of the second group of subcarriers are rotated by the first angle, where the second angle is greater than the first angle, and the first angle is greater than or equal to 0 degree; or

the first subcarrier polarity means that a first group of subcarriers in multiple subcarriers included in the frame structure indication field are filled, and a second group of subcarriers are vacant; and the second subcarrier polarity means that the first group of subcarriers in the multiple subcarriers included in the frame structure indication field are vacant, and the second group of subcarriers are filled; or

the first subcarrier polarity means that phases of all subcarriers included in the frame structure indication field are rotated by a third angle, and the second subcarrier polarity means that the phases of all the subcarriers included in the frame structure indication field are rotated by a fourth angle, where the fourth angle is greater than the third angle, and the third angle is greater than 0 degree.

[0216] In some embodiments of the present invention, the receiving module 801 is specifically configured to:

receive, by the receiving device, a physical header of a first transmission frame that is sent by the sending device and has the first frame structure or a physical header of a second transmission frame that is sent by the sending device and has the second frame structure.

[0217] After a frame structure indication field, the physical header of the first transmission frame includes a time domain repetition of a particular field.

[0218] The physical header of the second transmission frame includes the particular field, but does not include the time domain repetition of the particular field.

[0219] In some embodiments of the present invention, the particular field is an HE-SIG-A.

[0220] In some embodiments of the present invention, the frame structure indication field closely follows a legacy signaling field L-SIG; and

5 the frame structure indication field in the first frame structure and that in the second frame structure both are RL-SIGs, where the RL-SIG is a time domain repetition of the L-SIG; or

10 the frame structure indication field in the first frame structure is all or a part of OFDM symbols of the HE-SIG-A, and the frame structure indication field in the second frame structure is an RL-SIG, where the RL-SIG is a time domain repetition of the L-SIG; or

the frame structure indication field in the first frame structure is all or a part of OFDM symbols of the HE-SIG-A, and the frame structure indication field in the second frame structure is all or a part of OFDM symbols of the HE-SIG-A; or

15 the frame structure indication field in the first frame structure is an RL-SIG, and the frame structure indication field in the second frame structure is all or a part of OFDM symbols of the HE-SIG-A, where the RL-SIG is a time domain repetition of the L-SIG.

[0221] The receiving device in this embodiment of the present invention may be a device, for example, a STA or an AP, and may be specifically a mobile phone, a tablet computer, a router, or the like.

[0222] It may be understood that, functions of function modules of the receiving device in this embodiment of the present invention may be specifically implemented according to the methods in the foregoing method embodiments. For a specific implementation process, reference may be made to related descriptions in the foregoing method embodiments, and details are not described herein.

[0223] It may be seen from the foregoing that, in some feasible implementation manners of the present invention, in a technical solution, a subcarrier polarity of a frame structure indication field in a physical header of a transmission frame is used to indicate different frame structures, so as to obtain the following technical effects:

[0224] First, because a subcarrier polarity may have more expression manners, and may be used to indicate more frame structures, design of multiple frame structures in a WLAN standard is supported, so as to satisfy a requirement that a HEW needs to support more transmission modes, support more frame structures, and

indicate more frame structures.

[0225] Second, in some implementation manners, a frame structure indication field in a second frame structure includes only common information. In a scenario in which multiple devices perform sending, and one device performs receiving, frame structure indication fields in transmission frames sent by the multiple devices are the same, and may still be properly received and parsed after the frame structure indication fields superpose. Therefore, the second frame structure supports a scenario in which multiple devices perform sending, and one device performs receiving, and may be applied to a HEW into which any one or more of transmission modes in transmission modes of UL OFMDA, DL OFDMA, and UL MU MIMO are introduced.

[0226] Third, in some implementation manners, whether to perform time domain repetition on a particular field, for example, an HE-SIG-A, may be indicated by using a subcarrier polarity of a frame structure indication field. In some scenarios, the particular field is repeated to enhance reliability of the particular field, and in some other scenarios, the particular field is not repeated to reduce overheads.

[0227] Fourth, in some implementation manners, an expression manner of a subcarrier polarity is that a group of subcarriers are filled/phases of a group of subcarriers are rotated, and another group of subcarriers are vacant/phases of another group of subcarriers are not rotated. Because the expression manner has a higher identification degree, in comparison with an indication method in the prior art, in this embodiment of the present invention, a receiving device can more easily identify a structure of a transmission frame.

Embodiment 5

[0228] Referring to FIG. 9, this embodiment of the present invention further provides a communications system 900, including: a sending device 700 and a receiving device 800. The sending device 700 may be the sending device shown in Embodiment 3, and the receiving device 800 may be the receiving device shown in FIG. 4. Specifically,

[0229] The sending device 700 may include: a generation module 701, configured to generate a transmission frame, where a physical header of the transmission frame includes a frame structure indication field, a subcarrier polarity of the frame structure

indication field is used to indicate a frame structure of the transmission frame, where when the subcarrier polarity of the frame structure indication field is a first subcarrier polarity, the transmission frame has a first frame structure, or when the subcarrier polarity of the frame structure indication field is a second subcarrier polarity, the transmission frame has a second frame structure; and a sending module 702, configured to send the transmission frame, so that the receiving device determines the frame structure of the transmission frame according to the subcarrier polarity of the frame structure indication field.

[0230] The receiving device 800 may include: a receiving module 801, configured to receive the physical header of the transmission frame sent by the sending device, where the physical header of the transmission frame includes the frame structure indication field, and the subcarrier polarity of the frame structure indication field is used to indicate the frame structure of the transmission frame; and a determining module 802, configured to determine the frame structure of the transmission frame according to the subcarrier polarity of the frame structure indication field, where when the subcarrier polarity of the frame structure indication field is the first subcarrier polarity, the transmission frame has the first frame structure, or when the subcarrier polarity of the frame structure indication field is the second subcarrier polarity, the transmission frame has the second frame structure.

[0231] In some embodiments of the present invention, the frame structure indication field closely follows a legacy signaling field L-SIG.

[0232] The generation module 701 may be specifically configured to generate a first transmission frame that has the first frame structure, or generate a second transmission frame that has the second frame structure. In a physical header of the first transmission frame, there is a high efficiency wireless local area network first signaling field HE-SIG-A after an L-SIG and before a high efficiency wireless local area network short training field HE-STF. The HE-SIG-A includes control indication information, and the control indication information is used to instruct the receiving device how to decode all or a part of fields in a part that is of the first transmission frame and after the HE-SIG-A. The first transmission frame is used to support a single user SU transmission mode, a single user multiple-input multiple-output SU MIMO transmission mode, and a downlink multi-user multiple-input multiple-output DL MU MIMO transmission mode. In a physical header of the second transmission frame,

there is no HE-SIG-A after an L-SIG and before an HE-STF, or there is an HE-SIG-A, but the HE-SIG-A includes only common information, so that decoding can still be performed after HE-SIG-As in second transmission frames sent by multiple sending devices superpose. The second transmission frame is used to support an uplink
5 orthogonal frequency division multiple access UL OFDMA transmission mode. The common information includes at least one of the following information: a network identifier, an identifier of the receiving device, or remaining transmission duration.

[0233] The receiving module 801 may be specifically configured to receive the physical header of the first transmission frame that is sent by the sending device and
10 has the first frame structure or the physical header of the second transmission frame that is sent by the sending device and has the second frame structure. In the physical header of the first transmission frame, there is the high efficiency wireless local area network first signaling field HE-SIG-A after the L-SIG and before the high efficiency wireless local area network short training field HE-STF. The HE-SIG-A includes the
15 control indication information, and the control indication information is used to instruct the receiving device how to decode all or a part of fields in the part that is of the first transmission frame and after the HE-SIG-A. The first transmission frame is used to support the single user SU transmission mode, the single user multiple-input multiple-output SU MIMO transmission mode, and the downlink multi-user
20 multiple-input multiple-output DL MU MIMO. In the physical header of the second transmission frame, there is no HE-SIG-A after the L-SIG and before the HE-STF, or there is an HE-SIG-A, but the HE-SIG-A includes only the common information, so that decoding can still be performed after the HE-SIG-As in the second transmission frames sent by the multiple sending devices superpose. The second transmission
25 frame is used to support the uplink orthogonal frequency division multiple access UL OFDMA transmission mode. The common information includes at least one of the following information: the network identifier, the identifier of the receiving device, or the remaining transmission duration.

[0234] In some embodiments of the present invention, the first transmission frame
30 is further used to support a downlink orthogonal frequency division multiple access DL OFDMA transmission mode, or the second transmission frame is further used to support a DL OFDMA transmission mode.

[0235] In some embodiments of the present invention, the first transmission frame is further used to support an uplink multi-user multiple-input multiple-output UL MU

MIMO transmission mode, or the second transmission frame is further used to support a UL MU MIMO transmission mode.

[0236] In some embodiments of the present invention, a high efficiency wireless local area network second signaling field HE-SIG-B is further included after the HE-SIG-A of the first transmission frame and before the HE-STF of the first transmission frame. The HE-SIG-B includes control indication information, and the control indication information included in the HE-SIG-B is used to instruct the receiving device how to decode a part that is of the first transmission frame and after the HE-SIG-B.

[0237] In some embodiments of the present invention, the HE-SIG-A or the HE-SIG-B of the first transmission frame further includes mode indication information, and the mode indication information is used to indicate a transmission mode specifically supported by the first transmission frame.

[0238] In some embodiments of the present invention, the generation module 701 may be specifically configured to generate a first transmission frame that has the first frame structure, or generate a second transmission frame that has the second frame structure. After a frame structure indication field, a physical header of the first transmission frame includes a time domain repetition of a particular field. A physical header of the second transmission frame includes the particular field, but does not include the time domain repetition of the particular field. Optionally, the particular field is an HE-SIG-A.

[0239] The receiving module 801 may be specifically configured to receive, by the receiving device, the physical header of the first transmission frame that is sent by the sending device and has the first frame structure or the physical header of the second transmission frame that is sent by the sending device and has the second frame structure. After the frame structure indication field, the physical header of the first transmission frame includes the time domain repetition of the particular field. The physical header of the second transmission frame includes the particular field, but does not include the time domain repetition of the particular field. Optionally, the particular field is the HE-SIG-A.

[0240] In some embodiments of the present invention, the frame structure indication field closely follows a legacy signaling field L-SIG; and

the frame structure indication field in the first frame structure and that in the second frame structure both are RL-SIGs, where the RL-SIG is a time domain

repetition of the L-SIG; or the frame structure indication field in the first frame structure is all or a part of OFDM symbols of the HE-SIG-A, and the frame structure indication field in the second frame structure is an RL-SIG, where the RL-SIG is a time domain repetition of the L-SIG; or the frame structure indication field in the first frame structure is all or a part of OFDM symbols of the HE-SIG-A, and the frame structure indication field in the second frame structure is all or a part of OFDM symbols of the HE-SIG-A; or the frame structure indication field in the first frame structure is an RL-SIG, and the frame structure indication field in the second frame structure is all or a part of OFDM symbols of the HE-SIG-A, where the RL-SIG is a time domain repetition of the L-SIG.

[0241] In some embodiments of the present invention, the first subcarrier polarity means that phases of a first group of subcarriers in multiple subcarriers included in the frame structure indication field are rotated by a first angle, and phases of a second group of subcarriers are rotated by a second angle; and the second subcarrier polarity means that the phases of the first group of subcarriers in the multiple subcarriers included in the frame structure indication field are rotated by the second angle, and the phases of the second group of subcarriers are rotated by the first angle, where the second angle is greater than the first angle, and the first angle is greater than or equal to 0 degree; or the first subcarrier polarity means that a first group of subcarriers in multiple subcarriers included in the frame structure indication field are filled, and a second group of subcarriers are vacant; and the second subcarrier polarity means that the first group of subcarriers in the multiple subcarriers included in the frame structure indication field are vacant, and the second group of subcarriers are filled; or the first subcarrier polarity means that phases of all subcarriers included in the frame structure indication field are rotated by a third angle, and the second subcarrier polarity means that the phases of all the subcarriers included in the frame structure indication field are rotated by a fourth angle, where the fourth angle is greater than the third angle, and the third angle is greater than 0 degree.

[0242] It may be seen from the foregoing that, in some feasible implementation manners of the present invention, in a technical solution, a subcarrier polarity of a frame structure indication field in a physical header of a transmission frame is used to indicate different frame structures, so as to obtain the following technical effects:

[0243] First, because a subcarrier polarity may have more expression manners, and may be used to indicate more frame structures, design of multiple frame

structures in a WLAN standard is supported, so as to satisfy a requirement that a HEW needs to support more transmission modes, support more frame structures, and indicate more frame structures.

[0244] Second, in some implementation manners, a frame structure indication field in a second frame structure includes only common information. In a scenario in which multiple devices perform sending, and one device performs receiving, frame structure indication fields in transmission frames sent by the multiple devices are the same, and may still be properly received and parsed after the frame structure indication fields superpose. Therefore, the second frame structure supports a scenario in which multiple devices perform sending, and one device performs receiving, and may be applied to a HEW into which any one or more of transmission modes in transmission modes of UL OFMDA, DL OFDMA, and UL MU MIMO are introduced.

[0245] Third, in some implementation manners, whether to perform time domain repetition on a particular field, for example, an HE-SIG-A, may be indicated by using a subcarrier polarity of a frame structure indication field. In some scenarios, the particular field is repeated to enhance reliability of the particular field, and in some other scenarios, the particular field is not repeated to reduce overheads.

[0246] Fourth, in some implementation manners, an expression manner of a subcarrier polarity is that a group of subcarriers are filled/phases of a group of subcarriers are rotated, and another group of subcarriers are vacant/phases of another group of subcarriers are not rotated. Because the expression manner has a higher identification degree, in comparison with an indication method in the prior art, in this embodiment of the present invention, a receiving device can more easily identify a structure of a transmission frame.

Embodiment 6

[0247] Referring to FIG. 10, this embodiment of the present invention further provides a subcarrier polarity expression method. The method may include the following steps:

[0248] 1001. Divide multiple subcarriers included in a specified OFDM symbol into at least two groups.

[0249] The division may be performed in any manner. For example, all

odd-numbered subcarriers are put into a first group, and all even-numbered subcarriers are put into a second group.

[0250] 1002. Rotate phases of one or more groups of subcarriers by a specific angle, so that phases of at least one group of subcarriers are different from phases of another group of subcarriers.

[0251] A phase of a subcarrier may be rotated by any angle, for example, 90 degrees, 45 degrees, or 75 degrees.

[0252] Phases of some subcarriers in the multiple subcarriers included in the specified OFDM symbol are rotated, so that the specified OFDM symbol may express multiple subcarrier polarities. The multiple subcarrier polarities may be used to indicate multiple types of information, for example, multiple transmission frame structures or whether a transmission frame includes some particular information, for example, a time domain repetition of a particular field (for example, an HE-SIG-A). Information indicated by using a subcarrier polarity is not limited in this specification.

[0253] This method not only may be used to indicate different transmission frame structures by using different subcarrier polarities, but also may be used for similar frame structure identification in an existing 802.11 standard. It may be stipulated that phases of some subcarriers in the first symbol after an L-SIG of a HEW frame structure are rotated, while some are not rotated, which is similar to the existing standard. For example, when phases of odd-numbered subcarriers are rotated by 90 degrees, and phases of even-numbered subcarriers are not rotated, it is indicated that the frame is a HEW frame. In comparison with an existing method in which phase rotation is performed on all subcarriers, this method has a higher identification degree.

[0254] An embodiment of the present invention further provides a computer storage medium. The computer storage medium may store a program. When being executed, the program includes all or a part of steps of the method for indicating a transmission frame structure that are recorded in the foregoing method embodiments.

[0255] Referring to FIG. 11, an embodiment of the present invention further provides a sending device 1100.

[0256] The sending device 1100 may be a computer with a microprocessor. For example, the sending device 1100 may be a portable device such as a general-purpose computer, a customized machine, a mobile phone terminal, or a tablet machine. The sending device 1100 includes: a processor 1104, a memory 1106, a communications interface 1102, and a bus 1108. By using the bus 1108, the processor 1104, the

memory 1106, and the communications interface 1102 are connected to each other and communicate with each other.

[0257] The bus 1108 may be an industry standard architecture (Industry Standard Architecture, ISA for short) bus, a Peripheral Component Interconnect (Peripheral Component, PCI for short) bus, an extended industry standard architecture (Extended Industry Standard Architecture, EISA for short) bus, or the like. The bus may be classified as one or more of an address bus, a data bus, a control bus, and the like. For ease of indication, the bus is represented by using only one thick line in FIG. 11. However, it does not indicate that there is only one bus or only one type of buses.

[0258] The memory 1106 is configured to store executable program code. The program code includes a computer operation instruction. When the sending device 1100 executes the program code, the sending device 1100 may complete steps 301 and 302 in Embodiment 1, and may also implement all functions of the sending device 700 in Embodiment 3. The memory 1106 may include a high-speed RAM (Random Access Memory) memory. Optionally, the memory 1106 may further include a non-volatile memory (non-volatile memory). For example, the memory 1106 may include a magnetic disk memory.

[0259] The processor 1104 may include one or more central processing units (Central Processing Unit, CPU for short), or the processor 1104 may be an application-specific integrated circuit (Application Specific Integrated Circuit, ASIC for short), or the processor 1104 may be one or more integrated circuits configured to implement this embodiment of the present invention.

[0260] The processor 1104 is configured to generate a transmission frame. A physical header of the transmission frame includes a frame structure indication field, and a subcarrier polarity of the frame structure indication field is used to indicate a frame structure of the transmission frame. When the subcarrier polarity of the frame structure indication field is a first subcarrier polarity, the transmission frame has a first frame structure. When the subcarrier polarity of the frame structure indication field is a second subcarrier polarity, the transmission frame has a second frame structure.

[0261] The communications interface 1102 may be a transceiver and is configured to send the transmission frame, so that a receiving device determines the frame structure of the transmission frame according to the subcarrier polarity of the frame structure indication field.

[0262] Optionally, the processor 1104 is further configured to generate a first

transmission frame that has the first frame structure, or generate a second transmission frame that has the second frame structure.

[0263] In a physical header of the first transmission frame, there is a high efficiency wireless local area network first signaling field HE-SIG-A after an L-SIG and before a high efficiency wireless local area network short training field HE-STF. The HE-SIG-A includes control indication information, and the control indication information is used to instruct the receiving device how to decode all or a part of fields in a part that is of the first transmission frame and after the HE-SIG-A. The first transmission frame is used to support a single user SU transmission mode, a single user multiple-input multiple-output SU MIMO transmission mode, and a downlink multi-user multiple-input multiple-output DL MU MIMO transmission mode.

[0264] In a physical header of the second transmission frame, there is no HE-SIG-A after an L-SIG and before an HE-STF, or there is an HE-SIG-A, but the HE-SIG-A includes only common information, so that decoding can still be performed after HE-SIG-As in second transmission frames sent by multiple sending devices superpose. The second transmission frame is used to support an uplink orthogonal frequency division multiple access UL OFDMA transmission mode.

[0265] Optionally, the common information includes at least one of the following information: a network identifier, an identifier of the receiving device, or remaining transmission duration.

[0266] Optionally, the first transmission frame is further used to support a downlink orthogonal frequency division multiple access DL OFDMA transmission mode, or the second transmission frame is further used to support a DL OFDMA transmission mode.

[0267] Optionally, the first transmission frame is further used to support an uplink multi-user multiple-input multiple-output UL MU MIMO transmission mode, or the second transmission frame is further used to support a UL MU MIMO transmission mode.

[0268] Optionally, a high efficiency wireless local area network second signaling field HE-SIG-B is further included after the HE-SIG-A of the first transmission frame and before the HE-STF of the first transmission frame. The HE-SIG-B includes control indication information, and the control indication information included in the HE-SIG-B is used to instruct the receiving device how to decode a part that is of the first transmission frame and after the HE-SIG-B.

[0269] Optionally, the HE-SIG-A or the HE-SIG-B of the first transmission frame further includes mode indication information, and the mode indication information is used to indicate a transmission mode specifically supported by the first transmission frame.

- 5 **[0270]** Optionally, the first subcarrier polarity means that phases of a first group of subcarriers in multiple subcarriers included in the frame structure indication field are rotated by a first angle, and phases of a second group of subcarriers are rotated by a second angle; and the second subcarrier polarity means that the phases of the first group of subcarriers in the multiple subcarriers included in the frame structure indication field are rotated by the second angle, and the phases of the second group of subcarriers are rotated by the first angle, where the second angle is greater than the first angle, and the first angle is greater than or equal to 0 degree; or

the first subcarrier polarity means that a first group of subcarriers in multiple subcarriers included in the frame structure indication field are filled, and a second group of subcarriers are vacant; and the second subcarrier polarity means that the first group of subcarriers in the multiple subcarriers included in the frame structure indication field are vacant, and the second group of subcarriers are filled; or

the first subcarrier polarity means that phases of all subcarriers included in the frame structure indication field are rotated by a third angle, and the second subcarrier polarity means that the phases of all the subcarriers included in the frame structure indication field are rotated by a fourth angle, where the fourth angle is greater than the third angle, and the third angle is greater than 0 degree.

- 20 **[0271]** Optionally, the processor 1104 is further configured to generate a first transmission frame that has the first frame structure, or generate a second transmission frame that has the second frame structure.

[0272] After a frame structure indication field, a physical header of the first transmission frame includes a time domain repetition of a particular field.

[0273] A physical header of the second transmission frame includes the particular field, but does not include the time domain repetition of the particular field.

- 30 **[0274]** Optionally, the particular field is an HE-SIG-A.

[0275] Optionally, the frame structure indication field closely follows a legacy signaling field L-SIG; and

the frame structure indication field in the first frame structure and that in the second frame structure both are RL-SIGs, where the RL-SIG is a time domain

repetition of the L-SIG; or

the frame structure indication field in the first frame structure is all or a part of OFDM symbols of the HE-SIG-A, and the frame structure indication field in the second frame structure is an RL-SIG, where the RL-SIG is a time domain

5 repetition of the L-SIG; or

the frame structure indication field in the first frame structure is all or a part of OFDM symbols of the HE-SIG-A, and the frame structure indication field in the second frame structure is all or a part of OFDM symbols of the HE-SIG-A; or

the frame structure indication field in the first frame structure is an RL-SIG,
10 and the frame structure indication field in the second frame structure is all or a part of OFDM symbols of the HE-SIG-A, where the RL-SIG is a time domain repetition of the L-SIG.

[0276] It should be noted that, functional units of the sending device provided in this embodiment of the present invention may be based on specific implementation of
15 the method provided in Embodiment 1 and that of functions that the device provided in Embodiment 3 has. Definitions and descriptions of terms are consistent with those in Embodiment 1 and Embodiment 3, and details are not described herein.

[0277] According to the sending device provided in this embodiment of the present invention, a subcarrier polarity of a frame structure indication field in a
20 physical header of a transmission frame is used to indicate different frame structures, so as to obtain the following technical effects:

[0278] First, because a subcarrier polarity may have more expression manners, and may be used to indicate more frame structures, design of multiple frame structures in a WLAN standard is supported, so as to satisfy a requirement that a
25 HEW needs to support more transmission modes, support more frame structures, and indicate more frame structures.

[0279] Second, in some implementation manners, a frame structure indication field in a second frame structure includes only common information. In a scenario in which multiple devices perform sending, and one device performs receiving, frame
30 structure indication fields in transmission frames sent by the multiple devices are the same, and may still be properly received and parsed after the frame structure indication fields superpose. Therefore, the second frame structure supports a scenario in which multiple devices perform sending, and one device performs receiving, and may be applied to a HEW into which any one or more of transmission modes in

transmission modes of UL OFMDA, DL OFDMA, and UL MU MIMO are introduced.

5 **[0280]** Third, in some implementation manners, whether to perform time domain repetition on a particular field, for example, an HE-SIG-A, may be indicated by using a subcarrier polarity of a frame structure indication field. In some scenarios, the particular field is repeated to enhance reliability of the particular field, and in some other scenarios, the particular field is not repeated to reduce overheads.

10 **[0281]** Fourth, in some implementation manners, an expression manner of a subcarrier polarity is that a group of subcarriers are filled/phases of a group of subcarriers are rotated, and another group of subcarriers are vacant/phases of another group of subcarriers are not rotated. Because the expression manner has a higher identification degree, in comparison with an indication method in the prior art, in this embodiment of the present invention, a receiving device can more easily identify a structure of a transmission frame.

15 **[0282]** Referring to FIG. 12, an embodiment of the present invention further provides a receiving device 1200.

20 **[0283]** The receiving device 1200 may be a computer with a microprocessor. For example, the receiving device 1200 may be a portable device such as a general-purpose computer, a customized machine, a mobile phone terminal, or a tablet machine. The receiving device 1200 includes: a processor 1204, a memory 1206, a communications interface 1202, and a bus 1208. By using the bus 1208, the processor 1204, the memory 1206, and the communications interface 1202 are connected to each other and communicate with each other.

25 **[0284]** The bus 1208 may be an industry standard architecture (Industry Standard Architecture, ISA for short) bus, a Peripheral Component Interconnect (Peripheral Component, PCI for short) bus, an extended industry standard architecture (Extended Industry Standard Architecture, EISA for short) bus, or the like. The bus may be classified as one or more of an address bus, a data bus, a control bus, and the like. For ease of indication, the bus is represented by using only one thick line in FIG. 12.
30 However, it does not indicate that there is only one bus or only one type of buses.

[0285] The memory 1206 is configured to store executable program code. The program code includes a computer operation instruction. When the receiving device 1200 executes the program code, the receiving device 1200 may complete steps 601 and 602 in Embodiment 2, and may also implement all functions of the sending

device 800 in Embodiment 4. The memory 1206 may include a high-speed RAM (Random Access Memory) memory. Optionally, the memory 1206 may further include a non-volatile memory (non-volatile memory). For example, the memory 1206 may include a magnetic disk memory.

5 **[0286]** The processor 1204 may be a central processing unit (Central Processing Unit, CPU for short), or the processor 1204 may be an application-specific integrated circuit (Application Specific Integrated Circuit, ASIC for short), or the processor 1204 may be one or more integrated circuits configured to implement this embodiment of the present invention.

10 **[0287]** The communications interface 1202 may be a transceiver and is configured to receive a physical header of a transmission frame sent by a sending device. The physical header of the transmission frame includes a frame structure indication field, and a subcarrier polarity of the frame structure indication field is used to indicate a frame structure of the transmission frame.

15 **[0288]** The processor 1204 is configured to determine the frame structure of the transmission frame according to the subcarrier polarity of the frame structure indication field. When the subcarrier polarity of the frame structure indication field is a first subcarrier polarity, the transmission frame has a first frame structure. When the subcarrier polarity of the frame structure indication field is a second subcarrier polarity, the transmission frame has a second frame structure.

20 **[0289]** Optionally, the frame structure indication field closely follows a legacy signaling field L-SIG. The communications interface 1202 is further configured to receive a physical header of a first transmission frame that is sent by the sending device and has the first frame structure or a physical header of a second transmission frame that is sent by the sending device and has the second frame structure.

25 **[0290]** In the physical header of the first transmission frame, there is a high efficiency wireless local area network first signaling field HE-SIG-A after an L-SIG and before a high efficiency wireless local area network short training field HE-STF. The HE-SIG-A includes control indication information, and the control indication information is used to instruct the receiving device how to decode all or a part of fields in a part that is of the first transmission frame and after the HE-SIG-A. The first transmission frame is used to support a single user SU transmission mode, a single user multiple-input multiple-output SU MIMO transmission mode, and downlink multi-user multiple-input multiple-output DL MU MIMO.

[0291] In the physical header of the second transmission frame, there is no HE-SIG-A after an L-SIG and before an HE-STF, or there is an HE-SIG-A, but the HE-SIG-A includes only common information, so that decoding can still be performed after HE-SIG-As in second transmission frames sent by multiple sending devices superpose. The second transmission frame is used to support an uplink orthogonal frequency division multiple access UL OFDMA transmission mode.

[0292] Optionally, the common information includes at least one of the following information: a network identifier, an identifier of the receiving device, or remaining transmission duration.

[0293] Optionally, the first transmission frame is further used to support a downlink orthogonal frequency division multiple access DL OFDMA transmission mode, or the second transmission frame is further used to support a DL OFDMA transmission mode.

[0294] Optionally, the first transmission frame is further used to support an uplink multi-user multiple-input multiple-output UL MU MIMO transmission mode, or the second transmission frame is further used to support a UL MU MIMO transmission mode.

[0295] Optionally, a high efficiency wireless local area network second signaling field HE-SIG-B is further included after the HE-SIG-A of the first transmission frame and before the HE-STF of the first transmission frame. The HE-SIG-B includes control indication information, and the control indication information included in the HE-SIG-B is used to instruct the receiving device how to decode a part that is of the first transmission frame and after the HE-SIG-B.

[0296] Optionally, the HE-SIG-A or the HE-SIG-B of the first transmission frame further includes mode indication information, and the processor 1204 is further configured to determine, according to the mode indication information, a transmission mode specifically supported by the frame structure of the first transmission frame.

[0297] Optionally, the first subcarrier polarity means that phases of a first group of subcarriers in multiple subcarriers included in the frame structure indication field are rotated by a first angle, and phases of a second group of subcarriers are rotated by a second angle; and the second subcarrier polarity means that the phases of the first group of subcarriers in the multiple subcarriers included in the frame structure indication field are rotated by the second angle, and the phases of the second group of subcarriers are rotated by the first angle, where the second angle is greater than the

first angle, and the first angle is greater than or equal to 0 degree; or

the first subcarrier polarity means that a first group of subcarriers in multiple subcarriers included in the frame structure indication field are filled, and a second group of subcarriers are vacant; and the second subcarrier polarity means that the first group of subcarriers in the multiple subcarriers included in the frame structure indication field are vacant, and the second group of subcarriers are filled; or

the first subcarrier polarity means that phases of all subcarriers included in the frame structure indication field are rotated by a third angle, and the second subcarrier polarity means that the phases of all the subcarriers included in the frame structure indication field are rotated by a fourth angle, where the fourth angle is greater than the third angle, and the third angle is greater than 0 degree.

[0298] Optionally, the communications interface 1202 is further configured to receive a physical header of a first transmission frame that is sent by the sending device and has the first frame structure or a physical header of a second transmission frame that is sent by the sending device and has the second frame structure.

[0299] After a frame structure indication field, the physical header of the first transmission frame includes a time domain repetition of a particular field.

[0300] The physical header of the second transmission frame includes the particular field, but does not include the time domain repetition of the particular field.

[0301] Optionally, the particular field is an HE-SIG-A.

[0302] Optionally, the frame structure indication field closely follows a legacy signaling field L-SIG; and

the frame structure indication field in the first frame structure and that in the second frame structure both are RL-SIGs, where the RL-SIG is a time domain repetition of the L-SIG; or

the frame structure indication field in the first frame structure is all or a part of OFDM symbols of the HE-SIG-A, and the frame structure indication field in the second frame structure is an RL-SIG, where the RL-SIG is a time domain repetition of the L-SIG; or

the frame structure indication field in the first frame structure is all or a part of OFDM symbols of the HE-SIG-A, and the frame structure indication field in the second frame structure is all or a part of OFDM symbols of the HE-SIG-A; or

the frame structure indication field in the first frame structure is an RL-SIG, and the frame structure indication field in the second frame structure is all or a part of

OFDM symbols of the HE-SIG-A, where the RL-SIG is a time domain repetition of the L-SIG.

[0303] It should be noted that, functional units of the receiving device provided in this embodiment of the present invention may be based on specific implementation of the method provided in Embodiment 2 and that of functions that the device provided in Embodiment 4 has. Definitions and descriptions of terms are consistent with those in Embodiment 2 and Embodiment 4, and details are not described herein.

[0304] According to the receiving device provided in this embodiment of the present invention, a frame structure of a transmission frame is determined by using a subcarrier polarity of a frame structure indication field in a received physical header of the transmission frame, so as to obtain the following technical effects:

[0305] First, because a subcarrier polarity may have more expression manners, and may be used to indicate more frame structures, design of multiple frame structures in a WLAN standard is supported, so as to satisfy a requirement that a HEW needs to support more transmission modes, support more frame structures, and indicate more frame structures.

[0306] Second, in some implementation manners, a frame structure indication field in a second frame structure includes only common information. In a scenario in which multiple devices perform sending, and one device performs receiving, frame structure indication fields in transmission frames sent by the multiple devices are the same, and may still be properly received and parsed after the frame structure indication fields superpose. Therefore, the second frame structure supports a scenario in which multiple devices perform sending, and one device performs receiving, and may be applied to a HEW into which any one or more of transmission modes in transmission modes of UL OFMDA, DL OFDMA, and UL MU MIMO are introduced.

[0307] Third, in some implementation manners, whether to perform time domain repetition on a particular field, for example, an HE-SIG-A, may be indicated by using a subcarrier polarity of a frame structure indication field. In some scenarios, the particular field is repeated to enhance reliability of the particular field, and in some other scenarios, the particular field is not repeated to reduce overheads.

[0308] Fourth, in some implementation manners, an expression manner of a subcarrier polarity is that a group of subcarriers are filled/phases of a group of subcarriers are rotated, and another group of subcarriers are vacant/phases of another

group of subcarriers are not rotated. Because the expression manner has a higher identification degree, in comparison with an indication method in the prior art, in this embodiment of the present invention, a receiving device can more easily identify a structure of a transmission frame.

5 **[0309]** In the foregoing embodiments, the description of each embodiment has respective focuses. For a part that is not described in detail in an embodiment, reference may be made to related descriptions in other embodiments.

10 **[0310]** It should be noted that, for ease of description, the foregoing method embodiments are described as a series of action combinations. However, a person skilled in the art should understand that the present invention is not limited to the described sequence of the actions, because some steps may be performed in another sequence or performed at the same time according to the present invention. In addition, a person skilled in the art should also understand that all the embodiments described in the specification are exemplary embodiments, and the related actions and
15 modules are not necessarily mandatory to the present invention.

20 **[0311]** A person of ordinary skill in the art may understand that all or some of the steps of the methods in the foregoing embodiments may be implemented by instructing relevant hardware by a program. The program may be stored in a computer readable storage medium. The storage medium may include: a ROM, a RAM, a magnetic disk, or an optical disc.

25 **[0312]** The method and device for indicating a transmission frame structure, and a system provided in the embodiments of the present invention are described in detail in the foregoing. Principles and implementation manners of the present invention are described by using specific examples in this specification. The descriptions about the embodiments are merely intended to help understand the method and core ideas of the present invention. In addition, a person of ordinary skill in the art can make modifications to a specific implementation manner and an application scope according to the ideas of the present invention. In conclusion, the content of this specification shall not be construed as a limitation on the present invention.

CLAIMS

What is claimed is:

1. A method for indicating a transmission frame structure, applied to a wireless local area network WLAN, wherein the method comprises:

5 generating, by a sending device, a transmission frame, wherein a physical header of the transmission frame comprises a frame structure indication field, and a subcarrier polarity of the frame structure indication field is used to indicate a frame structure of the transmission frame, wherein

10 when the subcarrier polarity of the frame structure indication field is a first subcarrier polarity, the transmission frame has a first frame structure, or when the subcarrier polarity of the frame structure indication field is a second subcarrier polarity, the transmission frame has a second frame structure; and

 sending the transmission frame.

15 2. The method according to claim 1, wherein the frame structure indication field closely follows a legacy signaling field L-SIG, and the generating, by a sending device, a transmission frame comprises:

 generating, by the sending device, a first transmission frame that has the first frame structure, or generating a second transmission frame that has the second frame structure, wherein

20 in a physical header of the first transmission frame, there is a high efficiency wireless local area network first signaling field HE-SIG-A after an L-SIG and before a high efficiency wireless local area network short training field HE-STF, wherein the HE-SIG-A comprises control indication information, the control indication information is used to instruct a receiving device how to decode all or a part of fields
25 in a part that is of the first transmission frame and after the HE-SIG-A, and the first transmission frame is used to support a single user SU transmission mode, a single user multiple-input multiple-output SU MIMO transmission mode, and a downlink multi-user multiple-input multiple-output DL MU MIMO transmission mode;

30 in a physical header of the second transmission frame, there is no HE-SIG-A after an L-SIG and before an HE-STF, or there is an HE-SIG-A, but the HE-SIG-A comprises only common information, so that decoding can still be performed after HE-SIG-As in second transmission frames sent by multiple sending devices that

comprise the sending device superpose, wherein the second transmission frame is used to support an uplink orthogonal frequency division multiple access UL OFDMA transmission mode, and

the common information comprises at least one of the following information: a network identifier, an identifier of the receiving device, or remaining transmission duration.

3. The method according to claim 2, wherein

the first transmission frame is further used to support a downlink orthogonal frequency division multiple access DL OFDMA transmission mode, or the second transmission frame is further used to support a DL OFDMA transmission mode.

4. The method according to claim 2 or 3, wherein

the first transmission frame is further used to support an uplink multi-user multiple-input multiple-output UL MU MIMO transmission mode, or the second transmission frame is further used to support a UL MU MIMO transmission mode.

5. The method according to any one of claims 2 to 4, wherein

a high efficiency wireless local area network second signaling field HE-SIG-B is further comprised after the HE-SIG-A of the first transmission frame and before the HE-STF of the first transmission frame, wherein the HE-SIG-B comprises control indication information, and the control indication information comprised in the HE-SIG-B is used to instruct the receiving device how to decode a part that is of the first transmission frame and after the HE-SIG-B.

6. The method according to claim 5, wherein

the HE-SIG-A or the HE-SIG-B of the first transmission frame further comprises mode indication information, wherein the mode indication information is used to indicate a transmission mode specifically supported by the first transmission frame.

7. The method according to claim 1, wherein

the generating, by a sending device, a transmission frame comprises: generating, by the sending device, a first transmission frame that has the first frame structure, or generating a second transmission frame that has the second frame structure, wherein

after a frame structure indication field, a physical header of the first transmission frame comprises a time domain repetition of a particular field; and

a physical header of the second transmission frame comprises the particular field, but does not comprise the time domain repetition of the particular field.

8. The method according to claim 7, wherein the particular field is an HE-SIG-A.

9. The method according to any one of claims 1 to 8, wherein the frame structure indication field closely follows a legacy signaling field L-SIG; and

the frame structure indication field in the first frame structure and that in the second frame structure both are RL-SIGs, wherein the RL-SIG is a time domain repetition of the L-SIG; or

the frame structure indication field in the first frame structure is all or a part of OFDM symbols of the HE-SIG-A, and the frame structure indication field in the second frame structure is an RL-SIG, wherein the RL-SIG is a time domain repetition of the L-SIG; or

the frame structure indication field in the first frame structure is all or a part of OFDM symbols of the HE-SIG-A, and the frame structure indication field in the second frame structure is all or a part of OFDM symbols of the HE-SIG-A; or

the frame structure indication field in the first frame structure is an RL-SIG, and the frame structure indication field in the second frame structure is all or a part of OFDM symbols of the HE-SIG-A, wherein the RL-SIG is a time domain repetition of the L-SIG.

10. The method according to any one of claims 1 to 9, wherein

the first subcarrier polarity means that phases of a first group of subcarriers in multiple subcarriers comprised in the frame structure indication field are rotated by a first angle, and phases of a second group of subcarriers are rotated by a second angle; and the second subcarrier polarity means that the phases of the first group of subcarriers in the multiple subcarriers comprised in the frame structure indication field are rotated by the second angle, and the phases of the second group of subcarriers are rotated by the first angle, wherein the second angle is greater than the first angle, and the first angle is greater than or equal to 0 degree; or

the first subcarrier polarity means that a first group of subcarriers in multiple subcarriers comprised in the frame structure indication field are filled, and a second group of subcarriers are vacant; and the second subcarrier polarity means that the first group of subcarriers in the multiple subcarriers comprised in the frame structure indication field are vacant, and the second group of subcarriers are filled; or

the first subcarrier polarity means that phases of all subcarriers comprised in the frame structure indication field are rotated by a third angle, and the second subcarrier polarity means that the phases of all the subcarriers comprised in the frame structure indication field are rotated by a fourth angle, wherein the fourth angle is greater than

the third angle, and the third angle is greater than 0 degree.

11. The method according to any one of claim 1, 7, or 8, wherein the frame structure indication field in the first frame structure is all or a part of OFDM symbols of the HE-SIG-A, and the frame structure indication field in the second frame structure is all or a part of OFDM symbols of the HE-SIG-A.

12. The method according to claim 11, wherein the HE-SIG-A is after an L-SIG and an RL-SIG.

13. A method for indicating a transmission frame structure, applied to a wireless local area network WLAN, wherein the method comprises:

10 receiving, by a receiving device, a physical header of a transmission frame sent by a sending device, wherein the physical header of the transmission frame comprises a frame structure indication field, and a subcarrier polarity of the frame structure indication field is used to indicate a frame structure of the transmission frame; and

determining the frame structure of the transmission frame according to the subcarrier polarity of the frame structure indication field, wherein when the subcarrier polarity of the frame structure indication field is a first subcarrier polarity, the transmission frame has a first frame structure, or when the subcarrier polarity of the frame structure indication field is a second subcarrier polarity, the transmission frame has a second frame structure.

14. The method according to claim 13, wherein the frame structure indication field closely follows a legacy signaling field L-SIG, and the receiving, by a receiving device, a physical header of a transmission frame sent by a sending device comprises:

receiving, by the receiving device, a physical header of a first transmission frame that is sent by the sending device and has the first frame structure or a physical header of a second transmission frame that is sent by the sending device and has the second frame structure, wherein

in the physical header of the first transmission frame, there is a high efficiency wireless local area network first signaling field HE-SIG-A after an L-SIG and before a high efficiency wireless local area network short training field HE-STF, wherein the HE-SIG-A comprises control indication information, the control indication information is used to instruct the receiving device how to decode all or a part of fields in a part that is of the first transmission frame and after the HE-SIG-A, and the first transmission frame is used to support a single user SU transmission mode, a single user multiple-input multiple-output SU MIMO transmission mode, and

downlink multi-user multiple-input multiple-output DL MU MIMO;

in the physical header of the second transmission frame, there is no HE-SIG-A after an L-SIG and before an HE-STF, or there is an HE-SIG-A, but the HE-SIG-A comprises only common information, so that decoding can still be performed after
5 HE-SIG-As in second transmission frames sent by multiple sending devices superpose, wherein the second transmission frame is used to support an uplink orthogonal frequency division multiple access UL OFDMA transmission mode, and

the common information comprises at least one of the following information: a network identifier, an identifier of the receiving device, or remaining transmission
10 duration.

15. The method according to claim 14, wherein

the first transmission frame is further used to support a downlink orthogonal frequency division multiple access DL OFDMA transmission mode, or the second transmission frame is further used to support a DL OFDMA transmission mode.

15 16. The method according to claim 14 or 15, wherein

the first transmission frame is further used to support an uplink multi-user multiple-input multiple-output UL MU MIMO transmission mode, or the second transmission frame is further used to support a UL MU MIMO transmission mode.

17. The method according to any one of claims 14 to 16, wherein

20 a high efficiency wireless local area network second signaling field HE-SIG-B is further comprised after the HE-SIG-A of the first transmission frame and before the HE-STF of the first transmission frame, wherein the HE-SIG-B comprises control indication information, and the control indication information comprised in the HE-SIG-B is used to instruct the receiving device how to decode a part that is of the
25 first transmission frame and after the HE-SIG-B.

18. The method according to claim 17, wherein the HE-SIG-A or the HE-SIG-B of the first transmission frame further comprises mode indication information, and the method further comprises:

determining, according to the mode indication information, a transmission mode
30 specifically supported by the frame structure of the first transmission frame.

19. The method according to claim 13, wherein the receiving, by a receiving device, a physical header of a transmission frame sent by a sending device comprises:

receiving, by the receiving device, a physical header of a first transmission frame that is sent by the sending device and has the first frame structure or a physical header

of a second transmission frame that is sent by the sending device and has the second frame structure, wherein

after a frame structure indication field, the physical header of the first transmission frame comprises a time domain repetition of a particular field; and

5 the physical header of the second transmission frame comprises the particular field, but does not comprise the time domain repetition of the particular field.

20. The method according to claim 19, wherein the particular field is an HE-SIG-A.

21. The method according to any one of claims 13 to 20, wherein the frame
10 structure indication field closely follows a legacy signaling field L-SIG; and

the frame structure indication field in the first frame structure and that in the second frame structure both are RL-SIGs, wherein the RL-SIG is a time domain repetition of the L-SIG; or

the frame structure indication field in the first frame structure is all or a part of
15 OFDM symbols of the HE-SIG-A, and the frame structure indication field in the second frame structure is an RL-SIG, wherein the RL-SIG is a time domain repetition of the L-SIG; or

the frame structure indication field in the first frame structure is all or a part of OFDM symbols of the HE-SIG-A, and the frame structure indication field in the
20 second frame structure is all or a part of OFDM symbols of the HE-SIG-A; or

the frame structure indication field in the first frame structure is an RL-SIG, and the frame structure indication field in the second frame structure is all or a part of OFDM symbols of the HE-SIG-A, wherein the RL-SIG is a time domain repetition of the L-SIG.

22. The method according to any one of claims 13 to 21, wherein

the first subcarrier polarity means that phases of a first group of subcarriers in multiple subcarriers comprised in the frame structure indication field are rotated by a first angle, and phases of a second group of subcarriers are rotated by a second angle; and the second subcarrier polarity means that the phases of the first group of
30 subcarriers in the multiple subcarriers comprised in the frame structure indication field are rotated by the second angle, and the phases of the second group of subcarriers are rotated by the first angle, wherein the second angle is greater than the first angle, and the first angle is greater than or equal to 0 degree; or

the first subcarrier polarity means that a first group of subcarriers in multiple

subcarriers comprised in the frame structure indication field are filled, and a second group of subcarriers are vacant; and the second subcarrier polarity means that the first group of subcarriers in the multiple subcarriers comprised in the frame structure indication field are vacant, and the second group of subcarriers are filled; or

5 the first subcarrier polarity means that phases of all subcarriers comprised in the frame structure indication field are rotated by a third angle, and the second subcarrier polarity means that the phases of all the subcarriers comprised in the frame structure indication field are rotated by a fourth angle, wherein the fourth angle is greater than the third angle, and the third angle is greater than 0 degree.

10 23. The method according to any one of claim 13, 19, or 20, wherein the frame structure indication field in the first frame structure is all or a part of OFDM symbols of the HE-SIG-A, and the frame structure indication field in the second frame structure is all or a part of OFDM symbols of the HE-SIG-A.

15 24. The method according to claim 23, wherein the HE-SIG-A is after an L-SIG and an RL-SIG.

25. A sending device for indicating a transmission frame structure, applied to a wireless local area network WLAN, wherein the sending device comprises:

20 a generation module, configured to generate a transmission frame, wherein a physical header of the transmission frame comprises a frame structure indication field, and a subcarrier polarity of the frame structure indication field is used to indicate a frame structure of the transmission frame, wherein

25 when the subcarrier polarity of the frame structure indication field is a first subcarrier polarity, the transmission frame has a first frame structure, or when the subcarrier polarity of the frame structure indication field is a second subcarrier polarity, the transmission frame has a second frame structure; and

 a sending module, configured to send the transmission frame.

30 26. The device according to claim 25, wherein the frame structure indication field closely follows a legacy signaling field L-SIG, and the generation module is specifically configured to generate a first transmission frame that has the first frame structure, or generate a second transmission frame that has the second frame structure, wherein

 in a physical header of the first transmission frame, there is a high efficiency wireless local area network first signaling field HE-SIG-A after an L-SIG and before a high efficiency wireless local area network short training field HE-STF, wherein the

HE-SIG-A comprises control indication information, the control indication information is used to instruct a receiving device how to decode all or a part of fields in a part that is of the first transmission frame and after the HE-SIG-A, and the first transmission frame is used to support a single user SU transmission mode, a single user multiple-input multiple-output SU MIMO transmission mode, and a downlink multi-user multiple-input multiple-output DL MU MIMO transmission mode;

in a physical header of the second transmission frame, there is no HE-SIG-A after an L-SIG and before an HE-STF, or there is an HE-SIG-A, but the HE-SIG-A comprises only common information, so that decoding can still be performed after HE-SIG-As in second transmission frames sent by multiple sending devices that comprise the sending device superpose, wherein the second transmission frame is used to support an uplink orthogonal frequency division multiple access UL OFDMA transmission mode, and

the common information comprises at least one of the following information: a network identifier, an identifier of the receiving device, or remaining transmission duration.

27. The device according to claim 26, wherein

the first transmission frame is further used to support a downlink orthogonal frequency division multiple access DL OFDMA transmission mode, or the second transmission frame is further used to support a DL OFDMA transmission mode.

28. The device according to claim 26 or 27, wherein

the first transmission frame is further used to support an uplink multi-user multiple-input multiple-output UL MU MIMO transmission mode, or the second transmission frame is further used to support a UL MU MIMO transmission mode.

29. The device according to any one of claims 26 to 28, wherein

a high efficiency wireless local area network second signaling field HE-SIG-B is further comprised after the HE-SIG-A of the first transmission frame and before the HE-STF of the first transmission frame, wherein the HE-SIG-B comprises control indication information, and the control indication information comprised in the HE-SIG-B is used to instruct the receiving device how to decode a part that is of the first transmission frame and after the HE-SIG-B.

30. The device according to claim 29, wherein

the HE-SIG-A or the HE-SIG-B of the first transmission frame further comprises mode indication information, wherein the mode indication information is used to

indicate a transmission mode specifically supported by the first transmission frame.

31. The device according to claim 25, wherein the generation module is specifically configured to:

5 generate a first transmission frame that has the first frame structure, or generate a second transmission frame that has the second frame structure, wherein

after a frame structure indication field, a physical header of the first transmission frame comprises a time domain repetition of a particular field; and

a physical header of the second transmission frame comprises the particular field, but does not comprise the time domain repetition of the particular field.

10 32. The device according to claim 31, wherein the particular field is an HE-SIG-A.

33. The device according to any one of claims 25 to 32, wherein the frame structure indication field closely follows a legacy signaling field L-SIG; and

15 the frame structure indication field in the first frame structure and that in the second frame structure both are RL-SIGs, wherein the RL-SIG is a time domain repetition of the L-SIG; or

the frame structure indication field in the first frame structure is all or a part of OFDM symbols of the HE-SIG-A, and the frame structure indication field in the second frame structure is an RL-SIG, wherein the RL-SIG is a time domain repetition
20 of the L-SIG; or

the frame structure indication field in the first frame structure is all or a part of OFDM symbols of the HE-SIG-A, and the frame structure indication field in the second frame structure is all or a part of OFDM symbols of the HE-SIG-A; or

the frame structure indication field in the first frame structure is an RL-SIG, and
25 the frame structure indication field in the second frame structure is all or a part of OFDM symbols of the HE-SIG-A, wherein the RL-SIG is a time domain repetition of the L-SIG.

34. The device according to any one of claims 25 to 33, wherein

the first subcarrier polarity means that phases of a first group of subcarriers in
30 multiple subcarriers comprised in the frame structure indication field are rotated by a first angle, and phases of a second group of subcarriers are rotated by a second angle; and the second subcarrier polarity means that the phases of the first group of subcarriers in the multiple subcarriers comprised in the frame structure indication field are rotated by the second angle, and the phases of the second group of

subcarriers are rotated by the first angle, wherein the second angle is greater than the first angle, and the first angle is greater than or equal to 0 degree; or

the first subcarrier polarity means that a first group of subcarriers in multiple subcarriers comprised in the frame structure indication field are filled, and a second group of subcarriers are vacant; and the second subcarrier polarity means that the first group of subcarriers in the multiple subcarriers comprised in the frame structure indication field are vacant, and the second group of subcarriers are filled; or

the first subcarrier polarity means that phases of all subcarriers comprised in the frame structure indication field are rotated by a third angle, and the second subcarrier polarity means that the phases of all the subcarriers comprised in the frame structure indication field are rotated by a fourth angle, wherein the fourth angle is greater than the third angle, and the third angle is greater than 0 degree.

35. The method according to any one of claims 25, 31, or 32, wherein the frame structure indication field in the first frame structure is all or a part of OFDM symbols of the HE-SIG-A, and the frame structure indication field in the second frame structure is all or a part of OFDM symbols of the HE-SIG-A.

36. The method according to claim 35, wherein the HE-SIG-A is after an L-SIG and an RL-SIG.

37. A receiving device for indicating a transmission frame structure, applied to a wireless local area network WLAN, wherein the receiving device comprises:

a receiving module, configured to receive a physical header of a transmission frame sent by a sending device, wherein the physical header of the transmission frame comprises a frame structure indication field, and a subcarrier polarity of the frame structure indication field is used to indicate a frame structure of the transmission frame; and

a determining module, configured to determine the frame structure of the transmission frame according to the subcarrier polarity of the frame structure indication field, wherein when the subcarrier polarity of the frame structure indication field is a first subcarrier polarity, the transmission frame has a first frame structure, or when the subcarrier polarity of the frame structure indication field is a second subcarrier polarity, the transmission frame has a second frame structure.

38. The device according to claim 37, wherein the frame structure indication field closely follows a legacy signaling field L-SIG, and the receiving module is specifically configured to receive a physical header of a first transmission frame that

is sent by the sending device and has the first frame structure or a physical header of a second transmission frame that is sent by the sending device and has the second frame structure, wherein

in the physical header of the first transmission frame, there is a high efficiency wireless local area network first signaling field HE-SIG-A after an L-SIG and before a high efficiency wireless local area network short training field HE-STF, wherein the HE-SIG-A comprises control indication information, the control indication information is used to instruct the receiving device how to decode all or a part of fields in a part that is of the first transmission frame and after the HE-SIG-A, and the first transmission frame is used to support a single user SU transmission mode, a single user multiple-input multiple-output SU MIMO transmission mode, and downlink multi-user multiple-input multiple-output DL MU MIMO;

in the physical header of the second transmission frame, there is no HE-SIG-A after an L-SIG and before an HE-STF, or there is an HE-SIG-A, but the HE-SIG-A comprises only common information, so that decoding can still be performed after HE-SIG-As in second transmission frames sent by multiple sending devices superpose, wherein the second transmission frame is used to support an uplink orthogonal frequency division multiple access UL OFDMA transmission mode, and

the common information comprises at least one of the following information: a network identifier, an identifier of the receiving device, or remaining transmission duration.

39. The device according to claim 38, wherein

the first transmission frame is further used to support a downlink orthogonal frequency division multiple access DL OFDMA transmission mode, or the second transmission frame is further used to support a DL OFDMA transmission mode.

40. The device according to claim 38 or 39, wherein

the first transmission frame is further used to support an uplink multi-user multiple-input multiple-output UL MU MIMO transmission mode, or the second transmission frame is further used to support a UL MU MIMO transmission mode.

41. The device according to any one of claims 38 to 40, wherein

a high efficiency wireless local area network second signaling field HE-SIG-B is further comprised after the HE-SIG-A of the first transmission frame and before the HE-STF of the first transmission frame, wherein the HE-SIG-B comprises control indication information, and the control indication information comprised in the

HE-SIG-B is used to instruct the receiving device how to decode a part that is of the first transmission frame and after the HE-SIG-B.

42. The device according to claim 41, wherein the HE-SIG-A or the HE-SIG-B of the first transmission frame further comprises mode indication information, and the
5 determining module is further configured to:

determine, according to the mode indication information, a transmission mode specifically supported by the frame structure of the first transmission frame.

43. The device according to claim 37, wherein the receiving module is specifically configured to:

10 receive a physical header of a first transmission frame that is sent by the sending device and has the first frame structure or a physical header of a second transmission frame that is sent by the sending device and has the second frame structure, wherein

after a frame structure indication field, the physical header of the first transmission frame comprises a time domain repetition of a particular field; and

15 the physical header of the second transmission frame comprises the particular field, but does not comprise the time domain repetition of the particular field.

44. The device according to claim 43, wherein the particular field is an HE-SIG-A.

20 45. The device according to any one of claims 37 to 44, wherein the frame structure indication field closely follows a legacy signaling field L-SIG; and

the frame structure indication field in the first frame structure and that in the second frame structure both are RL-SIGs, wherein the RL-SIG is a time domain repetition of the L-SIG; or

25 the frame structure indication field in the first frame structure is all or a part of OFDM symbols of the HE-SIG-A, and the frame structure indication field in the second frame structure is an RL-SIG, wherein the RL-SIG is a time domain repetition of the L-SIG; or

30 the frame structure indication field in the first frame structure is all or a part of OFDM symbols of the HE-SIG-A, and the frame structure indication field in the second frame structure is all or a part of OFDM symbols of the HE-SIG-A; or

the frame structure indication field in the first frame structure is an RL-SIG, and the frame structure indication field in the second frame structure is all or a part of OFDM symbols of the HE-SIG-A, wherein the RL-SIG is a time domain repetition of

the L-SIG.

46. The device according to any one of claims 37 to 45, wherein

the first subcarrier polarity means that phases of a first group of subcarriers in multiple subcarriers comprised in the frame structure indication field are rotated by a first angle, and phases of a second group of subcarriers are rotated by a second angle; and the second subcarrier polarity means that the phases of the first group of subcarriers in the multiple subcarriers comprised in the frame structure indication field are rotated by the second angle, and the phases of the second group of subcarriers are rotated by the first angle, wherein the second angle is greater than the first angle, and the first angle is greater than or equal to 0 degree; or

the first subcarrier polarity means that a first group of subcarriers in multiple subcarriers comprised in the frame structure indication field are filled, and a second group of subcarriers are vacant; and the second subcarrier polarity means that the first group of subcarriers in the multiple subcarriers comprised in the frame structure indication field are vacant, and the second group of subcarriers are filled; or

the first subcarrier polarity means that phases of all subcarriers comprised in the frame structure indication field are rotated by a third angle, and the second subcarrier polarity means that the phases of all the subcarriers comprised in the frame structure indication field are rotated by a fourth angle, wherein the fourth angle is greater than the third angle, and the third angle is greater than 0 degree.

47. The method according to any one of claim 37, 43, or 44, wherein the frame structure indication field in the first frame structure is all or a part of OFDM symbols of the HE-SIG-A, and the frame structure indication field in the second frame structure is all or a part of OFDM symbols of the HE-SIG-A.

48. The method according to claim 47, wherein the HE-SIG-A is after an L-SIG and an RL-SIG.

49. A communications system, wherein

the communications system comprises: the sending device according to any one of claims 25 to 30, and the receiving device according to any one of claims 37 to 42; or

the communications system comprises: the sending device according to any one of claims 31, 32, 35, and 36, and the receiving device according to any one of claims 43, 44, 47, and 48.