



LUMINANCE/CHROMINANCE SEPARATING FILTER

BACKGROUND OF THE INVENTION

The present invention relates to a luminance/chrominance separating filter for separating luminance and chrominance signals from, for example, an NTSC composite color television signal.

Fig. 43 shows an example of a conventional luminance/chrominance separating filter (YC separating filter) with an NTSC composite color television signal applied to the input terminal 11. An A/D converter 12 converts the analog composite color television signal input via the input terminal 11 into a digital signal. The output signal of the A/D converter 12 is applied to a first 1-line delay circuit 13.

The conventional system further comprises a second 1-line delay circuit 14, a compensating delay circuit 19, a vertical chrominance (V-C) extraction filter 15, a horizontal chrominance (H-C) extraction filter 16, a horizontal and vertical chrominance (HV-C) extraction filter 17, a picture non-correlation decision circuit 18, compensating delay circuits 19 - 22, a selector 23 provided with an output terminal 26, and a subtractor 27 provided with an output terminal 28.

Fig. 11 shows an example of the picture non-correlation decision circuit 18 in Fig. 43. As illustrated, the picture non-correlation decision circuit 18 comprises a horizontal chrominance non-correlation (H-C) energy extractor 29, a horizontal luminance (H-Y) non-correlation energy extractor 30, a vertical chrominance (V-C) non-correlation energy extractor 31, a vertical luminance (V-Y) non-correlation energy extractor 32, maximum value circuits (MAXs) 33 - 36, comparators 37 - 39, a decision circuit 40, multipliers 71, 72, 73a, 73b, 74a, 74b, 77, 78, 79a, 79b and 80, and delay



circuits 86 - 89.


The output signal 101 from the A/D converter 12 in Fig. 43 is applied to the horizontal luminance non-correlation energy extractor 30, the vertical chrominance non-correlation energy extractor 31 and the vertical luminance non-correlation energy extractor 32.

In the foregoing, "non-correlation energy" refers to the signal high frequency component arising, depending on the degree of signal variation. As the signal variation is increased or sharper the high frequency component in the direction of the variation is increased. Thus, the "non-correlation energy" represents the signal high frequency component energy, which can be obtained by extracting the required band (high-frequency band) component through a two dimensional (or one dimensional) filtering process (energy extraction). The required band can be expressed on a two dimensional frequency plane, shown for example in Fig. 44 to Fig. 47.

The output signal 102 of the first 1-line delay circuit 13 is applied to the horizontal chrominance non-correlation energy extractor 29, the horizontal luminance non-correlation energy extractor 30 and the vertical luminance non-correlation energy extractor 32.

The output signal 103 of the second 1-line delay circuit 14 is applied to the horizontal luminance non-correlation energy extractor 30, the vertical chrominance non-correlation energy extractor 31 and the vertical luminance non-correlation energy extractor 32.

The output signal DCH of the horizontal chrominance non-correlation energy extractor 29 is branched in three routes. In the first route, the signal is multiplied by a coefficient b at the multiplier 72 and the resultant signal is sent to the maximum value circuit 33. In the second route, the signal is multiplied by a coefficient f_1 at the



multiplier 74a and the resultant signal is sent to the maximum value circuit 34. In the third route, the signal is multiplied by a coefficient f_2 at the multiplier 74b and the resultant signal is sent to the maximum value circuit 35.

The output signal DYH of the horizontal luminance non-correlation energy extractor 30 is branched in three routes. In the first route, the signal is multiplied by a coefficient a at the multiplier 71 and the resultant signal is sent to the maximum value circuit 34. In the second route, the signal is multiplied by a coefficient e_1 at the multiplier 73a and the resultant signal is sent to the maximum value circuit 34. In the third route, the signal is multiplied by a coefficient e_2 at the multiplier 73b and the resultant signal is sent to the maximum value circuit 35.

The output signal DCV of the vertical chrominance non-correlation energy extractor 31 is branched in two routes. In the first route, the signal is sent to the comparator 38. In the second route, the signal is multiplied by a coefficient d at the multiplier 78 and the resultant signal is sent to the maximum value circuit 36.

The output signal DYV of the vertical luminance non-correlation energy extractor 32 is branched in two routes. In the first route, the signal is sent to the comparator 39. In the second route, the signal is multiplied by a coefficient c at the multiplier 77 and the resultant signal is sent to the maximum value circuit 36.

The output signal of the maximum value circuit 33 is applied as a first horizontal non-correlation energy DH1 to the comparator 37.

The output signal of the maximum value circuit 34, as a second horizontal non-correlation energy DH21, is multiplied by a coefficient m_1 at the multiplier 79a, and is then sent to the comparator 38.

The output signal of the maximum value circuit 35, as a



third horizontal non-correlation energy DH22. is multiplied by a coefficient m2 at the multiplier 79b, and is then sent to the comparator 39.

The output of the the maximum value circuit 36, as a vertical non-correlation energy DV, is multiplied by a coefficient n, and is then sent to the comparator 37.

The comparator 37 compares the first horizontal non-correlation energy DH1 and the product $n \cdot DV$ obtained by multiplying the vertical non-correlation energy DV by the coefficient n, and produces a high level output signal 116 when $DH1 \geq n \cdot DV$, and a low level output signal 116 at other times.

The comparator 38 compares the vertical chrominance non-correlation energy DCV and the product $m1 \cdot DH21$ obtained by multiplying the second horizontal non-correlation energy DH21 by the coefficient m1, and produces a high level output signal 117 when $DCV \geq m1 \cdot DH21$, and a low level output signal 117 at other times.

The comparator 39 compares the vertical luminance non-correlation energy DYV and the product $m2 \cdot DH22$ obtained by multiplying the third horizontal non-correlation energy DH22 by the coefficient m2, and produces a high level output signal 118 when $DYV \geq m2 \cdot DH22$, and a low level output signal 118 at other times.

The output signal 116 of the comparator 37 is applied to the delay circuit 86 and the output signal 117 of the comparator 38 is applied to the delay circuit 87.

The output signal 118 of the comparator 39 is applied to the delay circuit 88 and the AND circuit 90; the output signal 121 of the delay circuit 88 is applied to the delay circuit 89 and the AND circuit 90.

The output signal 122 of the delay circuit 89 is applied to the AND circuit 90. The output signal 119 of the delay circuit 86, the output signal 120 of the delay circuit



87 and the output signal 124 of the AND circuit are applied to the decision circuit 40. The output signal 110 of the decision circuit 40 is then sent out as the output of the picture non-correlation decision circuit 18.

Fig. 48 shows an example of the decision circuit 40 in Fig. 11. The circuit comprises AND circuits 41 and 42, a NOT circuit 43 and a NOR circuit 44. The output signal 119 of the delay circuit 86 is applied to one input of the AND circuit 42 and to the input of the NOT circuit 43. The respective output signals 120 and 123 of the delay circuit 87 and AND circuit 90 are applied to the NOR circuit 44.

The output signal of the NOR circuit 44 is applied to the other input of the AND circuit 42 and to one input of the AND circuit 41. The output signal of the NOT circuit 43 is applied to the other input of the AND circuit 41.


The outputs of the AND circuits 41 and 42 form the output signal 110 of the decision circuit 40.

Fig. 49 shows an example of the horizontal chrominance non-correlation energy extractor 29 in Fig. 11. The circuit comprises a delay circuit 45 having a delay equivalent to one period ($1/f_{sc}$) of the color subcarrier having a frequency f_{sc} , a subtractor 46 and an absolute value circuit (ABS) 47.

The output signal 102 of the first 1-line delay circuit 13 is applied to the delay circuit 45 and one input of the subtractor 46. The output signal of the delay circuit 45 is applied to the other input of the subtractor 46. The output signal of the subtractor 46 is applied to the absolute value circuit 47.

The output of this absolute value circuit 47 forms the horizontal chrominance non-correlation energy.

Fig. 50 shows an example of the horizontal luminance non-correlation energy extractor 30 used in Fig. 11. The circuit comprises a vertical direction lowpass filter (LPF)



48, delay circuits 49 and 50 each having a delay equivalent to $1/2$ the period ($1/2f_{sc}$) of the color subcarrier, subtractors 51 and 52, absolute value circuits 53 and 54, and a maximum value circuit 55.

The respective output signals 101, 102 and 103 of the A/D converter 12, the first 1-line delay circuit 13 and the second 1-line delay circuit 14 are applied to the vertical direction lowpass filter 48.

The output signal of the vertical direction lowpass filter 48 is applied to the delay circuit 49 and one input of the subtractor 51. The output signal of the delay circuit 49 is applied to the delay circuit 50, the other input of the subtractor 51 and one input of the subtractor 52. The output signal of the delay circuit 50 is applied to the other input of the subtractor 52.

The output signal of the subtractor 51 is applied to the absolute value circuit 53 and the output signal of the absolute value circuit 53 is applied to the maximum value circuit 55. The output signal of the subtractor 52 is applied to the absolute value circuit 54 and the output signal of the absolute value circuit 54 is applied to the maximum value circuit 55.

The output signal of the maximum value circuit 55 forms the output DYH of the horizontal luminance non-correlation energy extractor 30.

Fig. 51 shows an example of the vertical chrominance non-correlation energy extractor 31 in Fig. 11. The circuit comprises horizontal bandpass filters (BPFs) 56 and 57, a subtractor 58 and an absolute value circuit 59.

The output signal 101 of the A/D converter 12 is applied to the horizontal bandpass filter 56. The output signal 103 of the second 1-line delay circuit 14 is applied to the horizontal bandpass filter 57. The output signal of the horizontal bandpass filter 56 is applied to one input of



the subtractor 58, while the output signal of the horizontal bandpass filter 57 is applied to the other input of the subtractor 58. The output signal of the subtractor 58 is applied to the absolute value circuit 59. The output signal of the absolute value circuit 59 forms the output DCV of the vertical chrominance non-correlation energy extractor 31.

Fig. 52 shows an example of the vertical luminance non-correlation energy extractor 32 used in Fig. 11. The circuit comprises horizontal lowpass filters 60, 61 and 62, subtractors 63 and 64, absolute value circuits 65 and 66, and a maximum value circuit 67.

The output signal 101 of the A/D converter 12 is applied to the horizontal lowpass filter 60. The output signal 102 of the first 1-line delay circuit 13 is applied to the horizontal lowpass filter 61. The output signal 103 of the second 1-line delay circuit 14 is applied to the horizontal lowpass filter 62.

The output signal of the horizontal lowpass filter 60 is applied to one input of the subtractor 63. The output signal of the horizontal lowpass filter 61 is applied to the other input of the subtractor 63 and to one input of the subtractor 64. The output signal of the horizontal lowpass filter 62 is applied to the other input of the subtractor 64.

The output signal of the subtractor 63 is applied to the absolute value circuit 65 and the output signal of the subtractor 64 is applied to the absolute value circuit 66.

The outputs of the absolute value circuits 65 and 66 are applied to the maximum value circuit 67. The output signal of the absolute value circuit 67 forms the output DYV of the vertical luminance non-correlation energy extractor 32.

Following is a description of the principle and operation of the conventional YC separating filter indicated



in Fig. 43, Fig. 11, and Fig. 48 to Fig. 52.

When the horizontal frequency μ and vertical frequency ν axes are plotted on a two dimensional plane, the NTSC composite color television signal distribution appears as shown in Fig. 44. This signal distribution takes different forms according to the two dimensional correlation of the picture. For example, if the correlation is weak in the vertical direction, but strong in the horizontal, the signal distribution appears as indicated in Fig. 45. In this case, the chrominance signal can be extracted using a horizontal chrominance extraction filter having a passband as indicated by the shaded rectangles in the figure.

If the correlation is strong in the vertical direction, but weak in the horizontal, the signal distribution appears as indicated in Fig. 46. In this case, the chrominance signal can be extracted using a vertical chrominance extraction filter having a passband as indicated by the shaded rectangles in the figure.

When the correlation is strong in both directions, the signal distribution appears as indicated in Fig. 47. In this case, the chrominance signal can be extracted by using a horizontal and vertical chrominance extraction filter having a passband as indicated by the shaded rectangles in the figure.

As indicated in Fig. 43, in the case of this YC separating filter, the selection is made in accordance with the output of the picture non-correlation decision circuit 18 provided with the vertical chrominance extraction filter 15, the horizontal chrominance extraction filter 16, and the horizontal and vertical chrominance extraction filter 17.

It will be seen from Fig. 45 that the condition on which the horizontal chrominance extraction filter is selected is that there is much chrominance signal vertical high frequency component (there is much color component in



the shaded rectangles) and there is little luminance signal horizontal high frequency component (there is little color component in the shaded rectangles).

It will be seen from Fig. 46 that the condition on which the vertical chrominance extraction filter is selected is that there is much chrominance signal horizontal high frequency component (there is much color component in the shaded rectangles) and there is little luminance signal vertical high frequency component (there is little luminance component in the shaded rectangles).

If neither of the conditions for selecting either of the above horizontal or vertical chrominance signal extraction filters is met, the horizontal and vertical chrominance extraction filter is selected.

Following is a description of the process from derivation of these conditions to the filter selection.

When an NTSC composite color television signal is applied via the input terminal 11, the A/D converter 12 samples this composite color television signal at a sampling frequency $f_s = 4 \cdot f_{sc}$ (f_{sc} is the color subcarrier frequency). The sampled composite color television signal forms a two dimensional arrangement on the screen as indicated in Fig. 53. Since $f_{sc} = (455/2)f_H$, the phase of the chrominance signal C reverses 180 degrees every line and 4 samples per period are taken.

In the figure, Y denotes the luminance signal, C_1 and C_2 denote chrominance signals having a 180° phase difference, blank circles are $Y + C_1$, shaded circles are $Y - C_1$, blank triangles are $Y + C_2$ and shaded triangles are $Y - C_2$. By passing this composite color television signal through the first and second 1-line delay circuits 13 and 14, the sample value at a specific sampling point and two reference sampling points respectively one line above and one line below the specific sampling point on the screen are



simultaneously extracted. Here the term "specific sampling point" means the sampling point for which the signal processing is made, and the term "reference sampling points" means sampling points which are situated in the neighborhood of the specific sampling point when the sampling points are arranged on a two-dimensional plane corresponding to a display screen used for the display of the picture.

In other words, at the time point the composite color television signal (sample value) $S(m, n)$ at the position of coordinate (m, n) appears at the output 102 of the first 1-line delay circuit 13, the signal $(m, n-1)$ appears at the output 103 of the second 1-line delay circuit 13 and the signal $(m, n+1)$ appears at the output 101 of the A/D converter 12.

The signal 102 is applied to the horizontal chrominance extraction filter 16. This signal 102 and the other two signals 101 and 103 are respectively applied to the vertical chrominance extraction filter 15, the horizontal and vertical chrominance extraction filter 17, and the picture non-correlation decision circuit 18.

Using Z conversion, 1-sample delay and 1-line delay can be expressed by Z^{-1} and Z^{-L} , respectively. In this case,

$$Z^{-1} = \exp(-j2\pi f/4 \text{ fsc})$$


Also, since $\text{fsc} = (455/2)$, $L = 910$.

For example, in this case, the transfer function of the vertical chrominance extraction filter 15 is expressed as follows.

$$C_v(Z) = (-1/4)(1-Z^{-L})^2$$

The transfer function of the horizontal chrominance extraction filter 16 is expressed as follows.

$$C_h(Z) = (-1/4)(1-Z^{-2})^2$$



The transfer function of the horizontal and vertical chrominance extraction filter 17 is expressed as follows.

$$\text{Chv}(Z) = (-1/4)(1-Z^{-2})^2 \cdot (-1/4)(1-Z^{-L})^2$$

The output signal 106 of the vertical chrominance extraction filter 15 is supplied as the output signal 107 of the compensating delay circuit 20 to the selector 23. The output signal 108 of the horizontal chrominance extraction filter 16 is supplied as the output signal 109 of the compensating delay circuit 21 to the selector 23. The output signal 110 of the horizontal and vertical chrominance extraction filter 17 is supplied as the output signal 111 of the compensating delay circuit 22 applied to the selector 23.

The vertical and horizontal picture non-correlation of a specific sampling point is detected and the selector 23 functions in the following manner.

When the horizontal non-correlation is particularly strong, the output signal 107 of the compensating delay circuit 20 to which the output signal 106 of the vertical chrominance extraction filter 15 is supplied is selected. When the vertical non-correlation is particularly strong, the output signal 109 of the compensating delay circuit 21 to which the output signal 108 of the horizontal chrominance extraction filter 16 is selected. At other times, the output signal 111 of the compensating delay circuit 22 to which the output signal 110 of the horizontal and vertical chrominance extraction filter 17 is supplied is selected.

The detection of the picture non-correlation and control over the selector 23 are performed by the picture non-correlation decision circuit 18. This picture non-correlation decision circuit 18 operates in the following



manner to control the selector.

The horizontal chrominance non-correlation energy represented $DCH(Z)$, the horizontal luminance non-correlation energy $DYH(Z)$, the vertical chrominance non-correlation energy $DCV(Z)$ and the vertical luminance non-correlation energy $DYV(Z)$ can be expressed as follows.

$$DCH(Z) = |1 - Z^{-4}|$$

$$DYH(Z) = \max \{ |(1/4) \cdot (1 + Z^{-L})^2 \cdot (1 - Z^{-2})|, \\ |(1/4) \cdot (1 + Z^{-L})^2 \cdot (Z^{-2} - Z^{-4})| \}$$

$$DCV(Z) = |(-1/4) \cdot (1 - Z^{-2})^2 \cdot (1 - Z^{-2L})|$$

$$DYV = \max \{ |(1/4) \cdot (1 + Z^{-2})^2 \cdot (1 - Z^{-L})|, \\ |(1/4) \cdot (1 + Z^{-2})^2 \cdot (Z^{-L} - Z^{-2L})| \}$$

The first horizontal non-correlation energy $DH1$, the second horizontal non-correlation energy $DH21$, the third horizontal non-correlation energy $DH22$ and the vertical non-correlation energy DV can be expressed as follows.

$$DH1 = \max (a \cdot DYH, b \cdot DCH)$$

$$DH21 = \max (e1 \cdot DYH, f1 \cdot DCH)$$

$$DH22 = \max (e2 \cdot DYH, f2 \cdot DCH)$$

$$DV = \max (c \cdot DYV, d \cdot DCV)$$

At the comparator 37, $DH1$ and $n \cdot DV$ are compared. If $DH1 \geq n \cdot DV$ the horizontal non-correlation is interpreted as strong, and a "1" signal 116 is sent to the delay circuit 86. If

$$DH1 < n \cdot DV$$

the horizontal non-correlation is interpreted as weak, and a "0" signal 116 is sent to the delay circuit 86. This signal 116 is delayed $1/2fsc$ by the delay circuit 86 and is sent as the signal 119 to the decision circuit 40.

At the comparator 38, DCV and $m1 \cdot DH21$ are compared. If



$$DCV \geq m1 \cdot DH21$$

the vertical non-correlation is interpreted as strong, and a "1" signal 117 is sent to the delay circuit 87. If

$$DCV < m1 \cdot DH21$$

the horizontal non-correlation is interpreted as weak, and a "0" signal 117 is sent to the delay circuit 87. The signal 117 delayed $1/2fsc$ by the delay circuit 87 is sent as a signal 120 to the decision circuit 40.

At the comparator 39, DYV and $m2 \cdot DH22$ are compared. If

$$DYV \geq m2 \cdot DH22$$

the vertical non-correlation is interpreted as strong, and a "1" signal 118 is sent to the delay circuit 88 and the AND circuit 90. If

$$DYV < m2 \cdot DH22$$

the vertical non-correlation is interpreted as weak, and a "0" signal 118 is sent to the delay circuit 88 and the AND circuit 90.

The output signal 121 of the delay circuit 88 is sent to the delay circuit 89 and the AND circuit 90. The output signal 122 of the delay circuit 89 is sent to the AND circuit 90. The output signal 123 of the AND circuit 90 is applied to the decision circuit 40.

According to the results of the above correlation detection, the decision circuit 40 controls the selector 23 in the following manner. That is, the relationship between the input signals 119, 120 and 123 of the decision circuit 40 and the selection of the chrominance output signal 107, 109 or 111 at the selector 23 is as shown in Table 1.



Table 1

Output 119 of Delay Circuit 86	Output 120 of Delay Circuit 87	Output 123 of Delay Circuit 90	Output 1120 of Decision Circuit 40		Chrominance Output 113 Selected by Selector 23
			Output 110a of AND 41	Output 110b of AND 42	
0	0	0	1	0	111
0	0	1	0	0	109
0	1	0	0	0	109
0	1	1	0	0	109
1	0	0	0	1	107
1	0	1	0	0	109
1	1	0	0	0	109
1	1	1	0	0	109

When the output signal 110a of the AND circuit 41 and the output signal 110b of the AND circuit 42 are both "0", the selector 23 selects the output signal 109 of the compensating delay circuit 21. When the output signal 110a of the AND circuit 41 is "0" and the output signal 110b of the AND circuit 42 is "1", the selector 23 selects the output signal 107 of the compensating delay circuit 20. When the output signal 110a of the AND circuit 41 is "1" and the output signal 110b of the AND circuit 42 is "0", the selector 23 selects the output signal 111 of the compensating delay circuit 22.

Consequently, in this example, the overall $C(z)$ response of the filter for extracting the chrominance signal to be output at the output terminal 26 is switched as follows according to the presence or absence of correlation. When the vertical non-correlation is strong:

$$C(Z) = Ch(Z)$$

When the horizontal non-correlation is strong:

$$C(Z) = Cv(Z)$$

If neither of these conditions are met:

$$C(Z) = Chv(Z)$$



In the conventional YC separating filter described above, the luminance signal Y and the chrominance signal C are separated by adaptively selecting one of the horizontal filter, the vertical direction filter, and the horizontal and vertical direction filter. As a result, in areas where the picture horizontal or vertical direction luminance or chrominance signal variation is sharp, e.g., in areas at the boundary between different color regions, such as at an edge of a color bar signal, picture quality impairment such as dot crawl (due to leakage of the chrominance signal component into the luminance signal) does not occur. However, the conventional YC separating filter described above is associated with the problems of considerable cross color (due to leakage of high frequency luminance components into chrominance signal areas), particularly at the areas where the picture includes inclined fine stripes or gratings, and the diagonal resolution is insufficiently high.

SUMMARY OF THE INVENTION

Aspects of the invention are defined in the claims.

It would be desirable to resolve the problems mentioned above.

It would also be desirable to provide a luminance/chrominance separating filter which can perform accurate luminance/chrominance separation even when sharp variations occur in the television signal, and which is associated with less cross color and smaller diagonal resolution impairment.

In one aspect, the invention provides a luminance/chrominance separating filter for separating a composite color television signal into a luminance signal and a chrominance signal, and comprises:

means (13,14,13a,14a) for producing sample values of



a specific sampling point and a plurality of reference sampling points of the composite color television signal, said reference sampling points which are situated in the neighborhood of the sampling points when the sampling points are arranged on a two-dimensional plane corresponding to a display screen;

a first horizontal chrominance extraction filter (16) for extracting, from said sample value of said specific and reference sampling points, frequency components corresponding to components of a color subcarrier in a horizontal to produce a first chrominance signal (107);

a vertical chrominance extraction filter (15) for extracting, from said sample values of said specific and reference sampling points, frequency components corresponding to components of a color subcarrier in a vertical direction to produce a second chrominance signal (108);

a horizontal and vertical chrominance extraction filter (17) for extracting, from said sample values of said specific and reference sampling points, frequency components corresponding to components of a color subcarrier in horizontal and vertical directions to produce a third chrominance signal (110);

a first selector (23) for selecting one of said first, second and third chrominance signals;

a second horizontal chrominance extraction filter (24, 24a) receiving said selected chrominance signal and having a narrower bandwidth than said first horizontal chrominance extraction filter (16); and

a second selector (25, 25a) receiving the output of said second horizontal chrominance extraction filter (24, 24a) and the output of said first selector (23), and selecting said output of said second horizontal chrominance extraction filter (24, 24a) when said first selector selects



either said first or third chrominance signal, and selecting said output of said first selector (23) when said first selector selects said second chrominance signal.

The luminance/chrominance separating filter may further comprises:

a picture non-correlation decision circuit (18) responsive to the sample values of said specific and reference sampling points for detecting non-correlation in the horizontal direction and non-correlation in the vertical direction of said sample values and outputting a chrominance signal selection signal;

wherein said first selector (23) selects said one of the first to third chrominance signals on the basis of said chrominance signal selection signal;

wherein said picture non-correlation decision circuit (18) comprises:

a horizontal chrominance non-correlation energy extractor (29, 129) responsive to the sample values of said specific and reference sampling points for extracting horizontal chrominance non-correlation energy (DCH) consisting primarily of the chrominance signal extending in the horizontal direction;

a horizontal luminance non-correlation energy extractor (30) responsive to the sample values of said specific and reference sampling points for extracting horizontal luminance non-correlation energy (DYH) consisting primarily of the luminance signal extending in the horizontal direction;

a vertical chrominance non-correlation energy extractor (31, 131) responsive to the sample values of said reference sampling points for detecting vertical chrominance non-correlation energy (DCV) consisting primarily of the chrominance signal extending in the vertical direction;

a vertical luminance non-correlation energy extractor




(32) responsive to the sample values of said specific and reference sampling points for detecting vertical luminance non-correlation energy (DYV) of consisting primarily of the luminance signal extending in the vertical direction; and

judging means (33-36, 37-39, 40) responsive to the outputs of said horizontal chrominance non-correlation energy extractor (29, 129), said horizontal luminance non-correlation energy extractor (30), said vertical chrominance non-correlation energy extractor (31, 131) and said vertical luminance non-correlation energy extractor (32) for determining which of the horizontal and vertical non-correlations is stronger, causing said first chrominance signal selecting means (23) to select said first chrominance signal when the vertical non-correlation is strong, to select said second chrominance signal when the horizontal non-correlation is strong, and to select said third chrominance signal when neither of above conditions is met, and causing said second chrominance signal selector (25, 25a) to select the output of said second horizontal chrominance extraction filter (24) when said first selector selects either said first or third chrominance signal.

With the above arrangement, dot crawl is avoided in areas where the variation in the picture in the horizontal or vertical direction is sharp.

The output of said second selector (25) may be used for calculation with the composite video signal to produce an output luminance signal. The calculation may be accomplished by providing a subtractor (27) for subtracting the output of said second selector (25) from said composite video signal to produce said output luminance signal.

With the above arrangement, the second horizontal chrominance non-correlation extraction filter is used for further band-limiting the chrominance signal used for determining the luminance signal, so that the diagonal



resolution can be improved.

The output of said second selector (25a) may alternatively be used as an output chrominance signal. In such a case, there may be further provided a subtractor (27) for subtracting the output of said first selector (23) from the composite video signal to produce an output luminance signal.

With the above arrangement, the second horizontal chrominance non-correlation extraction filter is used for further band-limiting the output chrominance signal, so that cross color can be further reduced.

The horizontal chrominance non-correlation energy extractor may comprise first and second horizontal chrominance non-correlation energy extractors.

With the above arrangement, cross colors appearing with the inclined stripes or gratings can be restrained.

The picture non-correlation decision circuit may be additionally provided with delay circuits and an AND circuit to receive the outputs of the comparators comparing the non-correlation energies with each other.

With the above arrangement, it is possible to avoid degradation in the horizontal resolution.

The judging means may comprise four maximum value circuits. With the above arrangement, the non-correlation can be detected without being affected by the noise components.

The judging means may alternatively comprise one or more maximum value circuits and one or more adders in combination. With the above arrangement, accurate non-correlation detection is achieved where the non-correlation of the luminance signal and the non-correlation of the chrominance signal are both strong.

BRIEF DESCRIPTION OF THE DRAWINGS



Fig. 1 is a block diagram showing a luminance/chrominance separating filter of an embodiment of the present invention.

Fig. 2 is a block diagram showing a luminance/chrominance separating filter of another embodiment of the present invention.

Fig. 3 is a block diagram showing the second horizontal chrominance non-correlation energy extractor.

Fig. 4 is a block diagram showing the second vertical chrominance non-correlation energy extractor.

Fig. 5A to Fig. 5C are diagrams showing the frequency distributions of the signals representing non-correlation energy at the outputs of various circuits.

Fig. 6A to Fig. 6C are diagrams showing the frequency distributions of the signals representing non-correlation energy at the outputs of various circuits.

Fig. 7A to Fig. 7D are diagrams showing the frequency distributions of the signals representing non-correlation energy at the outputs of various circuits.

Fig. 8 is a diagram showing the frequency distribution of the signal due to diagonal stripes or diagonal grating.

Fig. 9 is a block diagram showing a picture non-correlation decision circuit 18 used in Embodiments 1 and 2.

Fig. 10 is a block diagram showing a picture non-correlation decision circuit 18 used in Embodiments 3 and 4.

Fig. 11 is a block diagram showing a picture non-correlation decision circuit 18 used in Embodiments 5 and 6.

Fig. 12 is a block diagram showing a picture non-correlation decision circuit 18 used in Embodiments 7 and 8.

Fig. 13 is a block diagram showing a picture non-correlation decision circuit 18 used in Embodiments 9 and 10.

Fig. 14 is a block diagram showing a picture non-correlation decision circuit 18 used in Embodiments 11 and



12.

Fig. 15 is a block diagram showing a picture non-correlation decision circuit 18 used in Embodiments 13 and 14.

Fig. 16 is a block diagram showing a picture non-correlation decision circuit 18 used in Embodiments 15 and 16.

Fig. 17 is a block diagram showing a picture non-correlation decision circuit 18 used in Embodiments 17 and 18.

Fig. 18 is a block diagram showing a picture non-correlation decision circuit 18 used in Embodiments 19 and 20.

Fig. 19 is a block diagram showing a picture non-correlation decision circuit 18 used in Embodiments 21 and 22.

Fig. 20 is a block diagram showing a picture non-correlation decision circuit 18 used in Embodiments 23 and 24.

Fig. 21 is a block diagram showing a picture non-correlation decision circuit 18 used in Embodiments 25 and 26.

Fig. 22 is a block diagram showing a picture non-correlation decision circuit 18 used in Embodiments 27 and 28.

Fig. 23 is a block diagram showing a picture non-correlation decision circuit 18 used in Embodiments 29 and 30.

Fig. 24 is a block diagram showing a picture non-correlation decision circuit 18 used in Embodiments 31 and 32.

Fig. 25 is a block diagram showing a picture non-correlation decision circuit 18 used in Embodiments 32 and 34.



Fig. 26 a block diagram showing a picture non-correlation decision circuit 18 used in Embodiments 35 and 36.

Fig. 27 is a block diagram showing a picture non-correlation decision circuit 18 used in Embodiments 37 and 38.

Fig. 28 is a block diagram showing a picture non-correlation decision circuit 18 used in Embodiments 39 and 40.

Fig. 29 is a block diagram showing a picture non-correlation decision circuit 18 used in Embodiments 41 and 42.

Fig. 30 is a block diagram showing a picture non-correlation decision circuit 18 used in Embodiments 43 and 44.

Fig. 31 is a block diagram showing a picture non-correlation decision circuit 18 used in Embodiments 45 and 46.

Fig. 32 is a block diagram showing a picture non-correlation decision circuit 18 used in Embodiments 47 and 48.

Fig. 33 is a block diagram showing a picture non-correlation decision circuit 18 used in Embodiments 49 and 50.

Fig. 34 is a block diagram showing a picture non-correlation decision circuit 18 used in Embodiments 51 and 52.

Fig. 35 is a block diagram showing a picture non-correlation decision circuit 18 used in Embodiments 53 and 54.

Fig. 36 is a block diagram showing a picture non-correlation decision circuit 18 used in Embodiments 55 and 56.

Fig. 37 is a block diagram showing a picture non-



correlation decision circuit 18 used in Embodiments 57 and 58.

Fig. 38 is a block diagram showing a picture non-correlation decision circuit 18 used in Embodiments 59 and 60.

Fig. 39 is a block diagram showing a picture non-correlation decision circuit 18 used in Embodiments 61 and 62.

Fig. 40 is a block diagram showing a picture non-correlation decision circuit 18 used in Embodiments 63 and 64.

Fig. 41 is a block diagram showing a luminance/chrominance separating filter of another embodiment of the present invention.

Fig. 42 is a block diagram showing a luminance/chrominance separating filter of another embodiment of the present invention.

Fig. 43 is a block diagram showing a luminance/chrominance separating filter in the prior art.

Fig. 44 is a diagram showing the frequency distribution on a two-dimensional plane of the NTSC composite color television signal.

Fig. 45 is a diagram showing the frequency distribution on a two-dimensional plane of the NTSC composite color television signal of a picture having a strong horizontal correlation and weak vertical correlation.

Fig. 46 is a diagram showing the frequency distribution on a two-dimensional plane of the NTSC composite color television signal of a picture having a strong vertical correlation and weak horizontal correlation.

Fig. 47 is a diagram showing the frequency distribution on a two-dimensional plane of the NTSC composite color television signal of a picture having a strong horizontal correlation and a strong vertical correlation.



Fig. 48 is a block diagram showing an example of decision circuit used in the luminance/chrominance separating filter of Fig. 43 and that of Fig. 1.

Fig. 49 is a block diagram showing an example of horizontal chrominance non-correlation energy extractor used in the luminance/chrominance separating filter of Fig. 43 and that of Fig. 1.

Fig. 50 is a block diagram showing an example of horizontal luminance non-correlation energy extractor used in the luminance/chrominance separating filter of Fig. 43 and that of Fig. 1.

Fig. 51 is a block diagram showing an example of vertical chrominance non-correlation energy extractor used in the luminance/chrominance separating filter of Fig. 43 and that of Fig. 1.

Fig. 52 is a block diagram showing an example of vertical luminance non-correlation energy extractor used in the luminance/chrominance separating filter of Fig. 43 and that of Fig. 1.


Fig. 53 is a diagram showing the arrangement of the sampling points for the sample values obtained by sampling the NTSC composite color television signal at a frequency four times the frequency of the color subcarrier.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

Following is a description of Embodiment 1 to Embodiment 64.

Embodiment 1

Fig. 1 is a schematic block diagram showing a YC separating filter of Embodiment 1. In the figure, an NTSC system composite color television signal is applied to an input terminal 11. The applied composite color television signal, which is an analog signal, is converted into a



digital signal by an A/D converter 12. The A/D conversion at the A/D converter 12 is effected at a frequency $4f_{sc}$ four times the frequency of the color subcarrier, and the A/D converter 12 therefore produces a sequence of digital signals representing sample values corresponding to sampling points which are situated as shown in Fig. 53 when the sampling points are arranged on a two-dimensional plane corresponding to a display screen used for display of the picture. The output signal of the A/D converter 12 is applied to a first 1-line delay circuit 13.

There are also provided a second 1-line delay circuit 14, a vertical chrominance (V-C) extraction filter 15, a horizontal chrominance (H-C) extraction filter 16, a horizontal and vertical chrominance (HV-C) extraction filter 17, a picture non-correlation decision circuit 18, compensating delay circuits 19, 20, 21 and 22, a first selector 23, a horizontal chrominance extraction filter 24 for receiving the output signal of the selector 23, a second selector 25, an output terminal 26 for an output chrominance signal, a subtractor 27, and an output terminal 28 for a luminance signal.

Fig. 9 shows the picture non-correlation decision circuit 18 of the Embodiment 1 of Fig. 1. As illustrated, it comprises a horizontal chrominance (H-C) non-correlation energy extractor 29, a horizontal luminance (H-Y) non-correlation energy extractor 30, a vertical chrominance (V-C) non-correlation energy extractor 31, a vertical luminance (V-Y) non-correlation energy extractor 32, comparators 37, 38 and 39, multipliers 71, 72, 73a, 73b, 74a, 74b, 77, 78, 79a, 79b and 80, and maximum value circuits (MAXs) 33 - 36.

The horizontal chrominance non-correlation energy extractor 29 receives the output signal 102 of the first 1-line delay circuit 13 in Fig. 1.

The horizontal luminance non-correlation energy



extractor 30 receives the output signal 101 of the A/D converter 12, the output signal 102 of the first 1-line delay circuit 13 and the output signal 103 of the second 1-line delay circuit 14 in Fig. 1.

The vertical chrominance non-correlation energy extractor 31 receives the output signal 101 of the A/D converter 12, and the output signal 103 of the second 1-line delay circuit 14 in Fig. 1.

The vertical luminance non-correlation energy extractor 32 receives the output signal 101 of the A/D converter 12, the output signal 102 of the first 1-line delay circuit 13, and the output signal 103 of the second 1-line delay circuit 14 in Fig. 1.

The output signal DCH of the horizontal chrominance non-correlation energy extractor 29 is branched in three routes. In the first route, the signal is multiplied by a coefficient b at the multiplier 72 and the resultant signal is sent to the maximum value circuit 33. In the second route, the signal is multiplied by a coefficient f_1 at the multiplier 74a and the resultant signal is sent to the maximum value circuit 34. In the third route, the signal is multiplied by a coefficient f_2 at the multiplier 74b and the resultant signal is sent to the maximum value circuit 35.

The output signal DYH of the horizontal luminance non-correlation energy extractor 30 is branched in three routes. In the first route, the signal is multiplied by a coefficient a at the multiplier 71 and the resultant signal is sent to the maximum value circuit 33. In the second route, the signal is multiplied by a coefficient e_1 at the multiplier 73a and the resultant signal is sent to the maximum value circuit 34. In the third route, the signal is multiplied by a coefficient e_2 at the multiplier 73b and the resultant signal is sent to the maximum value circuit 35.

The output signal DCV of the vertical chrominance non-



correlation energy extractor 31 is branched in two routes. In the first route, the signal is applied to the comparator 38. In the second route, the signal is multiplied by a coefficient d at the multiplier 78 and the resultant signal is sent to the maximum value circuit 36.

The output signal DYV of the vertical luminance non-correlation energy extractor 32 is branched in two routes. In the first route, the signal is applied to the comparator 39. In the second route, the signal is multiplied by a coefficient c at the multiplier 77 and the resultant signal is sent to the maximum value circuit 36.

The output signal of the maximum value circuit 33 is applied as the first horizontal non-correlation energy DH1 to the comparator 37. The output signal of the maximum value circuit 34 is multiplied by a coefficient $m1$ at the multiplier 79a, and the resultant signal is sent as the second horizontal non-correlation energy DH21 to the comparator 38. The output signal of the maximum value circuit 35, as the third horizontal non-correlation energy DH22, is multiplied by a coefficient $m2$ at the multiplier 79b, and the resultant signal is sent to the comparator 39. The output signal of the maximum value circuit 36, as the vertical non-correlation energy DV, is multiplied by a coefficient n at the multiplier 80, and the resultant signal is sent to the comparator 37.

The comparator 37 compares the first horizontal non-correlation energy DH1 and the product $n \cdot DV$ of the vertical non-correlation energy DV and the coefficient n , and produces a high level output signal 116 when $DH1 \geq n \cdot DV$, and a low level output signal 116 at other times.

The comparator 38 compares the vertical chrominance non-correlation energy DCV and the product $m1 \cdot DH21$ of the second horizontal non-correlation energy DH21 and the coefficient $m1$, and produces a high level output signal 117



when $DCV \geq m1 \cdot DH21$, and a low level output signal 117 at other times.

The comparator 39 compares the vertical luminance non-correlation energy DYV and the product $m2 \cdot DH22$ of the third horizontal non-correlation energy $DH22$ and the coefficient $m2$, and produces a high level output signal 118 when $DYV \geq m2 \cdot DH22$, and a low level output signal 118 at other times.

The respective output signals 116, 117 and 118 of the comparators 37, 38 and 39 are applied to the decision circuit 40. The output signal 110 of the decision circuit 40 serves as the output of the picture non-correlation decision circuit 18.

The decision circuit 40 shown in Fig. 9 may be identical to that shown in Fig. 48. However, the output signal 116 of the comparator 37 is applied to one input of the AND circuit 42 and to the NOT circuit 43. The respective output signals 117 and 118 of the comparators 38 and 39 are applied to the NOR circuit 44.

The horizontal chrominance non-correlation energy extractor 29, the horizontal luminance non-correlation energy extractor 30, the vertical chrominance non-correlation energy extractor 31, and the vertical luminance non-correlation energy extractor 32 used in Fig. 9 may be identical to that shown in Fig. 49, Fig. 50, Fig. 51, and Fig. 52, respectively.

Following is a description of the operation of this embodiment with reference to Fig. 1, Fig. 9, Fig. 48 to Fig. 52, as well as Fig. 5A to Fig. 5C and Fig. 6A to Fig. 6C illustrating the frequency distribution on a two-dimensional plane of the non-correlation energy at outputs of the various circuits.

When an NTSC system composite color television signal is applied via the input terminal 11, the A/D converter 12 samples this composite color television signal at a sampling



frequency $f_s = 4f_{sc}$. By passing the sampled composite color television signal through the first and second 1-line delay circuits 13 and 14, the sample values at a certain specific sampling point and at reference sampling points 1-line above and 1-line below this specific sampling point on the screen are simultaneously extracted. Consequently, at the time point the composite color television signal (sample value) $S(m, n)$ at the coordinate position (m, n) on the screen appears as the output signal 102 of the first 1-line delay circuit 13, a signal $(m, n - 1)$ appears as the output signal 103 of the second 1-line delay circuit 14 and signal $S(m, n + 1)$ appears as the output signal 101 of the the A/D converter 12, as illustrated in Fig. 53.

The signal 102 is applied to the horizontal chrominance extraction filter 16. This signal 102 and the other two signals 101 and 103 are respectively applied to the vertical chrominance extraction filter 15, the horizontal and vertical chrominance extraction filter 17, and the picture non-correlation decision circuit 18.

For example, the transfer function of the vertical chrominance extraction filter 15 is expressed as follows.

$$C_v(Z) = (-1/4)(1-Z^{-L})^2$$

The transfer function of the horizontal chrominance extraction filter 16 is expressed as follows.

$$C_h1(Z) = (-1/4)(1-Z^{-2})^2$$

The transfer function of the horizontal and vertical chrominance extraction filter 17 is expressed as follows.

$$C_{hv}(Z) = (-1/4)(1-Z^{-2})^2 \cdot (-1/4)(1-Z^{-L})^2$$



The output signal 107 of the compensating delay circuit 20, the output signal 109 of the compensating delay circuit 21, and the output signal 110 of the compensating delay circuit 22 are respectively applied to the selector 23.

The vertical and horizontal direction picture non-correlation of a specific sampling point is detected, and, in accordance with the result of the detection of the non-correlation, the selector 23 selectively outputs one of its input signals as follows:

When the horizontal non-correlation is particularly strong, the output signal 107 of the compensating delay circuit 20 to which the output signal 106 of the vertical chrominance extraction filter 15 is applied is selected. When the vertical non-correlation is particularly strong, the output signal 109 of the compensating delay circuit 21 to which output signal 108 of the horizontal chrominance extraction filter 16 is applied is selected. At other times, the output signal 111 of the compensating delay circuit 22 to which the output signal 110 of the horizontal and vertical chrominance extraction filter 17 is applied is selected.

The operation of the second selector 25 is as follows. When the chrominance signal selected by the selector 23 is the output signal 109 of the compensating delay circuit 21 or the output signal 111 of the compensating delay circuit 22, the selector 25 selects the output signal 1132 of the horizontal chrominance extraction filter 24, and when the chrominance signal selected by the selector 23 is the output signal 107 of the compensating delay circuit 20, the selector 25 selects the signal 1131 at the output of the compensating delay circuit 91.

The horizontal chrominance extraction filter 24 has a narrower band, and serves to band-limit the output signal 113 of the selector 23.



The transfer function of the horizontal chrominance extraction filter 24 is expressed, for example, as follows:

$$\text{Ch2}(Z) = (-1/16) (1 - Z^{-2})^4$$

The detection of the picture non-correlation and control over the selectors 23 and 25 are performed by the picture non-correlation decision circuit 18. The operation of the picture non-correlation decision circuit 18 for control over the selectors 23 and 25 is as follows:

The horizontal chrominance non-correlation energy $\text{DCH}(Z)$, the horizontal luminance non-correlation energy $\text{DYH}(Z)$, the vertical chrominance non-correlation energy $\text{DCV}(Z)$ and vertical luminance non-correlation energy $\text{DYV}(Z)$ are expressed as follows.

$$\text{DCH}(Z) = |1 - Z^{-4}|$$

$$\text{DYH}(Z) = \max \{ |(1/4) \cdot (1 + Z^{-L})^2 \cdot (1 - Z^{-2})|, \\ |(1/4) \cdot (1 + Z^{-L})^2 \cdot (Z^{-2} - Z^{-4})| \}$$

$$\text{DCV}(Z) = |(-1/4) \cdot (1 - Z^{-2})^2 \cdot (a - Z^{-2L})|$$

$$\text{DYV}(Z) = \max \{ |(1/4) \cdot (1 + Z^{-2})^2 \cdot (1 - Z^{-L})|, \\ |(1/4) \cdot (1 + Z^{-2})^2 \cdot (Z^{-L} - Z^{-2L})| \}$$


The frequency distributions on the two-dimensional plane of $\text{DCH}(Z)$, $\text{DYH}(Z)$, $\text{DCV}(Z)$ and $\text{DYV}(Z)$ are respectively illustrated in Fig. 5B, Fig. 5A, Fig. 6B and Fig. 6A.

The first horizontal non-correlation energy DH1 , the second horizontal non-correlation energy DH21 , the third horizontal non-correlation energy DH22 and the vertical non-correlation energy DV can be expressed as follows.

$$\text{DH1} = \max (a \cdot \text{DYH}, b \cdot \text{DCH})$$

$$\text{DH21} = \max (e1 \cdot \text{DYH}, f1 \cdot \text{DCH})$$

$$\text{DH22} = \max (e2 \cdot \text{DYH}, f2 \cdot \text{DCH})$$



$$DV = \max (c \cdot DYV, d \cdot DCV)$$

The frequency distributions on the two-dimensional plane of DH1 and DV are respectively illustrated in Fig. 5C and Fig. 6C.

At the comparator 37, DH1 and $n \cdot DV$ are compared. If

$$DH1 \geq n \cdot DV$$

the horizontal non-correlation is interpreted as strong, and a "1" signal 116 is sent to the decision circuit 40. If

$$DH1 < n \cdot DV$$

the horizontal non-correlation is interpreted as weak, and a "0" signal 116 is sent to the decision circuit 40. At the comparator 38, DCV and $m1 \cdot DH21$ are compared. If

$$DCV \geq m1 \cdot DH21$$

the vertical non-correlation is interpreted as strong, and a "1" signal 117 is sent to the decision circuit 40. If

$$DCV < m1 \cdot DH21$$

the horizontal non-correlation is interpreted as weak, and a "0" signal 117 is sent to the delay circuit 87. At the comparator 39, DYV and $m2 \cdot DH22$ are compared. If

$$DYV \geq m2 \cdot DH22$$

the vertical non-correlation is interpreted as strong, and a "1" signal 118 is sent to the decision circuit 40. If

$$DYV < m2 \cdot DH22$$

the vertical non-correlation is interpreted as weak, and a "0" signal 118 is sent to the decision circuit 40. On the basis of the results of the detection of the correlation as described above, the decision circuit 40 controls the selector 23 in the following manner. The relationship between the input signals 116, 117 and 118 of the decision circuit 40, and its output signal 110, the selection of the chrominance output signal 107, 109 or 111 at the selector 23 and the selection of the chrominance output signal 1131 or 1132 at the selector 25 is as shown in Table 2.



Table 2

Output 116(119) of Delay Circuit 86	Output 117(120) of Delay Circuit 87	Output 118(123) of Delay Circuit 90	Output 110 of of Decision Circuit 40		Chrominance Output 113 Selected by Selector 23	Chrominance Output 1133(1134) Selected by Selector 25 (25a)
			Output 110a of AND 41	Output 110b of AND 42		
0	0	0	1	0	111	1132
0	0	1	0	0	109	1132
0	1	0	0	0	109	1132
0	1	1	0	0	109	1132
1	0	0	0	1	107	1131
1	0	1	0	0	109	1132
1	1	0	0	0	109	1132
1	1	1	0	0	109	1132

When the output signals 110a and 110b of the AND circuits 41 and 42 are both "0", the selector 23 selects the output signal 109 of the compensating delay circuit 21. When the output signal 110a of the AND circuit 41 is "0" and the output signal 110b of the AND circuit 42 is "1", the output signal 107 of the compensating delay circuit 20 is selected. When the output signal 110a of the AND circuit 41 is "1" and the output signal 110b of the AND circuit 42 is "0", the output signal 111 of the compensating delay circuit 22 is selected.

When the output signal 110b of AND circuit 42 is "1", the selector 25 selects the output signal 1131 of the compensating delay circuit 91. When the output signal 110b of the AND circuit 42 is "0", the selector 25 selects the output signal 1132 of the horizontal chrominance extraction filter 24.

Consequently, in the embodiment of Fig. 1, the response $C11(Z)$ of the filter for extracting the chrominance signal output via the terminal 26, and the response $C12(Z)$ of the chrominance signal extraction filter for extracting the



luminance signal via the terminal 28 are related as follows:

When the vertical non-correlation is strong,

$$C11(Z) = Ch1(Z)$$

$$C12(Z) = Ch1(Z) \cdot Ch2(Z)$$

When the horizontal non-correlation is strong,

$$C11(Z) = C12(Z) = Cv(Z)$$

When neither of these conditions are met,


$$C11(Z) = Chv(Z)$$

$$C12(Z) = Chv(Z) \cdot CH2(Z)$$

Embodiment 2

Fig. 2 shows a YC separating filter of Embodiment 2. The YC separating filter of Fig. 2 is similar to that of Fig. 1, and but in place of the horizontal chrominance extraction filter 24, the compensating delay circuit 91, and the selector 25, a horizontal chrominance extraction filter 24a, a compensating delay circuit 91a, and a selector 25a are provided. The horizontal chrominance extraction filter 24a and the compensating delay circuit 91a are coupled to receive the output signal of the selector 23, and the selector 25a is coupled to receive the output signals of the horizontal chrominance extraction filter 24a and the compensating delay circuit 91a and selects one of its input signals according to the output signal from the picture non-correlation decision circuit 18. The output of the selector 25a is connected to the output terminal. The subtractor 27 receives the output signal of the selector 23.

The picture non-correlation decision circuit 18 may be the one shown in Fig. 9. The selecting operation of the YC separating filter of Fig. 2 is the same as that of the YC separating filter of Fig. 1. Consequently, the relationship between the input signals 116, 117 and 118 of the decision circuit 40, and its output signal 110, the selection of the



chrominance output signal 107, 109 or 111 at the selector 23 and the selection of the chrominance output signal 1131 or 1132 at the selector 25a is as shown in Table 2.

That is, when the output signals 110a and 110b of the AND circuits 41 and 42 are both "0", the selector 23 selects the output signal 109 of the compensating delay circuit 21. When the output signal 110a of the AND circuit 41 is "0" and the output signal 110b of the AND circuit 42 is "1", the output signal 107 of the compensating delay circuit 20 is selected. When the output signal 110a of the AND circuit 41 is "1" and the output signal 110b of the AND circuit 42 is "0", the output signal 111 of the compensating delay circuit 22 is selected.

When the output signal 110b of the AND circuit 42 is "1", the selector 25a selects the output signal 1131 of the compensating delay circuit 91a. When the signal 110b is "0", the output signal 1132 of the horizontal chrominance extraction filter 24a is selected.

Consequently, in the case of the embodiment of Fig. 2, the response $C21(Z)$ of the filter for extracting the chrominance signal output through the terminal 26, and the response $C22(Z)$ of the filter for extracting the chrominance signal used for extracting the luminance signal are given below: That is, when the vertical non-correlation is strong,

$$C21(Z) = Ch1(Z) \cdot Ch2(Z)$$

$$C22(Z) = Ch1(Z)$$

When horizontal non-correlation is strong,

$$C21(Z) = C22(Z) = Cv(Z)$$

When neither of these conditions are met,

$$C21(Z) = Chv(Z) \cdot CH2(Z)$$

$$C22(Z) = Chv(Z)$$

The arrangement of Fig. 2 has an advantage over the



arrangement of Fig. 1 in that the cross color is further reduced. On the other hand, the arrangement of Fig. 1 has an advantage over the arrangement of Fig. 2 in that the resolution is higher.

Embodiment 3

This embodiment is similar to Embodiment 1, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 10 is used. The picture non-correlation decision circuit 18 is similar to that shown in Fig. 9. However, the horizontal chrominance non-correlation energy extractor 29 and the vertical chrominance non-correlation energy extractor 31 in Fig. 9 are replaced by a horizontal chrominance non-correlation energy extractor 129 and vertical chrominance non-correlation energy extractor 131.

The horizontal chrominance non-correlation energy extractor 129 comprises a first horizontal chrominance non-correlation energy extractor 29a and a second horizontal chrominance non-correlation energy extractor 29b. The configuration of the first horizontal chrominance non-correlation energy extractor 29a is identical to that of the horizontal chrominance non-correlation energy extractor 29 of Fig. 49. The configuration of the second horizontal chrominance non-correlation energy extractor 29b may be as shown in Fig. 3.

The vertical chrominance non-correlation energy extractor 131 comprises a first vertical chrominance non-correlation energy extractor 31a and a second vertical chrominance non-correlation energy extractor 31b. The configuration of the first vertical chrominance non-correlation energy extractor 31a is identical to that of the vertical chrominance non-correlation energy extractor 31 of Fig. 51. The configuration of the second vertical



chrominance non-correlation energy extractor 31b may be as shown in Fig. 4.

The second horizontal chrominance non-correlation energy extractor 29b shown in Fig. 3 comprises a vertical direction bandpass filter 151, delay circuits 152, 153 and 156, multipliers 154 and 158, subtractors 155 and 157, and an absolute value circuit (ABS) 159.

The output signal 101 of the A/D converter 12, the output signal 102 of the first 1-line delay circuit 13 and the output signal 103 of the second 1-line delay circuit 14 are applied to the vertical direction bandpass filter 151. The output signal of the vertical direction bandpass filter 151 is applied to the delay circuit 152 and the subtractor 155.

The output signal of the delay circuit 152 is applied to the delay circuit 153 and the multiplier 154. The output signal of the delay circuit 153 is applied to the subtractor 155. The output signal of the multiplier 154 is applied to the subtractor 155.

The output signal of the subtractor 155 is applied to the delay circuit 156 and the subtractor 157. The output signal of the subtractor 157 is applied to the multiplier 158. The output signal of the multiplier 158 is applied to the absolute value circuit 159.

The output signal of the absolute value circuit 159 forms the output DCH2 of the horizontal chrominance non-correlation energy extractor 29b.

The second vertical chrominance non-correlation energy extractor 31b shown in Fig. 4 comprises a subtractor 160 and an absolute value circuit 161.

The output signal 101 of the A/D converter 12 and output signal 103 of the second 1-line delay circuit 13 are applied to the subtractor 160. The output signal of the subtractor 160 is applied to the absolute value circuit 161.



The output signal of the absolute value circuit 161 forms the output DCV2 of the vertical chrominance non-correlation energy extractor 31b.

The output signal DCH1 (whose frequency band is identical to that of DCH and is as shown in Fig. 5B) of the the first horizontal chrominance non-correlation energy extractor 29a is multiplied by the coefficient f1 at the multiplier 74a, and the product f1·DCH1 and the output signal e1·DYH of the multiplier 73a are applied to the maximum value circuit 34 for detecting DH21. Thus, in this case, the following relationship is obtained.

$$DH21 = \max (e1 \cdot DYH, f1 \cdot DCH1)$$

The comparator 38 compares the output signal DCV1 (whose frequency band is identical to that of DCV and is as shown in Fig. 6B) of the vertical chrominance non-correlation energy extractor 31a and the product m1·DH21 of the above-mentioned DH21 and the coefficient m1. When

$$DCV1 \geq m1 \cdot \max (e1 \cdot DYH, f1 \cdot DCH1)$$

the vertical non-correlation is interpreted as strong, and the output signal of the horizontal chrominance extraction filter 16 is selected by the selector 23 under control of the decision circuit 40.

The output signal DCH1 of the horizontal chrominance non-correlation energy extractor 29a is also multiplied by the coefficient f2 at the multiplier 74b, and the product f2·DCH1 and e2·DYH are applied to the maximum value circuit 35 for obtaining a larger one of them, DH22. That is,

$$DH22 = \max (e2 \cdot DYH, f2 \cdot DCH1)$$



The comparator 39 compares the output signal DYV (Fig. 6A) of the vertical luminance non-correlation energy extractor 32 and the product $m2 \cdot DH22$ of the above-mentioned DH22 and the coefficient $m2$. Thus, when

$$DYV \geq m2 \cdot \max (e2 \cdot DYH, f2 \cdot DCH1)$$

the vertical non-correlation is again interpreted as strong, and the decision circuit 40, responsive to the result of this interpretation, causes the output signal of the horizontal chrominance extraction filter 16 to be selected.


The output signal of the vertical chrominance extraction filter 15 is selected on the basis of the following judgement.

The output signal DCH2 (Fig. 7A) of the second horizontal chrominance non-correlation energy extractor 29b is multiplied by the coefficient b at the multiplier 72 to produce a product $b \cdot DCH2$. The output signal DYH (Fig. 5A) of the horizontal luminance non-correlation energy extractor 30 is multiplied by the coefficient a at the multiplier 71 to produce a product $a \cdot DYH$. The maximum value circuit 33 obtains the larger one of $b \cdot DCH2$ and $a \cdot DYH$ to produce DH1. That is,

$$DH1 = \max (a \cdot DYH, b \cdot DCH2)$$

The frequency band on the two-dimensional plane of DH1 is as shown in Fig. 7B, and is different from that shown in Fig. 5C).

The output signal DCV2 (Fig. 7C) of the vertical chrominance non-correlation energy extractor 31b is multiplied by the coefficient d to produce $d \cdot DCV2$. The output signal DYV of the vertical chrominance non-correlation energy extractor 32 is multiplied by the



coefficient c at the multiplier 77 to produce a product $c \cdot DYV$. The maximum value circuit 36 obtains a larger one of $d \cdot DCV2$ and $c \cdot DYV$ to produce DV . That is,

$$DV = \max (c \cdot DYV, d \cdot DCV2)$$

The frequency band on the two-dimensional plane of DV is as shown in Fig. 7D, and is different from that shown in Fig. 6C).

The output signal DV of the maximum value circuit 36 is multiplied by the coefficient n at the multiplier 80 to produce a product $n \cdot DV$.

The comparator 37 compares $DH1 = \max (a \cdot DYH, b \cdot DCH2)$ and $n \cdot DV = n \cdot \max (c \cdot DYV, d \cdot DCV2)$. If

$\max (a \cdot DYH, b \cdot DCH2) \geq n \cdot \max (c \cdot DYV, d \cdot DCV2)$
the horizontal non-correlation is interpreted as strong, and the decision circuit 40, responsive to this result of interpretation, causes the output signal of the vertical chrominance extraction filter 15 to be selected.

The picture non-correlation decision circuit 18 of this embodiment shares the same concept as the picture non-correlation decision circuit 18 of Fig. 9 in the selection between the horizontal chrominance extraction filter 16 and the vertical chrominance extraction filter 15, but the former differs from the latter in that the selection of the output signal of the horizontal chrominance extraction filter 16 is based on $DCV1$ in place of DCV , and on $DCH1$ in place of DCH , and the selection of the output signal of the vertical chrominance extraction filter 15 is based on $DCH2$ in place of DCH , and on $DCV2$ in place of DCV .

Consequently, if $DCH2$ and $DCV2$ are so set that the left side of the expression expressing the condition for selecting the vertical chrominance extraction filter 15, i.e., $\max (a \cdot DYH, b \cdot DCH2)$ results in less extraction,



compared with the counterpart in Embodiment 1, $\max(a \cdot DYH, b \cdot DCH)$, of luminance signal diagonal components indicated by cross hatching DIA in Fig. 8 (due to the oblique stripes in the picture, for example), and the right side of the above expression, $\max(c \cdot DYV, d \cdot DCV2)$ results in more extraction, compared with the counterpart in Embodiment 1, $\max(c \cdot DYV, d \cdot DCV)$, of such luminance signal diagonal components, then it is possible to prevent undue selection of the vertical chrominance extraction filter 15, and therefore to restrain cross color due to leakage of the vertically extending luminance signal components (of the horizontal and vertical frequency components originating from luminance signal diagonal components) into the chrominance signal region.

The control over the selection by the selectors 23 and 25 in accordance with the basis of the output signal 110 of the decision circuit 40 of Fig. 10 is as shown in Table 2.

Embodiment 4

This embodiment is similar to Embodiment 41, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 10 is used. The selecting operation of the selector 23 responsive to the output of the decision circuit 40 is as shown in Table 2.

Embodiment 5

This embodiment is similar to Embodiment 1, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 11 is used.

The picture non-correlation decision circuit 18 of Fig. 11 is similar to that of Fig. 9, but delay circuits 86, 87, 88 and 89, an AND circuit 90 are additionally provided, between the comparators 37, 38 and 39 and the decision



circuit 40. The delay time of each of the delay circuits 86, 87, 88 and 89 is $1/2fsc$.

Specifically, the output signal 116 of the comparator 37 is applied to the delay circuit 86, the output signal 117 of the comparator 38 is applied to the delay circuit 87, and the output signal 118 of the comparator 39 is applied to the delay circuit 88, whose output 121 is applied to another delay circuit 89. The output signals 118, 121 and 122 of the comparator 39, and the delay circuits 88 and 89 are applied to the AND circuit 90. The decision circuit 40 receives the output signals 119, 120 and 123 of the delay circuits 86 and 87, and the AND circuit 90.

Following is a description of the operation of the embodiment of Fig. 11. The operation up to comparators 37, 38 and 39 is the same as the embodiment of Fig. 9.

The signal 116 is delayed $1/2fsc$ by the delay circuit 86 and the signal 117 is delayed $1/2fsc$ by the delay circuit 87, and these signals are then respectively applied to the decision circuit 40. The signal 118 is delayed $1/2fsc$ by the delay circuit 88. This output signal 121 is further delayed $1/2fsc$ by the delay circuit 89 and applied to the AND circuit 90. The signals 118 and 121 are also applied to this AND circuit 90.

The output signals 119, 120 and 123 of the delay circuits 86 and 87, and the AND circuit 90 are respectively applied to the decision circuit 40.

As described in connection with the picture non-correlation decision circuit 18 of Fig. 9, the decision circuit 40 controls the selecting operation of the selectors 23 and 25 according to the results of the correlation detection. The control over the selection by the selectors 23 and 25 in accordance with the output signal 110 of the decision circuit 40 is as shown in Table 2.

When the output signals 110a and 110b of the AND



circuits 41 and 42 are both "0", the selector 23 selects the output signal 109 of the compensating delay circuit 21. When the output signal 110b of the AND circuit 41 is "0" and the output signal 110b of the AND circuit 42 is "1", the output signal 107 of the compensating delay circuit 20 is selected. When the output signal 110a of the AND circuit 41 is "1" and the output signal 110b of the AND circuit 42 is "0", the output signal 111 of the compensating delay circuit 22 is selected.

When the output signal 110b of the AND circuit 42 is "1", the selector 25 selects the output signal 1131 of the compensating delay circuit 91. When the signal 110b is "0", the output signal 1132 of the horizontal chrominance extraction filter 24 is selected.

Consequently, in the case of this embodiment, the response $C11(Z)$ of the filter for extracting the chrominance signal output through the terminal 26 and the response $C12(Z)$ of the filter for extracting the chrominance signal for extracting the luminance signal are given according to the presence or absence of correlation in the following manner.

When vertical non-correlation is strong,

$$C11(Z) = Ch1(Z)$$

$$C12(Z) = Ch1(Z) \cdot Ch2(Z)$$

When horizontal non-correlation is strong,

$$C11(Z) = C12(Z) = Cv(Z)$$

When neither of these conditions are met,

$$C11(Z) = Chv(Z)$$

$$C12(Z) = Chv(Z) \cdot CH2(Z)$$

Embodiment 6

This embodiment is similar to Embodiment 41, but in place of the picture non-correlation decision circuit 18 of



Fig. 9, the picture non-correlation decision circuit shown in Fig. 11 is used.

The relationship between the input signals 119, 120 and 123 of the decision circuit 40, and its output signal 110 (see Fig. 48), the selection of the chrominance output signal 107, 109 or 111 at the selector 23, and the selection of the chrominance output signal 1131 or 1132 at the selector 25a is as shown in Table 2.

When the output signals 110a and 110b of the AND circuits 41 and 42 are both "0", the selector 23 selects the output signal 109 of the compensating delay circuit 21. When the output signal 110a of the AND circuit 41 is "0" and the output signal 110b of the AND circuit 42 is "1", the output signal 107 of the compensating delay circuit 20 is selected. When the output signal 110a of the AND circuit 41 is "1" and the output signal 110b of the AND circuit 42 is "0", the output signal 111 of the compensating delay circuit 22 is selected.

When the output signal 110b of the AND circuit 42 is "1", the selector 25a selects the output signal 1131 of the compensating delay circuit 91a. When the signal 110b is "0", the output signal 1132 of the horizontal chrominance extraction filter 24a is selected.

Consequently, in the case of this embodiment, the response $C21(Z)$ of the filter for extracting the chrominance signal output through the terminal 26, and the response $C22(Z)$ of the filter for extracting the chrominance signal used for extracting the luminance signal are given below:

When vertical non-correlation is strong,

$$C21(Z) = Ch1(Z) \cdot Ch2(Z)$$

$$C22(Z) = Ch1(Z)$$

When horizontal non-correlation is strong,

$$C21(Z) = C22(Z) = Cv(Z)$$



When neither of these conditions are met,

$$C21(Z) = Chv(Z) \cdot CH2(Z)$$

$$C22(Z) = Chv(Z)$$

Embodiment 7

This embodiment is similar to Embodiment 1, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 12 is used.

The picture non-correlation decision circuit 18 of this embodiment is basically similar to that of Fig. 9, but the modifications described with reference to Fig. 10 and Fig. 11 are both applied. That is, compared with the picture non-correlation decision circuit of Fig. 11, the picture non-correlation decision circuit of Fig. 12 is provided with the horizontal chrominance non-correlation energy extractor 129 comprising the first and second horizontal chrominance non-correlation energy extractors 29a and 29b, and the vertical chrominance non-correlation energy extractor 131 comprising the first and second vertical chrominance non-correlation energy extractors 31a and 31b. The output signal DCH1 of the first horizontal chrominance non-correlation energy extractor 29a is multiplied by a coefficient f1 is applied at the multiplier 74a to produce a product f1·DCH1, which, together with e1·DYH, is applied to the maximum value circuit 34 for detecting the larger one of them, DH21. The output signal DCH1 is also multiplied by a coefficient f2 at the multiplier 74b to produce their product f2·DCH1, which, together with e2·DYH, is applied to the maximum value circuit 35 for detecting the larger one of them, DH22.

The output signal DCH2 of the second horizontal chrominance non-correlation energy extractor 29b is multiplied by a coefficient b at the multiplier 72 to



produce their product $b \cdot DCH2$, which, together with $a \cdot DYH$, is applied to the maximum value circuit 33 for detecting the larger one of them, $DH1$. The output signal $DCV2$ of the second vertical chrominance non-correlation energy extractor 31b is multiplied by a coefficient d at the multiplier 78 to produce their product $d \cdot DCV2$, which together with $c \cdot DYV$, is applied to the value circuit 36 for detecting the larger one of them, DV .

The signals $DH1$ and $n \cdot DV$ are compared at the comparator 37, the signals $DCV1$ and $m1 \cdot 21$ are compared at the comparator 38, and the signals DYV and $m2 \cdot DH22$ are compared at comparator 39.

The control over selection by the selectors 23 and 25 according to the output 110 of the decision circuit 40 of the embodiment of Fig. 12 is the same as shown in Table 2.

In the case of the above embodiment, the signal 118 is sent through two delay circuits and when the sample values of reference sampling points one before and one after the specific sampling point are both "1", the signal 123 is "1". However, the number of the reference sampling points may be other than two, but what is required is that the same number of reference sampling points be provided before and after the specific sampling points so as to enable non-correlation. When the number of the reference sampling points is R (integer), the same number (R) of delay circuits are needed to delay the signals 116 and 117.

Embodiment 8

This embodiment is similar to Embodiment 41, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 12 is used.

The control over selection by the selectors 23 and 25 according to the output 110 of the decision circuit 40 is



the same as shown in Table 2.

Embodiment 9

This embodiment is similar to Embodiment 1, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 13 is used.

The picture non-correlation decision circuit 18 of Fig. 13 is similar to that of Fig. 9 in that it comprises the non-correlation energy extractors 29 to 31, the maximum value circuits 33 to 36, the comparators 37 to 39, and the decision circuit 40. However, they are interconnected differently, via a different set of multipliers 71, 72, 75, 76b, 77a, 77b, 78a, 78b, 79, 80a and 80b. The output signal DCH of the horizontal chrominance non-correlation energy extractor 29 is branched in two routes. In the first route, the signal is directly applied to the comparator 36. In the second route, the signal is multiplied by a coefficient f at the multiplier 72 and the resultant signal is sent to the maximum value circuit 33.

The output signal DYH of the horizontal luminance non-correlation energy extractor 30 is branched in two routes. In the first route, the signal is applied directly to the comparator 39. In the second route, the signal is multiplied by a coefficient e at the multiplier 72 and the resultant signal is sent to the maximum value circuit 33.

The output signal DCV of the circuit for vertical chrominance non-correlation energy extractor 31 is branched in three routes. In the first route, the signal is multiplied by a coefficient h at the multiplier 76 and the resultant signal is sent to the maximum value circuit 34. In the second route, the signal is multiplied by a coefficient $d1$ at the multiplier 78a and the resultant signal is sent to the maximum value circuit 35. In the



third route, the signal is multiplied by a coefficient d2 at the multiplier 78b and the resultant signal is sent to the maximum value circuit 36.

The output signal DYV of the vertical luminance non-correlation energy extractor 32 is branched in three routes. In the first route, the signal is multiplied by a coefficient g at the multiplier 75 and the resultant signal is sent to the maximum value circuit 34. In the second route, the signal is multiplied by a coefficient c1 at the multiplier 77a and the resultant signal is sent to the maximum value circuit 35. In the third route, the signal is multiplied by a coefficient c2 at the multiplier 77b and the resultant signal is sent to the maximum value circuit 36.

The multiplier 79 multiplies the output signal of the maximum value circuit 33 by a coefficient m, and sends the product to the comparator 37 as the horizontal non-correlation energy DH.

The output signal of the maximum value circuit 33 is applied as a first vertical non-correlation energy DV1 to the comparator 37.

The output signal of the maximum value circuit 35, as a second vertical non-correlation energy DV21, is multiplied by a coefficient n1 at the multiplier 80a, and the product is sent to the comparator 38.

The output signal of the maximum value circuit 36, as a third vertical non-correlation energy DV22, is multiplied by a coefficient n2 at the multiplier 80b, and the product is sent to the comparator 39.

The comparator 37 compares the first vertical non-correlation energy DV1 and the product of the horizontal non-correlation energy DH and the coefficient m, and produces a high level output signal 116 when $DV1 \geq m \cdot DH$, and a low level output signal 116 at other times.

The comparator 38 compares the horizontal chrominance



non-correlation energy DCH and the product of the second vertical non-correlation energy DV21 and the coefficient n_1 , and produces a high level output signal 117 when $DCH \geq n_1 \cdot DV21$, and a low level output signal 117 at other times.

The comparator 39 compares the horizontal luminance non-correlation energy DYH and the product of the third vertical non-correlation energy DV22 and the coefficient n_2 , and produces a high level output signal 118 when $DYH \geq n_2 \cdot DV22$, and a low level output signal 118 at other times.

The respective output signals 116, 117 and 118 of the comparators 37, 38 and 39 are applied to the decision circuit 40. The output signal 110 of the decision circuit 40 serves as the output signal of the picture non-correlation decision circuit 18.

Following is a description of the picture non-correlation decision circuit 18 operation in accordance with this embodiment.

The horizontal non-correlation energy DH, the first vertical non-correlation energy DV1, the second vertical non-correlation energy DV21 and the third vertical non-correlation energy DV22 can be expressed as follows.

$$DH = \max (e \cdot DYH, f \cdot DCH)$$

$$DV1 = \max (g \cdot DYV, h \cdot DCV)$$

$$DV21 = \max (c1 \cdot DYV, d1 \cdot DCV)$$

$$DV22 = \max (c2 \cdot DYV, d2 \cdot DCV)$$

At the comparator 37, DV1 and $n \cdot DH$ are compared. If $DV1 \geq m \cdot DH$ the vertical non-correlation is interpreted as strong, and a "1" signal 116 is sent to the decision circuit 40. If

$$DV1 < m \cdot DH$$

the vertical non-correlation is interpreted as weak, and a "0" signal 116 is sent to the decision circuit 40.



At the comparator 38, DCH and $n1 \cdot DV21$ are compared. If
 $DCH \geq n1 \cdot DV21$
the horizontal non-correlation is interpreted as strong, and
a "1" signal 117 is sent to the decision circuit 40. If
 $DCH < n1 \cdot DV21$
the horizontal non-correlation is interpreted as weak, and a
"0" signal 117 is sent to the decision circuit 40.

At the comparator 39, DYH and $n2 \cdot DV22$ are compared. If
 $DYH \geq n2 \cdot DV22$
the horizontal non-correlation is interpreted as strong, and
a "1" signal 118 is sent to the decision circuit 40. If
 $DYH < n2 \cdot DV22$
the horizontal non-correlation is interpreted as weak, and a
"0" signal 118 is sent to the decision circuit 40.

According to the results of the above correlation
detection, the decision circuit 40 controls the selector 23
in the following manner. That is, the relationship of the
input signals 116, 117 and 118 of the decision circuit 40,
and its output signal 110, the selection of the chrominance
output signal 107, 109 or 111 at the selector 23 and the
selection of the chrominance output signal 1131 or 1132 at
the selector 25 is as shown in Table 3.



Table 3

Output 116(119) of Delay Delay Circuit 86	Output 117(120) of Delay Circuit 87	Output 118(123) of Circuit Circuit 90	Output 110 of of Decision Circuit 40		Chrominance Output 113 Selected by Selector Circuit 23	Chrominance Output 1133(1134) Selected by Selector 25 (25a)
			Output 110a of AND 41	Output 110b of AND 42		
0	0	0	1	0	111	1132
0	0	1	0	0	107	1131
0	1	0	0	0	107	1131
0	1	1	0	0	107	1131
1	0	0	0	1	109	1132
1	0	1	0	0	107	1131
1	1	0	0	0	107	1131
1	1	1	0	0	107	1131

When the output signals 110a and 110b of the AND circuits 41 and 42 are both "0", the selector 23 selects the output signal 107 of the compensating delay circuit 20. When the output signal 110a of the AND circuit 41 is "0" and the output signal 110b of the AND circuit 42 is "1", the output signal 109 of the compensating delay circuit 21 is selected. When the output signal 110a of the AND circuit 41 is "1" and the output signal 110b of the AND circuit 42 is "0", the output signal 111 of the compensating delay circuit 22 is selected.

When the output signals 110a and 110b of the AND circuits 41 and 42 are both "0", the selector 25 selects the output signal 1131 of the compensating delay circuit 91. At other times, the selector 25 selects the output signal 1132 of the horizontal chrominance extraction filter 24.

Consequently, in this embodiment, the response $C11(Z)$ of the filter for extracting the chrominance signal output through the terminal 26 and the response $C12(Z)$ of the filter for extracting the chrominance signal for extracting the luminance signal are given according to the presence or



absence of correlation in the following manner.

When the vertical non-correlation is strong,

$$C11(Z) = Ch1(Z)$$

$$C12(Z) = Ch1(Z) \cdot Ch2(Z)$$

When the horizontal non-correlation is strong,

$$C11(Z) = C12(Z) = Cv(Z)$$

When neither of these conditions are met,

$$C11(Z) = Chv(Z)$$

$$C12(Z) = Chv(Z) \cdot CH2(Z)$$


Embodiment 10

This embodiment is similar to Embodiment 41, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 13 is used.

Operation of the picture non-correlation decision circuit 18 used in this embodiment is similar to that of Embodiment 9.

The relationship of the input signals 116, 117 and 118 of the decision circuit 40, and its output signal 110, the selection of the chrominance output signal 107, 109 or 111 at the selector 23 and the selection of the chrominance output signal 1131 or 1132 at the selector 25a is as shown in Table 3.

When the output signals 110a and 110b of the AND circuits 41 and 42 are both "0", the selector 23 selects the output signal 107 of the compensating delay circuit 20. When the output signal 110a of the AND circuit 41 is "0" and the output signal 110b of the AND circuit 42 is "1", the output signal 109 of the compensating delay circuit 21 is selected. When the output signal 110a of the AND circuit 41 is "1" and the output signal 110b of the AND circuit 42 is "0", the output signal 111 of the compensating delay circuit 22



is selected.

When the output signals 110a and 110b of the AND circuits 41 and 42 are both "0", the selector 25a selects the output signal 1131 of the compensating delay circuit 91a. At other times, the selector 25a selects the output signal 1132 of the horizontal chrominance extraction filter 24a.

Consequently, in this embodiment, the response $C21(Z)$ of the filter for extracting the chrominance signal output through the terminal 26, and the response $C22(Z)$ of the filter for extracting the chrominance signal used for extracting the luminance signal are given below:

When the vertical non-correlation is strong,

$$C21(Z) = Ch1(Z) \cdot Ch2(Z)$$

$$C22(Z) = Ch1(Z)$$

When the horizontal non-correlation is strong,

$$C21(Z) = C22(Z) = Cv(Z)$$

When neither of these conditions are met,

$$C21(Z) = Chv(Z) \cdot CH2(Z)$$

$$C22(Z) = Chv(Z)$$

Embodiment 11

This embodiment is similar to Embodiment 1, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 14 is used.

The picture non-correlation decision circuit 18 of this embodiment is basically similar to that of Fig. 13, but is modified in the same way as described in connection with Fig. 10. That is, it differs from the circuit of Fig. 13, in that it is provided with the horizontal chrominance non-correlation energy extractor 129 comprising the first and second horizontal chrominance non-correlation energy



extractors 29a and 29b, and the vertical chrominance non-correlation energy extractor 131 comprising the first and second vertical chrominance non-correlation energy extractors 31a and 31b. The control over the circuits 23 and 25 in accordance with the signal 110 of the decision circuit 40 is as shown in Table 3.

Embodiment 12

This embodiment is similar to Embodiment 41, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 14 is used.

The operation of the picture non-correlation decision circuit 18 is the same as Embodiment 11 and the control over the selectors 23 and 25a in accordance with the output signal 110 of the decision circuit 40 is as shown in Table 3.

Embodiment 13

This embodiment is similar to Embodiment 1, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 15 is used.

The picture non-correlation decision circuit 18 of this embodiment is basically similar to that of Fig. 13, but is modified in the same way as described in connection with Fig. 11. That is, it differs from the circuit of Fig. 13, in that the delay circuits 86 - 89 and the AND circuit 90 similar to those in Fig. 11 are provided between the comparators 37 - 39 and the decision circuit 40.

Operation of these added circuits is the same as the embodiment of Fig. 11. The decision circuit 40 controls the selectors 23 and 25 on the basis of the input signals 119, 120 and 123 according to the results of correlation



detection described in the embodiment of Fig. 13. The control over the selectors 23 and 25a in accordance with the output signal 110 of the decision circuit 40 is as shown in Table 3.

Embodiment 14

This embodiment is similar to Embodiment 41, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 15 is used.


The operation of the picture non-correlation decision circuit 18 is the same as Embodiment 13 and the control over the selectors 23 and 25a in accordance with the output signal 110 of the decision circuit 40 is as shown in Table 3.

Embodiment 15

This embodiment is similar to Embodiment 1, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 16 is used.

The picture non-correlation decision circuit 18 of this embodiment is basically similar to that of Fig. 15, but is further modified in the same way as described in connection with Fig. 10.

Thus, the picture non-correlation decision circuit 18 of Fig. 16 differs from that of Fig. 15 in that it is provided with the horizontal chrominance non-correlation energy extractor 129 comprising the first and second horizontal chrominance non-correlation energy extractors 29a and 29b, and the vertical chrominance non-correlation energy extractor 131 comprising the first and second vertical chrominance non-correlation energy extractors 31a and 31b. The control over the selectors 23 and 25 in accordance with



the output signal 110 of the decision circuit 40 is the same as shown in Table 3.

Embodiment 16

This embodiment is similar to Embodiment 41, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 16 is used.

The operation of the picture non-correlation decision circuit 18 of this embodiment is the same as Embodiment 15 and the control over the selectors 23 and 25a in accordance with the output signal 110 of the the decision circuit 40 is the same as shown in Table 3.

Embodiment 17

This embodiment is similar to Embodiment 1, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 17 is used.

The picture non-correlation decision circuit 18 of this embodiment is generally similar to that of Fig. 9, but the maximum value circuit 36 of Fig. 9 is replaced by an adder 84.

That is, the output signal DCH of the horizontal chrominance non-correlation energy extractor 29 is branched in three routes. In the first route, the signal is multiplied by a coefficient b at the multiplier 72 and the resultant signal is sent to the maximum value circuit 33. In the second route, the signal is multiplied by a coefficient f1 at the multiplier 74a and the resultant signal is sent to the maximum value circuit 34. In the third route, the signal is multiplied by a coefficient f2 at the multiplier 74b and the resultant signal is sent to the maximum value circuit 35.



The output signal DYH of the horizontal luminance non-correlation energy extractor 30 is branched in three routes. In the first route, the signal is multiplied by a coefficient a at the multiplier 71 and the resultant signal is sent to the maximum value circuit 33. In the second route, the signal is multiplied by a coefficient e1 at the multiplier 73a and the resultant signal is sent to the maximum value circuit 34. In the third route, the signal is multiplied by a coefficient e2 at the multiplier 73b and the resultant signal is sent to the maximum value circuit 35.

The output signal DCV of the vertical chrominance non-correlation energy extractor 31 is branched in two routes. In the first route, the signal is applied directly to the comparator 38. In the second route, the signal is multiplied by a coefficient d at the multiplier 78 and the resultant signal is sent to the adder 84.

The output signal DYV of the vertical luminance non-correlation energy extractor 32 is branched in two routes. In the first route, the signal is applied directly to the comparator 39. In the second route, the signal is multiplied by a coefficient c at the multiplier 77 and the resultant signal is sent to the adder 84.

The output signal of the maximum value circuit 33 is applied as a first horizontal non-correlation energy DH1 to the comparator 37. The output signal of the maximum value circuit 34, as a second horizontal non-correlation energy DH21, is multiplied by a coefficient m1 at the multiplier 79a and the product is sent to the comparator 38. The output signal of the maximum value circuit 35, as a third horizontal non-correlation energy DH22, is multiplied by a coefficient m2 at the multiplier 79b, and the product is sent to the comparator 39.

The output signal of the adder 84, as the vertical non-correlation energy DV, is multiplied by a coefficient n at



the multiplier 80, and the product is sent to the comparator 37.

The comparator 37 compares the first horizontal non-correlation energy $DH1$ and the product $n \cdot DV$ of the vertical non-correlation energy DV and the coefficient n , and produces a high level output signal 116 when $DH1 \geq n \cdot DV$, and a low level output signal 116 at other times.

The comparator 38 compares the vertical chrominance non-correlation energy DCV and the product $m1 \cdot DH21$ of the second horizontal non-correlation energy $DH21$ and the coefficient $m1$, and produces a high level output signal 117 when $DCV \geq m1 \cdot DH21$, and a low level output signal 117 at other times.

The comparator 39 compares the vertical luminance non-correlation energy DYV and the product $m2 \cdot DH22$ of the third horizontal non-correlation energy $DH22$ and the coefficient $m2$, and produces a high level output signal 118 when $DYV \geq m2 \cdot DH22$, and a low level output signal 117 at other times.

The respective output signals 116, 117 and 118 of the comparators 37, 38 and 39 are applied to the decision circuit 40. The output signal 110 of the decision circuit 40 serves as the picture non-correlation decision circuit 18 output.

Following is a description of the operation of the picture non-correlation decision circuit 18 of this embodiment.

The first horizontal non-correlation energy $DH1$, the second horizontal non-correlation energy $DH21$, the third horizontal non-correlation energy $DH22$ and the vertical non-correlation energy DV can be expressed as follows.

$$DH1 = \max (a \cdot DYH, b \cdot DCH)$$

$$DH21 = \max (e1 \cdot DYH, f1 \cdot DCH)$$

$$DH22 = \max (e2 \cdot DYH, f2 \cdot DCH)$$



$$DV = \max (c \cdot DYV + d \cdot DCV)$$

At the comparator 37, $DH1$ and $n \cdot DV$ are compared. If

$$DH1 \geq n \cdot DV$$

the horizontal non-correlation is interpreted as strong, and a "1" signal 116 is sent to the decision circuit 40. If

$$DH1 < n \cdot DH$$

the horizontal non-correlation is interpreted as weak, and a "0" signal 116 is sent to the decision circuit 40.

At the comparator 38, DCV and $m1 \cdot DH21$ are compared. If

$$DCV \geq m1 \cdot DH21$$

the vertical non-correlation is interpreted as strong, and a "1" signal 117 is sent to the decision circuit 40. If

$$DCV < m1 \cdot DH21$$

the horizontal non-correlation is interpreted as weak, and a "0" signal 117 is sent to the decision circuit 40.

At the comparator 39, DYV and $m2 \cdot DH22$ are compared. If

$$DYV \geq m2 \cdot DH22$$

the vertical non-correlation is interpreted as strong, and a "1" signal 118 is sent to the decision circuit 40. If

$$DYV < m2 \cdot DH22$$

the vertical non-correlation is interpreted as weak, and a "0" signal 118 is sent to the decision circuit 40.

According to the results of the above correlation detection, the decision circuit 40 controls the selectors 23 and 25 in the following manner.

The relationship between the input signals 116, 117 and 118 of the decision circuit 40, and its output signal 110, the selection of the chrominance output signal 107, 109 or 111 at the selector 23 and the selection of the chrominance output signal 1131 or 1132 at the selector 25 is as shown in Table 2.

When the output signals 110a and 110b of the AND circuits 41 and 42 are both "0", the selector 23 selects the



output signal 109 of the compensating delay circuit 21. When the output signal 110a of the AND circuit 41 is "0" and the output signal 110b of the AND circuit 42 is "1", the output signal 107 of the compensating delay circuit 20 is selected. When the output signal 110a of the AND circuit 41 is "1" and the output signal 110b of the AND circuit 42 is "0", the output signal 111 of the compensating delay circuit 22 is selected.

When the output signal 110b of the AND circuit 42 is "1", the selector 25 selects the output signal 1131 of the compensating delay circuit 91. When the output signal 110b is "0", the selector 25 selects the output signal 1132 of the horizontal chrominance extraction filter 24.

Consequently, in this embodiment, the response $C11(Z)$ of the filter for extracting the chrominance signal output through the terminal 26, and the response $C12(Z)$ of the filter for extracting the chrominance signal used for extracting the luminance signal are given below:

When the vertical non-correlation is strong,

$$C11(Z) = Ch1(Z)$$

$$C12(Z) = Ch1(Z) \cdot Ch2(Z)$$

When the horizontal non-correlation is strong,

$$C11(Z) = C12(Z) = Cv(Z)$$

When neither of these conditions are met,

$$C11(Z) = Chv(Z)$$

$$C12(Z) = Chv(Z) \cdot CH2(Z)$$

Embodiment 18

This embodiment is similar to Embodiment 41, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 17 is used. The operation of the picture non-correlation decision circuit 18 is the same as Embodiment



17.

According to the results of the above correlation detection, the decision circuit 40 controls the selectors 23 and 25a in the following manner.

The relationship of the input signals 116, 117 and 118 of the decision circuit 40, and its output signal 110, the selection of the chrominance output signal 107, 109 or 111 at the selector 23 and the selection of the chrominance output signal 1131 or 1132 at the selector 25a is as shown in Table 2.

When the output signals 110a and 110b of the AND circuits 41 and 42 are both "0", the selector 23 selects the output signal 109 of the compensating delay circuit 21. When the output signal 110a of the AND circuit 41 is "0" and the output signal 110b of the AND circuit 42 is "1", the output signal 107 of the compensating delay circuit 20 is selected. When the output signal 110a of the AND circuit 41 is "1" and the output signal 110b of the AND circuit 42 is "0", the output signal 111 of the compensating delay circuit 22 is selected.

When the output signal 110b of the AND circuit 42 is "1", the selector 25a selects the output signal 1131 of the compensating delay circuit 91a. When the signal 110b is "0", the selector 25 selects the output signal 1132 of the horizontal chrominance extraction filter 24a.

Consequently, in the embodiment of Fig. 2, the response $C21(Z)$ of the filter for extracting the chrominance signal output through the terminal 26, and the response $C22(Z)$ of the filter for extracting the chrominance signal used for extracting the luminance signal are given below:

When the vertical non-correlation is strong,

$$C21(Z) = Ch1(Z) \cdot Ch2(Z)$$

$$C22(Z) = Ch1(Z)$$



When the horizontal non-correlation is strong,

$$C21(Z) = C22(Z) = C_v(Z)$$

When neither of these conditions are met,

$$C21(Z) = Ch_v(Z) \cdot CH2(Z)$$

$$C22(Z) = Ch_v(Z)$$

Embodiment 19

This embodiment is similar to Embodiment 1, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 18 is used.

The picture non-correlation decision circuit 18 of this embodiment is similar to that of Fig. 17, but is modified in the manner described with reference to Fig. 10 or Fig. 14. That is, it is provided with the horizontal chrominance non-correlation energy extractor 129 comprising the first and second horizontal chrominance non-correlation energy extractors 29a and 29b, and the vertical chrominance non-correlation energy extractor 131 comprising the first and second vertical chrominance non-correlation energy extractors 31a and 31b. The control over the selection by the selectors 23 and 25 according to the output signal 110 of the decision circuit 40 is as shown in Table 2.

Embodiment 20

This embodiment is similar to Embodiment 41, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 18 is used.

The operation of the picture non-correlation decision circuit 18 is the same as Embodiment 19. The control over the selection by the selectors 23 and 25a according to the output signal 110 of the decision circuit 40 is as shown in Table 2.



Embodiment 21

This embodiment is similar to Embodiment 1, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 19 is used.

The picture non-correlation decision circuit 18 of this embodiment is similar to that of Fig. 17, but is modified in the same manner as described with reference to Fig. 11. That is, the picture non-correlation decision circuit 18 of Fig. 19 differs from that of Fig. 17 in that the delay circuits 86 - 89 and the AND circuit 90 as in Fig. 11 are provided between the comparators 37 - 39 and the decision circuit 40 of the embodiment of Fig. 17. Operation of these added portions is the same as the embodiment of Fig. 11. The decision circuit 40 controls the selectors 23 and 25 on the basis of the input signals 119, 120 and 123, in accordance with the results of the correlation detection described in the embodiment of Fig. 17.

The relationship of the input signals 119, 120 and 123 of the decision circuit 40, and its output signal 110, the selection of the chrominance output signal 107, 109 or 111 at the selector 23 and the selection of the chrominance output signal 1131 or 1132 at the selector 25 is as shown in Table 2.

Embodiment 22

This embodiment is similar to Embodiment 41, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 19 is used.

The operation of the picture non-correlation decision circuit 18 is the same as Embodiment 21.

The relationship of the input signals 119, 120 and 123



of the decision circuit 40, and its output signal 110, the selection of the chrominance output signal 107, 109 or 111 at the selector 23 and the selection of the chrominance output signal 1131 or 1132 at the selector 25a is as shown Table 2.

Embodiment 23

This embodiment is similar to Embodiment 1, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 20 is used.

The picture non-correlation decision circuit 18 of this embodiment is similar to that of Fig. 19, but is modified in the same way as Fig. 10. That is, it is provided with the horizontal chrominance non-correlation energy extractor 129 comprising the first and second horizontal chrominance non-correlation energy extractors 29a and 29b, and the vertical chrominance non-correlation energy extractor 131 comprising the first and second vertical chrominance non-correlation energy extractors 31a and 31b. The control over the selection of the selectors 23 and 25 according to the output signal 110 of the decision circuit 40 is as shown in Table 2.

Embodiment 24

This embodiment is similar to Embodiment 41, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 20 is used.

The operation of the picture non-correlation decision circuit 18 is the same as Embodiment 23. The control over the selection of the selectors 23 and 25a according to the output signal 110 of the decision circuit 40 is as shown in Table 2.



Embodiment 25

This embodiment is similar to Embodiment 1, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 21 is used.

The picture non-correlation decision circuit 18 of this embodiment is similar to that of Fig. 9, but the maximum value circuit 33 of Fig. 9 is replaced by an adder 81.

That is, the output signal DCH of the horizontal chrominance non-correlation energy extractor 29 is branched in two routes. In the first route, the signal is applied directly to the comparator 38. In the second route, the signal is multiplied by a coefficient f at the multiplier 72 and the resultant signal is sent to the adder 81.

The output signal DYH of the horizontal luminance non-correlation energy extractor 30 is branched in two routes. In the first route, the signal is applied directly to the comparator 39. In the second route, the signal is multiplied by a coefficient e at the multiplier 71 and the resultant signal is sent to the adder 81.

The output signal DCV of the vertical chrominance non-correlation energy extractor 31 is branched in three routes. In the first route, the signal is multiplied by a coefficient h at the multiplier 76 and the resultant signal is sent to the maximum value circuit 34. In the second route, the signal is multiplied by a coefficient $d1$ at the multiplier 78a and the resultant signal is sent to the maximum value circuit 35. In the third route, the signal is multiplied by a coefficient $d2$ at the multiplier 78b and the resultant signal is sent to the maximum value circuit 36.

The output signal DYV of the vertical luminance non-correlation energy extractor 32 is branched in three routes.



In the first route, the signal is multiplied by a coefficient g at the multiplier 75 and the resultant signal is sent to the maximum value circuit 34. In the second route, the signal is multiplied by a coefficient $c1$ at the multiplier 77a and the resultant signal is sent to the maximum value circuit 35. In the third route, the signal is multiplied by a coefficient $c2$ at the multiplier 77b, and the resultant signal is sent to the maximum value circuit 36.

The output signal of the adder 81, as the horizontal non-correlation energy DH , is multiplied by a coefficient m at the multiplier 79, whose output is sent to the comparator 37. The output signal of the maximum value circuit 34 is applied as a first vertical non-correlation energy $DV1$ to the comparator 37. The output signal of the maximum value circuit 35, as a second vertical non-correlation energy $DV21$, is multiplied by a coefficient $n1$ at the multiplier 80a, and is sent to the comparator 38. The output signal of the maximum value circuit 36, third vertical non-correlation energy $DV22$, is multiplied by a coefficient $n2$ at the multiplier 80 to the comparator 39.

The comparator 37 compares the first vertical non-correlation energy $DV1$ and the product $m \cdot DH$ of the horizontal non-correlation energy DH and the coefficient m , and produces a high level output signal 116 when $DV1 \geq m \cdot DH$, and a low level output signal 116 at other times.

The comparator 38 compares the horizontal chrominance non-correlation energy DCH and the product $n1 \cdot DV21$ of the second vertical non-correlation energy $DV21$ and the coefficient $n1$, and produces a high level output signal 117 when $DCH \geq n1 \cdot DV21$, and a low level output signal 117 at other times.

The comparator 39 compares the horizontal luminance non-correlation energy DYH and the product $n2 \cdot DV22$ of the



vertical non-correlation energy DV22 and the coefficient n_2 , and produces a high level output signal 118 when $DYH \geq n_2 \cdot DV22$, and a low level output signal 117 at other times.

The respective output signals 116, 117 and 118 of the comparators 37, 38 and 39 are applied to the decision circuit 40. The output signal 110 of the decision circuit 40 serves as the output signal of the picture non-correlation decision circuit 18.

Following is a description of the picture non-correlation decision circuit 18 of this embodiment.

The first vertical non-correlation energy DV1, the second vertical non-correlation energy DV21, the third vertical non-correlation energy DV22 and the horizontal non-correlation energy DH can be expressed as follows.

$$\begin{aligned} DH &= \max (e \cdot DYH + f \cdot DCH) \\ DV1 &= \max (g \cdot DYV, h \cdot DCV) \\ DV21 &= \max (c_1 \cdot DYV, d_1 \cdot DCV) \\ DV22 &= \max (c_2 \cdot DYV + d_2 \cdot DCV) \end{aligned}$$

At the comparator 37, DV1 and $m \cdot DH$ are compared. If $DV1 \geq m \cdot DH$ the vertical non-correlation is interpreted as strong, and a "1" signal 116 is sent to the decision circuit 40. If $DV1 < m \cdot DV$

the vertical non-correlation is interpreted as weak, and a "0" signal 116 is sent to the decision circuit 40.

At the comparator 38, DCH and $n_1 \cdot DV21$ are compared. If $DCH \geq n_1 \cdot DV21$ the horizontal non-correlation is interpreted as strong, and a "1" signal 117 is sent to the decision circuit 40. If $DCH < n_1 \cdot DV21$

the horizontal non-correlation is interpreted as weak, and a "0" signal 117 is sent to the decision circuit 40.



At the comparator 39, DYH and $n2 \cdot DV22$ are compared. If $DYH \geq n2 \cdot DV22$ the horizontal non-correlation is interpreted as strong, and a "1" signal 118 is sent to the decision circuit 40. If

$DYH < n2 \cdot DV22$ the horizontal non-correlation is interpreted as weak, as indicated below, a "0" signal 118 is sent to the decision circuit 40.

According to the results of the above correlation detection, the decision circuit 40 controls the selectors 23 and 25 in the following manner.

The relationship between the input signals 116, 117 and 118 of the decision circuit 40, and its output signal 110, the selection of the chrominance output signal 107, 109 or 111 at the selector 23 and the selection of the chrominance output signal 1131 or 1132 at the selector 25 is as shown in Table 3.

When the output signals 110a and 110b of the AND circuits 41 and 42 are both "0", the selector 23 selects the output signal 107 of the compensating delay circuit 20. When the output signal 110a of the AND circuit 41 is "0" and the output signal 110b of the AND circuit 42 is "1", the output signal 109 of the compensating delay circuit 21 is selected. When the output signal 110a of the AND circuit 41 is "1" and the output signal 110b of the AND circuit 42 is "0", the output signal 111 of the compensating delay circuit 22 is selected.

When the output signals 110a and 110b of the AND circuits 41 and 42 are both "1", the selector 25 selects the output signal 1131 of the compensating delay circuit 91. At other times, the selector 25 selects the output signal 1132 of the horizontal chrominance extraction filter 24.

Consequently, in the embodiment of Fig. 2, the response $C11(Z)$ of the filter for extracting the chrominance signal



output through the terminal 26, and the response $C12(Z)$ of the filter for extracting the chrominance signal used for extracting the luminance signal are given below:

When the vertical non-correlation is strong,

$$C11(Z) = Ch1(Z)$$

$$C12(Z) = Ch1(Z) \cdot Ch2(Z)$$

When the horizontal non-correlation is strong,

$$C11(Z) = C12(Z) = Cv(Z)$$

When neither of these conditions are met,

$$C11(Z) = Chv(Z)$$

$$C12(Z) = Chv(Z) \cdot CH2(Z)$$

Embodiment 26

This embodiment is similar to Embodiment 41, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 21 is used.

The operation of the picture non-correlation decision circuit 18 is the same as Embodiment 25

The relationship between the input signals 116, 117 and 118 of the decision circuit 40, and its output signal 110, the selection of the chrominance output signal 107, 109 or 111 at the selector 23 and the selection of the chrominance output signal 1131 or 1132 at the selector 25a is as shown in Table 3.

Embodiment 27

This embodiment is similar to Embodiment 1, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 22 is used.

The picture non-correlation decision circuit 18 of this embodiment is similar to that of Fig. 21, but is modified in



the same way as in Fig. 10. That is, it is provided with the horizontal chrominance non-correlation energy extractor 129 comprising the first and second horizontal chrominance non-correlation energy extractors 29a and 29b, and the vertical chrominance non-correlation energy extractor 131 comprising the first and second vertical chrominance non-correlation energy extractors 31a and 31b. The control over the selection by the selectors 23 and 25 according to the output signal 110 of the decision circuit 40 is as shown in Table 3.

Embodiment 28

This embodiment is similar to Embodiment 41, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 22 is used.

The operation of this picture non-correlation decision circuit 18 is the same as Embodiment 27. The control over the selection by the selectors 23 and 25a according to the output signal 110 of the decision circuit 40 is as shown in Table 3.

Embodiment 29

This embodiment is similar to Embodiment 1, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 23 is used.

The picture non-correlation decision circuit of Fig. 23 is similar to that of Fig. 21, but is modified in the same way as Fig. 11. That is, delay circuits 86 - 89 and AND circuit 90 similar to those in Fig. 11 are provided between the comparators 37 - 39 and the decision circuit 40. Operation of these added circuits is the same as the embodiment of Fig. 11. The decision circuit 40 controls the



selectors 23 and 25 on the basis of the input signals 119, 120 and 123 according to the results of the correlation detection described in the embodiment of Fig. 21. The control over the selectors 23 and 25 in accordance with the output signal 110 of the decision circuit 40 is as shown in Table 3.

Embodiment 30

This embodiment is similar to Embodiment 41, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 23 is used.

The operation of this picture non-correlation decision circuit 18 operation is the same as Embodiment 29, and the control over the selectors 23 and 25a in accordance with the output signal 110 of the decision circuit 40 is as shown in Table 3.

Embodiment 31

This embodiment is similar to Embodiment 1, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 24 is used.

The picture non-correlation decision circuit 18 of this embodiment is similar to that of Fig. 23, but is modified in the same way as in Fig. 10. That is, it is provided with the horizontal chrominance non-correlation energy extractor 129 comprising the first and second horizontal chrominance non-correlation energy extractors 29a and 29b, and the vertical chrominance non-correlation energy extractor 131 comprising the first and second vertical chrominance non-correlation energy extractors 31a and 31b. The control over the selection by the selectors 23 and 25 according to the output signal 110 of the decision circuit 40 is as shown in



Table 3.

Embodiment 32

This embodiment is similar to Embodiment 41, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 24 is used.

The operation of this picture non-correlation decision circuit 18 operation is the same as Embodiment 31, and the control over the selectors 23 and 25a in accordance with the output signal 110 of the decision circuit 40 output 110 is as shown in Table 3.

Embodiment 33

This embodiment is similar to Embodiment 1, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 25 is used.

The picture non-correlation decision circuit 18 of this embodiment is similar to that of Fig. 9, but the maximum value circuit 34 of Fig. 9 is replaced by an adder 82, and the maximum value circuit 35 of Fig. 9 is replaced by an adder 83.

The output signal DCH of the horizontal chrominance non-correlation energy extractor 29 is branched in three routes. In the first route, the signal is multiplied by a coefficient b at the multiplier 72, and the resultant signal is sent to the maximum value circuit 33. In the second route, the signal is multiplied by a coefficient f_1 at the multiplier 74a, and the resultant signal is sent to the adder 82. In the third route, the signal is multiplied by a coefficient f_2 at the multiplier 74b, and the resultant signal is sent to the adder 83.

The output signal DYH of the horizontal luminance non-



correlation energy extractor 30 is branched in three routes. In the first route, the signal is multiplied by a coefficient a at the multiplier 71, and the resultant signal is sent to the maximum value circuit 33. In the second route, the signal is multiplied by a coefficient e_1 at the multiplier 73a, and the resultant signal is sent to the adder 82. In the third route, the signal is multiplied by a coefficient e_2 at the multiplier 73b, and the resultant signal is sent to the adder 83.

The output signal DCV of the vertical chrominance non-correlation energy extractor 31 is branched in two routes. In the first route, the signal is applied directly to the comparator 38. In the second route, the signal is multiplied by a coefficient d at the multiplier 78, and the resultant signal is sent to the maximum value circuit 36.

The output signal DYV of the vertical luminance non-correlation energy extractor 2 is branched in two routes. In the first route, the signal is applied directly to the comparator 39. In the second route, the signal is multiplied by a coefficient e at the multiplier 77, and the resultant signal is sent to the maximum value circuit 36.

The output signal of the maximum value circuit 33 is applied as a first horizontal non-correlation energy DH1 to the comparator 37. The output signal of the the adder 82, as a second horizontal non-correlation energy DH21, is multiplied by a coefficient m_1 at multiplier 79a, and the product is sent to the comparator 38. The output signal of the adder 83, as as a third horizontal non-correlation energy DH22, is multiplied by a coefficient m_2 at the multiplier 79b, and the product is sent to the comparator 39.

The output signal of the the maximum value circuit 36, as the vertical non-correlation energy DV, is multiplied by a coefficient n at the multiplier 80, and the product is



sent to the comparator 37.

The comparator 37 compares the first horizontal non-correlation energy DH1 and the product $n \cdot DV$ of the vertical non-correlation energy DV and the coefficient n , and produces a high level output signal 116 when $DH1 \geq n \cdot DV$, and a low level output signal 116 at other times.

The comparator 38 compares the vertical chrominance non-correlation energy DCV and the product $m1 \cdot DH21$, of the second horizontal non-correlation energy DH21 and the coefficient $m1$, and produces a high level output signal 117 when $DCV \geq m1 \cdot DH21$, and a low level output signal 117 at other times.

The comparator 39 compares the vertical luminance non-correlation energy DYV and the product $m2 \cdot DH22$ of the third horizontal non-correlation energy DH22 and the coefficient $m2$, and produces a high level output signal 118 when $DYV \geq m2 \cdot DH22$, and a low level output signal 117 at other times.

The respective output signals 116, 117 and 118 of the comparators 37, 38 and 39 are applied to the decision circuit 40. The output signal 110 of the decision circuit 40 serves as the output signal of the picture non-correlation decision circuit 18.

Following is a description of the operation of the picture non-correlation decision circuit 18 of this embodiment.

The first horizontal non-correlation energy DH1, the second horizontal non-correlation energy DH21, the third horizontal non-correlation energy DH22 and the vertical non-correlation energy DV can be expressed as follows.

$$DH1 = \max (a \cdot DYH, b \cdot DCH)$$

$$DH21 = e1 \cdot DYH + f1 \cdot DCH$$

$$DH22 = e2 \cdot DYH + f2 \cdot DCH$$

$$DV = \max (c \cdot DYV, d \cdot DCV)$$



At the comparator 37, $DH1$ and $n \cdot DV$ are compared. If
 $DH1 \geq n \cdot DV$
the horizontal non-correlation is interpreted as strong, and
a "1" signal 116 is sent to the decision circuit 40. If

$DH1 < n \cdot DV$
the horizontal non-correlation is interpreted as weak, and a
"0" signal 116 is sent to the decision circuit 40.

At the comparator 38, DCV and $m1 \cdot DH21$ are compared. If
 $DCV \geq m1 \cdot DH21$
the vertical non-correlation is interpreted as strong, and a
"1" signal 117 is sent to the decision circuit 40. If

$DCV < m1 \cdot DH21$
the vertical non-correlation is interpreted as weak, and a
"0" signal 117 is sent to the decision circuit 40.


At the comparator 39, DYV and $m2 \cdot DH22$ are compared. If
 $DYV \geq m2 \cdot DH22$
the vertical non-correlation is interpreted as strong, and a
"1" signal 118 is sent to the decision circuit 40. If

$DYV < m2 \cdot DH22$
the vertical non-correlation is interpreted as weak, and a
"0" signal 118 is sent to the decision circuit 40.

According to the results of the above correlation
detection, the decision circuit 40 controls the selectors 23
and 25 in the following manner.

The relationship between the input signals 116, 117 and
118 of the decision circuit 40, and its output signal 110,
the selection of the chrominance output signal 107, 109 or
111 at the selector 23 and the selection of the chrominance
output signal 1131 or 1132 at the selector 25 is as shown in
Table 2.

When the output signals 110a and 110b of the AND
circuits 41 and 42 are both "0", the selector 23 selects the
compensating delay circuit 21 output signal 109. When the



output signal 110a of the AND circuit 41 is "0" and the output signal 110b of the AND circuit 42 is "1", the output signal 107 of the compensating delay circuit 20 is selected. When the output signal 110a of the AND circuit 41 is "1" and the output signal 110b of the AND circuit 42 is "0", the output signal 111 of the compensating delay circuit 22 is selected.

When the output signal 110b of the AND circuit 42 is "1", the selector 25 selects the output signal 1131 of the compensating delay circuit 91. At other times, the selector 25 selects the output signal 1132 of the horizontal chrominance extraction filter 24.

Consequently, in the embodiment of Fig. 2, the response $C11(Z)$ of the filter for extracting the chrominance signal output through the terminal 26, and the response $C12(Z)$ of the filter for extracting the chrominance signal used for extracting the luminance signal are given below:

When the vertical non-correlation is strong,

$$C11(Z) = Ch1(Z)$$

$$C12(Z) = Ch1(Z) \cdot Ch2(Z)$$

When the horizontal non-correlation is strong,

$$C11(Z) = C12(Z) = Cv(Z)$$

When neither of these conditions are met,


$$C11(Z) = Chv(Z)$$

$$C12(Z) = Chv(Z) \cdot CH2(Z)$$

Embodiment 34

This embodiment is similar to Embodiment 41, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 25 is used.

The operation of this picture non-correlation decision circuit 18 is the same as Embodiment 33.



The relationship between the input signals 116, 117 and 118 of the decision circuit 40, and its output signal 110, the selection of the chrominance output signal 107, 109 or 111 at the selector 23 and the selection of the chrominance output signal 1131 or 1132 at the selector 25a is as shown in Table 2.

When the output signals 110a and 110b of the AND circuits 41 and 42 are both "0", the selector 23 selects the output signal 109 of the compensating delay circuit 21. When the output signal 110a of the AND circuit 41 is "0" and the output signal 110b of the AND circuit 42 is "1", the output signal 107 of the compensating delay circuit 20 is selected. When the output signal 110a of the AND circuit 41 is "1" and the output signal 110b of the AND circuit 42 is "0", the output signal 111 of the compensating delay circuit 22 is selected.

When the output signal 110b of the AND circuit 42 is "1", the selector 25 selects the output signal 1131 of the compensating delay circuit 91. At other times, the selector 25 selects the output signal 1132 of the horizontal chrominance extraction filter 24.

Consequently, in the embodiment of Fig. 2, the response $C21(Z)$ of the filter for extracting the chrominance signal output through the terminal 26, and the response $C22(Z)$ of the filter for extracting the chrominance signal used for extracting the luminance signal are given below:

When the vertical non-correlation is strong,

$$C21(Z) = Ch1(Z) \cdot Ch2(Z)$$

$$C22(Z) = Ch1(Z)$$

When the horizontal non-correlation is strong,

$$C21(Z) = C22(Z) = Cv(Z)$$

When neither of these conditions are met,

$$C21(Z) = Chv(Z) \cdot CH2(Z)$$



$$C22(Z) = Chv(Z)$$

Embodiment 35

This embodiment is similar to Embodiment 1, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 26 is used.

The picture non-correlation decision circuit 18 of this embodiment is similar to that of Fig. 25, but is modified in the same way as in Fig. 10. That is, it is provided with the horizontal chrominance non-correlation energy extractor 129 comprising the first and second horizontal chrominance non-correlation energy extractors 29a and 29b, and the vertical chrominance non-correlation energy extractor 131 comprising the first and second vertical chrominance non-correlation energy extractors 31a and 31b. The control over the selection by the selectors 23 and 25 according to the output signal 110 of the decision circuit 40 is as shown in Table 2.

Embodiment 36

This embodiment is similar to Embodiment 41, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 26 is used.

The operation of this picture non-correlation decision circuit 18 is the same as Embodiment 35, and the control over the selectors 23 and 25a in accordance with the output signal 110 of the decision circuit 40 is as shown in Table 2.

Embodiment 37

This embodiment is similar to Embodiment 1, but in place of the picture non-correlation decision circuit 18 of



Fig. 9, the picture non-correlation decision circuit shown in Fig. 27 is used.

The picture non-correlation decision circuit 18 of this embodiment is similar to that of Fig. 25, but is modified in the same way as in Fig. 11. That is, the delay circuits 86 - 89 and the AND circuit 90 are provided between the comparators 37 - 39 and the decision circuit 40. Operation of these added portions is the same as the embodiment of Fig. 11. The decision circuit 40 controls selectors 23 and 25 on the basis of input signals 119, 120 and 123 according to the correlation detection results described in the embodiment of Fig. 21. The control over the selectors 23 and 25 in accordance with the output signal 110 of the decision circuit 40 is as shown in Table 2.

Embodiment 38


This embodiment is similar to Embodiment 41, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 27 is used.

The operation of this picture non-correlation decision circuit 18 is the same as Embodiment 37 and the control over the selectors 23 and 25a in accordance with the output signal 110 of the decision circuit 40 is as shown in Table 2.

Embodiment 39

This embodiment is similar to Embodiment 1, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 28 is used.

The picture non-correlation decision circuit 18 of this embodiment is similar to that of Fig. 27, but is modified in the same way as in Fig. 10. That is, it is provided with



the horizontal chrominance non-correlation energy extractor 129 comprising the first and second horizontal chrominance non-correlation energy extractors 29a and 29b, and the vertical chrominance non-correlation energy extractor 131 comprising the first and second vertical chrominance non-correlation energy extractors 31a and 31b. The control over the selection of the selectors 23 and 25 according to the the decision circuit 40 is as shown Table 2.

Embodiment 40

This embodiment is similar to Embodiment 41, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 28 is used.

The operation of this picture non-correlation decision circuit 18 is the same as that of Embodiment 39, and the control over the selectors 23 and 25a in accordance with the output signal 110 of the decision circuit 40 is as shown in Table 2.

Embodiment 41

This embodiment is similar to Embodiment 1, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 29 is used.

The picture non-correlation decision circuit 18 of this embodiment is similar to that of Fig. 25, but the inputs of the adders 82 and 83 are coupled via multipliers 75, 76, 77a and 78a to the outputs of the vertical luminance non-correlation energy extractor 32 and the vertical chrominance non-correlation energy extractor 31, respectively.

Moreover, the output of the horizontal luminance non-correlation energy extractor 30 is coupled directly to one of the comparators, 39. This is in contrast to Fig. 25, in



which the output of the vertical chrominance non-correlation energy extractor 31 is directly coupled one of the maximum value circuits, 38. Details of the interconnection of the embodiment of Fig. 29 is as follows:

The output signal DCH of the horizontal chrominance non-correlation energy extractor 29 is branched in two routes. In the first route, the signal is applied directly to the comparator 38. In the second route, the signal is multiplied by a coefficient f at the multiplier 72, and the resultant signal is sent to the maximum value circuit 33.

The output signal DYH of the horizontal luminance non-correlation energy extractor 30 is branched in two routes. In the first route, the signal is applied directly to the comparator 39. In the second route, the signal is multiplied by a coefficient c at the multiplier 71, and the resultant signal is sent to the maximum value circuit 33.

The output signal DCV of the vertical chrominance non-correlation energy extractor 31 is branched in three routes. In the first route, the signal is multiplied by a coefficient h at the multiplier 76, and the resultant signal is sent to the adder 82. In the second route, the signal is multiplied by a coefficient $d1$ at the multiplier 78a, and the resultant signal is sent to the adder 83. In the third route, the signal is multiplied by a coefficient $d2$ at the multiplier 78b, and the resultant signal is sent to the maximum value circuit 36.

The output signal DYV of the vertical luminance non-correlation energy extractor 32 is branched in three routes. In the first route, the signal is multiplied by a coefficient g at the multiplier 75, and the resultant signal is sent to the adder 82. In the second route, the signal is multiplied by a coefficient $c1$ at the multiplier 77a, and the resultant signal is sent to the adder 83. In the third route, the signal is multiplied by a coefficient $c2$ at the



multiplier 77b, and the resultant signal is sent to the maximum value circuit 36.

The output signal of the maximum value circuit 33, as the horizontal non-correlation energy DH , is multiplied by a coefficient m at the multiplier 79, and the product is sent to the comparator 37. The output signal of the adder 82 is applied as a first vertical non-correlation energy $DV1$ to the comparator 37. The output signal of the adder 83, as a second vertical non-correlation energy $DV21$, is multiplied by a coefficient $n1$ at the multiplier 80a, and the product is sent to the comparator 38. The output signal of the maximum value circuit 36, as a third vertical non-correlation energy $DV22$, is multiplied by a coefficient $n2$ at the multiplier 80b, and the product is sent to the comparator 39.

The comparator 37 compares the first vertical non-correlation energy $DV1$ and the product $m \cdot DH$ of the horizontal non-correlation energy DH and the coefficient m , and produces a high level output signal 116 when $DV1 \geq m \cdot DH$, and a low level output signal 116 at other times.

The comparator 38 compares the horizontal chrominance non-correlation energy DCH and the product $n1 \cdot DV21$ of the second vertical non-correlation energy $DV21$ and the coefficient $n1$, and produces a high level output signal 117 when $DCH \geq n1 \cdot DV21$, and a low level output signal 117 at other times.

The comparator 39 compares the horizontal luminance non-correlation energy DYH and the product $n2 \cdot DV22$ of the third vertical non-correlation energy $DV22$ and the coefficient $n2$, and produces a high level output signal 118 when $DYH \geq n2 \cdot DV22$, and a low level output signal 117 at other times.

The respective output signals 116, 117 and 118 of the comparators 37, 38 and 39 are applied to the decision



circuit 40. The output signal 110 of the decision circuit 40 serves as the output signal of the picture non-correlation decision circuit 18.

Following is a description of operation of the picture non-correlation decision circuit 18 of this embodiment.

The first vertical non-correlation energy DV1, the second vertical non-correlation energy DV21, the third vertical non-correlation energy DV22 and the horizontal non-correlation energy DH can be expressed as follows.

$$DH = \max (e \cdot DYH, f \cdot DCH)$$

$$DV1 = g \cdot DYV + h \cdot DCV$$

$$DV21 = c1 \cdot DYV + d1 \cdot DCV$$

$$DV22 = \max (c2 \cdot DYV, d2 \cdot DCV)$$

At the comparator 37, DV1 and $m \cdot DH$ are compared. If $DV1 \geq m \cdot DH$ the vertical non-correlation is interpreted as strong, and a "1" signal 116 is sent to the decision circuit 40. If

$DV1 < m \cdot DH$ the vertical non-correlation is interpreted as weak, as indicated below, a "0" signal 116 is sent to the decision circuit 40.

At the comparator 38, DCH and $n1 \cdot DV21$ are compared. If $DCH \geq n1 \cdot DV21$ the horizontal non-correlation is interpreted as strong, and a "1" signal 117 is sent to the decision circuit 40. If

$DCH < n1 \cdot DV21$ the horizontal non-correlation is interpreted as weak, and a "0" signal 117 is sent to the decision circuit 40.

At the comparator 39, DYH and $n2 \cdot DV22$ are compared. If $DYH \geq n2 \cdot DV22$ the horizontal non-correlation is interpreted as strong, and a "1" signal 118 is sent to the decision circuit 40. If



DYH < n2·DV22

the horizontal non-correlation is interpreted as weak, and a "0" signal 118 is sent to the decision circuit 40.

According to the results of the above correlation detection, the decision circuit 40 controls the selectors 23 and 25 in the following manner.

The relationship between the input signals 116, 117 and 118 of the decision circuit 40, and its output signal 110, the selection of the chrominance output signal 107, 109 or 111 at the selector 23 and the selection of the chrominance output signal 1131 or 1132 at the selector 25 is as shown in Table 3.

When the output signals 110a and 110b of the AND circuits 41 and 42 are both "0", the selector 23 selects the output signal 107 of the compensating delay circuit 20. When the output signal 110a of the AND circuit 41 is "0" and the output signal 110b of the AND circuit 42 is "1", the output signal 109 of the compensating delay circuit 21 is selected. When the output signal 110a of the AND circuit 41 is "1" and the output signal 110b of the AND circuit 42 is "0", the output signal 111 of the compensating delay circuit 22.

When the output signals 110a and 110b of the AND circuits 41 and 42 are both "1", the selector 25 selects the output signal 1131 of the compensating delay circuit 91. At other times, the selector 25 selects the output signal 1132 of the horizontal chrominance extraction filter 24.

Consequently, in this embodiment, the response C11(Z) of the filter for extracting the chrominance signal output through the terminal 26, and the response C12(Z) of the filter for extracting the chrominance signal used for extracting the luminance signal are given below:

When the vertical non-correlation is strong,



$$C11(Z) = Ch1(Z)$$

$$C12(Z) = Ch1(Z) \cdot Ch2(Z)$$

When the horizontal non-correlation is strong,

$$C11(Z) = C22(Z) = Cv(Z)$$

When neither of these conditions are met,

$$C11(Z) = Chv(Z)$$

$$C12(Z) = Chv(Z) \cdot CH2(Z)$$

Embodiment 42

This embodiment is similar to Embodiment 41, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 29 is used.

The operation of this picture non-correlation decision circuit 18 is the same as that of Embodiment 41.

The relationship between the input signals 116, 117 and 118 of the decision circuit 40, and its output signal 110, the selection of the chrominance output signal 107, 109 or 111 at the selector 23 and the selection of the chrominance output signal 1131 or 1132 at the selector 25a is as shown in Table 3.

Embodiment 43

This embodiment is similar to Embodiment 1, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 30 is used.

The picture non-correlation decision circuit 18 of this embodiment is similar to that of Fig. 29, but is modified in the same way as in Fig. 10. That is, it is provided with the horizontal chrominance non-correlation energy extractor 129 comprising the first and second horizontal chrominance non-correlation energy extractors 29a and 29b, and the vertical chrominance non-correlation energy extractor 131



comprising the first and second vertical chrominance non-correlation energy extractors 31a and 31b. The control over the selection by the selectors 23 and 25 according to the Fig. 28 decision circuit 40 output 110 is as shown in Table 3.

Embodiment 44


This embodiment is similar to Embodiment 41, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 30 is used.

The operation of this picture non-correlation decision circuit 18 is the same as that of Embodiment 43, and the control over the selectors 23 and 25a in accordance with the output signal 110 of the decision circuit 40 is as shown in Table 3.

Embodiment 45

This embodiment is similar to Embodiment 1, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 31 is used.

The picture non-correlation decision circuit 18 of Fig. 31 is similar to that of Fig. 29, but is modified in the same way as in Fig. 11. That is, the delay circuits 86 - 89 and the AND circuit 90 are provided between the comparators 37 - 39 and the decision circuit 40. Operation of these added circuits is the same as that of the embodiment of Fig. 11. The decision circuit 40 controls selectors 23 and 25 on the basis of the input signals 119, 120 and 123 according to the results of the correlation detection described in the embodiment of Fig. 29. The control over the selectors 23 and 25 in accordance with the output signal 110 of the decision circuit 40 is as shown in Table 3.



Embodiment 46

This embodiment is similar to Embodiment 41, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 31 is used.

The operation of this picture non-correlation decision circuit 18 is the same as that of Embodiment 45, and the control over the selectors 23 and 25a in accordance with the output signal 110 of the decision circuit 40 is as shown in Table 3.

Embodiment 47

This embodiment is similar to Embodiment 1, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 32 is used.

The picture non-correlation decision circuit 18 of this embodiment is similar to that of Fig. 31, but is modified in the same way as in Fig. 11. That is, it is provided with the horizontal chrominance non-correlation energy extractor 129 comprising the first and second horizontal chrominance non-correlation energy extractors 29a and 29b, and the vertical chrominance non-correlation energy extractor 131 comprising the first and second vertical chrominance non-correlation energy extractors 31a and 31b. The control over the selection by the selectors 23 and 25 according to the output signal 110 of the decision circuit 40 is as shown in Table 3.

Embodiment 48

This embodiment is similar to Embodiment 41, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown



in Fig. 32 is used.

The operation of this picture non-correlation decision circuit 18 is the same as that of Embodiment 47, and the control over the selectors 23 and 25a in accordance with the output signal 110 of the decision circuit 40 is as shown in Table 3.


Embodiment 49

This embodiment is similar to Embodiment 1, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 33 is used.

The picture non-correlation decision circuit 18 of this embodiment is similar to that of Fig. 25, but another one of the maximum value circuits, 36 is replaced by an adder 84. That is, the interconnection of the circuits of the embodiment of Fig. 33 is as follows:

The output signal DCH of the horizontal chrominance non-correlation energy extractor 29 is branched in three routes. In the first route, the signal is multiplied by a coefficient b at the multiplier 72 and the resultant signal is sent to the maximum value circuit 33. In the second route, the signal is multiplied by a coefficient f_1 at the multiplier 74a, and the resultant signal is sent to the adder 82. In the third route, the signal is multiplied by a coefficient f_2 at the multiplier 74b, and the resultant signal is sent to the adder 83.

The output signal DYH of the circuit for the horizontal luminance non-correlation energy extractor 30 is branched in three routes. In the first route, the signal is multiplied by a coefficient a at the multiplier 71, and the resultant signal is sent to the maximum value circuit 33. In the second route, the signal is multiplied by a coefficient e_1 at the multiplier 73a, and the resultant signal is sent to



the adder 82. In the third route, the signal is multiplied by a coefficient e2 at the multiplier 73b, and the resultant signal is sent to the adder 83.

The output signal DCV of the vertical chrominance non-correlation energy extractor 31 is branched in two routes. In the first route, the signal is applied directly to the comparator 38. In the second route, the signal is multiplied by a coefficient d at the multiplier 78, and the resultant signal is sent to the adder 84.

The output signal DYV of the vertical luminance non-correlation energy extractor 32 is branched in two routes. In the first route, the signal is applied directly to the comparator 39. In the second route, the signal is multiplied by a coefficient c at the multiplier 77, and the resultant signal is sent to the adder 84.

The output signal of the maximum value circuit 33 is applied as a first horizontal non-correlation energy DH1 to the comparator 37. The output signal of the adder 82, as a second horizontal non-correlation energy DH21, is multiplied by a coefficient m1 at the multiplier 79a, and the product is sent to the comparator 38. The output signal of the adder 83, as a third horizontal non-correlation energy DH22, is multiplied by a coefficient m2 at the multiplier 79b, and the product is sent to the comparator 39.

The output signal of the maximum value circuit 36, as the vertical non-correlation energy DV, is multiplied by a coefficient n at the multiplier 80, and the product is sent to the comparator 37.

The comparator 37 compares the first horizontal non-correlation energy DH1 and the product $n \cdot DV$ of the vertical non-correlation energy DV and the coefficient n, and produces a high level output signal 116 when $DH1 \geq n \cdot DV$, and a low level output signal 116 at other times.

The comparator 38 compares the vertical chrominance



non-correlation energy DCV and the product $m1 \cdot DH21$ of the second horizontal non-correlation energy DH21 and the coefficient $m1$, and produces a high level output signal 117 when $DCV \geq m1 \cdot DH21$, and a low level output signal 117 at other times.

The comparator 39 compares the vertical luminance non-correlation energy DYV and the product $m2 \cdot DH22$ of the third horizontal non-correlation energy DH22 and the coefficient $m2$, and produces a high level output signal 118 when $DYV \geq m2 \cdot DH22$, and a low level output signal 117 at other times.

The respective output signals 116, 117 and 118 of the comparators 37, 38 and 39 are applied to the decision circuit 40. The output signal 110 of the decision circuit 40 serves as the output signal of the picture non-correlation decision circuit 18.

Following is a description of the operation of the picture non-correlation decision circuit 18 operation in accordance with this embodiment.

The first horizontal non-correlation energy DH1, the second horizontal non-correlation energy DH21, the third horizontal non-correlation energy DH22 and the vertical non-correlation energy DV can be expressed as follows.

$$DH1 = \max (a \cdot DYH, b \cdot DCH)$$

$$DH21 = e1 \cdot DYH + f1 \cdot DCH$$

$$DH22 = e2 \cdot DYH + f2 \cdot DCH$$

$$DV = c \cdot DYV + d \cdot DCV$$

At the comparator 37, DH1 and $n \cdot DV$ are compared. If

$$DH1 \geq n \cdot DV$$

the horizontal non-correlation is interpreted as strong, and a "1" signal 116 is sent to the decision circuit 40. If

$$DH1 < n \cdot DV$$

the horizontal non-correlation is interpreted as weak, and a



"0" signal 116 is sent to the decision circuit 40.

At the comparator 38, DCV and $m1 \cdot DH21$ are compared. If

$$DCV \geq m1 \cdot DH21$$

the vertical non-correlation is interpreted as strong, and a

"1" signal 117 is sent to the decision circuit 40. If

$$DCV < m1 \cdot DH21$$

the vertical non-correlation is interpreted as weak, and a

"0" signal 117 is sent to the decision circuit 40.

At the comparator 39, DYV and $m2 \cdot DH22$ are compared. If

$$DYV \geq m2 \cdot DH22$$

the vertical non-correlation is interpreted as strong, and a

"1" signal 118 is sent to the decision circuit 40. If

$$DYV < m2 \cdot DH22$$


the vertical non-correlation is interpreted as weak, and a

"0" signal 118 is sent to the decision circuit 40.

According to the results of the above correlation detection, the decision circuit 40 controls the selectors 23 and 25 in the following manner.

The relationship between the input signals 116, 117 and 118 of the decision circuit 40, and its output signal 110, the selection of the chrominance output signal 107, 109 or 111 at the selector 23 and the selection of the chrominance output signal 1131 or 1132 at the selector 25 is as shown in Table 2.

When the output signals 110a and 110b of the AND circuits 41 and 42 are both "0", the selector 23 selects the output signal 109 of the compensating delay circuit 21. When the output signal 110a of the AND circuit 41 is "0" and the output signal 110b of the AND circuit 42 is "1", the output signal 107 of the compensating delay circuit 20 is selected. When the output signal 110a of the AND circuit 41 is "1" and the output signal 110b of the AND circuit 42 is "0", the output signal 111 of the compensating delay circuit 22 is selected.



When the output signal 110b of the AND circuit 42 is "1", the selector 25 selects the output signal 1131 of the compensating delay circuit 91. At other times, the selector 25 selects the output signal 1132 of the horizontal chrominance extraction filter 24.

Consequently, in this embodiment, the response $C11(Z)$ of the filter for extracting the chrominance signal output through the terminal 26, and the response $C12(Z)$ of the filter for extracting the chrominance signal used for extracting the luminance signal are given below:

When the vertical non-correlation is strong,

$$C11(Z) = Ch1(Z)$$

$$C12(Z) = Ch1(Z) \cdot Ch2(Z)$$

When the horizontal non-correlation is strong,

$$C11(Z) = C12(Z) = Cv(Z)$$

When neither of these conditions are met,

$$C11(Z) = Chv(Z)$$

$$C12(Z) = Chv(Z) \cdot CH2(Z)$$


Embodiment 50

This embodiment is similar to Embodiment 41, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 33 is used.

The operation of this picture non-correlation decision circuit 18 is the same as Embodiment 49

The relationship between the input signals 116, 117 and 118 of the decision circuit 40, and its output signal 110, the selection of the chrominance output signal 107, 109 or 111 at the selector 23 and the selection of the chrominance output signal 1131 or 1132 at the selector 25a is as shown in Table 3.

When the output signals 110a and 110b of the AND



circuits 41 and 42 are both "0", the selector 23 selects the output signal 109 of the compensating delay circuit 21. When the output signal 110a of the AND circuit 41 is "0" and the output signal 110b of the AND circuit 42 is "1", the output signal 107 of the compensating delay circuit 20. When the output signal 110a of the AND circuit 41 is "1" and the output signal 110b of the AND circuit 42 is "0", the output signal 111 of the compensating delay circuit 22 is selected.

When the output signal 110b of the AND circuit 42 is "1", the selector 25a selects the output signal 1131 of the compensating delay circuit 91a. At other times, the selector 25a selects the output signal 1132 of the horizontal chrominance extraction filter 24a.

Consequently, in this embodiment, the response $C21(Z)$ of the filter for extracting the chrominance signal output through the terminal 26, and the response $C22(Z)$ of the filter for extracting the chrominance signal used for extracting the luminance signal are given below:

When the vertical non-correlation is strong,

$$C21(Z) = Ch1(Z) \cdot Ch2(Z)$$

$$C22(Z) = Ch1(Z)$$

When the horizontal non-correlation is strong,

$$C21(Z) = C22(Z) = Cv(Z)$$

When neither of these conditions are met,

$$C21(Z) = Chv(Z) \cdot CH2(Z)$$

$$C22(Z) = Chv(Z)$$

Embodiment 51

This embodiment is similar to Embodiment 1, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 34 is used.



The picture non-correlation decision circuit 18 of this embodiment is similar to that of Fig. 33, but is modified in the same way as in Fig. 10. That is, it is provided with the horizontal chrominance non-correlation energy extractor 129 comprising the first and second horizontal chrominance non-correlation energy extractors 29a and 29b, and the vertical chrominance non-correlation energy extractor 131 comprising the first and second vertical chrominance non-correlation energy extractors 31a and 31b. The control over the selection by the selectors 23 and 25 according to the output signal 110 of the decision circuit 40 is as shown in Table 2.

Embodiment 52


This embodiment is similar to Embodiment 41, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 34 is used.

The operation of this picture non-correlation decision circuit 18 is the same as Embodiment 51, and the control over the selectors 23 and 25a in accordance with the output signal 110 of the decision circuit 40 is as shown in Table 3.

Embodiment 53

This embodiment is similar to Embodiment 1, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 35 is used.

The picture non-correlation decision circuit 18 of this embodiment is similar to that of Fig. 33, but is modified in the same way as in Fig. 11. That is, the delay circuits 86 - 89 and the AND circuit 90 are provided between the comparators 37 - 39 and the decision circuit 40.



The decision circuit 40 controls the selectors 23 and 25 on the basis of the input signals 119, 120 and 123 according to the results of the correlation detection described in the embodiment of Fig. 33. The control over the selectors 23 and 25 in accordance with the output signals 110a and 110b of the decision circuit 40 is as shown in Table 2.

Embodiment 54


This embodiment is similar to Embodiment 41, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 35 is used.

The operation of this picture non-correlation decision circuit 18 is the same as Embodiment 53 and the control over the selectors 23 and 25a in accordance with the output signal 110 of the decision circuit 40 is as shown in Table 3.

Embodiment 55

This embodiment is similar to Embodiment 1, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 36 is used.

The picture non-correlation decision circuit 18 of this embodiment is similar to that of Fig. 35, but is modified in the same way as in Fig. 10. That is, it is provided with the horizontal chrominance non-correlation energy extractor 129 comprising the first and second horizontal chrominance non-correlation energy extractors 29a and 29b, and the vertical chrominance non-correlation energy extractor 131 comprising the first and second vertical chrominance non-correlation energy extractors 31a and 31b. The control over the selection by the selectors 23 and 25 according to the



output signal 110 of the decision circuit 40 is as shown in Table 2.

Embodiment 56

This embodiment is similar to Embodiment 41, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 36 is used.

The operation of this picture non-correlation decision circuit 18 is the same as Embodiment 55, and the control over the selectors 23 and 25a in accordance with the output signal 110 of the decision circuit 40 is as shown in Table 3.

Embodiment 57

This embodiment is similar to Embodiment 1, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 37 is used.

The picture non-correlation decision circuit 18 of this embodiment is similar to that of Fig. 29, but the maximum value circuit 33 is replaced by an adder 81, and the interconnection is as follows:

The output signal DCH of the horizontal chrominance non-correlation energy extractor 29 is branched in two routes. In the first route, the signal is applied directly to the comparator 38. In the second route, the signal is multiplied by a coefficient f at the multiplier 72, and the resultant signal is sent to the adder 81.

The output signal DYH of the horizontal luminance non-correlation energy extractor 30 is branched in two routes. In the first route, the signal is applied directly to the comparator 39. In the second route, the signal is multiplied by a coefficient e at the multiplier 71, and the



resultant signal is sent to the adder 81.

The output signal DCV of the vertical chrominance non-correlation energy extractor 31 is branched in three routes. In the first route, the signal is multiplied by a coefficient h at the multiplier 76, and the resultant signal is sent to the adder 82. In the second route, the signal is multiplied by a coefficient $d1$ at the multiplier 78a, and the resultant signal is sent to the adder 83. In the third route, the signal is multiplied by a coefficient $d2$ at the multiplier 78b, and the resultant signal is sent to the maximum value circuit 36.

The output signal DYV of the vertical luminance non-correlation energy extractor 32 is branched in three routes. In the first route, the signal is multiplied by a coefficient g at the multiplier 75, and the resultant signal is sent to the adder 82. In the second route, the signal is multiplied by a coefficient $c1$ at the multiplier 77a, and the resultant signal is sent to the adder 83. In the third route, the signal is multiplied by a coefficient $c2$ at the multiplier 77b, and the resultant signal is sent to the maximum value circuit 36.

The output signal of the adder 81, as the horizontal non-correlation energy DH1, is multiplied by a coefficient m at the multiplier 79, and the product is applied to the comparator 37. The output signal of the adder 82 is applied as a first vertical non-correlation energy DV1 to the comparator 37. The output signal of the adder 83, as a second vertical non-correlation energy DV21, is multiplied by a coefficient $n1$ at the multiplier 80a, and the product is applied to the comparator 38. The output signal of the maximum value circuit 36, as a third vertical non-correlation energy DV22, is multiplied by a coefficient $n2$ at the multiplier 80b, and the product is applied to the comparator 39.



The comparator 37 compares the first vertical non-correlation energy DV1 and the product $m \cdot DH$ of the horizontal non-correlation energy DH and the coefficient m , and produces a high level output signal 116 when $DV1 \geq m \cdot DH$, and a low level output signal 116 at other times.

The comparator 38 compares the horizontal chrominance non-correlation energy DCH and the product $n1 \cdot DV21$ of the second vertical non-correlation energy DV21 and the coefficient $n1$, and produces a high level output signal 117 when $DCH \geq n1 \cdot DV21$, and a low level output signal 117 at other times.

The comparator 39 compares the horizontal luminance non-correlation energy DYH and the product $n2 \cdot DV22$ of the third vertical non-correlation energy DV22 and the coefficient $n2$, and produces a high level output signal 118 when $DYH \geq n2 \cdot DV22$, and a low level output signal 117 at other times.

The respective output signals 116, 117 and 118 of the comparators 37, 38 and 39 are applied to the decision circuit 40. The output signal 110 of the decision circuit 40 serves as the output signal of the picture non-correlation decision circuit 18.

Following is a description of the operation of the picture non-correlation decision circuit 18 in accordance with this embodiment.


The first vertical non-correlation energy DV1, the second vertical non-correlation energy DV21, the third vertical non-correlation energy DV22 and the horizontal non-correlation energy DH can be expressed as follows.

$$DH = e \cdot DYH + f \cdot DCH$$

$$DV1 = g \cdot DYV + h \cdot DCV$$

$$DV21 = c1 \cdot DYV + d1 \cdot DCV$$

$$DV22 = \max (c2 \cdot DYV, d2 \cdot DCV)$$



At the comparator 37, $DV1$ and $m \cdot DH$ are compared. If
 $DV1 \geq m \cdot DH$
the vertical non-correlation is interpreted as strong, and a
"1" signal 116 is sent to the decision circuit 40. If

$DV1 < m \cdot DH$
the vertical non-correlation is interpreted as weak, and a
"0" signal 116 is sent to the decision circuit 40.

At the comparator 38, DCH and $n1 \cdot DV21$ are compared. If
 $DCH \geq n1 \cdot DV21$
the horizontal non-correlation is interpreted as strong, as
indicated below, a "1" signal 117 is sent to the decision
circuit 40. If

$DCH < n1 \cdot DV21$
the horizontal non-correlation is interpreted as weak, as
indicated below, a "0" signal 117 is sent to the decision
circuit 40.

At the comparator 39, DYH and $n2 \cdot DV22$ are compared. If
 $DYH \geq n2 \cdot DV22$
the horizontal non-correlation is interpreted as strong, as
indicated below, a "1" signal 118 is sent to the decision
circuit 40. If

$DYH < n2 \cdot DV22$
the horizontal non-correlation is interpreted as weak, as
indicated below, a "0" signal 118 is sent to the decision
circuit 40.

According to results of the above correlation
detection, the decision circuit 40 controls the selectors 23
and 25 in the following manner.

The relationship between the input signals 116, 117 and
118 of the decision circuit 40, and its output signal 110,
the selection of the chrominance output signal 107, 109 or
111 at the selector 23 and the selection of the chrominance
output signal 1131 or 1132 at the selector 25 is as shown in




Table 3.

When the output signals 110a and 110b of the AND circuits 41 and 42 are both "0", the selector 23 selects the output signal 107 of the compensating delay circuit 20. When the output signal 110a of the AND circuit 41 is "0" and the output signal 110b of the AND circuit 42 is "1", the output signal 109 of the compensating delay circuit 21 is selected. When the output signal 110a of the AND circuit 41 is "1" and the output signal 110b of the AND circuit 42 is "0", the output signal 111 of the delay circuit 22 is selected.

When the output signals 110a and 110b of the AND circuits 41 and 42 are both "1", the selector 25 selects the output signal 1131 of the compensating delay circuit 91. At other times, the selector 25 selects the output signal 1132 of the horizontal chrominance extraction filter 24.

Consequently, in this embodiment, the response $C11(Z)$ of the filter for extracting the chrominance signal output through the terminal 26, and the response $C12(Z)$ of the filter for extracting the chrominance signal used for extracting the luminance signal are given below:

When the vertical non-correlation is strong,

$$C11(Z) = Ch1(Z)$$

$$C12(Z) = Ch1(Z) \cdot Ch2(Z)$$

When the horizontal non-correlation is strong,

$$C11(Z) = C22(Z) = Cv(Z)$$

When neither of these conditions are met,

$$C11(Z) = Chv(Z)$$

$$C12(Z) = Chv(Z) \cdot CH2(Z)$$

Embodiment 58

This embodiment is similar to Embodiment 41, but in place of the picture non-correlation decision circuit 18 of



Fig. 9, the picture non-correlation decision circuit shown in Fig. 37 is used.

The operation of this picture non-correlation decision circuit 18 is the same as Embodiment 57.

The relationship between the input signals 116, 117 and 118 of the decision circuit 40, and its output signal 110, the selection of the chrominance output signal 107, 109 or 111 at the selector 23 and the selection of the chrominance output signal 1131 or 1132 at the selector 25a is as shown in Table 3.


Embodiment 59

This embodiment is similar to Embodiment 1, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 38 is used.

The picture non-correlation decision circuit 18 of this embodiment is similar to that of Fig. 37, but is modified in the same way as in Fig. 10. That is, it is provided with the horizontal chrominance non-correlation energy extractor 129 comprising the first and second horizontal chrominance non-correlation energy extractors 29a and 29b, and the vertical chrominance non-correlation energy extractor 131 comprising the first and second vertical chrominance non-correlation energy extractors 31a and 31b. The control over the selection by the selectors 23 and 25a according to the output signal 110 of the decision circuit 40 is as shown in Table 3.

Embodiment 60

This embodiment is similar to Embodiment 41, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 38 is used.



The picture non-correlation decision circuit 18 of this embodiment is the same as Embodiment 59, and the control over the selectors 23 and 25a in accordance with the output signal 110 of the decision circuit 40 is as shown in Table 3.

Embodiment 61

This embodiment is similar to Embodiment 1, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 39 is used.

The picture non-correlation decision circuit 18 of this embodiment is similar to that of Fig. 37, but is modified in the same way as in Fig. 11. That is, the delay circuits 86 - 89 and the AND circuit 90 are provided between the comparators 37 - 39 and the decision circuit 40.

The operation of these added circuits is the same as the corresponding circuits in Fig. 11. The decision circuit 40 controls the selectors 23 and 25 on the basis of the input signals 119, 120 and 123 according to the results of the correlation detection described in the embodiment of Fig. 37. The control over the selectors 23 and 25 in accordance with the output signal 110 of the decision circuit 40 is as shown in Table 3.

Embodiment 62

This embodiment is similar to Embodiment 41, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 39 is used.

The operation of this picture non-correlation decision circuit 18 is the same as Embodiment 61, and the control over the selectors 23 and 25a in accordance with the output signal 110 of the decision circuit 40 is as shown in Table



3.

Embodiment 63

This embodiment is similar to Embodiment 1, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 40 is used.

The picture non-correlation decision circuit 18 of this embodiment similar to that of Fig. 39, but is modified in the same way as in Fig. 10. That is, it is provided with the horizontal chrominance non-correlation energy extractor 129 comprising the first and second horizontal chrominance non-correlation energy extractors 29a and 29b, and the vertical chrominance non-correlation energy extractor 131 comprising the first and second vertical chrominance non-correlation energy extractors 31a and 31b. The control over the selection by the selectors 23 and 25 according to the output signal 110 of the decision circuit 40 is as shown in Table 3.

Embodiment 64

This embodiment is similar to Embodiment 41, but in place of the picture non-correlation decision circuit 18 of Fig. 9, the picture non-correlation decision circuit shown in Fig. 40 is used.

The operation of this picture non-correlation decision circuit 18 is the same as Embodiment 63, and the control over the selectors 23 and 25a in accordance with the output signal 110 of the decision circuit 40 is as shown in Table 3.

Modifications

In the above embodiments, the composite color television signal was sampled at a frequency 4 times the




color subcarrier frequency synchronized to the horizontal scanning frequency. However, sampling may be other than 4 times the color subcarrier frequency, if it is so arranged that the sampling points are arranged in a grid pattern on the screen.

The digital filters used in the above embodiments are examples and it is also acceptable, for example, to construct filters with higher orders. In addition, in the above embodiments, the digital filters are FIR filters, but IIR filters can also be used.

Although an NTSC system YC separating filter was described in the above embodiments, by replacing the 1-line delay circuits 13 and 14 of Fig. 1 or Fig. 2 with two 2-line delay circuits 13a and 14a such as indicated in Fig. 41 or Fig. 42, this invention can be applied to a PAL system YC separating filter.

It will be appreciated that the above description refers merely to preferred forms of the invention, and that modifications may be made within the scope and/or principles of the invention. Aspects of the invention are defined in the claims of this application, but it will be appreciated that other features of the invention described herein may be advantageous independently of the presently claimed aspects.



CLAIMS:

1. A luminance/chrominance separating filter for separating a composite color television signal into a luminance signal and a chrominance signal, said separating filter comprising:

means (12, 13, 14, 13a, 14a) for producing sample values of a specific sampling point and a plurality of reference sampling points of the composite color television signal, said reference sampling points being situated in the neighborhood of the specific sampling point when the sampling points are arranged on a two-dimensional plane corresponding to a display screen;

a first horizontal chrominance extraction filter (16) for extracting, from said sample value of said specific and reference sampling points, frequency components corresponding to components of a color subcarrier in a horizontal direction to produce a first chrominance signal (107);

a vertical chrominance extraction filter (15) for extracting, from said sample values of said specific and reference sampling points, frequency components corresponding to components of a color subcarrier in a vertical direction to produce a second chrominance signal (108);

a horizontal and vertical chrominance extraction filter (17) for extracting, from said sample values of said specific and reference sampling points, frequency components corresponding to components of a color subcarrier in horizontal and vertical directions to produce a third chrominance signal (110); and

a first selector (23) for selecting one of said first, second and third chrominance signals;

CHARACTERIZED BY FURTHER COMPRISING:





a second horizontal chrominance extraction filter (24, 24a) receiving said selected chrominance signal and having a narrower bandwidth than said first horizontal chrominance extraction filter (16); and

a second selector (25, 25a) receiving the output of said second horizontal chrominance extraction filter (24, 24a) and the output of said first selector (23), and selecting said output of said second horizontal chrominance extraction filter (24, 24a) when said first selector selects either said first or third chrominance signal, and selecting said output of said first selector (23) when said first selector selects said second chrominance signal.

2. A luminance/chrominance separating filter according to claim 1, further comprising:

a picture non-correlation decision circuit (18) responsive to the sample values of said specific and reference sampling points for detecting non-correlation in the horizontal direction and non-correlation in the vertical direction of said sample values and outputting a chrominance signal selection signal;

wherein


said first selector (23) selects said one of the first to third chrominance signals on the basis of said chrominance signal selection signal; and

said picture non-correlation decision circuit (18) comprises:

a horizontal chrominance non-correlation energy extractor (29, 129) responsive to the sample values of said specific and reference sampling points for extracting horizontal chrominance non-correlation energy (DCH) consisting primarily of the chrominance signal extending in the horizontal direction;

a horizontal luminance non-correlation energy extractor





(30) responsive to the sample values of said specific and reference sampling points for extracting horizontal luminance non-correlation energy (DYH) consisting primarily of the luminance signal extending in the horizontal direction;

a vertical chrominance non-correlation energy extractor (31, 131) responsive to the sample values of said reference sampling points for detecting vertical chrominance non-correlation energy (DCV) consisting primarily of the chrominance signal extending in the vertical direction;

a vertical luminance non-correlation energy extractor (32) responsive to the sample values of said specific and reference sampling points for detecting vertical luminance non-correlation energy (DYV) of consisting primarily of the luminance signal extending in the vertical direction; and

judging means responsive to the outputs of said horizontal chrominance non-correlation energy extractor (29, 129), said horizontal luminance non-correlation energy extractor (30), said vertical chrominance non-correlation energy extractor (31, 131) and said vertical luminance non-correlation energy extractor (32) for determining which of the horizontal and vertical non-correlations is stronger, causing said first chrominance signal selecting means (23) to select said first chrominance signal when the vertical non-correlation is strong, to select said second chrominance signal when the horizontal non-correlation is strong, and to select said third chrominance signal when neither of above conditions is met, and causing said second chrominance signal selector (25, 25a) to select the output of said second horizontal chrominance extraction filter (24, 24a) when said first selector selects either said first or third chrominance signal.

3. A luminance/chrominance separating filter according to





claim 2, wherein the output of said second selector (25) is used for calculation with the composite color television signal to produce an output luminance signal.

4. A luminance/chrominance separating filter according to claim 3, further comprising a subtractor (27) for subtracting the output of said second selector (25) from said composite video signal to produce said output luminance signal.

5. A luminance/chrominance separating filter according to claim 2, wherein the output of said second selector (25a) is used as an output chrominance signal.


6. A luminance/chrominance separating filter according to claim 5, further comprising a subtractor (27) for subtracting the output of said first selector (23) from the composite video signal to produce an output luminance signal.

7. A luminance/chrominance separating filter according to claim 3 or 5, wherein said judging means comprises:

a first maximum value circuit (33) for receiving the horizontal chrominance non-correlation energy (DCH) multiplied by a predetermined coefficient (b) and the horizontal luminance non-correlation energy (DYH) multiplied by a predetermined coefficient (a), and producing, as an output thereof, the larger one of them;

a second maximum value circuit (34) for receiving the horizontal chrominance non-correlation energy (DCH) multiplied by a predetermined coefficient (f1) and the horizontal luminance non-correlation energy (DYH) multiplied by a predetermined coefficient (e1), and producing, an output thereof, the larger one of them;





a third maximum value circuit (35) for receiving the horizontal chrominance non-correlation energy (DCH) multiplied by a predetermined coefficient (f2) and the horizontal luminance non-correlation energy (DYH) multiplied by a predetermined coefficient (e2), and producing, as an output thereof, the larger one of them;

a fourth maximum value circuit (36) for receiving the vertical chrominance non-correlation energy (DCV) multiplied by a predetermined coefficient (d) and the vertical luminance non-correlation energy (DYV) multiplied by a predetermined coefficient (c), and producing, as an output thereof, the larger one of them;

a first comparator (37) for comparing the output (DH1) of said first maximum value circuit (33) and the output (DV) of said fourth maximum value circuit (36) multiplied by a predetermined coefficient (n), and producing an output signal which indicates that the horizontal non-correlation is strong when the former is larger, and which indicates that the horizontal non-correlation is weak when the latter is larger;

a second comparator (38) for comparing the vertical chrominance non-correlation energy (DCV) with the output (DH21) of the second maximum value circuit (34) multiplied by a predetermined coefficient (m1), and producing an output signal which indicates that the vertical non-correlation is strong when the former is larger, and which indicates that the vertical non-correlation is weak when the latter is larger;

a third comparator (39) for comparing the vertical luminance non-correlation energy (DYV) with the output (DH22) of the third maximum value circuit (35) multiplied by a predetermined coefficient (m2), and producing an output signal which indicates that the vertical non-correlation is strong when the former is larger, and which indicates that





the vertical non-correlation is weak when the latter is larger; and

a decision circuit (40) receiving the output signals of the first to third comparators, determining strength of horizontal non-correlation and vertical non-correlation, causing said first chrominance signal selecting means to select said first chrominance signal when the vertical non-correlation is strong, the second chrominance signal when the horizontal non-correlation is strong, and the third chrominance signal when neither of these conditions are met, and causing said second chrominance signal selecting means (25) to select the output of said second horizontal chrominance extraction filter (24), when said first selector selects either said first or third chrominance signal.

8. A luminance/chrominance separating filter according to claim 7, wherein

said horizontal chrominance non-correlation energy extractor (129) comprises:

a first horizontal chrominance non-correlation energy extractor (29a) responsive to the sample values of said specific and reference sampling points for detecting first horizontal chrominance non-correlation energy (DCH1) consisting primarily of the chrominance signal in the horizontal direction; and

a second horizontal chrominance non-correlation energy extractor (29b) responsive to the sample values of said specific and reference sampling points for detecting second horizontal chrominance non-correlation energy (DCH2) consisting primarily of the chrominance signal in the horizontal direction;

said vertical chrominance non-correlation energy extractor (131) comprises:

a first vertical chrominance non-correlation energy





extractor (31a) responsive to the sample values of said reference sampling points for detecting first vertical chrominance non-correlation energy (DCV1) consisting primarily of the chrominance signal in the vertical direction; and

a second vertical chrominance non-correlation energy extractor (31b) responsive to the sample values of said reference sampling points for detecting second vertical chrominance non-correlation energy (DCV2) consisting primarily of the chrominance signal in the vertical direction;

said first maximum value circuit is coupled to receive said second horizontal chrominance non-correlation energy multiplied by a predetermined coefficient and the horizontal luminance non-correlation energy multiplied by a predetermined coefficient, and produces, as an output thereof, the larger one of them;

said second maximum value circuit is coupled to receive said first horizontal chrominance non-correlation energy multiplied by a predetermined coefficient and the horizontal luminance non-correlation energy multiplied by a predetermined coefficient, and produces, as an output thereof, the larger one of them;

said third maximum value circuit is coupled to receive said first horizontal chrominance non-correlation energy multiplied by a predetermined coefficient and the horizontal luminance non-correlation energy multiplied by a predetermined coefficient, and produces, as an output thereof, the larger one of them;

said fourth maximum value circuit is coupled to receive said second vertical chrominance non-correlation energy multiplied by a predetermined coefficient and the vertical luminance non-correlation energy multiplied by a predetermined coefficient, and produces, as an output





thereof, the larger one of them; and

said second comparator (38) is coupled to receive said first vertical chrominance non-correlation energy and the output signal of the second maximum value circuit multiplied by a predetermined coefficient, and produces an output signal which indicates that the vertical non-correlation is strong when the former is larger, and which indicates that the vertical non-correlation is weak when the latter is larger.


9. A luminance/chrominance separating filter according to claim 3 or 5, wherein said judging means comprises:

a first maximum value circuit (33) for receiving the horizontal chrominance non-correlation energy multiplied by a predetermined coefficient and the horizontal luminance non-correlation energy multiplied by a predetermined coefficient, and producing, as an output thereof, the larger one of them;

a second maximum value circuit (34) for receiving the vertical chrominance non-correlation energy multiplied by a predetermined coefficient and the vertical luminance non-correlation energy multiplied by a predetermined coefficient, and producing, as an output thereof, the larger one of them;

a third maximum value circuit (35) for receiving the vertical chrominance non-correlation energy multiplied by a predetermined coefficient and the vertical luminance non-correlation energy multiplied by a predetermined coefficient, and producing, as an output thereof, the larger one of them;

a fourth maximum value circuit (35) for receiving the vertical chrominance non-correlation energy multiplied by a predetermined coefficient and the vertical luminance non-correlation energy multiplied by a predetermined





coefficient, and producing, as an output thereof, the larger one of them;

a first comparator (37) for comparing the output signal of said second maximum value circuit with the output signal of said first maximum value circuit multiplied by a predetermined coefficient, and producing an output signal which indicates that the vertical non-correlation is strong when the former is larger, and which indicates that the vertical non-correlation is weak when the latter is larger;

a second comparator (38) for comparing the horizontal direction chrominance signal non-correlation energy with the output signal of the third maximum value circuit multiplied by a predetermined coefficient, and producing an output signal which indicates that the horizontal non-correlation is strong when the former is larger, and which indicates that the horizontal non-correlation is weak when the latter is larger;

a third comparator (39) for comparing the horizontal luminance non-correlation energy with the output signal of the fourth maximum value circuit multiplied by a predetermined coefficient, and producing an output signal which indicates that the horizontal non-correlation is strong when the former is larger, and which indicates that the horizontal non-correlation is weak when the latter is larger; and

a decision circuit (40) receiving the output signals of the three comparators, determining strength of horizontal non-correlation and vertical non-correlation, causing said first chrominance signal selecting means to output said first chrominance signal when the vertical non-correlation is strong, the second chrominance signal when the horizontal non-correlation is strong, and the third chrominance signal when neither of these conditions are met, and causing said second chrominance signal selecting means (25) to select the





output of said second horizontal chrominance extraction filter (24), when said first selector selects either said first or third chrominance signal.

10. A luminance/chrominance separating filter according to claim 9, wherein

said horizontal chrominance non-correlation energy extractor (129) comprises:

a first horizontal chrominance non-correlation energy extractor (29a) responsive to the sample values of said specific and reference sampling points for detecting first horizontal chrominance non-correlation energy (DCH1) consisting primarily of the chrominance signal in the horizontal direction; and

a second horizontal chrominance non-correlation energy extractor (29b) responsive to the sample values of said specific and reference sampling points for detecting second horizontal chrominance non-correlation energy (DCH2) consisting primarily of the chrominance signal in the horizontal direction;

said vertical chrominance non-correlation energy extractor (131) comprises:

a first vertical chrominance non-correlation energy extractor (31a) responsive to the sample values of said reference sampling points for detecting first vertical chrominance non-correlation energy (DCV1) consisting primarily of the chrominance signal in the vertical direction; and

a second vertical chrominance non-correlation energy extractor (31b) responsive to the sample values of said reference sampling points for detecting second vertical chrominance non-correlation energy (DCV2) consisting primarily of the chrominance signal in the vertical direction;





said first maximum value circuit is coupled to receive the first horizontal chrominance non-correlation energy multiplied by a predetermined coefficient and the horizontal luminance non-correlation energy multiplied by a predetermined coefficient, and produces, as an output thereof, the larger one of them;

said second maximum value circuit is coupled to receive the first vertical chrominance non-correlation energy multiplied by a predetermined coefficient and the vertical luminance non-correlation energy multiplied by a predetermined coefficient, and produces, as an output thereof, the larger one of them;

said third maximum value circuit is coupled to receive the second vertical chrominance non-correlation energy multiplied by a predetermined coefficient and the vertical luminance non-correlation energy multiplied by a predetermined coefficient, and produces, as an output thereof, the larger one of them;

said fourth maximum value circuit is coupled to receive the second vertical chrominance non-correlation energy multiplied by a predetermined coefficient and the vertical luminance non-correlation energy multiplied by a predetermined coefficient, and produces, as an output thereof, the larger one of them;

said first comparator is coupled to receive the output signal of said second maximum value circuit and the output signal of said first maximum value circuit multiplied by a predetermined coefficient, and produces an output signal which indicates that the vertical non-correlation is strong when the former is larger, and which indicates that the vertical non-correlation is weak when the latter is larger;

said second comparator is coupled to receive the second horizontal direction chrominance signal non-correlation energy and the output signal of the third maximum value





circuit multiplied by a predetermined coefficient, and produces an output signal which indicates that the horizontal non-correlation is strong when the former is larger, and which indicates that the horizontal non-correlation is weak when the latter is larger;

said third comparator is coupled to receive the horizontal luminance non-correlation energy and the output signal of the fourth maximum value circuit multiplied by a predetermined coefficient, and produces an output signal which indicates that the horizontal non-correlation is strong when the former is larger, and which indicates that the horizontal non-correlation is weak when the latter is larger.

11. A luminance/chrominance separating filter according to claim 3 or 5, wherein said judging means comprises:

a first maximum value circuit (33) for receiving the horizontal chrominance non-correlation energy multiplied by a predetermined coefficient and the horizontal luminance non-correlation energy multiplied by a predetermined coefficient, and producing, as an output thereof, the larger one of them;

a second maximum value circuit (34) for receiving the horizontal chrominance non-correlation energy multiplied by a predetermined coefficient and the horizontal luminance non-correlation energy multiplied by a predetermined coefficient, and producing, as an output thereof, the larger one of them;

a third maximum value circuit (35) for receiving the horizontal chrominance non-correlation energy multiplied by a predetermined coefficient and the horizontal luminance non-correlation energy multiplied by a predetermined coefficient, and producing, as an output thereof, the larger one of them;





an adder (84) for adding the vertical chrominance non-correlation energy multiplied by a predetermined coefficient to the vertical luminance non-correlation energy multiplied by a predetermined coefficient, and producing, as an output thereof, the sum of them;

a first comparator (37) for comparing the output signal of said first maximum value circuit with the output signal of said adder multiplied by a predetermined coefficient, and producing an output signal which indicates that the horizontal non-correlation is strong when the former is larger, and which indicates that the horizontal non-correlation is weak when the latter is larger;

a second comparator (38) for comparing the vertical chrominance non-correlation energy with the output signal of the second maximum value circuit multiplied by a predetermined coefficient, and producing an output signal which indicates that the vertical non-correlation is strong when the former is larger, and which indicates that the vertical non-correlation is weak when the latter is larger;

a third comparator (39) for comparing the vertical luminance non-correlation energy with the output signal of the third maximum value circuit multiplied by a predetermined coefficient, and producing an output signal which indicates that the vertical non-correlation is strong when the former is larger, and which indicates that the vertical non-correlation is weak when the latter is larger; and

a decision circuit (40) receiving the output signals of the three comparators, determining strength of horizontal non-correlation and vertical non-correlation, causing said first chrominance signal selecting means to output said first chrominance signal when the vertical non-correlation is strong, the second chrominance signal when the horizontal non-correlation is strong, and the third chrominance signal





when neither of these conditions are met, and causing said second chrominance signal selecting means (25) to select the output of said second horizontal chrominance extraction filter (24), when said first selector selects either said first or third chrominance signal.

12. A luminance/chrominance separating filter according to claim 11, wherein

said horizontal chrominance non-correlation energy extractor (129) comprises:

a first horizontal chrominance non-correlation energy extractor (29a) responsive to the sample values of said specific and reference sampling points for detecting first horizontal chrominance non-correlation energy (DCH1) consisting primarily of the chrominance signal in the horizontal direction; and


a second horizontal chrominance non-correlation energy extractor (29b) responsive to the sample values of said specific and reference sampling points for detecting second horizontal chrominance non-correlation energy (DCH2) consisting primarily of the chrominance signal in the horizontal direction;

said vertical chrominance non-correlation energy extractor (131) comprises:

a first vertical chrominance non-correlation energy extractor (31a) responsive to the sample values of said reference sampling points for detecting first vertical chrominance non-correlation energy (DCV1) consisting primarily of the chrominance signal in the vertical direction; and

a second vertical chrominance non-correlation energy extractor (31b) responsive to the sample values of said reference sampling points for detecting second vertical chrominance non-correlation energy (DCV2) consisting





primarily of the chrominance signal in the vertical direction;

said first maximum value circuit is coupled to receive the first horizontal chrominance non-correlation energy multiplied by a predetermined coefficient and the horizontal luminance non-correlation energy multiplied by a predetermined coefficient, and produces, as an output thereof, the larger one of them;

said second maximum value circuit is coupled to receive the second horizontal chrominance non-correlation energy multiplied by a predetermined coefficient and the horizontal luminance non-correlation energy multiplied by a predetermined coefficient, and produces, as an output thereof, the larger one of them;

said third maximum value circuit is coupled to receive the second horizontal chrominance non-correlation energy multiplied by a predetermined coefficient and the horizontal luminance non-correlation energy multiplied by a predetermined coefficient, and produces, as an output thereof, the larger one of them;

said adder is coupled to add the second vertical chrominance non-correlation energy multiplied by a predetermined coefficient to the vertical luminance non-correlation energy multiplied by a predetermined coefficient; and

said second comparator (38) for comparing the first vertical chrominance non-correlation energy with the output signal of the second maximum value circuit multiplied by a predetermined coefficient, and producing an output signal which indicates that the vertical non-correlation is strong when the former is larger, and which indicates that the vertical non-correlation is weak when the latter is larger.

13. A luminance/chrominance separating filter according to





claim 3 or 5, wherein said judging means comprises:

an adder (81) for adding the horizontal chrominance non-correlation energy multiplied by a predetermined coefficient to the horizontal luminance non-correlation energy multiplied by a predetermined coefficient, and producing, as an output thereof, the sum of them;

a first maximum value circuit (34) for receiving the vertical chrominance non-correlation energy multiplied by a predetermined coefficient and the vertical luminance non-correlation energy multiplied by a predetermined coefficient, and producing, as an output thereof, the larger one of them;

a second maximum value circuit (35) for receiving the vertical chrominance non-correlation energy multiplied by a predetermined coefficient and the vertical luminance non-correlation energy multiplied by a predetermined coefficient, and producing, as an output thereof, the larger one of them;

a third maximum value circuit (36) for receiving the vertical chrominance non-correlation energy multiplied by a predetermined coefficient and the vertical luminance non-correlation energy multiplied by a predetermined coefficient, and producing, as an output thereof, the larger one of them;

a first comparator (37) for comparing the output signal of said first maximum value circuit with the output signal of said adder multiplied by a predetermined coefficient, and producing an output signal which indicates that the vertical non-correlation is strong when the former is larger, and which indicates that the vertical non-correlation is weak when the latter is larger;

a second comparator (38) for comparing the horizontal direction chrominance signal non-correlation energy with the output signal of the second maximum value circuit multiplied





by a predetermined coefficient, and producing an output signal which indicates that the horizontal non-correlation is strong when the former is larger, and which indicates that the horizontal non-correlation is weak when the latter is larger;

a third comparator (39) for comparing the horizontal luminance non-correlation energy with the output signal of the third maximum value circuit multiplied by a predetermined coefficient, and producing an output signal which indicates that the horizontal non-correlation is strong when the former is larger, and which indicates that the horizontal non-correlation is weak when the latter is larger; and

a decision circuit (40) receiving the output signals of the three comparators, determining strength of horizontal non-correlation and vertical non-correlation, causing said first chrominance signal selecting means to output said first chrominance signal when the vertical non-correlation is strong, the second chrominance signal when the horizontal non-correlation is strong, and the third chrominance signal when neither of these conditions are met, and causing said second chrominance signal selecting means (25) to select the output of said second horizontal chrominance extraction filter (24), when said first selector selects either said first or third chrominance signal.

14. A luminance/chrominance separating filter according to claim 13, wherein

said horizontal chrominance non-correlation energy extractor (129) comprises:

a first horizontal chrominance non-correlation energy extractor (29a) responsive to the sample values of said specific and reference sampling points for detecting first horizontal chrominance non-correlation energy (DCH1)





1 181811 141811 141811 141811

consisting primarily of the chrominance signal in the horizontal direction; and

a second horizontal chrominance non-correlation energy extractor (29b) responsive to the sample values of said specific and reference sampling points for detecting second horizontal chrominance non-correlation energy (DCH2) consisting primarily of the chrominance signal in the horizontal direction;

said vertical chrominance non-correlation energy extractor (131) comprises:

a first vertical chrominance non-correlation energy extractor (31a) responsive to the sample values of said reference sampling points for detecting first vertical chrominance non-correlation energy (DCV1) consisting primarily of the chrominance signal in the vertical direction; and

a second vertical chrominance non-correlation energy extractor (31b) responsive to the sample values of said reference sampling points for detecting second vertical chrominance non-correlation energy (DCV2) consisting primarily of the chrominance signal in the vertical direction;

said adder is coupled to add the first horizontal chrominance non-correlation energy multiplied by a predetermined coefficient to the horizontal luminance non-correlation energy multiplied by a predetermined coefficient;

said first maximum value circuit is coupled to receive the first vertical chrominance non-correlation energy multiplied by a predetermined coefficient and the vertical luminance non-correlation energy multiplied by a predetermined coefficient, and produces, as an output thereof, the larger one of them;

said second maximum value circuit is coupled to receive





the second vertical chrominance non-correlation energy multiplied by a predetermined coefficient and the vertical luminance non-correlation energy multiplied by a predetermined coefficient, and produces, as an output thereof, the larger one of them;

said third maximum value circuit is coupled to receive the second vertical chrominance non-correlation energy multiplied by a predetermined coefficient and the vertical luminance non-correlation energy multiplied by a predetermined coefficient, and produces, as an output thereof, the larger one of them; and


said second comparator (38) is coupled to receive the second horizontal direction chrominance signal non-correlation energy and the output signal of the second maximum value circuit multiplied by a predetermined coefficient, and produces an output signal which indicates that the horizontal non-correlation is strong when the former is larger, and which indicates that the horizontal non-correlation is weak when the latter is larger.

15. A luminance/chrominance separating filter according to claim 3 or 5, wherein said judging means comprises:

a first maximum value circuit (33) for receiving the horizontal chrominance non-correlation energy multiplied by a predetermined coefficient and the horizontal luminance non-correlation energy multiplied by a predetermined coefficient, and producing, as an output thereof, the larger one of them;

a first adder (82) for adding the horizontal chrominance non-correlation energy multiplied by a predetermined coefficient to the horizontal luminance non-correlation energy multiplied by a predetermined coefficient, and producing, as an output thereof, the sum of them;





a second adder (83) for adding the horizontal chrominance non-correlation energy multiplied by a predetermined coefficient to the horizontal luminance non-correlation energy multiplied by a predetermined coefficient, and producing, as an output thereof, the sum of them;

a second maximum value circuit (36) for receiving the vertical chrominance non-correlation energy multiplied by a predetermined coefficient and the vertical luminance non-correlation energy multiplied by a predetermined coefficient, and producing, as an output thereof, the larger one of them;

a first comparator (37) for comparing the output signal of said first maximum value circuit with the output signal of said second maximum value circuit multiplied by a predetermined coefficient, and producing an output signal which indicates that the horizontal non-correlation is strong when the former is larger, and which indicates that the horizontal non-correlation is weak when the latter is larger;

a second comparator (38) for comparing the vertical chrominance non-correlation energy with the output signal of the first adder multiplied by a predetermined coefficient, and producing an output signal which indicates that the vertical non-correlation is strong when the former is larger, and which indicates that the vertical non-correlation is weak when the latter is larger;

a third comparator (39) for comparing the vertical luminance non-correlation energy with the output signal of the second adder multiplied by a predetermined coefficient, and producing an output signal which indicates that the vertical non-correlation is strong when the former is larger, and which indicates that the vertical non-correlation is weak when the latter is larger; and





a decision circuit (40) receiving the output signals of the three comparators, determining strength of horizontal non-correlation and vertical non-correlation, causing said first chrominance signal selecting means to output said first chrominance signal when the vertical non-correlation is strong, the second chrominance signal when the horizontal non-correlation is strong, and the third chrominance signal when neither of these conditions are met, and causing said second chrominance signal selecting means (25) to select the output of said second horizontal chrominance extraction filter (24), when said first selector selects either said first or third chrominance signal.

16. A luminance/chrominance separating filter according to claim 15, wherein

said horizontal chrominance non-correlation energy extractor (129) comprises:

a first horizontal chrominance non-correlation energy extractor (29a) responsive to the sample values of said specific and reference sampling points for detecting first horizontal chrominance non-correlation energy (DCH1) consisting primarily of the chrominance signal in the horizontal direction; and

a second horizontal chrominance non-correlation energy extractor (29b) responsive to the sample values of said specific and reference sampling points for detecting second horizontal chrominance non-correlation energy (DCH2) consisting primarily of the chrominance signal in the horizontal direction;

said vertical chrominance non-correlation energy extractor (131) comprises:

a first vertical chrominance non-correlation energy extractor (31a) responsive to the sample values of said reference sampling points for detecting first vertical





chrominance non-correlation energy (DCV1) consisting primarily of the chrominance signal in the vertical direction; and

a second vertical chrominance non-correlation energy extractor (31b) responsive to the sample values of said reference sampling points for detecting second vertical chrominance non-correlation energy (DCV2) consisting primarily of the chrominance signal in the vertical direction;

said first maximum value circuit is coupled to receive the second horizontal chrominance non-correlation energy multiplied by a predetermined coefficient and the horizontal luminance non-correlation energy multiplied by a predetermined coefficient, and produces, as an output thereof, the larger one of them;

said first adder is coupled to add the first horizontal chrominance non-correlation energy multiplied by a predetermined coefficient to the horizontal luminance non-correlation energy multiplied by a predetermined coefficient;

said second adder is coupled to add the first horizontal chrominance non-correlation energy multiplied by a predetermined coefficient to the horizontal luminance non-correlation energy multiplied by a predetermined coefficient;

said second maximum value circuit is coupled to receive the second vertical chrominance non-correlation energy multiplied by a predetermined coefficient and the vertical luminance non-correlation energy multiplied by a predetermined coefficient, and produces, as an output thereof, the larger one of them; and

said second comparator (38) is coupled to receive the first vertical chrominance non-correlation energy and the output signal of the first adder multiplied by a





predetermined coefficient, and produces an output signal which indicates that the vertical non-correlation is strong when the former is larger, and which indicates that the vertical non-correlation is weak when the latter is larger.

17. A luminance/chrominance separating filter according to claim 3 or 5, wherein said judging means comprises:

- a first maximum value circuit (33) for receiving the horizontal chrominance non-correlation energy multiplied by a predetermined coefficient and the horizontal luminance non-correlation energy multiplied by a predetermined coefficient, and producing, as an output thereof, the larger one of them;

- a first adder (82) for adding the vertical chrominance non-correlation energy multiplied by a predetermined coefficient to the vertical luminance non-correlation energy multiplied by a predetermined coefficient, and producing, as an output thereof, the sum of them;

- a second adder (83) for adding the vertical chrominance non-correlation energy multiplied by a predetermined coefficient to the vertical luminance non-correlation energy multiplied by a predetermined coefficient, and producing, as an output thereof, the sum of them;

- a second maximum value circuit (36) for receiving the vertical chrominance non-correlation energy multiplied by a predetermined coefficient and the vertical luminance non-correlation energy multiplied by a predetermined coefficient, and producing, as an output thereof, the larger one of them;

- a first comparator (37) for comparing the output signal of said first adder with the output signal of said first maximum value circuit multiplied by a predetermined coefficient, and producing an output signal which indicates that the vertical non-correlation is strong when the former





is larger, and which indicates that the vertical non-correlation is weak when the latter is larger;

a second comparator (38) for comparing the horizontal direction chrominance signal non-correlation energy with the output signal of the second adder multiplied by a predetermined coefficient, and producing an output signal which indicates that the horizontal non-correlation is strong when the former is larger, and which indicates that the horizontal non-correlation is weak when the latter is larger;

a third comparator (39) for comparing the horizontal luminance non-correlation energy with the output signal of the second maximum value circuit multiplied by a predetermined coefficient, and producing an output signal which indicates that the horizontal non-correlation is strong when the former is larger, and which indicates that the horizontal non-correlation is weak when the latter is larger; and

a decision circuit (40) receiving the output signals of the three comparators, determining strength of horizontal non-correlation and vertical non-correlation, causing said first chrominance signal selecting means to output said first chrominance signal when the vertical non-correlation is strong, the second chrominance signal when the horizontal non-correlation is strong, and the third chrominance signal when neither of these conditions are met, and causing said second chrominance signal selecting means (25) to select the output of said second horizontal chrominance extraction filter (24), when said first selector selects either said first or third chrominance signal.

18. A luminance/chrominance separating filter according to claim 17, wherein

said horizontal chrominance non-correlation energy





extractor (129) comprises:

a first horizontal chrominance non-correlation energy extractor (29a) responsive to the sample values of said specific and reference sampling points for detecting first horizontal chrominance non-correlation energy (DCH1) consisting primarily of the chrominance signal in the horizontal direction; and

a second horizontal chrominance non-correlation energy extractor (29b) responsive to the sample values of said specific and reference sampling points for detecting second horizontal chrominance non-correlation energy (DCH2) consisting primarily of the chrominance signal in the horizontal direction;

said vertical chrominance non-correlation energy extractor (131) comprises:


a first vertical chrominance non-correlation energy extractor (31a) responsive to the sample values of said reference sampling points for detecting first vertical chrominance non-correlation energy (DCV1) consisting primarily of the chrominance signal in the vertical direction; and

a second vertical chrominance non-correlation energy extractor (31b) responsive to the sample values of said reference sampling points for detecting second vertical chrominance non-correlation energy (DCV2) consisting primarily of the chrominance signal in the vertical direction;

said first maximum value circuit is coupled to receive the first horizontal chrominance non-correlation energy multiplied by a predetermined coefficient and the horizontal luminance non-correlation energy multiplied by a predetermined coefficient, and produces, as an output thereof, the larger one of them;

said first adder is coupled to add the first vertical





chrominance non-correlation energy multiplied by a predetermined coefficient to the vertical luminance non-correlation energy multiplied by a predetermined coefficient;

said second adder is coupled to add the second vertical chrominance non-correlation energy multiplied by a predetermined coefficient to the vertical luminance non-correlation energy multiplied by a predetermined coefficient;

said second maximum value circuit is coupled to receive the second vertical chrominance non-correlation energy multiplied by a predetermined coefficient and the vertical luminance non-correlation energy multiplied by a predetermined coefficient, and produces, as an output thereof, the larger one of them; and

said second comparator (38) is coupled to receive the second horizontal direction chrominance signal non-correlation energy and the output signal of the second adder multiplied by a predetermined coefficient, and produces an output signal which indicates that the horizontal non-correlation is strong when the former is larger, and which indicates that the horizontal non-correlation is weak when the latter is larger.

19. A luminance/chrominance separating filter according to claim 3 or 5, wherein said judging means comprises:

a maximum value circuit (33) for receiving the horizontal chrominance non-correlation energy multiplied by a predetermined coefficient and the horizontal luminance non-correlation energy multiplied by a predetermined coefficient, and producing, as an output thereof, the larger one of them;

a first adder (82) for adding the horizontal chrominance non-correlation energy multiplied by a





predetermined coefficient to the horizontal luminance non-correlation energy multiplied by a predetermined coefficient, and producing, as an output thereof, the sum of them;

a second adder (83) for adding the horizontal chrominance non-correlation energy multiplied by a predetermined coefficient to the horizontal luminance non-correlation energy multiplied by a predetermined coefficient, and producing, as an output thereof, the sum of them;


a third adder (84) for adding the vertical chrominance non-correlation energy multiplied by a predetermined coefficient to the vertical luminance non-correlation energy multiplied by a predetermined coefficient, and producing, as an output thereof, the sum of them;

a first comparator (37) for comparing the output signal of said maximum value circuit with the output signal of said third adder multiplied by a predetermined coefficient, and producing an output signal which indicates that the horizontal non-correlation is strong when the former is larger, and which indicates that the horizontal non-correlation is weak when the latter is larger;

a second comparator (38) for comparing the vertical chrominance non-correlation energy with the output signal of the first adder multiplied by a predetermined coefficient, and producing an output signal which indicates that the vertical non-correlation is strong when the former is larger, and which indicates that the vertical non-correlation is weak when the latter is larger;

a third comparator (39) for comparing the vertical luminance non-correlation energy with the output signal of the second adder multiplied by a predetermined coefficient, and producing an output signal which indicates that the vertical non-correlation is strong when the former is





larger, and which indicates that the vertical non-correlation is weak when the latter is larger; and

a decision circuit (40) receiving the output signals of the three comparators, determining strength of horizontal non-correlation and vertical non-correlation, causing said first chrominance signal selecting means to output said first chrominance signal when the vertical non-correlation is strong, the second chrominance signal when the horizontal non-correlation is strong, and the third chrominance signal when neither of these conditions are met, and causing said second chrominance signal selecting means (25) to select the output of said second horizontal chrominance extraction filter (24), when said first selector selects either said first or third chrominance signal.

20. A luminance/chrominance separating filter according to claim 19, wherein

said horizontal chrominance non-correlation energy extractor (129) comprises:

a first horizontal chrominance non-correlation energy extractor (29a) responsive to the sample values of said specific and reference sampling points for detecting first horizontal chrominance non-correlation energy (DCH1) consisting primarily of the chrominance signal in the horizontal direction; and

a second horizontal chrominance non-correlation energy extractor (29b) responsive to the sample values of said specific and reference sampling points for detecting second horizontal chrominance non-correlation energy (DCH2) consisting primarily of the chrominance signal in the horizontal direction;

said vertical chrominance non-correlation energy extractor (131) comprises:

a first vertical chrominance non-correlation energy





extractor (31a) responsive to the sample values of said reference sampling points for detecting first vertical chrominance non-correlation energy (DCV1) consisting primarily of the chrominance signal in the vertical direction; and

a second vertical chrominance non-correlation energy extractor (31b) responsive to the sample values of said reference sampling points for detecting second vertical chrominance non-correlation energy (DCV2) consisting primarily of the chrominance signal in the vertical direction;

said maximum value circuit is coupled to receive the second horizontal chrominance non-correlation energy multiplied by a predetermined coefficient and the horizontal luminance non-correlation energy multiplied by a predetermined coefficient, and produces, as an output thereof, the larger one of them;

said first adder is coupled to add the first horizontal chrominance non-correlation energy multiplied by a predetermined coefficient to the horizontal luminance non-correlation energy multiplied by a predetermined coefficient;

said second adder is coupled to add the first horizontal chrominance non-correlation energy multiplied by a predetermined coefficient to the horizontal luminance non-correlation energy multiplied by a predetermined coefficient;

said third adder is coupled to add the second vertical chrominance non-correlation energy multiplied by a predetermined coefficient to the vertical luminance non-correlation energy multiplied by a predetermined coefficient; and

said second comparator (38) is coupled to receive the first vertical chrominance non-correlation energy and the





output signal of the first adder multiplied by a predetermined coefficient, and produces an output signal which indicates that the vertical non-correlation is strong when the former is larger, and which indicates that the vertical non-correlation is weak when the latter is larger.

21.. A luminance/chrominance separating filter according to claim 3 or 5, wherein said judging means comprises:

- a first adder (81) for adding the horizontal chrominance non-correlation energy multiplied by a predetermined coefficient to the horizontal luminance non-correlation energy multiplied by a predetermined coefficient, and producing, as an output thereof, the sum of them;

- a second adder (82) for adding the vertical chrominance non-correlation energy multiplied by a predetermined coefficient to the vertical luminance non-correlation energy multiplied by a predetermined coefficient, and producing, as an output thereof, the sum of them;

- a third adder (83) for adding the vertical chrominance non-correlation energy multiplied by a predetermined coefficient to the vertical luminance non-correlation energy multiplied by a predetermined coefficient, and producing, as an output thereof, the sum of them;

- a maximum value circuit (36) coupled to receive the vertical chrominance non-correlation energy multiplied by a predetermined coefficient and the vertical luminance non-correlation energy multiplied by a predetermined coefficient, and producing, as an output thereof, the larger one of them;

- a first comparator (37) for comparing the output signal of said second adder with the output signal of said first adder multiplied by a predetermined coefficient, and producing an output signal which indicates that the vertical





non-correlation is strong when the former is larger, and which indicates that the vertical non-correlation is weak when the latter is larger;

a second comparator (38) for comparing the horizontal direction chrominance signal non-correlation energy with the output signal of the third adder multiplied by a predetermined coefficient, and producing an output signal which indicates that the horizontal non-correlation is strong when the former is larger, and which indicates that the horizontal non-correlation is weak when the latter is larger;


a third comparator (39) for comparing the horizontal luminance non-correlation energy with the output signal of the maximum value circuit multiplied by a predetermined coefficient, and producing an output signal which indicates that the horizontal non-correlation is strong when the former is larger, and which indicates that the horizontal non-correlation is weak when the latter is larger; and

a decision circuit (40) receiving the output signals of the three comparators, determining strength of horizontal non-correlation and vertical non-correlation, causing said first chrominance signal selecting means to output said first chrominance signal when the vertical non-correlation is strong, the second chrominance signal when the horizontal non-correlation is strong, and the third chrominance signal when neither of these conditions are met, and causing said second chrominance signal selecting means (25) to select the output of said second horizontal chrominance extraction filter (24), when said first selector selects either said first or third chrominance signal.

22. A luminance/chrominance separating filter according to claim 21, wherein

said horizontal chrominance non-correlation energy





extractor (129) comprises:

a first horizontal chrominance non-correlation energy extractor (29a) responsive to the sample values of said specific and reference sampling points for detecting first horizontal chrominance non-correlation energy (DCH1) consisting primarily of the chrominance signal in the horizontal direction; and

a second horizontal chrominance non-correlation energy extractor (29b) responsive to the sample values of said specific and reference sampling points for detecting second horizontal chrominance non-correlation energy (DCH2) consisting primarily of the chrominance signal in the horizontal direction;

said vertical chrominance non-correlation energy extractor (131) comprises:

a first vertical chrominance non-correlation energy extractor (31a) responsive to the sample values of said reference sampling points for detecting first vertical chrominance non-correlation energy (DCV1) consisting primarily of the chrominance signal in the vertical direction; and

a second vertical chrominance non-correlation energy extractor (31b) responsive to the sample values of said reference sampling points for detecting second vertical chrominance non-correlation energy (DCV2) consisting primarily of the chrominance signal in the vertical direction;

said first adder is coupled to add the first horizontal chrominance non-correlation energy multiplied by a predetermined coefficient to the horizontal luminance non-correlation energy multiplied by a predetermined coefficient;

said second adder is coupled to add the first vertical chrominance non-correlation energy multiplied by a





predetermined coefficient to the vertical luminance non-correlation energy multiplied by a predetermined coefficient;

said third adder is coupled to add the second vertical chrominance non-correlation energy multiplied by a predetermined coefficient to the vertical luminance non-correlation energy multiplied by a predetermined coefficient;

said maximum value circuit is coupled to receive the second vertical chrominance non-correlation energy multiplied by a predetermined coefficient and the vertical luminance non-correlation energy multiplied by a predetermined coefficient, and produces, as an output thereof, the larger one of them; and

said second comparator (38) is coupled to receive the second horizontal direction chrominance signal non-correlation energy and the output signal of the third adder multiplied by a predetermined coefficient, and produces an output signal which indicates that the horizontal non-correlation is strong when the former is larger, and which indicates that the horizontal non-correlation is weak when the latter is larger.

23. A luminance/chrominance separating filter according to any one of claims 7 to 22, further comprising:

a first delay circuit for delaying the output signal of the first comparator by a time length $(1/2f_{sc})$ half a period of the color subcarrier to produce a first delayed output signal;

a second delay circuit for delaying the output signal of the second comparator by said time length to produce a second delayed output signal;

a third delay circuit for delaying the output signal of the third comparator by said time length to produce a





third delayed output signal;

a fourth delay circuit for delaying the output signal of the third delay circuit by said time length to produce a fourth delayed output signal;

an AND circuit for producing a logical product of the output signal of the third comparator, said third delayed output signal and said fourth delayed output signal;

wherein said decision circuit receives said first, and second delayed output signals, and said logical product, and determines strength of the horizontal non-correlation and the vertical non-correlation on the basis of said first and second delayed signals and said logical product.





24. Apparatus for separating a chrominance component from a luminance component of a composite colour video or television signal, wherein the apparatus is operable to extract a chrominance component from the composite signal by a process selected from a plurality of extraction processes, the plurality of extraction processes including at least a first extraction process comprising extracting frequency components corresponding to colour sub-carrier components in a first video direction, and a second extraction process comprising extracting frequency components corresponding to colour sub-carrier components in a second video direction, and wherein the apparatus is operable to control selectively a frequency band characteristic of an extracted chrominance signal derived using the selected extraction process, depending on which of the extraction processes is used.

25. Apparatus according to claim 24, wherein the apparatus is operable to produce a luminance component output by subtracting from the composite signal a subtraction signal derived from the aforementioned extracted signal.

26. Apparatus according to claim 24, wherein the





apparatus is operable to produce a basic extracted signal using the selected extraction process but without the aforementioned selective controlling of the frequency band characteristic, and wherein the apparatus is operable to produce a chrominance component output based on the first mentioned extracted signal, and to use the basic extracted signal as a subtraction signal for producing a luminance component output from the composite signal.

27. Apparatus according to any one of claims 24 to 26, wherein the selective control of the frequency band characteristic of the extracted signal is operative when the selected extraction process extracts frequency components corresponding to colour sub-carrier components in a video direction having a direction component in the horizontal direction.

28. Apparatus according to claim 27, wherein the selective control of the frequency band characteristic comprises processing an extracted signal after the selected extraction process by using a filter having a narrower horizontal frequency band characteristic than that of said extraction process.

29. A method for separating a chrominance component





from a luminance component of a composite colour video or television signal, the method comprising extracting a chrominance component by a selected one of a plurality of available extraction processes, the plurality of extraction processes including at least a first extraction process comprising extracting frequency components corresponding to colour sub-carrier components in a first video direction, and a second extraction process comprising extracting video components corresponding to colour sub-carrier components in a second video direction, the method further comprising selectively controlling a frequency band characteristic of an extracted chrominance signal derived using the selected extraction process, depending on which of the extraction processes is used.

30. Apparatus for producing a luminance signal output and a chrominance signal output from a composite colour video or television signal, wherein the apparatus is operable to produce an extracted chrominance signal and a subtraction signal from the composite signal by a process selected from a plurality of extraction processes, the plurality of extraction processes including at least a first extraction process comprising extracting frequency





components corresponding to colour sub-carrier components in a first video direction, and a second extraction process comprising extracting frequency components corresponding to colour sub-carrier components in a second video direction, and wherein the apparatus is operable to produce the luminance signal output based on the composite signal and on the subtraction signal, and wherein the apparatus is further operable to produce selectively a difference between the chrominance signal and the subtraction signal in terms of their respective frequency band characteristic, depending on which of the extraction processes is used.

31. Apparatus for separating a chrominance component from a luminance component of a composite colour video or television signal, the apparatus being substantially as hereinbefore described with reference to any of Figures 1-42 of the accompanying drawings.

32. A method for separating a chrominance component from a luminance component of a composite colour video or television signal, the method being substantially as hereinbefore described with reference to any of Figures 1-42 of the accompanying drawings.

