

RASTER DISTORTION CORRECTION CIRCUIT

The invention, which is divided from our application No. 8714912.6, relates to video display systems and, more particularly, to a raster distortion  
5 correction circuit in a video display apparatus.

Recent interest in the development of high definition television systems (HDTV) has been directed towards techniques that are intended to enhance the subjective performance of present systems within the  
10 constraints of existing standards. One approach, a technique referred to as progressive scan, or non-interlaced scan, has been described in patent materials and literature. For example, all the scan lines are scanned consecutively from the top of the cathode ray  
15 tube (CRT) display screen downward to the bottom of the display screen during each vertical scanning interval. Progressive scan results in the reduction of artifacts related to interlaced scanning format, such as interline flicker.

In progressive scan double-frequency scanning format, for example, the incoming interlaced television signal, such as illustrated schematically in FIGURE 2, may be processed in well known techniques to produce, for example, pairs of video lines of R, G and B color  
20 component video signals, whose picture content is to be displayed in corresponding pairs of scan lines of the progressive scanned raster. A video line of each color component video signal may include, during a period H of a given video line, that in NTSC, for example, is 63.5  
25 microseconds long, a picture information containing portion that is 52.6 microseconds long and that represents the active portion of the video line. This active portion may be considered as being divided into a series of pixel signals that represent associated pixels, or picture  
30 elements, that are displayed at corresponding locations within a corresponding horizontal scan line. The pixel signals may be distributed uniformly in time throughout the active portion of the video line.

In some prior art progressive scan systems, the incoming television signal is sampled at a given rate that meets the Nyquist criteria. The samples are processed to obtain processed samples that represent the pixel signals of the video line pairs of the color component video signals. The pixel signals are stored at a given rate in a storage element such as, for example, a line store, and then read out at a higher rate. In this way, each video line is speeded-up or time-compressed. A given speeded-up video line of a given line pair is time-multiplexed with the other speeded-up video line of that line pair, to provide a noninterlaced time compressed color video signal that is applied to the cathode of the corresponding gun of the CRT. The noninterlaced time compressed color video signal is displayed in a progressive scan manner on the screen of the television receiver. The duration of each line of the time compressed color video signal is, for example, half that of the corresponding incoming interlaced television signal.

In a raster scanning display system, display distortions, such as east-west and linearity distortions, may occur. Additionally, convergence distortion of the tricolor electron beams may also occur. For example, when a television video signal that contains picture information of a pattern of, for example, vertical lines, is displayed on a cathode ray tube (CRT) screen, east-west distortion, if left uncorrected, will produce the pattern shown in FIGURE 4a. Note that the separation  $l_a$  between distorted vertical lines 77 and 71 along a horizontal scan line 40 at the top, or along a horizontal scan line 40' at the bottom of the screen is greater than the corresponding separation  $l_b$  along a horizontal scan line 41 at the center of the screen. The different separations occur because the geometry of the CRT is such that the electron beam travels a longer distance at the top or bottom of the screen than at the center, during the same corresponding portions of the trace interval.

Another related distortion may create nonoverlapping color images when the CRT screen is scanned by the tricolor electron beams. The mismatch among the corresponding color images produces convergence error. A horizontal convergence error that may occur when a vertical bar is displayed, is shown in FIGURE 4b.

In some interlaced display systems, raster distortion is corrected by storing the picture information of an incoming interlaced video signal in a memory and then reading out the stored information to form an output interlaced video signal that is coupled to an interlaced video display. The stored information is read out sequentially using a clock signal. The clock signal has a frequency that varies in accordance with a distortion information providing signal. The distortion information providing signal varies in accordance with the location on a faceplate of the video display where the picture information of the output interlaced video signal that was read out from the memory is displayed. The output interlaced video signal is then displayed without raster distortion of the picture. The output interlaced video signal includes video line signals that occur at the horizontal rate, the rate at which the video line signals of the incoming interlaced video signal occur. The output interlaced video signal that provides raster distortion correction may not, by itself, be suitable for providing picture information to a noninterlaced display since it must first be time-compressed to be suitable for display in the noninterlaced video display. Disadvantageously, such time-compression may result in the loss of the timing information that provides the raster distortion correction.

According to the invention, there is provided a display apparatus responsive to an incoming video signal for generating an output video signal coupled to a video display apparatus to provide information that is

5 displayed in a plurality of display lines on said video display that form a raster during a given deflection cycle such that a distortion in said video display apparatus that is associated with the display of picture information derived from said incoming video signal in

10 said raster is compensated by varying said output video signal. The apparatus comprises: a memory responsive to said incoming video signal for storing therein the picture information derived from said incoming video signal and for reading out therefrom the stored picture

15 information to generate said output video signal that provides the stored picture information to said video display apparatus; means for generating a correction signal that varies in accordance with said distortion in said video display apparatus; a controlled oscillator for

20 generating a first clock signal that is coupled to said memory to generate said output video signal at a rate that is determined in accordance with the frequency of said clock signal, said controlled oscillator being responsive, outside a calibration interval, to said

25 correction signal for varying the frequency of said first clock signal in accordance with said correction signal; and means for generating a calibration reference signal having a value during said calibration interval that is representative of a first operating frequency, wherein

30 said controlled oscillator is responsive during said calibration interval to said calibration reference signal for providing calibration of the operation of said controlled oscillator during said calibration interval.

In the drawings:

FIGURE 1 illustrates a video display apparatus that generates speeded-up red, blue and green video signals;

FIGURE 2 illustrates, schematically, the timing diagram of an NTSC signal that is coupled to the video display apparatus of FIGURE 1;

FIGURES 3a-3h illustrate, schematically, timing diagrams useful in explaining the operation of the apparatus of FIGURE 1;

FIGURES 4a and 4b illustrate display distortions caused by east-west pincushion distortion and horizontal convergence error, respectively, when the incoming television signal contains a picture of vertical bars;

FIGURES 5a and 5b illustrate schematically two examples of video line signals that contain substantially identical picture information and that are adapted for display at the top and at the center of the raster, respectively; and

FIGURE 6 illustrates schematically a diagram of a timing unit embodying aspects of the invention, that is suitable for the apparatus of FIGURE 1.

FIGURE 1 illustrates a video apparatus 150, for displaying in a CRT 119 the picture information of an interlaced NTSC

television signal 130 of FIGURE 2 in a non-interlaced scanning format. Similar numbers and symbols in FIGURES 1 and 2 represent similar items or functions. NTSC signal 130 of FIGURE 2 is applied from a source, which is not  
5 shown, to a terminal 400c of a separator block 135 of FIGURE 1. The source of signal 130 may be the demodulated output of a standard IF stage.

Separator block 135, such as may be used in a progressive scan system, generates during each video line,  
10 such as line n of NTSC signal 130 of FIGURE 2, two groups of concurrent video line component signals. The signals of the first group, signals  $I_a$ ,  $Q_a$  and  $Y_a$  of FIGURE 1, are derived from the corresponding I, Q and Y component signals, respectively, from NTSC signal 130. The first  
15 group contains picture information for display in each display line of a first set of alternate display lines of CRT 119 screen. The signals of a second group, signals  $I_b$ ,  $Q_b$  and  $Y_b$ , are also derived from the corresponding I, Q, and Y component signals, respectively, from NTSC signal  
20 130. The second group contains picture information for display in each display line of a second set of alternate display lines that are displayed on CRT 119 screen between the corresponding display lines of the first set to form a frame of displayed picture. When the picture information  
25 displayed in a given display line is supplied from each signal of the first group of signals, the picture information displayed in the immediately preceding or following display line is supplied from each signal of the second group of signals.

30 In one example, signals  $I_a$ ,  $Q_a$  and  $Y_a$  may be identical to signal  $I_b$ ,  $Q_b$  and  $Y_b$ , respectively. In such example, each of the corresponding signals  $I_a$ ,  $Q_a$  and  $Y_a$  may be obtained from NTSC signal 130 using conventional signal component separation techniques. However,  
35 different methods have evolved in progressive scan systems for generating the two groups of concurrent video line signals such that the two groups that are not identical provide a more pleasing picture. For example, an

apparatus for generating the two groups of concurrent signals is described in U.S. Patent No. 4598309, issued 1 July 1986, to R.F. Casey, entitled, A TELEVISION RECEIVER THAT INCLUDES A FRAME STORE USING NON-INTERLACED SCANNING  
5 FORMAT WITH MOTION COMPENSATION.

Signals  $I_a$ ,  $Q_a$  and  $Y_a$  are coupled to the respective terminals of an I, Q, Y matrix 439a, of conventional construction. Matrix 439a generates signals  $R_a$ ,  $G_a$  and  $B_a$  that contain red, green and blue color  
10 components, respectively, from signals  $I_a$ ,  $Q_a$  and  $Y_a$ . Similarly, signals  $I_b$ ,  $Q_b$  and  $Y_b$  are coupled to the respective terminals of a similar I, Q, Y matrix 439b. Matrix 439b similarly generates signals  $R_b$ ,  $G_b$  and  $B_b$  from signals  $I_b$ ,  $Q_b$  and  $Y_b$ .

15 NTSC signal 130 of FIGURE 2 is also coupled to a timing unit 430 of FIGURE 1. Timing unit 430 utilizes, for example, horizontal and vertical sync pulses of NTSC signal 130 for generating a horizontal scanning control, or deflection cycle forming signal  $S_{2H}$  and a vertical  
20 scanning control signal  $S_v$  that are coupled to a horizontal and vertical deflection stage 500. Stage 500 controls deflection currents  $i_{2H}$  and  $i_v$  in a horizontal deflection winding 432 and in a vertical deflection winding 431, respectively, of CRT 119. The frequency of  
25 horizontal scanning control signal  $S_{2H}$  is, illustratively,  $2xf_H$ ,  $f_H$  being the conventional scanning frequency of a standard television receiver that employs the conventional interlaced scanning format. The frequency of vertical scanning control signal  $S_v$  is, illustratively, the same as  
30 in the standard television receiver. Timing unit 430 may include a phase-locked-loop circuit, not shown in FIGURE 1, that is phase locked to horizontal sync pulses  $h_{sp}$  of NTSC signal 130 of FIGURE 2 for generating each of clock signals 230f-230i, and 230l of FIGURE 1. Timing unit 430  
35 is described in further detail later on.

Green signal  $G_a$ , for example, from matrix 439a is applied through a terminal F to a 1-H delay 434 and to a 1-H delay 435 of a speed-up unit 433 that

time-compresses signal  $G_a$ . Green signal  $G_b$  from matrix 439b is applied through a terminal G to a 1-H delay 436 and to a 1-H delay 437 of unit 433 that time-compresses signal  $G_b$ . Each of 1-H delay units 434, 435, 436 and 437 may comprise first-in first-out (FIFO) buffers that may be implemented using analog or digital techniques.

FIGURES 3a-3h illustrate schematically a simplified example of timing diagrams of clock signals 230f, 230g, 230h and 230i of FIGURE 1, respectively, that are coupled to 1-H delay units 434, 436, 435 and 437, respectively of speed-up unit 433. Similar numbers and symbols in FIGURES 1, 2 and 3a-3h represent similar items or functions. Clock signal 230f of FIGURE 3d clocks in samples of, for example, video line 143 of signal  $G_a$  of FIGURE 3a into 1-H delay unit 434 of FIGURE 1 between, for example, time  $t_5$  and time  $t_8$  at, illustratively, a constant first clock rate, as illustrated by the short vertical lines in the corresponding interval of FIGURE 3d. Simultaneously, clock signal 230g of FIGURE 3e clocks in samples of video line 143 of signal  $G_b$ , that may also be schematically represented by the timing diagram of FIGURE 3a, into 1-H delay unit 436 of FIGURE 1 at, illustratively, the same first clock rate. Note that the timing diagram of FIGURE 3a may represent, in the respective context, any of signals  $G_a$ ,  $G_b$ ,  $R_a$ ,  $R_b$ ,  $B_a$  or  $B_b$ . The samples in unit 434 of FIGURE 1 are clocked out, or read out at a second clock rate of clock signal 230f that is illustrated schematically by the short vertical lines in FIGURE 3d between times  $t_9$  and  $t_{11}$ . The second clock rate may vary between times  $t_9$  and  $t_{11}$  for providing raster distortion compensation. The second clock rate is higher than the first clock rate so as to provide an output signal  $G_{2H}$  of FIGURE 3f that is speeded-up relative to, for example, signal  $G_a$ . Similarly, the samples in delay unit 436 of FIGURE 1 are clocked out, or read out at, illustratively, the second clock rate, that may be

also variable, of clock signal 230g, as illustrated schematically by the short vertical lines in FIGURE 3e between times t12 and t13. The samples that are read out from delay unit 434 and 436, respectively, of FIGURE 1 are coupled to input terminals A and B of a switch 433a, respectively. An example of a pixel signal of signal G<sub>a</sub> is schematically illustrated in line 143 in FIGURE 3a.

FIGURE 3f illustrates schematically signal G<sub>2H</sub> that is coupled by a wiper k of switch 433a to a terminal E. Wiper k is controlled by timing signal 230l of timing unit 430. Wiper k couples to terminal E the speeded-up samples, or pixel signals, that are read out of unit 434 and that appear at terminal A, to form the corresponding signal of speeded-up video line signal G<sub>2H</sub> between, for example, times t9 and t11, as illustrated in FIGURE 3f. An example of a speeded-up pixel signal is schematically illustrated in FIGURE 3f for the video line signal G<sub>2H</sub> between times t<sub>9</sub> - t<sub>11</sub>. Likewise, wiper k of FIGURE 1, in response to timing signal 230l couples the speeded-up samples, or pixel signals, that are read out of unit 436 and that appear at terminal B, to output terminal E between, for example, times t12 and t13 of FIGURE 3f.

In a like manner, clock signal 230h of FIGURE 3c clocks samples of video line 141 of signal G<sub>a</sub> of FIGURE 3a between time t0 and time t3 into 1-H delay unit 435 of FIGURE 1 at the first clock rate as illustrated by the short vertical lines in FIGURE 3c. Simultaneously, clock signal 230i of FIGURE 3b clocks samples of video line 141 of signal G<sub>b</sub> of FIGURE 3a into 1-H delay unit 437 of FIGURE 1 at the same first clock rate. In a similar manner to that described before, the samples in unit 435 of FIGURE 1 are clocked out or read out at the variable second rate of clock 230h, as illustrated schematically in a simplified manner by the short vertical lines of clock 230h in FIGURE 3c between times t7 and t8. The samples in unit 437 of FIGURE 1 are clocked out or read out at the variable second rate of clock signal 230i, as illustrated schematically in a simplified manner by the short vertical

lines of clock signal 230i of FIGURE 3b, respectively, between times  $t_4$  and  $t_6$ . The samples from unit 435 and 437 of FIGURE 1 are coupled to terminals C and D of switch 433a, respectively.

5           Wiper k couples the samples, or pixel signals of unit 435 at terminal C to output terminal E between times  $t_7$  and  $t_8$  of FIGURE 3f for generating speeded-up signal  $G_{2H}$ ; likewise, wiper k of FIGURE 1 couples the samples or pixel signals of unit 437 at terminal D to terminal E  
10 between times  $t_4$  and  $t_6$ . Thus, signal  $G_{2H}$  of FIGURE 3f that appears at terminal E of FIGURE 1 contains the speeded up, time-multiplexed, picture information of signals  $G_a$  and  $G_b$  of FIGURE 3a. The picture information of signals  $G_a$  and  $G_b$  appears in alternate time slots,  
15 respectively, such as, for example, intervals  $t_4-t_6$  and  $t_7-t_8$ , respectively, of FIGURE 3f to form signal  $G_{2H}$ . Signal  $G_{2H}$  is applied to control the green electron beam gun of CRT 119.

A speedup unit 433" in FIGURE 1, that is  
20 illustratively constructed similarly to speedup unit 433 has terminals E", F" and G" that correspond with terminals E, F and G respectively, of speedup unit 433. Unit 433" of FIGURE 1 receives, from timing unit 430, clock signals that are functionally equivalent to clocks signals  
25 230f-230i. Unit 433" operates similarly to unit 433 for generating speeded-up red signal  $R_{2H}$ .

A speedup unit 433' in FIGURE 1 that is illustratively also constructed similarly to speedup unit 433 has terminals E', F' and G' that correspond with  
30 terminals E, F and G, respectively, of speedup unit 433. Unit 433' of FIGURE 1 receives from timing unit 430, clock signals that are functionally equivalent to clock signals 230f-230i, respectively. Unit 433' operates similarly to units 433 or 433" for generating speeded-up signal  $B_{2H}$ .

35           Thus, signals  $R_{2H}$ ,  $G_{2H}$  and  $B_{2H}$  of FIGURE 1 provide the picture information of interlaced NTSC signal 130 for display in non-interlaced display format.

In a conventional television display apparatus, raster distortion may be corrected by modulating the scanning current, such as scanning current  $i_y$  of FIGURE 1. In contrast, in video apparatus 150 of FIGURE 1, embodying aspects of the invention, distortion correction may be accomplished without modulation of scanning current  $i_y$ .

Each pixel signal of, for example, a video line of green signal  $G_{2H}$  at terminal E is coupled to the input terminal of the green electron beam gun of CRT 119 at a corresponding instant that is selected by timing unit 430.

The timing of such pixel signal is such that the corresponding pixel displayed on the screen of CRT 119 appears at a horizontal position of the electron beams within the scan line so as to eliminate the appearance of distortion in the displayed picture. Selectively varying the timing of the pixel signals is done to compensate for geometry distortion in CRT 119. In contrast, in a given video line  $n$  of, for example, NTSC signal 130 of FIGURE 2, the pixel signals of video line  $n$  are distributed uniformly in time and should be displayed, in accordance with the NTSC standard, as uniformly distributed pixels along the corresponding scan line on the screen of CRT 119 of FIGURE 1.

In some progressive scan television systems, the sample read-out rate, in a speed-up unit that is similar to, for example, speed-up unit 433 of FIGURE 1, is constant. Such constant rate may be equal to twice that of the sample write-in rate to provide double frequency scanning format. In contrast, in video apparatus 150 of FIGURE 1, the sample read-out rate, such as the frequency of clock 230g of FIGURE 3c, between times  $t_2$  and  $t_3$ , may be different in different segments, respectively, of each scan line, as described later on. Furthermore, in other progressive scan television systems, the samples are read out, in each scan line, beginning after a constant delay time  $t_d$  from, time  $T_{2H}$  at, for example, the center of the preceding retrace interval.

The samples, or pixel signals, associated with a given scan line are read out beginning after a delay time  $t_d$  of FIGURE 3f that may be different for corresponding different scan lines. In one example, the sample read-out beginning time, such as time  $t_4$  of FIGURE 3f, is separately controllable for each individual scan line. In a second example, the samples read-out beginning time for each group of scan lines is the same time  $t_d$  that is controllable on a group of lines basis.

The delay time  $t_d$ , as well as, for example, the sample read-out rate, may be separately and independently controlled for each of signals  $G_{2H}$ ,  $B_{2H}$  and  $R_{2H}$  of FIGURE 1.

FIGURE 4a illustrates a hypothetical example that shows the effect of east-west raster distortion, when left uncorrected, on the image of vertical bars 71-77. The picture information of the vertical bars is contained in NTSC signal 130 of FIGURE 2. Portion "a" of a scan line 40, appearing between lines 71 and 77 of FIGURE 4a that is displayed at the top of the screen of CRT 119 of FIGURE 1, has a length  $l_a$ ; whereas portion "b" of a scan line 41, appearing between lines 71 and 77 of FIGURE 4a at the center of the screen, has a length  $l_b$  that is shorter than length  $l_a$ . Without being distorted, parallel portions "a" and "b" that appear in parallel on the screen of CRT 119 of FIGURE 1 should have identical length, as follows from NTSC signal 130.

It may be desirable to display the entire picture information associated with portion "a" of, for example, scan line 40 in the smaller portion "a1" of scan line 40 that is situated directly above portion "b" of scan line 41, in order to make the image of, for example, vertical line 71 in scan line 40, appear on the screen directly above the corresponding image of vertical line 71 in scan line 41, as dictated by the picture information content of NTSC signal 130 of FIGURE 2. In this way,

east-west raster distortion may be substantially eliminated. To this end, it is desirable to begin reading out the samples, or signal pixels, that are associated with vertical bar 71 in scan line 40 of FIGURE 4a, after  
5 such delay time  $t_d$  that is larger than the corresponding delay time associated with the samples of vertical bar 71 in scan line 41 of FIGURE 4a.

Because the electron beam scan velocity in the horizontal direction varies along, for example, scan line  
10 40, it is desirable to vary the sample read-out rate, such as between times  $t_2$  and  $t_3$  of FIGURE 3e, to correspond with the varying beam scanning velocity. Varying such read-out rate is desirable in order to obtain uniform distribution of the pixels displayed in, for example, scan  
15 line 40 of FIGURE 4a, so as to correspond with the uniformly distributed pixel signals of incoming NTSC signal 130 of FIGURE 2.

In a second hypothetical example, the picture information of signals  $G_{2H(a)}$  and  $G_{2H(b)}$  of FIGURES 5a and  
20 5b, respectively, of signal  $G_{2H}$  of FIGURE 1 is displayed on the screen of CRT 119. The screen of CRT 119 includes, for example, scan lines 40 and 41 such as shown in FIGURE 4a. Signal  $G_{2H(a)}$  of FIGURE 5a, for example, may also be represented by portion 140a of speeded-up signal  $G_{2H}$  of  
25 FIGURE 3f, that is generated by video apparatus 150 of FIGURE 1 and that provides a corresponding, substantially distortion free, image for display in, for example, scan line 40 of FIGURE 4a. The position of scan line 40 is shown in FIGURE 4a. Similarly, signal  $G_{2H(b)}$ , shown in  
30 FIGURE 5b, contains, illustratively, picture pattern that is identical to that contained in signal  $G_{2H(a)}$  of FIGURE 5a and that is suitable for display in scan line 41 of FIGURE 4a. As a result of raster distortion correction of video apparatus 150 of FIGURE 1, when the video line  
35 signals of FIGURE 5a and 5b are displayed in scan lines 40 and 41, respectively, the picture patterns that are displayed in each scan line appear identical and one pattern appears directly above the other. Such pattern

is, illustratively, different from the vertical bar pattern referred to in a previous example. Similar numbers and symbols in FIGURES 5a, 5b, 4a, 3a-3f, 2 and 1 illustrate similar items or functions.

5           The sample read-out beginning times, times  $T_i'$  and  $T_i$ , in FIGURES 5a and 5b, respectively, are delayed by delay times  $t_d'$  and  $t_d$ , respectively, from time  $T_{2H}$ , that occurs at, for example, the center of the retrace interval of the preceding speeded-up video line. Note that delay  
10   time  $t_d'$  of FIGURE 5a is greater than delay time  $t_d$  of FIGURE 5b. This is so because signal  $G_{2H(a)}$  of FIGURE 5a is adapted for display in scan line 40 of FIGURE 4a, that is at the top of the screen; whereas, signal  $G_{2H(b)}$  of  
15   FIGURE 5b is adapted for display in scan line 41 of FIGURE 4a that is at the center of the screen.

          Video line signals  $G_{2H(b)}$  and  $G_{2H(a)}$  of FIGURES 5b and 5a, are provided during intervals  $T_b$  and  $T_a$ , having durations  $T_{sb}$  and  $T_{sa}$ , respectively. For example, the ratio  $T_{sb}/T_{sa}$  in the distortion compensated signals is,  
20   illustratively, equal to the ratio  $l_a/l_b$  of portions "a" and "b" of scan lines 40 and 41, respectively, of the distorted image of FIGURE 4a. Thus video signal  $G_{2H(a)}$  of FIGURE 5a is compressed more, relative to video signal  
25    $G_{2H(b)}$  of FIGURE 5b, so as to compensate for the difference in the horizontal scanning speed in the corresponding scan lines. The desired compression ratio is achieved by having the read-out clock frequency, that is used for reading out the pixel signals of scan line 41 of FIGURE 4a, higher than that of the read-out clock that  
30   is used for reading out the pixel signals that are displayed in scan line 40.

          FIGURE 6 illustrates a more detailed embodiment of timing unit 430 of FIGURE 1 embodying an aspect of the invention. Unit 430 of FIGURE 6 generates, for example,  
35   clock signals 230f-230i that determine the sample read-out rates and delay times such as delay time  $t_d$  or  $t_d'$  of FIGURES 5a or 5b. Similar numbers and symbols in FIGURES

1, 2, 3a-3h, 5a, 5b and 6 indicate similar items or functions.

NTSC signal 130 of FIGURE 6 is coupled to a sync separator unit 51 that supplies, in a conventional manner, a horizontal rate signal  $H_s$  having a frequency of  $f_H$  and a vertical rate signal  $V_s$  from the corresponding horizontal and vertical sync pulses of NTSC signal 130. Horizontal rate signal  $H_s$  is coupled to a phase detector 52. Phase detector 52 supplies a voltage 52a that controls the phase and frequency of a clock signal CL at an output terminal 50a of a VCO 50. VCO 50 provides clock signal CL having a frequency of, illustratively,  $1820 \times f_H$ . Clock signal CL is coupled through a chain of frequency dividers 53, 54, 55 and 56 to phase detector unit 52. The phase and frequency of a signal 56a at an output terminal that is at the end of the chain of the frequency dividers is phase-compared, in detector 52, with signal  $H_s$  for supplying phase and frequency controlling voltage 52a. Voltage 52a maintains a fixed phase and frequency relationship between clock signal CL and signal  $H_s$ .

Frequency divider 53 divides the frequency of clock signal CL by 2 for generating a clock WRITE signal that is used for generating each of the samples write-in clock signals such as used, illustratively, in speed-up unit 433 of FIGURE 1.

Frequency divider 54 of FIGURE 6 generates a clock SEGCLK that is illustrated schematically by the short vertical lines of FIGURE 3g. Clock SEGCLK provides a discrete clocking edge in each interval SG, so as to divide each period  $H/2$  between consecutive times  $T_{2H}$  of, for example, signal  $G_{2H}$  of FIGURE 3f into corresponding time segments. Clock SEGCLK of FIGURE 6 is coupled to a horizontal segment counter 57 that provides an output word HORSEG. Word HORSEG contains the location of a segment within each video line of, for example, signal  $G_{2H}$  of FIGURE 3f. Thus each speeded-up video line is divided into a predetermined number of corresponding segments SG1 - SGn. After counter 57 of FIGURE 6 sequences through

each of the the segment intervals SG of FIGURE 3g that are included in a given horizontal period  $H/2$ , it generates a signal 57a that increments counter 58. An output word HORLINE of counter 58 provides the horizontal line number within a given picture frame that is displayed in CRT 119 of FIGURE 1. Illustratively, each of words HORSEG and HORLINE of FIGURE 6 is initialized to zero by vertical rate signal  $V_s$  of sync separator unit 51 at the beginning of each picture frame.

A combination word that includes both words HORSEG and HORLINE provides an input address word to a read only memory (ROM) 59. Memory 59 generates corresponding words  $F_R$ ,  $F_G$  and  $F_B$  for each such combination word during the corresponding horizontal segment interval SG. Words  $F_R$ ,  $F_G$  and  $F_B$  control the frequency of clock signals  $R_{CK}$ ,  $G_{CK}$  and  $B_{CK}$ , respectively, that are coupled, respectively, to a multiplexer unit 60 for generating the corresponding read-out clock signals, as described below.

Word  $F_G$  is coupled to a digital-to-analog (D/A) converter unit 61 of a read-out clock generator 64. Converter unit 61 provides an analog control signal  $A_G$  that controls, in accordance with the value of word  $F_G$ , the frequency of an output signal  $VC_g$ , produced by a VCO 62. Signal  $VC_g$  is coupled via an input terminal 63b of an AND gate 63 to provide clock  $G_{CK}$  that is coupled to multiplexer unit 60. Word  $F_G$  controls the frequency of clock signal  $G_{CK}$  separately for each segment interval SG of each horizontal period  $H/2$  of FIGURE 3g. Different words  $F_G$  that are stored in ROM 59 and are read out in corresponding different intervals SG to vary the rate of clock  $G_{CK}$  from one segment interval to another in accordance with the type of distortion being corrected.

Multiplexer unit 60 of FIGURE 6, that is controlled also by output word HORLINE, couples, by multiplexer operation, each of clocks WRITE and  $G_{CK}$  to the

corresponding signal lines of FIGURE 1 for developing clock signals 230f, 230g, 230h and 230i, at times that are illustrated in FIGURES 3d, 3e, 3c and 3b, respectively.

Output signal  $VC_g$  of oscillator 62 of FIGURE 6 is coupled as clock signal  $G_{CK}$  to multiplexer unit 60, starting at, for example, time  $t_4$  of FIGURE 3b that is delayed by an amount  $t_d$  after the immediately preceding time  $T_{2H}$ , that is between times  $t_3$  and  $t_4$ . The amount of delay time of variable delay  $t_d$  is controlled by a control pulse  $G_{dl}$  of FIGURE 3h that is supplied at an input terminal 63a of AND gate 63 by a programmable pulse generator 67 of FIGURE 6, as described below.

Word HORLINE supplies the address word to a memory 66. An output word  $G_{dwd}$  at a port 66a of memory 66 that is selected in accordance with the corresponding state of word HORLINE is coupled to programmable pulse generator 67. Pulse generator 67 receives, at, for example, each time  $T_{2H}$  of FIGURE 3f, a corresponding leading edge of a clock pulse  $D_{2H}$  of FIGURE 6 from divider 55 of the frequency divider chain. Pulse generator 67 counts clock WRITE pulses of FIGURE 6, up to a number that is determined in accordance with the value of word  $G_{dwd}$ . Such counting begins, for example, with the occurrence of the leading edge of clock  $D_{2H}$  at time  $T_{2H}$  of FIGURE 3f. At the end of such counting, generator 67 generates, at time  $(T_{2H} + t_d)$ , the leading edge of pulse  $G_{dl}$  of FIGURE 6 that occurs at, for example, time  $t_4$  in the timing diagram of FIGURE 3h. The pulse width  $t_{DW}$  of each pulse  $G_{dl}$ , for example, is sufficiently long for enabling the reading-out of all the samples stored in the corresponding 1-H delay unit such as 1-H delay 437 of FIGURE 1.

During interval  $t_{DW}$  of FIGURE 3h of each pulse  $G_{dl}$ , AND gate 63 of FIGURE 6 couples output signal  $VC_g$  of VCO 62 to multiplexer 60 to provide the corresponding read-out clocking edges of signal  $G_{CK}$ . During the intervals in which signal  $G_{dl}$  is not asserted, signal  $VC_g$  of FIGURE 6 is blocked by AND gate 63.

In accordance with the invention, time ( $T_{2H} + t_d$ ), which is the sample read-out beginning time in a corresponding video line period, may be programmable on, for example, a line-to-line basis.

5 Alternatively, it may be programmable on a group of lines basis, with the delay being the same for all the lines within a given group.

In accordance with another aspect of the invention, the frequency of signal  $VC_g$  of, for example, VCO 62 is calibrated in an interval during which, for  
10 example, signal  $G_{CK}$  is not otherwise used by video apparatus 150 of FIGURE 1. Calibration of the frequency of signal  $VC_g$  of FIGURE 6 is accomplished by a phase detector 68, that compares the phase of signal  $VC_g$  with that of  
15 clock signal CL to provide a frequency control signal PH. The frequency of signal  $VC_g$  is controlled by calibrating word  $F_G$  of memory 59, as described below.

Signal PH is coupled to an input terminal of a sample-and-hold, or track-and-hold, unit 69 that, in  
20 regular and continuous operation of video apparatus 150 of FIGURE 1, samples signal PH of FIGURE 6, during, for example, the vertical retrace interval, and holds the sampled value until the next sampling period to provide a signal SH. The sampling time is controlled by vertical  
25 sync signal  $V_s$ . During the period in regular operation, when calibration does not take place, such as when Clock  $G_{CK}$  is required to provide the clocking signal to form clocks 230f - 230i, sample and hold unit 69 provides constant signal SH that was established by the value of  
30 signal PH at the end of the preceding calibration period. Both signal SH and word  $F_G$  control the frequency of signal  $VC_g$  of VCO 62. During calibration, word  $F_G$  of memory 59 is selected to contain a predetermined calibration value that, when VCO 62 is properly calibrated, should result in  
35 a corresponding predetermined expected frequency of signal  $VC_g$  for such value of word  $F_G$ . Such frequency may be different than the frequency of signal  $VC_g$  outside the calibration time. For example, such expected frequency

may be equal to that of clock CL. Any deviation from such expected frequency, is corrected by signal SH. This arrangement provides a single point correction in that correction of the frequency is performed for one value of word  $F_G$ .

It should be understood that a multiple point correction scheme may be used. In such a scheme, different values of signal SH may be obtained during a calibration interval by applying, during calibration, correspondingly different values of calibration words  $F_G$ , respectively. Such different values of signal SH may be separately stored for usage outside the calibration interval. In such multiple point correction scheme, the value of word  $F_G$  that is applied outside the calibration interval may be used for selecting the particular stored value of signal SH to be coupled to a control terminal of the oscillator for calibrating the oscillator outside the calibration interval.

Each of read-out clock generators 64' and 64" operates similarly to read-out clock generator 64 for producing the corresponding sample read-out clocks for units 433' and 433", respectively, of FIGURE 1. In a like manner, each of programmable pulse generators 67' and 67" of FIGURE 6 operates similarly to programmable pulse generator 67. Thus, signals  $G_{2H}$ ,  $R_{2H}$  and  $B_{2H}$  of FIGURE 1 may be separately controlled by clock signals  $G_{CK}$ ,  $R_{CK}$  and  $B_{CK}$ , respectively, of FIGURE 6 that may be generated, each, independently of the other two.

It should be understood that various other types of raster distortions, such as convergence error or east-west distortion, may be corrected by the arrangement of FIGURE 1. For example, convergence correction may be obtained by controlling clocks  $G_{CK}$ ,  $R_{CK}$  and  $B_{CK}$  separately and independently such that the pixels formed by the corresponding guns of the CRT appear at the proper location in the corresponding scan line so as to produce convergence on the CRT screen.



CLAIMS:

1. A display apparatus responsive to an incoming video signal for generating an output video signal coupled to a video display apparatus to provide information that is displayed in a plurality of display lines on said video display that form a raster during a given deflection cycle such that a distortion in said video display apparatus that is associated with the display of picture information derived from said incoming video signal in said raster is compensated by varying said output video signal, comprising:

a memory responsive to said incoming video signal for storing therein the picture information derived from said incoming video signal and for reading out therefrom the stored picture information to generate said output video signal that provides the stored picture information to said video display apparatus;

means for generating a correction signal that varies in accordance with said distortion in said video display apparatus;

a controlled oscillator for generating a first clock signal that is coupled to said memory to generate said output video signal at a rate that is determined in accordance with the frequency of said clock signal, said controlled oscillator being responsive, outside a calibration interval, to said correction signal for varying the frequency of said first clock signal in accordance with said correction signal; and

means for generating a calibration reference signal having a value during said calibration interval that is representative of a first operating frequency, wherein said controlled oscillator is responsive during said calibration interval to said calibration reference signal for providing calibration of the operation of said controlled oscillator during said calibration interval.



2. An apparatus according to Claim 1 wherein said calibrating means comprises means responsive to said first clock signal of said controlled oscillator and to said calibration reference signal for generating a control signal that varies, during said calibration interval, in accordance with a difference between the the frequency of said calibration reference signal and that of said first clock signal, said control signal being coupled to said controlled oscillator for establishing the frequency of said first clock signal, during said calibration interval, to be in accordance with that of said calibration reference signal, such that, outside said calibration interval, said control signal causes the varying frequency of said first clock signal to be calibrated.

3. An apparatus according to Claim 2 wherein said control signal generating means comprises a phase detector coupled to said controlled oscillator to form therewith a phase-lock-loop circuit during said calibration interval such that outside said calibration interval said second control signal is substantially constant.

4. An apparatus according to Claim 3 wherein said phase-lock-loop circuit comprises a sample-and-hold circuit having an input terminal that is coupled to an output terminal of said phase detector and an output terminal that is coupled to said controlled oscillator to form said control signal that calibrates the frequency of said clock signal, said sample-and-hold circuit generating said control signal during said calibration interval such that outside said calibration interval both said correction and control signals determine the frequency of said controlled oscillator.



5. An apparatus according to Claim 1 wherein said calibration interval occurs during a vertical retrace portion of said given deflection cycle.