

CURRENT SENSING DEVICES AND METHODS

5 Priority

This application claims priority to U.S. Patent Application Serial No. 12/684,056 filed January 7, 2010 of the same title, which is a continuation-in-part of and claims priority to U.S. Patent Application Serial No. 12/567,622 filed September 25, 2009 of the same title, which claims priority to U.S. Provisional Patent Application Serial No. 61/230,474 filed July 31, 2009 of the same title, each of which is incorporated herein by reference in its entirety.

Copyright

A portion of the disclosure of this patent document contains material that is
15 subject to copyright protection. The copyright owner has no objection to the facsimile
reproduction by anyone of the patent document or the patent disclosure, as it appears
in the Patent and Trademark Office patent files or records, but otherwise reserves all
copyright rights whatsoever.

20 1. Field of the Invention

The present invention relates generally to circuit elements and more particularly in one exemplary aspect to devices for the sensing of current, and methods of utilizing and manufacturing the same.

25 2. Description of Related Technology

A myriad of different configurations of current sensing devices are known in the prior art. One common approach to the manufacture of current sensing devices is via the use of a so-called "Rogowski coil". A Rogowski coil is an electrical device for measuring alternating current ("AC"). It typically consists of a helical coil of wire with the lead from one end returning through the center of the coil and passing through the helical coil of wire to the other end. The whole helical coil of wire is then positioned around an alternate current carrying conductor whose current is to be measured. The voltage that is induced in the coil is proportional to the rate of change

of current in the conductor such that the output of the Rogowski coil is indicative to the amount of current passing through the conductor.

Rogowski coils can be made open-ended and flexible, allowing it to be wrapped around a current carrying conductor without otherwise directly disturbing the current passing through that conductor. A Rogowski coil typically utilizes air, rather than a magnetically permeable core therefore giving the Rogowski coil the properties of possessing both a relatively low inductance along with response to relatively fast-changing currents. Furthermore, the output of a Rogowski coil is typically highly linear, even when subjected to large currents such as those used in electric power transmission, welding, or other pulsed power applications. In addition, properly constructed Rogowski coils are often also largely immune to electromagnetic interference, thereby making them resistant to outside tampering. However, due to the relatively complex winding configurations involved, prior art attempts at manufacturing Rogowski type coils have been labor intensive and expensive.

Numerous methodologies exist for producing Rogowski coils in the prior art, including for example, those disclosed in United States Patent No. 4,616,176 to Mercure, et al. issued October 7, 1986 and entitled "Dynamic current transducer"; United States Patent No. 5,414,400 to Gris, et al. issued May 9, 1995 and entitled "Rogowski coil"; United States Patent No. 5,442,280 to Baudart issued August 15, 1995 and entitled "Device for measuring an electrical current in a conductor using a Rogowski coil"; United States Patent No. 5,982,265 to Von Skarczinski, et al. issued November 9, 1999 and entitled "Current-detection coil for a current transformer"; United States Patent No. 6,094,044 to Kustera, et al. issued July 25, 2000 and entitled "AC current sensor having high accuracy and large bandwidth"; United States Patent No. 6,313,623 to Kojovic, et al. issued November 6, 2001 and entitled "High precision Rogowski coil"; United States Patent No. 6,614,218 to Ray issued September 2, 2003 and entitled "Current measuring device"; United States Patent No. 6,731,193 to Meier, et al. issued May 4, 2004 and entitled "Printed circuit board-based current sensor"; United States Patent No. 6,822,547 to Saito, et al. issued November 23, 2004 and entitled "Current transformer"; United States Patent No. 7,227,441 to Skendzic, et al. issued June 5, 2007 and entitled "Precision Rogowski coil and method for manufacturing same"; United States Patent No. 7,253,603 to Kovanko, et al. issued August 7, 2007 and entitled "Current sensor arrangement"; United States

Patent No. 7,538,541 to Kojovic issued May 26, 2009 and entitled "Split Rogowski coil current measuring device and methods"; United States Patent Pub. No. 20050248430 to Dupraz, et al. published November 10, 2005 and entitled "Current transformer with Rogowski type windings comprising an association of partial circuits forming a complete circuit"; United States Patent Pub. No. 20060220774 to Skendzic published October 5, 2006 and entitled "Precision printed circuit board based Rogowski coil and method for manufacturing same"; United States Patent Pub. No. 20070290695 to Mahon published December 20, 2007 and entitled "Method and Apparatus for Measuring Current"; United States Patent Pub. No. 20080007249 to Wilkerson; et al. published January 10, 2008 and entitled "Precision, Temperature-compensated, shielded current measurement device"; United States Patent Pub. No. 20080079418 to Rea; et al. published April 3, 2008 and entitled "High-precision Rogowski current transformer"; United States Patent Pub. No. 20080106253 to Kojovic published May 8, 2008 and entitled "Shielded Rogowski coil assembly and methods"; and United States Patent Pub. No. 20080211484 to HOWELL; et al. published September 4, 2008 and entitled "Flexible current transformer assembly".

Despite the broad variety of prior art current sensing configurations, there is a salient need for current sensing devices (including Rogowski coils) that both are low in cost to manufacture, such low cost being enabled by *inter alia* addressing the difficulties associated with the complex coil configurations of prior art current sensing devices, and offer improved or at least comparable electrical performance over prior art devices. Ideally such a solution would not only offer very low manufacturing cost and improved electrical performance for the current sensing device, but also provide a high level of consistency and reliability of performance by limiting opportunities for errors or other imperfections during manufacture of the device.

Moreover, an ideal solution would also be at least somewhat scalable, and able to assume various desired form factors.

Summary of the Invention

In a first aspect of the invention, an improved current sensing inductive device is disclosed. In one embodiment, the current sensing inductive device includes multiple ones of segmented winding elements. A return conductor electrically couples

a leading one of the segmented winding elements with a trailing one of the segmented winding elements.

In one embodiment, the segmented winding elements comprise segmented bobbin elements upon which a number of windings are disposed.

5 In another embodiment, the windings are effectively free-standing such that no bobbin or other internal support structure is required.

In a second aspect of the invention, an improved form-less current sensing inductive device is disclosed. In one embodiment, the inductive device includes multiple ones of form-less wound air coils. These air coils are then placed within
10 respective cavities located on an encapsulating header. A return conductor couples a leading one of the form-less coils with a trailing one of the form-less coils.

In a third aspect of the invention, a system apparatus that incorporates the aforementioned current sensing inductive devices is disclosed. In one embodiment, the system apparatus comprises a power distribution utility box that incorporates an
15 improved current sensing inductive device. The power distribution utility box includes a network interface that transmits data collected by the current sensing inductive device over a network to a device or location (e.g., centralized repository or control center) for monitoring, billing, and/or control applications.

In a fourth aspect of the invention, methods of manufacturing the
20 aforementioned device(s) are disclosed. In one embodiment, the method comprises continuously winding an insulated conductor over multiple segmented bobbin elements. A return conductor is routed between each of the segmented bobbin elements. The return conductor is then electrically coupled with the insulated conductor so as to form the current sensing inductive device.

25 In a fifth aspect of the invention, methods of using the aforementioned apparatus are disclosed.

In a sixth aspect of the invention, a scalable inductive device is disclosed. In one embodiment, the device comprises a number of winding segments, and the number of winding segments (and/or number of turns per segment) can be varied as desired so as to
30 achieve a desired tradeoff between higher performance and higher cost of manufacturing.

In a seventh aspect of the invention, a low cost and highly precise inductive device is disclosed. In one embodiment, a number of segments are used to effectively approximate a circular, continuous Rogowski coil device.

5 In an eighth aspect of the invention, a user-tunable multi-coil assembly is disclosed. In one embodiment, two or more segmented coils are stacked (i.e., in juxtaposed disposition with a common central axis), such that the angular disposition (rotation) of the coils around the common axis can be varied by an installer or end user, and/or the number of coils present can be changed. As the segments of one coil are placed in different position with respect to the segments of the other coil(s) (and/or the
10 number of coils increased or decreased), the output of the devices will vary, thereby allowing the installer/user to “tune” the effective output of the coil assembly to the desired level of performance.

In another embodiment, the two or more coils are substantially concentric with one another, such that they have different radii. Similarly, when the relative position of
15 the coils is changed (and/or number of coils varied), the output of the coils will vary as well, and can be tuned or adjusted to a desired level of performance.

Moreover, in yet another embodiment, the vertical spacing or disposition of the different coils (whether in “stacked” or “concentric” configuration) can be varied, thereby increasing/decreasing the coupling or interaction of the coils.

20 In a ninth aspect of the invention, a coil device having a conductor receiving insert is disclosed. In one embodiment, the device comprises a segmented coil of the type referenced above, which further includes a central portion adapted to orient and place one or more conductors being monitored at a prescribed location within the center region of the coil.

25 In a tenth aspect of the invention, a support structure for use with the aforementioned current sensing inductive devices is disclosed. In one embodiment, the support structure includes multiple ones of bobbin elements. At least a portion of the bobbin elements also include connection features that are utilized for joining a bobbin element to an adjacent bobbin element.

30 In an eleventh aspect of the invention, a bobbin element for use in the aforementioned current sensing inductive devices is disclosed. In one embodiment, the bobbin element includes a spool element which defines an interior volume and

further having an outer winding diameter associated with the spool element. A pair of flange features is also disposed on opposing ends of the spool element.

In a variant, at least one of the pair of flange features includes an electrically conductive clip disposed therein.

5 In yet another variant, the interior volume includes a return conductor support feature that positions a return conductor at a predetermined position with respect to the spool element.

Brief Description of the Drawings

10 The features, objectives, and advantages of the invention will become more apparent from the detailed description set forth below when taken in conjunction with the drawings, wherein:

FIG. 1 is a perspective view illustrating a first embodiment of a Rogowski coil device in accordance with the principles of the present invention.

15 FIG. 1A is a perspective view illustrating the Rogowski coil header of FIG. 1 in accordance with the principles of the present invention.

FIG. 1B is a perspective sectional view taken along line 1B–1B of FIG. 1A.

FIG. 1C is a perspective view illustrating a Rogowski coil formed by the segmented or continuous application of an adhesive in accordance with the principles
20 of the present invention.

FIG. 1D is a top elevation view illustrating a field installable Rogowski coil device with overlapping conductor ends in accordance with the principles of the Rogowski coil.

FIG. 1E is a top elevation view illustrating a field installable Rogowski coil device with abutting conductor ends in accordance with the principles of the
25 Rogowski coil.

FIG. 2 is a perspective view illustrating a portion of a second embodiment of a Rogowski coil device in accordance with the principles of the present invention.

FIG. 2A is a perspective sectional view taken along line 2A–2A of FIG. 2.

30 FIG. 2B is a perspective view of a single Rogowski coil segment, as illustrated in FIG. 2, in accordance with the principles of the present invention.

FIG. 2C is a perspective view of the single Rogowski coil segment illustrated in FIG. 2B, shown from a different perspective.

FIG. 3 is a perspective view illustrating a single Rogowski coil segment for a third embodiment of a Rogowski coil device in accordance with the principles of the present invention.

FIG. 3A is a side elevation view of the Rogowski coil segment illustrated in
5 FIG. 3.

FIG. 3B is a perspective view illustrating four (4) assembled Rogowski coil segments, as illustrated in FIG. 3, forming one-half of a Rogowski coil device in accordance with the principles of the present invention.

FIG. 3C is a perspective view illustrating the four (4) assembled Rogowski
10 coil segments of FIG. 3B mounted on a winding mandrel in accordance with the principles of the present invention.

FIG. 3D is a side elevation view of the winding mandrel mounted Rogowski coil segments shown in FIG. 3C.

FIG. 4 is a perspective view illustrating a single Rogowski coil segment for a
15 fourth embodiment of a Rogowski coil device in accordance with the principles of the present invention.

FIG. 4A is a perspective view illustrating two wound Rogowski coil segments, as illustrated in FIG. 4, mounted between two header segments in accordance with the principles of the present invention.

FIG. 4B is a perspective view illustrating eight (8) assembled Rogowski coil
20 segments of FIG. 4 mounted on a winding mandrel in accordance with the principles of the present invention.

FIG. 5 is a perspective view illustrating a single Rogowski coil segment for a
25 fifth embodiment of a Rogowski coil device in accordance with the principles of the present invention.

FIG. 5A is a side elevation view illustrating the single Rogowski coil element of FIG. 5.

FIG. 5B is a perspective view illustrating two Rogowski coil segments of FIG.
5 mountable together in accordance with the principles of the present invention.

FIG. 5C is a perspective view illustrating eight (8) assembled Rogowski coil
30 segments of FIG. 5 mounted on a winding mandrel in accordance with the principles of the present invention.

FIG. 6 is a perspective view illustrating a single Rogowski coil segment for a sixth embodiment of a Rogowski coil device in accordance with the principles of the present invention.

FIG. 6A is a side elevation view illustrating the single Rogowski coil element
5 of FIG. 6.

FIG. 6B is a perspective view illustrating two Rogowski coil segments of FIG. 6 mountable together in accordance with the principles of the present invention.

FIG. 6C is a perspective view illustrating another embodiment of a coil segment adapted to receive a peripheral cord, in accordance with the principles of the present invention.
10

FIG. 7 is a side elevation view illustrating various positions for the pass through conductor of a current sensing device in accordance with the principles of the present invention.

FIG. 8 is a top elevation view illustrating an alternate configuration for a Rogowski coil device positioned about a rectangular power conductor in accordance with the principles of the present invention.
15

FIG. 8A is a top elevation view illustrating a first exemplary embodiment of the Rogowski coil device of FIG. 8 with alignment features incorporated thereon to prevent skewing and biasing in accordance with the principles of the present invention.
20

FIG. 8B is a top elevation view of another embodiment of the sensing device of the invention, adapted for use on a 4-sided (e.g., rectangular) bus bar (with cover removed).

FIG. 8B-1 is a cross-section of the device of FIG. 8B, taken along line 8B-1-8B-1, with cover installed.
25

FIG. 9 is a side elevation view illustrating an alternate configuration for a Rogowski coil device in accordance with the principles of the present invention.

FIG. 10 is a process flow diagram for manufacturing the current sensing apparatus of FIGS. 1 – 1B in accordance with the principles of the present invention.

FIG. 11 is a process flow diagram for manufacturing the current sensing apparatus of FIGS. 2 – 2C and FIGS. 4 – 4B in accordance with the principles of the present invention.
30

FIG. 12 is a process flow diagram for manufacturing the current sensing apparatus of FIGS. 3 – 3D in accordance with the principles of the present invention.

FIG. 13 is a process flow diagram for manufacturing the current sensing apparatus of FIGS. 5 – 5C in accordance with the principles of the present invention.

5 FIG. 14 is a process flow diagram for manufacturing the current sensing apparatus of FIGS. 6 – 6B in accordance with the principles of the present invention.

FIG. 15A is a perspective view of an exemplary stacked Rogowski coil device in accordance with the principles of the present invention.

10 FIG. 15B is a top elevation view of the stacked Rogowski coil device of FIG. 15A.

FIG. 15C is a perspective view of a tunable implementation of the stacked Rogowski coil device of FIG. 15A.

15 FIG. 15D is a perspective section view of a second exemplary embodiment of a tunable stacked Rogowski coil device in accordance with the principles of the present invention.

FIG. 15E is a top elevation view of a concentrically stacked Rogowski coil device in accordance with the principles of the present invention.

FIG. 16 is a perspective view illustrating a portion of a seventh embodiment of a Rogowski coil segment in accordance with the principles of the present invention.

20 FIG. 16A is a perspective view illustrating the Rogowski coil segment of FIG. 16, linked together with other like segments to form a Rogowski coil device.

FIG. 16B is a perspective view of an exploded view of the seventh embodiment of a Rogowski coil device and housing.

FIG. 16C is a sectional view taken along line 16C–16C of FIG. 16B.

25 FIG. 16D is a top elevation view of the bottom housing portion associated with the Rogowski coil device illustrated in FIG. 16B.

FIG. 17 is a perspective view illustrating an eighth embodiment of a Rogowski coil segment in accordance with the principles of the present invention.

30 FIG. 17A is a perspective view illustrating the Rogowski coil segment of FIG. 17 linked together with other like segments to form a Rogowski coil device.

FIG. 17B is a sectional view taken along line 17B–17B of FIG. 17A.

FIG. 18A is a perspective view illustrating the insertion of the start clip for a Rogowski coil segment in accordance with one embodiment of the present invention.

FIG. 18B is a perspective view illustrating the insertion of the end clip for a Rogowski coil segment in accordance with one embodiment of the present invention.

FIG. 18C is a perspective view illustrating the insertion of the Rogowski coil segments onto a winding mandrel in accordance with one embodiment of the present invention.

FIG. 18D is a perspective view illustrating the installation of the core assembly into the bobbin segment grooves in accordance with one embodiment of the present invention.

FIG. 18E is a perspective view illustrating the start of one embodiment of the winding process in accordance with the principles of the present invention.

FIG. 18F is a cross sectional view illustrating layered windings disposed on the first Rogowski coil segment in accordance with one embodiment of the present invention.

FIG. 18G is a perspective view illustrating the passage of the winding between Rogowski coil segments in accordance with one embodiment of the present invention.

FIG. 18H is a perspective view of the Rogowski coil segments mounted on the winding mandrel and wound in accordance with one embodiment of the present invention.

FIG. 18I is a perspective view illustrating the termination of the winding to the start clip in accordance with one embodiment of the present invention.

FIG. 18J is a cross sectional view illustrating the shielding layer windings on a first Rogowski coil segment in accordance with one embodiment of the present invention.

FIG. 18K is a perspective view of the Rogowski coil segments mounted on the winding mandrel and wound with the shielding layer in accordance with one embodiment of the present invention.

FIG. 18L is a perspective view illustrating the winding of a tape layer over the shielding layer of windings in accordance with one embodiment of the present invention.

FIG. 18M is a perspective view illustrating the termination of the windings to the end clip in accordance with one embodiment of the present invention.

FIG. 18N is a perspective view illustrating the insertion of the return conductor in accordance with one embodiment of the present invention.

FIG. 18O is a perspective view illustrating the insertion of the finish wire conductor in accordance with one embodiment of the present invention.

FIG. 18P is a top elevation view illustrating the insertion of the Rogowski coil segments into the header in accordance with one embodiment of the present invention.

5 FIG. 18Q is a perspective view illustrating the installation of the wire conductors in the Rogowski header in accordance with one embodiment of the present invention.

10 FIG. 18R is a perspective view illustrating the deposit of epoxy into the top header of the Rogowski device in accordance with one embodiment of the present invention.

FIG. 18S is a perspective view illustrating the Rogowski coil device manufactured using the process illustrated in FIGS. 18A – 18R.

All Figures disclosed herein are © Copyright 2009-2010 Pulse Engineering, Inc. All rights reserved.

15 Detailed Description of the Preferred Embodiment

Reference is now made to the drawings wherein like numerals refer to like parts throughout.

20 As used herein, the terms “bobbin” and “form” (or “former”) are used without limitation to refer to any structure or component(s) disposed on or within or as part of an inductive device which helps form or maintain one or more windings of the device.

25 As used herein, the terms “electrical component” and “electronic component” are used interchangeably and refer to components adapted to provide some electrical and/or signal conditioning function, including without limitation inductive reactors (“choke coils”), transformers, filters, transistors, gapped core toroids, inductors (coupled or otherwise), capacitors, resistors, operational amplifiers, and diodes, whether discrete components or integrated circuits, whether alone or in combination.

As used herein, the term “inductive device” refers to any device using or implementing induction including, without limitation, inductors, transformers, and inductive reactors (or “choke coils”).

30 As used herein, the terms “network” and “bearer network” refer generally to any type of data, telecommunications or other network including, without limitation, data networks (including MANs, PANs, WANs, LANs, WLANs, micronets, piconets, internets, and intranets), hybrid fiber coax (HFC) networks, satellite networks, cellular

networks, and telco networks. Such networks or portions thereof may utilize any one or more different topologies (e.g., ring, bus, star, loop, etc.), transmission media (e.g., wired/RF cable, RF wireless, millimeter wave, optical, etc.) and/or communications or networking protocols (e.g., SONET, DOCSIS, IEEE Std. 802.3, 802.11, ATM, X.25, 5 Frame Relay, 3GPP, 3GPP2, WAP, SIP, UDP, FTP, RTP/RTCP, H.323, etc.).

As used herein, the terms “network interface” or “interface” typically refer to any signal, data, or software interface with a component, network or process including, without limitation, those of the FireWire (e.g., FW400, FW800, etc.), USB (e.g., USB2, USB 3.0, USB On-the-Go, etc.), Ethernet (e.g., 10/100, 10/100/1000 10 (Gigabit Ethernet), 10-Gig-E, etc.), MoCA, optical (e.g., PON, DWDM, etc.), Serial ATA (e.g., SATA, e-SATA, SATAII), Ultra-ATA/DMA, Coaxsys (e.g., TVnet™), radio frequency tuner (e.g., in-band or OOB, cable modem, etc.), WiFi (802.11a,b,g,n), WiMAX (802.16), PAN (802.15), IrDA, or other wireless families.

As used herein, the term “signal conditioning” or “conditioning” shall be 15 understood to include, but not be limited to, signal voltage transformation, filtering and noise mitigation, signal splitting, impedance control and correction, current limiting, capacitance control, and time delay.

As used herein, the terms “top”, “bottom”, “side”, “up”, “down” and the like merely connote a relative position or geometry of one component to another, and in no 20 way connote an absolute frame of reference or any required orientation. For example, a “top” portion of a component may actually reside below a “bottom” portion when the component is mounted to another device (e.g., to the underside of a PCB).

As used herein, the term “wireless” means any wireless signal, data, communication, or other interface including without limitation Wi-Fi, Bluetooth, 3G 25 (e.g., 3GPP, 3GPP2, and UMTS), HSDPA/HSUPA, TDMA, CDMA (e.g., IS-95A, WCDMA, etc.), FHSS, DSSS, GSM, PAN/802.15, WiMAX (802.16), 802.20, narrowband/FDMA, OFDM, PCS/DCS, analog cellular, CDPD, satellite systems, millimeter wave or microwave systems, optical, acoustic, and infrared (i.e., IrDA).

30 *Overview*

The present invention provides, *inter alia*, improved low cost current sensing apparatus and methods for manufacturing, and utilizing the same. In one embodiment, the current sensing apparatus are formed in segments that are, in exemplary

embodiments, generally linear in nature so as to facilitate the winding of the apparatus. The formed segments are subsequently positioned into complex geometries, such as circular, polygonal, or elliptical torus/toroidal like geometries. While torus geometries are common, the formed segments can be adapted for use with
5 a wide variety of geometries in which the conductors they are formed around are irregular in nature. In addition to substantially fixed forms, additional embodiments disclosed herein are also suitable for flexible assemblies.

The aforementioned "segmented" coil approach advantageously allows for the control of cost of manufacturing the device to be balanced against the required
10 performance or precision level. As greater precision is required for a given application, a greater number of segments (and/or greater number of turns per segment) can be employed, which also generally corresponds to greater cost of manufacture. In low-precision applications, a lower-precision device with fewer segments and/or turns can be utilized, thereby providing the lowest possible cost for
15 the required level of precision.

In one exemplary implementation, the segments are formed from bobbin elements with features and/or geometries that advantageously facilitate their assembly into the final completed current sensing apparatus. These bobbin elements include one or more of hinged couplings, alignment features, molded flexible webbing, etc. in
20 order to facilitate assembly. In an alternative embodiment, the segments are formed from self-supporting bonded wire windings which are subsequently placed into a protective header element. One or more return conductor(s) or pass through conductor(s) is/are also utilized which is electrically coupled to the windings to form the current sensing apparatus.

25 In addition, some embodiments disclosed herein include an insert-molded or post-inserted conductive clip which may be utilized not only for wire wrapping (i.e., in order to secure the windings prior to being wound onto the bobbin elements), but also for electrically coupling external lead wires to the bobbin element windings, thus facilitating the electrical connections needed to form a Rogowski coil device. Bosses
30 formed on the outer flanges of the bobbin elements are also disclosed for use in some embodiments. These bosses are included with corresponding paired holes to provide alignment and stability during winding operations.

In exemplary embodiments of the device, the header and/or bobbin elements are formed with features that are advantageously incorporated into the geometry of the device so as to support and accurately position the return conductor(s) with respect to the windings on the device. The positioning of the return conductor can be weighed
5 against both performance considerations and manufacturing considerations in order to provide a high performance and low-cost current sensing apparatus. The positioning of the conductor can even be variable in nature; e.g., through a structure which supports multiple different positions of the conductor(s).

“Free space” or “formless” embodiments of the device are also disclosed,
10 wherein the turns of the winding(s) (and the segments themselves) are formed and used without a bobbin or other supporting structure. In one variant, so-called “bonded” wire is used, wherein the individual turns of the winding are selectively bonded to one another (e.g., via a thermally activated adhesive or other substance) so as to maintain the turns in a desired position and orientation relative to one another,
15 thereby obviating the bobbin and reducing manufacturing cost. In another variant, the windings (and center conductor) are encapsulated in a polymer or other encapsulating compound which “pots” the windings and conductor in relative position, and adds mechanical stability and rigidity.

“Tunable” embodiments are also envisioned that place two (2) or more of the
20 aforementioned current sensing apparatus adjacent to one another in order to correct for segment-related electrical performance deficiencies, and/or allow for selective tuning of the coil performance by a user or installer. In one embodiment, two or more coils are arranged in a stacked or juxtaposed orientation, and placed relative to one another so as to cancel out or mitigate flux leakage associated with the gaps between
25 coil segments. In another variant, the two or more coils are substantially concentric.

Detailed Description of Exemplary Embodiments

Detailed descriptions of the various embodiments and variants of the apparatus and methods of the invention are now provided. While primarily discussed in the
30 context of current sensing devices, and in particular in one embodiment to current sensing devices that operate according to the Rogowski principle, the various apparatus and methodologies discussed herein are not so limited. In fact, many of the apparatus and methodologies described herein are useful in the manufacture of any

number of complex coil configurations (such as wound torus shapes) that can benefit from the segmented manufacturing methodologies and apparatus described herein, including devices that do not utilize or need a pass through or return conductor.

In addition, it is further appreciated that certain features discussed with respect to specific embodiments can, in many instances, be readily adapted for use in one or more other contemplated embodiments that are described herein. It would be readily appreciated by one of ordinary skill, given the present disclosure that many of the features described herein possess broader usefulness outside of the specific examples and implementations with which they are described.

10 Rogowski Coil Principles –

In order to better understand various design considerations in implementing the methodologies for the manufacture of exemplary coils as described subsequently herein, it is useful to understand the underlying principles that govern the behavior of a Rogowski-type coil. As is well understood in the electronic arts, the voltage produced by a Rogowski coil is driven by Equation (1) below:

$$\text{Equation (1)} \quad V = \frac{-AN\mu_0}{l} \frac{dI}{dt}$$

Where:

A = the area of one of the small loops;

N = the number of turns;

20 l = is the length of the winding;

μ_0 = a magnetic constant; and

dI/dt = is the rate of change of the current in the loop.

In order for a real-life implementation to operate closer to the theoretical behavior set forth in Equation (1), various assumptions are made including that the turns are evenly spaced, and that the radius of the device is comparatively large as compared with the radius of the turns themselves. Accordingly, these assumptions and how they affect the sensitivity of the Rogowski coil itself should be kept in mind in the subsequent discussion of various coil devices as set forth below.

Current Sensing Apparatus –

Referring now to FIGS. 1 – 1B, a first embodiment of a current sensing apparatus 100 is shown and described in detail. Specifically a Rogowski-type current sensing apparatus is illustrated in the embodiment of FIGS. 1 – 1B. FIG. 1 illustrates the main elements associated with the current sensing apparatus including a wound coil 102, a pass through or return conductor 104 and a segmented header 110.

As can be seen in FIG. 1, a first salient advantage of this device 100 over other prior art Rogowski coils is readily apparent. Specifically, typical prior art Rogowski coils emphasized a uniform distribution of coil windings throughout the entire loop of the device, which was largely believed to be necessary in order to achieve adequate electrical performance for the device. However, it has been discovered by the Assignee hereof that such prior art construction is not only difficult to manufacture (resulting in relatively high selling prices for the device), but also not necessary in order to achieve a desired level of electrical performance for the device. Rather, by segmenting the current sensing apparatus 100 into multiple substantially uniformly wound coil segments 102, the underlying device is not only easier to manufacture, but provides similar or improved electrical performance over traditional Rogowski coil devices.

In an exemplary embodiment, the coil segments 102 are wound on a linear mandrel using a bonded wire winding. Moreover, a regular insulated wire may also be used in conjunction with a bonding/gluing process. Bonded wire is a well-established product/process that is used to produce so-called “air coils”. Air coils themselves are inductors, and have been conventionally used in RFID tags, voice coils, sensors, and the like. The materials and manufacturing equipment for producing bonded wire are commercially available from a variety of sources known to the artisan of ordinary skill. Bonded wire is essentially an enamel-coated wire having additional coating applied (by either the wire vendor or the device manufacturer) to the outer surfaces of the enamel. Generally, during winding, the bonded wire coating may be activated (normally by heat, although other types of processes including radiation flux, chemical agents, and so forth) to cause the coated wires to stick/bond together. This approach provides certain benefits and cost economies in the context of electronic component production. By using bonded wire, the coil segment 102 itself becomes a self supporting structure. The use of bonded wire generally is well known, and its use in

constructing inductive devices is described in detail at, for example, co-owned U.S. Patent Application Serial No. 10/885,868 filed July 6, 2004 and entitled "Form-less Electronic Device and Methods of Manufacturing", the contents of which are incorporated herein by reference in its entirety.

5 The device 100 of FIG. 1 illustrates only a single coil segment 102 installed in the segmented header 110, although it is appreciated that the device 100 is intended to operate with eight (8) coil segments as illustrated. Furthermore, while eight (8) coil segments are shown, it is appreciated that more or less segments can be added depending largely on the overall size of the current sensing apparatus 100 and its
10 desired shape/profile. The ability to modify the number of coil segments provides a distinct competitive advantage over prior art methods of manufacturing current sensing apparatus. Specifically, as the number of coil segments increases (i.e. advances towards a theoretic infinite amount of segments), the behavior of the current sensing apparatus will tend to perform more like an ideal coil, however this is at the
15 expense of manufacturing complexity and cost. Conversely however, the number of segments can also be decreased until a minimum acceptable level of electrical performance has been achieved, thereby minimizing manufacturing complexity as well as manufacturing cost.

 Referring now to FIGS. 1A and 1B, the construction of the exemplary
20 embodiment of the segmented header 110 is more easily seen. The segmented header 110, in the illustrated embodiment, comprises eight (8) cavities 112, each associated with individual ones of the coil segments 102. Preferably, the segmented header 110 is constructed from an injection molded polymer material, although other construction materials including without limitation composites, fibrous materials (e.g., paper) and
25 combinations of the foregoing as well as alternative methodologies (e.g., transfer molding or assembly/adhesive processes) would be readily apparent to one of ordinary skill given the present disclosure. In exemplary embodiments, multiple ones of pass through conductor retaining features 114 are positioned at multiple points along the segmented header, and between adjacent cavities 112 and are utilized to retain the
30 pass through conductor (or conductors) 104 (FIG. 1) at a desired location with respect to the positioned coil segments 102. The retaining features 114, in the illustrated embodiment, position the pass through conductor(s) 104 along the longitudinal axis of each of the coil segments, although it is recognized that the positioning of the pass

through conductor(s) may be varied (and in the case where multiple conductors may be used, may actually occupy different positions within the segments). See, for example, the discussion of FIG. 7 subsequently herein. In addition, post features 116 provide a place for the wire-wrapping of interconnection wires between segments.

5 While, the current sensing apparatus illustrated in FIGS. 1 – 1B is specifically adapted for applications in which the conductor from which the current will be ultimately sensed is capable of being passed through the center portion the apparatus 100, it is recognized that the segmented header can be manufactured such that it is not a static uniform structure. For example, it is recognized that the apparatus 100 could
10 be hinged such that segmented header 110 is capable of being wrapped around the current carrying conductor for purposes of installation, or to permit measurement/testing by an operator/installer in the field. Furthermore, a hinged segmented header could also be readily adapted so that the flexible nature of the header operates in more than just a single rotational degree of freedom. For example,
15 the segmented header could not only be adapted so as to permit the enclosed loop of the device to be opened and closed but also allowed to pivot and twist so as to facilitate the ability for the segmented header to be accommodated into any number of difficult installation locations in the field.

 The opposing end (i.e. the portion that is not hinged) could then further be
20 adapted with a retaining mechanism (such as a snap and the like) that retains the hinged apparatus in its closed form. It is further recognized that this can be accomplished without hinges (e.g. via the use of dowels, snaps, the tension of the pass through conductor, etc.) or via the segmentation of the header 110 into two or more separable or movable portions depending on the needs of the system in which the
25 apparatus will be ultimately installed. The separable or movable segmented embodiment of the current sensing apparatus 100 described in FIGS. 1 – 1B is also recognized to be equally applicable to the other current sensing apparatus embodiments described subsequently herein.

 It should also be noted that the header 110 is, in certain applications, readily
30 modified to facilitate the mounting of the current sensing apparatus onto an external substrate (whether via surface mount or through-hole applications). For example, in through hole applications, the header 110 incorporates apertures (not shown) which hold and position the ends of the conductors used in the current sensing apparatus at a

predetermined spacing. These conductors are preferably formed from a conductive wire of sufficient thickness that deformation of the wire prior to installation is unlikely. In surface mount applications, the header is readily adapted with two or more conductive areas. These conductive areas can either be formed from discrete metallic plates that are attached to the header or alternatively, incorporated via any number of well known polymer plating processes. The ends of the conductors can then be electrically coupled to the conductive areas via soldering, resistive welding, etc., so as to form an electrical connection between the current sensing apparatus windings and the conductive areas to be mounted on an external substrate via a surface mounting process.

The current sensing apparatus (whether static or otherwise) can also optionally be encased in a clamshell cover or otherwise encapsulated/molded/over-molded, etc. to protect against dirt and debris as well as provide enhanced resistance to high voltages from, for example, the conductor that is being measured by the current sensing apparatus. In addition, it has been found that in certain implementations, the performance of the current sensing apparatus is extremely sensitive to deformations to the coil segments 102. Accordingly, by encasing the current sensing apparatus in a clamshell cover or otherwise encapsulating the windings, the performance of the current sensing apparatus can be protected at a relatively inexpensive cost to the end customer. In addition to static embodiments (i.e. where the encased apparatus 100 is substantially rigid), it is recognized that flexible embodiments can be readily implemented by using an encasement that is flexible. Such a flexible device is, in an exemplary variant, formed by utilizing a rubberized shrink tubing disposed about at least portions of the header 110.

Referring now to FIG. 1C, an alternative embodiment of the current sensing apparatus illustrated in FIGS. 1 – 1B is shown and described in detail. Specifically, the embodiment of FIG. 1C illustrates a continuously constructed helical coil for use with or without a header or bobbin element as illustrated in FIG. 1. The current sensing apparatus 180 of FIG. 1C is effectively divided into segments 102 via use of a bead of adhesive 120 disposed e.g., on the inner circumference of the coil. Depending on the particular application, the types of adhesive utilized can vary widely. For example, where some flexibility is desired within individual segments 102, a flexible adhesive (such as silicone) is used to allow some movement between individual turns

of wire within a segment 102. Alternatively, where flexibility is not desired, a harder adhesive, such as a two-part epoxy, is used to limit the amount of movement between individual turns of wire within a segment.

In the embodiment illustrated, the current sensing apparatus is formed on a
5 mandrel in one continuous winding. The adhesive is then placed in segmented portions 102 on the inner diameter of the finished current sensing apparatus using an auto-dispensing apparatus, thereby substantially automating the manufacture of the current sensing apparatus. Note also that the return conductor (not shown) is routed in the interior of the coil prior to winding. Although the adhesive is primarily envisioned
10 as being placed on the inner diameter of the finished current sensing apparatus, it is recognized that alternative embodiments could readily place the adhesive anywhere else on the windings (such as the outer diameter) and even at multiple locations on the windings (to further secure and minimize movement between adjacent windings in any given segment). In addition, while the adhesive is primarily envisioned as being
15 disposed onto the windings in discrete segments, it is recognized that the bead of adhesive placed on the windings can be continuously applied along the length of the windings, especially in cases where the adhesive used cures in a flexible form.

Advantageously, the foregoing process also lends itself to mass, parallel manufacturing operations. For instance, one long mandrel can be used, with the
20 segments for many coils being formed (and cured if applicable) thereon, with the foregoing adhesive being applied rapidly in one movement down the mandrel. The individual coils can then be severed on the mandrel (or after removal of the entire assembly from the mandrel if desired), and the individual severed coils formed into the desired shape (e.g., substantially circular or polygonal) and terminated. Similarly,
25 multiple such mandrels can be processed in parallel, up to the limitations of the manufacturing equipment. Such mass manufacturing provides yet additional economies of scale over those afforded by the coil design alone.

The device of FIG. 1C can also be encapsulated within a host compound if desired (e.g., potting compound, silicone, etc.) such that its mechanical rigidity is
30 substantially maintained, at least in the critical dimensions. Specifically, it has been recognized by the inventor(s) hereof that the coils described herein may in many cases be sensitive (in terms of degradation in performance) to changes in the cross-sectional area or profile of the turns of each segment. For instance, if the coils of the segments

in the device of FIG. 1C were crushed or distorted, the accuracy of the device as a whole can degrade significantly. This dimension is more important than, for example, maintaining the “circularity” of the device as a whole, as well as maintaining the conductor(s) being monitored within the geometric center of the coil/polygon, the device advantageously being largely tolerant to the latter. Accordingly, the mechanical stability of at least the cross-sectional area of the coil turns is a salient consideration in many applications. Whether such stability is maintained via use of a hard or rigid exterior “shell” (e.g., a case, or alternatively a sleeve or other such arrangement which enshrouds the exterior of the coil), or via encapsulation, or via internal support such as a bobbin or header is largely a design choice.

FIG. 1D illustrates a top down view of a current sensing apparatus 100 as illustrated in, for example, FIG. 1C that does not possess a header element as illustrated in FIGS. 1 – 1B. Specifically, FIG. 1D illustrates a first exemplary way of making the current sensing apparatus field-installable around a conductor (without necessitating the removal of the conductor from the device to which the conductor is attached). The current sensing apparatus illustrated in FIG. 1D possesses an overlapping end 185 that can be routed around a conductor. The overlapping end can then be attached via an adhesive and the like to the other “end” of the coil. In this fashion, the free ends of the coil device can be routed around the extant conductor installation, and the two ends overlapped and secured in place, thereby forming an effectively unbroken loop. While it will be appreciated that such an “overlapping” configuration has less precision than a comparable “unbroken” device (e.g., one with no ends *per se*, but rather made as a continuous loop), it also affords the aforementioned capability of field installation without disassembly, and also very low manufacturing cost (as described in greater detail below).

It is noted that while the device of FIG. 1D illustrates the two ends of the coil overlapping in the vertical plane (i.e., normal to the plane of the Figure), the overlapping ends may overlap radially, while maintaining a “flat” vertical profile (i.e., one end being disposed at a radius smaller than that of the other end).

The two free ends of the device of FIG. 1C can be joined using any number of different techniques, including (without limitation): (1) merely utilizing the existing rigidity or malleability of the coil device if applicable to maintain the two ends in the desired proximate relationship (i.e., “bending” the device into shape); (2) an adhesive

to bond the two ends; (3) a section of shrink tubing (e.g., shrinks when heated) of the type well known in the electrical and environmental sealing arts; (4) a plastic or other tie-wrap; (5) using tape (e.g., electrical or duct tape); or (6) a molded or formed snap-fit assembly disposed on the two respective ends. Each of the foregoing (to varying
5 degrees) provides the benefit of very low cost, especially when used in conjunction with the cost-effective forming techniques for the device itself.

FIG. 1E illustrates an alternative field-installable embodiment of the device, in which the free ends of the current sensing apparatus 100 abut one another at 190. The embodiment of FIG. 1E is anticipated to be higher in cost to manufacture than that
10 shown in FIG. 1D, but provides better electrical/magnetic performance (precision) over the previous embodiment illustrated in FIG. 1C, due largely to the fact that the abutted ends effectively allow the coil to be nearly "perfect" in shape, and obviate any overlap (which causes magnetic distortions and leakage). The ends of the current sensing apparatus can be abutted using any number of assembly techniques including,
15 without limitation: (1) a locating pin coupling; (2) a magnetic coupling; (3) a screw-on coupling; (4) a shrink tube coupling; and (5) a snap/pivot type coupling. With regards to the use of a magnetic coupling, it should be noted that the use of magnet does not influence a change in the current to be measured (i.e. dI/dt) and accordingly, advantageously does not affect the electrical performance capabilities of the device.
20 The embodiment of FIG. 1D is somewhat more costly to manufacture than that of FIG. 1C (due in large part to the cost of the abutting requirement for the coupling), yet also provides greater precision.

It will also be recognized that the embodiments of FIGS. 1D and 1E may be fashioned so as to be flexible in multiple dimensions. For instance, in one variant, the
25 coil ends can be pulled apart somewhat (so as to permit wrapping around an installed conductor or bus bar) due to the flexibility of the coil (particularly, the gaps between segments), yet also varied vertically with respect to one another (i.e., maintain the same radius, yet move relative to one another as torsional forces are applied to both ends). In another variant, only a prescribed portion of the coil (e.g., a "hinge" region;
30 not shown) is permitted to flex significantly. This can be accomplished in any number of different ways, such as by using a thinner covering material, or actual mechanical hinge, in the hinge region, so that it flexes preferentially in that region.

Referring now to FIGS. 2 – 2C, a second exemplary embodiment of a header- or bobbin-based current sensing apparatus 200 is shown and described in detail. Specifically, the current sensing apparatus 200 of FIGS. 2 – 2C comprise multiple ones of segmented bobbin elements 210. Each of these bobbin elements 210 is disposed next to one another via an optionally hinged coupling 220. In one exemplary embodiment, this hinged coupling 220 includes features (such as snaps and the like) which retain adjacent segmented bobbin elements so that they remain attached to one another, however it is recognized that in alternative embodiments the hinged coupling may provide only a pivoting, as opposed to a pivoting and retaining function. In an alternative embodiment, the hinged coupling may be accomplished by molding a thin web of connecting material between adjacent ones of bobbin elements 210. Such a configuration could be made static (such as for use in embodiments in which the final application geometry is known) or flexible as described previously herein. The coupling may also be made frangible; i.e., severable after a limited number of loading cycles, if desired, so as to facilitate selective separation of the components.

Referring now to FIGS. 2 and 2A, a partial segment of a current sensing apparatus 200 is shown. Specifically, only a forty-five degree (45°) segment of a three-hundred sixty degree (360°) apparatus 200 is illustrated. Accordingly, as can be seen in the illustrated embodiment, the complete apparatus 200 would consist of eight (8) segmented bobbin elements 210. While eight elements are contemplated, this number is arbitrarily defined by the underlying geometry of the current sensing apparatus application as well as defined performance parameters. Hence, it is readily recognized that more or less elements or elements of different shapes or configurations (including also heterogeneous “mixes” of two or more different bobbin element configurations) could be utilized in alternative embodiments.

The embodiment illustrated in FIGS. 2 – 2C also includes a central passageway 230 that is intended to position the pass through conductor at a precise location within each of the segmented bobbin elements. In the illustrated configuration, the passageway is positioned along the longitudinal axis (i.e., the geometrical center) of each of the cylindrical bobbin elements 210; however, as noted elsewhere herein, the position of the central conductor(s) may be (i) non-symmetrical with respect to the cross-section of passageway 230 or bobbin element; (ii) may be variable or changeable; and/or (iii) may reside at other locations.

FIGS. 2B and 2C illustrate differing perspective views of a single segmented bobbin element 210 according to one embodiment. The bobbin element 210 is characterized by a winding channel 212 adapted for receiving one or more layers of windings, while flanges 218 retain the windings in the winding channel 212 resulting in a uniform distribution of the windings within the bobbin element 210. While the winding channel is illustrated with a smooth winding barrel, it is appreciated that grooves could be formed into the winding barrel in order to provide additional features to guide the windings so that they are wound more uniformly. Moreover, the cross-section of this "barrel" need not be symmetric, and/or can also include segmentation (i.e., may comprise an octagon, ellipse, polygon, etc. in cross-section).

Positioned on opposing ends of the flanges are alignment posts 216 positioned above standoffs 240. These alignment posts 216 are optional but are utilized to facilitate individual placement of the bobbin elements 210 within an encapsulating header (see for example FIG. 4A, 460 described subsequently herein). Routing posts 214 are utilized for facilitating the routing of the windings between individual ones of bobbin elements 210 during automated winding on a mandrel as will be discussed more fully subsequently herein. These routing posts 214 act as entry/exit points for the wire wound within the winding channel 212.

Recall the discussion of the hinged coupling 220 with regards to FIG. 2A. As can be seen in FIGS. 2B and 2C, the hinged coupling comprises a protruding portion 222 and a respective receptacle portion 224 which is sized so as to accommodate the protruding portion from an adjacent bobbin element 210. Routing channel 232 can also optionally be utilized to route the exit wire of the last segment to the return wire inside the coil. Note that in the illustrated embodiment the hinged coupling 220 does not include elements that allow adjacent elements 210 to remain movably coupled to one another. Rather, the tension associated with the respective windings and pass through conductor is actually used to retain the assembled current sensing device in its finished torus-like shape. However, it is recognized that alternative embodiments may readily include features that physically couple adjacent elements 210 to one another, use adhesives or other bonding agents, etc.

Referring now to FIGS. 3 – 3D, yet another embodiment for a Rogowski-type current sensing device 350 is illustrated. FIG. 3 illustrates a single bobbin element 300, of which eight (8) are required (for the illustrated embodiment) to create a single

current sensing device 350. It is recognized that more or less bobbin elements, those of heterogeneous configuration, etc. could be utilized in alternative embodiments as discussed previously with respect to other embodiments. Unlike the bobbin element 210 of FIGS. 2 – 2C, the bobbin element 300 of FIG. 3 does not necessitate a hinged coupling. Instead, the bobbin element 300 of FIG. 3 is constructed so that they collectively form the torus-like structure of the current sensing device 350 when bobbin elements 300 are placed adjacent to one another. See for example, FIG. 3B which shows exactly one half (i.e. four (4) bobbin elements) of the current sensing device 350. Each bobbin element includes a winding channel 310, which is defined by respective flange elements 330. These flange elements maintain and define the winding width for the winding channel 310. The bobbin element 300 further comprises routing posts 312 which again are utilized as exit/entry points for the winding as they exit and enter the winding channel 310. In addition, these exit/entry points can also be used to anchor the pass through or return conductor prior to winding. Optional pass through conductor routing channels 314 are included adjacent to the routing posts 312. The routing channels 314 are adapted to accommodate one or more pass through conductors underneath the windings placed within winding channel 310. Accordingly, the pass through conductor which is routed through channel 315 advantageously helps to maintain the structural integrity of the assembled device 350 when assembled, via tension applied to the pass through conductor (not shown).

In an alternative embodiment, the pass through conductor can instead be routed through the center cavity 320 (i.e., along the inner diameter of the center cavity). Furthermore, the bobbin element 300 could be readily be adapted to accommodate through a central passageway constructed within the center cavity 320 (similar to that shown in FIG. 2B, 230). These and other embodiments would be readily apparent to one of ordinary skill in the art given the present disclosure.

FIG. 3A illustrates a side elevation view of the bobbin element 300 shown in FIG. 3. Specifically, as can be seen in FIG. 3A, despite the curved geometry of the bobbin element 300, center cavity 320 passes, in the illustrated embodiment, in a straight line through the body of the bobbin element. This facilitates the automated winding of the bobbin element (see e.g., FIGS. 3C – 3D). Keyed notch 322 also passes linearly along the inside wall of the center cavity 320, thereby providing a feature that

can be received within a respective slot (see FIG. 3D, 362) on a mandrel which allows the bobbin element 300 to be rotated with precision during the winding process.

FIGS. 3C and 3D illustrate four (4) such bobbin elements 300 mounted on a mandrel 360. Note that because the bobbin elements 300 are configured in a linear fashion, the automated winding of the final “torus-like” shape is very much simplified over a truly torus (circular) shape. The collar 370 is mounted on the end of the mandrel 360 and secures the bobbin elements onto the mandrel 360. The embodiment illustrated in FIGS. 3 – 3D can then optionally be encased in a header or housing, such as e.g., an over-lapping clamshell type header (not shown) or other encasement.

Referring now to FIGS. 4 – 4B, a fourth exemplary embodiment of a current sensing apparatus 400 is shown and described in detail. Specifically, the current sensing apparatus 400 of FIGS. 4 – 4B comprise multiple ones of segmented bobbin elements 410. Each of these bobbin elements 410 are disposed next to one another via the use of an external ring-like header 460 (FIG. 4A). FIG. 4 illustrates a partial segment of the current sensing apparatus 400 of FIG. 4A. Specifically, only a forty-five degree (45°) segment of a three-hundred sixty degree (360°) apparatus 400 is shown. Accordingly, in the illustrated embodiment, the complete apparatus 400 would consist of eight (8) segmented bobbin elements 410, as can be seen by counting the number of cavities 464 on the ring-like headers 460 of FIG. 4A. The bobbin element 410 illustrated in FIG. 4 includes a central passageway 430 that is intended to position the pass through conductor at a precise location within each of the segmented bobbin elements. In the embodiment illustrated, the passageway is positioned along the longitudinal axis of the cylindrical bobbin element 410. The bobbin element 410 of FIG. 4 also includes an alternative passageway 432 which can be utilized to route the return wire through the center of the bobbin segment for the purpose of facilitating assembly. The bobbin element 410 is characterized by a winding channel 412 adapted for receiving one or more layers of windings, while flanges 418 retain the windings in the winding channel 412 resulting in a uniform distribution of the windings within the bobbin element 410. Positioned on opposing ends of the flanges are alignment posts 416 positioned above standoffs 440. These alignment posts 416 are optional but are utilized to facilitate individual placement of the bobbin elements 410 within the header 460. Routing features 422 are utilized for facilitating the routing of the windings between individual ones of bobbin elements 410 during automated winding

on a mandrel as will be discussed more fully subsequently herein with respect to FIG. 4B. These routing features 422 act as entry/exit points for the wire wound within the winding channel 412.

FIG. 4B illustrates the individual bobbin elements 410 mounted on a mandrel 470 for the purpose of the automated winding of individual ones of the bobbin elements. As can be seen, a slot 472 is machined or otherwise formed in the winding mandrel 470. This slot 472 is sized to accommodate a respective feature 434 (FIG. 4) on the individual bobbin elements which facilitates the winding operation. A collar 480 is placed over an end of the mandrel 470 in order to secure and position the individual bobbin elements 410 at a reliable location along the shaft of the mandrel. This approach permits repeatability and consistency during the winding process, without necessitating the use of vision equipment to help locate the feed end of the automated winder.

Note also that all eight (8) segments 410 utilized to form the current sensing apparatus are disposed on a single winding mandrel 470. While previous embodiments (FIG. 3C) have illustrated only a portion of the entire sensing apparatus being formed at any one time on a mandrel, the embodiment of FIG. 4B illustrates an embodiment in which *all* segments can be wound in a single winding operation. The wound segments can then be subsequently removed from the mandrel and placed into the headers 460 as shown in FIG. 4A.

Referring now to FIGS. 5 – 5C, yet another embodiment of a bobbin element 510 for use in a current sensing device is shown and described in detail. The bobbin element illustrated in FIG. 5 is similar in construction with the hinged embodiment previously illustrated in FIGS. 2 – 2C. Specifically, the embodiment illustrated in FIG. 5 is similar in that it possesses a winding channel 512 defined by outer winding flanges 518. Furthermore, the embodiment illustrated further includes routing posts 514 for facilitating the routing of magnet wire between adjacent ones of winding channels (see FIG. 5C). The hinge element 522 also is adapted for receipt in a respective feature located on an adjacent bobbin element 510 and acts as a pivot point for the bobbin elements, similar to the functionality as described with regards to FIGS. 2 – 2C. See also the hinge point 550 illustrated in FIG. 5B. In addition, the collective bobbin elements can then optionally be placed inside of a clamshell type cover (not

shown) or other encasement, or between a pair of header elements (similar to that shown in FIG. 4A, 460).

However, unlike the previous embodiments discussed, the embodiment of the bobbin element 510 illustrated in FIG. 5 differs in that the pass through or return conductor(s) (not shown) is not routed through the center aperture 534, as has been illustrated in the previous embodiment of FIGS. 2 – 2C; rather wire routing aperture 530 is utilized for this purpose. The wire routing aperture 530 is positioned within the body of the winding barrel, the outer diameter of which defines the winding channel 512. Such a configuration has advantages in terms of assembly, as the pass through conductor is resident on the inner diameter of the finished current sensing device. Because the pass through conductor is on the inner diameter, the length of the pass through conductor advantageously does not need to be significantly lengthened as the individual bobbin elements 510 are formed into their final torus shape. This allows for, *inter alia*, greater simplicity and efficiency in manufacturing and assembly.

In addition, as the pass through conductor is not positioned within the center aperture 534, it can be easily accommodated during the mandrel winding process with the individual bobbin elements 510 each mounted on the mandrel 560. Note also that flat surface 536 (as perhaps is best shown in FIG. 5A) corresponds with a flat surface 570 located on the mandrel 560. This geometry helps ensure that the bobbin elements 510 spin as the mandrel spins.

FIGS. 6 – 6B illustrate yet another variant of the current sensing apparatus of FIGS. 5 – 5C. The embodiment of FIGS. 6 – 6B is similar in that it is made up of bobbin elements 610 for use in a current sensing device. The bobbin element 610 comprises a hinged assembly similar to that illustrated in FIGS. 2 – 2C. The bobbin element further possesses a winding channel 612 defined by outer winding flanges 618 and further includes routing posts 614 for facilitating the routing of magnet wire between adjacent ones of winding channels (see FIG. 6B). The hinge element 622 also is adapted for receipt in a respective feature located on an adjacent bobbin element 610 and acts as a pivot point for the bobbin elements, similar to the functionality as described with regards to FIGS. 2 – 2C and FIGS. 5 – 5C. See also the hinge point 650 illustrated in FIG. 6B. The collective bobbin elements 610 can then optionally be placed inside of a clamshell type cover (not shown) or other encasement, or between a pair of header elements (similar to that shown in FIG. 4A, 460).

The embodiment of the bobbin element 610 illustrated in FIG. 6 differs over prior illustrated embodiments in one salient aspect; i.e., that the return conductor (not shown) is not routed through the center aperture 634 or a wire routing aperture (FIG. 5A, 530) passing through the winding barrel, as has been illustrated in previous
5 embodiments. Rather, the wire routing slot 630 is utilized for this purpose. The wire routing slot 630 is positioned on the exterior periphery or outer diameter of the winding channel. Such a configuration has advantages in terms of assembly as the return conductor is resident not only on the inner diameter of the finished current sensing device, but also does not need to be threaded through an aperture, thereby
10 simplifying assembly.

It is also noted that routing slot may be used to run the return wire (conductor) and/or a flexible cord inlay (non-conductor). For example, in one variant (see FIG. 6C), the wire being wound around the bobbins would capture and secure the
15 aforementioned cord (not shown) in the outer slot 631 to the individual bobbin elements, so as to provide a flexible hinge between them, and add mechanical stability (as well as protect the crossover wire during assembly). This cord does not have to be round in cross-section; in fact, it may have literally any cross sectional shape including without limitation square, rectangular, polygonal, oval/elliptical, or even be
a composite of multiple discrete strands (e.g., braided).

20 Furthermore, because the return conductor is on the inner diameter, the length of the return conductor does not need to be significantly lengthened as the individual bobbin elements 610 are formed into their torus shape, as previously discussed. In addition, as the return conductor is not positioned within the center aperture 634, it can be easily accommodated during the mandrel winding process with the individual
25 bobbin elements 610 each mounted on the mandrel 560 illustrated in FIG. 5C.

Referring now to FIG. 7, various exemplary positions for a return or return conductor on a bobbin element 700 are shown. Specifically, FIG. 7 illustrates various options for positioning the return conductor with respect to the bobbin element 700 and the respective windings 710 disposed on that element. While simultaneously
30 illustrating multiple return conductors (720, 730, 740, 750, 760), it is recognized that in most embodiments, only a single position for the return conductor will exist at a time. The various illustrated options are as follows (these are not intended to be limiting, and other options exist):

Option (1) The return conductor 720 can be placed at the inner diameter radius of the bobbin element 700, similar to the positioning as set forth in the embodiment of FIGS. 5 – 5C;

5

Option (2) The return conductor 730 can also be placed external to the windings 710. While unconventional, it has been found that such an arrangement is effective so long as the return conductor 730 is in physical contact with the windings 710. It is appreciated that the return conductor 730 can literally be placed anywhere along the outer periphery of the windings 710;

10

Option (3) The pass through conductor 740 can be placed at the geometric center of the bobbin element 700 (i.e. along the longitudinal winding axis) as set forth in, for example, FIGS. 2 – 2C;

15

Option (4) The pass through conductor 750 can be positioned along the outer diameter radius of the bobbin element 700 internal to the windings 710; and/or

20

Option (5) The pass through conductor 760 can be positioned off-plane with respect to the inner conductor 720 and outer conductor 750 positions as set forth in (1) and (4) above.

25 The various options discussed above with respect to FIG. 7 have various electrical performance versus manufacturability tradeoffs. For example, in some applications, the degradation in electrical performance seen by a current sensing apparatus is not significant enough to offset the benefits in terms of ease of manufacture by placing the feed through conductor closer to the inner diameter of the completed current sensing
30 apparatus (as discussed above with respect to, for example, FIGS. 5 – 5C). Alternatively, in high performance and/or precision applications, the additional manufacturing cost may be justified for the higher level of performance/precision.

Such tradeoffs would be readily understood by one of ordinary skill given the present disclosure and accordingly are not discussed further herein.

Referring now to FIG. 8, yet another embodiment of a current sensing apparatus 810 is shown and described in detail. Specifically, the embodiment of FIG. 8 addresses the special case where the current carrying conductor 820 to be sensed is oblong or otherwise irregular in shape. Such an oblong shape as illustrated is common in, e.g., many electrical utility company applications (such as for example in so-called busbars utilized in electrical power distribution switchboards, distribution stations and substations). As discussed previously, the current sensing apparatus of previous embodiments was primarily contemplated as being generally torus-like in shape as is conventional in the prior art. However, it has been found that by elongating the current sensing apparatus 810 such that it now comprises a generally oval or elliptical type shape to accommodate the oblong shape of the conductor 820, improved electrical performance is achieved. Recall from above that the voltage sensitivity of a Rogowski coil is driven by equation (1) in which:

$$\text{Equation (1)} \quad V = \frac{-AN\mu_0}{l} \frac{dI}{dt}$$

Accordingly, by possessing a generally oval type shape, the current sensing apparatus has a relatively shorter length (than a prior art round Rogowski coil), thereby increasing the voltage level seen in the current carrying conductor 820. In addition to curved configurations, it is also recognized that square and rectangular configurations can be utilized as well.

In embodiments that utilize the segmented bobbin elements (e.g. segmented bobbin element 210, FIG. 2) or alternatively the header element (110, FIG. 1), it is appreciated that the center opening 830 can be sized to accommodate the conductor 820 without having to physically vary the shape of the segmented windings themselves. In other words, the bobbin element or header element itself is physically sized to accommodate the conductor. FIG. 8A illustrates on such exemplary implementation. Specifically, FIG. 8A illustrates a current sensing apparatus 850 formed of a multiplicity of segmented bobbin elements 852 each having a number of conductive windings 854 wound thereon. These segmented bobbin elements are then utilized in conjunction with

alignment elements 856 so as to align the bobbin elements around the conductor 820 to be measured. In this manner, the alignment elements prevent skewing and biasing of the current sensing apparatus 850 when placed around the conductor, and further provide accurate and repeatable placement (ensuring consistent electrical performance for
5 current sensing apparatus installed in the field).

Moreover, in other embodiments, the alignment elements are interchangeable, such as to accommodate bus bars of different shapes and sizes, and/or the placement of the conductor within different portions of the center opening of the coil.

Similarly, for the free-space or former-less embodiments described elsewhere
10 herein, a central alignment element can be used which positively places (and orients) the sensing apparatus around the conductor.

FIGS. 8B and 8B-1 illustrates yet another embodiment of the sensing coil of the invention, rendered in a substantially rectangular form factor having four (4) (or multiples of 2) segments corresponding to each of the four sides of a rectangular
15 conductor. As shown in FIG. 8B, the four segments 870, 872, 874, 876 are disposed at 90 degrees relative to one another, corresponding to the four sides of the bus bar 878. The lateral coil segments 872, 876 are longer in length (and have more turns) than the end coil segments 870, 874, although it will be appreciated that other configurations may be used (including four identical segments, segments of the same length but
20 different turn density, segments of different length but the same turn density, and so forth). Moreover, the configuration of FIG. 8B can be used with square conductors (not shown), or multiple conductors whose composite outline forms an effective rectangle or square.

The device 868 of FIGS. 8B and 8B-1 is in the illustrated embodiment, disposed
25 within a hard shell or case 880 (shown with part of the case "clamshell" removed in FIG. 8B), although other approaches (including for example encapsulation, or use of a header or bobbin for support) may be used as well.

FIG. 9 illustrates an alternative to the substantially round winding channels 910 associated with typical prior art current sensing apparatus. As can be seen in FIG. 9, the
30 cross sectional length of the current sensing apparatus 920 has been lengthened along the path of the conductor 940 in which current is desired to be sensed. The feed through conductor 930 can be placed within the current sensing apparatus 920 in any number of locations, considering the various design tradeoffs, as set forth in the discussion of FIG.

7 above. Accordingly, because the cross sectional area (A) has been increased (as set forth in Equation (1) above), the voltage level measuring the current carrying conductor 940 increases. While prior art Rogowski-type coils have typically maintained their traditionally circular and torus-like shapes due to a fear that deviating from these shapes
5 would adversely impact the electrical performance of the coil, it has been found that in many typical applications, such deviations are acceptable in implementation.

In yet another embodiment of the invention, two or more “layers” of windings may be utilized to form the coil and the return conductor. For example, in one variant, a first layer of windings is applied over the top of the bobbin or header segments so as to
10 effectively provide complete coverage of the segmented bobbin or header elements. At completion of the first layer, the same winding is “doubled back” upon itself and over the top of the first layer so as to form a second layer. The first layer in effect acts as a return conductor within the second layer, although the return conductor layer need not necessarily be the first layer. It will be appreciated that more layers for the return and/or
15 “top” (second) layer may be used as well if desired. Moreover, the winding densities and topologies may be varied for each layer, such as e.g., where the return conductor layer is wound at a lower density (greater inter-turn spacing) than the top layer.

It is also appreciated that the aforementioned “layered” approach need not be used in conjunction with a bobbin or header at all. For instance, in one “free standing”
20 variant, bonded wire of the type discussed previously herein is used to form the first and subsequent layers (e.g., wound atop a mandrel or other removable structure, and then bonded, and the mandrel/structure removed). Alternatively, non-bonded wire can be used, and subsequently encapsulated or held in place with an adhesive before removal of the mandrel/support. Myriad other variations will be appreciated by those of ordinary
25 skill given the present disclosure.

Referring now to FIGS. 16 – 16D, yet another exemplary embodiment of a header- or bobbin-based current sensing apparatus 1600 is shown and described in detail. Similar to other disclosed embodiments, the current sensing apparatus 1600 of FIGS. 16 – 16D comprise multiple ones of segmented bobbin elements 1610. FIG. 16
30 illustrates a single one of these segmented bobbin elements 1610 in detail, with the illustrated bobbin element 1610 adapted for coupling to another segmented bobbin element via a hinged coupling 1620. Other coupling types may be used consistent with this embodiment as well.

In the illustrated embodiment, this hinged coupling 1620 includes a pair of hinge features 1621, 1623, with a through-hole 1632 disposed on each of these features that is sized to accommodate an inserted pin (item 1650, FIG. 16A). The hinged coupling in combination with the inserted pin is somewhat akin to what is seen on a typical door hinge. These hinged couplings include an outer hinged coupling pair 1623, and an inner hinged coupling pair 1621, which are designed so as to retain adjacent segmented bobbin elements. Specifically, the outer hinged coupling pair 1623 is spaced apart at a distance in which a respective inner hinged coupling pair 1621 can fit therebetween. It will be recognized that each segment element 1610 (i.e., each side or interface portion thereof) can include (i) the outer hinge pair, (ii) the inner hinge pair, or (iii) some mixture of the foregoing. In one variant, the segment elements are each made identical to one another for ease of assembly and lower cost, although this is by no means a requirement. Moreover, the segment elements can have at least 2-dimensional symmetry such that they can be inserted into the assembly in two different orientations, thereby simplifying assembly from the standpoint that an automated or manual assembly process does not have to orient the part correctly in all three dimensions for assembly (rather only with respect to two dimensions).

Each of the hinged coupling pairs illustrated in FIG. 16 also incorporate a chamfered inlet for the through hole 1632. This chamfered inlet facilitates the insertion of the inserted pin order to ease assembly.

Furthermore, and similar to other illustrated bobbin embodiments discussed previously herein, bobbin element 1610 of FIG. 16 also includes a winding channel 1612 with flanges 1618 disposed on either side of the winding channel. The winding channel is further defined by a spool or barrel 1613 which provides the radial mechanical support for the insulated windings.

The bobbin element also includes a return conductor passageway 1630 positioned within a return conductor alignment feature 1634. The return conductor passageway 1630 is intended to position the pass-through conductor at a precise location within each of the segmented bobbin elements. In the illustrated configuration, the passageway is positioned along the longitudinal axis (i.e., the geometrical center) of each of the cylindrical bobbin elements 1610; however, as noted elsewhere herein, the position of the central conductor(s) may be (i) non-

symmetrical with respect to the cross-section of passageway 1630 or bobbin element; (ii) may be variable or changeable; and/or (iii) may reside at other locations.

FIG. 16 also illustrates some additional features not present in some of the other illustrated bobbin element embodiments, although it is recognized that these other illustrated embodiments could readily incorporate these features. These features include winding alignment bosses 1638 along with associated alignment holes 1636. These bosses and holes are useful during the winding process to ensure proper alignment is maintained between adjacent bobbin elements 1610 (i.e., to prevent relative twisting when wire is being wound on a winding mandrel, etc.), and to maintain stability when the bobbin elements are rotated at high speed.

Conductive clip apertures 1616 are also included on the illustrated embodiment of the flange. These apertures 1616 are sized to accommodate a respective clip (not shown), which is then used to facilitate the connection of the windings resident with the winding channel 1612 to the return conductor and to an external connection (see e.g. the manufacturing discussion with relation to, *inter alia*, FIGS. 18A – 18S). Note that the illustrated embodiment of the bobbin element 1610 includes two (2) substantially identical clip apertures 1616 located on opposing flanges 1618. However, alternative embodiments could utilize “keyed” clip apertures that differ so as to, for example, prevent the insertion of improper clips (i.e., where clips differ between the “start” and “finish” winding ends of the Rogowski coil device).

Furthermore, while illustrated as a so-called post inserted configuration, it is recognized that the conductive clip could also be insert molded into the flange (i.e., during the injection molding of the bobbin element itself), thereby securing the clip to the bobbin element. Yet other techniques recognized by those of ordinary skill given the present disclosure may be used as well.

FIG. 16A illustrates the total or collective number of bobbin elements 1610 in a single device 1600, coupled together via their respective hinge coupling pins 1650. Note also that the windings 1660 have now been added to each of the bobbin elements as illustrated in FIG. 16A. As discussed previously herein, the bobbin element 1610 is characterized by a winding channel adapted for receiving one or more layers of windings, while flanges retain the windings in the winding channel resulting in at least a substantially uniform distribution of the windings within each of the bobbin

elements 1610. While the winding channel is illustrated with a smooth winding barrel or spool, it is appreciated that grooves could be formed into the winding barrel in order to provide a means to further guide the windings during the winding process so that they are wound more uniformly. Moreover, while illustrated as a symmetric and circular barrel, it is recognized that the cross-section of this “barrel” need not be symmetric, and/or can also include segmentation (i.e., may comprise an octagon, ellipse, polygon, etc. in cross-section) as discussed previously herein.

FIG. 16B illustrates an exploded view of the Rogowski coil device 1600 as each of the bobbin elements are about to be mounted within a housing. The housing in this embodiment is comprised of a top 1670 and a bottom 1680 housing cover, although other configurations may be used.

FIGS. 16C – 16D illustrate how each of the bobbin elements 1610 are supported within the housing. As can be seen in FIG. 16D, the bottom housing cover 1680 includes a number of features that facilitate device assembly. More specifically, these features aid in the accurate placement of the bobbin elements 1610 within the housing. Hinge pin receptacle features 1684 are adapted to accommodate the hinge pins 1650 present on the assembled grouping of bobbin elements 1610. These features help ensure that each of the bobbin elements 1610 is precisely spaced to ensure repeatable electrical performance from the underlying Rogowski coil device 1600, and also aid in the assembly process by registering the various components of the core at a desired location. Flange support features 1682, 1686 are also sized to accommodate the shape of the bobbin elements and ensure that they are adequately supported within the bottom housing 1680. The bottom housing also includes a central aperture 1688 that is designed to accommodate the electrical conductor(s) to be measured by the Rogowski coil device 1600. As previously noted, this central aperture may be (i) of a shape that is not circular and/or non-symmetric; and/or (ii) made replaceable to accommodate different conductor cross-sections (e.g., round, side-by-side, rectangular “bar”, etc.).

Referring now to FIGS. 17 – 17C, yet another exemplary implementation of a header-based or bobbin-based current sensing apparatus 1700 is shown and described in detail. This embodiment incorporates a so-called “living hinge” design, as described in greater detail below. FIG. 17 illustrates a singular segmented bobbin element 1710, which in combination with other bobbin elements (e.g., six (6) in the

illustrated embodiment), forms the Rogowski coil device 1700 illustrated in FIG. 17A. Similar to previous embodiments discussed herein, the bobbin segments illustrated in FIGS. 17 – 17C each are disposed next to one another in a common plane via a hinged coupling 1720. In the illustrated embodiment however, this hinged coupling 1720 includes a flexible hinge feature 1725 that connects the flange 1718 of the bobbin element with a coupling portion comprised of a winding spool portion 1721 along with an insertable portion 1723, the latter sized to fit within an associated aperture 1722 located on the winding channel 1712 of an adjacent bobbin element. The winding spool portion 1721 includes a curved surface which is shaped to possess a diameter substantially identical to the underlying winding spool. In addition, the thickness of the winding spool portion of the hinged coupling is approximately the same as the depth of the spool cavity 1727, such that when the hinged coupling is coupled to an adjacent bobbin element, the coupling provides a near seamless fit.

Similar to other illustrated bobbin embodiments discussed previously herein, the bobbin element 1710 of FIG. 17 includes a winding channel 1712 defined by a barrel or spool 1713, and flanges 1718 disposed on either side of the winding channel in order to define a winding “window” for the bobbin. Furthermore, the bobbin element includes a return conductor passageway 1730 positioned within a return conductor alignment feature 1734. The return conductor passageway 1730 positions the pass through conductor at a precise location within each of the segmented bobbin elements as discussed previously. In the illustrated configuration, the passageway is positioned along the longitudinal axis (i.e., the geometrical center) of each of the cylindrical bobbin elements 1610; however, as noted elsewhere herein, the position of the central conductor(s) may be located at a variety of differing locations while still providing adequate electrical performance in most current sensing applications.

FIG. 17 also illustrates the use of winding alignment bosses 1738 along with associated alignment holes 1736. These bosses and holes are useful during the winding process to ensure proper alignment and stability is maintained between adjacent bobbin elements 1710 (i.e., to prevent relative twisting when wire is being wound onto a winding mandrel, etc.). In addition, conductive clip apertures 1716 are included on the flange. These apertures 1716 are sized to accommodate a respective clip (not shown) which is then used to facilitate the connection of the windings resident with the winding channel 1712 to the return conductor and to an external

connection (see e.g. the manufacturing discussion with relation to, *inter alia*, FIGS. 18A – 18S). Note that the illustrated embodiment of the bobbin element 1710 includes two (2) substantially identical clip apertures 1716 located on opposing flanges 1718. Furthermore, while illustrated as a post-inserted clip design, insert molding or other techniques could be readily substituted as well.

FIG. 17B illustrates a cross-sectional view of the Rogowski coil device 1700 of FIG. 17A, taken along line 17B – 17B. The cross-sectional view of FIG. 17B helps illustrate the fit of the various elements of the hinged coupling. Specifically, it shows the insertable portion 1723 of the hinged coupling pushed against the winding spool aperture 1722 so as to prevent over insertion when coupling the various bobbin elements. Also, as can be seen in FIG. 17B, the external surfaces 1731 of the return conductor alignment feature 1734 is disposed offset from (i.e., inward of) the external surface 1719 of the bobbin element 1710. This offset allows for the insertion and alignment of, for example, the start and end clips (1890, 1892 in FIGS. 18A and 18B, respectively).

Exemplary Current Sensing Apparatus Applications –

The exemplary current sensing apparatus described herein can be used in any large number of applications, and/or where it is desirable to measure the current of a conductor without otherwise disturbing the current carrying conductor itself. One such common application is in the incorporation of current sensing apparatus in electrical meters for use in residential, commercial and industrial applications. By measuring the current being consumed by a consumer of electricity, and passing this information along to the utility company via a network interface on the meter, the utility company or other entity can better gauge what to charge its consumers, and/or better understand the energy being consumed throughout various parts of an electricity grid or system.

As well as being resistant to tampering and electromagnetic interference, current sensing apparatus such as Rogowski coils have wide applicability to various applications included in the recent push towards so-called smart grids. Furthermore, in addition to being utilized in power distribution metering applications (such as circuit breakers, residential and industrial monitoring stations, etc.), the use of current sensing apparatus in a wide variety of appliance applications which utilize large amounts of current (such as for example, electric welders and motor controls) are envisioned as well.

Multi-Coil Current Sensing Apparatus –

Referring now to FIG. 15A, a first exemplary embodiment of a multi-coil Rogowski coil device is illustrated. Specifically, the multi-coil Rogowski coil device of FIG. 15A comprises two (2) Rogowski coil devices of the type previously illustrated with respect to FIG. 1 above, disposed in a “stacked” or juxtaposed arrangement. While illustrated with the coil embodiment of FIG. 1, it is appreciated that any of the current sensing apparatus embodiments described herein could readily be stacked in such a manner (including without limitation the free-space or bobbin-less embodiments described elsewhere herein). Furthermore, the upper and lower Rogowski coil devices are each shown with only a single coil element or segment 1510 and 1520, respectively. It should be recognized however that in practice, each of the Rogowski coil devices of the illustrated embodiment would have eight (8) wound coils; the single wound coil is illustrated FIG. 15A merely so as to more easily illustrate the relative offset between the top and bottom Rogowski coil devices.

Recall from the previous discussion of prior art Rogowski coil devices, that these prior art devices are uniform in their distribution of their windings (i.e. they are non-segmented). Furthermore, as the Rogowski coil devices 100 illustrated in FIG. 15A are segmented, there is expected to be some flux leakage or “imperfection” in the gaps between the wound coils of these devices. Accordingly, by stacking the Rogowski coil devices in FIG. 15A in proximity to one another, and angularly offsetting the top segmented wound coil 1510 from the bottom segmented wound coil 1520 (and combining the outputs from the two coils), the combined devices behave more like an ideal Rogowski coil with a non-segmented uniform distribution of windings.

It will be appreciated that while only two coils are shown in the embodiment of FIG. 15A, three (or more) coils can be stacked in such a manner if desired. For example, it may be desirable to utilize three (3) such coils in stacked arrangement (not shown), with the gaps between segments in the middle coil corresponding to coil segments of both the upper and lower coils, such that the flux leakage from the middle coil gaps is addressed substantially symmetrically (from both top and bottom) by the upper and lower coils, respectively.

In another configuration (such as where the gaps are appreciable in size relative to the length of the coil segments), the placement of the coils of the respective stacked coils can be “phased” with respect to the gap of the first; e.g., a first coil at vertical

position zero (0) at an angular position zero (0), the second coil at vertical position one (1) atop the first coil at angular position zero plus x , the third coil at vertical position two (2) atop the second coil at angular position zero plus y (where y is greater than x), and so forth.

5 Generally speaking, for any appreciable affect on leakage or precision to occur due to the addition of more coils, the coils must be offset from one another in azimuth somewhat (i.e., segments of one coil overlap with gaps in another coil); however, this is not always the case. At least some effect on precision/leakage may be achieved in certain configurations simply by stacking two or more coils with their segments aligned,
10 due to the fact the leakage from the gap of one coil couples with the adjacent segments of the other coil(s) even when the adjacent segments of the second coil are not aligned with the gaps.

 FIG. 15B illustrates a top down view of the two Rogowski coil devices of FIG. 15A. Specifically, the angular offset can be clearly seen in FIG. 15B with the bottom
15 wound coils 1520 offset or shifted with respect to the top wound coils 1510. While the stacked Rogowski coil device of FIGS. 15A and 15B illustrate only two (2) such devices, it is recognized that three (3) or more Rogowski coil devices can also be stacked with their outputs combined and angularly offset from one another in order to provide a more ideal behavior when measuring current passing through a conductor to
20 be measured.

 FIG. 15C illustrates another embodiment of a stacked Rogowski coil apparatus. Specifically, FIG. 15C illustrates a variant to the apparatus shown in FIG. 15A in which tuning covers 1530 are placed about the Rogowski coil devices 100. These covers 1530 are preferably made from a molded polymer and have features (not shown) which permit
25 the covers to rotate with respect to one another while coupled. As the two devices are permitted to rotate 1534, a user can effectively tune the output of the stacked Rogowski coil devices in order to optimize the performance of the stacked Rogowski coil device. The tuning covers also include a hinge 1532 which permits the covers and the Rogowski coil devices to be positioned about the conductor to be measured without necessitating
30 that the conductor be threaded through the central aperture 1536.

 Referring now to FIG. 15D, an alternative tunable stacked Rogowski coil apparatus 1540 is shown and described in detail. The apparatus of FIG. 15D includes three (3) Rogowski coil devices 100; although the middle device has been removed from

view in order to better illustrate the inner workings of the stacked apparatus 1540. The Rogowski coil devices 100 are received within a protective cover 1560 which is illustrated in cross section. The devices 100 are similar in construction to those devices shown in FIG. 1; however they have been, in an exemplary embodiment, constructed from a laser direct sintering (LDS) polymer material. Each of the devices have formed thereon two (2) conductively plated surfaces 1540 which are electrically coupled to respective ends of the Rogowski coil segmented windings. The Rogowski coil devices 100 are received within a channel 1550 formed within the protective cover 1560. These channels 1550 act as a guide which permits the Rogowski coil devices 100 to rotate within the cover 1560.

The cover 1560 is also preferably formed from an LDS polymer material thereby permitting the channels 1550 to be conductively plated as well. Accordingly, the conductive channels 1550 of the cover are electrically coupled to the conductive pads 1548 of the Rogowski coil devices. Various interfaces (including LDS polymer interfaces) between the individual devices 100 and the cover 1560 can be utilized such as those described in co-owned and co-pending United States Patent Application Serial No. 12/482,371 filed June 10, 2009 and entitled "Miniaturized Connectors and Methods", the contents of which are incorporated herein by reference in its entirety. The conductive channels 1550 are then electrically coupled to one another and also to output terminals 1562. These output terminals 1562 can then either be attached to external conductors (not shown) or alternatively mounted as either a through hole or surface mount contact to an external substrate (not shown).

As an alternative to the use of LDS polymers, the Rogowski coil devices 100 and cover 1560 could also be constructed as a composite structure. Specifically, the conductive pads 1548 on the Rogowski coil device and the conductive channels 1550 is constructed from a metallic alloy placed onto the underlying polymer structures. These metallic alloys can either be insert-molded or post inserted into pre-formed apertures present on the cover and Rogowski coil header, respectively. In addition, these metallic alloys are preferably shaped so as to act as a spring and provide additional contact force while the Rogowski coil devices 100 are rotated within the cover. The Rogowski coil devices are rotated within the cover via a protrusion 1566 through an aperture 1564 located on the cover 1560. By manipulating the protrusion

1566 in a lateral (azimuth) direction 1568, the individual Rogowski coil devices can be tuned within the assembly 1540.

Referring now to FIG. 15E, a concentrically arranged stacked Rogowski coil apparatus 1570 is shown and described in detail. Specifically, the stacked Rogowski coil apparatus 1570 comprises an inner Rogowski coil 1580 and an outer Rogowski coil 1575. Both the inner and outer Rogowski coils are adapted to rotate in a circumferential direction 1572 with respect to one another. Similar to the stacked concepts illustrated in FIGS. 15A – 15D, the concentrically stacked Rogowski coil apparatus of FIG. 15E permits the windings 1577 of the outer coil 1575 to be positioned adjacent the unoccupied intermediate segments 1582 of the inner coil 1580. Similarly, the windings 1584 of the inner coil 1584 are positioned adjacent the unoccupied intermediate segments 1579 of the outer coil 1575. The respective ends of the inner and outer Rogowski coil devices are then electrically coupled to one another to provide a combined output for a conductor to be measured.

In yet another exemplary embodiment two (2) or more of these concentrically arranged stacked Rogowski coil apparatus 1570 can be placed in a top-to-bottom disposition (similar to that shown with respect to FIG. 15A), thereby adding yet another layer of redundancy to help correct against distortions in electrical performance due to the segmenting of the coils. In such a configuration it is desirable that the winding portions 1584 of the inner coil be placed adjacent to the unoccupied intermediate segments 1582 of the adjacent inner coil, while the winding portions 1577 of the outer coil are placed adjacent the unoccupied intermediate segments 1579 of the adjacent outer coil.

In another variant, a “hybrid” stacked/concentric configuration (not shown) is provided. In this variant, the individual coils of the multi-coil assembly are of different radius, yet not so that one fits entirely within the other (i.e., the outer diameter of one coil is such that it is greater than the inner “hole” diameter of the next adjacent coil, such that they sit in a stacked configuration, but with the coils having different diameters. The variation of the coil diameter as a function of vertical position may be progressive (e.g., diameter of coil at vertical position zero (0) being smaller than that of the next higher coil, and the diameter of that next higher coil being smaller than that of the third coil above it, and so forth), or assume other patterns (such as an “hourglass”, wherein the lowest coil is of a larger diameter than

the (second) coil directly above it, and the coil directly above that second coil is also of a/the larger diameter).

Furthermore, while primarily envisioned as tunable embodiments, the stacked Rogowski coil devices of FIGS. 15A – 15E are not so limited. In fact, it may be desirable in some embodiments to maintain a fixed relationship between adjacent ones of Rogowski coil devices thereby simplifying the assembly.

It will also be appreciated that in yet another embodiment, the vertical spacing or disposition of the different coils (whether in “stacked” or “concentric” configuration) can be varied, thereby increasing/decreasing the coupling or interaction of the coils. For instance, the vertical height between tow stacked coils can range from zero (0) to literally any value consistent with the form factor of the application. Obviously, the most coupling effect will be achieved when the coils are immediately proximate one another, but it is contemplated by the present invention that “tuning” of the assembly may also comprise variation of the vertical spacing of coils in the stacked or concentric configurations. In one variant, such variable spacing is accomplished by simply substituting non-conductive spacers (e.g., flat toroids or “washers” of prescribed thickness made from e.g., a polymer, paper, kapton, etc.) between the individual coils. In another variant, the case which contains the coils may be configured so that the stacked coils may reside at different elevations relative to one another. Myriad other techniques for allowing variation of the spacing between coils will be appreciated by those of ordinary skill when given the present disclosure.

It is also noted that while the aforementioned embodiments of stacked and concentric (and hybrid) coil assemblies may be “tuned” by varying the placement of the coils relative to one another - whether vertically, horizontally, or in azimuth or even attitude (yaw) – they may also be tuned to achieve the desired level of performance by virtue of their constituency. For example, in one embodiment of the assembly, the user/installer is provided with a plurality (e.g., two or more) of very low cost, lower-precision coils. These coils each may for example only have a few number of segments, relatively large spacing between segments, and/or less turn density in each segment, such that they are a more gross approximation of the “perfect” Rogowski coil (yet are also very inexpensive to manufacture). It may be that one user of the assembly merely requires a low-precision, gross approximation of the sensed parameter(s) (e.g., current through a conductor), and hence the use of a single one of the aforementioned coils

within the assembly may suffice for these purposes. Alternatively, another user of the assembly may require much higher levels of precision in their intended application; such levels of precision cannot be achieved through use of one of the low precision coils alone, yet can be achieved with perhaps two or three coils used in stacked/concentric/hybrid configuration. In this fashion, one embodiment of the invention is configured such that coils can be added or subtracted by the user as required in order to achieve their desired level of precision, while also achieving the most economical implementation (in contrast to a “one-size-fits all” approach of the prior art, wherein the device precision/accuracy is effectively fixed).

The foregoing methodology may also be applied in installations where large numbers of individual or aggregated coils may be required, such as by a utility implementing a customer-wide monitoring program. For example, where the installed electrical meter base for the utility’s customers is substantially homogeneous, the utility can “tune” the device installation on an exemplary or representative meter, and then simply replicate that installation on all other meters within the customer base (without having to individually tune each one). Hence, the utility can purchase one “tuning kit”, which may for example have myriad different types, diameters, winding densities, segment spacings, and configurations of coils/coil assemblies, and tune the prototype or representative installation so as to optimize performance and/or cost (i.e., achieve the desired level of precision at the lowest possible cost). Once the optimal configuration (or configurations for respective types of customer installations) is/are known, the utility can then simply purchase the cost/performance-optimized configuration *en masse* from a supplier, thereby obviating the waste and cost of “leftover” or unused parts (e.g., coils) that would result from purchasing a multitude of individual tuning kits.

It is also noted that while some of the foregoing embodiments contemplate the use of homogeneous coil configurations (e.g., two or three substantially identical coils used in a stacked arrangement), the present invention further contemplates the use of heterogeneous coil configurations. For instance, in the stacked assembly described above, the first coil might have a certain segment winding density and segment spacing/number of segments. The second coil, however, might utilize a different density/spacing/number, albeit having the same effective radius and/or vertical height. Moreover, as noted previously, the coils may also (or alternatively) have different coil heights and/or radii, different cross-sectional profiles, etc. Hence, an assembly which

can “mix and match” different coil types is contemplated herein. For such an assembly, the housing (if any) may also be configured to accept the different coil types, so as to obviate the user/installer having to procure a different housing type depending on the selected combinations/configuration of component coils. This “universal” housing can readily be constructed so as to accommodate the various possible configurations, yet meet the aims of relative conservation of space, low cost, holding the coil(s) in a desired orientation relative to the monitored conductor(s), and so forth.

Methods of Manufacture for Current Sensing Apparatus –

Referring now to FIG. 10, a first exemplary method for manufacturing a current sensing apparatus 1000 is shown and described in detail. Specifically FIG. 10 illustrates the methodology for manufacturing the current sensing apparatus illustrated in FIGS. 1 – 1B. At step 1010, the bobbin-less coils are wound on a mandrel. These coils can optionally be wound either one at a time or alternatively may be wound together so as to avoid having to interconnect them at a later processing step. These coils may be wound either using a single layer of windings or alternatively in a multi-layer configuration. The wound coils are then bonded together via the application of heat. The manufacture of bobbin-less coils is described at, *inter alia*, co-owned U.S. Patent Application Serial No. 11/203,042 filed August 12, 2005 and entitled “Stacked Inductive Device and Methods of Manufacturing”, the contents of which are incorporated herein by reference in its entirety.

At step 1020, the wound coils are threaded on a preformed return loop of copper wire (FIG. 1, 104). In an exemplary embodiment, the return loop of copper wire is formed so as to be generally “c-shaped” with a relatively small gap between the start and finish of the copper wire return loop.

At step 1030, each of the bobbin-less coils (FIG. 1, 102) are positioned within corresponding cavities (FIG. 1A, 112) of the segmented header (FIG. 1, 110).

At step 1040, the return loop of copper wire is snapped into the positioning radial slot (FIG. 1B, 114) of the segmented header. In a variant, the return loop can be secured to the radial slot via the use of an epoxy adhesive.

At step 1050, the finish lead of the last wound coil is attached to an end of the return wire loop. This attachment may utilize any number of known techniques such as eutectic solder operations, sonic welding, and the like.

At step 1060, the start lead of the first wound coil and the start of the return loop to the connection wires for the current sensing apparatus are connected. In an exemplary embodiment, the connection wires comprise twisted pair, shielded lead wires.

5 At step 1070, the coil assembly is placed within or otherwise encapsulated with a protective shell or coating thereby finishing the assembly. In an exemplary embodiment, the coil assembly is placed within an over-lapping protective plastic clamshell case. The over-lapping nature of the plastic clamshell case provides enhanced protection against resistance to high potential (also known as "Hi-Pot") by
10 increasing the path length between the wires on the current sensing apparatus and the conductor to be monitored.

Referring now to FIG. 11, an alternative method for manufacturing a current sensing apparatus 1100 is shown and described in detail. Specifically FIG. 11 illustrates the methodology for manufacturing the current sensing apparatus illustrated
15 in for example FIGS. 2 – 2C; and FIGS. 4 – 4B. At step 1110, the segmented bobbin elements (FIG. 2, 210) are loaded onto a mandrel. In an exemplary embodiment, starting at one end, each bobbin element is wound continuously over successive bobbin elements such that a continuous coil winding with no discrete interconnections is included. These wound coils can be either single or multi-layer in nature.

20 At step 1120, the return wire is threaded through respective apertures (FIG. 2A, 230) of the bobbin elements. In one embodiment, the return wire comprises one or more twisted pair, shielded lead wires that are pre-stripped, separated and straightened so that they may be placed through the holes provided in the bobbin elements as they sit on the mandrel. In an alternative embodiment, step 1120 is performed prior to
25 bobbin winding at step 1110.

At step 1130, the wound bobbin elements are removed from the mandrel as a single assembly. The removed wound bobbin element assembly resembles pearls on a string.

At step 1140, the end wire of the last coil is terminated to one end of the
30 twisted pair return wire. In embodiments which utilize two apertures (see e.g. FIG. 4, 432), the return wire can be routed back through the center portion of the segmented wound bobbin elements.

At step 1150, the bobbin elements are formed into their final shape (such as the exemplary torus-like or radial pattern described previously herein). In exemplary embodiments that include hinged couplings (e.g. FIG. 2, 220), the hinged couplings are positioned such that they are on the inside diameter of the torus-like pattern.

5 At step 1160, each of the bobbin elements are placed within corresponding cavities or slots associated with a plastic carrier. For example, in the illustrated embodiment of FIG. 4A, each bobbin element 410 is placed within a respective cavity 464 of the external ring-like header 460.

10 At step 1170, the start lead of the first coil is terminated to the other end of the return wire loop.

At step 1180, the coil assembly is placed within or otherwise encapsulated with a protective shell or coating thereby finishing the assembly such as that described with respect to step 1070 of FIG. 10 previously discussed herein.

15 Referring now to FIG. 12, a third exemplary method for manufacturing a current sensing apparatus 1200 is shown and described in detail. Specifically FIG. 12 illustrates the methodology for manufacturing the current sensing apparatus illustrated in FIGS. 3 – 3D. At step 1210, the segmented bobbin elements (FIG. 3, 300) are loaded onto a mandrel. In an exemplary embodiment, starting at one end, the winding is anchored on one end and the wire is run along the top grooves (FIG. 3, 314) across
20 all the bobbin elements. This wire is to be utilized as the return wire.

At step 1220, and starting on the far end (from the starting point of the return wire), the wire is wound back along the length of bobbin elements with windings placed on each bobbin element thereby making a continuous coil winding with no interconnections while simultaneously wrapping over the return wire. Similar
25 to previous embodiments discussed above, the coils can be either single or multi-layer depending on design considerations associated with the particular application for the current sensing apparatus.

At step 1230, the wound bobbin elements are removed from the mandrel.

30 At step 1240, the bobbin elements are formed into their final shape (such as the exemplary torus-like or radial pattern described previously herein). With respect to the embodiment illustrated in FIGS. 3 – 3D, the return wire will now run along the outer diameter of the bobbin elements.

At step 1250, the finish lead and return wire are terminated to conductors associated with the connection wires (e.g. twisted pair, shielded lead wires).

At step 1260, the coil assembly is placed within or otherwise encapsulated with a protective shell or otherwise encapsulated with a coating thereby finishing the assembly.

Referring now to FIG. 13, yet another embodiment for manufacturing a current sensing apparatus 1300 is shown and described in detail. Specifically FIG. 13 illustrates the methodology for manufacturing the current sensing apparatus illustrated in for example FIGS. 5 – 5C. At step 1310, the segmented bobbin elements (FIG. 5, 510) are loaded onto a mandrel. In an exemplary embodiment, starting at one end each bobbin element is wound continuously over successive bobbin elements such that a continuous coil winding with no discrete interconnections is included. These wound coils can be either single or multi-layer in nature.

At step 1320, the return wire is threaded through respective apertures (FIG. 5, 522) of the bobbin elements. In one embodiment, the return wire comprises one or more twisted pair, shielded lead wires that are pre-stripped, separated and straightened so that they may be placed through the holes provided in the bobbin elements as they sit on the mandrel. In an alternative embodiment, step 1320 is performed prior to bobbin winding at step 1310.

At step 1330, the wound bobbin elements are removed from the mandrel. The wound bobbin elements, because they are interconnected, are removed in a single assembly.

At step 1340, the end wire of the last coil is terminated to one end of the twisted pair return wire.

At step 1350, the bobbin elements are formed into their final shape (such as the exemplary torus-like or radial pattern described previously herein). In exemplary embodiments that include hinged couplings (e.g. FIG. 5B, 550), the hinged couplings are positioned such that they are on the inside diameter of the torus-like pattern.

At step 1360, each of the bobbin elements are placed within corresponding cavities or slots associated with a plastic carrier, similar to that shown in the illustrated embodiment of FIG. 4A.

At step 1370, the start lead of the first coil is terminated to the other end of the return wire loop.

At step 1380, the coil assembly is placed within or otherwise encapsulated with a protective shell.

Referring now to FIG. 14, yet another method for manufacturing a current sensing apparatus 1400 is shown and described in detail. Specifically FIG. 14 illustrates the methodology for manufacturing the current sensing apparatus illustrated in, for example, FIGS. 6 – 6B. At step 1410, the segmented bobbin elements (FIG. 6, 610) are loaded onto a mandrel. The return wire is, starting at one end, routed in the cavity (FIG. 6, 630) on the outer diameter of the bobbin element. Then, starting at the opposite end, each bobbin element is wound continuously over successive bobbin elements such that a continuous coil winding with no discrete interconnections is included. These wound coils can be either single or multi-layer in nature and are positioned over the return wire.

At step 1420, the wound bobbin elements are removed from the mandrel. The wound bobbin elements, because they are interconnected, are removed in a single attached assembly.

At step 1430, the end wire of the last coil is terminated to one end of the twisted pair return wire.

At step 1440, the bobbin elements are formed into their final shape (such as the exemplary torus-like or radial pattern described previously herein).

At step 1450, each of the bobbin elements are placed within corresponding cavities or slots associated with a plastic carrier, similar to that shown in the illustrated embodiment of FIG. 4A. In another embodiment, each of the bobbin elements is placed within the bottom portion of an over-lapping clam shell case.

At step 1460, the start lead of the first coil is terminated to the other end of the return wire loop.

Finally at step 1470, the coil assembly is placed within or otherwise encapsulated with a protective shell. In embodiments in which a plastic clam shell case is used, this step is accomplished by placing and securing the top over-lapping protective plastic clam shell case over the assembly.

Referring now to FIGS 18A – 18S, one embodiment of the methodology for assembling an exemplary Rogowski coil device of the invention is shown in detail. FIG. 18A illustrates a first exemplary step in the manufacturing process. In FIG. 18A, the starting end clip 1890 is inserted within a respective aperture located on the

starting end bobbin segment 1810. The end clip 1890 is in one variant manufactured from a conductive sheet of metal, which is stamped and optionally plated so as to protect the surface finish of the clip. After insertion, the clip is subsequently bent. This bend 1891 is, in the illustrated example, formed at a 60-degree angle with respect to the non-bent portion of the clip 1890. Alternatively, the starting end clip can be insert molded into the bobbin element during the injection molding process. In an exemplary process, the clip is formed up away from the surface of the bobbin segment by hand subsequent to insertion. Furthermore, exemplary embodiments incorporate notches at the bend line of the end clip so as to reduce the force needed to perform the bend operation thereby reducing the possibility of cracking the bobbin segment during the bend operation.

FIG. 18B illustrates the insertion of the finish end clip 1892 into the finish end bobbin segment 1810. Note that the bobbin segments themselves are identical between that shown in FIG. 18A and that shown in FIG. 18B (i.e. the start and end bobbin segments are identical with only the clips being different between the segments). Furthermore, also note that the “start” end clip of FIG. 18A and the “finish” end clip of FIG. 18B are disposed on opposite ends of their respective bobbin segments. The finish end clip 1892 is also preferably not bent prior to insertion, such that the notched end of the end clip 1892 is positioned over the pass through conductor passageway 1893.

FIG. 18C illustrates the next step in the exemplary process, wherein each of the bobbin elements 1810 are loaded onto a winding mandrel 1870. The end clip bobbin element 1810 (i.e., the bobbin element discussed with regards to FIG. 18B) is inserted onto the mandrel first, followed by six (6) bobbin elements that are devoid of any conductive clips. Finally, the starting bobbin element (i.e., the bobbin element discussed with regards to FIG. 18A) is inserted on the end of the string of bobbin elements with the starting end clip 1890 facing away from the other assembled bobbin elements.

Referring now to FIG. 18D, a polymer cord 1860 is slid into a groove 1813 that is collectively formed by the assembly of bobbin elements 1810. Note that the end of the cord is trimmed so that the end of the cord does not protrude past the outer wall 1811 of the end bobbin element flange. In an exemplary embodiment, the cord is manufactured from an electrical grade polytetrafluoroethylene (PTFE). The diameter

illustrated is .031 inches although it is recognized that other shapes (i.e. rectangular, polygonal, etc.) and sizes could be readily be substituted in alternative designs. This cord is utilized to create a connective “spine” that ultimately holds the assembly together in its final form. While illustrated as using a PTFE cord, it is recognized that
5 other items (such as tape, etc.) could also be readily substituted in order to provide the so-called connective “spine” to the finished Rogowski coil device.

FIG. 18E illustrates the start of the winding process. Specifically, the wire 1862 to be wound onto the bobbin elements is first secured to the winding pin 1872 of the mandrel and subsequently secured to the end clip 1892. The conductive wire is, in
10 the illustrated embodiment, wrapped around the end clip 1892 twice prior to being routed into the bobbin element winding barrel.

FIG. 18F illustrates the remainder of the end bobbin element 1810 being wound with the required number of turns of wire 1862. In the illustrated example, three (3) layers of wire are wound onto the bobbin element with fifty-two (52) turns of
15 wire being wound in each layer. The layers are constructed with the first layer being wound from left-to-right; the second layer being wound from right-to-left; and the third layer being wound again from left-to-right, although other numbers of layers and/or lay patterns may be used consistent with the invention. For instance, all of the turns (e.g., 52 in this example) could be wound in a single layer in one direction.
20 Alternatively, a two-layer back-and-forth pattern could be utilized.

FIG. 18G illustrates the routing of the wire 1862 from the newly wound end bobbin element to an adjacent bobbin element. Note that both bobbin elements shown include a transition feature 1863 comprised of a protrusion that includes a curved edge. This curved edge helps prevent damage to the wire as it is routed between
25 adjacent bobbin elements. The adjacent bobbin element is then wound identically to that seen in FIG. 18F (i.e. with three (3) layers comprised of fifty-two (52) turns each. The remaining bobbin elements 1810 are then similarly wound as illustrated in FIG. 18H.

FIG. 18I illustrates the end of the winding 1862 subsequent to being routed
30 over each of the previously discussed bobbin elements, and secured to the starting clip 1890. Similar to the end clip, the wire is secured to the starting clip by wrapping the wire around the start clip twice, although other mechanisms may be used.

FIG. 18J illustrates the winding of the shielding layer 1864 onto the bobbin elements. As can be seen in FIG. 18J, the shielding layer is composed of an additional layer of fifty-two (52) turns that are wound in the opposite direction of the previously wound winding layers. Note also that the wire that makes up the shielding wire is the same wire that was used to previously wind the bobbin elements. The process is continued on as shown in FIG. 18K, with the remaining bobbin elements each receiving a shielding layer. The use of the same wire that was used in the previous windings is particularly advantageous from the perspective of manufacturing cost. As the bobbin elements are already disposed onto a winding mandrel for the purposes of automating the placement of the windings, no additional processing steps need to be performed by an operator in order to wind the shielding layer onto the bobbin elements. Accordingly, the only additional costs added to the device by adding the shielding layer comes from the additional time the bobbin elements spend on the winding mandrel, which is minimal, along with the added material cost associated with the shielding layer which is also minimal. Furthermore, it has been found that the use of the same wire 1862 for the shielding layer is just as effective at providing shielding for the device as other more labor intensive methods which utilize copper foil, etc.

FIG. 18L illustrates how the wire 1862 is secured to the bobbin element assembly. Specifically, FIG. 18L illustrates how the end of the shielding layer wire is secured at the end bobbin element. Essentially, a single turn of tape 1870 is wound onto the end bobbin element and the end of the wire 1862 is then routed over this single layer of tape and subsequently secured by the additional wrapping of extra layers of tape. Both the excess wire 1862 and excess tape 1870 is then trimmed. Note that the end of the shielding layer wire is not secured to the end clip 1892.

Referring now to FIG. 18M, the wound bobbin elements are removed from the mandrel and the wire is secured to both the end clip 1892 and the starting clip 1890 (not shown). The securing of the wire to these clips can be accomplished in any number of differing ways. One implementation utilizes a resistance welding process to weld a portion 1866 of the wire to the respective clips. Alternatively, a eutectic soldering operation could be used to physically and electrically secure the wire to the respective clips. Yet other methods will be recognized by those of ordinary skill given the present disclosure.

FIG. 18N illustrates the installation of the return wire 1850. The return wire is inserted into the central passageway of the starting end bobbin element (i.e., the end with start clip 1890) and routed through each of the bobbin elements until it meets the end clip element 1892 on the end bobbin segment. This return wire 1850 is then subsequently electrically secured to the end clip 1892 via a eutectic soldering operation, resistance welding, etc. FIG. 18O illustrates that the finish wire 1852 is secured to the start clip 1890. Again this can be accomplished by using e.g., either solder or resistance welding to secure the finish wire to the start clip on the starting bobbin element.

FIG. 18P illustrates the insertion of the bobbin element assembly into a housing 1880. The end bobbin element 1810 (i.e., the bobbin with tape 1870 mounted thereon) is inserted into a respective cavity 1886 located on the housing first, and subsequent bobbin elements are inserted into their respective housing cavities around the ring-like shape of the housing. Note also that the end bobbin element is disposed adjacent the finish wire groove 1884 and return wire groove 1882 associated with the housing.

FIG. 18Q illustrates the finish wire 1852 and return wire 1850 after being inserted into their respective grooves of the housing. Note that the finish wire 1852 is disposed on top of the return wire in the illustrated embodiment which keeps the wires close together for the purposes of mitigating unwanted external electrical interference.

Referring now to FIG. 18R, small drops of epoxy 1888 or another adhesive is inserted into each of the cavities 1889 of the top housing 1883. In addition, a light bead of epoxy is also applied to the middle hole wall 1887. The top housing 1883 is then mounted onto the housing 1880 as illustrated in FIG. 18S. The finish wire 1852 and return wire 1850 are then twisted together in a clockwise direction for the purposes of mitigating the effects of external electrical interference.

It will be recognized that while certain aspects of the invention are described in terms of a specific sequence of steps of a method, these descriptions are only illustrative of the broader methods of the invention, and may be modified as required by the particular application. Certain steps may be rendered unnecessary or optional under certain circumstances. Additionally, certain steps or functionality may be added to the disclosed embodiments, or the order of performance of two or more steps

permuted. All such variations are considered to be encompassed within the invention disclosed and claimed herein.

While the above detailed description has shown, described, and pointed out novel features of the invention as applied to various embodiments, it will be understood
5 that various omissions, substitutions, and changes in the form and details of the device or process illustrated may be made by those skilled in the art without departing from the invention. The foregoing description is of the best mode presently contemplated of carrying out the invention. This description is in no way meant to be limiting, but rather should be taken as illustrative of the general principles of the invention. The scope of
10 the invention should be determined with reference to the claims.

WHAT IS CLAIMED IS:

1. A current sensing inductive device, comprising:
a plurality of inductive elements, each element comprised of a conductive winding; and
5 a return conductor that electrically couples a leading one of said plurality of inductive elements with a trailing one of said plurality of inductive elements;
wherein a first element of said plurality of inductive elements includes a first conductive element, said first conductive element electrically coupling said return conductor to a first end of said conductive winding.
- 10 2. The current sensing inductive device of Claim 1, wherein said plurality of inductive elements each comprise a discrete bobbin element.
3. The current sensing inductive device of Claim 2, further comprising a second conductive element disposed on a second one of said plurality of bobbin elements, said second conductive element attached to an end of said conductive
15 winding opposite the first end of said conductive winding.
4. The current sensing inductive device of Claim 3, wherein said second conductive element is bent at a defined angle with respect to a surface of said second one of said plurality of bobbin elements.
5. The current sensing inductive device of Claim 2, wherein said first
20 conductive element is disposed on or within a flange of said first bobbin element.
6. The current sensing inductive device of Claim 2, wherein at least two of said plurality of bobbin elements are physically coupled to one another via a hinged coupling.
7. The current sensing inductive device of Claim 6, wherein said hinged
25 coupling comprises:
a pair of outer hinge features disposed on a first of said plurality of bobbin elements;
a pair of inner hinge features disposed on a second of said plurality of bobbin elements; and
30 a hinge pin disposed within said pairs of inner and outer hinge features.
8. The current sensing inductive device of Claim 7, further comprising a housing that encases said plurality of bobbin elements, said housing including a hinge pin receiving aperture sized to accommodate said hinge pin.

9. The current sensing inductive device of Claim 8, wherein said housing further comprises a plurality of hinge pin receiving apertures, said hinge pin receiving apertures adapted to position and align said plurality of bobbin elements with respect to one another.

5 10. The current sensing inductive device of Claim 6, wherein each of said bobbin elements comprises a pair of flanges with a winding spool disposed substantially therebetween, said conductive winding wound onto said winding spool.

11. The current sensing inductive device of Claim 10, wherein said hinged coupling comprises an aperture and a cavity on a first one of said plurality of bobbin
10 elements; and

a coupling element comprised of a winding spool portion and an insertable portion on a second one of said plurality of bobbin elements;

wherein said winding spool portion of said second one of said plurality of bobbin elements fits within said cavity of said first one of said plurality of bobbin
15 elements, while said insertable portion of said second one of said plurality of bobbin elements simultaneously fits within said aperture of said first one of said plurality of bobbin elements.

12. The current sensing inductive device of Claim 1, wherein each of said plurality of inductive elements comprises a linearly wound inductive element, each
20 element having said conductive winding disposed thereon, said conductive winding disposed in two or more layers of windings.

13. The current sensing inductive device of Claim 12, wherein at least one of said two or more layers of windings comprises a shielding layer.

14. The current sensing inductive device of Claim 13, wherein said
25 shielding layer is only electrically coupled to one of said leading or trailing ones of said plurality of linearly wound inductive elements.

15. The current sensing inductive device of Claim 12, wherein at least a portion of said plurality of linearly wound inductive elements comprises a winding barrel with a pair of flanges disposed on either side of said winding barrel.

30 16. The current sensing inductive device of Claim 15, wherein a first of said pair of flanges comprises a boss and a second of said pair of flanges comprises a boss mating aperture; and

wherein said boss is adapted to be received within an adjacent boss mating aperture to facilitate the winding of the plurality of linearly wound inductive elements.

17. A method of manufacturing a current sensing inductive device, comprising:

5 securing an insulated conductor to a first end of a plurality of segmented winding elements;

 continuously winding said insulated conductor onto said plurality of segmented winding elements;

 securing said insulated conductor to a second end of said plurality of segmented winding elements;

10 routing a return conductor between each of said plurality of segmented winding elements; and

 electrically coupling said return conductor with said insulated conductor so as to form said current sensing inductive device.

15 18. The method of Claim 17, wherein said act of securing said insulated conductor to said second end facilitates the electrical coupling of said return conductor with said insulated conductor.

 19. The method of Claim 18, wherein said act of securing said insulated conductor to said second end comprises wire wrapping said insulated conductor to a conductive clip, said conductive clip disposed on said second end of said plurality of segmented winding elements.

20 20. The method of Claim 19, further comprising securing said return conductor to said conductive clip.

 21. The method of Claims 17, further comprising continuously winding said insulated conductor onto said plurality of segmented winding elements in a reverse direction subsequent to said act of securing said insulated conductor to said second end of said plurality of segmented winding elements.

25 22. The method of Claim 21, wherein the insulated conductor wound onto said plurality of segmented winding elements in said reverse direction is wound in a single layer winding.

30 23. A support structure for use in a current sensing inductive device, said support structure, comprising:

 a plurality of bobbin elements;

wherein at least a portion of said plurality of bobbin elements include one or more connection features, said connection features utilized for joining at least said portion to other of said plurality of bobbin elements adjacent thereto so as to form said support structure.

5 24. The support structure of Claim 23, wherein said connection features comprise:

 a hinge feature that allows for a movable relationship between joined bobbin elements.

 25. The support structure of Claim 24, wherein the hinge feature comprises
10 a first set of spaced hinge elements, each of said hinge elements including an aperture disposed at least partly there through.

 26. The support structure of Claim 23, wherein said connection features comprise:

 a flexible hinge feature; and
15 an aperture that is sized to accommodate the flexible hinge feature of an adjacent one of the bobbin elements.

 27. The support structure of Claim 26, wherein the flexible hinge feature is integrally molded with the bobbin element to which the flexible hinge feature is associated.

20 28. A bobbin element for use in a current sensing inductive device, said bobbin element, comprising:

 a spool element comprised of an outer winding diameter and defining an interior volume; and

 a pair of flange features disposed on opposing ends of said spool element.

25 29. The bobbin element of Claim 28, wherein at least one of the pair of flange features includes an electrically conductive clip disposed therein.

 30. The bobbin element of Claim 29, wherein a portion of the electrically conductive clip is received within the interior volume of the spool element.

30 31. The bobbin element of Claim 30, wherein an end of the electrically conductive clip includes a notched end for wire wrapping of a conductor.

 32. The bobbin element of Claim 28, wherein the interior volume includes a return conductor support feature disposed therein, the return conductor support feature

adapted to position a return conductor at a predetermined position with respect to said spool element.

33. The bobbin element of Claim 32, wherein the predetermined position comprises the geometric center of the spool element.