

REPLACED SHEETS		SG
☒	Description : paged 1 to paged 4	
☒	Claim(s) : paged 10 to paged 11	
☒	Drawing(s) : paged 14 to paged 14	
☒	Abstract : paged 12 to paged 12	
DATE OF RECEIPT		

710499-9 2805

FM DEMODULATION CIRCUIT

BACKGROUND OF THE INVENTION

The present invention relates to an FM demodulation circuit, more specifically to an FM demodulation circuit using PLL circuit.

In recent years, the mobile vehicle communication system utilizing FM modulation has been widely employed. From the view point of miniaturization requirement for portability of the radiowave equipment, LSI technology has been rapidly progressed. This tendency is also seen in FM demodulation circuit. The FM demodulation circuit using PLL has been popular with the progress of LSI technology and may be established by the process of C-MOS and the like suitable for LSI technology.

The conventional FM demodulation circuit using PLL will be described by reference to FIG.2. In FIG.2, an FM signal supplied from a signal input terminal 1 is inputted to a phase comparator 2 to detect a phase difference between the frequencies of the input signal from a comparison signal oscillator 3 and the FM signal. A comparison detection signal corresponding to the phase difference is sent to the comparison signal oscillator 3 to make a coincidence between the phase of the oscillation frequency signal of the comparison signal oscillator 3 and that of the FM signal. The comparison detection signal obtained in the phase comparator 2 is the DC voltage corresponding to the modulated frequency of the FM signal and is outputted from a demodulation signal output terminal



4 as the FM demodulation signal.

In such conventional FM demodulation circuit, required is that the oscillation frequency of the comparison signal oscillator 3 is coincident with the frequency of the FM signal to be demodulated. However, if a frequency variable range of this oscillation deviates due to, for example, temperature rise, the frequencies will not be coincident owing to a limitation of the comparison detection signal (DC voltage) from the phase comparator 2, causing a distortion in the FM demodulation signal.

FIG.3 shows relationships between the comparison detection signal (corresponding to the oscillation frequency voltage) and the oscillation frequency for two conditions, i.e., the normal condition of the normal variable range of the oscillation and the deviation condition from the normal condition. In the normal condition as shown in FIG.3A, the accurate comparison detection voltage may be obtained depending upon the frequency of the FM signal to be demodulated. However, when the deviation occurs as shown in FIG.3B, the frequencies are not coincident even the comparison detection signal reaches the limit value due to the nonlinear characteristics, causing the distortion in the comparison detection signal (demodulated signal).

More concretely, it is assumed now that the output voltage range generated from the phase comparator 2 is +1 to +4 V. Normally, when a power source voltage for exciting the phase comparator 2 is +5 V, the phase comparator 2 is



capable of generating the output voltages of +1 V to +4 V.

Referring to Fig. 3A illustrating the normal characteristic at the room temperature, the oscillation frequency varies from -16 kHz to +24 kHz with the frequency control input terminal voltage of +0 V to +5 V for the carrier frequency 455 kHz. When the modulation frequency range of the FM demodulation signal to be FM demodulated is -8 kHz to +8 kHz, the frequency control signal voltage (output voltage of the phase comparator 2) ranges from +1 V to +3 V. On the other hand, as shown in Fig. 3B, when the characteristic of the comparison signal oscillator 3 deviates due to the external condition change such as the temperature rise, the voltage range of +0.5 V to +2.5 V is required as the frequency control signal for accurate response to the modulation frequency range of -8 kHz to +8 kHz.

However, since the phase comparator 3 can not generate the voltage lower than +1 V, the demodulation signal is maintained at +1 V for the frequency range from 455 kHz -4 kHz to 455 kHz +8 kHz of the signal to be FM demodulated, resulting in the demodulation signal distortion.

In order to solve this problem, it is required to adjust the respective oscillation frequency characteristic of the comparison signal oscillators. However, there has been no LSI circuit equipped with means for adjusting the respective deviations of the comparison signal oscillators.

SUMMARY OF THE INVENTION

It is therefore an object of the present invention to



provide an FM demodulation circuit capable of eliminating the deterioration of the linear demodulation characteristics due to the deviation of the oscillation frequency, and of adjusting the respective characteristic
5 deviations of the comparison signal oscillators.

According to the present invention there is provided an FM demodulation circuit comprising, an oscillation circuit means whose oscillation frequency is variable by a control signal, a phase comparator means for comparing
10 phases of signals between an FM signal to be demodulated and the output signal of the oscillation circuit means and generating a comparison signal corresponding to the phase difference, an additional voltage determining means for determining an additional voltage based upon the comparison
15 signal, and an adder means for adding the comparison signal and the additional voltage, and supplying the added result as the control voltage.

The additional voltage determining means may comprise an A/D converter for converting the comparison signal into
20 a digital signal, memory for storing the determined additional voltage data, and a D/A converter for converting the additional voltage data read out from the memory into an analogue signal, and supplying the converted analogue signal to the adder means.

25 The additional voltage may be a value which makes the comparison signal level at a center level of the operable range of the phase comparator means or a difference value between a center level of the operable range of the phase



comparator means and the comparison signal from the phase comparator means when an unmodulated carrier signal without being modulated is inputted to the phase comparator means.

In another aspect the invention provides an FM demodulation circuit comprising an oscillator whose oscillation frequency is variable by a control signal; a phase comparator for comparing the phases of an FM signal to be demodulated and the oscillator frequency and for generating a comparison signal indicative of the phase difference; compensating means for modifying the comparison signal to compensate for changes in an operating characteristic of the oscillator; and means for applying the modified comparison signal to the oscillator as said control signal.

The compensating means may be adapted to modify the comparison signal such that the comparison signal is at the centre of the output range of the phase comparator when the oscillator output frequency is equal to the carrier frequency of the FM signal.

Other objects and features of the invention will be clarified from the following description with reference to the attached drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a block diagram illustrating one embodiment of an FM demodulation circuit according to the present invention.

FIG. 2 is an example of a block diagram of the conventional FM demodulation circuit.

FIG. 3 is a graph showing the demodulation characteristic in the case that the oscillation frequency characteristic is deviated from the normal operation characteristic.



DESCRIPTION OF PREFERRED EMBODIMENTS

The present invention will now be described in detail by way of example only with reference to the accompanying drawings.

Illustrated in FIG. 1 is a block diagram of an embodiment according to the present invention. The signal input terminal 1, the phase comparator 2, the comparison signal oscillator 3, and the demodulation signal output terminal 4 are the same as those in the conventional circuit shown in FIG. 2. An adder 5 is inserted into the input side of the comparison signal oscillator 3. To the inputs of the adder 5 supplied with the comparison detection signal from the phase comparator 2 and data signal from an additional



voltage setting means. The additional voltage setting means comprises an A/D converter 6, a data processing circuit 7, an additional data memory 8, and a D/A converter 9.

The adder 5 adds the DC voltage from the D/A converter 9 and the comparison detection signal from the phase comparator 2, and outputs the added result to the frequency control signal input terminal of the comparison signal oscillator 3. The A/D converter 6 converts the comparison detection signal into the digital data signal and sends the digital data signal to the data processing circuit 7. The required additional voltage to obtain an appropriate comparison detection signal is determined based upon the input data signal in the data processing circuit 7, and is stored in the additional data memory 8. From the additional data memory 8, the stored appropriate data signal is supplied to the D/A converter 9. The D/A converter 9 converts the additional voltage read out from the additional data memory 8 into the analog signal, and outputs it to the adder 5.

According to the above circuit, if no additional voltage is exist (0 V), the comparison detection signal is supplied to the frequency control input terminal of the comparison signal oscillator 3, and the similar operation is executed. On the other hand, if the deviation of the oscillation frequency of the comparison signal oscillator 3 is caused and the voltage signal higher than the limit value of the comparison detection signal is required, the appropriate additional voltage is determined in the data



processing circuit 7 and is added to the comparison detection signal by the adder 5. The comparison signal oscillator 3 operates by this additional voltage.

According to the foregoing operation, the oscillation
5 frequency of the comparison signal oscillator 3 is made coincident with that of the FM signals, eliminating the distortion of the demodulated signal.

It is to be noted here that the voltage at frequency control input terminal of the comparison signal oscillator
10 3 becomes higher as much as the additional voltage when the additional voltage is added to the comparison detection signal. On the contrary, the FM signal is compared with the output of the comparison signal oscillator 3 in the phase comparator 2, therefore the generated FM signal and
15 the output of the comparison signal oscillator 3 become lower as much as the amount of the additional voltage. That is, the comparison detection signal varies inversely as much as the amount of the additional voltage. The additional voltage may be determined as a value which makes
20 the comparison detection signal level; at a center level of the operable range of the phase comparator 2 when the carrier signal without being modulated is inputted in the phase comparator 2.

More specifically, in the foregoing case with
25 reference to Figs. 3A and 3B, the output range of +1.5 V. to +3.5 V of the phase comparator 2 at the room temperature is obtained by adding -0.5 V to the comparison detection signal in the adder 5. As a result, the control with the



voltage of +1 V to +3 V is realized under the deviation of 0.5 V in the oscillation frequency due to the temperature change is caused, eliminating the demodulation signal distortion. Thus, even if the voltage becomes higher than
5 the limit value of the comparison detection signal due to the oscillation frequency deviation of the comparison detection signal, the demodulation distortion is eliminated by adding the appropriate additional voltage.

The determination process of the additional voltage in
10 the data processing circuit 7 will be explained hereunder. As the initial set for the adjustment, inputted to the signal input terminal 1 is the carrier signal without being modulated having a center modulation frequency of 455 kHz. At that time, the output voltage V_T from the phase
15 comparator 2 is supplied to the data processing circuit 7 through the A/D converter 6. The data processing circuit 7 determines the additional voltage V_H using the voltage V_T so as to set the output voltage of the phase comparator 2 at +2.5 V which is a center level, or voltage of the range
20 +1 V to +4 V, i.e., $V_H = +2.5 - V_T$. The determined additional voltage V_H is memorized in the additional data memory 8. In the normal demodulation operation the voltage V_H read out from the memory 8 is supplied to the adder 5 through the D/A converter 9.


25 As described in the foregoing, the present invention improves the limitation of the operable range of the phase comparator 2 due to the oscillation frequency deviation of the comparison signal oscillator 3 by adding the additional



voltage to the comparison detection signal, maintaining the linear demodulation characteristics. Providing the circuit to memorize the additional voltage may adjusts the individual deviation of the comparison signal oscillator 3.

This Sheet Has Been Replaced





What is claimed is:

1. An FM demodulation circuit comprising:

an oscillation circuit means whose oscillation frequency is variable by a control signal;

a phase comparator means for comparing phases of signals between an FM signal to be demodulated and the output signal of said oscillation circuit means and generating a comparison signal corresponding to the phase difference;

an additional voltage determining means for determining an additional voltage based upon said comparison signal; and

an adder means for adding said comparison signal and said additional voltage, and supplying the added result as said control signal.

2. The FM demodulation circuit as set forth in claim 1, wherein said additional voltage determining means comprises, an A/D converter for converting said comparison signal into a digital signal, memory for storing the determined additional voltage data, and a D/A converter for converting the additional voltage data read out from said memory into an analogue signal, and supplying the converted analogue signal to said adder means.

3. The FM demodulation circuit as set forth in claim 1, wherein said additional voltage determining means determines the additional voltage as a value which makes the comparison signal level at a center level of the operable range of said phase comparator means.





4. The FM demodulation circuit as set forth in claim 1, wherein said additional voltage is determined as a difference value between a center level of the operable range of said phase comparator means and the comparison signal from said phase comparator means when an unmodulated FM carrier signal is inputted to the phase comparator means.

5. An FM demodulation circuit comprising
an oscillator whose oscillation frequency is variable by a control signal;

a phase comparator for comparing the phases of an FM signal to be demodulated and the oscillator frequency and for generating a comparison signal indicative of the phase difference;

compensating means for modifying the comparison signal to compensate for changes in an operating characteristic of the oscillator; and

means for applying the modified comparison signal to the oscillator as said control signal.

6. The FM demodulation circuit as set forth in Claim 5 wherein the compensating means is adapted to modify the comparison signal such that the comparison signal is at the centre of the output range of the phase comparator when the oscillator output frequency is equal to the carrier frequency of the FM signal.

