

Description

The present invention relates generally to the field of cardiac defibrillation and in particular to an apparatus for applying to the body of a patient a voltage calculated to induce in that particular patient a desired defibrillation current.

A defibrillator is a device used to administer a high voltage shock pulse through a pair of electrodes, or "paddles," to the chest of a patient in cardiac arrest. A selected, discrete quantity of energy is stored in a capacitor and is then electrically discharged into the patient through the paddle circuit. In prior art devices, the quantity of energy is typically selected on the basis of patient size, weight and condition.

The success achieved with such prior art devices has been variable. While an energy of 150 joules might successfully defibrillate one patient, another ostensibly comparable patient may not respond until the energy level is raised to 360 joules. The risk of damage to the myocardium from large defibrillation shocks dictates that defibrillation should be attempted with the lowest energy practicable. However, delays associated with charging the defibrillator to successively higher energy levels if lower energy pulses fail increase the risk of patient brain damage due to oxygen deprivation.

The differing responses of patients to a given defibrillation pulse is believed attributable, in significant part, to patients' differing transthoracic impedances. Transthoracic impedance is the term given the load resistance presented by a patient at the paddles during defibrillation and determines, *inter alia*, the fraction of energy stored in the storage capacitor that is actually delivered to the patient. One type of known defibrillator, shown in U.S. Patent 4,328,808, is able to compute the transthoracic impedance of the patient being defibrillated from measured pre- and post-discharge parameters. This information can be used by the operator as an aid in selecting the energy of a second defibrillation pulse if the first pulse proves ineffective.

In an article by Kerber et al. entitled "Automated Impedance-Based Energy Adjustment for Defibrillation: Experimental Studies," *Circulation*, Vol. 71, No. 1, pp. 136-140 (1985), there is described an experimental animal defibrillator in which transthoracic impedance is detected in advance of defibrillation by using a low current A.C. sampling signal. The defibrillation energy level selected by the operator is automatically increased, generally by a factor of two, if the detected patient impedance exceeds 70 ohms. Although an improvement over prior systems, the Kerber et al. system still suffers from a number of deficiencies making it poorly suited for clinical application.

Principal among the deficiencies of the Kerber et al. system is its lack of control over current delivered to the patient. Our work has indicated that defibrillation success as a function of current is optimized in humans about a narrow range of current values for a given pulse shape. For a pulse duration of four milliseconds, the optimum current is approximately 30 amperes. Currents only slightly below this value have a much poorer success rate. The magnitude of transthoracic impedance encountered in typical patients, however, ranges from approximately 15 to 150 ohms, a 10 to 1 ratio, rendering the delivery of an optimum current unlikely if the defibrillator can only alter the operator-selected energy to a single other value.

US-A-4574870 discloses an automatic threshold defibrillator which determines an optimum threshold level of peak defibrillation current by calculation of transthoracic resistance and multiplication of this resistance by an "ampere per ohm factor". The transthoracic resistance is obtained by noting the voltage across electrodes of the defibrillator when a low amplitude current is applied to the electrodes. Further, circuit means are provided for to discontinue the charging of the capacitor when the accumulated charge is sufficient to deliver the selected current to a patient having the measured transthoracic impedance.

Accordingly, a need exists for a defibrillation apparatus that permits selection of a determined defibrillation current for a patient in cardiac arrest, irrespective of the magnitude of that patient's transthoracic impedance.

The primary objective of the present invention, therefore, is to deliver to a patient a defibrillation pulse having a magnitude calculated to induce in that particular patient a desired defibrillation current.

Another object of the present invention is to characterize in advance of defibrillation a patient's transthoracic impedance and to automatically tailor the magnitude of a defibrillation pulse accordingly.

A further object of the present invention is to provide an accurate measurement of transthoracic impedance upon which a computation of an appropriate storage capacitor charge can be based.

According to the invention, there is provided a defibrillator apparatus for delivering an electrical shock to a patient to restore normal cardiac rhythm comprising: a capacitor for accumulating an electrical charge; first and second electrodes for applying an electrical shock from the capacitor to the patient; charging means for charging the capacitor; detector means for detecting the charge accumulated by the capacitor; means for selecting a current which is desired to be delivered to the patient; impedance measuring means for determining a transthoracic impedance of the patient subsequent

to selecting the desired current, the impedance measuring means including means for sampling the patient's transthoracic impedance periodically; and circuit means coupled to the aforesaid means for discontinuing the charging of the capacitor when the accumulated charge is sufficient to deliver the selected current to a patient having the measured transthoracic impedance, including means for determining the charge accumulation required to deliver the desired current to a patient having a transthoracic impedance equal to the lowest value of transthoracic impedance sampled, the desired current being delivered, in use, irrespective of the measured transthoracic impedance.

In accordance with the preferred embodiment of the present invention, an apparatus is provided for characterizing in advance of defibrillation the response of a patient to a defibrillation pulse and determining therefrom the voltage that must be applied to the patient to induce a desired defibrillation current to flow. The patient's response to a defibrillation pulse is characterized by repeatedly sampling the patient's transthoracic impedance to a small alternating current excitation signal. The impedance sample having the lowest magnitude is taken to represent the patient's true transthoracic impedance, with higher values being attributed to varying degrees of patient contact resistance.

The lowest sampled impedance is normalized to take into account the shape of the expected waveform with which the stored charge will be delivered. In defibrillators employing a capacitor as the energy storage device, this normalized factor is multiplied by the desired current to yield a target voltage level to which the capacitor must be charged to induce the desired current to flow in the patient on discharge. If a different form of energy storage device is used, a different scaling factor is used to relate patient impedance to energy storage requirements. Charging of the capacitor desirably begins before the measurement of transthoracic impedance is completed and continues until the target voltage level is reached. Discharge of a capacitor so charged causes the desired current flow through the patient.

These and other objects, features and advantages of the present invention will be more readily apparent from the following detailed description of a preferred embodiment thereof, which proceeds with reference to the accompanying drawings.

Brief Description of the Drawings

Fig. 1 is a functional block diagram illustrating the preferred embodiment of the present invention.

Fig. 2 is a functional block diagram of the impedance sampling circuit included in Fig. 1.

Fig. 3 is a flow chart detailing the sequence of steps executed by the embodiment of Fig. 1.

Description of Preferred Embodiment

Fig. 1 is a functional block diagram illustrating the basic arrangement of a current-based defibrillator 10 in accordance with the preferred embodiment of the present invention. The apparatus includes an energy storage device 12 such as a capacitor, paddles 14 for applying an electrical shock from the capacitor to a patient 16 and an energy source 18 for charging the capacitor. A detector 20 detects the charge accumulated by the capacitor and feeds this data back to a comparator/charge control circuit 22 which controls the capacitor's charging accordingly.

Charging of the capacitor continues until the voltage across the capacitor reaches a target value. This target value is determined by a multiplier 24 which multiplies the magnitude of current desired to be delivered to the patient, I_d , with a normalized impedance factor, Z_0 . I_d is selected by the operator using a selector switch 26. Z_0 is retrieved from a look-up table 28 in response to transthoracic impedance measurements made by an impedance measurement system 30.

Impedance measurement system 30 includes an impedance sensing circuit 32 that excites the patient with a low current A.C. excitation signal through paddles 14 and produces a corresponding output signal related to the patient's transthoracic impedance at the excitation signal frequency. In the preferred embodiment, the excitation signal has a frequency of 31 kilohertz, a frequency at which the patient's transthoracic impedance closely approximates the patient's impedance to a high current defibrillation pulse. In alternative embodiments, however, other excitation signal frequencies can be used and the non-linear correspondence with the patient's response to a high current defibrillation pulse can be reflected in the scaled impedance factors stored in look-up table 28.

Impedance sensing circuit 32 is connected to paddles 14 by relay contacts 66. The relay is arranged so that relay contacts 66 are closed when relay contacts 68, connecting the energy storage capacitor to the paddles, are open, and vice versa. Relay contacts 66 are normally closed at all times except when the storage capacitor is actually being discharged into the patient.

Impedance sensing circuit 32 is shown in more detail in Fig. 2. A 31 kilohertz, five volt peak-to-peak square wave signal generator 70 drives a voltage divider comprised of resistors 72 and 74 to produce a 25 millivolt (peak-to-peak) signal at circuit node 76. This 25 millivolt signal is applied to the primary winding of an isolation transformer 78,

the secondary of which is connected to defibrillator paddles 14 through relay contacts 66.

The patient impedance between paddles 14 is reflected across transformer 78 and becomes an element of the gain setting circuitry of a high gain amplifier 80. With resistors 82 and 84 having values of 31.6 and 1210 ohms respectively, the gain of amplifier 80 equals $1210/(31.6 + Z_p)$ where Z_p is the magnitude of the impedance reflected from the patient across the primary winding.

The output of amplifier 80 is fed to the input of a band pass filter 86 which extracts and amplifies the fundamental frequency component of the 31 kilohertz square wave, yielding a sine wave at its output. This sine wave output signal has an amplitude which is a function of the impedance between paddles 14. The output of filter 86 is then input to a peak detector 88 which stores the peak value on a capacitor 90.

The foregoing arrangement provides a continuous voltage signal corresponding inversely to the patient's transthoracic impedance. This relationship is non-linear and is empirically characterized for a given implementation. In the illustrated embodiment, an output of four volts corresponds to a patient impedance of 0 ohms and an output of 0.125 volts corresponds to a patient impedance of 255 ohms. This relationship can also be derived from the gain characteristics of amplifier 80, filter 86 and peak detector 88.

The analog signal at the output of impedance sensing circuit 32 is provided to an eight bit analog-to-digital converter 38, such as a National Semiconductor type ADC-0844, which periodically samples the analog signal and converts each sample into digital form. If the signal provided to converter 38 has a magnitude of less than 1.25 volts, it is desirably amplified by an additional factor of four. Such amplification provides two additional data bits of digital resolution for low amplitude signals.

The frequency at which A/D converter 38 samples the output of impedance sensing circuit 32 is dictated by an associated single board computer (SBC) 34 and is approximately 240 hertz in the preferred embodiment. Computer 34 is built around an Intel 8052 microprocessor and 8K of associated ROM and implements many of the subsequent processing functions illustrated in Fig. 1. The A/D sampling continues during a predetermined measurement period, here termed the patient contact indication (PCI) interval, the length of which is set by a software implemented decrementing timer 36 in computer 34. This period is typically about two seconds, a period long enough to yield approximately 500 impedance samples.

The samples output from A/D converter 38 are provided to single board computer 34 for further

processing. The first processing step is to low pass filter the digitized voltage using a software implemented filter 40 to remove the 20 to 40 millivolts of noise that may be impressed on this signal. The filtered, digitized voltage signal is then used to index a first look-up table 42 that correlates the output from A/D converter 38 to the patient's transthoracic impedance.

First look-up table 42, together with the other look-up tables illustrated in Fig. 1, are implemented using the ROM memory associated with single board computer 34. Table 42 is arranged in two segments, with the second segment relating to those signals from A/D converter 38 which have been amplified by an additional factor of four to provide increased resolution. A total of approximately 500 pairs of entries are provided in this first table memory.

Each transthoracic impedance value retrieved from first look-up table 42 is compared by a minimum impedance detector 44 against a minimum impedance value, Z_{pmin} , stored in a register 46 in the microprocessor. This register is initially loaded with a value of 255 ohms (FF hex). Thereafter, as each of the impedance values is retrieved from table 42, it is compared with the register value. If a sampled impedance value is lower than the previously stored minimum, the register is loaded with the new minimum value. At the end of the two second PCI interval, this Z_{pmin} register contains the lowest impedance value sampled during the interval. This impedance value is sent to a strip chart recorder 48 for display. The minimum sampled impedance value obtained by this technique is believed more accurately to reflect the patient's true transthoracic impedance, with higher sampled values being attributed to poorer contact between the paddles and the patient.

At the conclusion of the two second sampling interval, the lowest transthoracic impedance value detected is used as an index into a second look-up table memory 28. Look-up table 28 provides a normalized impedance factor Z_o as its output that is used to compute the capacitor charge needed to deliver the desired current to the patient, taking into account the shape of the defibrillation pulse's waveform.

It will be recognized that the energy stored in storage capacitor 12 is solely a function of the voltage on the capacitor and its capacitance, by the formula $E = 1/2 CV^2$. The peak current delivered to the patient on discharge of the capacitor, however, depends in large part on the shape of the waveform with which this energy is delivered. The shape of the waveform depends, inter alia, on the capacitance, inductance and resistance of the discharge path. The resistance of the discharge path includes not only the transthoracic impedance of

the patient but also the loss resistance of the defibrillator itself, about eleven ohms in the illustrated embodiment. The normalized impedance factor provided by look-up table 28 thus reflects the correlation between peak delivered current as a function of patient impedance for the particular characteristics of the defibrillator's discharge path. This correlation can be established empirically or by resort to mathematical modelling of the discharge circuit.

The normalized impedance factor output from second look-up table 28 is provided to a first input of a multiplier stage 24. A signal responsive to selector switch 26 is provided to the multiplier's second input.

Selector switch 26, by which the operator selects the desired defibrillation current, I_s , provides a four-bit digital signal to the input of a third look-up table 50. Third look-up table 50 converts the setting of switch 26 into an 8-bit digital signal representing the selected current to be delivered to the patient. This is the signal applied to the second input of multiplier 24. The multiplication of the 8-bit current signal from third look-up table 50 with the 8-bit normalized impedance factor signal from second look-up table 28 yields a 16-bit output signal representing the final target voltage to which capacitor 12 is to be charged. This sixteen bit result is stored in two eight bit voltage limit registers 52 associated with a voltage limit stage 54.

Capacitor 12 is charged to the voltage limit stored in registers 52 by an energy source 18. Energy source 18 can comprise a conventional flyback charger in which a 14 volt DC battery source is applied to one end of a transformer winding and the bottom end of that winding gated on and off to ground. Suitable chargers are described in U.S. Patents 4,233,659 and 4,119,903, both to Pirkle and assigned to the present assignee.

The charge on capacitor 12 is sampled through a 1000 to 1 voltage divider network 20 and is converted into digital form by a second analog-to-digital converter 56. Second A/D converter 56 is actually a second channel of the National Semiconductor ADC 0844 circuit employed for first A/D converter 38. Again, like the first A/D converter, the analog voltage applied to the input of second A/D converter input is multiplied by a factor of four if its magnitude is less than 1.25 volts. By this technique, increased resolution of low voltages is provided.

The output from second A/D converter 56 is periodically stored in a capacitor voltage register 58 and is compared by comparator/charge control circuit 22 against the limit voltage value stored in voltage limit registers 52. As long as the capacitor's voltage is less than this stored limit, capacitor

charge control 22 allows energy source 18 to continue charging the capacitor. When, however, the sampled capacitor voltage equals or exceeds the limit voltage, charging is terminated.

To expedite charging of storage capacitor 12, it is generally desirable to begin the charging operation before the patient's transthoracic impedance, and consequently the final limit voltage, have been determined. To accomplish this, the patient is initially assumed to have an arbitrary transthoracic impedance and charging is begun towards a corresponding voltage limit. In the preferred embodiment, this initial voltage limit is provided by a fourth look-up table 60 based on a presumed 50 ohm impedance and on the particular current selected. The resultant initial voltage limit is stored in the microprocessor's voltage limit registers 52 for the two seconds of the PCI interval. After the impedance measurement is completed and the final voltage limit has been determined, that final value is substituted for the initial value in the voltage limit registers.

In certain unusual instances, the charge provided to storage capacitor 12 during the two second PCI interval may exceed the charge that is ultimately determined to be required. This may be the case if, for example, the patient's transthoracic impedance is on the order of 20 ohms, a value which would correspond to a relatively low capacitor charge. In such instance, excess charge may be bled off storage capacitor 12 and dissipated in a resistor 62 through a relay circuit 64 connected to the storage capacitor. Second A/D converter 56 and comparator/charge control 22 monitor this discharging of the capacitor and interrupt it when the desired capacitor voltage has been reached.

Fig.3 is a flow chart detailing the various sequences of steps executed by the above-described embodiment of the present invention.

When the instrument is activated, capacitor charge control 22 and voltage limit circuit 54 are reset, resetting the capacitor limit voltage stored in voltage limit registers 52 to zero. When selection switch 26 is operated to initiate circuit operation, an initial Z_{pmth} value of 255 ohms is loaded in minimum impedance register 46 and PCI contact interval timer 36 is initialized to a two second time period. The current I_s corresponding to the selection on switch 26 is then retrieved from third look-up table 50 and is sent to strip chart recorder 48 for display. The initial voltage limit corresponding to the selected current is retrieved from fourth look-up table 60 and is stored in voltage limit registers 52. Capacitor comparator/charge control circuit 22 is then activated.

As the first step in the primary processing loop, second A/D converter 56 provides to comparator/charge control circuit 22 a digital repre-

sensation of the capacitor voltage. This value is stored in capacitor voltage register 58 and is compared with the limit voltage stored in voltage limit registers 52, as illustrated by block A of Fig.3. If the capacitor voltage is less than this limit, the process proceeds to block B to check whether the final voltage limit has yet been determined. If it has not, the process proceeds to block C to examine whether the two second PCI interval has yet expired. If it has not, PCI interval timer 36 is decremented and a new transthoracic impedance sample is taken. The resultant impedance value provided by first look-up table 42 is compared against the previously stored minimum impedance value Z_{pmin} in block D. If it is less than the previously stored minimum value, the old minimum value is replaced by the new value and the processing loop repeats, comparing the capacitor voltage with the limit voltage.

The above-described loop repeats itself at a rate of approximately 240 hertz until the two second PCI timer 36 has timed out. At this point, the process branches from block C and determines the normalized impedance factor Z_0 corresponding to the lowest impedance value Z_{pmin} sampled during the two second interval. Normalized impedance factor Z_0 is provided to multiplier 24 where it is multiplied by the magnitude of I_s to determine the final limit voltage V_f . This final limit voltage is substituted in voltage limit registers 52 which previously contained the initial limit voltage.

The process then checks, in block E, whether the voltage accumulated on capacitor 12 during the two second impedance measuring interval is greater than the final limit voltage which has just been determined. If so, the capacitor is connected through relay contacts 64 to discharge load 62 to bleed off the excess charge. When the charge bleeds down to the desired final voltage, the process returns to block A.

At block A, the voltage on the capacitor is again examined. This time through the loop, the final voltage limit has been determined, so block B causes the process to loop indefinitely, comparing the voltage on the capacitor with the final limit voltage until the limit voltage is reached. At this point, charging of capacitor 12 is discontinued.

It may happen that the voltage limit initially stored in voltage limit registers 52 is reached before the final voltage limit has been determined. In this case, charging is interrupted and the process loops idly through block F until the final voltage limit is determined. If, after the final voltage limit is determined, it is found at block A to be greater than the initial voltage limit which has already been reached, charging will resume until the new, final voltage limit is reached.

After the charge on the capacitor has reached the final voltage limit, the process escapes from the charging loop at block F. The apparatus then sets a ready indicator and awaits a discharge request. If any charge is lost from the capacitor due to the capacitors internal leakage resistance while awaiting a discharge request, a trickle charge circuit (not shown) restores the lost charge.

When a discharge request is received, relay contacts 66 open and relay contacts 68 close, discharging capacitor 12 through the patient. The peak instantaneous current actually delivered to the patient is detected by a current sampling loop (not shown) and the associated energy delivered and patient impedance are calculated using known techniques. These parameters are then sent to strip chart recorder 48 for display.

The invention can be modified in arrangement and detail, for example, while the current delivered to the patient in the illustrated embodiment is controlled by limiting the charge accumulated in the capacitor, the same result can be achieved by providing a current limiting resistance in the capacitor discharge path. Similarly, while the preferred embodiment has been phrased in terms of charging a capacitor up to a desired charge, the same result can be achieved by discharging a fully charged capacitor down to the desired point. It will also be apparent that the energy storage means employed need not be a capacitor. The invention is equally applicable to inductive storage media, in which defibrillation energy is stored in a magnetic field, and to superconducting storage media, in which defibrillation energy is stored as a continuously circulating current.

Claims

1. A defibrillator apparatus for delivering an electrical shock to a patient to restore normal cardiac rhythm comprising:
 - a capacitor (12) for accumulating an electrical charge;
 - first and second electrodes (14) for applying an electrical shock from the capacitor to the patient;
 - charging means (18) for charging the capacitor;
 - detector means (20) for detecting the charge accumulated by the capacitor;
 - means (26) for selecting a current which is desired to be delivered to the patient;
 - impedance measuring means (30) for determining a transthoracic impedance of the patient subsequent to selecting the desired current, the impedance measuring means (32, 38) including means for sampling the patient's transthoracic impedance periodically; and



sensation of the capacitor voltage. This value is stored in capacitor voltage register 58 and is compared with the limit voltage stored in voltage limit registers 52, as illustrated by block A of Fig.3. If the capacitor voltage is less than this limit, the process proceeds to block B to check whether the final voltage limit has yet been determined. If it has not, the process proceeds to block C to examine whether the two second PCI interval has yet expired. If it has not, PCI interval timer 36 is decremented and a new transthoracic impedance sample is taken. The resultant impedance value provided by first look-up table 42 is compared against the previously stored minimum impedance value Z_{pmin} in block D. If it is less than the previously stored minimum value, the old minimum value is replaced by the new value and the processing loop repeats, comparing the capacitor voltage with the limit voltage.

The above-described loop repeats itself at a rate of approximately 240 hertz until the two second PCI timer 36 has timed out. At this point, the process branches from block C and determines the normalized impedance factor Z_0 corresponding to the lowest impedance value Z_{pmin} sampled during the two second interval. Normalized impedance factor Z_0 is provided to multiplier 24 where it is multiplied by the magnitude of I_s to determine the final limit voltage V_f . This final limit voltage is substituted in voltage limit registers 52 which previously contained the initial limit voltage.

The process then checks, in block E, whether the voltage accumulated on capacitor 12 during the two second impedance measuring interval is greater than the final limit voltage which has just been determined. If so, the capacitor is connected through relay contacts 64 to discharge load 62 to bleed off the excess charge. When the charge bleeds down to the desired final voltage, the process returns to block A.

At block A, the voltage on the capacitor is again examined. This time through the loop, the final voltage limit has been determined, so block B causes the process to loop indefinitely, comparing the voltage on the capacitor with the final limit voltage until the limit voltage is reached. At this point, charging of capacitor 12 is discontinued.

It may happen that the voltage limit initially stored in voltage limit registers 52 is reached before the final voltage limit has been determined. In this case, charging is interrupted and the process loops idly through block F until the final voltage limit is determined. If, after the final voltage limit is determined, it is found at block A to be greater than the initial voltage limit which has already been reached, charging will resume until the new, final voltage limit is reached.

After the charge on the capacitor has reached the final voltage limit, the process escapes from the charging loop at block F. The apparatus then sets a ready indicator and awaits a discharge request. If any charge is lost from the capacitor due to the capacitors internal leakage resistance while awaiting a discharge request, a trickle charge circuit (not shown) restores the lost charge.

When a discharge request is received, relay contacts 66 open and relay contacts 68 close, discharging capacitor 12 through the patient. The peak instantaneous current actually delivered to the patient is detected by a current sampling loop (not shown) and the associated energy delivered and patient impedance are calculated using known techniques. These parameters are then sent to strip chart recorder 48 for display.

The invention can be modified in arrangement and detail, for example, while the current delivered to the patient in the illustrated embodiment is controlled by limiting the charge accumulated in the capacitor, the same result can be achieved by providing a current limiting resistance in the capacitor discharge path. Similarly, while the preferred embodiment has been phrased in terms of charging a capacitor up to a desired charge, the same result can be achieved by discharging a fully charged capacitor down to the desired point. It will also be apparent that the energy storage means employed need not be a capacitor. The invention is equally applicable to inductive storage media, in which defibrillation energy is stored in a magnetic field, and to superconducting storage media, in which defibrillation energy is stored as a continuously circulating current.

Claims

1. A defibrillator apparatus for delivering an electrical shock to a patient to restore normal cardiac rhythm comprising:
 - a capacitor (12) for accumulating an electrical charge;
 - first and second electrodes (14) for applying an electrical shock from the capacitor to the patient;
 - charging means (18) for charging the capacitor;
 - detector means (20) for detecting the charge accumulated by the capacitor;
 - means (26) for selecting a current which is desired to be delivered to the patient;
 - impedance measuring means (30) for determining a transthoracic impedance of the patient subsequent to selecting the desired current, the impedance measuring means (32, 38) including means for sampling the patient's transthoracic impedance periodically; and



circuit means (34) coupled to the aforesaid means for discontinuing the charging of the capacitor when the accumulated charge is sufficient to deliver the selected current to a patient having the measured transthoracic impedance, including means for determining the charge accumulation required to deliver the desired current to a patient having a transthoracic impedance equal to the lowest value of transthoracic impedance sampled, the desired current being delivered, in use, irrespective of the measured transthoracic impedance.

2. The apparatus of claim 1 in which the circuit means (24, 28) includes processing means for determining the accumulated charge required in the capacitor to deliver the desired current to a patient having the measured transthoracic impedance.
3. The apparatus of claim 2 in which the processing means includes means (60) for establishing an initial value of accumulated charge towards which the capacitor can be charged while the impedance measuring means is determining the transthoracic impedance of the patient.

Patentansprüche

1. Defibrillator-Einrichtung zum Abgeben eines Elektroschocks an einen Patienten zum Wiederherstellen eines normalen Herz-Rhythmus mit:
einem Kondensator (12) zum Speichern einer elektrischen Ladung,
ersten und zweiten Elektroden (14) zum Übertragen eines Elektroschocks aus dem Kondensator auf den Patienten;
einer Ladevorrichtung (18) zum Laden des Kondensators;
einer Detektorvorrichtung (20) zum Messen der von dem Kondensator gespeicherten Ladung;
Mitteln (26) zum Auswählen eines zur Abgabe an einen Patienten erwünschten Stromes;
einer Impedanz-Meßvorrichtung (30) zum Bestimmen der Transthorax-Impedanz des Patienten auf das Wählen des erwünschten Stromes hin, wobei die Impedanz-Meßvorrichtung (32, 38) Mittel zum periodischen Abtasten der Transthorax-Impedanz des Patienten hat, und einer an die genannten Vorrichtungen bzw. Mittel angeschlossenen Schaltung (34) zum Unterbrechen des Ladens des Kondensators, wenn die gespeicherte Ladung ausreichend zum Abgeben des ausgewählten Stroms zu einem Patienten mit der gemessenen Transthorax-Impedanz ist, wobei die Schaltung Mittel zum Bestimmen der akkumulierten La-

dung aufweist, welche zum Abgeben des erwünschten Stroms zu einem Patienten mit einer Transthorax-Impedanz gleich dem niedrigsten Wert der abgetasteten Transthorax-Impedanz erforderlich ist, und wobei der erwünschte Strom im Betrieb unabhängig von der gemessenen Transthorax-Impedanz abgegeben wird.

2. Einrichtung nach Anspruch 1, bei welcher die Schaltung (24, 28) Verarbeitungsmittel zum Bestimmen der akkumulierten Ladung aufweist, welche an dem Kondensator erforderlich ist, um den erwünschten Strom einem Patienten mit der gemessenen Transthorax-Impedanz zuzuführen.
3. Einrichtung nach Anspruch 2, bei welcher die Verarbeitungsvorrichtung Mittel (60) zum Herstellen eines Anfangswertes der akkumulierten Ladung umfaßt, auf den der Kondensator geladen werden kann, während die Impedanz-Meßvorrichtung die Transthorax-Impedanz des Patienten bestimmt.

Revendications

1. Un appareil défibrillateur destiné à envoyer un choc électrique à un patient afin de restaurer un rythme cardiaque normal comprenant :
un condensateur (12) pour accumuler une charge électrique;
une première et une deuxième électrodes (14) pour appliquer au patient un choc électrique à partir du condensateur;
un moyen de chargement (18) pour charger le condensateur;
un moyen détecteur (26) pour détecter la charge accumulée par le condensateur;
un moyen (26) de choix d'un courant que l'on souhaite envoyer au patient;
un moyen de mesure d'impédance (30), pour déterminer une impédance transthoracique du patient après le choix du courant souhaité, le moyen de mesure d'impédance (31, 38) incluant un moyen d'échantillonnage périodique de l'impédance transthoracique du patient; et
un moyen de circuit (34), couplé auxdits moyens, afin de discontinuer le chargement du condensateur lorsque la charge accumulée est suffisante pour envoyer le courant choisi à un patient présentant l'impédance transthoracique mesurée, incluant un moyen de détermination de l'accumulation de charge nécessaire pour envoyer le courant souhaité à un patient dont l'impédance thoracique est égale à la plus basse des valeurs d'impédance thoracique



échantillonnées, le courant souhaité étant envoyé, en utilisation, quelle que soit l'impédance thoracique mesurée;

2. L'appareil selon la revendication 1 dans lequel le moyen de circuit (24, 28) inclut un moyen de traitement pour déterminer la charge accumulée nécessaire dans le condensateur pour envoyer le courant souhaité à un patient présentant l'impédance transthoracique souhaitée. 5 10

3. L'appareil selon la revendication 2 dans lequel le moyen de traitement inclut un moyen (60) d'établissement d'une valeur initiale de charge accumulée à laquelle le condensateur peut être chargé pendant que le moyen de mesure d'impédance est en train de déterminer l'impédance thoracique du patient. 15 20

25

30

35

40

45

50

55

8