

METHOD FOR OPEN LOOP POWER CONTROL AND BIT RATE SELECTION

5

BACKGROUND OF THE INVENTIONTechnical Field

10 This invention relates generally to the field of signal transmission in a wireless telecommunications network, and more particularly to power control.

Discussion of Related Art

15 In an open loop power control system, transmission power is selected without benefit of immediate feedback, and thus without exact knowledge of the power level necessary to insure faultless signal reception at the other end of the transmission. Consequently, a typical transmitting device in an open loop power control system necessarily makes power estimates based upon incomplete information. If a power estimate is too low, then the signal will not be received at the other end of the transmission; but if the power estimate is too high, then the
20 signal interferes needlessly with other users. Both the problem of low power estimation and the problem of high power estimation occur in the prior art, due to inadequate estimation methods. See, for example, 3rd Generation Partnership Project; Technical Specification Group GERAN; Digital Cellular Telecommunications System, Phase 2t; Radio Subsystem Link Control (3GPP TS 05.08 V8.6.0, September 2000, Annex B, pages 85-88). This is a problem in the
25 downlink from a base station to a mobile device, and in the uplink direction as well.

A further problem with prior art is the problem of fixed bit rate. When bit rate is fixed and constant, then transmission power is correspondingly limited. If the fixed bit rate is high, then high transmission power is required, which may
30 induce excessive interference. However, if the fixed bit rate is low, then the transmission is slower (i.e., large transport time) and the transmission channel is occupied longer at the expense of other users. It is therefore evident that a fixed bit rate makes it difficult or impossible to adjust transmission power so as to minimize both transport time and induced interference. This is a major problem in prior art,

wherein the bit rate is typically a constant, possibly chosen based upon traffic estimation.

Even when the prior art employs a fixed bit rate, the limited flexibility of the transmission power is often not exploited. For example, in the downlink, power transmission in prior art may be a constant that is chosen by radio network planning. In the uplink, power transmission may be adjustable, but only according to the uplink pathloss (i.e., signal attenuation) presumed equal to the measured downlink pathloss. The uplink transmission power may also be adjusted depending upon what sector the mobile transmitter is located in; a sector-specific constant offset may be broadcast in each sector. The rudimentary nature of all of these prior art techniques results in transmission power that induces excessive interference, and results in bit rates that produce excessive transport delays.

DISCLOSURE OF THE INVENTION

The central idea of the present invention is to select bit rate and transmission power so as to minimize the induced interference problem and the transport delay problem. According to the present invention, neither bit rate nor transmission power is constant. In comparison to methods with fixed bit rate or transmission power, the present method makes better use of the available radio resource in diverse load conditions, and the result is higher throughput with lower system interference.

The method and device of the present invention provide a wireless transmission signal having appropriate transmission power and bit rate. To accomplish this, a set of input parameters are used to calculate bit rate and transmission power that minimize a cost function representing induced interference and transport delay. A command signal indicates the calculated bit rate and calculated transmission power in response to the input parameters which were provided by an input parameter signal. The invention then provides the transmission signal having the bit rate and transmission power dictated by the command signal.

The command signal is provided by a computing module in response to the input parameter signal. The command signal is received by a transmitter module, which provides the transmission signal having the bit rate and transmission power determined by the computing module.

5 This invention can operate in either the uplink direction (i.e. from a mobile device to a base station) or the downlink direction (i.e. from a base station to a mobile device), or both, in a wireless telecommunications system. This invention is especially designed for a system employing open loop power control.

10 Brief Description of the Drawings

Figure 1 is a flow chart showing steps of an embodiment of the present invention.

Figure 2 is a diagram showing how the invention works in the uplink direction.

15 Figure 3 is a diagram showing how the present invention works in the downlink direction.

Figure 4 is a diagram showing how the present invention works regardless of whether transmission is uplinked or downlinked.

20 Figure 5 shows the structure of a mobile device according to the present invention.

Figure 6 shows the structure of a base station according to an embodiment of the present invention.

Figure 7 shows how a mobile device, a base station, and a radio network controller interact according to an embodiment of the present invention.

25

Best Mode for Carrying Out the Invention

As can be seen in the flow chart of Figure 1, the best mode for carrying out the present invention essentially involves providing a set of input parameters, calculating from those parameters the bit rate and transmission power that minimize cost, and then sending the transmission signal having the calculated bit rate and the calculated transmission power. This method provides a transmission signal having appropriate transmission power and bit rate in a wireless telecommunications

system, for example a telecommunications system employing wideband code division multiple access (WCDMA). Typically, this will involve signals transmitted between a mobile device **20** and a base station **26** as seen in Figure 2, in the context of an open loop power control system **28**. The cost function represents induced interference and transport delay, and thus the present invention is aimed at minimizing interference and delay.

Figure 2 shows a preferred embodiment of the best mode, in which the transmission signal **22** goes in the uplink direction from the mobile device **20** to the base station **26**. However, in other embodiments of the best mode, the present invention can operate in the downlink direction, as seen in the open loop power control system **28** of Figure 3.

Regardless of whether the transmission signal **22** is in the downlink or the uplink direction, the method and device of the present invention can be seen from Figure 4, which is independent of the transmission direction. Figure 4 shows that a command signal **39** is provided in response to an input parameter signal **47**. The command signal has a magnitude indicative of calculated transmission bit rate and calculated transmission power, which in turn have magnitudes selected to minimize a cost function representing induced interference and transport delay. Figure 4 also shows that a transmission signal **22** is provided in response to the command signal **39**, and the transmission signal **22** employs the calculated transmission bit rate and the calculated transmission power.

Returning to Figure 2, which involves an uplink transmission signal **22**, an additional step involves a broadcast parameter signal **24** being provided by the base station **26**. This broadcast parameter signal **24** has a magnitude indicative of at least one of the input parameters. In other words, at least one of the input parameters can be broadcast to the mobile device **20**. The input parameter signal **47** shown in Figure 4 is provided in response to the broadcast parameter signal **24**, and may include the broadcast parameter(s) as well as other parameters that need not be broadcast from the base station **26**.

Figure 3, which involves a downlink transmission signal **22** from the base station **36** to the mobile device **30**, exemplifies the situation where the command

signal 39 is provided by a radio network controller 31 to the base station 36. However, it is certainly possible for the command signal 39 to be generated and sent entirely within the base station 36 without involvement of the radio network controller 31.

5 In order to properly and fully understand the present invention, it is important to understand the underlying principles. High transmission power is desirable to ensure reception at the opposite device, and high transmission power is also desirable so that data transmission can occur at a high bit rate (b) and thus without overutilizing channels and delaying other users. A simple model of the
10 interrelation between the bit rate (b) and the transmission power (p) may be given by this formula:

$$p = \frac{E \cdot L \cdot I}{C} \cdot b, \quad (1)$$

which shows that a higher transmission power (p) allows a higher bit rate (b) in a WCDMA system. In formula (1), " L " represents pathloss which measures the
15 amount of signal attenuation, " I " is the total interference, " C " is the chip rate, and " E " stands for "ebno" which is the ratio of received bit energy to received total interference density required for proper signal decoding.

Despite the desirable advantages of higher transmission power (p), higher transmission power will also tend to cause more induced interference (I_i), which
20 may in turn disrupt other users. In other words, raising or lowering bit rate (b) and transmission power (p) involves a trade-off between induced interference (I_i) and transport delay (d). Thus, selecting high transmission power (p) and/or bit rate (b) has associated costs, just as selecting low transmission power (p) and/or bit rate (b) has different associated costs.

25 Preferred embodiments of the present invention minimize a linear cost function $F(b)$ that is linearly dependent upon induced interference (I_i) and transport delay (d), and thus the cost function represents the aforementioned trade-off:

$$F(b) = K_1 I_i + K_2 d. \quad (2)$$

Throughout this disclosure, " K " with a subscript indicates a quantity that is
30 independent of bit rate (b). It can be assumed that the induced interference (I_i) is

directly proportional to the bit rate (b) so that $I_i = K_3 b$. Likewise, it can be assumed that the transport delay (d) is inversely proportional to the bit rate (b) and directly proportional to the packet size (S) so that $d = S/b$ gives the transport time of a packet. Equation (2) therefore leads to the following, where we set $K_4 = K_1 K_3$:

$$5 \quad F(b) = K_4 b + \frac{K_2 \cdot S}{b} . \quad (3)$$

In order to minimize this cost function, we can simply differentiate equation (3) with respect to the bit rate (b), and set this derivative equal to zero. Using this procedure, it is found that cost is minimized when bit rate is given by this formula:

$$b = \sqrt{\frac{K_2 \cdot S}{K_4}} . \quad (4)$$

10 Notice that, for large bit rates, equation (3) dictates that the function F is approximately equal to $K_4 b$. Likewise, for large time delays, we have small bit rates according to the formula $d = S/b$ discussed above, so equation (3) tells us that F is approximately equal to $K_2 \cdot S/b = K_2 d$. Because our object is to limit cost, we assume that cost (F) above a maximum amount is not allowable, and therefore we
15 find that $K_2 \cdot D$ can be equated to $K_4 \cdot B$ where “ D ” is the maximum value of transport delay (d) and “ B ” is the maximum value of bit rate (b). Inserting this result into equation (4) allows equation (4) to be rewritten as follows:

$$b = \sqrt{\frac{B}{D} \cdot S} . \quad (5)$$

It is straightforward to obtain from equation (1) a formula for the maximum
20 value “ P ” of transmission power (p) that applies in the special case when cost (F) is at its maximum:

$$P = \frac{E \cdot L \cdot I}{C} \cdot B . \quad (6)$$

This formula (6) can now be used to eliminate the maximum bit rate (B) from equations (1) and (5), and it is then useful to solve for transmission power (p) and
25 bit rate (b). We are thus able to reach the following two novel formulae for bit rate (b) and transmission power (p) in terms of packet size (S), chip rate (C), maximum transmission power (P), maximum transport delay (D), ebno (the ratio “ E ” between

received bit energy and received total interference density required for proper signal decoding), pathloss (L), and total interference (I):

$$b = \sqrt{\frac{S \cdot C \cdot P}{D \cdot E \cdot L \cdot I}}. \quad (7)$$

$$p = \sqrt{\frac{S \cdot E \cdot L \cdot I \cdot P}{D \cdot C}}. \quad (8)$$

Equations (7) and (8) exemplify how bit rate (b) and transmission power (p) can be selected according to the present invention, for the uplink and/or for the downlink, using open loop power control. All of the quantities on the right-hand-sides of equation (7) and (8) are input parameters that may be included in the input parameter signal 47 shown in Figure 4.

To compensate for a possible bias, the ebno parameter (E) could be regularly adjusted so that it is slightly increased when a frame error is detected, and decreased when a frame is received correctly. The amounts of increase and decrease can be selected to give a target frame error rate, on average. Uplink frame errors can be directly detected by a radio network controller (RNC); for detecting downlink frame errors, the RNC can use information about retransmission requests.

When the cost of a transmission signal in the uplink direction is to be minimized, ebno (E) and total interference (I) in a particular geographic sector can be broadcast to the user equipment (UE), and the UE can then use these broadcast values to determine bit rate and transmission power according to equations (7) and (8). Moreover, the UE can approximate pathloss (L) from the measured signal-to-interference ratio (SIR) of a common broadcast channel, the broadcast channel's transmission power ($BCTP$) also being broadcast.

The formulae (7) and (8) can also be used to select bit rate (b) and transmission power (p) for the downlink. In that case, the radio network controller (RNC) can approximate the product of pathloss (L) and total interference (I) because that product is needed to calculate the transmission power and bit rate.

There are various alternative ways for the RNC to approximate the product of pathloss and total interference. The first way assumes that the RNC has recently received a measurement report from the UE , including the signal-to-interference

ratio (*SIR*) of the common broadcast channel, and also assumes that the measured *SIR* is that of the received common channel power to the total wideband interference. The measured *SIR*, together with sector total transmission power (*STTP*), broadcast channel transmission power (*BCTP*), and planned or measured
 5 downlink code orthogonality (*DCO*), yield the product of pathloss and total interference:

$$L \cdot I = \frac{BCTP}{SIR} - DCO \cdot STTP. \quad (9)$$

Figure 3 shows a measurement report signal 35 provided by the mobile device 30 to the base station 36, and this measurement report signal 35 may have a magnitude
 10 indicative of measured *SIR*. Note that formula (9) can very easily be derived algebraically from the following four equations:

$$I_W = I_{INTRA} + I_{INTER} + I_{NOISE}. \quad (10a)$$

$$I = (1 - DCO)I_{INTRA} + I_{INTER} + I_{NOISE}. \quad (10b)$$

$$SIR = \frac{BCTP}{L \cdot I_W}. \quad (10c)$$

$$15 \quad I_{INTRA} = \frac{STTP}{L}. \quad (10d)$$

Equation (10a) is simply a statement that total wideband interference (I_W) may be defined as the sum of intra-cell interference (I_{INTRA}), inter-cell interference (I_{INTER}), and noise (I_{NOISE}) such as thermal noise. Equation (10b) indicates that, in the downlink, the observed total interference (I) is somewhat lower than the total
 20 wideband interference (I_W) given by equation (10a), due to orthogonality of codes. Equation (10c) is simply a consequence of *SIR* measuring standards. Equation (10d) indicates that the intra-cell interference (I_{INTRA}) is equal to the sector total transmission power (*STTP*) divided by the pathloss (L) between the sector antenna and the *UE*.

25 The second way for the RNC to approximate the product of pathloss (L) and total interference (I) is by estimating the average pathloss-interference factor in a sector, based on transmission powers of active users in the sector. Fast closed-loop power control adjusts the transmission powers to just outbalance the downlink

pathloss-interference factors, and thus the individual pathloss-interference factors can be determined from the individual transmission power (p_i), bit rate (b_i), planned *ebno* (E_i) and chip rate (C), yielding this average pathloss-interference factor for “ N ” users in the sector:

$$L \cdot I = \frac{C}{N} \sum_{i=1}^N \frac{p_i}{b_i E_i}. \quad (11)$$

The accuracy of this statistical formula (10) depends upon the number and distribution of users in the sector, and on the accuracy of planned *ebno* values. Other statistical formulas could be warranted instead of the averaging formula (11); for example, less than all of the N users in the sector could be sampled, and/or a weighted average could be employed, and/or an offset could be added to the product of pathloss (L) and total interference (I).

The third way for the *RNC* to approximate the product of pathloss (L) and total interference (I) is as follows:

$$L \cdot I = (1 + ICI - DCO) \cdot STTP. \quad (12)$$

This formula (12) assumes that the mobile device is located in a sector where interference from outside the sector has a fixed ratio (ICI) to interference from inside the sector, and also assumes that noise (I_{NOISE}) is negligible. Note that formula (12) can be easily derived algebraically from equations (10b) and (10d). The ICI value may be measurable, or alternatively a constant value suggested by radio network planning may be used (an ICI value of 0.5 is typical).

As discussed previously, the present invention involves a method as well as a device for carrying out that method. Figure 4 shows two essential components of the best mode for carrying out this invention: namely, a computing module **43** and a transmitter module **44**. The computing module **43** essentially takes the input parameters and uses them to calculate the appropriate transmission bit rate and the appropriate transmission power, and those two appropriate values are then communicated to the transmitter module **44** which then sends a transmission signal having the bit rate and transmission power dictated by the computing module **43**.

A mobile device **50** according to the present invention is detailed in Figure 5, and this mobile device **50** interacts with a base station **56**. Of course, it will be

well understood by those skilled in the art that Figure 5, and the other figures, depict components and signals that are especially relevant to the present invention; these figures do not detail the many other features which may be included in a mobile device **50** and a base station **56**. In the embodiment shown by Figure 5, a
5 parameter storage module **55** maintains and updates the input parameters, which are provided to the computing module **43** via an input parameter signal **47**. One source for at least part of the input parameters is a broadcast parameter signal **51** from the base station **56** to the parameter storage module **55**. The computing module **43**
10 responds to the input parameter signal **47** by providing a command signal **59** to the transmitter module **44**, and the transmitter module **44** in turn provides the transmission signal **22** to the base station **56** at the bit rate and power dictated by the command signal **59**. It should be emphasized that, as those skilled in the art will realize, all of the components and signals described herein may be properly considered as preferred structures and interactions that can be implemented in a
15 variety of different ways by a variety of different hardware and software combinations.

As can be seen from Figure 6, the base station **66** may be equipped with a transmitter module **44** and a computing module **43** for use in downlink transmissions. The transmission signal **22** goes from the base station **66** to the
20 mobile device **60**. Figure 6 does not explicitly show a parameter storage module as in Figure 5, but such a parameter storage module could easily be added; however, one may also simply assume that the computing module **43** includes components which perform the functions of a parameter storage module. The measurement report signal **65** in Figure 6 is comparable to the measurement report signal **35**
25 already discussed with reference to Figure 3, and this measurement report signal **65** has a magnitude that may be indicative of measured SIR. In Figure 6, the command signal **69** is both sent and received within the base station **66**, because both the computing module **43** and the transmitter module **44** are located within the base station **66**.

30 An alternative embodiment is shown by Figure 7, in which the transmitter module **74** is located at the base station **76** but the computing module **43** is located at

the RNC 71. Thus, the command signal 79 goes from the RNC 71 to the base station 76. Of course, the transmission signal 72 goes from the base station 76 to the mobile device 70.

5 Although this invention has been shown and described with respect to a best mode embodiment thereof, it should be understood by those skilled in the art that the foregoing and various other changes, omissions and additions in the form and detail thereof may be made therein without departing from the spirit and scope of the invention.

WHAT IS CLAIMED IS:

- 1 1. A method for providing a transmission signal having appropriate
2 transmission power and bit rate, in a wireless telecommunications system,
3 characterized by:
4 providing a command signal (39) having a magnitude indicative of calculated
5 transmission bit rate and calculated transmission power, in response to an input
6 parameter signal (47), said calculated transmission bit rate and said calculated
7 transmission power having magnitudes selected to minimize a cost function
8 representing induced interference and transport delay, and
9 providing the transmission signal (22) having the calculated transmission bit
10 rate and the calculated transmission power, in response to the command signal (39).
- 1 2. The method of claim 1, characterized by said steps carried out in an open
2 loop power control system (28).
- 1 3. The method of claim 2, characterized by the cost function comprising a
2 linear function of the induced interference and the transport delay.
- 1 4. The method of claim 2 further characterized by providing a broadcast
2 parameter signal (24), wherein the transmission signal (22) is from a mobile device
3 (20) to a base station (26), by the broadcast parameter signal (24) having a
4 magnitude indicative of at least one of the input parameters, and by the input
5 parameter signal (47) provided in response to the broadcast parameter signal (24).
- 1 5. The method of claim 2, characterized by the input parameter signal (47)
2 having a magnitude indicative of input parameters that include pathloss (L) and total
3 interference (I) as a product ($L \cdot I$).

1 6. The method of claim 5, characterized by the input parameters also including
 2 maximum delay (D), maximum power (P), ebno value (E), chip rate (C), and packet
 3 size (S).

1 7. The method of claim 6, characterized by the bit rate (b) given by

$$2 \quad b = \sqrt{\frac{P \cdot C \cdot S}{D \cdot E \cdot L \cdot I}}.$$

1 8. The method of claim 7, characterized by the transmission power (p) given
 2 by

$$3 \quad p = \sqrt{\frac{S \cdot E \cdot L \cdot I \cdot P}{D \cdot C}}.$$

1 9. The method of claim 5, characterized by the transmission signal (22) sent
 2 from a base station (36) to a mobile device (30), and by the product of pathloss and
 3 interference approximately calculated prior to sending the transmission signal (22) in
 4 order to determine bit rate and transmission power of the transmission signal (22).

1 10. The method of claim 9, characterized by transmission bit rate and
 2 transmission power calculated at a radio network controller (31).

1 11. The method of claim 9, characterized by the product of pathloss and
 2 interference approximated using a measurement report signal (35) from the mobile
 3 device (30), the measurement report signal (35) having a magnitude indicative of
 4 measured signal-to-interference ratio.

1 12. The method of claim 9, characterized by the product of pathloss and
 2 interference approximated by statistically examining other active users in a sector.

1 13. The method of claim 9, characterized by the product of pathloss and
 2 interference estimated based on an assumption that the mobile device (30) is located

3 in a sector where interference from outside the sector is a fixed proportion of
4 interference from inside the sector.

1 14. The method of claim 6, characterized by increasing the ebno value when a
2 frame error is detected, and decreasing when a frame is received correctly.

1 15. The method of claim 2, characterized by the wireless telecommunications
2 system employing wideband code division multiple access.

1 16. A device for transmitting a signal having appropriate transmission power and
2 bit rate, in a wireless telecommunication system, characterized by:
3 a transmitter module (44), responsive to a command signal (39) having a
4 magnitude indicative of calculated transmission bit rate and calculated transmission
5 power, for providing a transmission signal (22) having the calculated transmission
6 bit rate and the calculated transmission power, and by
7 a computing module (43), responsive to an input parameter signal (47), for
8 providing the command signal (39), said transmission bit rate and said transmission
9 power having magnitudes selected to minimize a cost function representing induced
10 interference and transport delay.

1 17. The device of claim 16, characterized by open loop power control being
2 employed.

1 18. The device of claim 17, characterized by the cost function being a linear
2 function of the induced interference and the transport delay.

1 19. The device of claim 17 further characterized by a parameter storage module
2 (55) responsive to a broadcast parameter signal (51), for providing the input
3 parameter signal (47), by the transmitter module (44), the parameter storage module
4 (55) and the computing module (43) being located at a mobile device (50), and by

5 the broadcast parameter signal (51) having a magnitude indicative of at least one of
6 the input parameters.

1 20. The device of claim 17, characterized by the input parameter signal (47)
2 having a magnitude indicative of input parameters that include pathloss (L) and total
3 interference (I) as a product ($L \cdot I$).

1 21. The device of claim 20, characterized by the input parameters also including
2 maximum delay (D), maximum power (P), ebno value (E), chip rate (C), and packet
3 size (S).

1 22. The device of claim 21, characterized by the bit rate (b) given by

2
$$b = \sqrt{\frac{P \cdot C \cdot S}{D \cdot E \cdot L \cdot I}}.$$

1 23. The device of claim 22, characterized by the transmission power (p) given
2 by

3
$$p = \sqrt{\frac{S \cdot E \cdot L \cdot I \cdot P}{D \cdot C}}.$$

1 24. The device of claim 20, characterized by the transmitter module (44) located
2 at a base station (66), and by the computing module (43) equipped and programmed
3 to approximately calculate the product of pathloss and interference in order to
4 determine bit rate and transmission power of the transmission signal (22).

1 25. The device of claim 24, characterized by the computing module (43) located
2 at a radio network controller (71).

1 26. The device of claim 24, characterized by the product of pathloss and
2 interference approximated using a measurement report signal (65) from the mobile

3 device, and by the measurement report signal (65) having a magnitude indicative of
4 measured signal-to-interference ratio.

1 27. The device of claim 24, characterized by the product of pathloss and
2 interference approximated by statistically examining other active users in a sector.

1 28. The device of claim 24, characterized by the product of pathloss and
2 interference estimated based on an assumption that the mobile device is located in a
3 sector where interference from outside the sector is a fixed proportion of
4 interference from inside the sector.

1 29. The device of claim 21, characterized by the ebno value increasing when a
2 frame error is detected, and decreasing when a frame is received correctly.

1 30. The device of claim 17, characterized by the wireless telecommunications
2 system employing wideband code division multiple access.