Description

This invention relates to television display apparatus, for displaying the picture information of a television signal in a non-interlaced scanning format.

Television signals based on present day standards create visible artifacts on conventional television receivers and monitors. In broadcast systems such as the 525 line-per-frame, 30 frame-per-second 525/30 NTSC system or the 625/25 PAL system, artifacts occur because of the interlaced scanning process. This process divides the 525-line picture or frame of the NTSC standard into two successive 262½-line fields. The 262½ lines of one field are scanned in 1/60th of a second followed by scanning of an additional 262½ lines of another field with lines of the second field occupying the spaces between the lines of the first field. One subjective effect of this interlaced scan is to create in the presence of motion in the picture scene, an apparent vertical drift of the lines of the raster known as "line crawl". The apparent drift is substantially more apparent when viewing a wide-screen display at close range. Another well-known objectionable visible effect is interline flicker on line-to-line transitions that occur because of the interlaced scanning format.

Recent interest in the development of high definition television systems (HDTV) has been directed toward techniques that are intended to enhance the subjective performance of present systems within the contraints of existing standards. One approach, a technique referred to as progressive scan, or non-interlaced scan, has been described in patent documents and in the literature. For example, all the scan lines of one frame are scanned consecutively from the top of the display screen and downward to the bottom of the display screen during one vertical scanning interval. Progressive scan results in the reduction of interlaced scanning format related artifacts such as interline flicker and line crawl that exist in conventional two-to-one interlaced displays. The subjective effect is a more pleasing picture presentation to the viewer.

The picture details displayed in the non-interlaced format are made to substantially conform to the picture details contained in the interlaced signal, in the case where no motion in the picture scene is detected. Motion related aspects of the invention are described later on. Where no motion occurs, the picture information of one field of the interlaced NTSC signal is displayed in one set of the alternate scan lines, and that of the other field is displayed in a different set of scan lines that interleaves with the scan lines to form a picture frame. In the non-interlaced scanning format, each scan line of the one set is scanned immediately after the scanning of a scan line of the different set, for example, such that the picture progressively fills the screen of the display. All the scan lines of a picture frame are scanned consecutively during one vertical scanning interval.

In the prior art, as typified for instance by EP—A1—0018856, DE—A1—2915359, US—A—4400719, GB—A—2111343, JP—A—59-40772, GB—A—2090505, at least one of the sets of interleaved scan lines is derived, using line and field delays, by interpolation between lines occurring in the same field or in successive fields, with the possibility, in some proposals, of selecting between one and the other mode of interpolation according to whether or not there is motion in the scene to be displayed. In contrast, the present invention, at least in the absence of motion, provides one of the interleaved sets of scan lines by interpolation between lines of successive frames (frame-combing) while the other set of scan lines are derived from field-delayed lines of the original TV signal.

According to one aspect of the invention, television signal is applied to a delay element that delays the television signal by one field period and by one frame period, respectively, to produce field and frame delayed television signals. First and second luminance component signals are produced, respectively, from the frame and field delayed television signals, respectively. The first and second luminance component signals are combined to produce a first luminance output signal. A second luminance output signal is generated from the second luminance signal. The first and second luminance output signals are capable of providing picture information for display in a first plurality and in a different second plurality of display lines, respectively, of a non-interlaced television display, to form a picture frame.

Differences in scene content due to object movement or television camera panning that occur from one field time to the immediately following one are characterized as being visual motion of the scene content. If such motion is not taken into account in the course of displaying the picture contents of an interlaced signal in a non-interlaced scanning format, edges of moving objects may appear as having discontinuous transitions. This is so because the one set of displayed lines represents picture information that occurred one sixtieth of a second apart from picture information that is represented by the other set of displayed lines. The result is a jagged appearance for horizontal motion, and a smearing effect for vertical motion; such artifacts are objectionable.

According to another aspect of the invention, when motion is detected in a section of the picture, then one field of the interlaced signal primarily is made to provide picture information for display in the scan lines of that section of the display where motion occurs. Thus, the picture information of moving edges of an object that is displayed in a non-interlaced format, is derived predominantly from one field of the interlaced signal. For example, assume that the picture information that is displayed in each display line of the one set of display lines is contained in the corresponding active video line of one field of the interlaced signal. In this case, the picture information that is dispayed in each of the interleaving lines of the other set of display lines in the section of the display where motion occurs, is obtained by averaging the two signals

that provide picture information for display in the immediately preceding and following scan lines, respectively. As a result the zigzag or jagged types of artifacts of moving objects, that occur when a motion compensation scheme is not utilized, are reduced when the picture information of moving objects is derived from one field of the interlaced signal.

Though some picture details are lost in such sections of the display screen when motion is detected, as a result of the motion compensation scheme of the invention, this loss in the presence of motion is not highly discernible. This is so because of the well-known fact that the ability of the human eye to discern fine picture details of moving objects is not as good as its ability to discern fine picture details of the same objects when they are stationary.

In an embodiment of the invention, motion is detected by comparing two video lines of the interlaced signal that are separated by one frame time. Thus, a difference signal produced by the comparison process is indicative of picture scene changes between a given pixel of one frame and the same pixel of the immediately following frame.

The invention will now be described by way of example with reference to the drawings in which:

Figure 1a, b, c and d are useful in explaining the picture information from the television signal of Figure 2 that is displayed in the corresponding scan lines of the cathode ray tube of Figure 4;

Figure 2 illustrates schematically video lines in three consecutive fields of the television signal;

Figure 3 illustrates the block diagram of the separator block of Figure 4;

Figure 4 illustrates the block diagram of a television apparatus of the invention that includes the separator block of Figure 3 for displaying the picture information of the television signal of Figure 2, in non-interlaced scanning format; and

Figure 5a—l illustrate schematically timing diagrams useful in explaining the operation of the television apparatus of Figure 4.

Figure 1a illustrates a faceplate 121 of a cathode ray tube such as illustrated in Figure 4, as described later on, that includes in a given portion 120 four horizontal display lines, 122—125, illustrated in solid lines, and four interleaving horizontal display lines, 126—129, illustrated in broken lines. Figure 1a is used below in explaining the standard interlaced as well as the non-interlaced scanning format of the invention.

Figure 2 illustrates schematically a composite interlaced color NTSC signal 130. In an interlaced scanning format, video lines n, n+1, n+2 and n+3 of a field m of signal 130 provide picture information for display in lines 122, 123, 124 and 125, respectively, of Figure 1a. Figure 1b illustrates schematically the vertical spacing between lines 122—125, respectively, and the associated video line n through n+3 of field m of Figure 2 having their picture information displayed in a vertical scanning interval s. Likewise, Figure 2 illustrates schematically video lines n+263, n+264, n+265 and n+266, of the immediately following field, m+1, of signal 130 that provide picture information for display in lines 126, 127, 128 and 129, respectively, of Figure 1a having their picture information displayed in a vertical scanning interval s+1. Similarly, Figure 1b illustrates schematically the vertical spacing between lines 126—129, respectively and the four associated video lines n+263 through n+266 of field m+1 of Figure 2 for the standard interlaced format. In the same manner, video lines n+525, n+526, n+527 and n+528 of a field m+2 of Figure 2, supply picture information for display in a vertical scanning interval s+2 in the interlaced scanning format in scan lines 122—125, as illustrated in Figure 1b.

In 2:1 interlaced scanning format the picture information of only one field is displayed during one vertical scanning interval. Two adjacent display lines that display picture information from field m, such as display lines 122 and 123, are spaced vertically by a distance 2d, as illustrated in Figure 1b. Whereas, adjacent display lines in which the picture information from fields m and m+1, respectively, is displayed, for example lines 122 and 126, are displaced vertically by a distance d which is ½ the length of distance 2d, as illustrated in Figure 1b.

Figure 4 illustrates a television apparatus 150, embodying aspects of the invention, that displays the picture information of an interlaced television signal in a non-interlaced format, as described later on. Apparatus 150 includes a cathode ray tube 119 having a faceplate 121 such as illustrated in Figure 1a.

Figure 3 illustrates a separator block 135 of apparatus 150 of Figure 4 embodying aspects of the invention, for generating the signals that provide picture information for display in the display lines of faceplate 121 of Figure 4 in a non-interlaced format. Identical numbers and symbols in Figures 1b, 2, 3, and 4 indicate similar items or functions. Referring to Figure 3, a baseband, analog, composite NTSC signal 130 of Figure 2 is applied to a terminal 400c of separator block 135 from a source which is not shown. The source of signal 130 may be the demodulated output of an IF stage of a standard television receiver. It should be noted that the invention will be described with reference to NTSC composite signal but other television signals are within the scope of the invention. The invention may be implemented using digital or analog techniques, or both.

NTSC signal 130 is delayed by a 262-H delay unit 400, where 262-H delay is equal to 262 times the scan line time of 63.5 microseconds, which is approximately a field delay time, as illustrated in Figure 2, to form a signal V_{fd} of Figure 3. Unit 400 is a clocked first-in first-out buffer. Clock 230k supplies the clock signal to unit 400, as described later on. Signal V_{fd} is applied to a separator 404' of Figure 3 which is, illustratively, a two-terminal transversal filter having a 1-H delay unit 401', also known as a comb filter. The 1-H delay is equal to the scan line time of 63.5 microseconds, as illustrated in Figure 2. Signal V_{fd} of Figure 3 is delayed by 1-H delay unit 401' to produce a signal V_{fd+1}. 1-H delay unit 401' is a clocked first-in first-out (FIFO) buffer.

clock 230k supplies the clock signal to unit 401', as described later on. In separator 404' of Figure 3, signal V_{fd+1} and signal V_{fd} are combined and the result multiplied by a scale factor of $\frac{1}{2}$, in an adder/scaler 402', to form a signal Y'_{fd} which is combed. Signal Y_{fd} includes the luminance-representative component of NTSC signal 130 of Figure 2 having a frequency spectrum with signal energy in the vicinity of integer multiples of the 15734 Hz line rate and nulls of signal energy in the vicinity of odd integer multiples of one half of the line rate. As a result of the combing process, the chrominance-representative component that originated in NTSC signal 130 is substantially reduced in signal Y_{fd} of Figure 3.

Delayed and undelayed signals are applied to a subtractor/scaler 403' of separator 404' that subtracts signal V_{fd+1} from signal V_{fd} and multiplies the result by a scale factor of $\frac{1}{2}$ to form a combed signal C'_{fd}. Signal C'_{fd} represents a portion of the luminance information and the chrominance information having a frequency spectrum with signal energy concentrated in the vicinity of odd integer multiples of one half the line rate and nulls of signal energy in the vicinity of integer multiples of the line rate. As a result of the combing process, the luminance-representative component that originated in NTSC signal 130 of Figure 2 is substantially reduced in signals C'_{fd} of Figure 3. To restore vertical detail into luminance signal Y'_{fd} lost through the combing process, signal C'_{fd} is applied through a low pass filter 413 having a cutoff frequency of illustrative 1 MHz for generating a signal Y_{vd} that contains luminance vertical detail information. Signal Y_{vd} is applied to one input terminal of an adder/scaler 414, whereas signal Y'_{fd} is coupled to its other terminal. Adder/scaler 414 adds the signals at its respective terminals and the result is multiplied by a scale factor of $\frac{1}{2}$ to produce a luminance signal Y''_{fd} containing restored vertical detail. Signal Y''_{fd} is applied through a 1-H delay 415 to produce a luma signal Y_{fd}, that is discussed later on. 1-H delay 415 is illustratively similar to 1-H delay 401' and receives the same clock signal 230k at the respective terminal.

Signal Y_{fd+1} is delayed by a 262-H delay unit 400' of, approximately by a field time, to form a signal V_{fr}. Unit 400' is a clocked first-in first-out buffer, illustratively, identical to unit 400. Clock 230k supplies the clock signal to unit 400', as described later on. Signal V_{fr} is equal to NTSC signal 130 delayed by one image, or frame, time delay that is equal to 525 display line periods.

Signal V_{fr} and NTSC signal 130 are summed together in an adder/scaler 405. The luminance components of the signals being in phase add and the result is multiplied by a scale factor of $\frac{1}{2}$, the chrominance components being 180 degrees out of phase, and therefore cancel each other. The result is applied to a terminal 405a to substantially produce chrominance-free luminance signal Y'_{fr} when successive frame signals are records of the same stationary scene.

Signal V_{fr} is subtracted from NTSC signal 130 in a subtractor/scaler 406 in which the chrominance components of the two frames sum constructively and the result is multiplied by the scale factor $\frac{1}{2}$, while the luminance components cancel each other. The result is applied at a terminal 406a to substantially produce a luminance-free chrominance signal C'_{fr} when successive frame signals are records of the same stationary scene. Signal C'_{fr} is applied through a low pass filter 407 to substantially produce a chrominance-free motion signal 207. Motion signal 207 contains the low frequency luminance cross components occurring in the chrominance signal during interframe image motion. Thus, in the absence of motion, low pass filter 407 produces no motion descriptive signal.

Motion signal 207 is coupled to a motion detector 408. Motion detector 408 outputs a motion signal M having, illustratively, an amplitude that is directly related to the absolute value of motion signal 207, illustratively, by means of a full wave rectifier. Motion detector 408 may also include a threshold detector that causes motion signal M to indicate that motion occurred only when the absolute value of motion signal 207 exceeds a predetermined threshold voltage. Luminance signal Y'_{fr} at a terminal 412b of combining unit 412 is applied through a gain controlled device 411 of unit 412, having a gain factor J, to a terminal 410b of an adder 410 of unit 412. Likewise, luminance signal Y'_{fd} at a terminal 412a is coupled through a gain controlled device 409 of unit 412, having a gain factor K, to a terminal 410a of adder 410 of unit 412. Adder 410 adds the signals at terminals 410a and b, respectively, to produce a weighted sum luminance signal Y'_m at a terminal 412d of combining unit 412. Thus, signal Y'_m of unit 412 may be expressed as a function of the signals at terminals 412a, and b, respectively, of unit 412 as follows:

$$\text{Signal } Y'_m = K \times \text{signal } Y'_{fd} + J \times \text{signal } Y'_{fr}.$$

Signal Y'_m is applied through a 1-H delay 416 to produce a luma signal Y_m that is discussed later on. 1-H delay 416 is illustratively similar to 1-H delay 401' and receives the same clock signal 230k at the respective terminal. Motion signal M at a terminal 412c is coupled to gain controlled devices 409 and 411, respectively, for controlling their respective gain factors, as discussed below.

As a first hypothetical example, assume the following facts. In gain controlled device 409, the gain factor K equals 1 when the absolute value of motion signal 207 exceeds a first threshold level, corresponding to a detected interframe motion; conversely, K=0 when motion signal 207 does not exceed the first threshold level, corresponding to stationary picture or the absence of detected motion. Assume also that in gain controlled device 411, the gain factor J equals 0 when the absolute value of motion signal 207 exceeds the first threshold level; conversely, J=1 when motion signal 207 does not exceed the first threshold level. Thus, when motion is detected, signal Y'_m=signal Y'_{fd}; conversely, when motion is not detected, signal Y'_m=signal Y'_{fr}.

Figure 5e illustrates schematically successive video lines of interlaced NTSC signal 130 of Figure 2. In

Figure 5e, video line n+527 is illustrated as occurring between time t5 and time t8. Identical numbers in Figures 5e and 2 indicate identical items or functions.

Assume that video line n+527 is present at terminal 400c of block 135 of Figure 3 as illustrated symbolically in the respective circle in Figure 3 that contains the symbol n+527. It follows from this assumption that signals V_{fd}, V_{fd+1} and V_{fr} of Figure 3 contain the video information of video lines n+265, n+264 and n+2 of Figure 2, respectively, when video line n+527 is present in NTSC signal 130, as illustrated symbolically inside the respective circles in Figure 3. Thus, luminance signal Y'_{fd} of Figure 3 represents the averaged luminance signal contained in consecutive video lines n+264 and n+265, respectively in field m+1 of NTSC signal 130 of Figure 2. Simultaneously, chrominance signal C'_{fd} of Figure 3 represents the averaged chrominance signal derived from consecutive video lines n+264 and n+265, respectively of field m+1.

Figure 5c illustrates schematically luma signal Y_{fd} that is equal to the restored luminance signal Y''_{fd} at the output of 1-H delay 415. One luma line 60 of luma signal Y_{fd} is schematically illustrated as occurring between time t10 and time t13. When video line n+527 of Figure 5c is at terminal 400c of Figure 3, signal Y''_{fd} may be calculated, assuming the facts of the first hypothetical example as follows:

$$\text{signal } Y''_{fd}=\frac{\text{video line n+264 plus video line n+265}}{2}$$

$$+\frac{\text{video line n+265 minus video line n+264}}{2}=\text{the luminance portion of video line n+265.}$$

Luma line 60 of luma signal Y_{fd} contains the delayed luminance signal Y''_{fd} as illustrated in Figure 5c; therefore, it is equal the luminance portion of video line n+265 of Figure 2. It should be understood that the evaluation of luma line 60 is valid for the frequency range up to the cutoff frequency of low pass filter 413 of Figure 3, and that luma line 60 of Figure 5c contains mainly the luminance component of signal part n+265 of Figure 5e. Luma line 60 of luma signal Y_{fd} of Figure 5c is identified in Figures 5c, 5k, 1b and 1c as ~(n+265).

Figure 5a illustrates schematically luma signal Y_m that is the 1-H delayed luma signal Y'_m at the output of combining unit 412. One luma line 52 of luma signal Y_m is schematically illustrated between time t10 and time t13. As explained before, signal Y'_m of Figure 3 equals signal Y'_{fd} when motion is detected, and equals signal Y'_{fr} when it is not detected. Thus, for the same facts assumed in the first hypothetical example, and when video line n+527 of Figure 5e is at terminal 400c of Figure 3, signal Y'_m may be calculated as follows:

when no motion is detected,

$$\text{signal } Y'_m=\frac{\text{video line n+2 plus video line n+527}}{2}=Y'_{fr}$$

Because the luminance component of video line n+2 equals that of video line n+527, when no motion is detected, the following equation holds:

$$\text{signal } Y'_m=\text{the luminance portion of video line n+2.}$$

When motion is detected,

$$\text{signal } Y'_m=Y'_{fd}=\frac{\text{video line n+264 plus video line n+265}}{2}$$

Luma line 52, illustrated in Figure 5a, has the same value as signal Y'_m but is delayed by 1-H. When no motion is detected, luma line 52 of luma signal Y_m of Figure 5a is identified in Figures 5a, 5k and 1c as n~(n+2), because it does not contain identical luminance information of video line n+2 but only an approximation of it.

Figure 5l illustrates an example of motion signal M of Figure 3. In Figure 5l motion is detected from time t6a to time t7a. Motion signal M of Figure 5l causes, in the first example, that the luminance component of the average value of video lines n+264 and n+265 of Figure 2, from time t11a to time t12a is included in luma line 52 of Figure 5a.

As explained later on, luma line 52 of luma signal Y_m provides the luminance picture information for display in line 124 of Figure 1a. Similarly, luma line 60 of luma signal Y_{fd} provides the luminance picture information for display in line 128 of Figure 1a that is immediately below line 124.

As explained before, whether or not motion occurs, luma line 60 of luma signal Y_{fd} of Figure 5c, that is

ociated with line 128 of Figure 1a, contains the luminance picture information of video line n+265 of field m+1 of NTSC signal 130 of Figure 2. As can be deduced from Figure 1b, the same luminance picture information is displayed in line 128 in the standard interlaced scanning format.

When no motion is detected, luma line 52 of luma signal Y_m of Figure 5a, that is associated with line 124 of Figure 1a, contains the same luminance information as in video line n+2 or in video line n+527 of field m of NTSC signal 130 of Figure 2. As can be observed from Figure 1b, the same luminance information is displayed in line 124 in the standard interlaced scanning format.

As explained before, Figure 5l illustrates an example of motion signal M of Figure 3 that occurs between time 6a and time 7a. As a result of motion signal M of Figure 5l, luma line 52 of luma signal Y_m of Figure 5a contains substantially the luminance picture information of the average value of video lines 265 and 264 of Figure 5e. Thus, so long as motion is detected, the picture information that is displayed in adjacent display lines is derived from the same field m+1. Therefore, the artifacts that would have caused discontinuities in the edges of moving objects, as explained before, are eliminated, in accordance with the motion compensation aspect of the invention.

The motion compensation scheme may be activated by motion detector 408 of Figure 3 on a pixel basis as illustrated in Figures 5a and 5l, thus compensating for motion in a given section of a display line; alternatively, it may be activated on a line or a frame basis.

As explained before, each of signals C'_{fr} and C'_{fd} of Figure 3 contains chrominance component of NTSC signal 130 of Figure 2. In the absence of motion, signal C'_{fr}, being the output signal of the frame comb filter, has lower cross luminance components than signal C'_{fd} which is obtained from the line comb filter. However, signal C'_{fr} becomes distorted as a result of frame-to-frame motion.

Therefore, it is desirable to display the chrominance information of signal C'_{fr} when the scene is stationary. Conversely, when the scene is not stationary, it is desirable to display the chrominance information of signal C'_{fd}.

Signals C'_{fd} and C'_{fr} are coupled to terminals 412'a and 412'b, respectively, of a unit 412' that operates, illustratively, similarly to unit 412. Terminals 412'a, b, c and d of unit 412' correspond to terminals 412a, b, c and d, respectively, of unit 412. Motion signal M is coupled to terminal 412'c. A chrominance or color signal C' at output terminal 412'd is coupled through a band pass filter 421, that passes signals within the band of frequencies around the color subcarrier frequency that contains chrominance information. The chrominance signal C at the output of bandpass filter 421 is coupled to an input terminal 417a of an I, Q demodulator 417.

Thus, assuming the facts of the first hypothetical example, when motion is detected signal C' is equal to signal C'_{fd} that is not contaminated by motion related distortions. Conversely, when no motion is detected, it is equal to signal C'_{fr} in which the luminance cross component is reduced relative to that in signal C'_{fd}.

Demodulator 417, of conventional design, generates a color signal I and a color signal Q that contain the demodulated I and Q components, respectively, of signal C'. Signal I is coupled through a 1-H delay 419 to form a signal I_a. 1-H delay 419 operates similarly to 1-H delay 401' and receives the same clock signal 230k at the respective terminal. Signal I_a and undelayed signal I are coupled to two respective terminals of an adder/scaler 420 that sums the respective signals and multiplies the result by a scale factor of $\frac{1}{2}$ to produce a signal I_b. Note that signal I_b is obtained by averaging technique. Thus, signal I_b contains the interpolated I information of a preceding and a following video lines. Figures 5b and d illustrate schematically signals I_a and I_b, respectively.

Signal Q is coupled to a 1-H delay 419' and to an adder/scaler 420' to form signals Q_a and Q_b. Thus, signals Q_a and Q_b are formed from signal Q similarly to the way signals I_a and I_b, respectively, are formed from signal I.

In the first hypothetical example, it was assumed that the gain factor K of device 409 of unit 412 is equal to 1 and the gain factor J of device 411 of unit 412 is equal to 0 when motion is detected; conversely, when no motion is detected, it was assumed that the gain factor K of device 409 is equal to 0 and the gain factor J of device 411 is equal to 1.

As a trade off between motion compensation, vertical picture resolution and to avoid switching artifacts that may occur, the respective gain factor may exhibit a smoother or soft characteristic as a function of the absolute value of motion signal 207 of Figure 3. Thus, motion signal M may cause devices 409 and 411 of unit 412 to proportionate signals Y'_{fd} and Y'_{fr} respectively, for forming signal Y'_m. Similarly, it may cause unit 412' to proportionate signals C_{fd} and C'_{fr} respectively, for forming signal C'. Alternatively, some or all of the gain factors K and J of units 412 and 412' may be set to a certain value independently of motion signal M.

Television apparatus 150 of Figure 4 includes separator block 135 of Figure 3. NTSC signal 130 of Figure 2 is also coupled in apparatus 150 to a timing unit 430. Timing unit 430 utilizes horizontal and vertical sync pulses of NTSC signal 130 for generating a horizontal scanning current H and a vertical scanning current V for driving a horizontal deflection winding 432 and a vertical deflection winding 431, respectively. The scanning frequency of horizontal scanning current H is twice that of a standard television receiver using the interlaced scanning format; whereas, the frequency of vertical scanning current V is of the same. Timing unit 430 may include a phase-locked-loop circuit, not shown, that generates clock signals that are phase locked to the color burst signal of NTSC signal 130 of Figure 2 for generating clock signals 230j—k

and for generating a timing signal 230l, all of Figure 4. Clock signal 230k of illustratively 4×Sc, where Sc is the 3.58 MHz frequency of the color subcarrier of NTSC signal 130 of Figure 2 is coupled to separator block 135 for clocking the clocked delay lines, as explained before.

Referring to Figure 4, signal I_a of block 135 of Figure 3 is applied through a terminal F to 1-H delays 434 and 435, respectively. Signal I_b of block 135 of Figure 3 is applied through a terminal G to 1-H delay units 436 and 437 of Figure 4, respectively. The 1-H delay units 434—437 may comprise first-in first-out (FIFO) buffers.

Figures 5f—5i illustrate schematically clocks 230f, 230g, 230h and 230i of Figure 4, respectively, that are coupled to 1-H delay units 434, 436, 435 and 437, respectively. Clock 230f of Figure 5f clocks samples of a chroma line 55 of signal I_a of Figure 5b between time t5 and time t8, for example, into 1-H delay unit 434 of Figure 4 at a first clock rate as illustrated by the short vertical lines in Figure 5f. Simultaneously, clock 230g of Figure 5g clocks samples of a chroma line 63 of signal I_b of Figure 5d into 1-H delay unit 436 of Figure 4 at the same first clock rate. The samples in unit 434 of Figure 4 are clocked out at a second clock rate which is double the rate of the first clock, as illustrated by the short vertical lines of clock 230f in Figure 5f, between times t9 and t11. The samples in unit 436 of Figure 4 are clocked out at the second clock rate, as illustrated by the short vertical lines of clock 230g of Figure 5g between time t12 and t13. The samples from unit 434 and 436, respectively, of Figure 4 are coupled to terminals A and B of a switch 433a, respectively. Figure 5j illustrates schematically a signal I_{2H} that is coupled by a wiper k of switch 433a to a terminal E. Wiper k is controlled by timing signal 230l. Wiper k couples the samples of unit 434 at terminal A to terminal E for forming the respective portion of signal I_{2H} between times t9 and t11 as illustrated in Figure 5j; likewise, wiper k of Figure 4 couples the samples of unit 436 at terminal B to terminal E between times t12 and t13.

In a like manner, clock 230i of Figure 5i clocks samples of a chroma line 56 of Figure 5b between time t10 and time t13 into 1-H delay unit 435 of Figure 4 at the first clock rate as illustrated by the short vertical lines in Figure 5i. Simultaneously, clock 230h of Figure 5g clocks samples of a chroma line 64 of Figure 5d into 1-H delay unit 437 of Figure 4 at the same first clock rate. The samples in unit 435 of Figure 4 are clocked out at the second clock rate which is double the rate of the first clock, as illustrated by the short vertical lines of clock 230i in Figure 5i between times t14 and t16. The samples in unit 437 of Figure 4 are clocked out at the second clock rate, as illustrated by the short vertical lines of clock 230h of Figure 5h, respectively, between time t17 and t18. The samples from unit 435 and 437 of Figure 4 are coupled to terminals C and D of switch 433a, respectively. Wiper k couples the samples of unit 435 at terminal C to terminal E between times t14 and t16 of Figure 5j for generating the respective portion of signal I_{2H}, likewise, wiper k of Figure 4 couples the samples of unit 437 at terminal D to terminal E between times t17 and t18. Thus, signal I_{2H} of Figure 5j contains the speeded up signals I_a and I_b of Figures 5b and d, respectively, in alternate time slots. For the example of Figure 5j, each time slot is equal to one-half the 53.6 microseconds active scan line time of NTSC signal 130 of Figure 2.

A speed unit 433''.in Figure 4, that is, illustratively, constructed similarly to speedup unit 433 has terminals E'', F'' and G'' that correspond to terminals E, F and G respectively, of speedup unit 433. Unit 433'' of Figure 4 receives clocks 230f—i and signal 230l as does unit 433 and it operates similarly. Signal Q_a of block 135 of Figure 3 is applied to terminal F'' of speedup unit 433'' of Figure 4 and signal Q_b is applied to terminal G'' of speedup unit 433''. A signal Q_{2H} at terminal E'' of unit 433'' is coupled to matrix 439. Thus, signal Q_{2H} contains the speeded up signals Q_a and Q_b respectively in alternate time slots. Figure 5j may also illustrate schematically signal Q_{2H} of Figure 4.

A speedup unit 433' in Figure 4, that is illustratively constructed similarly to speedup unit 433 has terminals E', F' and G' that correspond to terminals E, F and G, respectively, of speedup unit 433. Unit 433' of Figure 4 receives clocks 230f—i and signal 230l as does unit 433 and it operates similarly. Luma signal Y_m of block 135 of Figure 3 is applied to terminal F' of speedup unit 433' of Figure 4 and luma signal Y_{fd} is applied to terminal G' of speedup unit 433'. A signal Y_{2H} at terminal E' of unit 433' contains the speeded up luminance information of both luma signal Y_m of Figure 5a and luma signal Y_{fd} of Figure 5c, respectively, in alternate time slots. Figure 5k illustrates schematically signal Y_{2H} of Figure 4 for the first example. Note that the luminance picture information of luma line 52 is speeded up to be contained in signal Y_{2H} between time t14 and time t16. Signal Y_{2H} of Figure 5k, between times t15a and time t16a contains a speeded up portion of luma signal Y_m. The signal contents of this portion is selected by motion signal M of Figure 5l. Signals I_{2H}, Q_{2H} and Y_{2H} are coupled to the respective terminals of an I, Q, Y matrix 439, of conventional construction, but of expanded bandwidth, I, Q, Y matrix 439 generates signals R, G and B from signals I_{2H}, Q_{2H} and Y_{2H} for driving the respective guns of cathode ray tube 119. Figure 5j may also illustrate schematically signals R, G and B, respectively.

Figure 1c illustrates diagrammatically, as an approximation, the respective video lines of NTSC signal 130 of Figure 2 that supply luminance picture information for display during a vertical scanning interval s in each of scan lines 122—129 of Figure 1a for an example in which no motion is detected. The picture information is displayed in non-interlaced format during one vertical scanning interval. Note that the same respective video line of NTSC signal 130 of Figure 2 provides luminance information for display in the same line as in the interlace scanning format of Figure 1b. For example, between time t14 and time t16 of Figure 5j, signals R, G and B of Figure 4 provide the luminance information of video line n+1 for display in line 123.

Figure 1d illustrates diagrammatically, as an approximation, the respective video lines of NTSC signal 130 of Figure 2 that supply luminance information for display during the vertical scanning interval s in each

scan lines 122—129 of Figure 1a. Figure 1d illustrates the situation in which motion compensation is performed in scan line 124. In the case where no motion is detected, as illustrated in Figure 1c, the same luminance information of video line n+2 of NTSC signal 130 of Figure 2 supplies the luminance picture information for display in scan line 124. When motion is detected between time t6a and time t7a of Figure 5l, a portion of signal Y_{2H} of Figure 5k bewteen time t15a and t16a supplies the average value of video lines n+264 and n+265 of Figure 2 that are contained in the previous coupled field m+1 of NTSC signal 130 of Figure 2, as illustrated in figure line 124 of Figure 1d. Thus, assuming the facts of the first hypothetical example, the luminance information for displaying a moving object is derived, in each vertical scanning interval, from the immediately preceding field only. Moreover, the substituted picture information, in the presence of motion, is derived from signals that provide picture information for display in the immediately preceding and following scan lines. As illustrated in Figures 5k and 1d, the luminance information that is displayed in line 124 is derived from the luminance information that is displayed in line 127 and 128 and that originated in video lines n+264 and n+265 of field m+1 of NTSC signal 130 of Figure 2.

Claims

1. Television apparatus for generating from an incoming composite color television signal first (Y_m) and second (Y_{fd}) luminance output signals that are capable of providing picture information for display in a first plurality and in a different second plurality of display lines, respectively, of a non-interlaced television display, to form a picture frame, comprising:

an input for receiving said incoming television signal;

delay means (400, 400') coupled to said input for delaying said incoming television signal by substantially one field period and by one frame period, respectively to produce field (V_{fd}) and frame (V_{fr}) delayed television signals, respectively;

means (405) for adding said incoming television signal and said frame delayed television signal (V_{fr}) to produce a first frame-combed, luminance video signal (Y_{fr}) containing a luminance component derived from said incoming and frame delayed television signals;

means (404') responsive to said field delayed television signal (V_{fd}) for producing a second luminance video signal (Y'_{fd}) containing a luminance component derived from said field delayed television signal;

means (412, 416) for combining said first (Y_{fr}) and second luminance (Y_{fd}) video signals to produce said first luminance output signal (Y_m); and

means (414, 415) responsive to said second luminance video (Y'_{fd}) signal for generating said second luminance output signal (Y_{fd}) therefrom.

2. Television apparatus as recited in Claim 1 further comprising, means (403', 413) for extracting a picture detail signal from said field delayed television signal (V_{fd}) wherein said generating means (414, 415) is responsive to said picture detail signal for producing said second luminance output signal containing restored picture details.

3. Television apparatus as recited in Claim 1 or 2, wherein said delay means (400, 400') includes first and second intermediate output taps spaced apart by a delay (401') of one video line time, and wherein said second luminance signal producing means (406') comprises means (402') for summing the signals at said first and second output taps to form said second luminance video signal (Y'_{fd}).

4. Television apparatus as recited in Claim 1, 2 or 3 further comprising, means (406) for combining said incoming television signal and said frame delayed television signal (V_{fr}) to produce the difference ($412'_b$) thereof and means (407) for producing from said difference signal a motion indicative signal (207) and wherein said combining means (412) combines said first and second luminance video signals in dependence upon said motion indicative signal.

5. Television apparatus as recited in Claim 4 wherein said motion indicative signal assumes a preset level when said television signal manifests a non-stationary picture scene.

6. Television apparatus as recited in Claim 4, wherein the combining means proportionally combines the said first and second luminance signals in accordance with the motion indicative signal.

7. Television apparatus as recited in Claim 6, wherein the contribution of said second luminance video signal in the combined first and second luminance video signal is directly proportional to the amplitude of said motion indicative signal.

8. Television apparatus as recited in Claim 4 further comprising, means (412', 421, 417) responsive to said difference signal (412'b) for producing therefrom first I and second Q color output signals.

9. Television apparatus as recited in Claim 8 wherein there are means (403') responsive to the field delayed television signal for producing a field delayed chrominance signal and said first and second color output signals producing means further comprises means (412') for combining said field delayed chrominance and difference signals in dependence upon the motion indicative signal.

10. Television apparatus as recited in Claim 9 wherein said field delayed difference signals combining means is responsive to said motion indicative signal for proportionally combining the said field delayed chrominance signal and the said difference signal.

11. Television apparatus as recited in Claim 8, 9 or 10, wherein said motion indicative signal producing means (406, 407) comprises a low pass filter (407) for producing a signal from said difference signal such that chrominance components of said television signal are attenuated and means (407, 408) for producing

* C L M S *

scan lines 122—129 of Figure 1a. Figure 1d illustrates the situation in which motion compensation is performed in scan line 124. In the case where no motion is detected, as illustrated in Figure 1c, the same luminance information of video line n+2 of NTSC signal 130 of Figure 2 supplies the luminance picture information for display in scan line 124. When motion is detected between time t6a and time t7a of Figure 5l, a portion of signal Y_{2H} of Figure 5k bewteen time t15a and t16a supplies the average value of video lines n+264 and n+265 of Figure 2 that are contained in the previous coupled field m+1 of NTSC signal 130 of Figure 2, as illustrated in figure line 124 of Figure 1d. Thus, assuming the facts of the first hypothetical example, the luminance information for displaying a moving object is derived, in each vertical scanning interval, from the immediately preceding field only. Moreover, the substituted picture information, in the presence of motion, is derived from signals that provide picture information for display in the immediately preceding and following scan lines. As illustrated in Figures 5k and 1d, the luminance information that is displayed in line 124 is derived from the luminance information that is displayed in line 127 and 128 and that originated in video lines n+264 and n+265 of field m+1 of NTSC signal 130 of Figure 2.

Claims

1. Television apparatus for generating from an incoming composite color television signal first (Y_m) and second (Y_{fd}) luminance output signals that are capable of providing picture information for display in a first plurality and in a different second plurality of display lines, respectively, of a non-interlaced television display, to form a picture frame, comprising:

an input for receiving said incoming television signal;

delay means (400, 400') coupled to said input for delaying said incoming television signal by substantially one field period and by one frame period, respectively to produce field (V_{fd}) and frame (V_{fr}) delayed television signals, respectively;

means (405) for adding said incoming television signal and said frame delayed television signal (V_{fr}) to produce a first frame-combed, luminance video signal (Y_{fr}) containing a luminance component derived from said incoming and frame delayed television signals;

means (404') responsive to said field delayed television signal (V_{fd}) for producing a second luminance video signal (Y'_{fd}) containing a luminance component derived from said field delayed television signal;

means (412, 416) for combining said first (Y_{fr}) and second luminance (Y_{fd}) video signals to produce said first luminance output signal (Y_m); and

means (414, 415) responsive to said second luminance video (Y'_{fd}) signal for generating said second luminance output signal (Y_{fd}) therefrom.

2. Television apparatus as recited in Claim 1 further comprising, means (403', 413) for extracting a picture detail signal from said field delayed television signal (V_{fd}) wherein said generating means (414, 415) is responsive to said picture detail signal for producing said second luminance output signal containing restored picture details.

3. Television apparatus as recited in Claim 1 or 2, wherein said delay means (400, 400') includes first and second intermediate output taps spaced apart by a delay (401') of one video line time, and wherein said second luminance signal producing means (406') comprises means (402') for summing the signals at said first and second output taps to form said second luminance video signal (Y'_{fd}).

4. Television apparatus as recited in Claim 1, 2 or 3 further comprising, means (406) for combining said incoming television signal and said frame delayed television signal (V_{fr}) to produce the difference ($412'_b$) thereof and means (407) for producing from said difference signal a motion indicative signal (207) and wherein said combining means (412) combines said first and second luminance video signals in dependence upon said motion indicative signal.

5. Television apparatus as recited in Claim 4 wherein said motion indicative signal assumes a preset level when said television signal manifests a non-stationary picture scene.

6. Television apparatus as recited in Claim 4, wherein the combining means proportionally combines the said first and second luminance signals in accordance with the motion indicative signal.

7. Television apparatus as recited in Claim 6, wherein the contribution of said second luminance video signal in the combined first and second luminance video signal is directly proportional to the amplitude of said motion indicative signal.

8. Television apparatus as recited in Claim 4 further comprising, means (412', 421, 417) responsive to said difference signal (412'b) for producing therefrom first I and second Q color output signals.

9. Television apparatus as recited in Claim 8 wherein there are means (403') responsive to the field delayed television signal for producing a field delayed chrominance signal and said first and second color output signals producing means further comprises means (412') for combining said field delayed chrominance and difference signals in dependence upon the motion indicative signal.

10. Television apparatus as recited in Claim 9 wherein said field delayed difference signals combining means is responsive to said motion indicative signal for proportionally combining the said field delayed chrominance signal and the said difference signal.

11. Television apparatus as recited in Claim 8, 9 or 10, wherein said motion indicative signal producing means (406, 407) comprises a low pass filter (407) for producing a signal from said difference signal such that chrominance components of said television signal are attenuated and means (407, 408) for producing

said motion indicative signal from said signal produced by said low pass filter such that the amplitude of said motion indicative signal is directly related to the amplitude of said signal that is produced by said low pass filter.

Patentansprüche

1. Fernsehgerät zum Erzeugen eines ersten (Y_m) und eines zweiten (Y_{fd}) Leuchtdichteausgangssignales aus einem eintreffenden Fernsehsignalgemisch, welche Bildinformation zur Wiedergabe in einer ersten Mehrzahl bzw. einer zweiten Mehrzahl von Bildzeilen eines nichtverschachtelten Fernsehbildes zur Erzeugung eines Vollbildes zu liefern vermögen, mit:

einem Eingang zum Empfangen des eintreffenden Fernsehsignales;

einer mit dem Eingang gekoppelten Verzögerungseinrichtung (400, 400') zum Verzögern des eintreffenden Fernsehsignales um im wesentlichen eine Teilbildperiode bzw. eine Vollbildperiode unter Erzeugung eines teilbildverzögerten (V_{fd}) bzw. eines vollbildverzögerten (V_{fr}) Fernsehsignales;

einer Einrichtung (405) zum Addieren des eintreffenden Fernsehsignales und des vollbildverzögerten Fernsehsignales (V_{fr}) zum Erzeugen eines ersten, vollbild-kammgefilterten Leuchtdichtevideosignals (Y_{fr}), welches einen Leuchtdichteanteil enthält, der von dem eintreffenden und von dem vollbildverzögerten Fernsehsignal gewonnen ist;

einer auf das teilbildverzögerte Fernsehsignal (V_{fd}) ansprechenden Einrichtung (404') zum Erzeugen eines zweiten Leuchtdichtevideosignals (Y'_{fd}), welches eine von dem teilbildverzögerten Fernsehsignal gewonnene Leuchtdichtekomponente enthält;

einer Einrichtung (412, 416) zum Kombinieren des ersten (Y_{fr}) und des zweiten (Y_{fd}) Leuchtdichtevideosignals unter Erzeugung des erwähnten ersten Leuchtdichteausgangssignales (Y_m); und

einer Einrichtung (414, 415), die auf das zweite Leuchtdichtevideosignal (Y'_{fd}) anspricht, um hieraus das erwähnte zweite Leuchtdichteausgangssignal(Y_{fd}) zu erzeugen.

2. Fernsehgerät nach Anspruch 1, weiterhin enthaltend eine Einrichtung (403', 413) zum Extrahieren eines Bilddetailsignales aus dem teilbildverzögerten Fernsehsignal (V_{fd}), wobei die Erzeugungseinrichtung (414, 415) auf das Bilddetailsignal anspricht, um das zweite Leuchtdichteausgangssignal, welches wiederhergestellte Bilddetails enthält, zu erzeugen.

3. Fernsehgerät nach Anspruch 1 oder 2, dadurch gekennzeichnet, daß die Verzögerungseinrichtung (400, 400') einen ersten und einen zweiten Zwischenausgangsabgriff aufweist, die um eine Verzögerung (401') von einer Videozeilendauer getrennt sind, und daß die das zweite Leuchtdichtesignal erzeugende Einrichtung (406') eine Anordnung (402') zum Summieren der Signale am ersten und am zweiten Ausgangsabgriff enthält, um das zweite Leuchtdichtevideosignal (Y'_{fd}) zu erzeugen.

4. Fernsehgerät nach Anspruch 1, 2 oder 3, weiterhin enthaltend eine Einrichtung (406) zum Kombinieren des eintreffenden Fernsehsignales und des vollbildverzögerten Fernsehsignales (V_{fr}) unter Erzeugung der Differenz (412'b) hiervon, und eine Einrichtung (407) zum Erzeugen eines bewegungsanzeigenden Signales (207) aus diesem Differenzsignal, wobei die Kombiniereinrichtung (412) das erste und das zweite Leuchtdichtevideosignal in Abhängigkeit von dem bewegungsanzeigenden Signales kombiniert.

5. Fernsehgerät nach Anspruch 4, dadurch gekennzeichnet, daß das bewegungsanzeigende Signal einen vorgegebenen Wert annimmt, wenn das Fernsehsignal eine nichtstationäre Bildszene aufweist.

6. Fernsehgerät nach Anspruch 4, dadurch gekennzeichnet, daß die Kombiniereinrichtung das erste und das zweite Leuchtdichtesignal entsprechend dem bewegungsanzeigenden Signal proportional kombiniert.

7. Fernsehgerät nach Anspruch 6, dadurch gekennzeichnet, daß der Beitrag des zweiten Leuchtdichtevideosignals in den kombinierten ersten und zweiten Leuchtdichtevideosignalen direkt proportional zur Amplitude des bewegungsanzeigenden Signales ist.

8. Fernsehgerät nach Anspruch 4, weiterhin gekennzeichnet durch eine Einrichtung (412', 421, 417), die auf das Differenzsignal (412'b) anspricht, um hieraus ein erstes I- und ein zweites Q-Farbausgangssignal zu erzeugen.

9. Fernsehgerät nach Anspruch 8, dadurch gekennzeichnet, daß eine Einrichtung (403') vorgesehen ist, welche auf das teilbildverzögerte Fernsehsignal anspricht, um ein teilbildverzögertes Farbartsignal zu erzeugen, und daß die das erste und das zweite Farbausgangssignal erzeugende Einrichtung außerdem eine Anordnung (412') zum Kombinieren des teilbildverzögerten Farbartsignals und des Differenzsignals in Abhängigkeit von dem bewegungsanzeigenden Signal enthält.

10. Fernsehgerät nach Anspruch 9, dadurch gekennzeichnet, daß die die teilbildverzögerten Differenzsignale vereinigende Einrichtung auf das bewegungsanzeigende Signal anspricht, um das teilbildverzögerte Farbartsignal und das Differenzsignal proportional zu kombinieren.

11. Fernsehgerät nach Anspruch 8, 9 oder 10, dadurch gekennzeichnet, daß die das bewegungsanzeigende Signal erzeugende Einrichtung (406, 407) ein Tiefpaßfilter (407) zum Erzeugen eines Signales aus dem Differenzsignal, bei dem die Farbartanteile des Fernsehsignales gedämpft sind, und eine Anordnung (407, 408) zum derartigen Erzeugen des bewegungsabhängigen Signales aus dem durch das Teifpaßfilter erzeugten Signal, daß die Amplitude des bewegungsabhängigen Signales in direkter Beziehung zur Amplitude des durch das Teifpaßfilter erzeugten Signales steht, enthält.

* C L M S *

Revendications

1. Appareil de télévision pour produire à partir d'un signal de télévision couleur composé d'entrée des premier (Ym) et second (Yfd) signaux de sortie de luminance qui sont susceptibles de produire une information d'image pour visualisation en une première pluralité et une seconde pluralité différente de lignes de visualisation, respectivement, d'une image de télévision non entrelacées, pour former une image, comprenant:

une entrée pour recevoir le signal de télévision d'entrée;

un moyen à retard (400, 400') couplé à ladite entrée pour retarder le signal de télévision d'entrée de sensiblement une période de trame et d'une période d'image, respectivement, pour produire des signaux de télévision retardés de trame (V_{fd}) et d'image (V_{fr}), respectivement;

un moyen (405) pour additionner le signal de télévision d'entrée et le signal de télévision retardé d'image (V_{fr}) pour produire un premier signal vidéo de luminance filtré en peigne d'image (Y_{fr}) contenant une composante de luminance dérivée des signaux de télévision retardés d'entrée et d'image;

un moyen (404') répondant au signal de télévision retardé de trame (V_{fd}) pour produire un second signal vidéo de luminance (Y'_{fd}) contenant une composante de luminance dérivée du signal de télévision retardé de trame;

un moyen (412, 416) pour combiner les premier (Y_{fr}) et second (Y_{fd}) signaux vidéo de luminance pour produire le premier signal de sortie de luminance (Y_m); et

un moyen (414, 415) répondant au second signal vidéo de luminance (Y'_{fd}) pour produire à partir de celui-ci le second signal de sortie de luminance (Y_{fd}).

2. Appareil de télévision selon la revendication 1, comprenant de plus un moyen (403', 413) pour extraire un signal de détail d'image du signal de télévision retardé de trame (V_{fd}), où le moyen de production précité (414, 415) répond au signal de détail d'image pour produire le second signal de sortie de luminance précité contenant des détails d'image restitués.

3. Appareil de télévision selon la revendication 1 ou 2, où le moyen de retard précité (400, 400') comprend des première et secondes bornes de sortie intermédiaire espacées l'une de l'autre d'un retard (401') d'une période de ligne vidéo, et où le moyen de production du second signal de luminance précité (406') comprend un moyen (402') pour additionner les signaux auxdites première et secondes bornes de sortie pour former le second signal vidéo de luminance (Y'_{fd}).

4. Appareil de télévision selon l'une des revendications 1 à 3, comprenant de plus un moyen (406) pour combiner le signal de télévision d'entrée précité et le signal de télévision retardé d'image (V_{fr}) pour produire la différence (412'b) de ceux-ci et un moyen (416) pour produire à partir du signal de différence un signal d'indication de déplacement (207) et où le moyen de combinaison (402) combine les premier et second signaux vidéo de luminance en dépendance du signal d'indication de déplacement.

5. Appareil de télévision selon la revendication 4, où le signal d'indication de déplacement précité assume un niveau préétabli lorsque le signal de télévision manifeste une scène d'image non stationnaire.

6. Appareil de télévision selon la revendication 4, où le moyen de combinaison combine proportionnellement les premier et second signaux de luminance précités suivant le signal d'indication de déplacement.

7. Appareil de télévision selon la revendication 6, où la contribution du second signal vidéo de luminance précité dans les premier et second signaux vidéo de luminance combinés est directement proportionnelle à l'amplitude du signal d'indication du déplacement précité.

8. Appareil de télévision selon la revendication 4, comprenant de plus un moyen (412', 421, 417) répondant au signal de différence (412'b) pour produire de celui-ci des premier I et second Q signaux de sortie de couleur.

9. Appareil de télévision selon la revendication 8, où un moyen (403') répond au signal de télévision retardé de trame pour produire un signal de chrominance retardé de trame et le moyen de production précité des premier et second signaux de sortie de couleur comprend de plus un moyen (412') pour combiner les signaux de chrominance retardés de trame et de différence en dépendance du signal d'indication du déplacement.

10. Appareil de télévision selon la revendication 9, où le moyen de combinaison des signaux de différence retardés de trame répond au signal d'indication de déplacement précité pour proportionnellement combiner le signal de chrominance retardé de trame et le signal de différence.

11. Appareil de télévision selon la revendication 8, 9 ou 10, où le moyen de production (406, 407) du signal d'indication de déplacement comprend un filtre passe-bas (407) pour produire un signal à partir du signal de différence tel que la composante de chrominance du signal de télévision soit atténuée et un moyen (407, 408) pour produire le signal d'indication de déplacement à partir du signal produit par le filtre passe-bas tel que l'amplitude du signal d'indication de déplacement soit directement en relation avec l'amplitude du signal qui est produit par le filtre passe-bas.