

RELAXATION CCO FOR PLL-BASED TIME CONSTANT TUNING OF G_M -C FILTERS

BACKGROUND OF THE INVENTION

1. Field of the Invention

The invention relates to relaxation oscillators for use in PLL circuits and in particular to current controlled oscillators without start-up or amplitude control problems used in PLLs for automatic time-constant or bandwidth tuning of g_m -C filters.

2. Description of the Related Art

The design of a two-integrator based sinusoidal quadrature oscillator, which is widely used in phase locked loop (PLL) bandwidth tuning of g_m -C filters (where g_m -C stands for transconductance-Capacitor), is associated with amplitude control/start-up problems. See Khen Sang Tan and Paul R. Gray, "Fully Integrated Analog Filters Using Bipolar-JFET Technology", IEEE Journal of Solid-State Circuits, vol. SC-2, pp. 814-821, Dec. 1978, and John M. Khoury, "Design of a 15MHz CMOS Continuous-Time Filter with On-Chip Tuning", IEEE Journal of Solid-State Circuits vol. SC-26, no. 12, pp. 1988-1997, Dec. 1991.

The above-mentioned PLL-based bandwidth-tuning scheme is shown in Fig. 1 and the two-integrator based quadrature sinusoidal current controlled oscillator (CCO) based on the traditional concept is shown in Fig. 2. The PLL-based bandwidth-tuning scheme 10 of Fig. 1 is comprised of phase detector (PD) 12, a charge pump (CP) 14, a loop filter (LF) 16, a voltage to

current converter (VIC) 18, and a current controlled oscillator (CCO) 20. Block 12 receives as input the reference frequency f_{REF} and from block 20 the feedback input f_0 . Block 12 feeds block 14 which feeds block 16. The output of block 16 is a voltage which get converted by block 18 to the current I_{tunc} . Signal I_{tunc} feeds other blocks for tuning (not shown) and block 20. Fig. 2 is a more detailed diagram of CCO 20 which shows transconductance amplifiers 22 and 24 coupled in series, each with a transconductance of g_m . The output OUT 2 of 22 is coupled to the negative input IN4 of 24. The output OUT4 of 24 feeds the positive input IN2 of 22. The negative input of 22 and the positive input of 24 are grounded. Blocks 22 and 24 receive equal signals I_{tunc} 28 and 29, respectively. The outputs OUT2 and OUT4 are coupled via equal capacitors 26 and 27, respectively, to ground. This type of sinusoidal oscillators suffers from amplitude control and startup problems

US Patents which have some bearing on the present invention are:

6,201,450 (Shakiba et al) describes a relaxation oscillator which provides a very wide linear range of frequency variation versus control voltage (or current). 6,111,467 (Luo) discloses a time constant tuning circuit which uses a frequency of a clock to tune the circuit time constant. 6,084,465 (Dasgupta) describes a time constant tuning circuit in which a reference clock frequency is used to adjust the g_m of a transconductor. 6,060,957 (Kodrnja et al.) teaches a relaxation oscillator with low phase noise particularly applicable to PLLs. 6,020,792 (Nolan et al.) describes a precision relaxation oscillator with temperature compensation to produce a stable clock frequency. 5,497,127 presents a voltage controlled oscillator with a wide range of frequencies and which includes a relaxation oscillator. 5,489,878 (Gilbert) discloses an oscillator which includes two gm/C stages. 5,418,502 (Ma et al.) teaches the use of an R-C

relaxation oscillator where two comparators control the charge/discharge of the capacitor via an SCR. 5,093,634 (Khoury) shows using a triple input, triple output linear transconductance amplifier as an oscillator by feeding back the output of the amplifier to the input. 5,070,311 (Nicolai) describes using current sources, selected by a register, to control the charge/discharge of a capacitor and thereby adjusting the frequency of an oscillator. 4,977,381 (Main) presents a relaxation oscillator where the direction of the current to the capacitor in the oscillator is alternated, based on the state of a bistable circuit. 4,963,840 (Thommen) is similar to 4,977,381 above but in addition reduces power consumption. 4,725,993 (Owen et al.) discloses a low duty cycle relaxation oscillator which periodically gates an ultrasonic frequency relaxation oscillator. 4,377,790 (Zobel et al.) teaches a relaxation oscillator where a capacitor is charged and discharged between an upper and lower voltage level based on a signal from a comparator. 4,535,305 (Matsuo et al.) describes a transmission gate relaxation oscillator using a comparator which compares the charge/discharge voltage with a reference voltage. The invention is different from all of the above cited US Patents.

The invention below describes several equivalent relaxation CCOs that overcome startup/amplitude control problems of sinusoidal CCOs, are simple to design and totally compatible with modern PLL circuits.

SUMMARY OF THE INVENTION

It is an object of at least one embodiment of the present invention to provide a circuit and a method for a relaxation current controlled oscillator (CCO) for phase locked loop (PLL)-based time constant tuning of g_m -C filters.

It is another object of the present invention to provide a CCO which does not have amplitude control problems.

It is yet another object of the present invention to provide a CCO which does not have start-up problems.

It is still another object of the present invention to provide a CCO which is simple to design and is totally compatible with modern PLL circuits.

It is a further object of the present invention is to provide a CCO where there is great flexibility in choosing the reference frequency f_{REF} or the oscillation frequency f_0 .

It is yet a further object of the present invention is to provide a CCO with a truly 50% duty cycle output waveform.

It is still a further object of the present invention is to provide a CCO with a non overlapping output waveform.

These and many other objects have been achieved by forming a test integrator out of a transconductance amplifier and a capacitor. The output of the integrator is fed to comparators which in turn feed a bistable circuit such as a SR flip flop. The output Q and its inverse QB of the bistable circuit controls either the polarity of the input signals to the transconductance

amplifier or the polarity of the input signals to the comparators (when the transconductance amplifier has a differential output). Switches, controlled by the bistable circuit, in turn control the polarity of the input signals. The feedback path created by the transconductance amplifier, comparators, flip-flops, and switches causes continuous oscillation to take place. A DC current input adjusts the g_m of the transconductance amplifier allowing the oscillation frequency of the CCO to be adjusted by varying the DC current input. There is great flexibility in choosing the reference frequency f_{REF} or the oscillation frequency f_0 by the proper choice of a resistive divider.

These and many other objects and advantages of the present invention will be readily apparent to one skilled in the art to which the invention pertains from a perusal of the claims, the appended drawings, and the following detailed description of the preferred embodiments.

BRIEF DESCRIPTION OF THE DRAWINGS

Fig. 1 is a block diagram of a time-constant Tuning PLL for g_m -C filters of the prior art.

Fig. 2 is a block diagram of a quadrature sinusoidal oscillator of the prior art.

Fig. 3a is a schematic of a first preferred embodiment of a CCO for a time-constant tuning PLL of the present invention.

Fig. 3b is a graph of the input and output waveforms of Fig. 3a.

Fig. 4a is a schematic of a second preferred embodiment of a CCO for a time-constant tuning PLL of the present invention.

Fig. 4b is a graph of the input and output waveforms of Fig. 4a.

Fig. 5a is a schematic of a third preferred embodiment of a CCO for a time-constant tuning PLL of the present invention.

Fig. 5b is a graph of the input and output waveforms of Fig. 5a.

Fig. 6a is a schematic of a fourth preferred embodiment of a CCO for a time-constant tuning PLL of the present invention.

Fig. 6b is a graph of the input and output waveforms of Fig. 6a.

Fig. 7 is a graph of the tuning characteristics of the typical CCO of the preferred embodiment of the present invention.

Fig. 8 is a block diagram of the preferred method of the invention.

DESCRIPTION OF THE PREFERRED EMBODIMENT

Fig. 3a shows the schematic of the first preferred embodiment of the inventive relaxation CCO 30. A test integrator is formed out of the test transconductance amplifier 32 (of transconductance g_m) and a capacitor 34 (of capacitance C). The output V_{cap} of the integrator is fed to two comparators 36a and 36b. The outputs of the comparators feed a SR latch 38 with outputs Q and QB. SR latch 38 is not further described here since it is a basic component of digital circuitry and well known. The latch controls the polarity of the input DC voltage (across R_B) to the transconductance amplifier. A switching network comprising switching means S1, S2, S3, and S4 is coupled across resistor R_B of a resistor string and the plus and minus inputs of transconductance amplifier 32. The resistor string itself is a series network of resistors with values R_A , R_C , R_B , R_C , and R_A coupled between voltage supply V_{DD} and its return side (typically ground GND). V_H and V_L are nodes along the resistor string which couple to the plus and minus inputs of comparators 36a and 36b, respectively. The output V_{cap} of transconductance amplifier 32 couples to the minus and plus input of comparators 36a and 36b, respectively, and to capacitor 34. In addition, current I_{tune} is applied to transconductance amplifier 32 of Figs. 3a as well as all transconductance amplifiers 32 of Figs. 4a, 5a (including transconductance amplifier 52), and 6a.

If Q is high and QB low (latch set), switching means S1 and S4 are open and S2 and S3 are closed. If QB is high and Q low (latch reset), switching means S1 and S4 are closed with S2 and S3 open. The latter state (when the latch is reset) applies the small voltage across R_B at the input to the integrator and as a consequence, its output V_{cap} rises linearly with time. This continues

till V_{cap} reaches V_{H1} and the upper comparator trips setting the latch (Q is high and QB low).

Now S_1, S_4 opens and S_2, S_3 closes. This also applies the small voltage across R_B to the input of the integrator, but in the opposite direction. As a result, V_{cap} now goes down linearly with time till it reaches V_L . At this point, the lower comparator trips and resets the latch. Therefore the above two sequences will repeat again and again causing continuous oscillation to take place.

Fig. 3b displays the waveshapes at nodes V_{cap} (Curve 31), Q, and QB (Curves 32 and 33, respectively). Note that the graphs of Figures 3b, 4b, 5b, and 6b represent voltages in the vertical axis.

Below is the calculation to find the oscillation frequency f_0 .

$$V_L = \frac{R_A}{\Sigma R} V_{DD}, V_H = \frac{R_A + 2R_C + R_B}{\Sigma R} V_{DD}, \text{ where } \Sigma R = 2R_A + 2R_C + R_B \quad (1)$$

$$I_O = g_m \frac{R_B}{\Sigma R} V_{DD} \quad (2)$$

$$T_1 = T_2 = \frac{C(V_H - V_L)}{I_O} = \left(1 + \frac{2R_C}{R_B}\right) \frac{C}{g_m} \quad (3)$$

$$f_0 = \frac{1}{T_1 + T_2} = \frac{1}{2\left(1 + \frac{2R_C}{R_B}\right)} \frac{g_m}{C} \quad (4)$$

$$\text{From (4), } f_0 \cong \frac{1}{2\pi} \frac{g_m}{C}, \quad \text{if } \frac{R_C}{R_B} = 1.07 \quad (5)$$

$$\text{Also, } f_0 = \frac{1}{2} \frac{g_m}{C}, \quad \text{if } R_C = 0 \quad (6)$$

Equation (5) shows that the circuit can be adjusted to have a frequency very nearly equal to that of the traditional two-integrator sinusoidal oscillator.

I_{tune} is the DC current input to adjust the g_m of the transconductance amplifier. This means the oscillation frequency f_0 of the CCO can be adjusted by varying I_{tune} . When this CCO is used in the PLL shown in Fig. 1, we have:

$$f_{\text{REF}} = f_0 = \frac{1}{2 \left(1 + \frac{2R_C}{R_B} \right)} \frac{g_m}{C} \quad (7)$$

from (7) we have:
$$\frac{g_m}{C} = 2 \left(1 + \frac{2R_C}{R_B} \right) f_{\text{REF}} \quad (8)$$

Since R_C/R_B is a constant, the g_m/C of the test integrator is determined directly by f_{REF} . If all the integrators in a g_m -C filter are made identical to the test integrator and if I_{tune} from the PLL is used to control each transconductor (using current mirroring), then the bandwidth of the filter (determined by g_m/C) is also determined by f_{REF} and can be tuned by it. Equation (8) shows that there is a great flexibility in choosing f_{REF} or f_0 due to the ratio R_C/R_B . In the case of the traditional sinusoidal oscillator, the constant multiplier of f_{REF} in (8) would be fixed at 2π .

The transconductance amplifier and the integrator formed by it are referred to as 'test' integrators because they are identical to those used in the main filter for which time-constant or bandwidth tuning one wants to do. The problem is to find out the ' g_m ' of the ones in the main filter. Since this cannot be done directly without affecting the filter performance, an additional

integrator, identical to the one in the filter, is used as a 'test' element and its ' g_m ' is found out instead and corrected with a PLL using the inventive circuit.

Fig. 4a shows a second preferred embodiment of a CCO in the form of CCO 40. Here differential outputs A (+) and B (-) are used for the transconductor 32. However, again only one timing capacitor 34 is used. This implementation uses output switching instead of input switching of Fig. 3a. This helps in getting rid of any delay through the transconductor and, therefore, allows higher frequency of operation. It is to be noted that non-overlapping output waveforms are generated, as shown in Fig. 4b Curves 47 and 48, to avoid discharging of the timing capacitor 34 during switching. Curves 47 and 48 are enlarged sections of Curves 45 and 46, respectively, to more clearly demonstrate non-overlapping. Fig. 4b also shows the waveforms for outputs A and B (Curves 41 and 42, respectively), the waveform at Vcap and node C (Curves 43 and 44, respectively), and output waveforms for ϕ_2 and ϕ_1 (Curves 45 and 46, respectively). The resistor string of Fig. 4a is the same as that for Fig. 3a including connections to transconductor 32, comparators 36a and 36b, V_{DD} and ground. A switching network comprising switching means S1-4 is coupled between outputs A and B and nodes Vcap and C. Vcap in turn is coupled to the positive and negative inputs of comparators 36a and 36b, respectively, and via timing capacitor 34 (of capacitance C) to ground. Node C is coupled via resistors R_D to both V_{DD} and ground. Note also that capacitors C_d are connected at the NOR gates of SR latch 38 to help generate the non-overlap. R_D for Fig. 4a is defined as:

$$R_D = R_A + R_C + R_B / 2$$

Note that the suffix for S1 to S4 indicates during which phase the switching means is active, such that: S1- ϕ 2 and S3- ϕ 2 are on when output ϕ 2 of SR latch 38 is high, and that S2- ϕ 1 and S4- ϕ 1 are on when output ϕ 1 is high.

Fig. 5a shows a third preferred embodiment of a CCO in the form of CCO 50. This implementation uses two differential output transconductors 32 and 52. This implementation also employs output switching. The resistor string of Fig. 5a is the same as that for Fig. 3a including connections to transconductor 32, comparators 36a and 36b, V_{DD} and ground. A switching network comprising switching means S1 to S4 is coupled between outputs A and B of transconductor 32 and node Vcap and outputs C and D of transconductor 52. More specifically, A is coupled via S4- ϕ 1 to C and via S1- ϕ 2 to Vcap, B is coupled via S3- ϕ 2 to D and via S2- ϕ 1 to Vcap. As in Fig. 4, Vcap is coupled to the positive and negative inputs of comparators 36a and 36b, respectively, and via timing capacitor 34 (of capacitance C) to ground. Outputs C and D are coupled to nodes V_L' and V_H' , respectively. Nodes V_L' and V_H' are part of a second resistive network comprising two resistor strings in parallel having resistors of value R_A and R_D in series between V_{DD} and ground, respectively, and, similarly, resistors R_D and R_A in series between V_{DD} and ground, respectively. R_D is defined as: $R_D = R_A + R_B + 2R_C$. Note that the voltages at nodes V_H and V_H' are identical, so are the voltages at nodes V_L and V_L' .

Current from one output of the transconductor (32) charges the timing capacitor 34 of capacitance C and the other transconductor 52 helps to maintain continuity of the current from

the other output of transconductor 32. The advantage of this implementation is that transconductor 32 outputs A and B do not see voltage jumps when the switching means connect them to the timing capacitor, unlike in the second embodiment of Fig. 4. This enables higher frequency of operation. Here also, non-overlapping output waveforms are generated. As in Fig. 4a, capacitances C_d are added to SR latch 38, which help to generate the non-overlapping waveform.

Note that the suffix for S1 to S4 indicates during which phase the switching means is active, such that: S1- $\phi 2$ and S3- $\phi 2$ are on when output $\phi 2$ of SR latch 38 is high, and that S2- $\phi 1$ and S4- $\phi 1$ are on when output $\phi 1$ is high.

Fig. 5b shows the waveforms for V_{cap} (Curve 51), A (Curve 52), B (Curve 53), C (Curve 54), D (Curve 55), $\phi 2$ (Curve 56), and $\phi 1$ (Curve 57). Curves 58 and 59 are enlarged sections of Curves 56 and 57 to more clearly demonstrate non-overlapping.

Fig. 6a shows a fourth preferred embodiment of a CCO in the form of CCO 60. This is a fully differential implementation employing both input and output switching and four timing capacitors 64a-d each of capacitance C. Each timing capacitor is charged to the appropriate reference voltage and applied to the output of transconductor 32 for integration. The integration of a pair of capacitors is conducted while charging of the other pair is carried out. In this case also a non-overlapping output waveform is generated. However, the output frequency is double of the previous embodiments. Being fully differential, this circuit provides a truly 50% duty

cycle output waveform as errors due to minor mismatches in the differential transistors balance off.

Still referring to Fig. 6a, the circuit is explained in more detail. Resistive strings R_A - R_E - R_A and R_D - R_B - R_D are both coupled between V_{DD} and a reference potential (typically ground as shown in Fig. 6a). The node between R_A and R_E is labelled V_H , and the node between R_E and R_A is labelled V_L . In the identical switching arrangement as that of Fig. 3a for switching means S1 to S4, the high side of R_B couples via S1- ϕ_2 and S2- ϕ_1 to the positive and negative input of transconductor 32, respectively. The low side of R_B couples via S3- ϕ_1 and S4- ϕ_2 to the positive and negative input of transconductor 32, respectively. The plus and minus output of transconductor 32 couples to the plus and minus input of dual-output comparator 66, respectively. The plus and minus outputs of comparator 66 feed SR latch 38. Coupled between nodes V_H and V_L are in series switching means S5- ϕ_2 , S6- ϕ_1 , S7- ϕ_2 , S8- ϕ_1 . The junction between S6- ϕ_1 and S7- ϕ_2 is node Vcap. A capacitor 64a is coupled between ground and the junction of S5- ϕ_2 and S6- ϕ_1 , and capacitor 64b is coupled between ground and the junction of S7- ϕ_2 and S8- ϕ_1 . Node Vcap connects to the plus output of transconductor 32. Similarly, coupled between nodes V_H and V_L are in series switching means S9- ϕ_1 , S10- ϕ_2 , S11- ϕ_1 , S12- ϕ_2 . The junction between S10- ϕ_2 and S11- ϕ_1 is node Vcap' and connects to the negative output of transconductor 32. Capacitor 64c is coupled between ground and the junction of S9- ϕ_1 and S10- ϕ_2 , and capacitor 64d is coupled between ground and the junction of S11- ϕ_1 and S10- ϕ_2 .

Node Vcap' connects to the minus output of transconductor 32. Resistor R_D is defined as:

$R_D = R_A + R_C$, and resistor R_E is defined as: $R_E = R_B + 2R_C$.

Note that the suffix for S1 to S12 indicates during which phase the switching means is active, e.g., S1- ϕ_2 , S4- ϕ_2 and S5- ϕ_2 are on when output ϕ_2 of SR latch 38 is high, and S2- ϕ_1 , S3- ϕ_1 , and S6- ϕ_1 are on when output ϕ_1 is high.

Fig. 6b shows the waveforms for Vcap (Curve 61), Vcap' (Curve 62), ϕ_2 (Curve 63), and ϕ_1 (Curve 64). Curves 65 and 66 are enlarged sections of Curves 63 and 64 to more clearly demonstrate non-overlapping, caused by capacitors Cd.

The following table shows the comparison of the four embodiments:

Embodiment no.	H.F. capability	Circuit complexity	Waveform symmetry
1	Low	Low	Good
2	Medium	Medium	Average
3	High	High	Average
4	Low	Medium	Very good

Simulation Results:

Simulation results show that the circuit functions as expected. The calculated (with formula) and simulation frequency are very close. The curve of Fig. 7 shows a typical tuning

characteristic of the CCO relating the bias current (I_{tune}) to the CCO frequency (f_0), valid for any of the above described preferred embodiments.

The method of providing a relaxation current controlled oscillator is shown in Fig. 8 and comprises the following steps:

Block 1: forming an integrator from a test transconductance amplifier and capacitive means;

Block 2: coupling the output of the integrator to comparator means;

Block 3: applying the output of the comparator means to a bistable circuit;

Block 4: applying a DC tuning current to adjust the transconductance g_m of the transconductance amplifier;

Block 5: controlling switching means via the bistable circuit to alternate the state of the bistable circuit thus producing continuous oscillations.

In summary the advantages of the present invention include:

- (1) A relaxation oscillator which is compatible with PLL-based tuning of g_m -C filters.
- (2) No start-up/amplitude control problems have to be overcome.
- (3) There is more flexibility in deciding f_{REF} or f_0 .

While the invention has been particularly shown and described with reference to the preferred embodiments thereof, it will be understood by those skilled in the art that various changes in form and details may be made without departing from the spirit and scope of the invention.

CLAIMS.

1. A relaxation current controlled oscillator, comprising:

an integrator having a first and a second input and at least one output, said integrator integrating a voltage signal applied at its inputs, said integrator further comprising

5

a transconductance amplifier having a first and a second input and at least one output, said transconductance amplifier having a transconductance g_m , said transconductance amplifier providing at its output a signal proportional to its inputs, said inputs of said transconductance amplifier coupled to said inputs of said integrator, said output of said transconductance amplifier coupled to said output of said integrator; and

10

capacitive means coupled to the output of said transconductance amplifier, where said capacitive means is charged up by the output signal of said transconductance amplifier;

15 first comparator means for comparing the output signal of said transconductance amplifier against a first reference voltage, said first comparator means setting a Set-Reset type flip-flop when said output signal of said transconductance amplifier matches said first reference voltage;

second comparator means for comparing the output signal of said transconductance amplifier

20 against a second reference voltage, said second comparator means resetting a Set-Reset type flip-

flop when said output signal of said transconductance amplifier matches said second reference voltage; and

first and second switching means in communication with said inputs of said transconductance amplifier for controlling the polarity of said voltage signal applied to said inputs of said transconductance amplifier.

2. The relaxation current controlled oscillator of claim 1, wherein said output of said flip-flop and the inverse of said output of said flip-flop control said first and said second switching means thus producing continuous oscillations.

3. The relaxation current controlled oscillator of claim 1, wherein a DC tuning current is applied to said transconductance amplifier to adjust the transconductance g_m of said transconductance amplifier.

4. The relaxation current controlled oscillator of claim 1, wherein the oscillation frequency f_0 of said relaxation current controlled oscillator can be adjusted by varying a DC tuning current applied to said transconductance amplifier.

5. The relaxation current controlled oscillator of claim 1, wherein said voltage signal at said input of said integrator is derived from a network comprising resistive means.

6. The relaxation current controlled oscillator of claim 5, wherein said network comprising resistive means is coupled between a positive voltage supply and its return side.

7. A relaxation current controlled oscillator, comprising:

5 an integrator having a first and a second input and a first and a second output, said integrator integrating a voltage signal applied at its inputs, said integrator further comprising

a transconductance amplifier having a first and a second input and a first and a second output, said transconductance amplifier having a transconductance g_m , said

10 transconductance amplifier providing at its outputs a signal proportional to its inputs, said inputs of said transconductance amplifier coupled to said inputs of said integrator, said outputs of said transconductance amplifier coupled to said outputs of said integrator; and

capacitive means coupled to the outputs of said transconductance amplifier, where the
15 voltage across said capacitive means is controlled by the output signals of said transconductance amplifier;

first comparator means for comparing a first output signal of said transconductance amplifier against a first reference voltage, said first comparator means setting a Set-Reset type flip-flop
20 when said output signal of said transconductance amplifier matches said first reference voltage;

second comparator means for comparing the output signal of said transconductance amplifier against a second reference voltage, said second comparator means resetting a Set-Reset type flip-flop when said output signal of said transconductance amplifier matches said second reference voltage;

5

first and second switching means coupled between said outputs of said transconductance amplifier and said first and second comparator for controlling the polarity of said voltage signal applied to the positive input of said first comparator and the negative input of said second comparator, respectively; and

10

said first and said second switching means further coupled between said outputs of said transconductance amplifier and a first terminal of resistive means.

8. The relaxation current controlled oscillator of claim 7, wherein said output of said flip-flop and the inverse of said output of said flip-flop control said first and said second switching means thus producing continuous oscillations.

15

9. The relaxation current controlled oscillator of claim 7, wherein a DC tuning current is applied to said transconductance amplifier to adjust the transconductance g_m of said transconductance amplifier.

20

10. The relaxation current controlled oscillator of claim 7, wherein the oscillation frequency f_0 of said relaxation current controlled oscillator can be adjusted by varying a DC tuning current applied to said transconductance amplifier.

5 11. The relaxation current controlled oscillator of claim 7, wherein said voltage signal at said inputs of said integrator is derived from a network comprising resistive means.

12. The relaxation current controlled oscillator of claim 11, wherein said network comprising resistive means is coupled between a positive voltage supply and its return side.

10

13. The relaxation current controlled oscillator of claim 12, wherein a second terminal of said resistive means is coupled to said positive voltage supply return side.

14. A relaxation current controlled oscillator, comprising:

15

an integrator having differential inputs and outputs, said integrator integrating a voltage signal applied at its inputs, said integrator further comprising

20

a first transconductance amplifier having differential inputs and outputs, said first transconductance amplifier having a transconductance g_m , said first transconductance amplifier providing at its outputs a signal proportional to its inputs, said inputs of said

first transconductance amplifier coupled to said inputs of said integrator, said outputs of said first transconductance amplifier coupled to said outputs of said integrator;

a second transconductance amplifier having differential inputs and outputs, said second transconductance amplifier having a transconductance g_m , said second transconductance amplifier providing at its output a signal proportional to its inputs, said inputs of said second transconductance amplifier coupled to said inputs of said integrator, said outputs of said second transconductance amplifier coupled to said outputs of said integrator ; and

capacitive means in communication with the differential outputs of said first transconductance amplifier, where said capacitive means is charged up by differential output signals of said first transconductance amplifier depending on the state of first and second switching means;

first comparator means for comparing the positive output signal of said first transconductance amplifier against a first reference voltage, said first comparator means forcing a Set-Reset type flip-flop to a first state when said output signal of said transconductance amplifier matches said first reference voltage;

second comparator means for comparing the negative output signal of said first transconductance amplifier against a second reference voltage, said second comparator means forcing said Set-

Reset type flip-flop to the opposite of said first state when said output signal of said transconductance amplifier matches said second reference voltage;

said first and second switching means coupled between said outputs of said first trans-

- 5 conductance amplifier and said first and second comparator for controlling the polarity of said voltage signal applied to the positive input of said first comparator and the negative input of said second comparator, respectively;

- said first and second switching means further coupled between said outputs of said first and said
10 second transconductance amplifier; and

a first network of resistive means coupled to the outputs of said second transconductance amplifier.

- 15 15. The relaxation current controlled oscillator of claim 14, wherein said output of said flip-flop and the inverse of said output of said flip-flop control said first and said second switching means thus producing continuous oscillations.

16. The relaxation current controlled oscillator of claim 14, wherein a DC tuning current is
20 applied to said first and said second transconductance amplifier to adjust the transconductance g_m of said first and said second transconductance amplifier.

17. The relaxation current controlled oscillator of claim 14, wherein the oscillation frequency f_0 of said relaxation current controlled oscillator can be adjusted by varying a DC tuning current applied to said first and said second transconductance amplifier.

5 18. The relaxation current controlled oscillator of claim 14, wherein said first switching means is controlled by the state opposite to said first state of said flip-flop.

19. The relaxation current controlled oscillator of claim 14, wherein said second switching means is controlled by said first state of said flip-flop.

10

20. The relaxation current controlled oscillator of claim 14, wherein said voltage signal at said differential inputs of said integrator is derived from a second network comprising resistive means.

15 21. The relaxation current controlled oscillator of claim 20, wherein said first and said second network comprising resistive means are coupled between a positive voltage supply and its return side.

22. A relaxation current controlled oscillator, comprising:

20

an integrator having differential inputs and outputs, said integrator integrating a voltage signal applied at its inputs, said integrator further comprising:

a transconductance amplifier having differential inputs and outputs, said
transconductance amplifier having a transconductance g_m , said transconductance
amplifier providing at its outputs a signal proportional to its inputs, said inputs of said
transconductance amplifier coupled to said inputs of said integrator, said output of said
5 transconductance amplifier coupled to said output of said integrator; and

capacitive means in communication with the outputs of said transconductance amplifier,
where the voltage across said capacitive means is controlled by the output signals of said
transconductance amplifier;

10 comparator means for comparing the output signals of said transconductance amplifier, said
comparator means controlling the state of a Set-Reset type flip-flop based on said output signal
of said transconductance amplifier;

15 a resistive network coupled between a positive voltage supply and its return side, said resistive
network providing voltage references for said transconductance amplifier;

a first set of switching means, coupled between said resistive network and the inputs of said
transconductance amplifier, for reversing the polarity applied to said inputs of said

20 transconductance amplifier, said first set of switching means responsive to the state of said flip-
flop; and

a second set of switching means serially coupled between said voltage references, said second set of switching means controlling the connection between the output of said transconductance amplifier and said capacitive means, said second set of switching means responsive to the state of said flip-flop.

5

23. The relaxation current controlled oscillator of claim 22, wherein said output of said flip-flop and the inverse of said output of said flip-flop control said switching means thus producing continuous oscillations.

10 24. The relaxation current controlled oscillator of claim 22, wherein a DC tuning current is applied to said transconductance amplifier to adjust the transconductance g_m of said transconductance amplifier.

15 25. The relaxation current controlled oscillator of claim 22, wherein the oscillation frequency f_0 of said relaxation current controlled oscillator can be adjusted by varying a DC tuning current applied to said transconductance amplifier

20 26. The relaxation current controlled oscillator of claim 22, wherein said first and said second set of switching means further comprise a first switching means, said first switching means controlled by the inverse output of said flip-flop.

27. The relaxation current controlled oscillator of claim 22, wherein said first and said second set of switching means further comprise a second switching means, said second switching means controlled by the output of said flip-flop.
- 5 28. The method of providing a relaxation current controlled oscillator, comprising the steps of:
- a) forming an integrator from a test transconductance amplifier and capacitive means;
 - b) coupling the output of said integrator to comparator means;
 - c) applying the output of said comparator means to a bistable circuit;
 - 10 d) applying a DC tuning current to adjust the transconductance g_m of said transconductance amplifier; and
 - e) controlling switching means via said bistable circuit to alternate the state of said bistable circuit thus producing continuous oscillations.
- 15 29. The method of claim 28, wherein said bistable circuit has first and complimentary output signals.
30. The method of claim 28, wherein the input signal to said integrator is produced by a voltage drop across resistive means.
- 20 31. The method of claim 28, wherein the polarity of said input signal is controlled by said switching means.

32. The method of claim 28, wherein the output of said integrator is coupled to said capacitive means via said switching means.
- 5 33. The method of claim 28, wherein the output of said integrator is coupled to said comparator means via said switching means.
34. The method of claim 28, wherein the oscillation frequency f_0 of said transconductance amplifier is adjusted by varying the DC tuning current.
- 0 35. A time-constant tuning PLL for g_m -C filters with time relaxation oscillator, comprising:
- a PLL used for bandwidth tuning of transconductance-capacitor (g_m -C) filters, said PLL comprising serially coupled a phase detector, a charge pump, a loop filter, a voltage-current
- 5 converter, and a relaxation current controlled oscillator, where a first input of said phase detector receives a reference frequency and a second input of said PLL is coupled to the output of said relaxation current controlled oscillator, said output of said relaxation current controlled oscillator providing an oscillation frequency f_0 ; where said relaxation current controlled oscillator is compatible with said PLL, said relaxation current controlled oscillator furthermore providing
- 10 more flexibility in selection of said reference frequency and said oscillation frequency f_0 , said relaxation current controlled oscillator further comprising:

an integrator having a first and a second input and at least one output, said integrator integrating a voltage signal applied at its inputs, said integrator further comprising

5 a transconductance amplifier having a first and a second input and at least one output, said transconductance amplifier having a transconductance g_m , said transconductance amplifier providing at its output a signal proportional to its inputs, said inputs of said transconductance amplifier coupled to said inputs of said integrator, said output of said transconductance amplifier coupled to said output of said integrator; and

10 capacitive means coupled to the output of said transconductance amplifier, where said capacitive means is charged up by the output signal of said transconductance amplifier;

15 first comparator means for comparing the output signal of said transconductance amplifier against a first reference voltage, said first comparator means setting a Set-Reset type flip-flop when said output signal of said transconductance amplifier matches said first reference voltage;

20 second comparator means for comparing the output signal of said transconductance amplifier against a second reference voltage, said second comparator means resetting a

Set-Reset type flip-flop when said output signal of said transconductance amplifier matches said second reference voltage; and

first and second switching means in communication with said inputs of said

transconductance amplifier for controlling the polarity of said voltage signal applied to said inputs of said transconductance amplifier.

36. The time-constant tuning PLL of claim 35, wherein a DC tuning current is applied to said transconductance amplifier to adjust the transconductance g_m of said transconductance amplifier.

37. The time-constant tuning PLL of claim 35, wherein the oscillation frequency f_0 of said relaxation current controlled oscillator can be adjusted by varying a DC tuning current applied to said transconductance amplifier.