

Description

This invention relates to television receivers and particularly to receivers of the type employing « progressive scanning » to effectively increase the vertical resolution of displayed images.

"Progressively" scanned television receivers have been proposed wherein the horizontal scan rate is multiplied, e.g., doubled, and each line of video is displayed twice thereby providing a displayed image having reduced visibility of line structure and subjectively improved vertical resolution. In a typical progressively scanned receiver, each line of video is stored in one of two memories. As one of the memories is being written with the incoming video signal at the standard line rate, the other memory is read two times at twice the standard line rate thereby providing two lines of time compressed video within one standard line interval. The memory output is applied to a display having a doubled horizontal sweep rate synchronized with read-out of the memory thereby doubling the number of displayed lines of video signal.

When implementing a progressively scanned receiver with digital signal processing circuits, one may employ random access memories (RAM) to store line information. Digital signal processing systems typically utilize a coherent clock for purposes of signal sampling, memory address control and other functions. For simplicity of chroma processing, the clock is typically phase locked to an integer multiple of the color subcarrier frequency. For NTSC standard video signals, the clock frequency is often selected to be four times that of the color subcarrier ($4f_{sc}$) or about 14.3 MHz with a period of about 70 nanoseconds. One line of memory, for this clock frequency and the standard NTSC line period of about 63.5 microseconds, therefore requires 910 locations of a RAM to store 910 video samples or « pixels » (picture elements). This memory requirement is invariant for standard NTSC signals because under the NTSC standard there are exactly 227.5 color subcarrier cycles per horizontal line. With a digital-to-analog (D/A) conversion done at four times the color subcarrier frequency ($4f_{sc}$) there are thus, exactly 910 (4×227.5) pixels per line. As long as the memory read clock is exactly double the frequency of the write clock, the resultant « double-speed » or « time-compressed » pixels will have proper horizontal spacing and vertical alignment when displayed.

It is recognized herein that a subtle problem exists in progressively scanned systems of the type described when displaying what will be referred to hereinafter as non-standard video signals. As used herein, the term non-standard refers to video signals wherein the ratio of the color subcarrier frequency to horizontal line frequency does not conform exactly to a specified broadcasting standard (e.g., 227.5 in the NTSC standard). Where, for example, the video

source is a video disc player, a video cassette recorder, a video « game » unit or some source other than broadcast television, the burst/line-frequency ratio may differ substantially from the standard ratio. Under these conditions, the number of video samples (picture elements or « pixels ») in a horizontal line period will not, in general, be 910 (assuming a $4f_{sc}$ write clock).

The deviation of the number of samples (pixels) per line from the standard (910) is difficult to deal with because it represents a precession of the A/D converter sampling signal clock phase with respect to the incoming horizontal synchronizing signal phase. The effect of this precession, « phase-slip » or « skew » is that horizontal timing errors accumulate throughout each field. Moreover, in a progressive scan system, where a coherent $8f_{sc}$ read clock is used with double (2H) standard rate deflection for the display, the $8f_{sc}$ read clock precession relative to the 2H deflection will be double that of the $4f_{sc}$ (write) clock precession relative to the 1 H incoming video signal. This problem is unique to progressive scan systems and can cause accumulated horizontal timing errors, or full-pixel timing discontinuities between lines. The visible effects may be seen as picture skew, ragged edges or other undesirable artifacts.

In view of the foregoing, one might consider pre-processing the video signal prior to « speed-up » in the progressive scan processor (PSP) with a conventional time-base corrector (TBC). Examples of time-base correctors suitable for use with video tape recorder (VTR) reproduced signal are given in U.S. Patents US-A-4,249,198 of Ito et al., and US-A-4,443,821 of Kato. In Ito et al. a digitized video signal provided by an un-synchronized VTR is stored in the TBC memory (one field) and the storage locations as well as delay prior to storage of the digital samples of the video signal are controlled in response to the phase difference between the incoming video synchronizing signal components and a constant reference signal (e.g., « house synch »). The TBC of Kato is specifically addressed to correcting intra-line velocity errors of a VTR reproduced signal and includes a velocity error detector for detecting velocity errors in successive lines of the video signal written into memory. A sample level compensator at the output of the TBC memory adjusts the level of the video samples (pixels) read out from the memory as a function of the detected velocity error such that the level of the read out sample is modified to be equal to the level that the read-out sample should have had at the time it was read out if there had been no velocity error.

It is recognized herein that the use of conventional time-base correctors will not solve the unique problems encountered in progressively scanned video display systems. The problem in progressive scan systems involves more than time-base errors (e.g., « jitter »), it involves non-standard signals whe-

rein there may be a variation of the number of pixels per line and this variation is effectively multiplied by the double reading of each line which occurs only in progressively scanned systems. This problem does not exist in conventional time-base correctors because there each line is read only once.

Simply stated, in a progressively scanned display system, the number of pixels to be stored in the video « speed-up » memory during a memory write operation may vary for different sources and there may even be variations during a program provided by a single source. This can lead to a problem with regard to the second memory read operation under certain circumstances. As an example, assume that the memory address generator is clocked at 4 times the color subcarrier frequency ($4 f_{sc}$) and that the video signal is « non-standard » having, say, 227 rather than 227.5 color subcarrier cycles per line. Under these conditions 908 pixels will be stored in the memory during a write operation. If the memory address generator is programmed to reset for the second memory read operation at the NTSC standard (910 pixels, addresses 000-909) then the start of the second memory read operation for the 908 pixel line will begin two pixels late at address 910. A similar problem exists where the color subcarrier frequency is too high except that the memory read operation will start too early rather than being late.

The present invention resides in part in the recognition that « fixed » or constant modulo memory addressing in a progressively scanned system can lead to undesirable visual artifacts (ragged edges, etc.) for « non-standard » signals as hereinbefore defined. A progressive scan video processor embodying the invention includes a memory means for storing a video input signal supplied thereto during a first line interval and for recovering the stored signal N-times during a subsequent line interval to provide a processed video output signal having a line rate N-times that of said video input signal. An address generator means is provided for supplying read and write addresses to the memory means. A circuit means, coupled to the address generator means, stores the last address written in the memory means during a memory write operation and controls the starting time of at least one subsequent memory read operation in accordance with the stored address.

The invention is illustrated in the accompanying drawing wherein like elements are identified by like reference designators, and in which:

Figure 1 is a block diagram of a progressive scan television receiver embodying the invention;
Figure 2 is a block diagram illustrating certain details of an address generator suitable for use in the receiver of figure 1; and
Figure 3 is a timing diagram illustrating certain aspects of operation of the address generator of figure 2.

The receiver of figure 1 includes an input terminal 10 for connection to a source of television signals. When connected to an antenna for receiving standard broadcast signals, the received signal will conform to a standard (NTSC, for example) wherein the number of color subcarrier cycles per horizontal line is known exactly (e.g., 227.5). When connected to another source, such as a « consumer » disc or tape recorder, the color subcarrier/line frequency ratio may differ from the exact broadcast standard as previously discussed and this difference may tend to result in various visible artifacts being displayed if not compensated for as described hereinafter.

Terminal 10 is connected to a tuner/IF processing unit 12 of conventional design to provide a baseband video output signal S1. (For video « MONITOR » applications, tuner 12 may be omitted or bypassed by means of a switch.) The baseband video signal S1 is applied to an analog-to-digital (A/D) converter 14 and to a timing unit 16. Unit 16 includes conventional sync and burst detectors and multiplying phase locked loops to generate a plurality of timing signals including memory read and write clocks phase-locked to eight and four times the color subcarrier frequency, respectively, ($8 f_{sc}$, $4 f_{sc}$). Half line rate signals ($FH/2$) are provided for controlling memory read/write (R/W) selection and double line rate signals ($2 FH$) are provided for timing the horizontal sweep of the receiver display 18. The timing signals are distributed to the various elements of the receiver by means of timing bus 17.

Converter 14 is coupled to receive the $4 f_{sc}$ clock signal provided by timing unit 16 and samples the video signal S1 at that rate. The sampled signal is digitized in converter 14 to provide a parallel digital video output signal S2 of 8-bit resolution. To simplify the drawing, each digital data bus (8 bits) or address bus (10 bits) is drawn as a single line and each data bus multiplex switch is shown in simplified form (i.e., an eight-pole bus switch is represented by a one-pole switch).

The number of lines of the digitized video signal (S2) provided by A/D converter 14 is doubled for application to display 18 by means of a pair of progressive scan processors (PSP) 20 and 22 (outlined in phantom) each comprising a respective random access memory (RAM) 24, 26 coupled to a respective address generator 28, 30 for receiving read and write addresses therefrom. Alternate lines of the digitized video signal S2 are applied to respective ones of memories 24 and 26 by means of a switch 32 that is controlled by a half line-rate ($FH/2$) read/write (R/W) timing signal provided by timing unit 16. For purposes of discussion it will be assumed that switch 32 is in the position shown (upward) for even lines of the video signal S1 for storing (writing) signal S2 in RAM 24 and that switch 32 is in the opposite position during odd lines of signal S1 for writing signal S2 in RAM 26.

The data « ports » or terminals of memories 24 and 26 are bidirectional, that is, during a memory write operation they serve as inputs and during a memory read operation they serve as outputs. The data terminals of memories 24 and 26 are coupled to a digital-to-analog (D/A) converter 36 via a further switch 34. During even lines of signal S1, switch 34 (in the position shown) couples the output of RAM 26 to converter 36 and during odd lines it couples the output of RAM 24 to converter 36. Converter 36 receives $8 f_{sc}$ clock signals from timing unit 16 (via bus 17) and provides a preprocessed video output signal S3 for display on unit 18. Display unit 18 is supplied with normal field-rate (FV) and doubled line-rate (2FH) signals from unit 16 for providing a progressively scanned image of the double line-rate signal S3. Unit 18 may comprise a conventional kinescope or a projection unit and associated drive circuitry.

With the exception of the RAM address processing, as will be described, overall operation of the progressively scanned receiver is conventional. Briefly, the digitized video signal S2 is alternately stored in the memories 24 and 26. As one line is being written into memory 24, the previously stored line in memory 26 is read twice, converted back to analog form in converter 36 and then displayed on display 16 (e.g., a kinescope or projection display) which has a doubled horizontal sweep rate (2 FH) thereby displaying two lines of video for each line received.

The second line of each line pair may be interpolated as is known in the art or it may be an exact replica of the first line. An example of a progressively scanned receiver, wherein the added video lines are replicas of the original scan lines, is described in U.S. Pat. 4,415,931 entitled television display with doubled horizontal lines which issued November 15, 1983 to R.A. Dischert. A doubly scanned receiver in which the additional scan lines are obtained by interpolation from the original scan lines is described by K.H. Powers in U.S. Pat. 4,400,719 entitled television display system with reduced line-scan artifacts which issued August 23, 1983.

Of importance to the present invention is the determination of the exact starting point for each displayed line and this is controlled in accordance with the invention by means of the address generators 28 and 30 in progressive scan processors 20 and 22, respectively. Address generators 28 and 30 each include circuits for storing the highest address written into respective ones of memories 24 and 26 during a memory write operation and for controlling (limiting) the highest address read from the memory during at least one subsequent read operation in accordance with the stored address. This feature of the invention may be realized by resetting an address counter in the address generator whenever the current address during a memory read operation equals the highest address of the previous memory write operation. By

this means, it is assured that the memory read operation « tracks », in a manner of speaking, variations in the number of pixels stored during the immediately preceding memory write operation. Since the counter modulo (its counting range) continuously adapts to the number of pixels per line of the incoming video signal, the pixels displayed on unit 18 will have uniform horizontal spacing and vertical alignment regardless of whether or not the incoming video signal conforms to a specific broadcast standard ratio of color subcarrier frequency and horizontal line rate (f_{sc}/FH).

Figure 2 and the associated waveform diagram of figure 3 provides a more detailed illustration of the variable modulo addressing feature of the invention. The address generator of figure 2 is exemplary of generators 28 or 30 in figure 1. The read/write control signal should be inverted for one of the generators (as shown in processor 22 in figure 1) since in the overall system the RAM's are written and read from alternately (i.e., one RAM is written while the other is being read).

Generator 28 (or 30) comprises a 10 bit address counter 202 having an output coupled via an address bus 204 to the address input of RAM 24 (figure 1). Address bus 204 is also coupled to an address latch 206 and to one input of an address comparator 208 the other input of which is coupled to the output of latch 206. Clock signals for counter 202 are applied to its clock input (CL) by means of a half-line rate ($FH/2$) controlled switch 210 which couples the $4 f_{sc}$ and $8 f_{sc}$ clock signals provided by timing unit 16 to terminal CL during alternate line intervals. More specifically, the control for switch 210 comprises the system read/write signal R/W. When signal R/W is high, RAM 24 is placed in a write mode and switch 210 supplies $4 f_{sc}$ clock signals to address counter 202. Conversely, when signal R/W is low, RAM 24 is placed in a read mode and switch 210 supplies $8 f_{sc}$ clock signal to counter 202.

Address counter 202 has a reset input (R) which is coupled via an OR gate 212 to the output of address comparator 208 and to the output of a transition detector 214. The input of detector 214 is coupled to receive the R/W control signal supplied to switch 210. Detector 214 supplies a reset pulse to counter 202 via OR gate 212 upon each transition of signal R/W. Since signal R/W is a half line-rate square wave derived from the horizontal synchronizing component (HS) of signal S1, counter 202 is reset at the beginning of each line of the video input signal S1.

It is the function of latch 206 and comparator 208 to provide an end-of-line indicator signal to reset address counter 202 during a read operation whenever the current address for RAM 24 equals the highest address previously stored during the immediately preceding memory write operation. There are thus two means for resetting the counter 202 to its starting address (e.g., zero). Detector 214 resets

counter 202 at the start of every line of the video input signal S1. Comparator 208 resets counter 202 at the end of the first read operation of RAM 24 when the highest stored address is read to thereby initiate the start of the second read operation. Finally, during the second read operation, counter 202 is reset upon the occurrence of either the count reaching the stored value or upon the occurrence of a transition of the R/W signal which marks the beginning of the next write operation. To facilitate this operation, the timing of comparator 208 and latch 206 is controlled by the R/W signal which is inverted by an inverter 216 and applied to the clock input, CL, of latch 206 and to the enable input, ENA, of comparator 208. Latch 206 is responsive to negative transitions at its clock input and comparator 208 is enabled by a low level signal (logic zero) at its enable input. Accordingly, at the end of a write operation the negative transition of the inverted R/W signal causes latch 206 to store the highest address generated by counter 202 and enables comparator 208 which compares the present and previous addresses to reset counter 202 when the addresses are equal. This determines the end of the first read cycle and the beginning of the second read cycle.

Figure 3 provides a specific example of operation of generator 28 (or 30) for the assumed conditions that sampling is provided at a $4 f_{sc}$ rate and that the video signal S1 is « non-standard » in that the ratio F_{sc}/FH is such that there are 904 samples per line rather than 910 as would be the case for an NTSC standard signal. Waveforms A and B illustrate the $8 f_{sc}$ and $4 f_{sc}$ read and write clock waveforms, respectively. Waveform C is the read/write signal which is a symmetrical square wave of half the line rate of the video input signal S1. When this waveform is low, processor 20 is writing signal S2 in RAM 24 at the $4 f_{sc}$ rate and processor 22 is reading data from RAM 26 at the $8 f_{sc}$ rate for display on unit 18.

Assuming that the starting address is zero, the address of the last sample (No. 904) written during the memory write operation will be address 903. Waveform D represents the address data supplied to RAM 24 by generator 28. When the write-to-read transition of waveform C occurs the output of counter 202 will be address 903 for the assumed condition. This address (of the 904th pixel) is stored in latch 206 as indicated by waveform F. During the read operation the output of comparator 208 will go high, as shown by waveform E, when the current address (waveform D) equals the previously stored address (waveform F) thereby resetting counter 202 to zero. This starts the beginning of the second read operation exactly at the end of the last pixel stored during the write operation thereby ensuring that the second line displayed during a memory cycle is exactly aligned with the first line of the memory cycle. Since the starting point of the displayed video signal adapts on a line-by-line basis to changes in the number of pixels per-line, the pro-

gressive scan display system may be used with standard or non-standard signals without appearance of the undesirable visual artifacts previously described.

Claims

1. A progressive scan video processor of the type having addressable memory means (24) for storing a video input signal (52) supplied thereto during a first line interval thereof and for recovering the stored signal N-times during a subsequent line interval to provide a processed video output signal having a line rate N-times that of said video input signal, said memory means being coupled to address generator means (28) for receiving read and write addresses therefrom, characterized in that:

said address generator means (28) includes means (206, 208, 212) for storing (208) the last memory address written into during a memory write operation and for controlling (208, 212) in accordance with the stored address the end of one memory read operation and the start of the next memory read operation, whereby the counting range of said address generator means continuously adapts to the number of pixels per line of the incoming video signal.

2. A video processor as recited in Claim 1 characterized in that said controlling means (208, 212) includes means for initializing said address generator means (reset counter 202) to a given starting address in response to a horizontal synchronizing component of said video input signal.

3. A video processor as recited in Claim 1 characterized in that said storing and controlling means comprises:

- (a) latch means (206) coupled to receive (204) and store said last address written in said memory means during said memory write operation;
- (b) comparator means (208) coupled to input and output connections of said latch means for providing an end-of-line indicator signal; and
- (c) coupling means (212) for applying said end-of-line signal as an initializing signal (at R) which sets said address generator means to a given starting address in response to said end-of-line indicator signal.

4. Video processor as recited in claim 1 wherein said address generator means comprises address counter means (202) having a reset input (R) responsive to a reset signal supplied thereto for placing said counter means in a predetermined initial state corresponding to a given starting address of said memory means; characterized in that said circuit means comprises latch means (206) coupled to said counter means (202) for storing said last address written in said memory means (24) during said memory write operation and comparator means (208) coupled to input and output connections of said latch means for

counter 202 at the start of every line of the video input signal S1. Comparator 208 resets counter 202 at the end of the first read operation of RAM 24 when the highest stored address is read to thereby initiate the start of the second read operation. Finally, during the second read operation, counter 202 is reset upon the occurrence of either the count reaching the stored value or upon the occurrence of a transition of the R/W signal which marks the beginning of the next write operation. To facilitate this operation, the timing of comparator 208 and latch 206 is controlled by the R/W signal which is inverted by an inverter 216 and applied to the clock input, CL, of latch 206 and to the enable input, ENA, of comparator 208. Latch 206 is responsive to negative transitions at its clock input and comparator 208 is enabled by a low level signal (logic zero) at its enable input. Accordingly, at the end of a write operation the negative transition of the inverted R/W signal causes latch 206 to store the highest address generated by counter 202 and enables comparator 208 which compares the present and previous addresses to reset counter 202 when the addresses are equal. This determines the end of the first read cycle and the beginning of the second read cycle.

Figure 3 provides a specific example of operation of generator 28 (or 30) for the assumed conditions that sampling is provided at a $4 f_{sc}$ rate and that the video signal S1 is « non-standard » in that the ratio F_{sc}/FH is such that there are 904 samples per line rather than 910 as would be the case for an NTSC standard signal. Waveforms A and B illustrate the $8 f_{sc}$ and $4 f_{sc}$ read and write clock waveforms, respectively. Waveform C is the read/write signal which is a symmetrical square wave of half the line rate of the video input signal S1. When this waveform is low, processor 20 is writing signal S2 in RAM 24 at the $4 f_{sc}$ rate and processor 22 is reading data from RAM 26 at the $8 f_{sc}$ rate for display or unit 18.

Assuming that the starting address is zero, the address of the last sample (No. 904) written during the memory write operation will be address 903. Waveform D represents the address data supplied to RAM 24 by generator 28. When the write-to-read transition of waveform C occurs the output of counter 202 will be address 903 for the assumed condition. This address (of the 904th pixel) is stored in latch 206 as indicated by waveform F. During the read operation the output of comparator 208 will go high, as shown by waveform E, when the current address (waveform D) equals the previously stored address (waveform F) thereby resetting counter 202 to zero. This starts the beginning of the second read operation exactly at the end of the last pixel stored during the write operation thereby ensuring that the second line displayed during a memory cycle is exactly aligned with the first line of the memory cycle. Since the starting point of the displayed video signal adapts on a line-by-line basis to changes in the number of pixels per-line, the pro-

gressive scan display system may be used with standard or non-standard signals without appearance of the undesirable visual artifacts previously described.

Claims

1. A progressive scan video processor of the type having addressable memory means (24) for storing a video input signal (52) supplied thereto during a first line interval thereof and for recovering the stored signal N-times during a subsequent line interval to provide a processed video output signal having a line rate N-times that of said video input signal, said memory means being coupled to address generator means (28) for receiving read and write addresses therefrom, characterized in that:

said address generator means (28) includes means (206,208,212) for storing (208) the last memory address written into during a memory write operation and for controlling (208,212) in accordance with the stored address the end of one memory read operation and the start of the next memory read operation, whereby the counting range of said address generator means continuously adapts to the number of pixels per line of the incoming video signal.

2. A video processor as recited in Claim 1 characterized in that said controlling means (208, 212) includes means for initializing said address generator means (reset counter 202) to a given starting address in response to a horizontal synchronizing component of said video input signal.

3. A video processor as recited in Claim 1 characterized in that said storing and controlling means comprises:

- (a) latch means (206) coupled to receive (204) and store said last address written in said memory means during said memory write operation;
- (b) comparator means (208) coupled to input and output connections of said latch means for providing an end-of-line indicator signal; and
- (c) coupling means (212) for applying said end-of-line signal as an initializing signal (at R) which sets said address generator means to a given starting address in response to said end-of-line indicator signal.

4. Video processor as recited in claim 1 wherein said address generator means comprises address counter means (202) having a reset input (R) responsive to a reset signal supplied thereto for placing said counter means in a predetermined initial state corresponding to a given starting address of said memory means; characterized in that said circuit means comprises latch means (206) coupled to said counter means (202) for storing said last address written in said memory means (24) during said memory write operation and comparator means (208) coupled to input and output connections of said latch means for





detecting the starting time of said at least one subsequent memory read operation and supplying said reset signal to said address counter means (202) to initiate the start of said at least one subsequent memory read operation.

Patentansprüche

1. Folgeabtastung-Videoprozessor mit einer adressierbaren Speichereinrichtung (24) zum Speichern eines Videoeingangssignals (52), das ihr während eines ersten Zeilenintervalls zugeführt wird, und zum N-maligen Wiedergewinnen des gespeicherten Signals während eines folgenden Zeilenintervalls, um ein verarbeitetes Videoausgangssignal mit einer Zeilenfrequenz gleich dem N-fachen der des Videoeingangssignals zu liefern, wobei die Speichereinrichtung mit einer Adressengeneratoreinrichtung (28) gekoppelt ist, um von dieser Lese- und Schreibadressen zu erhalten, dadurch gekennzeichnet, daß die Adressengeneratoreinrichtung (28) eine Anordnung (206, 208, 212) zum Speichern (208) der letzten Adresse, die während einer Speicherschreiboperation eingeschrieben wurde, und zum Steuern (208, 212), entsprechend der gespeicherten Adresse, des Endes einer Speicherleseoperation und des Beginns der nächsten Speicherleseoperation, wobei sich der Zählbereich der Adressengeneratoreinrichtung kontinuierlich an die Anzahl der Pixel pro Zeile des ankommenden Videosignals anpaßt.

2. Videoprozessor nach Anspruch 1, dadurch gekennzeichnet, daß die Steueranordnung (208, 212) eine Einrichtung (Rücksetz-zähler 202) zum Initialisieren der Adressengeneratoreinrichtung auf eine vorgegebene Anfangsadresse in Ansprache auf eine Horizontalsynchronisierungskomponente des Video-Eingangssignals enthält.

3. Videoprozessor nach Anspruch 1, dadurch gekennzeichnet, daß die Speicher- und Steueranordnung enthält:

- a) eine Registeranordnung (202), die für den Empfang (204) und die Speicherung der letzten, während der genannten Speicherschreiboperation in die Speichereinrichtung geschriebenen Adresse geschaltet ist;
- b) eine Vergleichieranordnung (208), die mit Eingangs- und Ausgangsanschlüssen der Registeranordnung gekoppelt ist, um ein Zeilenende-Anzeigesignal zu liefern; und
- c) eine Kopplungsanordnung (212) zum Anlegen des Zeilenendesignals als Initialisierungssignal (an R), das die Adressengeneratoreinrichtung in Ansprache auf das Zeilenende-Anzeigesignal auf eine vorgegebene Anfangsadresse einstellt.

4. Videoprozessor nach Anspruch 1, bei welchem die Adressengeneratoreinrichtung eine Adressenzähleranordnung (202) mit einem Rücksetzeingang

(R) enthält, der auf ein ihm zugeführtes Rücksetzsignal anspricht, um die Zähleranordnung auf einen vorgegebenen Anfangszustand entsprechend einer vorgegebenen Anfangsadresse der Speichereinrichtung einzustellen, dadurch gekennzeichnet, daß die Schaltungsanordnung eine mit der Zähleranordnung (202) gekoppelte Registeranordnung (206) zum Speichern der letzten, während der erwähnten Speicherschreiboperation in die Speichereinrichtung (24) geschriebenen Adresse und eine mit den Eingangs- und Ausgangsanschlüssen der Registeranordnung gekoppelte Vergleichieranordnung (208) zum Feststellen der Anfangszeit der mindestens einen nachfolgenden Speicherleseoperation und zum Liefern des Rücksetzsignals an die Adressenzähleranordnung (202), um den Beginn der mindestens einen nachfolgenden Speicherleseoperation einzuleiten, enthält.

Revendications

1. Processeur vidéo à balayage progressif du type comprenant une mémoire adressable (24) pour mémoriser un signal (52) d'entrée vidéo fourni à la mémoire au cours d'un premier intervalle de lignes et pour récupérer le signal mémorisé N-fois au cours d'un intervalle de lignes consécutif pour fournir un signal de sortie vidéo traité ayant une fréquence de ligne N-fois celle dudit signal d'entrée vidéo, ladite mémoire étant couplée à un générateur d'adresses (28) pour recevoir de celui-ci les adresses de lecture et d'écriture, caractérisé en ce que ledit générateur d'adresses (28) comprend des moyens (206, 208, 212) pour stocker (208) la dernière adresse écrite dans, au cours d'une opération d'écriture en mémoire et pour contrôler (208, 212), selon l'adresse stockée, la fin d'une opération de lecture en mémoire et le début de l'opération suivante de lecture en mémoire, la plage de comptage dudit générateur d'adresses s'adaptant continuellement au nombre d'éléments d'image par ligne du signal vidéo reçu.

2. Processeur vidéo selon la revendication 1, caractérisé en ce que ledit moyen de contrôle (208, 212) comprend un moyen pour initialiser ledit générateur d'adresses (compteur de remise à zéro 202) à une adresse de démarrage donnée en réponse à un composant de synchronisation horizontale dudit signal d'entrée vidéo.

3. Processeur vidéo selon la revendication 1, caractérisé en ce que ledit moyen de stockage et de contrôle comprend :

- (a) un moyen de verrouillage (206) couplé pour recevoir (204) et stocker ladite dernière adresse écrite dans ladite mémoire au cours de ladite opération d'écriture en mémoire ;
- (b) un comparateur (208) couplé à des branchements d'entrée et de sortie dudit moyen de verrouillage pour fournir un signal indicateur de

fin de ligne ; et

(c) un moyen de couplage (212) pour appliquer ledit signal de fin de ligne sous forme d'un signal d'initialisation (à R) qui règle ledit générateur d'adresses à une adresse de démarrage donnée en réponse audit signal indicateur de fin de ligne. 5

4. Processeur vidéo selon la revendication 1 dans lequel ledit générateur d'adresses comprend un compteur d'adresses (202) ayant une entrée de remise à zéro (R) susceptible de réagir à un signal de remise à zéro qui lui est fourni pour placer ledit compteur dans un état initial prédéterminé correspondant à une adresse de démarrage donnée de ladite mémoire, caractérisé en ce que ledit circuit comprend un moyen de verrouillage (206) couplé audit compteur (202) pour stocker ladite dernière adresse écrite dans ladite mémoire (24) au cours de ladite opération d'écriture en mémoire et un comparateur (208) couplé à des branchements d'entrée et de sortie dudit moyen de verrouillage pour détecter l'instant de démarrage d'au moins une opération consécutive de lecture en mémoire et pour fournir ledit signal de remise à zéro audit compteur d'adresses (202) pour provoquer le démarrage d'au moins ladite opération consécutive de lecture en mémoire. 10 15 20 25

30

35

40

45

50

55

7

