

Description

This invention relates to a deflection circuit in which a supply current is coupled to a trace capacitor of the deflection circuit through a plurality of current paths.

Typically, a horizontal deflection circuit such as provided in association with a CRT display device comprises an output stage that includes a horizontal deflection winding and a trace capacitance that supplies deflection current to the deflection winding during each trace interval. A retrace capacitance is coupled across the deflection winding during the retrace interval to form a retrace resonant circuit. Energy is replenished during retrace via a flyback transformer.

High beam current in a secondary winding of the flyback transformer, that occurs in the course of displaying, for example, each white horizontal strip of a crosshatch pattern represents a heavy load to the flyback transformer during retrace. Consequently, the retrace capacitance may be slightly discharged during retrace due to the aforementioned loading. This may result in a discharge current from the trace capacitance into the retrace capacitance through the deflection winding and a slight drop of the voltage across the trace capacitance during the white horizontal strips of the crosshatch pattern. The charge of the trace capacitance is replenished during the retrace intervals associated with the scan lines that display the black picture portion underneath the white crosshatch stripes. This causes a small current in the opposite direction through the deflection winding. The charge and discharge current of the trace capacitance produces a small raster displacement and results in low frequency oscillations modulating the deflection winding trace current. This low frequency modulation may cause each vertical strip of the crosshatch pattern to appear as being of a zig-zag shape, instead of a straight line shape. The zig-zag shape appears in a given vertical strip immediately below the intersection point with a horizontal strip. Such distortions are sometimes referred to by the name "mouseeteeth" distortions. They appear, during and just after the times in which high beam transients occur, because the deflection circuit that represents a low impedance energy flywheel, supplies the transient increase in energy requirement of the ultor circuits. Thus, energy transferred from the deflection circuit to the ultor circuits may tend to cause variations in the deflection winding trace current.

"Mouseeteeth" distortions may be reduced using an arrangement such as described in UK Published application 2150796A, published 3 July 1985, corresponding to U.S. Patent No. 4,634,937, entitled EAST-WEST CORRECTION CIRCUIT, is-

sued to P.E. Haferl on 6 January 1987, that is referred to herein as the Haferl patent, by supplying an E-W modulation current generated by an east-west control circuit via a choke having a high impedance. This choke integrates the horizontal frequency components resulting in a sink current that is substantially a D.C. current that flows from the deflection circuit to the E-W control circuit. Deflection disturbances referred to as "mouseeteeth" are avoided because of the loose coupling between the flyback transformer and the deflection winding during the retrace interval. The loose coupling is provided by the choke that provides high frequency isolation of the deflection circuit output stage from the E-W control circuit.

Color television picture tubes with a large faceplate radius R, such as, for example, Philips 45AX picture tube, may require a significantly high amount of inside pincushion correction.

In consideration of the above, the present invention provides a deflection apparatus, comprising a deflection winding having deflection rate scanning current flowing therein during a trace interval and during a retrace interval of a deflection cycle, said deflection winding being included in a retrace resonant circuit during said retrace interval; switching means coupled to said deflection winding and responsive to said input signal for generating, during said retrace interval a retrace voltage; a trace capacitance series coupled to said deflection winding to form with said deflection winding a first trace resonant circuit during said trace interval such that said scanning current in said trace capacitance develops a parabolic voltage therein during said trace interval; a source of supply voltage developed at a supply terminal; a supply inductance coupled between said source of said supply voltage and said first trace resonant circuit for supplying via said supply inductance a first portion of a DC supply current that replenishes a first portion of energy losses in said retrace resonant circuit; characterized by means, coupled to said supply terminal and to said trace capacitance for supplying a second portion of said DC supply current to said trace capacitance in a current path that bypasses said supply inductance for replenishing a second portion of said energy losses, such that said second portion of said DC supply current is applied without significantly AC-loading said first trace resonant circuit.

In accordance with an aspect of the invention, a deflection apparatus includes a deflection winding for generating scanning current at a deflection rate. A trace capacitance is coupled to the deflection winding. A supply inductance is coupled to the trace capacitance to provide a first current path for conducting a first portion of a supply current. A circuit branch, including a second capacitance and

a second inductance, that is coupled to the trace capacitance forms with the trace capacitance a second resonant circuit for generating in the second inductance a second current. The second current is coupled to the trace capacitance to vary a parabolic voltage in the trace capacitance in accordance with the amplitude of the second current in a manner to reduce, for example, inside pincushion distortion. A voltage in the second capacitance is combined at a terminal of the second inductance with the parabolic voltage in the trace capacitance to reduce an alternating current voltage at the terminal. A second portion of the supply current is coupled to the trace capacitance through the terminal to reduce a discharge current from the trace capacitor during retrace. Thus, for example, mouse-teeth distortions are also reduced.

In a deflection apparatus embodying another aspect of the invention, a scanning current is generated in a deflection winding at a deflection rate during trace and retrace intervals of a deflection cycle. The deflection winding is included in a retrace resonant circuit during the retrace interval. Switching means that is coupled to the deflection winding, responsive to an input signal at a first frequency that is related to the deflection rate, generates, during the retrace interval, a retrace voltage. A trace capacitance coupled to the deflection winding forms with the deflection winding a first trace resonant circuit during the trace interval such that the scanning current in the trace capacitance develops a parabolic voltage in the trace capacitance during the trace interval. A supply voltage is developed at a supply terminal. A supply inductance is coupled between the supply voltage and the trace capacitance for supplying via the supply inductance a first portion of a DC supply current that replenishes a first portion of energy losses in the retrace resonant circuit. A second portion of the DC supply current is coupled to the trace capacitance in a current path that bypasses the supply inductance for replenishing a second portion of the energy losses.

In the Drawing:

FIGURE 1 illustrates a deflection circuit that includes an inside pincushion correction arrangement, embodying an aspect of the invention;

FIGURES 2a-2f illustrate waveforms useful in explaining the circuit of FIGURE 1;

FIGURES 3a-3e illustrate additional waveforms useful in explaining the circuit of FIGURE 1; and
FIGURE 4 illustrates a crosshatch pattern in which "mouse-teeth" distortion is uncorrected.

A deflection circuit 100 of FIGURE 1, embodying an aspect of the invention, may provide horizontal deflection of the electron beams in, for example, a Philips 110° 45AX FS color picture tube

type A66-EAK00X01. In FIGURE 1, a source of regulated direct current voltage B+, developed between a terminal 22 and ground, is coupled through a small-valued resistor R1 to a terminal 22a of a primary winding W1 of a horizontal flyback transformer T1. The other terminal of winding W1 is coupled to a junction terminal 23. A filtering capacitance C1 is coupled from terminal 22a to ground. Regulated voltage B+ is generated, for example, by a switched mode power supply 90. A secondary winding W3 of transformer T1, supplies an ultor voltage U through a rectifying diode D40.

A horizontal output transistor Q1, operating at a deflection rate f_H and having its base coupled to a conventional driver and oscillator circuit 50, has its collector-to-emitter path coupled between junction terminal 23 and ground. Circuit 50 is synchronized by a sync signal H_s and by a retrace pulse representative signal H_r , in a well known manner. Paralleling transistor Q1 is the series arrangement of two rectifiers, diodes D1 and D2 operating as a damper diode arrangement. Coupled in parallel with the anode and cathode electrodes of diode D1 is an arrangement of a horizontal deflection winding L_H that is coupled to an S-shaping, or trace, capacitance C_s . A deflection retrace capacitance C_{RD} , coupled also across the anode and cathode electrodes of diode D1, forms with deflection winding L_H , a parallel retrace resonant circuit 27. A second retrace capacitance C_{RT} is coupled between a junction terminal 28 and ground. A small-valued capacitance C_P is coupled between terminal 23 and ground. Capacitance C_P provides fine tuning of the resonance frequency of retrace resonance circuit 27. Coupled between terminal 28 and ground is a series arrangement of a diode D3 and a controllable East-West current source 25 that includes a current sink transistor Q4 having, at the collector electrode, a high output impedance during retrace. The collector electrode of transistor Q4 is coupled via a diode D3 to terminal 28 to provide a modulated sink current i_s that varies in a vertical rate parabolic manner. Diode D3 decouples the collector of transistor Q4 from ground, toward the end of trace, when diode D2 conducts, to prevent the flow of saturation collector current in transistor Q4, prior to retrace.

An inside pincushion distortion correction circuit 60, embodying an aspect of the invention, includes an inductance L1 that is coupled to a terminal 60a at the junction of capacitance C_s and inductor L_H . A capacitor C_6 of circuit 60 is coupled between a terminal 60b of inductance L1 and ground.

During the first half of trace, deflection current i_1 flows, in a direction opposing the arrow, in deflection winding L_H and in diode D1. During the second half of trace, deflection current i_1 flows in

deflection winding L_H , in the direction of the arrow, and in diode D_2 and transistor $Q1$ that is conductive. At the end of trace, transistor $Q1$ becomes nonconductive and a retrace voltage V_1 is developed between terminal 23 and ground.

During the retrace interval, charge is taken away from retrace capacitance C_{RT} by East-West modulated sink current i_3 that flows via diode D_3 . The higher the integral $\int i_3 dt$, over the entire retrace interval, for example, the larger becomes a retrace voltage V_{41} across capacitance C_{RD} and the smaller becomes a modulated voltage V_3 across capacitance C_{RT} . The peak of deflection current i_1 through deflection winding L_H , during the trace interval, is directly related to the peak of retrace voltage V_{41} across capacitance C_{RD} at the center of the retrace interval. By modulating current i_3 of transistor $Q4$ at a vertical rate, current source 25 provides outside pincushion correction to horizontal scanning current i_1 .

The high output impedance of transistor $Q4$ that is interposed between winding $W1$ and retrace resonant circuit 27 prevents, during horizontal retrace, an undesirable high frequency coupling through current source 25 between winding $W1$ of flyback transformer $T1$ and retrace resonant circuit 27 that, otherwise, could have caused "mouseteeth" distortion.

"Mouseteeth" distortion can also be reduced by supplying East-West modulated current, instead of through the high output impedance of the transistor, via a choke having a high impedance. The choke, however, disadvantageously, may be expensive. An example of such arrangement is described in the Haefel patent that was mentioned before.

Capacitor C_{RT} is coupled to winding $W1$ via ground and capacitor C_1 to form a second retrace resonant circuit that is coupled to retrace resonant circuit 27 so as to form a combined retrace resonant circuit that includes winding $W1$, capacitor C_{RT} and retrace resonant circuit 27. The combined retrace resonant circuit is tuned to, for example, the retrace frequency. In order to tune the combined resonant circuit to the retrace frequency, each of retrace resonant circuit 27 and the second retrace resonant circuit that includes winding $W1$ and capacitor C_{RT} is tuned to a frequency that may be lower than the retrace frequency.

Capacitor C_{RT} causes the retrace voltage across winding $W1$ and that across deflection winding L_H to occur simultaneously. Therefore, retrace voltage H_r across winding $W4$ that provides synchronization information to Driver and oscillator 50, advantageously, contains the same synchronization information as of the retrace voltage across deflection winding L_H or as of voltage V_{41} across capacitor C_{RD} . The purpose of capacitor C_{RT} is described in detail in the Haefel patent.

The values of the capacitors C_p , C_{RD} and C_{RT} are selected to obtain the correct retrace time and to avoid retrace time modulation of voltage V_1 . Capacitor C_{RT} determines the lowest deflection current amplitude that corresponds with current i_3 that is zero.

Except for a very short interval that occurs immediately at the beginning of retrace when transistor $Q4$ is still in saturation, transistor $Q4$ of E-W control circuit 25 of FIGURE 1 operates, during the rest of horizontal retrace interval, as a Class A sink current amplifier. Sink current i_3 in transistor $Q4$ develops a proportional feedback voltage V_{R4} across a resistor R_4 that is coupled between the emitter of transistor $Q4$ and ground. Voltage V_{R4} is fed back to the base of a transistor Q_3 via a resistor R_5 . The collector of transistor Q_3 is coupled to the base of transistor $Q4$ at a terminal 25a. The amplitude of sink current i_3 , during retrace, is kept independent from variations of the shape and amplitude of voltage V_3 , for example, by the negative feedback arrangement of resistors R_4 and R_5 ; therefore, high output impedance at the retrace frequency and above is established at the collector of transistor $Q4$. The average amplitude of sink current i_3 is adjusted by a width control resistor R_{11} , which determines, the emitter voltage of transistor Q_3 , in accordance with a vertical parabola voltage V_{10} , that is described below. Thus, the average value of current i_3 is modulated at a vertical rate in a parabolic manner in accordance with voltage V_{10} .

FIGURES 2a-2f and 3a-3e, illustrate waveforms useful in explaining the operation of the arrangement of FIGURE 1. Similar numbers and symbols in FIGURES 1, 2a-2f and 3a-3e indicate similar items or functions.

Parabola voltage V_{10} of FIGURE 1 is generated across a capacitor C_6 of, for example, a conventional vertical deflection circuit 300. Parabola voltage V_{10} of FIGURE 3d is AC coupled to the emitter of transistor Q_3 of FIGURE 1 via a DC blocking capacitor C_4 , a resistor R_{14} and an adjustable E-W control resistor R_{12} .

Retrace voltage V_3 is coupled via a diode D_3 , a time-integrating network, or lowpass filter that includes a resistor R_2 and a capacitor C_2 that filters out frequencies above the vertical frequency. The lowpass filtered voltage is coupled, via a resistor R_3 , to the emitter of transistor Q_3 . The low frequency negative feedback voltage that develops across capacitor C_2 causes the average value of voltage V_3 to vary in a vertical rate parabolic manner in accordance with vertical parabola voltage V_{10} . Because of the negative feedback, the peak, for example, of the vertical rate envelope of voltage V_3 is inversely related to the vertical parabola voltage applied across emitter-base junction of transis-

tor Q_3 that is obtained from voltage V_{10} . Such low frequency feedback arrangement of resistors R_2 and R_3 provides DC stabilization and improves linearity.

Also applied to the base of transistor Q_3 is an adjustable portion of a vertical sawtooth voltage V_{11} , that provides trapeze correction, shown in FIGURE 3e, that is obtained across a resistor R_5 of FIGURE 1. Resistor R_5 is coupled in series with a vertical deflection winding L_v and capacitor C_6 of circuit 300.

Correction of inside pincushion distortion is accomplished by the "S"-shaping of deflection current i_1 , in accordance with an inside pincushion correction modulation current i_2 that flows in capacitance C_6 an in inductor L_1 of inside pincushion distortion correction circuit 60. Current i_2 , that flows in a current path that includes trace capacitance C_2 , varies a voltage V_{cs} across trace capacitance C_s , during trace, at a frequency that is higher than the trace resonance frequency of the trace resonant circuit that includes deflection winding L_H and trace capacitance C_s . The amplitude of current i_2 is modulated by voltage V_3 of FIGURE 2f at terminal 28 of FIGURE 1 to provide inside pincushion correction. The higher is the amplitude of current i_2 , the higher is the peak-to-peak amplitude of trace voltage V_{cs} that is produced and the more significant is the amount of "S"-shaping of deflection current i_1 that is provided, and vice versa. Operation of circuit 60 is described in more detail in European Published Patent Application No. 0236064 entitled PINCUSHION CORRECTION IN DEFLECTION CIRCUIT, in the name of RCA Corporation, published 9 September 1987.

Capacitance C_6 and inductor L_1 of circuit 60 form, with trace capacitance C_s and deflection winding L_H , a resonance circuit portion of correction circuit 60 during trace. The resonance circuit portion of circuit 60 is tuned by inductor L_1 to a frequency that is lower than frequency f_H so that current i_2 will not reach zero value prior to the end of horizontal trace; yet, it is tuned to a frequency that is substantially higher than the resonance frequency of the trace resonant circuit of deflection winding L_H and trace capacitance C_s . Inside pin modulation inductor L_1 may be of a variable type if an adjustable amount of correction is required. For the circuit values showing in FIGURE 1, inductor L_1 may tune the resonance circuit portion of circuit 60 to a frequency of, for example, 14 KHz.

The portion of voltage V_{cs} that is caused by deflection current i_1 is generally a parabola shaped waveform that, in each horizontal period H , is composed of trace and retrace sinewave portions, respectively. During trace, the corresponding sinewave portion of voltage V_{cs} is at a frequency that is approximately equal to the trace resonance

frequency of winding L_H and capacitor C_s . Such resonance frequency is for example, equal to approximately 7 KHz. During retrace, the corresponding sinewave portion is at approximately 44 KHz.

Inductor L_1 and capacitance C_6 are included in a circuit branch that, during trace, is coupled in parallel with trace capacitance C_s . During the first half of trace, resonance current i_2 flows, in a direction opposite to the arrow, from ground, through capacitance C_6 , inductor L_1 , capacitance C_s , diode D_1 , deflection transistor Q_1 that is conductive and back to ground. During the second half of trace, current i_2 circulates in the direction of the arrow, from ground, through diode, D_2 , capacitance C_s , inductor L_1 and capacitance C_6 and back to ground.

Deflection current i_1 flows, during retrace, in a current path that includes retrace capacitor C_{RD} , deflection winding L_H and trace capacitor C_s . Trace capacitor C_s , that provides low impedance during retrace, prevent current i_1 from flowing, throughout retrace, in the branch of circuit 60 that includes capacitance C_6 and inductor L_1 . Because inductor L_1 is bypassed by capacitor C_s , the deflection inductance during retrace and retrace voltage V_1 are, advantageously, not substantially affected by inductor L_1 . Therefore, circuit 100 of FIGURE 1 may, advantageously, require a relatively low level of voltage $B+$ when operating at higher deflection frequencies such as, for example, $2xf_H$.

During horizontal trace, voltage V_3 of FIGURE 1 is maintained zero as shown in FIGURE 2f. At the center of vertical trace, when current i_3 is at a maximum level, horizontal retrace voltage V_3 is at minimum that may be, for example, at zero volts. Consequently, in this case, it is trace voltage V_{cs} across capacitor C_s that mainly generates resonant current i_2 . Current i_2 of FIGURE 2c that flows in capacitor C_s in the same phase as current i_1 of FIGURE 2a and adds in capacitor C_s to current i_1 to provide maximum "S" shaping of voltage V_{cs} when current i_3 is at the maximum. As current i_3 becomes smaller, during vertical trace, horizontal retrace voltage V_3 becomes increasingly larger as shown in the corresponding waveforms in FIGURE 1. The phase of voltage V_3 is shifted by approximately 180° from that of trace voltage V_{cs} , because the positive peak of trace voltage V_{cs} or V_2 of FIGURE 2d occurs at the center of horizontal trace; whereas the peak of modulated voltage V_3 of FIGURES 2f occurs during horizontal retrace. Therefore, voltage V_3 of FIGURE 1, which is added to trace voltage V_{cs} across capacitor C_s to form voltage V_2 , has an opposite effect on current i_2 than that of voltage V_{cs} . When retrace voltage V_3 increases, current i_2 decreases, causing less modulation of trace voltage V_{cs} or V_2 and less "S" shaping. A further increase of retrace voltage V_3

causes the amplitude of current i_2 to be zero. An even further increase of retrace voltage V_3 causes current i_2 to flow in the opposite direction.

Thus, current i_2 of FIGURE 2c, that modulates voltage V_2 of FIGURE 2d, is modulated by voltage V_3 of FIGURE 2f. Since voltage V_3 is modulated by current i_3 of FIGURE 2e, the parabolic waveform of trace voltage V_2 of FIGURE 2d is modulated in the vertical rate by current i_3 of FIGURE 2e to provide inside pincushion distortion correction.

The correction of outside pincushion distortion requires, at the top and bottom of the raster, a lower amplitude of deflection current i_1 of FIGURE 2a than at the center. The correction of inside pincushion distortion requires a lower amount of "S" shaping at the top and bottom than at the center. At the top and bottom, sink current i_3 that is lower, causes a higher amplitude of retrace voltage V_3 . The higher amplitude of voltage V_3 causes a lower amplitude of current i_2 . At the center of the vertical trace, sink current i_3 , that is at a maximum causes the amplitude of retrace voltage V_3 to be at a minimum. Accordingly, at the center of vertical trace, the amplitude of each of deflection current i_1 and inside pincushion correction current i_2 is at a maximum, resulting in more "S" shaping of voltage V_{cs} . Advantageously, by selecting the values of the circuit components of circuit 60, a required amount of inside pincushion correction can be obtained for a given amount of outside pincushion correction.

Circuit 60 is coupled in parallel with capacitor C_{RT} during the retrace interval. Therefore, the value of capacitor C_{RT} has to be larger than if circuit 60 was not used, so as to account for the effect of circuit 60 on the total retrace capacitance that is required. Increasing the value of capacitor C_{RT} has a tendency to increase the coupling between flyback transformer T1 and resonant circuit 27 that may, if not accounted for, disadvantageously, increase "mouseteeth" distortions.

During the first half of trace, current i_2 flows, in a direction that is opposite to that of the arrow, from ground, through capacitor C_5 , inductance L_1 , and capacitor C_8 to junction terminal 28 between diodes D_1 and D_2 . An energy recovery current i_{w1} flowing through winding W1 of flyback transformer T1 in a direction of the arrow, keeps diode D_2 conducting as long as current i_2 is smaller than energy recovery current i_{w1} and provides a ground return for current i_2 . However, diode D_2 may become nonconductive when the increasing amplitude of current i_2 is equal to the decreasing amplitude of energy recovery current i_{w1} in winding W1. Such situation is undesirable because it may cause the trace voltage at terminal 23 of transistor Q1 to rise significantly above ground potential.

Sink current transistor Q4 is switched into saturation at the beginning of the horizontal trace inter-

val. Advantageously, this provides a current path for inside pincushion modulation current i_2 during the first half of the trace interval. Current i_2 causes voltage V_3 , during trace, to increase so as to bias diode D_3 in the forward direction. Because transistor Q4 is saturated, diode D_3 , advantageously, provides a ground return for current i_2 via saturated transistor Q4 and clamps voltage V_3 to approximately zero volts.

Transistor Q4 is switched into saturation by retrace pulse H_r across winding W4 that is applied to the base of transistor Q3 through a capacitor C_5 . A waveform shaping network that includes capacitor C_5 and resistors R_{15} and R_{16} generates from pulse H_r an upramping voltage V_7 , during trace that is shown in the corresponding waveform in FIGURE 1. The negative portion of voltage V_7 is applied to the base of transistor Q3 via a diode D_4 and a resistor R_{17} to form a voltage V_9 that causes transistors Q3 and Q4 to saturate. The waveform, that is included within FIGURE 1, of voltage V_9 shows the base voltage of transistor Q3. At a time t_a in the waveform of voltage V_9 in FIGURE 1, that occurs at the end of retrace, transistors Q3 and Q4 are driven into saturation by negative going voltage V_9 . Both transistors Q3 and Q4 remain in saturation until a time t_b , when diode D_4 is reverse biased by upramping voltage V_7 . During the interval t_b-t_a , transistor Q4 is biased for Class A operation that occurs during horizontal retrace after time t_a' so as to provide high output impedance.

FIGURE 2a illustrates the waveform of retrace voltage V_1 at terminal 23 of FIGURE 1. Retrace voltage V_1 of FIGURE 2a is, advantageously, unaffected by modulation of E-W modulation current i_3 .

In carrying out an aspect of the invention, a resistor R18 is coupled between terminal 22a and an intermediate terminal, or tap 112 of inductor L1. Resistor R18 supplies a DC current i_4 that bypasses deflection winding L_H and winding W1. Current i_4 , that flows through resistor R18 and inductance L_1 , advantageously stabilizes the DC voltage in capacitor C_5 by providing an additional DC current path between supply voltage V_6 and capacitor C_5 .

The average DC voltage of voltage V_2 at junction terminal 60a of winding L_H and capacitance C_8 is equal to voltage V_6 that is at terminal 22a between capacitor C1 and resistor R18. Thus, advantageously, by supplying a portion of the DC current that is required for maintaining average voltage V_{cs} constant through resistor R18, in addition to the portion that is supplied through winding W1, transient discharge of capacitor C_8 due to varying ultor load is, advantageously, reduced; hence, "mouseteeth" distortion is reduced.

The AC portions of voltages V_2 of FIGURE 2d and V_5 of FIGURE 3c at the end terminals of inductor L1 have opposite phases. The location of tap 112 of FIGURE 1 is selected in such a way that, advantageously, causes voltage V_4 at tap 112 of inductor L1 of FIGURE 1, that is approximately equal to the average of voltages V_2 and V_5 , to have a minimal AC component during trace, as shown in FIGURE 3b. Consequently, resistor R18 of FIGURE 1, that is coupled to tap 112 does not significantly load deflection circuit 100 and inside pincushion correction circuit 60, and therefore advantageously does not increase AC losses in circuit 100.

In carrying out another aspect of the invention, current i_4 of FIGURE 3a that flows in resistor R18 of FIGURE 1 is sawtooth shaped because of the ripple voltage component of voltage V_6 . Advantageously, current i_4 may correct some of the asymmetrical horizontal linearity errors. Linearity errors occur because of power losses in winding L_H and in inductor L1 during trace that might have caused a slight decrease in voltage V_4 at tap 112. The decrease in voltage V_4 might have resulted in currents i_1 and i_2 having smaller amplitudes near the end of horizontal trace. To correct at least some of such asymmetrical linearity error, current i_4 , that is sawtooth shaped, advantageously reduces the amount of decrease in voltage V_4 that might have otherwise occurred.

Claims

1. A deflection apparatus, comprising :

a source of an input signal (H_s) at a first frequency that is integrally related to a deflection rate; a deflection winding (L_H) having deflection rate scanning current flowing therein during a trace interval and during a retrace interval of a deflection cycle, said deflection winding being included in a retrace resonant circuit (27) during said retrace interval;

switching means (Q1,D1,D2) coupled to said deflection winding (L_H) and responsive to said input signal for generating, during said retrace interval a retrace voltage;

a trace capacitance (C_s) series coupled to said deflection winding (L_H) to form with said deflection winding a first trace resonant circuit during said trace interval such that said scanning current in said trace capacitance (C_s) develops a parabolic voltage therein during said trace interval;

a source (90) of supply voltage developed at a supply terminal (22a);

a supply inductance (W1) coupled between said source (90) of said supply voltage and said first trace resonant circuit for supplying via said supply inductance (W1) a first

portion of a DC supply current that replenishes a first portion of energy losses in said retrace resonant circuit (27); characterized by

means (R18, L_1), coupled to said supply terminal (22a) and to said trace capacitance (C_s) for supplying a second portion of said DC supply current to said trace capacitance (C_s) in a current path that bypasses said supply inductance (W1) for replenishing a second portion of said energy losses, such that said second portion of said DC supply current is applied without significantly AC-loading said first trace resonant circuit.

2. An apparatus according to claim 1 characterized by a source (W1) of a ripple AC signal (V_6) at a frequency that is related to said first frequency that is coupled to said trace capacitance (C_s) for correcting asymmetrical linearity errors.
3. An apparatus according to Claim 1 characterized by a second resonant circuit (60), including a second capacitance (C_6) and a modulation inductance (L_1) coupled to said first trace resonant circuit (L, C_s) for providing inside pincushion distortion correction, said second resonant circuit including said means (R18, L_1) for supplying a second portion of said DC supply current.
4. An apparatus according to Claim 3 characterized in that said modulation inductance (L_1) has a first terminal (113) that is coupled to said trace capacitance (C_s) and a second terminal (111) that is coupled to said second capacitance (C_6) to form said second resonant circuit that generates in said modulation inductance (L_1) a first modulation current that provides inside pincushion distortion correction and wherein said second portion of said supply current is coupled to said modulation inductance (L_1) at a third terminal (112) intermediate said first (113) and second (111) terminals.
5. An apparatus according to Claim 4 characterized in that said trace capacitance (C_s) acts as a low impedance bypass capacitance for said scanning current around said modulation inductance (L_1) substantially throughout said retrace interval.
6. An apparatus according to Claim 4 characterized in that said third terminal (112) is chosen to be at such a point with respect to said first (113) and second (111) terminals of said modulation inductance as to substantially reduce an AC voltage component at said third terminal.

The AC portions of voltages V_2 of FIGURE 2d and V_5 of FIGURE 3c at the end terminals of inductor L1 have opposite phases. The location of tap 112 of FIGURE 1 is selected in such a way that, advantageously, causes voltage V_4 at tap 112 of inductor L1 of FIGURE 1, that is approximately equal to the average of voltages V_2 and V_5 , to have a minimal AC component during trace, as shown in FIGURE 3b. Consequently, resistor R18 of FIGURE 1, that is coupled to tap 112 does not significantly load deflection circuit 100 and inside pincushion correction circuit 60, and therefore advantageously does not increase AC losses in circuit 100.

In carrying out another aspect of the invention, current i_4 of FIGURE 3a that flows in resistor R18 of FIGURE 1 is sawtooth shaped because of the ripple voltage component of voltage V_6 . Advantageously, current i_4 may correct some of the asymmetrical horizontal linearity errors. Linearity errors occur because of power losses in winding L_H and in inductor L1 during trace that might have caused a slight decrease in voltage V_4 at tap 112. The decrease in voltage V_4 might have resulted in currents i_1 and i_2 having smaller amplitudes near the end of horizontal trace. To correct at least some of such asymmetrical linearity error, current i_4 , that is sawtooth shaped, advantageously reduces the amount of decrease in voltage V_4 that might have otherwise occurred.

Claims

1. A deflection apparatus, comprising :

a source of an input signal (H_s) at a first frequency that is integrally related to a deflection rate; a deflection winding (L_H) having deflection rate scanning current flowing therein during a trace interval and during a retrace interval of a deflection cycle, said deflection winding being included in a retrace resonant circuit (27) during said retrace interval;

switching means (Q1,D1,D2) coupled to said deflection winding (L_H) and responsive to said input signal for generating, during said retrace interval a retrace voltage;

a trace capacitance (C_s) series coupled to said deflection winding (L_H) to form with said deflection winding a first trace resonant circuit during said trace interval such that said scanning current in said trace capacitance (C_s) develops a parabolic voltage therein during said trace interval;

a source (90) of supply voltage developed at a supply terminal (22a);

a supply inductance (W1) coupled between said source (90) of said supply voltage and said first trace resonant circuit for supplying via said supply inductance (W1) a first

portion of a DC supply current that replenishes a first portion of energy losses in said retrace resonant circuit (27); characterized by

means (R18, L_1), coupled to said supply terminal (22a) and to said trace capacitance (C_s) for supplying a second portion of said DC supply current to said trace capacitance (C_s) in a current path that bypasses said supply inductance (W1) for replenishing a second portion of said energy losses, such that said second portion of said DC supply current is applied without significantly AC-loading said first trace resonant circuit.

2. An apparatus according to claim 1 characterized by a source (W1) of a ripple AC signal (V_6) at a frequency that is related to said first frequency that is coupled to said trace capacitance (C_s) for correcting asymmetrical linearity errors.

3. An apparatus according to Claim 1 characterized by a second resonant circuit (60), including a second capacitance (C_6) and a modulation inductance (L_1) coupled to said first trace resonant circuit (L, C_s) for providing inside pincushion distortion correction, said second resonant circuit including said means (R18, L_1) for supplying a second portion of said DC supply current.

4. An apparatus according to Claim 3 characterized in that said modulation inductance (L_1) has a first terminal (113) that is coupled to said trace capacitance (C_s) and a second terminal (111) that is coupled to said second capacitance (C_6) to form said second resonant circuit that generates in said modulation inductance (L_1) a first modulation current that provides inside pincushion distortion correction and wherein said second portion of said supply current is coupled to said modulation inductance (L_1) at a third terminal (112) intermediate said first (113) and second (111) terminals.

5. An apparatus according to Claim 4 characterized in that said trace capacitance (C_s) acts as a low impedance bypass capacitance for said scanning current around said modulation inductance (L_1) substantially throughout said retrace interval.

6. An apparatus according to Claim 4 characterized in that said third terminal (112) is chosen to be at such a point with respect to said first (113) and second (111) terminals of said modulation inductance as to substantially reduce an AC voltage component at said third terminal.



nal.

7. An apparatus according to Claim 4 characterized by a retrace capacitance (C_{RD}) coupled across said deflection winding (L_H) to form said retrace resonant circuit (27) and a source (Q4) of a second modulation current (i_2) that is modulated at a vertical rate to provide outside pincushion distortion correction, said second modulation current (i_2) being coupled to said retrace resonant circuit (27) via a high impedance (nonconductive Q4).
8. An apparatus according to Claim 7 characterized in that said source (Q4) of said second modulation current varies said first modulation current (i_1) to provide both inside and outside pincushion distortion correction.
9. An apparatus according to Claim 3 characterized in that said supply terminal (22a) and said third terminal (112) are at substantially the same DC voltage but at substantially different AC voltages.
10. A deflection apparatus comprising :
 - a source of an input signal (H_s) at a first frequency that is integrally related to a deflection rate;
 - a deflection winding (L_H) having deflection rate scanning current flowing therein during a trace interval and during a retrace interval of a deflection cycle, said deflection winding being included in a retrace resonant circuit (27) during said retrace interval;
 - switching means (Q1) coupled to said deflection winding (L_H) and responsive to said input signal (H_s) for generating, during said retrace interval, a retrace voltage that generates said scanning current in said deflection winding (L_H);
 - a trace capacitance (C_s) series coupled to said deflection winding (L_H) to form with said deflection winding a first trace resonant circuit during said trace interval such that said scanning current in said trace capacitance (C_s) develops during said trace interval a parabolic voltage in said trace capacitance;
 - a source (90) of supply voltage;
 - a supply inductance (W1) coupled between said source (90) of said supply voltage and said first trace resonant circuit for supplying via said supply inductance (W1) a first portion of supply current that replenishes a first portion of energy losses in said retrace resonant circuit (27); and
 - characterized by a circuit branch, including a second capacitance (C_2) and a second in-

ductance (L_1), said second inductance (L_1) having a first terminal (113) that is coupled to said trace capacitance (C_s) and a second terminal (111) that is coupled to said second capacitance (C_2) to form a second resonant circuit that generates in said second inductance (L_1) an alternating current to develop a voltage in said second capacitance (C_2) at a frequency that is related to said deflection rate, a third terminal of said second inductance being chosen to be at a point with respect to said first (113) and second (111) terminals which provides a substantial cancellation of an AC voltage component that is developed at said third (112) terminal; and

an impedance (R18) coupled between said source (90) of supply voltage and said third terminal (112) of said second inductance (L_1) for supplying a second portion of said supply current to said trace capacitance (C_s) through said third terminal (112) that replenishes a second portion of said energy losses such that said second current bypasses said supply inductance (W1).

11. An apparatus according to Claim 10 characterized in that said third terminal (112) is chosen to be at a point with respect to said first (113) and second (111) terminal that the AC voltage at said third terminal is substantially reduced to prevent said impedance (R18) from loading said trace capacitance.
12. An apparatus according to Claim 10 characterized in that said voltage at said second terminal (111) is substantially sinusoidal.
13. An apparatus according to Claim 10 characterized in that said voltages at said first (113) and second (111) terminals are substantially at opposite phases.
14. An apparatus according to Claim 10 characterized in that said third terminal (112) is coupled to said second inductance (L_1) between said first (113) and second (111) terminals of said inductance (L_1).

Patentansprüche

1. Ablenkvorrichtung mit
 - einer Quelle eines Eingangssignals (H_s) mit einer ersten Frequenz, die integral auf ein Ablenkraster bezogen ist;
 - einer Ablenkwicklung (L_H), in der während eines Vorlaufintervalls und während eines Rücklaufintervalls in einem Ablenkzyklus ein Abtaststrom mit der Ablenkrate fließt, wobei



die Ablenkwicklung während des Rücklaufintervalls in eine Rücklauf-Resonanzschaltung (27) einbezogen ist;

Schaltmitteln (Q , D_1 , D_2), die mit der Ablenkwicklung (L_H) verbunden sind und auf das Eingangssignal ansprechen, um während des Rücklaufintervalls eine Rücklaufspannung zu erzeugen;

einer Vorlaufkapazität (C_s), die in Reihe mit der Ablenkwicklung (L_H) geschaltet ist, um während des Vorlaufintervalls mit der Ablenkwicklung eine erste Vorlauf-Resonanzschaltung derart zu bilden, daß der Abtaststrom während des Vorlaufintervalls in der Vorlaufkapazität (C_s) eine parabolische Spannung entwickelt;

einer Quelle (90) einer Versorgungsspannung, die an einer Versorgungsklemme (22a) entwickelt wird;

einer Versorgungsinduktivität ($W1$), die zwischen der Versorgungsspannungsquelle (90) und der ersten Vorlauf-Resonanzschaltung liegt, um über die Versorgungsinduktivität ($W1$) einen ersten Teil eines Versorgungs-Gleichstroms zuzuführen, der einen ersten Teil von Energieverlusten in der Rücklauf-Resonanzschaltung (27) auffüllt, gekennzeichnet durch:

Mittel ($R18$, L_1), die mit der Versorgungsklemme (22a) und der Vorlaufkapazität (C_s) verbunden sind, um der Vorlaufkapazität (C_s) einen zweiten Teil des Versorgungs-Gleichstroms in einem Stromweg zuzuführen, der als Bypass zur Versorgungsinduktivität ($W1$) liegt, um einen zweiten Teil der Energieverluste so aufzufüllen, daß der zweite Teil des Versorgungs-Gleichstroms zugeführt wird, ohne die erste Vorlauf-Resonanzschaltung wechselstrommäßig nennenswert zu belasten.

2. Vorrichtung nach Anspruch 1, gekennzeichnet durch eine Quelle ($W1$) eines welligen Wechselstromsignals (V_6) mit einer Frequenz, die auf die erste Frequenz bezogen ist, das der Vorlaufkapazität (C_s) zur Korrektur asymmetrischer Linearitätsfehler zugeführt wird.
3. Vorrichtung nach Anspruch 1, gekennzeichnet durch eine zweite Resonanzschaltung (60) mit einer zweiten Kapazität (C_6) und einer Modulations-Induktivität (L_1), die mit der ersten Vorlauf-Resonanzschaltung (L , C_s) verbunden ist, um eine Korrektur der inneren Kissenverzeichnung zu bewirken, wobei die zweite Resonanzschaltung Mittel ($R18$, $L1$) enthält, um einen zweiten Teil des Versorgungs-Gleichstroms zuzuführen.
4. Vorrichtung nach Anspruch 3, dadurch gekennzeichnet, daß eine erste Klemme (113) der

Modulationsinduktivität (L_1) mit der Vorlaufkapazität (C_s) und eine zweite Klemme (111) mit der zweiten Kapazität (C_6) verbunden ist, um die zweite Resonanzschaltung zu bilden, die in der Modulationsinduktivität (L_1) einen ersten Modulationsstrom erzeugt, der die Korrektur der inneren Kissenverzeichnung bewirkt, und wobei der zweite Teil des Versorgungsstroms der Modulationsinduktivität (L_1) einer dritten Klemme (112) zwischen der ersten Klemme (113) und der zweiten Klemme (111) zugeführt wird.

5. Vorrichtung nach Anspruch 4, dadurch gekennzeichnet, daß die Vorlaufkapazität (C_s) während weitgehend des ganzen Rücklaufintervalls für den Abtaststrom um die Modulationsinduktivität (L_1) als Bypass-Kapazität mit niedriger Impedanz wirkt.
6. Vorrichtung nach Anspruch 4, dadurch gekennzeichnet, daß für die dritte Klemme (112) eine solche Stelle in bezug auf die erste Klemme (113) und die zweite Klemme (111) der Modulationsinduktivität gewählt ist, daß an der dritten Klemme eine Wechselspannungskomponente nennenswert vermindert ist.
7. Vorrichtung nach Anspruch 4, gekennzeichnet durch eine Rücklaufkapazität (C_{RD}), die über der Ablenkwicklung (L_H) liegt, um die Rücklauf-Resonanzschaltung (27) zu bilden, und durch eine Quelle ($Q4$) eines zweiten Modulationsstroms (i_2), der mit einer Vertikalrate moduliert wird, um eine Korrektur der äußeren Kissenverzeichnung zu bewirken, wobei der zweite Modulationsstrom (i_2) der Rücklauf-Resonanzschaltung (27) über eine hohe Impedanz (nicht leitend $Q4$) zugeführt wird.
8. Vorrichtung nach Anspruch 7, dadurch gekennzeichnet, daß die Quelle ($Q4$) des zweiten Modulationsstroms den ersten Modulationsstrom (i_1) ändert, um eine Korrektur sowohl der inneren als auch der äußeren Kissenverzeichnung zu bewirken.
9. Vorrichtung nach Anspruch 3, dadurch gekennzeichnet, daß die Versorgungsklemme (22a) und die dritte Klemme (112) auf weitgehend derselben Gleichspannung aber auf unterschiedlichen Wechselspannungen liegen.
10. Ablenkvorrichtung mit:
 - einer Quelle eines Eingangssignals (H_s) mit einer ersten Frequenz, die integral auf eine Ablenkrate bezogen ist;
 - einer Ablenkwicklung (L_H), in der während



eines Vorlaufintervalls und während eines Rücklaufintervalls in einem Ablenkzyklus ein Abtaststrom mit der Ablenkrate fließt, wobei die Ablenkwicklung während des Rücklaufintervalls in eine Rücklauf-Resonanzschaltung (27) einbezogen ist;

Schaltmitteln (Q1), die mit der Ablenkwicklung (L_H) verbunden sind und auf das Eingangssignal (H_S) ansprechen, um während des Rücklaufintervalls eine Rücklaufspannung zu erzeugen, die den Ablenkstrom in der Ablenkwicklung (L_H) erzeugt;

einer Vorlaufkapazität (C_s), die in Reihe mit der Ablenkwicklung (L_H) geschaltet ist, um während des Vorlaufintervalls mit der Ablenkwicklung eine erste Resonanzschaltung derart zu bilden, daß der Abtaststrom während des Vorlaufintervalls in der Vorlaufkapazität (C_s) eine parabolische Spannung entwickelt;

einer Quelle (90) einer Versorgungsspannung;

einer Versorgungsinduktivität (W1), die zwischen der Versorgungsstromquelle (90) und der ersten Vorlauf-Resonanzschaltung liegt, um über die Versorgungsinduktivität (W1) einen ersten Teil eines Versorgungsstroms zuzuführen, der einen ersten Teil von Energieverlusten in der Rücklauf-Resonanzschaltung (27) auffüllt;

gekennzeichnet:

durch einen Schaltungszweig, der eine zweite Kapazität (C_6) und eine zweite Induktivität (L_1) enthält, wobei die zweite Induktivität (L_1) eine erste Klemme (113) hat, die mit der Vorlaufkapazität (C_s) verbunden ist, und eine zweite Klemme (111), die mit der zweiten Kapazität (C_6) verbunden ist, um eine zweite Resonanzschaltung zu bilden, die in der zweiten Induktivität (L_1) einen Wechselstrom erzeugt, um in der zweiten Kapazität (C_6) eine Spannung mit einer auf die Ablenkrate bezogenen Frequenz zu entwickeln, wobei der Ort einer dritten Klemme der zweiten Induktivität in bezug auf die erste Klemme (113) und die zweite Klemme (111) so gewählt ist, daß eine Wechselfspannungskomponente, die an der dritten Klemme (112) entwickelt wird, weitgehend aufgehoben wird, und

durch eine Impedanz (R18), die zwischen der Versorgungs-Spannungsquelle (90) und der dritten Klemme (112) der zweiten Induktivität (L_1) geschaltet ist, um der Vorlaufkapazität (C_s) über die dritte Klemme (112) einen zweiten Teil des Versorgungsstroms zuzuführen, der einen zweiten Teil der Energieverluste derart auffüllt, daß der zweite Strom als Bypass zu der Versorgungsinduktivität (W1) fließt.

11. Vorrichtung nach Anspruch 10, dadurch gekennzeichnet, daß der Ort der dritten Klemme (112) in bezug auf die erste Klemme (113) und die zweite Klemme (111) so gewählt ist, daß die Wechselfspannung an der dritten Klemme so weit verringert wird, daß die Impedanz (R18) an einer Ladung der Vorlaufkapazität gehindert wird.

12. Vorrichtung nach Anspruch 10, dadurch gekennzeichnet, daß die Spannung an der zweiten Klemme (111) weitgehend sinusförmig ist.

13. Vorrichtung nach Anspruch 10, dadurch gekennzeichnet, daß die Spannung an der ersten Klemme (113) und an der zweiten Klemme (111) weitgehend entgegengesetzte Phasen hat.

14. Vorrichtung nach Anspruch 10, dadurch gekennzeichnet, daß die dritte Klemme (112) mit der zweiten Induktivität (L_1) zwischen der ersten Klemme (113) und der zweiten Klemme (111) verbunden ist.

Revendications

1. Dispositif de dérivation comprenant :

une source de signal d'entrée (H_S) à une première fréquence qui est intégralement reliée à une vitesse de déviation ; un enroulement de déviation (L_H) comportant un courant de balayage à la vitesse de déviation y circulant pendant un intervalle de tracé et pendant un intervalle de retour d'un cycle de déviation, ledit enroulement de déviation étant inclus dans un circuit résonant de retour (27) pendant ledit intervalle de retour ;

des moyens de commutation (Q1, D1, D2) couplés audit enroulement de déviation (L_H) et sensibles audit signal d'entrée pour générer, pendant ledit intervalle de retour, une tension de retour ;

une capacité de tracé (C_s) couplée audit enroulement de déviation (L_H) pour former avec ledit enroulement de déviation un premier circuit résonant de tracé pendant ledit intervalle de tracé de sorte que ledit courant de balayage dans ladite capacité de tracé (C_s) y développe une tension parabolique pendant ledit intervalle de tracé ;

une source (90) de tension d'alimentation développée au niveau d'une borne d'alimentation (22a);

une inductance d'alimentation (W1) couplée entre ladite source (90) de ladite tension d'alimentation et ledit premier circuit résonant de tracé pour fournir via ladite inductance d'ali-



- mentation (W1) une première partie d'un courant d'alimentation continu (CC) qui récupère une première partie des pertes d'énergie dans ledit circuit résonant de retour (27) ; caractérisé par
- des moyens (R18, L_1) couplés à ladite borne d'alimentation (22a) et à ladite capacité de tracé (C_s) pour fournir une seconde partie dudit courant d'alimentation CC à ladite capacité de tracé (C_s) dans un trajet de courant qui contourne ladite inductance d'alimentation (W1) pour récupérer une seconde partie desdites pertes d'énergie de telle sorte que ladite seconde partie dudit courant d'alimentation CC est appliquée sans charge en courant alternatif (CA) significative dudit premier circuit résonant de tracé.
2. Dispositif selon la revendication 1 caractérisé par la source (W1) d'un signal CA ondulatoire (V_s) à une fréquence qui est reliée à ladite première fréquence qui est couplée à ladite capacité de tracé (C_s) pour corriger des erreurs de linéarité asymétriques.
 3. Dispositif selon la revendication 1 caractérisé par un second circuit résonant (60), incluant une seconde capacité (C_6) et une inductance de modulation (L_1) couplées audit premier circuit résonant de tracé (L_1 , C_s) pour fournir une correction de distorsion en coussin intérieur, ledit second circuit résonant incluant lesdits moyens (R18, L_1) pour fournir une seconde partie dudit courant d'alimentation CC.
 4. Dispositif selon la revendication 3 caractérisé en ce que ladite inductance de modulation (L_1) possède une première borne (113) qui est couplée à ladite capacité de tracé (C_s) et une seconde borne (111) qui est couplée à ladite seconde capacité (C_6) pour former ledit second circuit résonant qui génère dans ladite inductance de modulation (L_1) un premier courant de modulation qui fournit une correction de distorsion en coussin intérieur et dans lequel ladite seconde partie dudit courant d'alimentation est couplée à ladite inductance de modulation (L_1) au niveau d'une troisième borne (112) entre lesdites première (113) et seconde (111) bornes.
 5. Dispositif selon la revendication 4 caractérisé en ce que ladite capacité de tracé (C_s) agit comme une capacité en dérivation de faible impédance pour ledit courant de balayage autour de ladite inductance de modulation (L_1) essentiellement tout le long dudit intervalle de retour.
 6. Dispositif selon la revendication 4 caractérisé en ce que ladite troisième borne (112) est choisie au niveau d'un point tel par rapport auxdites première (113) et seconde (111) bornes de ladite inductance de modulation qu'il réduit sensiblement une composante de tension CA au niveau de ladite troisième borne.
 7. Dispositif selon la revendication 4 caractérisé par une capacité de retour (C_{RD}) couplée à travers ledit enroulement de déviation (L_H) pour former ledit circuit résonant de retour (27) et une source (Q4) d'un second courant de modulation (I_3) qui est modulé à une vitesse verticale pour fournir une correction de distorsion en coussin extérieur, ledit second courant de modulation (I_3) étant couplé audit circuit résonant de retour (27) via une impédance élevée (Q4 non conducteur).
 8. Dispositif selon la revendication 7 caractérisé en ce que ladite source (Q4) dudit second courant de modulation fait varier ledit premier courant de modulation (I_2) pour fournir à la fois une correction de distorsion en coussin intérieur et extérieur.
 9. Dispositif selon la revendication 3 caractérisé en ce que ladite borne d'alimentation (22a) et ladite troisième borne (112) sont sensiblement à la même tension CC mais à des tensions CA sensiblement différentes.
 10. Dispositif de déviation comprenant : une source du signal d'entrée (H_s) à une première fréquence qui est intégralement reliée à une vitesse de déviation ;
un enroulement de déviation (L_H) ayant un courant de balayage à une vitesse de déviation y circulant pendant un intervalle de tracé et pendant un intervalle de retour d'un cycle de déviation, ledit enroulement de déviation étant inclus dans un circuit résonant de retour (27) pendant ledit intervalle de retour ;
des moyens de commutation (Q1) couplés audit enroulement de déviation (L_H) et sensibles audit signal d'entrée (H_s) pour générer, pendant ledit intervalle de retour, une tension de retour qui génère ledit courant de balayage dans ledit enroulement de déviation (L_H) ;
une capacité de tracé (C_s) couplée audit enroulement de déviation (L_H) pour former avec ledit enroulement de déviation un premier circuit résonant de tracé pendant ledit intervalle de tracé de telle sorte que ledit courant de balayage dans ladite capacité de tracé (C_s) développe pendant ledit intervalle de tracé une tension parabolique dans ladite capacité de



tracé ;

une source (90) de tension d'alimentation ;
une inductance d'alimentation (W1) couplée entre ladite source (90) de ladite tension d'alimentation et dudit premier circuit résonant de tracé pour alimenter via ladite inductance d'alimentation (W1) une première partie du courant d'alimentation qui récupère une première partie des pertes d'énergie dans ledit circuit résonant de retour (27) ; et

caractérisé par une branche de circuit incluant une seconde capacité (C_6) et une seconde inductance (L_1), ladite seconde inductance (L_1) comportant une première borne (113) qui est couplée à ladite capacité de tracé (C_5) et une seconde borne (111) qui est couplée à ladite seconde capacité (C_6) pour former un second circuit résonant qui génère dans ladite seconde inductance (L_1) un courant alternatif pour développer une tension dans ladite seconde capacité (C_6) à une fréquence qui est reliée à ladite vitesse de déviation, une troisième borne de ladite seconde inductance étant choisie pour être en un point par rapport auxdites première (113) et seconde (111) bornes qui fournit une annulation importante d'une composante de tension CA qui est développée à ladite troisième borne (112) ; et

une impédance (R18) couplée entre ladite source (90) de tension d'alimentation et ladite troisième borne (112) de ladite seconde inductance (L_1) pour fournir une seconde partie dudit courant d'alimentation à ladite capacité de tracé (C_5) à travers ladite troisième borne (112) qui récupère une seconde partie desdites pertes d'énergie de telle sorte que ledit second courant contourne ladite inductance d'alimentation (W1).

11. Dispositif selon la revendication 10 caractérisé en ce que ladite troisième borne (112) est choisie pour être en un point tel par rapport auxdites première (113) et seconde (111) bornes que la tension CA à ladite troisième borne est sensiblement réduite pour éviter à ladite impédance (R18) de charger ladite capacité de tracé.

12. Dispositif selon la revendication 10 caractérisé en ce que ladite tension à ladite seconde borne (111) est sensiblement sinusoïdale.

13. Dispositif selon la revendication 10 caractérisé en ce que lesdites tensions auxdites première (113) et seconde (111) bornes sont sensiblement en opposition de phase.

14. Dispositif selon la revendication 10 caractérisé en ce que ladite troisième borne (112) est couplée à ladite seconde inductance (L_1) entre lesdites première (113) et seconde (111) bornes de ladite inductance (L_1).

