

Description

Background of the Invention

5 This invention relates to optical switching networks and, more particularly, to optical switching network architectures that reduce crosstalk noise through judicious routing of signals.

Wideband optical signals can be switched with electronic control using electrooptic waveguide couplers using TiLiNbO_3 waveguides on a planar LiNbO_3 crystal. The basic switching element is a coupler with two active inputs and two active outputs. Depending on the amount of voltage at the junction of the two waveguides which
10 carry the two input signals, the two inputs can be coupled to either of the two outputs. Several architectures have been proposed to construct an $N \times N$ switch with the 2×2 directional coupler as the basic component. These architectures are essentially analogs of similar architectures for electronic switching and interconnection networks. However, due to the difference in characteristics of the electronic and optical switching elements, performance of the optical architectures is significantly different.

15 Specifically, regeneration of signals in optical systems is difficult. This difficulty leads to the desire to reduce losses and eliminate noise sources so that the need for regeneration can be diminished. In light of this desire, some architectures that are useful when realized with electronics are less favored for optical realizations.

The attenuation of light passing through a waveguide optical coupler switch has several components: (a) fiber-to-switch and switch-to-fiber coupling loss, (b) propagation loss in the medium, (c) loss at waveguide bends, and (d) loss at the couplers on the substrate. Often, the last factor predominates and, therefore, a substantial part of the attenuation in a switch fabric is directly proportional to the number of couplers that the optical path passes through.

Optical crosstalk results when two signals interact with each other. There are two primary ways in which
25 signals flowing in optical paths can interact in a planar substrate. First, the channels (waveguides) carrying the signals could cross each other in order to imbue a particular topology and the interaction occurs in the neighborhood of the crossover. Secondly, two paths sharing a switching element experience some undesired coupling from one path to the other. We call the former *path crossover* crosstalk, and the latter *switch crossover* crosstalk. The easiest way to reduce *path crossover* crosstalk is to reduce the size of the neighborhood within
30 which the interaction occurs. This can be accomplished by keeping the intersection angles above a certain minimum amount. A more difficult approach is to make the interaction neighborhood precisely long enough to couple the signal entirely from one path to the other and back. With *path crossover* crosstalk reduced to a negligible level, *switch crossovers* remain as the major source of crosstalk in optical switching networks constructed out of electrooptic waveguide couplers.

35 The effort to reduce crosstalk is hence directed at the switch design, at the number of switches that a particular architecture requires in the optical path, and at the signal flow patterns within the network.

In the *IEEE Transactions on Communications*, Vol. COM-35, No. 12, December 1987, we published an article titled "Dilated Networks for Photonic switching". The article presents a number of networks where the third approach to reducing crosstalk is disclosed. We call this the dilated networks approach. Specifically, we
40 disclosed a design for the Benes network that, while maintaining the rearrangeable non-blocking characteristic of the network, insures that no 2×2 switch in the network has optical signals applied concurrently to both its inputs. We also mentioned that a corresponding design for the Omega network is possible.

What we have not described, however, is a method for modifying the structure of any given network to create a corresponding network that is dilated.

Summary of the Invention

In accordance with the principles of our invention, our method can be applied to any given switching network design that employs 2×2 switches the method yields a corresponding dilated switching network design.
50 The dilated switching network differs from the original switching network in only two characteristics. First our dilated network guarantees that at no point in the network can two active signals concurrently appear at the two inputs (or two outputs) of a 2×2 switch. This eliminates crosstalk. Eliminating crosstalk extracts a price, however, and that price is the second difference between the networks. Specifically, the number of 2×2 switches in our dilated network (an corresponding connection links) is approximately twice the number of
55 switches in the original network.

Our method calls for three steps: first, replacing each 2×2 switch with a dual rail switch that contains a pair of 2×2 switches; second, replacing each link that connects an output lead of one switch to an input lead of another switch with a pair of links that connect a pair of output links of one dual rail switch to a pair of input

links of another dual rail switch; and third, combining pairs of output leads at the last stage of the network to form single output leads.

Brief Description of the Drawing

5

FIG. 1 illustrates a crossbar switch design using 2x2 switches;

FIG. 2 presents our dual rail 2x2 switch;

FIG. 3 presents a slight variation on the dual rail switch of FIG. 2;

FIG. 4 shows a dilated switching network realization for the Omega network with 8 inputs and outputs;

10

FIG. 5 shows an undilated and a dilated realization of a diamond array;

FIG. 6 shows an undilated and a dilated realization of a Banyan network; and

FIG. 7 shows an undilated and a dilated realization of a mesh-connected crossbar.

Detailed Description

15

The only condition on deriving a dilated version of a network is that no switch should concurrently carry two active signals, regardless of the permutation that is being realized. If every switch in the network has only one of its inputs connected, or only one of its outputs connected, then the network is dilated, by definition. We call such an implementation a "fan-in/fan-out" implementation. A fan-in/fan-out implementation of a four line crossbar is shown in FIG. 1. Elements 11, 12, and 13, for example, are one-to-two splitter elements. Though structurally they are 2x2 switches, each accepts an optical signal at only one input. As interconnected, they combine to develop four outputs. At any instant, no more than one of the four outputs can carry an optical signal. The four outputs of elements 12 and 13 are connected to two-to-one combiner elements such as element 21. Structurally, the combiner elements are also 2x2 switches, but they are arranged with the understanding that the control signals will insure that whatever optical signal is received at a combiner's input, it will be delivered to the combiner's selected output.

The disadvantage inherent in the fan-in/fan-out dilation of FIG. 1 is, of course, the large number of switches that is required. For an $N \times N$ crossbar, for example, the number of required 2x2 switches is $2N(N-1)$. This number is not the minimum number of switches with which an $N \times N$ network can be implemented. As shown in our aforementioned article by way of a counter example, we created a Benes network with a number of 2x2 switches on the order of $N \log_2 N$.

Neither the FIG. 1 architecture nor the Benes architecture are satisfactory for all applications. What would be useful, and what the instant invention offers, is the ability for artisans to select a particular network topology based on their specific set of system performance requirements, and then permit the developed network to be converted to a dilated realization. In accordance with the principles of our invention, a canonical implementation approach can be employed to achieve a dilated version of any interconnection network constructed from 2x2 switches.

Under the condition that no switching element carry at any instant an optical signal in both its input ports and/or both its output ports, the simplest switching function of two inputs is shown in FIG. 2. That is, in accordance with the principles of our invention, the FIG. 2 circuit is a direct substitute of a conventional 2x2 switch. Just as the conventional 2x2 switch has a "pass-thru" state and a "crossover" state, so does the circuit of FIG. 2. We call the arrangement of FIG. 2 a dual rail switch.

In FIG. 2, each of the two inputs signals is assumed to comprise two rails. One rail carries an active signal, while the other one does not. Each input pair (the two rails) is connected to a different 2x2 switch. In FIG. 2, one input pair is applied to input leads 31 and 32 of switch 30, while the other input pair is applied to input leads 33 and 34 of switch 40. As drawn, the active inputs (marked by "1") are at leads 31 and 33. Given that at most one of the two input leads of a 2x2 switch carry a signal, the switching state of switches 30 and 40 is well defined. Specifically, when the active signals are at the same spatial sense (i.e., leads 31 and 33 active or leads 32 and 34 active), then the states of switches 30 and 40 are reversed from one another. Conversely, when the active signals are at a crossed spatial sense (leads 31 and 34 active or leads 32 and 33 active) then the states of switches 30 and 40 are identical (i.e., both "crossover", or both "pass-thru"). A more detailed specification of the states of switches 30 and 40 is presented in the table below.

55

	input		input		connection type	switch 30	switch 40
	31	32	33	34			
5	1	0	1	0	pass-thru	pass-thru	pass-thru
	1	0	1	0	crossover	crossover	crossover
	1	0	0	1	pass-thru	pass-thru	crossover
10	1	0	0	1	crossover	crossover	pass-thru
	0	1	1	0	pass-thru	crossover	pass-thru
	0	1	1	0	crossover	pass-thru	crossover
	0	1	0	1	pass-thru	crossover	crossover
15	0	1	0	1	crossover	pass-thru	pass-thru

FIG. 3 presents a variation on the dual rail switch of FIG. 2. Its only difference is in the spatial sense that the outputs exhibit for different spatial senses of the input. Specifically, the FIG. 3 dual rail switch forces the two output pairs to have a like spatial sense. Either the top rail of both output pairs is active, or the bottom rail of both output pairs is active.

In accordance with the principles of our invention, any network topology or architecture that employs 2x2 switches can be realized in a dilated form by (1) replacing the single rail 2x2 switches of the network with the dual rail switches of FIG. 2 (or FIG. 3), (2) interconnecting the dual rail switches with pairs of lines in a manner that essentially replaces the single line interconnections of the undilated network with line pairs, and (3) insuring with appropriate control signals as described above that each pair of lines has, at most, one lead that carries active signal information. The latter, of course, is an operational requirement rather than a structural one.

FIG. 4 illustrates the use of our approach in connection with the network known as the omega network (with the input shuffle deleted for sake of simplicity). The dual rail switches are marked by dashed blocks 41-52. In blocks 41-44 only one input of each input pair is connected to the incoming signal. The other inputs are simply not used. This insures the first of the requirements for blocks 41-44; that of no more than one active input at each pair of inputs to each 2x2 coupler within the dual rail switch. The requirement that no pair of outputs should contain a signal in both of the output leads is satisfied by a judicious application of control signals to the couplers within the dual rail switches, as described above. The final stage of the network, which in the case of FIG. 4 is dual rail switches 49-52, the output pairs contain an active signal in only one of the leads. Each of the output pairs should be combined to a single output lead and, accordingly, FIG. 4 includes combiners 53-60 which serve this function. It may be noted that switches 41-44 could be constructed from switches that are simpler than the dual rail switch of FIG. 2. Conversely, the combiner switches 53-60 can be realized with the dual rail switches used elsewhere in the network. It is simply a designer's choice.

FIG. 4 depicts a very small network; only 8 inputs and outputs. Because of its small size, the connectivity pattern perhaps is not obvious from the figure itself but, of course, the omega network is well known in the art. Nevertheless, for the sake of completeness, the description below presents the connectivity pattern of the omega network in "closed form". The nomenclature developed for the omega network is also used in connection with other networks that are described *infra*.

The omega network is one of a class of networks that require $\log_2 N$ stages of switching elements for an N input and N output network. The connectivity of the switching elements can be described by designating each stage with a variable, such as i, ranging from 0 to $(\log_2 N) - 1$. Each input and output lead of a stage is labeled from 0 to N (starting, for example, from the top of the figure), and the label is expressed in binary form. A specific input link is thus identified by

$$I(p_{l-1}p_{l-2}p_{l-3} \dots p_j \dots p_2p_1p_0)_l$$

where $l = \log_2 N$, l is the stage number and I designates the link as an input link.

Similarly, a specific output link is identified by

$$O(p_{l-1}p_{l-2}p_{l-3} \dots p_j \dots p_2p_1p_0)_l$$

where O designates the link as an output link.

The connectivity pattern for the undilated omega network is

$$O(p_{l-1}p_{l-2}p_{l-3} \dots p_j \dots p_2p_1p_0)_l \rightarrow I(p_{l-2}p_{l-3} \dots p_j \dots p_2p_1p_0p_{l-1})_{l+1}$$

where $\rightarrow$ designates a connection between the links identified on the two sides of the arrow. Note that it merely

is a circular left shift.

The dilated omega network of our invention has twice as many links between the switching stages as there are in the undilated omega network. Accordingly, the link labels require an additional bit, p_1 . The connectivity pattern of the dilated network is therefore,

$$O(p_1 p_{i-1} p_{i-2} p_{i-3} \dots p_j \dots p_2 p_1 p_0) \rightarrow I(p_{i-1} p_{i-2} p_{i-3} \dots p_j \dots p_2 p_1 p_0)_{i+1}.$$

With respect to the above-mentioned control signals, the table describing the behavior of the FIG. 2 dual rail switch is couched in terms of the spatial sense of the incoming signals. However, it may be noted that the spatial sense of the signals throughout the remainder of the network is strictly a function of the route selected for the signal. Since the control circuitry is aware of the desired routing, the actual control signals of the couplers in each of the dual rail switches can easily be ascertained.

Expanding on the above, the control of networks that employ 2×2 switches can be external or embedded in the signals that flow through the network. Typically, for the latter approach the signals are arranged in packets that contain a fixed number of information bits, and each packet contains a header section which holds the destination address of the packet. That destination address controls the packet's routing. In some networks, the packets' destinations directly control the routing. In others, the routing is dependent on other packets. For example, in a Batcher network where each 2×2 switch is called upon to sort the two incoming packets, the destination address of both packets needs to be known before the state of the 2×2 switch can be determined.

Applications with external routing control typically relate to "circuit switching" situations. Circuit switching is used, for example, when a call is established from point A to point B and the call remains in effect for a relatively long period of time. Centralized external switching is also possible with packetized data. In such situations, the external circuitry (rather than the distributed control intelligence within each switch) develops the necessary routing signals. It is also possible for the external circuitry to mimic the routing algorithm that is otherwise implemented within the routing switches.

Indeed, in some applications it may be even advantageous to separate the routing control function from the actual routing of signals. For example, in waveguide electrooptic applications the routing control is electronic whereas the signals and the switching element are optic. Even though the bandwidth of the information signal modulated upon the optic carrier is very high, the packet rate may be quite reasonable for electronic implementations. Consequently, it is possible to create an electronic circuit that basically deals only with the address portions of each packet and evaluates the necessary routing control information. This electronic circuit can be centralized, or it can be distributed. Indeed, it can be distributed and appear identical in its interconnection of the distributed control circuitry portions to the network that it intends to control. We call this arrangement of the control circuitry, a "shadow network". With a shadow network arrangement, even sorting can be easily accomplished.

To illustrate the above control principles, FIG. 4 includes, by way of example, a particular interconnection pattern of four input signals to particular output ports; to wit, inputs A, B, C, and D at input ports I_1 , I_2 , I_3 , and I_4 , are to be connected to output ports O_4 , O_5 , O_2 , and O_7 , respectively. The figure also depicts the states of the relevant switches.

FIG. 5 presents the undilated and the dilated structures of the diamond array. In the dilated version, the inputs are applied to the dual rail switches that are situated at the top left diagonal; to wit, switches 61, 62, and 63. These switches, and the switches on the diagonal immediately below and to the right (i.e., switches 64 and 65) can be thought of as the $i=0$ stage. With such an arrangement, the input connections of the diamond array in the first stage ($i=0$) can be said to be:

a) input signals are injected into input links 0, and 2 of stage 0 (two inputs in dilated switch 61), input links 8, and 10 of stage 0 (two inputs in dilated switch 62), and input links 16, and 18 of stage 0 (two inputs in dilated switch 63);

b) output links 2-3 (switch 61) and 8-9 (switch 62) are connected to input links 4, 5, 6, and 7 of stage 0 (switch 64), and output links 10-11 (switch 62) and 16-17 of stage 0 (switch 63) are connected to input links 12, 13, 14 and 15 of stage 0.

Output links 0, 1, 4, 5, 6, 7, 12, 13, 14, 15, 18 and 19 are connected to the next stage. Generalizing, the connectivity of the diamond array is not accounting for the edge links 0, 1, 18 and 19:

1) $O(8n+j)_i$ for $j=0,1,2,3 \rightarrow I(8n+j-2)_i$ for all non-negative $8n+j-2$;

2) $O(8n+j)_i$ for $j=4,5 \rightarrow I(8n+j-2)_{i+1}$; and

3) $(8n+j)_i$ for $j=6,7 \rightarrow I(8n+j+2)_{i+1}$.

FIG. 6 depicts the undilated and the dilated structures of the banyan network. The connectivity pattern of the undilated network at any stage i is $O(p_{i-1} p_{i-2} \dots p_{i+2} p_{i+1} \dots p_1 p_0) \rightarrow I(p_{i-1} p_{i-2} \dots p_{i+2} p_0 \dots p_1 p_{i+1})_{i+1}$. It is basically a swap of bits p_0 and p_{i+1} . In the dilated banyan, $O(p_1 p_{i-1} \dots p_{i+2} p_{i+1} \dots p_1 p_0) \rightarrow I(p_{N+1} p_N \dots p_1 p_{i+1} \dots p_{i+2} p_0)$. In other words, a swap of bits p_1 and p_{i+2} .

FIG. 7 illustrates the undilated and the dilated structures of the mesh-connected crossbar network. The connectivity of the mesh-connected crossbar is most easily defined in terms of rows and columns. Each dilated switch has one pair of links connected to its neighbor in the same row, and one pair of links connected to its neighbor in the same column.

The above figures illustrate fully dilated networks, but a skilled artisan would clearly recognize that a partially dilated network can be easily obtained by simply implementing only a portion of a given network with dual rail switches. The simplest way to create a partially dilated network is to divide the given network into a dilated portion preceded by an undilated portion. It is simplest because no additional components are necessary. However, reversing the arrangements is not much more difficult. It merely requires the inclusion of a combining stage after the dilated portion and before the undilated portion.

Claims

1. A network for routing signals comprising:
 - an input stage including a plurality of initial routing elements, each comprising a first pair of output leads and a second pair of output leads, a first input lead connected to an input port of said network, and a second input lead connected to another input port of said network;
 - an output stage including a plurality of terminal routing elements, each comprising a pair of input leads and an output lead connected to an output port of said network;
 - a plurality of intermediate routing elements, each comprising a first pair of input leads, a second pair of input leads, a first pair of output leads and a second pair of output leads; and
 - an interconnection arrangement wherein
 - said first pair of input leads of an intermediate routing element is connected to a pair of output leads of either one of said initial routing elements or one of said intermediate elements,
 - said second pair of input leads of said intermediate routing element is connected to a pair of output leads of either one of said initial routing elements or one of said intermediate elements, and
 - said pair of input leads of a terminal routing element is connected to a pair of output leads of one of said intermediate elements.
2. The network of claim 1, further comprising control means for accepting at most one active signal at each of said pairs of input leads of an intermediate routing element, and routing at most one of said signals accepted at said intermediate routing element to each of said pairs of output leads of said intermediate routing element.
3. The network of claim 1 wherein each of said intermediate routing elements comprises:
 - a first 2x2 switch comprising a pair of input ports connected to said first input pair, and a pair of output ports
 - with one of said output ports of said first switch connected to said first pair of output leads and the other of said output ports of said first switch connected to said second pair of output leads; and
 - a second 2x2 switch comprising a pair of input ports connected to said second input pair, and a pair of output ports
 - with one of said output ports of said second switch connected to said first pair of output leads and the other of said output ports of said second switch connected to said second pair of output lead.
4. A method for creating an altered version of a given network that employs single rail 2x2 switches and includes single rail input signals and single rail output signals, comprising the steps of:
 - employing a dual rail switch in said altered version of a given network in place of a single rail switch in said given network, said dual rail switch comprising two input pairs of leads and two output pairs of leads;
 - employing a pair of links in said altered version of a given network in place of a single link in said given network; and
 - employing a combiner stage as the ultimate stage of said altered version of a given network to combine pairs of output signals in a penultimate stage of said altered version of a given network to form single rail output signals or said altered version of a given network that parallel said single rail output signals of said given network.
5. The method of claim 4 further comprising a step of developing a set of control signals, said set comprising



FIG. 7 illustrates the undilated and the dilated structures of the mesh-connected crossbar network. The connectivity of the mesh-connected crossbar is most easily defined in terms of rows and columns. Each dilated switch has one pair of links connected to its neighbor in the same row, and one pair of links connected to its neighbor in the same column.

- 5 The above figures illustrate fully dilated networks, but a skilled artisan would clearly recognize that a partially dilated network can be easily obtained by simply implementing only a portion of a given network with dual rail switches. The simplest way to create a partially dilated network is to divide the given network into a dilated portion preceded by an undilated portion. It is simplest because no additional components are necessary. However, reversing the arrangements is not much more difficult. It merely requires the inclusion of a combining stage after the dilated portion and before the undilated portion.
- 10

Claims

- 15 1. A network for routing signals comprising:
 an input stage including a plurality of initial routing elements, each comprising a first pair of output leads and a second pair of output leads, a first input lead connected to an input port of said network, and a second input lead connected to another input port of said network;
 an output stage including a plurality of terminal routing elements, each comprising a pair of input leads and an output lead connected to an output port of said network;
 a plurality of intermediate routing elements, each comprising a first pair of input leads, a second pair of input leads, a first pair of output leads and a second pair of output leads; and
 an interconnection arrangement wherein
 said first pair of input leads of an intermediate routing element is connected to a pair of output leads of either one of said initial routing elements or one of said intermediate elements,
 said second pair of input leads of said intermediate routing element is connected to a pair of output leads of either one of said initial routing elements or one of said intermediate elements, and
 said pair of input leads of a terminal routing element is connected to a pair of output leads of one of said intermediate elements.
- 20
- 25 2. The network of claim 1, further comprising control means for accepting at most one active signal at each of said pairs of input leads of an intermediate routing element, and routing at most one of said signals accepted at said intermediate routing element to each of said pairs of output leads of said intermediate routing element.
- 30 3. The network of claim 1 wherein each of said intermediate routing elements comprises:
 a first 2x2 switch comprising a pair of input ports connected to said first input pair, and a pair of output ports
 with one of said output ports of said first switch connected to said first pair of output leads and the other of said output ports of said first switch connected to said second pair of output leads; and
 a second 2x2 switch comprising a pair of input ports connected to said second input pair, and a pair of output ports
 with one of said output ports of said second switch connected to said first pair of output leads and the other of said output ports of said second switch connected to said second pair of output lead
- 35
- 40 4. A method for creating an altered version of a given network that employs single rail 2x2 switches and includes single rail input signals and single rail output signals, comprising the steps of:
 employing a dual rail switch in said altered version of a given network in place of a single rail switch in said given network, said dual rail switch comprising two input pairs of leads and two output pairs of leads;
 employing a pair of links in said altered version of a given network in place of a single link in said given network; and
 employing a combiner stage as the ultimate stage of said altered version of a given network to combine pairs of output signals in a penultimate stage of said altered version of a given network to form single rail output signals or said altered version of a given network that parallel said single rail output signals of said given network.
- 45
- 50
- 55 5. The method of claim 4 further comprising a step of developing a set of control signals, said set comprising



a pair of control signals for each of said dual rail switches, with each pair of control signals developed for a dual rail switch arranged to insure that no more than one of active signals applied to said dual rail switch is routed to each of said output pairs of leads of said dual rail switch.

- 5 6. A network for routing signals comprising:
 - a plurality of dual rail routing elements, each comprising a first pair of input leads, a second pair of input leads, a first pair of output leads and a second pairs of output leads;
 - a first interconnection arrangement wherein
 - said first pair of input leads of one of said dual rail routing elements is connected to a pair
 - 10 of output leads of another one of said dual rail routing elements, and
 - said second pair of input leads of said one of said dual rail routing elements is connected to a pair of output leads of still another one of said dual rail routing elements;
 - a plurality of single rail routing elements, each comprising one pair of input leads and one pair of output leads;
 - 15 a second interconnection arrangement wherein said input leads of one of said single rail routing elements are connected to output leads of different ones of said single rail routing elements; and
 - a combiner element interposed between each output pair of leads of dual rail switch that communicates the output signal of said output pair of leads to a single rail switch, with said combiner element having two inputs and one output.
- 20 7. The network of claim 6, wherein said combiner element performs a logical OR function.
8. the network of claim 6 wherein said combiner element performs a selection function.
- 25 9. A dilated omega network comprising
 - a plurality of interconnected stages, where each stage comprises N 2×2 switches that include 2 input links and two output links each, N being an integer, the interconnection of said stage comprising links that connect switches in stage i to switches in stage $i+1$, where i is an integer, in accordance with the pattern $O(p_{i-1}p_{i-2}\dots p_1p_0)_i \rightarrow I(p_{i-1}p_{i-2}\dots p_1p_0)_{i+1}$, where I is an integer such that $N \leq 2^I$, p_k represents the $k+1$ bit in a binary representation of a designation of a link of a switch, where such designation is an integer in the range 0 to $2N$ and is twice the value of the designation of the switch, and $O(p_{i-1}p_{i-2}\dots p_1p_0)_i$ designates output link $(p_{i-1}p_{i-2}\dots p_1p_0)$ at stage i while $I(p_{i-1}p_{i-2}\dots p_1p_0)_{i+1}$ designates input link $(p_{i-1}p_{i-2}\dots p_1p_0)$ at stage $i+1$.
- 30 10. A dilated diamond array comprising a plurality of interconnected stages, where each stage comprises 2×2 switches that include 2 input links and two output links each, the interconnection of said stage comprising links that connect switches in stage i to switches in stage $i+1$, where i is an integer, in accordance with the pattern
 - 1) $O(8n+j)_i$ for $j=0,1,2,3 \rightarrow I(8n+j-2)_i$ for all non-negative $8n+j-2$, where n is an integer, $O(8n+j)_i$ designates output link $8n+j$ in stage i and; $I(8n+j-2)_i$ designates input link $8n+j-2$ in stage i ;
 - 2) $O(8n+j)_i$ for $j=4,5 \rightarrow I(8n+j-2)_{i+1}$ where $I(8n+j-2)_{i+1}$ designates input link $8n+j-2$ in stage $i+1$; and
 - 3) $(8n+j)_i$ for $j=6,7 \rightarrow I(8n+j+2)_{i+1}$ where $I(8n+j+2)_{i+1}$ designates input link $8n+j+2$ in stage $i+1$.
- 35 11. A dilated banyan network comprising
 - a plurality of interconnected stages, where each stage comprises N 2×2 switches that include 2 input links and two output links each, N being an integer, the interconnection of said stage comprising links that connect switches in stage i to switches in stage $i+1$, where i is an integer, in accordance with the pattern $O(p_{i-1}\dots p_{j+2}p_{j+1}\dots p_1p_0)_i \rightarrow I(p_{i-1}\dots p_{j+2}p_{j+1}\dots p_1p_0)_{i+1}$, where I is an integer such that $N \leq 2^I$, p_k represents the $k+1$ bit in a binary representation of a designation of a link of a switch, where such designation is an integer in the range 0 to $2N$ and is twice the value of the designation of the switch, and $O(p_{i-1}\dots p_{j+2}p_{j+1}\dots p_1p_0)_i$ designates output link $(p_{i-1}\dots p_{j+2}p_{j+1}\dots p_1p_0)$ at stage i while $I(p_{i-1}\dots p_{j+2}p_{j+1}\dots p_1p_0)_{i+1}$ designates input link $(p_{i-1}\dots p_{j+2}p_{j+1}\dots p_1p_0)$ stage $i+1$.
- 40 12. A mesh-connected crossbar network comprising a plurality of interconnected 2×2 switches that include 2 input links and two output links each, arranged in an array of rows and columns, the interconnection of said switches comprising links that connect each switch in row i and column j , where i and j are integers, to a switch in row $i+1$ and column j with a pair of links and to a switch in row i and columns $j+1$ with a pair of links.
- 45
- 50
- 55



Patentansprüche

1. Netzwerk zur Wegführung von Signalen mit
 5 einer Eingangsstufe mit einer Vielzahl von Anfangs-Wegführungselementen, die je ein erstes und ein zweites Paar von Ausgangsleitungen, eine erste, mit einem Eingangsport des Netzwerks verbundene Eingangsleitung und eine zweite, mit einem weiteren Eingangsport des Netzwerks verbundene Eingangsleitung enthalten,
 einer Ausgangsstufe mit einer Vielzahl von Endwegführungselementen, die je ein Paar von Eingangsleitungen und eine mit einem Ausgangsport des Netzwerks verbundene Ausgangsleitung enthalten,
 10 einer Vielzahl von Zwischenwegführungselementen, die je ein erstes und ein zweites Paar von Eingangsleitungen sowie ein erstes und ein zweites Paar von Ausgangsleitungen enthalten, und einer Verbindungsanordnung, wobei
 das erste Paar von Eingangsleitungen eines Zwischenwegführungselementes mit einem Paar von Ausgangsleitungen entweder eines Anfangswegführungselementes oder eines Zwischenwegführungselementes verbunden ist,
 15 das zweite Paar von Eingangsleitungen des Zwischenwegführungselementes mit einem Paar von Ausgangsleitungen entweder eines Anfangswegführungselementes oder eines Zwischenwegführungselementes verbunden ist und
 das Paar von Eingangsleitungen eines Endwegführungselementes mit einem Paar von Ausgangsleitungen eines Zwischenwegführungselementes verbunden ist.
2. Netzwerk nach Anspruch 1 mit ferner einer Steuereinrichtung zur Aufnahme höchstens eines aktiven Signals an jedem Paar von Eingangsleitungen eines Zwischenwegführungselementes und zur Weiterleitung höchstens eines der am Zwischenwegführungselement aufgenommenen Signale zu jedem Paar von
 25 Ausgangsleitungen des Zwischenwegführungselementes.
3. Netzwerk nach Anspruch 1, bei dem jedes Zwischenwegführungselement aufweist:
 einen ersten 2x2-Koppler mit einem Paar von Eingangsporten, die mit dem ersten Eingangspaar verbunden sind, und einem Paar von Ausgangsporten,
 30 wobei einer der Ausgangsporten des ersten Kopplers mit dem ersten Paar von Ausgangsleitungen und der andere Ausgangsport des ersten Kopplers mit dem zweiten Paar von Ausgangsleitungen verbunden sind, und
 einem zweiten 2x2-Koppler mit einem Paar von Eingangsporten, die mit dem zweiten Eingangspaar verbunden sind, und einem Paar von Ausgangsporten,
 35 wobei einer der Ausgangsporten des zweiten Kopplers mit dem ersten Paar von Ausgangsleitungen und der andere Ausgangsport des zweiten Kopplers mit dem zweiten Paar von Ausgangsleitungen verbunden sind.
4. Verfahren zur Erzeugung einer abgeänderten Version eines gegebenen Netzwerks, das eingleisige 2x2-Koppler verwendet und eingleisige Eingangssignale und eingleisige Ausgangssignale besitzt, mit den Verfahrensschritten:
 40 Verwenden eines zweigleisigen Kopplers in der abgeänderten Version eines gegebenen Netzwerks anstelle eines eingleisigen Kopplers in dem gegebenen Netzwerk, wobei der zweigleisige Koppler zwei Paare von Eingangsleitungen und zwei Paare von Ausgangsleitungen aufweist,
 45 Verwenden eines Paares von Linkleitungen in der abgeänderten Version eines gegebenen Netzwerks anstelle einer einzelnen Linkleitung in dem gegebenen Netzwerk und
 Verwenden einer Kombinierstufe als letzte Stufe der abgeänderten Version eines gegebenen Netzwerks, die Paare von Ausgangssignalen in einer vorletzten Stufe der abgeänderten Version eines gegebenen Netzwerks kombiniert und eingleisige Ausgangssignale der abgeänderten Version eines gegebenen Netzwerks bildet, die eine Parallele zu den eingleisigen Ausgangssignalen des gegebenen Netzwerks darstellen.
5. Verfahren nach Anspruch 4 mit ferner dem Schritt:
 Erzeugen eines Satzes von Steuersignalen mit einem Paar von Steuersignalen für jeden zweigleisigen Koppler, wobei jedes Paar von für einen zweigleisigen Koppler erzeugten Steuersignalen so angeordnet ist, daß sichergestellt ist, daß nicht mehr als ein aktives, an den zweigleisigen Koppler angelegtes Signal zu jedem der Paare von Ausgangsleitungen des zweigleisigen Kopplers geführt wird.



6. Netzwerk zur Wegführung von Signalen mit einer Vielzahl von zweigleisigen Wegführungselementen, die je ein erstes und ein zweites paar von Eingangsleitungen sowie ein erstes und ein zweites Paar von Ausgangsleitungen enthalten, einer ersten Verbindungsanordnung, bei der
- 5 das erste Paar von Eingangsleitungen eines zweigleisigen Wegführungselementes mit einem paar von Ausgangsleitungen eines anderen zweigleisigen Wegführungselementes verbunden ist und das zweite paar von Eingangsleitungen eines zusätzlichen zweigleisigen Wegführungselementes verbunden ist,
- 10 einer Vielzahl von eingleisigen Wegführungselementen, die je ein Paar von Eingangsleitungen und ein Paar von Ausgangsleitungen besitze,
- einer zweiten Verbindungsanordnung, wobei die Eingangsleitungen eines eingleisigen Wegführungselementes mit Ausgangsleitungen unterschiedlicher eingleisiger Wegführungselemente verbunden sind, und einem Kombinierelement, das zwischen jedes Paar von Ausgangsleitungen eines zweigleisigen Kopplers geschaltet ist, der das Ausgangssignal des Paares von Ausgangsleitungen zu einem eingleisigen Koppler führt, wobei das Kombinierelement zwei Eingänge und einen Ausgang besitzt.
- 15
7. Netzwerk nach Anspruch 6, bei dem das Kombinierelement eine logische ODER-Funktion ausführt.
8. Netzwerk nach Anspruch 6, bei dem das Kombinierelement eine Auswahlfunktion ausführt.
- 20
9. Erweitertes Omega-Netzwerk mit einer Vielzahl von miteinander verbundenen Stufen, wobei jede Stufe $N \times 2$ -Koppler umfaßt, die je zwei Eingangsleitungen und zwei Ausgangsleitungen enthalten, N eine ganze Zahl ist, die Verbindung der Stufe Linkleitungen umfaßt, die Koppler in der Stufe i mit Kopplern in der Stufe $i+1$ verbinden, wobei
- 25 i eine ganze Zahl entsprechend dem Muster $O(p_1 p_{1-1} p_{1-2} \dots p_j \dots p_2 p_1 p_0)_i \rightarrow I(p_{1-1} p_{N-2} \dots p_j \dots p_2 p_1 p_0)_{i+1}$, wobei I eine ganze Zahl ist, derart, daß gilt $N \leq 2^i$, p_k das $(k+1)$ te Bit in einer Binärdarstellung für die Bezeichnung einer Linkleitung eines Kopplers darstellt, diese Bezeichnung eine ganze Zahl im Bereich von 0 bis $2N$ und gleich dem doppelten Wert der Bezeichnung des Kopplers ist, und $O(p_1 p_{1-1} p_{1-2} \dots p_j \dots p_2 p_1 p_0)_i$ die Ausgangslinkleitung $(p_1 p_{1-1} p_{1-2} \dots p_j \dots p_2 p_1 p_0)$ der Stufe i bezeichnet, während $I(p_{1-1} p_{N-2} \dots p_j \dots p_2 p_1 p_0)_{i+1}$ die Eingangslinkleitung $(p_{1-1} p_{N-2} \dots p_j \dots p_2 p_1 p_0)$ der Stufe $i+1$ bezeichnet.
- 30
10. Erweiterte Diamantanordnung mit einer Vielzahl von miteinander verbundenen Stufen, bei der jede Stufe 2×2 -Koppler mit je zwei Eingangsleitungen und zwei Ausgangsleitungen umfaßt, wobei die Verbindung der Stufe Linkleitungen enthält, die Koppler in der Stufe i mit Kopplern in der Stufe $i+1$ enthält, i eine ganze Zahl ist, entsprechend dem Muster
- 35 1) $O(8n+j)_i$ für $j=0,1,2,3 \rightarrow I(8n+j-2)_i$ für alle nicht-negativen $8n+j-2$, wobei n eine ganze Zahl ist, $O(8n+j)_i$ die Ausgangslinkleitung $8n+j$ in der Stufe i und $I(8n+j-2)_i$ die Eingangslinkleitung $8n+j-2$ in der Stufe i bezeichnen,
- 2) $O(8n+j)_i$ für $j=4,5 \rightarrow I(8n+j-2)_{i+1}$, wobei $I(8n+j-2)_{i+1}$ die Eingangslinkleitung $8n+j-2$ in der Stufe $i+1$ bezeichnet, und
- 40 3) $(8n+j)_i$ für $j=6,7 \rightarrow I(8n+j+2)_{i+1}$, wobei $I(8n+j+2)_{i+1}$ die Eingangslinkleitung $8n+j+2$ in der Stufe $i+1$ bezeichnet.
11. Erweitertes Banyan-Netzwerk mit einer Vielzahl von miteinander verbundenen Stufen, wobei jede Stufe $N \times 2$ -Koppler mit je zwei Eingangsleitungen und zwei Ausgangsleitungen umfaßt, N eine ganze Zahl ist, die Verbindung der Stufe Linkleitungen enthält, die Koppler in der Stufe i mit Kopplern in der Stufe $i+1$ verbinden, i eine ganze Zahl ist, entsprechend dem Muster
- 45 $O(p_1 p_{1-1} \dots p_{j+2} p_{j+1} \dots p_1 p_0)_i \rightarrow I(p_1 p_{1-1} \dots p_{j+2} p_0 \dots p_1 p_{j+1})_{i+1}$, wobei I eine ganze Zahl ist, derart, daß gilt $N \leq 2^i$, p_k das $(k+1)$ te Bit in einer Binärdarstellung einer Bezeichnung für eine Linkleitung eines Kopplers darstellt, wobei diese Bezeichnung eine ganze Zahl im Bereich 0 bis $2N$ und gleich dem doppelten Wert der Bezeichnung des Kopplers ist, und $O(p_1 p_{1-1} \dots p_{j+2} p_{j+1} \dots p_1 p_0)_i$ die Ausgangslinkleitung $(p_1 p_{1-1} \dots p_{j+2} p_{j+1} \dots p_1 p_0)$ der Stufe i bezeichnet, während $(p_1 p_{1-1} \dots p_{j+2} p_0 \dots p_1 p_{j+1})_{i+1}$ die Eingangslinkleitung $(p_1 p_{1-1} \dots p_{j+2} p_0 \dots p_1 p_{j+1})$ der Stufe $i+1$ angibt.
- 50
12. Vermaschtes Koordinatennetzwerk mit einer Vielzahl von miteinander verbundenen 2×2 -Kopplern, die je zwei Eingangsleitungen und zwei Ausgangsleitungen enthalten und in Zeilen und Spalten angeordnet sind, wobei die Verbindung der Koppler Linkleitungen umfaßt, die jeden Koppler in der Zeile i und Spalte j , i und j sind ganze Zahlen, mit einem Koppler in der Zeile $i+1$ und Spalte j mit einem Paar von
- 55



Linkleitungen und mit einem Koppler in der Zeile i und Spalte j+1 mit einem Paar von Linkleitungen verbindet.

5 Revendications

1. Un réseau pour l'acheminement de signaux, comprenant :

un étage d'entrée comprenant un ensemble d'éléments d'acheminement initiaux, comprenant chacun une première paire de conducteurs de sortie et une seconde paire de conducteurs de sortie, un premier conducteur d'entrée connecté à un accès d'entrée du réseau, et un second conducteur d'entrée connecté à un autre accès d'entrée du réseau;

un étage de sortie comprenant un ensemble d'éléments d'acheminement finals, comprenant chacun une paire de conducteurs d'entrée et un conducteur de sortie connecté à un accès de sortie du réseau;

un ensemble d'éléments d'acheminement intermédiaires, comprenant chacun une première paire de conducteurs d'entrée, une seconde paire de conducteurs d'entrée, une première paire de conducteurs de sortie et une seconde paire de conducteurs de sortie; et

une structure d'interconnexion dans laquelle

la première paire de conducteurs d'entrée d'un élément d'acheminement intermédiaire est connectée à une paire de conducteurs de sortie de l'un des éléments d'acheminement initiaux ou de l'un des éléments intermédiaires,

la seconde paire de conducteurs d'entrée de l'élément d'acheminement intermédiaire est connectée à une paire de conducteurs de sortie de l'un des éléments d'acheminement initiaux ou de l'un des éléments intermédiaires, et

la paire de conducteurs d'entrée d'un élément d'acheminement final est connectée à une paire de conducteurs de sortie de l'un des éléments intermédiaires.

2. Le réseau de la revendication 1, comprenant en outre des moyens de commande pour accepter au plus un signal actif sur chacune des paires de conducteurs d'entrée d'un élément d'acheminement intermédiaire, et pour acheminer au plus l'un des signaux acceptés à cet élément d'acheminement intermédiaire vers chacune des paires de conducteurs de sortie de cet élément d'acheminement intermédiaire.

3. Le réseau de la revendication 1, dans lequel chacun des éléments d'acheminement intermédiaires comprend :

un premier commutateur de 2 x 2, comprenant une paire d'accès d'entrée connectés à la première paire d'entrées, et une paire d'accès de sortie

avec l'un des accès de sortie du premier commutateur connecté à la première paire de conducteurs de sortie, et l'autre accès de sortie du premier commutateur connecté à la seconde paire de conducteurs de sortie; et

un second commutateur de 2 x 2 comprenant une paire d'accès d'entrée connectés à la seconde paire d'entrées et une paire d'accès de sortie

avec l'un des accès de sortie du second commutateur connecté à la première paire de conducteurs de sortie, et l'autre accès de sortie du second commutateur connecté à la seconde paire de conducteurs de sortie.

4. Un procédé pour créer une version modifiée d'un réseau donné qui utilise des commutateurs de 2 x 2 à un seul rail et qui comporte des signaux d'entrée à un seul rail et des signaux de sortie à un seul rail, comprenant les étapes suivantes :

on emploie un commutateur à deux rails dans cette version modifiée d'un réseau donné, à la place d'un commutateur à un seul rail dans le réseau donné, ce commutateur à deux rails comprenant deux paires de conducteurs d'entrée et deux paires de conducteurs de sortie;

on utilise une paire de mailles dans cette version modifiée d'un réseau donné, à la place d'une seule maille dans le réseau donné; et

on utilise un étage de combinaison à titre de dernier étage de la version modifiée d'un réseau donné, pour combiner des paires de signaux de sortie d'un avant-dernier étage de la version modifiée d'un réseau donné, pour former des signaux de sortie à un seul rail de la version modifiée d'un réseau donné, qui sont semblables aux signaux de sortie à un seul rail du réseau donné.

5. Le procédé de la revendication 4, comprenant en outre une étape qui consiste à élaborer un ensemble



de signaux de commande, cet ensemble comprenant une paire de signaux de commande pour chacun des commutateurs à deux rails, chaque paire de signaux de commande qui est élaborée pour un commutateur à deux rails étant conçue pour faire en sorte que pas plus d'un des signaux actifs qui sont appliqués au commutateur à deux rails, ne soit acheminé vers chacune des paires de conducteurs de sortie du commutateur à deux rails.

5

6. Un réseau pour acheminer des signaux, comprenant :

un ensemble d'éléments d'acheminement à deux rails, comprenant chacun une première paire de conducteurs d'entrée, une seconde paire de conducteurs d'entrée, une première paire de conducteurs de sortie et une seconde paire de conducteurs de sortie;

10

une première structure d'interconnexion dans laquelle

la première paire de conducteurs d'entrée de l'un des éléments d'acheminement à deux rails est connectée à une paire de conducteurs de sortie d'un autre des éléments d'acheminement à deux rails, et

15

la seconde paire de conducteurs d'entrée de l'un des éléments d'acheminement à deux rails est connectée à une paire de conducteurs de sortie d'un autre des éléments d'acheminement à deux rails;

un ensemble d'éléments d'acheminement à un seul rail, comprenant chacun une paire de conducteurs d'entrée et une paire de conducteurs de sortie;

20

une seconde structure d'interconnexion dans laquelle les conducteurs d'entrée de l'un des éléments d'acheminement à un seul rail sont connectés à des conducteurs de sortie de différents éléments parmi les éléments d'acheminement à un seul rail; et

un élément de combinaison interposé entre chaque paire de conducteurs de sortie d'un commutateur à deux rails qui transmet le signal de sortie de cette paire de conducteurs de sortie à un commutateur à un seul rail, cet élément de combinaison ayant deux entrées et une sortie.

25

7. Le réseau de la revendication 6, dans lequel l'élément de combinaison remplit une fonction logique OU.

8. Le réseau de la revendication 6, dans lequel l'élément de combinaison remplit une fonction de sélection.

30

9. Un réseau en oméga dilaté comprenant

un ensemble d'étages interconnectés, dans lequel chaque étage comprend N commutateurs de 2 x 2 qui comprennent 2 mailles d'entrée et deux mailles de sortie chacun, N étant un entier, l'interconnexion de cet étage étant constitué par des mailles qui connectent des commutateurs dans l'étage i à des commutateurs dans l'étage i+1, en désignant par i un entier, conformément à la configuration :

35

$$O(P_1P_{1-1}P_{1-2} \dots P_j \dots P_2P_1P_0)_i \rightarrow I(P_{1-1}P_{N-2} \dots P_j \dots (P_2P_1P_0)_{i+1})$$

dans laquelle I est un entier tel que $N \leq 2^I$, p_k représente le bit k+1 dans une représentation binaire d'une désignation d'une maille d'un commutateur, cette désignation étant un entier dans la plage de 0 à 2N et étant égale au double de la valeur de désignation du commutateur, et $O(P_1P_{1-1}P_{1-2} \dots P_j \dots P_2P_1P_0)_i$ désigne une maille de sortie $(P_1P_{1-1}P_{1-2} \dots P_j \dots P_2P_1P_0)$ à l'étage i, tandis que $I(P_{1-1}P_{N-2} \dots P_j \dots P_2P_1P_0)_{i+1}$ désigne une maille d'entrée $(P_{1-1}P_{1-2} \dots P_j \dots P_2P_1P_0)$ à l'étage i+1.

40

10. Un réseau en losange dilaté comprenant un ensemble d'étages interconnectés, dans lequel chaque étage comprend des commutateurs de 2 x 2 qui comportent 2 mailles d'entrée et 2 mailles de sortie chacun, l'interconnexion de cet étage comprenant des mailles qui connectent des commutateurs dans l'étage i à des commutateurs dans l'étage i+1, en désignant par i un entier, conformément à la configuration :

45

1) $O(8n+j)_i$ pour $j = 0, 1, 2, 3 \rightarrow I(8n+j-2)_i$ pour toute valeur non négative de $8n+j-2$, avec les notations suivantes : n est un entier, $O(8n+j)_i$ désigne la maille de sortie $8n+j$ dans l'étage i, et $I(8n+j-2)_i$ désigne la maille d'entrée $(8n+j-2)$ dans l'étage i;

2) $O(8n+j)_i$ pour $j = 4, 5 \rightarrow I(8n+j-2)_{i+1}$, le ternie $I(8n+j-2)_{i+1}$ désignant la maille d'entrée $8n+j-2$ dans l'étage i+1; et

50

3) $O(8n+j)_i$ pour $j = 6, 7 \rightarrow I(8n+j+2)_{i+1}$, le terme $I(8n+j+2)_{i+1}$ désignant la maille d'entrée $8n+j+2$ dans l'étage i+1.

11. Un réseau en benian dilaté comprenant

55

un ensemble d'étages interconnectés, dans lequel chaque étage comprend N commutateurs de 2 x 2 qui comprennent 2 mailles d'entrée et 2 mailles de sortie chacun, N étant un entier, l'interconnexion de cet étage comprenant des mailles qui connectent des commutateurs dans l'étage i à des commutateurs dans l'étage i+1, en désignant par i un entier, conformément à la configuration :



$$O(P_1 P_{i-1} \dots P_{j+2} P_{j+1} \dots P_1 P_0)_i \rightarrow I(P_1 P_{i-1} \dots P_{j+2} P_0 \dots P_1 P_{j+1})_{i+1}$$

dans laquelle i est un entier tel que $N \leq 2^i$, p_k représente le bit $k+1$ dans une représentation binaire d'une désignation d'une maille d'un commutateur, cette désignation étant un entier dans la plage de 0 à $2N$ et étant égale au double de la valeur de la désignation du commutateur, et $O(P_1 P_{i-1} \dots P_{j+2} P_{j+1} \dots P_1 P_0)_i$ désigne une maille de sortie $(P_1 P_{i-1} \dots P_{j+2} P_{j+1} \dots P_1 P_0)$ à l'étage i , tandis que $I(P_1 P_{i-1} \dots P_{j+2} P_0 \dots P_1 P_{j+1})_{i+1}$ désigne une maille d'entrée $(P_1 P_{i-1} \dots P_{j+2} P_0 \dots P_1 P_{j+1})$ à l'étage $i+1$.

12. Un réseau matriciel connecté en treillis, comprenant un ensemble de commutateurs de 2×2 interconnectés qui comportent 2 mailles d'entrée et 2 mailles de sortie chacun, disposés en une matrice de lignes et de colonnes, l'interconnexion de ces commutateurs comprenant des mailles qui connectent chaque commutateur dans la ligne i et la colonne j , en désignant par i et j des entiers, à un commutateur dans la ligne $i+1$ et la colonne j avec une paire de mailles, et à un commutateur dans la ligne i et la colonne $j+1$ avec une paire de mailles.