

Description

This invention relates to a fluid flow meter for measuring the flow of liquids and operating on the fluidic oscillator principle.

It is well known that the frequency of oscillation of a fluidic oscillator is dependent (though not necessarily linearly) on the quantity of flow through it. This has been proposed as a basis for flow measurement, both of liquids and of gases. However it is by no means a straightforward matter, especially where the measurement is to be accurate within one or two per cent over a wide range, and where the pressure of the fluid may vary substantially. An example of a fluidic oscillator is shown in EP-A-0251627 but this document does not give any detailed guidance on how the oscillations within the oscillator can be detected.

One way of detecting the oscillations has, in previous proposals, been by the use of pressure sensors or thermal sensors. The pressure sensors may operate electromagnetically, for example by responding to the movement of a captive ball oscillated in a channel or slot placed between the two fluid channels.

A particular problem arises in the metering of water consumption, where it may be required to maintain the accuracy of measurement over a turn-down ratio of as much as 200 to 1. Whereas in such a case the velocity will change over a corresponding range of 200 to 1, the pressure fluctuations to be sensed will, over the same range of flow, change by a factor of 40,000 to 1. It is almost impossible to maintain any degree of accuracy over such a wide range of pressure-sensing using a single pressure sensor.

Accordingly it is desirable to sense the oscillations not by means that respond to pressure, but by some means in which the amplitude of the signal is dependent on the velocity, rather than the pressure, of the changes in fluid conditions, so that the dynamic range of the sensing signal is only of the same order as that of the fluid flow.

It is known from e.g. FR-A-2448709, US-A-3878715 and Patent Abstracts of Japan vol.9 no.253 (P-395) (1976) and JP-A-60104222 and vol.9 no.64 (P-343) (1978) or JP-A- 59198317 to use electromagnetic sensors in vortex flow meters.

A further drawback of the known proposals is that they generally require external power for the sensing means, at least where these means are electric.

At the same time there is a strong incentive to replace the existing mechanical water meters, which have wearing parts and are open to corrosion as well as wear, and furthermore, with the increasing need for telemetry of the readings, they require the fitting of separate electric detecting means such as reed switches to produce an electric signal that can be further handled. Such switches involve an external power supply and a separate electrical equipment box alongside and separate from the mechanical meter.

A further drawback of the known mechanical meters is the lack of linearity at low flow rates, such as arise in domestic use, mainly as a result of 'stiction' of the moving parts.

An aim of the invention is therefore to provide a improved form of fluidic oscillator flow meter capable of handling a very wide turn-down range and requiring minimum power. Another aim is to achieve adequate linearity over the full range without requiring complex correction circuits or look-up tables.

According to the invention there is provided a meter for measuring the flow of electrically conducting liquids and capable of operating as a domestic water supply meter comprising a feedback fluidic oscillator of the kind having an inlet jet, an entry channel, a splitter dividing flow from the entry channel into first and second main channels, a feedback channel leading from each main channel to respective opposing sides of the entry channel wherein there is further provided means comprising at least one permanent magnet for producing a magnetic field across a channel in which the flow varies at a frequency dependent on the flow, a first pair of electrodes placed to detect the resultant potential difference generated in the liquid in a direction transverse to the flow and to the magnetic field, and means for measuring the frequency of that potential difference and/or counting the cycles of oscillation of the flow.

The invention has application in the metering of domestic water supplies, which involves large turn-down ratios and in which the accuracy of measurement has to meet certain statutory requirements. Other advantages of the invention for this particular purpose are low cost, no maintenance (since there are no moving parts within the fluid flow) and minimal power requirements. There is in fact no need for any power for the sensor itself, since the e.m.f. is generated by the electromagnetic inductive effect, so the only power required is that for whatever means are involved in amplifying and handling the generated signal.

According to a further feature of the invention there are at least two pairs of electrodes, and they can be connected in push-pull effectively to double the signal, and by connecting them differentially errors can be eliminated, for example due to changes in electrochemical potentials on the electrodes due to static pressure fluctuations. They may be in the main flow paths or the feedback paths or both.

The fluidic oscillator may be of a generally known kind, although preferably the splitter is a transverse wall rather than a knife-edge, as this is found to give better reliable oscillation over the wide range of flows involved.

Permanent magnets generating a magnetic field or fields (thus involving no power supplies) may be moulded into the casing of the oscillator during manufacture. If the magnets are made of an electrically

non-conducting material such as plastics-bonded ferrite, their faces can form part of the walls of the channels, thus keeping the magnetic gaps as small as possible.

According to a further aspect of the invention, which may also be applied to fluidic flow meters using sensing means other than the electromagnetic means described above, linearity, particularly at very low flows, is improved by a modification of the inlet nozzle such that instead of being of the usual rectangular cross-section, it is widened at the top or bottom, or both (the terms top and bottom being defined when thinking of the plane of symmetry of the oscillator as vertical). The widening may be of a step-like nature and give the overall cross-section the profile of a T or a I, as will become clear later.

An example of a fluidic oscillator flow meter suitable for metering domestic water supplies is illustrated in the accompanying drawings, in which:-

Figure 1 is longitudinal section through the meter on its main axis;

Figure 2 is a transverse section on the line A-A in Figure 1;

Figure 3 is a transverse section on the line B-B in Figure 1;

Figure 4 is a transverse section on the line C-C in Figure 1;

Figure 5 is a transverse section on the line D-D in Figure 1, showing a modification.

Figure 6 is a graph of oscillator frequency against flow, showing the results of calibration tests and illustrating the advantages of the modification in Figure 5.

The fluidic oscillator illustrated in Figure 1 is of a basically known kind, with body 1 containing an inlet jet 2 of rectangular cross-section leading into a pair of channels 3 and 4 separated by a splitter 5 which in this case is a flat wall transverse to the flow. Feedback loops 6 and 7 from the main channels lead back to opposite sides of the path of the fluid adjacent to the inlet jet 1. As is well-known, the flow of fluid will attach itself to the wall of one of the channels by the Coanda effect, but then as a result of the action of the fluid fed back, it will switch across to the other wall, repeatedly switching back and forth at a frequency dependent upon the rate of flow. This is a so-called feedback oscillator. Another kind known is a relaxation oscillator, the operation of which is analogous to an electronic free-running flip-flop or relaxation oscillator, but the present invention is applicable primarily to a feedback oscillator, as the known relaxation oscillators are less stable.

In a typical case the frequency may vary over a range of 0.15 to 30 Hz for a flow range from .15 litres a minute to 30 litres per minute, assuming the dimensions and characteristics are such as to produce 60 cycles for every litre of water that passes.

To achieve the sensing according to the invention

we mount permanent magnets in the walls of the channels to produce magnetic fields crossing the paths of flow of the water. In the simplest version it would be sufficient to have a single field in a single channel, but in practice, for the reasons given below, there is more than one.

Magnets 8 and 9 form part of the walls of the channels 3 and 4 respectively. Between them they produce a field across both channels and as the flow of water switches from one channel to the other the change in velocity in the water in each channel in turn produces an e.m.f. perpendicular to the flow and to the field, this e.m.f. being detected in the channel 3 by a pair of electrodes 10 and in channel 4 by a pair of electrodes 11, the disposition of these being shown in Figure 3.

It will be appreciated that the voltages appearing across the two pairs of electrodes will alternate and so if they are connected in a push-pull circuit a signal of double amplitude will be obtained.

In the example illustrated we also have further pairs of magnets 12 and 13 producing fields across the feedback loops 6 and 7 and the resulting e.m.f.s are picked up by pairs of electrodes 14 and 15. These may be used instead of those in the main channel, i.e. it is not necessary to have both sets, but by providing both and then measuring the ratio of the magnitudes of these two signals, it is possible to compensate, at least to a first order, for non-linearities in the meter factor as a function of flowrate.

The magnets may be of a known commercially available kind, for example samarium-cobalt, but as these sintered magnets are electrically conducting it is necessary to insulate them from the actual water in the channels to prevent them short-circuiting the e.m.f.s. generated. If the body 1 of the meter is of moulded plastics this is not difficult, as the plastics material can be moulded around the magnets, but it means that the magnetic gaps are wider than necessary, making the fields that much weaker. We therefore prefer to use an electrically insulating magnetic material such as a plastics-bonded ferrite, and expose the magnets to the flow, making the magnetic gaps equal to the width of the fluid channels.

If a greater field strength is required than can be produced by individual spaced magnets one could use semi-closed magnetic circuits, i.e. horseshoe magnets or externally placed magnets with pole shoes placed in the positions of the magnets shown in the drawings. The whole of the region between each main channel and the adjacent feedback loop may be formed by a magnet.

In the feedback loops the line joining the electrodes is in the middle of the flow path, but in the main channels it is as close as possible to the wall, as shown in Figure 3. The voltage generated in the feedback loop, tends to be smaller than that generated in the main channel because although there is a stron-

ger field than in the main jet resulting from a shorter flux path, the velocity of the main jet is significantly higher than the velocity of fluid in the feedback loop. Shorting of the induced signal in the main jet means that the e.m.f.s. generated in the main jet are typically greater than those induced in the feedback loop only by a factor 2.

In the example illustrated there are also electrodes 16 and magnetic fields produced by magnets 17 and 18 in the exit path for the fluid. The central magnet 18 forms a divider that keeps the two paths still separate at this point. However this is only a possible alternative to the sensors in the main channels and/or feedback loops, and it is generally not necessary to provide all three sets of electrodes simultaneously. Indeed, as indicated earlier, a single field and a single pair of electrodes is sufficient to put the invention into practice.

As will be seen in Figures 2 and 3 the signals from the two feedback loops are fed to the inverting and non-inverting inputs of a differential amplifier, effectively connecting them in push-pull, and those from the main channels are connected to another operational amplifier. The outputs from these amplifiers may be combined in whatever appears to be the best way, for example the ratio between them is a signal which is independent of many external factors.

The further processing of the signals need not concern us here; suffice it to say that we obtain signals of as large initial amplitude as possible (it is typically of the order of 2 to 400 microvolts) and measure its frequency as an indication of the rate of flow and/or we count the total number of cycles over a period to give a measure of the total flow. If the relationship between the frequency and the rate of flow is not sufficiently linear over the required range the instrument may be calibrated and the result of the calibration may be used to programme a correction circuit, in effect a series of look-up tables, through which the signal is passed to produce a final figure representing fluid flow. This can be incorporated in a microchip which can be mounted in or on the casing of the instrument, and the whole instrument is self-contained, complete with its electrical data-recording provisions. As the signal from the electrodes is generated by the flow itself, no external source of voltage is needed for this, and the only power supply that is required is that necessary for the signal-handling circuits. This very low requirement can be handled by a battery mounted on the instrument and having a useful life measured in years.

However, the use of correction circuits is undesirable and it is better, if possible, to achieve linearity over the desired range directly by the inherent design. Figure 6 is a graph of calibration tests in which the number of pulses or cycles per litre of flow is plotted against the rate of flow. The horizontal scale is logarithmic covering from 0.001 litres per second to 1 litre

per second. Ideally the points should lie on a single horizontal line. The graph reveals that with a jet 3mm wide, at least for flows greater than 0.05 litres per second, the pulse rate per litre is within 2% of a mean figure of 68.165, but at lower flow rates it falls off badly to around 57 pulses per litre at a flow rate of around 0.0035 litres per second. It must be remembered here that we are concerned solely with the frequency of the fluidic oscillator, and this has nothing to do with the manner in which it is detected, whether it be electromagnetic (such as described earlier) or one of the known ways.

Figure 5 shows a possible way which has been found to improve the linearity of response, in particular at low flow rates. Instead of the inlet jet being of plain rectangular cross-section, it is broadened out at the top and bottom to form an I section; it may be sufficient to broaden it only at one end. At the same time its width may be decreased. Figure 6 shows the substantial improvement obtained with a jet which is 2mm wide but has lateral slots top and bottom in the manner shown in Figure 5. The response is linear to within 2% down to .004 litres per second and to within 5% right down to 0.003 litres per second.

The reason for this improvement is not at present fully understood, but it is believed that at low flowrates the paths on the top and bottom of the jet provide a source of additional flow to that in the feedback loop to cause the jet to switch. At higher flowrates the impedance of the paths on the top and bottom of the jet to fluctuating flows are such that the path cannot provide the additional flow. This mechanism has the effect of increasing the switching rate at low flows.

Claims

1. A meter for measuring the flow of electrically conducting liquids and capable of operating as a domestic water supply meter comprising a feedback fluidic oscillator of the kind having an inlet jet (2), an entry channel, a splitter (5) dividing flow from the entry channel into first and second main channels (3,4), a feedback channel leading from each main channel to respective opposing sides of the entry channel (2) characterised in that there is further provided means (8,9,12,13, 17,18) comprising at least one permanent magnet for producing a magnetic field across a channel in which the flow varies at a frequency dependent on the flow, a first pair of electrodes (10,11,14,15,16) placed to detect the resultant potential difference generated in the liquid in direction transverse to the flow and to the magnetic field, and means for measuring the frequency of that potential difference and/or counting the cycles of oscillation of the flow.



ger field than in the main jet resulting from a shorter flux path, the velocity of the main jet is significantly higher than the velocity of fluid in the feedback loop. Shorting of the induced signal in the main jet means that the e.m.f.s. generated in the main jet are typically greater than those induced in the feedback loop only by a factor 2.

In the example illustrated there are also electrodes 16 and magnetic fields produced by magnets 17 and 18 in the exit path for the fluid. The central magnet 18 forms a divider that keeps the two paths still separate at this point. However this is only a possible alternative to the sensors in the main channels and/or feedback loops, and it is generally not necessary to provide all three sets of electrodes simultaneously. Indeed, as indicated earlier, a single field and a single pair of electrodes is sufficient to put the invention into practice.

As will be seen in Figures 2 and 3 the signals from the two feedback loops are fed to the inverting and non-inverting inputs of a differential amplifier, effectively connecting them in push-pull, and those from the main channels are connected to another operational amplifier. The outputs from these amplifiers may be combined in whatever appears to be the best way, for example the ratio between them is a signal which is independent of many external factors.

The further processing of the signals need not concern us here; suffice it to say that we obtain signals of as large initial amplitude as possible (it is typically of the order of 2 to 400 microvolts) and measure its frequency as an indication of the rate of flow and/or we count the total number of cycles over a period to give a measure of the total flow. If the relationship between the frequency and the rate of flow is not sufficiently linear over the required range the instrument may be calibrated and the result of the calibration may be used to programme a correction circuit, in effect a series of look-up tables, through which the signal is passed to produce a final figure representing fluid flow. This can be incorporated in a microchip which can be mounted in or on the casing of the instrument, and the whole instrument is self-contained, complete with its electrical data-recording provisions. As the signal from the electrodes is generated by the flow itself, no external source of voltage is needed for this, and the only power supply that is required is that necessary for the signal-handling circuits. This very low requirement can be handled by a battery mounted on the instrument and having a useful life measured in years.

However, the use of correction circuits is undesirable and it is better, if possible, to achieve linearity over the desired range directly by the inherent design. Figure 6 is a graph of calibration tests in which the number of pulses or cycles per litre of flow is plotted against the rate of flow. The horizontal scale is logarithmic covering from 0.001 litres per second to 1 litre

per second. Ideally the points should lie on a single horizontal line. The graph reveals that with a jet 3mm wide, at least for flows greater than 0.05 litres per second, the pulse rate per litre is within 2% of a mean figure of 68.165, but at lower flow rates it falls off badly to around 57 pulses per litre at a flow rate of around 0.0035 litres per second. It must be remembered here that we are concerned solely with the frequency of the fluidic oscillator, and this has nothing to do with the manner in which it is detected, whether it be electromagnetic (such as described earlier) or one of the known ways.

Figure 5 shows a possible way which has been found to improve the linearity of response, in particular at low flow rates. Instead of the inlet jet being of plain rectangular cross-section, it is broadened out at the top and bottom to form an I section; it may be sufficient to broaden it only at one end. At the same time its width may be decreased. Figure 6 shows the substantial improvement obtained with a jet which is 2mm wide but has lateral slots top and bottom in the manner shown in Figure 5. The response is linear to within 2% down to .004 litres per second and to within 5% right down to 0.003 litres per second.

The reason for this improvement is not at present fully understood, but it is believed that at low flowrates the paths on the top and bottom of the jet provide a source of additional flow to that in the feedback loop to cause the jet to switch. At higher flowrates the impedance of the paths on the top and bottom of the jet to fluctuating flows are such that the path cannot provide the additional flow. This mechanism has the effect of increasing the switching rate at low flows.

Claims

1. A meter for measuring the flow of electrically conducting liquids and capable of operating as a domestic water supply meter comprising a feedback fluidic oscillator of the kind having an inlet jet (2), an entry channel, a splitter (5) dividing flow from the entry channel into first and second main channels (3,4), a feedback channel leading from each main channel to respective opposing sides of the entry channel (2) characterised in that there is further provided means (8,9,12,13, 17,18) comprising at least one permanent magnet for producing a magnetic field across a channel in which the flow varies at a frequency dependent on the flow, a first pair of electrodes (10,11,14,15,16) placed to detect the resultant potential difference generated in the liquid in direction transverse to the flow and to the magnetic field, and means for measuring the frequency of that potential difference and/or counting the cycles of oscillation of the flow.



2. A meter according to claim 1 characterised in that the electrodes (10,11,16) are placed in one of the main channels.
3. A meter according to claim 1 characterised in that the electrodes (14,15) are placed in at least one of the feedback channels.
4. A meter according to any one of claims 1 to 3 characterised in that a second pair of electrodes is placed in a second of the channels which second channel also has a magnetic field across it.
5. A meter according to claim 4 characterised in that the first and second pairs of electrodes detect the potential differences in channels in which the flow changes in opposite senses and the pairs of electrodes are connected in a push-pull circuit.
6. A meter according to any one of claims 1 to 5 characterised in that the magnet is embedded in the walls of the casing of the meter and is electrically insulated from fluid flowing in any one of the channels.
7. A meter according to any one of claims 1-5 characterised in that the magnet is formed of electrically non-conducting material and forms part of one of the channels.
8. A meter according to any one of claims 1 to 7 characterised in that the cross-section of the inlet jet is generally rectangular and is broadened out laterally at least on one end to form a T-shaped or I-shaped cross-section.

Patentansprüche

1. Meßgerät zum Messen des Stroms elektrisch leitender Flüssigkeiten und ein betreibbar als Haushalts-Wasserzähler, umfassend: einen Rückkopplungs-Fluidoszillator der Art, die eine Einlaßdüse (2), einen Eintrittskanal, einen Aufspalter(5), der den Strom von dem Eintrittskanal in einen ersten und einen zweiten Hauptkanal (3,4) aufteilt, und einen von jedem Hauptkanal zu entsprechenden gegenüberliegenden Seiten des Eintrittskanals (2) führenden Rückkopplungskanal aufweist, dadurch gekennzeichnet, daß weiterhin mindestens einen Permanentmagneten aufweisende Mittel (8, 9, 12, 13, 17, 18) vorgesehen sind, um ein Magnetfeld über einem Kanal zu erzeugen, in welchen der Strom mit einer von dem Strom abhängigen Frequenz variiert, wobei ein erstes Paar von Elektroden (10, 11, 14, 15, 16) angeordnet ist, um die sich ergebende Potentialdifferenz zu erfassen, die in der Flüssigkeit in

einer Richtung quer zu dem Strom und zu dem Magnetfeld erzeugt wird und Mittel vorgesehen sind zum Messen der Frequenz der Potentialdifferenz und/oder zum Zählen der Schwingungszyklen des Stroms.

2. Meßgerät nach Anspruch 1, dadurch gekennzeichnet, daß die Elektroden (10, 11, 16) in einem der Hauptkanäle angeordnet sind.
3. Meßgerät nach Anspruch 1, dadurch gekennzeichnet, daß die Elektroden (14, 15) in mindestens einem der Rückkopplungskanäle angeordnet sind.
4. Meßgerät nach irgendeinem der Ansprüche 1 - 3 dadurch gekennzeichnet, daß ein zweites Paar von Elektroden in einem zweiten der Kanäle angeordnet ist, wobei der zweite Kanal ebenfalls quer zu sich ein Magnetfeld aufweist.
5. Meßgerät nach Anspruch 4, dadurch gekennzeichnet, daß das erste und das zweite Paar von Elektroden die Potentialdifferenzen in Kanälen erfassen, in welchen sich der Strom gegensinnig ändert, und daß die Paare von Elektroden in Form einer Gegentaktschaltung verschaltet sind.
6. Meßgerät nach irgendeinem der Ansprüche 1 - 5, dadurch gekennzeichnet, daß der Magnet in den Wänden des Gehäuses des Meßgerätes eingebettet und elektrisch von dem in irgendeinem der Kanäle strömenden Fluid isoliert ist.
7. Meßgerät nach irgendeinem der Ansprüche 1-5, dadurch gekennzeichnet, daß der Magnet aus elektrisch nicht-leitenden Material gebildet ist und einen Teil eines der Kanäle bildet.

Revendications

1. Appareil de mesure servant à mesurer l'écoulement de liquides électriquement conducteurs et apte à fonctionner en tant que compteur d'eau domestique, comprenant un oscillateur fluide à réaction du type comportant une tuyère d'entrée (2), un canal d'entrée, un diviseur (5) divisant l'écoulement provenant du canal d'entrée pour l'introduire dans des premier et second canaux principaux (3, 4), un canal de réaction raccordant



- chaque canal principal à des côtés opposés respectifs du canal d'entrée (2), caractérisé en ce qu'il est en outre prévu des moyens (8,9, 12,13,17,18) comprenant au moins un aimant permanent pour produire un champ magnétique en travers d'un canal, dans lequel le flux varie à une fréquence dépendant de l'écoulement, un premier couple d'électrodes (10,11,14,15, 16) disposées de manière à détecter la différence de potentiel résultante produite dans le liquide dans une direction transversale à l'écoulement et au champ magnétique, et des moyens pour mesurer la fréquence de cette différence de potentiel et/ou compter les cycles d'oscillation du flux.
2. Appareil de mesure selon la revendication 1, caractérisé en ce que les électrodes (10,11,16) sont placées dans l'un des canaux principaux.
 3. Appareil de mesure selon la revendication 1, caractérisé en ce que les électrodes (14,15) sont placées dans au moins l'un des canaux de réaction.
 4. Appareil de mesure selon l'une quelconque des revendications 1 à 3, caractérisé en ce qu'un second couple d'électrodes est placé dans un second des canaux, en travers duquel est également appliqué un champ magnétique.
 5. Appareil de mesure selon la revendication 4, caractérisé en ce que les premier et second couples d'électrodes détectent les différences de potentiel dans des canaux, dans lesquels le flux varie en des sens opposés, et les couples d'électrodes sont raccordés de manière à former un circuit push-pull.
 6. Appareil de mesure selon l'une quelconque des revendications 1 à 5, caractérisé en ce que l'aimant est enchâssé dans les parois du boîtier de l'appareil de mesure et est isolé électriquement vis-à-vis du fluide circulant dans l'un quelconque des canaux.
 7. Appareil de mesure selon l'une quelconque des revendications 1 à 5, caractérisé en ce que l'aimant est réalisé en un matériau non conducteur et fait partie de l'un des canaux.
 8. Appareil de mesure selon l'une quelconque des revendications 1 à 7, caractérisé en ce que la section transversale de la tuyère d'entrée est de forme générale rectangulaire et s'élargit latéralement à au moins une extrémité de manière à former une section transversale en forme de T ou de I.