

System for generating an analogue signal

The present invention concerns a system for generating an analog signal from various parameters. Without implying limitation, this invention can be used in the fields of telecommunications, radars, sonars and more generally of all electronic equipments, for example medical instrumentation, test benches or measurement benches.

The prior art discloses systems for which the analog signals are predetermined at the time at which the system is designed (in this case, the parameters of the signals are fixed). There are also known systems for which the analog signals are generated on request (in this case, the parameters are sent to the system in real time).

In the case of predetermined signals, the following systems are known:

- systems for generating analog signals using basic functions of ramp or logarithm type. These basic functions are obtained, by way of example, by using the knee voltage of one or more diodes,
- systems having surface acoustic wave filters (SAW), these filters being followed by frequency transposition,
- systems made up of a set of switched oscillators.

However, these solutions are not flexible and do not allow modification of the parameters of the signal that is generated. Moreover, when switched oscillators are used, the interferences between the oscillators damage the spectral purity of the generated signal.

In order to generate signals that have a predetermined form but whose parameters can evolve, it is known practice to use the following systems:

- a system having a voltage controlled oscillator (VCO). This oscillator can be followed by a phase locked loop (PLL),
- a system having a counter, a memory and a digital/analog converter, all of which is followed by a frequency transposition.

However, these systems are limited because the frequency spread band and the center frequency of the signal that is generated need to be in a limited range.

All of these devices can be integrated into a specialized programmable circuit, also known by the abbreviation “DDS” for direct digital synthesizer.

5

For signals that are not known in advance and need to be generated on request and in a very short time, the following systems are known:

10

- digital radio frequency memory (DRFM) systems, which allow an analog signal to be stored in memory and this recorded signal to be reconstructed and retransmitted. These systems are particularly used in radars for generating signals that decoy other radars. However, these systems can only generate signals with a small dynamic range, the number of bits of dynamics actually being of the order of a few bits. This order of magnitude is of the order of 1 to 6 bits according to the frequency of the signal to be generated,

15

20

- a sigma/delta converter, this type of converter being based on the principle of oversampling the input signal. This system then has a comparator using one bit to convert the difference between the input signal and the result of the conversion. The result of the comparison is used by a decimator filter, which sums the samples of the input signal. The sigma/delta converter is therefore a servosystem that uses input/output looping. This looping limits the bandwidth of the signal that can be generated.

25

It is also known practice to use a diode shaper, as shown in figure 1. In this system, a voltage ramp is sent to the terminals V_i and will generate a sinusoidal wave that is reconstructed by summation of trapezoids. However, this solution is limited in terms of frequency because the voltage to be generated, which will depend on the derivative of the voltage V_i (dV_i/dt), is limited by the production technology used.

30

35

One aim of this invention is to propose a system for generating signals that is totally reconfigurable, limits perturbations, is able to have a rapidly evolving center frequency, is able to generate large frequency spreadband signals and is able to be implemented on a hybrid

analog/digital integrated circuit. To this end, the subject of the invention is a system for generating an analog signal having:

- a set of at least two electric generators,
 - at least one capacitor ,
 - 5 - activation/deactivation means for said electric current generators;
- the electric current generating means being connected in parallel with one another and the capacitor being connected in series with the electric current generators, the activation/deactivation means controlling said generators by means of a digital stream allowing control of the intensity of
- 10 the electric current entering said capacitor and generating a trapezoidal voltage signal at the terminals of said capacitor, said analog signal being reconstructed through interpolation of said trapezoidal signal.

The system therefore provides the following advantages:

- 15 • reconfiguration is total owing to digital generation of the signals and a very short response time,
- the frequency generation is performed by a single generator and perturbations are reduced in relation to prior art systems. Thus, radio perturbations, known by the name "glitch", caused by switching are
- 20 reduced, owing to the use of first-order blockers. This makes it possible to have a reduction in spurious radiations,
- the speed of evolution of the center frequency of the generated signal is limited only by the clock speed of the activation/deactivation means. It is dependent on the technology used for implementing
- 25 these means. This makes it possible to generate a signal whose center frequency evolves from DC to microwave frequency,
- the useful dynamic is limited only by technological compromise, clock speed and bandwidth,
- the system is in open-loop form, which allows a signal having a large
- 30 frequency spreadband to be generated,
- this generation can be implemented totally in a single hybrid analog/digital integrated circuit,
- the system of the invention has low consumption because the charges of the capacitor are cumulative,
- 35 • moreover, the activation/deactivation device of the electric current generators is of serial type. This makes it possible to have a narrow data transfer bus. Finally, in order to limit the interchanged data, the system uses relative addressing, based on sending of the increase

or decrease in the charge of the capacitor, and of the value of the charge of this capacitor.

Advantageously, the activation/deactivation means are adapted
5 to determine the current generating means to be activated/deactivated from a Riemann interpolation of the analog signal to be generated.

Advantageously, the system moreover has:

- at least one transistor connected in parallel with the capacitor
10 and/or,
- at least one other electric current generating means connected in series with the capacitor,
- and means for comparing a value of a voltage at the terminals of said capacitor with a theoretical value.

15 Moreover, the transistor and/or the other generating means is/are adapted to modify the value of the voltage at the terminals of said capacitor when it is different than the theoretical value.

Advantageously, the system is moreover characterized in that it
20 is integrated on one and the same chip or an integrated circuit or an application-specific integrated circuit.

Advantageously, the system is moreover characterized in that
25 the capacitor is made up of a capacitor of a transistor belonging to the input stage of a power amplifier.

The invention will be better understood and other advantages
will emerge upon reading the detailed description provided by way of
nonlimiting example and with reference to the figures, among which:

- 30 - figure 1 presents a system that is known in the prior art
- figure 2 presents a first embodiment of the system presented in the invention
- figure 3 presents an embodiment of the control of the slope of the analog signal
- 35 - figure 4 presents an embodiment of a device for resetting the system.

The system, which is described in figure 2, has four electric current generators 101. These electric current generators are connected to

one another, in parallel, and are connected to a capacitor 102, which is therefore charged by this capacitor. The voltage at the terminals of the capacitor varies in accordance with the law $V = \frac{1}{C} \int I dt$. In this equation, V is the voltage (in volts) at the terminals of the capacitor, I is the intensity (in
 5 amps) of the electric current flowing through the capacitor and C is the capacitance (in farads) of the capacitor. The system also has activation/deactivation devices 103 that allow the electric current generators 101 to be activated and deactivated.

10 In this system, the intensity entering the capacitor is dependent on the number of electric current generators connected to the capacitor. Therefore, the slope of the increase in the voltage at the terminals of the capacitor is likewise dependent on this same number of generators.

15 In practice, one can afford just to dynamically vary the electric current in order to avoid the charge transfer in the capacitance. By way of example, it is possible to discharge the capacitor(s) by passing a negative current through it.

20 The activation/deactivation control 103 is provided by means of a digital stream allowing control of the intensity of the electric current entering the capacitor according to the signal to be generated. This control is effected by varying the number of intensity generators that are activated at a given instant. To this end, the digital stream controls, via suitable
 25 interfaces, the closing or opening of switches 21 that each connect a current generator 101 to the capacitor 102. The digital stream, for example of serial type, has a word defining a configuration for the switches.

Figure 3 presents this embodiment of the activation/deactivation
 30 control for the electric current generators. More particularly, it illustrates the digital stream 31, which is of serial type in this example. The serial data are encompassed by a table of correspondence 32 that presents, at the output, a word encoded using i bits, which is dependent on the serial input data and a clock cycle, these i bits controlling the transfer of current in the
 35 capacitor 102 from the current generators, each bit activating a switch to close or open. In one embodiment, the number of electric current generators is minimal and is fixed at two. In this embodiment, two slopes with opposite signs, which slopes are obtained via the two electric current generators having a different intensity, allow the analog signals to be

generated. Moreover, rapid switching between the two intensity generators allows faithful generation of the analog signal.

In another embodiment, the number of electric current generators is greater. In this embodiment, a plurality of slopes, obtained via the simultaneous activation of a plurality of electric current generators, via the digital stream, having a different intensity, allow the analog signals to be generated. In this embodiment, it is not necessary to effect rapid switching between the intensity generators in order to faithfully generate the analog signal.

10

For example, figure 3 presents different currents using power 2 values as shown in the table of correspondence.

The determination of the various slopes that the signal must successively follow (also called control law) is effected so as to minimize the gap between:

- the analog signal that there is a wish to generate
- the signal reconstructed from the use of these various slopes.

In order to effect this determination, various methods of interpolation of the signal can be set up (Riemann, Romberg, least squares, polynomials, Kalmann, etc.).

In one embodiment, it is possible to use an interpolation of Riemann type. In this case, the analog signal to be generated is modeled by a set of trapezoids representing the Riemann integral. The various slopes of the trapezoids are fixed by the value of the intensities that the combinations of the various electric current generators can deliver. This is because the voltage slopes that can be produced at the terminals of the capacitor are dependent on the intensity of the electric current I_{slope} flowing through it and on the capacitance C_{load} of the capacitor. Thus, the succession of the slopes of the voltage at the terminals of the capacitor is chosen on the basis of two criteria:

- these slopes can be produced by the system
- these slopes minimize the gap between the signal generated in this manner and the signal that there is a wish to generate.

The value of this electric current is chosen digitally from the possible values via a control word that controls the activation/deactivation of the electric current generators. A first-order blocker is obtained, which allows the value of the slope of the voltage at the terminals of the capacitor to be stored in

memory. The control words can be addressed by an addressing table, which is preprogrammed or computed dynamically. Moreover, as the high-impedance control is native, this can be accomplished by disconnecting the current generators so that the charge of the capacitor remains constant, a control word allowing cancellation of the electric current flowing through the capacitor resulting in the voltage at the terminals of the latter being maintained.

The system, which is made up of the plurality of electric current generators and the activation/deactivation device, forms a charge pump. This is because it allows the transfer of charges between the electric current generators 101 and the capacitor 102. The value of the charge in this capacitor is dependent on the value of the electric current passing through it and on the duration of this charge. Moreover, if the control law is based on the Riemann algorithm, this system is called a Riemann pump.

In an embodiment that is presented in figure 4, the system likewise has a device for compensating for the leakage electric current and for resetting. This device makes it possible to prevent the accumulation of errors that can cause the value of the charge in the capacitor to diverge. This device is asynchronous and can be produced by a transistor 401 connected in parallel with the capacitor or else an appended set of electric current generators. This system also has a device 402 for comparing a value of a voltage at the terminals of said capacitor with a theoretical value.

Compensation for slow drifts is provided by detection of the transition of the signal through known and referenced levels. Transitions to these levels prompt the system to compare the voltage with a theoretical value and to make the corrections to return to the setpoint value through successive increments. Thus, every transition through zero prompts the content of the capacitor to be reset in order to prevent any drift (offset).

Equally, it is possible to correct slope errors by modifying the control law generated by the device for activating/deactivating the electric current generators. If the control law is optimized, the errors will be minimal. It is then possible to predetermine the corrections by means of control extrapolations.

To prevent capacitor discharges and hence overheating, it is possible to take two capacitors and to interchange the capacitors on each

transition, the value of the charge of the capacitor off line being brought back to the reference value by a service circuit.

5 In one embodiment, the capacitor 102 is made up by the capacitor of a transistor belonging to the input stage of a power amplifier. In this case, the signal generated by the system has, directly, a high power of a few hundred milliwatts.

10 In one embodiment, the system is integrated on one and the same chip, an integrated circuit or an application-specific integrated circuit or "ASIC". The system is integrated in a chip with technology suited to the conditions of use. For example, it is possible to use:

- SiGe or CMOS for low-cost production of a large number of units
- 15 - GaN for quickness, robustness and the possibility of having a high-power output signal.

CLAIMS

1. A system for generating an analog signal having at least:
 - a set of at least two electric current generators (101)
 - 5 - at least one capacitor (102)
 - activation/deactivation means (103) for said electric current generators (101);

the electric current generating means being connected in parallel with one another and the capacitor being connected in series with the electric

- 10 current generators, the activation/deactivation means controlling said generators (101) by means of a digital stream allowing control of the intensity of the electric current entering said capacitor (102) and generating a trapezoidal voltage signal at the terminals of said capacitor, said analog signal being reconstructed through interpolation of said trapezoidal signal.
- 15
- 2. The system as claimed in claim 1, in which said interpolation is of Riemann type.
- 3. The system as claimed in claim 1 or 2, moreover having:
 - 20 - at least one transistor (401) connected in parallel with the capacitor and/or
 - at least one other electric current generating means (402) connected in series with the capacitor
 - and means for comparing a value of a voltage at the terminals of said
 - 25 capacitor with a theoretical value;

said transistor and/or said other generating means being adapted to modify said value of the voltage at the terminals of said capacitor when it is different than said theoretical value.

- 30
- 4. The system as claimed in one of claims 1 to 3, moreover characterized in that it is integrated on one and the same chip or an integrated circuit or an application-specific integrated circuit.
- 5. The system as claimed in one of claims 1 to 4, moreover characterized
- 35 in that said capacitor (102) is made up of a capacitor of a transistor belonging to the input stage of a power amplifier.