

Description

This invention relates to the control of cathode ray tubes (CRT's) and particularly, though not exclusively, to the control of CRT's in colour television receivers.

In use of CRT's and particularly colour CRT's the voltages and currents required to be applied to a CRT change both in the course of a single session of use (e.g. as the CRT "warms up") and during the life of the CRT as it ages. Thus it is desirable to monitor these signals while the CRT is in operation and adjust signals accordingly.

It is known to use such automatically adjusting loops to set the level of the tube cathode current at which the tube is nominally considered to be cut-off. However, such known loops may result in impractical cathode voltages.

It is an object of this invention to provide a circuit for controlling a cathode ray tube wherein the above-mentioned disadvantage may be overcome or at least alleviated.

In accordance with the invention, a circuit for controlling a cathode ray tube comprises:

control means for operatively monitoring tube parameters and adjusting the nominal cut-off level of the tube cathode current accordingly; and

means for sensing when the control means is near an extreme of its range of adjustment and

means responsive to the sensing means for changing a control signal applied to a grid of the tube so as to bring the nominal cut-off level control loop within its range of adjustment.

Preferably the changing means is arranged to change the voltage applied to the G_2 grid of the tube.

Preferably the changing means comprises a shunt feedback regulator connected in parallel with the voltage applied to the G_2 grid.

The shunt feedback regulator may be a high voltage transistor with resistive shunt feedback or preferably a low voltage transistor with a cascode high high voltage thyristor or triac.

One control circuit in accordance with the invention for controlling a cathode ray tube will now be described, by way of example only, with reference to the accompanying drawing, which is a schematic block diagram of the circuit.

Referring now to the drawing, the control circuit includes a differential amplifier comparator arrangement 2 for operatively monitoring the cathode voltage V_K of the cathode ray tube and for determining during the flyback period whether the cathode voltage is too low or too high.

The arrangement 2 provides two outputs respectively indicating that the cathode voltage is too high or too low with respect to predetermined reference voltages V_{REF1} and V_{REF2} . The two outputs of the monitoring arrangement 2 are connected to an up/down counter 4 to increment the counter up or down respectively. The count of the counter 4 is applied in parallel as a multi-bit word to a digital-to-analog converter 6. The D/A converter 6 provides at its output a voltage which is representative of the required nominal cut-off

level of the tube cathode current. The output of the D/A converter 6 is applied to tube cathode current generating circuitry (not shown).

The output of the D/A converter 6 is also applied to a differential amplifier comparator arrangement 7. The comparator arrangement 7 detects when the output of the D/A converter 6 is outside of a predetermined range with respect to predetermined reference voltages V_{REF3} and V_{REF4} . This predetermined range is chosen so as to include substantially all of the range of adjustment provided by the up/down counter 4.

The comparator arrangement 7 provides two outputs respectively indicating that the present level of the cathode voltage V_K is above or below the range of adjustment provided by the up/down counter 4. The two outputs of the comparator arrangement 7 are connected to an up/down counter 8 to increment the counter up and down respectively. The count of the counter 8 is applied as a multi-bit word to a digital-to-analog converter 9. The output of the digital-to-analog converter 9 is connected to the control input of a shunt feedback regulator 24. The shunt feedback regulator 24 includes a low voltage transistor 10. The base of transistor 10 is also connected via a current source S to ground. The emitter of transistor 10 is connected to ground and the collector of transistor 10 is connected via a thyristor 12 and resistors 14 and 16 to a source of high voltage supply V_H , typically 8 KV. The base of the transistor 10 is also connected via resistors 18 and 20 to the mid-point of the resistors 14 and 16. The mid-point of resistors 14 and 16 is also connected via a capacitor 22 to ground. The mid-point of resistors 14 and 16 is also connected to the G_2 electrode of the cathode ray tube.

Thus when the comparator arrangement 7 detects that the adjustment loop 2, 4, 6 is near an extreme of its range of adjustment, the comparator produces an output which accordingly controls the conduction of the transistor 10. In this way the voltage V_{G_2} is changed so as to bring the required nominal cut-off voltage level of the tube drive current back towards the centre of the range of adjustment of the adjustment loop 2, 4, 6.

It will be appreciated that the cascode arrangement of thyristor 12 and low voltage transistor 10 provides a simple, low cost alternative to using a single high power transistor as a shunt stabiliser for V_{G_2} . It will, of course, be understood that a triac or a similar component may be used in place of the thyristor 12.

It will also be appreciated that in practice the functions of the up/down counters 4 and 8, and possibly also the functions of the D-to-A converters 6 and 9, may be collectively performed within a microprocessor (not shown).

It will also be appreciated that in a variant of the above described control circuit, instead of optimising the level of the cathode voltage V_K so as to lie in the centre of the range of adjustment provided by the up/down counter 4, the cathode voltage V_K may alternatively be optimised so as to be just within an extreme of its adjustment range

so as to optimise tube performance in other known ways, for example, by setting VG_2 near to its maximum to give good focus of the tube.

It will also be appreciated that although the control circuit has been described above with reference to control of the voltage applied to the G_2 grid of the tube, the voltages applied to the other grids of the tube may alternatively or additionally controlled in accordance with the invention if so desired.

It will also be appreciated that substantially all of the (with the possible exception of the high voltage devices which may be more conveniently provided discretely) above described circuit may conveniently be incorporated in an integrated circuit device.

Claims

1. A circuit for controlling a cathode ray tube comprising:

control means (2, 4, 6) for operatively monitoring tube parameters and adjusting the nominal cut-off level of the tube cathode current accordingly; and

means (7) for sensing when the control means is near an extreme of its range of adjustment and

means (8, 9, 24) responsive to the sensing means for changing a control signal applied to a grid of the tube so as to bring the nominal cut-off level control loop within its range of adjustment.

2. A circuit according to claim 1 wherein the changing means is arranged to change the voltage applied to the G_2 grid of the tube.

3. A circuit according to claim 1 or 2 wherein the changing means comprises a shunt feedback regulator connected in parallel with the voltage applied to the G_2 grid.

4. A circuit according to claim 3 wherein the shunt feedback regulator comprises a low voltage transistor with a cascode high voltage thyristor.

5. A circuit according to claim 3 wherein the shunt feedback regulator comprises a low voltage transistor with a cascode high voltage triac.

6. A circuit according to any preceding claim wherein the changing means is so arranged as to bring the nominal cut-off level control loop to substantially an extreme of its range of adjustment.

7. An integrated circuit incorporating a circuit substantially according to any preceding claim.

Patentansprüche

1. Schaltungsanordnung zur Steuerung einer Kathodenstrahlröhre, enthaltend:

eine Steuerungseinrichtung (2, 4, 6) zum wirkungsmäßigen Überwachen von Röhrenparametern und zum entsprechenden Einstellen des nominalen Begrenzungspegels des Röhrenkathodenstroms; und

eine Einrichtung (7) zum Ermitteln, wenn die Steuerungseinrichtung nahe einem Extremwert ihres Einstellbereichs ist, und

eine Einrichtung (8, 9, 24), die auf die Ermitt-

lungseinrichtung anspricht, um ein Steuersignal zu verändern, das einem Gitter der Röhre zugeführt wird, um die Nominalbegrenzungspegel - Regelschleife in ihren Einstellbereich zu bringen.

2. Schaltungsanordnung nach Anspruch 1, bei der die Änderungseinrichtung dazu eingerichtet ist, die dem G_2 -Gitter der Röhre zugeführte Spannung zu ändern.

3. Schaltungsanordnung nach Anspruch 1 oder 2, bei der die Änderungseinrichtung einen Nebenschlußrückkopplungsregler enthält, der zu der Spannung parallel geschaltet ist, die dem G_2 -Gitter zugeführt ist.

4. Schaltungsanordnung nach Anspruch 3, bei der der Nebenschlußrückkopplungsregler einen Niederspannungstransistor mit einem Kaskode - Hochvoltthyristor enthält.

5. Schaltungsanordnung nach Anspruch 3, dadurch gekennzeichnet, daß der Nebenschlußrückkopplungsregler einen Niedervolttransistor mit einem Kaskode - Hochvolttriac enthält.

6. Schaltungsanordnung nach einem der vorhergehenden Ansprüche, bei der die Änderungseinrichtung dazu eingerichtet ist, die Nominalbegrenzungspegel - Regelschleife auf im wesentlichen einen Extremwert ihres Einstellbereichs zu bringen.

7. Integrierte Schaltung, die eine Schaltungsanordnung im wesentlichen nach einem der vorhergehenden Ansprüche enthält.

Revendications

1. Circuit permettant de commander un tube à rayons cathodiques, comprenant:

un moyen de commande (2, 4, 6) servant à fonctionnellement contrôler des paramètres du tube et à ajuster le niveau de coupure nominal du courant cathodique du tube en conséquence; et

un moyen (7) servant à déterminer le moment où le moyen de commande est proche d'une extrémité de son intervalle de réglage, et

un moyen (8, 9, 24) répondant au moyen de détermination en changeant un signal de commande appliqué à une grille du tube de manière à amener la boucle de commande du niveau de coupure nominal à l'intérieur de son intervalle de réglage.

2. Circuit selon la revendication 1, où le moyen de changement est conçu pour changer la tension appliquée à la grille G_2 du tube.

3. Circuit selon la revendication 1 ou 2, où le moyen de changement comprend un régulateur de réaction en shunt qui est connecté en parallèle avec la tension appliquée à la grille G_2 .

4. Circuit selon la revendication 3, où le régulateur de réaction en shunt comprend un transistor basse tension associé à un thyristor haute tension en cascode.

5. Circuit selon la revendication 3, où le régulateur de réaction en shunt comprend un transistor basse tension associé à un triac haute tension en cascode.

6. Circuit selon l'une quelconque des revendications précédentes, où le moyen de changement

so as to optimise tube performance in other known ways, for example, by setting V_{G2} near to its maximum to give good focus of the tube.

It will also be appreciated that although the control circuit has been described above with reference to control of the voltage applied to the G_2 grid of the tube, the voltages applied to the other grids of the tube may alternatively or additionally controlled in accordance with the invention if so desired.

It will also be appreciated that substantially all of the (with the possible exception of the high voltage devices which may be more conveniently provided discretely) above described circuit may conveniently be incorporated in an integrated circuit device.

Claims

1. A circuit for controlling a cathode ray tube comprising:

control means (2, 4, 6) for operatively monitoring tube parameters and adjusting the nominal cut-off level of the tube cathode current accordingly; and

means (7) for sensing when the control means is near an extreme of its range of adjustment and means (8, 9, 24) responsive to the sensing means for changing a control signal applied to a grid of the tube so as to bring the nominal cut-off level control loop within its range of adjustment.

2. A circuit according to claim 1 wherein the changing means is arranged to change the voltage applied to the G_2 grid of the tube.

3. A circuit according to claim 1 or 2 wherein the changing means comprises a shunt feedback regulator connected in parallel with the voltage applied to the G_2 grid.

4. A circuit according to claim 3 wherein the shunt feedback regulator comprises a low voltage transistor with a cascode high voltage thyristor.

5. A circuit according to claim 3 wherein the shunt feedback regulator comprises a low voltage transistor with a cascode high voltage triac.

6. A circuit according to any preceding claim wherein the changing means is so arranged as to bring the nominal cut-off level control loop to substantially an extreme of its range of adjustment.

7. An integrated circuit incorporating a circuit substantially according to any preceding claim.

Patentansprüche

1. Schaltungsanordnung zur Steuerung einer Kathodenstrahlröhre, enthaltend:

eine Steuerungseinrichtung (2, 4, 6) zum wirkungsmäßigen Überwachen von Röhrenparametern und zum entsprechenden Einstellen des nominalen Begrenzungspegels des Röhrenkathodenstroms; und

eine Einrichtung (7) zum Ermitteln, wenn die Steuerungseinrichtung nahe einem Extremwert ihres Einstellbereichs ist, und

eine Einrichtung (8, 9, 24), die auf die Ermitt-

lungseinrichtung anspricht, um ein Steuersignal zu verändern, das einem Gitter der Röhre zugeführt wird, um die Nominalbegrenzungspegel - Regelschleife in ihren Einstellbereich zu bringen.

2. Schaltungsanordnung nach Anspruch 1, bei der die Änderungseinrichtung dazu eingerichtet ist, die dem G_2 -Gitter der Röhre zugeführte Spannung zu ändern.

3. Schaltungsanordnung nach Anspruch 1 oder 2, bei der die Änderungseinrichtung einen Nebenschlußrückkopplungsregler enthält, der zu der Spannung parallel geschaltet ist, die dem G_2 -Gitter zugeführt ist.

4. Schaltungsanordnung nach Anspruch 3, bei der der Nebenschlußrückkopplungsregler einen Niederspannungstransistor mit einem Kaskode - Hochvoltthyristor enthält.

5. Schaltungsanordnung nach Anspruch 3, dadurch gekennzeichnet, daß der Nebenschlußrückkopplungsregler einen Niedervolttransistor mit einem Kaskode - Hochvolttriac enthält.

6. Schaltungsanordnung nach einem der vorhergehenden Ansprüche, bei der die Änderungseinrichtung dazu eingerichtet ist, die Nominalbegrenzungspegel - Regelschleife auf im wesentlichen einen Extremwert ihres Einstellbereichs zu bringen.

7. Integrierte Schaltung, die eine Schaltungsanordnung im wesentlichen nach einem der vorhergehenden Ansprüche enthält.

Revendications

1. Circuit permettant de commander un tube à rayons cathodiques, comprenant:

un moyen de commande (2, 4, 6) servant à fonctionnellement contrôler des paramètres du tube et à ajuster le niveau de coupure nominal du courant cathodique du tube en conséquence; et

un moyen (7) servant à déterminer le moment où le moyen de commande est proche d'une extrémité de son intervalle de réglage, et

un moyen (8, 9, 24) répondant au moyen de détermination en changeant un signal de commande appliqué à une grille du tube de manière à amener la boucle de commande du niveau de coupure nominal à l'intérieur de son intervalle de réglage.

2. Circuit selon la revendication 1, où le moyen de changement est conçu pour changer la tension appliquée à la grille G_2 du tube.

3. Circuit selon la revendication 1 ou 2, où le moyen de changement comprend un régulateur de réaction en shunt qui est connecté en parallèle avec la tension appliquée à la grille G_2 .

4. Circuit selon la revendication 3, où le régulateur de réaction en shunt comprend un transistor basse tension associé à un thyristor haute tension en cascode.

5. Circuit selon la revendication 3, où le régulateur de réaction en shunt comprend un transistor basse tension associé à un triac haute tension en cascode.

6. Circuit selon l'une quelconque des revendications précédentes, où le moyen de changement



est conçu de manière à amener la boucle de commande du niveau de coupure nominal jusqu'à sensiblement une extrémité de son intervalle de réglage.

7. Circuit intégré incorporant un circuit tel que sensiblement décrit selon l'une quelconque des revendications précédentes.

5

10

15

20

25

30

35

40

45

50

55

60

65

4

