

Description

This invention concerns a video signal processing and display system, such as a television receiver or video monitor, which includes apparatus for automatically controlling the operating characteristics of signal processing circuits associated with the system. In particular, this invention concerns an arrangement for reducing bias errors in conjunction with the operation of the automatic control apparatus.

Color television receivers sometimes employ several control circuits for automatically controlling various aspects of receiver operation. For example, a color television receiver may employ an automatic beam current limiter for limiting excessive beam currents conducted by a kinescope of the receiver, an automatic black level bias control circuit for maintaining a desired level of black current conduction by the kinescope, and an automatic "white balance" drive control circuit to compensate for variations of those kinescope electron gun emission characteristics which relate to the signal gain of the electron guns.

A color television receiver system which includes both automatic white balance and automatic beam limiter control networks is described in GB-A-2140652 published 28.11.1984 to US-A-4516152 (published 7.8.1985) titled "Video Signal Processor with Automatic Kinescope White Balance and Beam Current Limiter Control Systems," filed in the USA May 23, 1983. In that system an output control voltage from the beam limiter network is decoupled from the luminance and chrominance channels of the receiver during intervals when the white balance control system is operating so that the operation of the white balance system is not adversely affected by the beam limiter control voltage. A receiver of the latter type may also incorporate an automatic kinescope bias (AKB) control network for maintaining a desired level of kinescope black current conduction.

A color television receiver incorporating the AKB function in addition to automatic white balance and automatic beam current limiting features is described in "DIGIT 2000 VLSI Digital TV System", Technical Bulletin, Semiconductor Division of ITT Corporation, Publication Order No. 6251-190-3E, Apr. 1983. The ITT approach uses digital signal processing techniques implemented in integrated circuits comprising the MAA2000 Central Control Unit, the MAA 2100 Video Codec Unit and the MAA2200 Video Processor Unit, for providing a digital version of a composite color television signal, luminance-chrominance frequency selection, and various luminance and chrominance processing and control functions including automatic beam current limitation, automatic white balance control,

and automatic bias control.

Attention is also invited to US-A-4017681 and to our co-filed European Patent Application EP-A-0254537.

It is herein recognized that precautions should be taken to assure that the AKB system maintains a desired bias characteristic, e.g. level of kinescope black current conduction, in response to factors including bias offset errors introduced by the action of the automatic beam current limiter as well as in response to more conventional factors such as kinescope aging and temperature effects. More specifically, it is herein recognized that chrominance channel output bias offset errors can result when the chrominance signal processing circuits are gain controlled by the beam current limiter.

According to the invention, there is provided in a system including a video channel comprising luminance and chrominance channels for processing a video signal containing image intervals and image blanking intervals, and an image display device responsive to video signals coupled thereto via said video channel; apparatus comprising by

automatic drive control means coupled to said video channel for monitoring the conduction of said image display device during prescribed drive control intervals within image blanking intervals, to maintain a desired drive characteristic for said video channel; and

automatic bias control means coupled to said video channel for monitoring the conduction of said image display device during prescribed bias control intervals within image blanking intervals, to maintain a desired bias characteristic for said video channel;

means for automatically limiting excessive beam currents conducted by said image display device in response to video signal image information, said limiting means providing an output beam current limiting control signal; characterized by

channel control means for rendering said video channel responsive to said control signal during said image intervals; for rendering said chrominance channel responsive to said control signal during said bias control intervals; and for rendering said luminance channel non-responsive to said control signal during said drive control intervals.

In an embodiment of the invention, disclosed hereinafter and which includes an automatic white balance drive control network an AKB automatic black level control system and an automatic beam current limiter, a control voltage from the beam limiter serves to control the signal gain of the chrominance and luminance channels of the receiver. In accordance with the principles of the present invention, the beam limiter control voltage is decoupled from the luminance channel during

intervals when the white balance control system operates, but the beam limiter control voltage is coupled to at least the chrominance channel during intervals when the automatic black level bias control (AKB) system operates so that bias offset errors, which may cause noticeable color errors, in the chrominance channel caused by gain controlling effect of the beam limiter control voltage can be sensed and compensated for by the AKB system.

In accordance with a feature of the embodiment, the beam limiter control voltage is coupled to the luminance and chrominance channels via an electronic switch. Timing signals cause the switch to inhibit the beam limiter control voltage coupling during white balance control intervals, but enable the control voltage to be coupled in particular to the chrominance channel during bias control intervals when the AKB system operates.

In the drawing:

FIGURE 1 shows a portion of a color television receiver including an automatic white balance control system, an automatic kinescope beam limiter system, and an automatic bias control system together with apparatus according to the present invention;

FIGURES 2 and 2a show timing signal waveforms helpful in understanding the operation of the arrangement of FIGURE 1; and

FIGURE 3 shows details of a portion of the arrangement of FIGURE 1.

In FIGURE 1, color television signals from a source 10 are supplied to a frequency selection network 12 (e.g., including a comb filter) for providing a separated luminance component of the television signal to a luminance processor 14 in a luminance channel of the receiver, and a separated chrominance component to a chrominance processor 16 in a chrominance channel of the receiver. Chrominance processor 16 provides output R-Y and B-Y color difference signals which are combined in a matrix 18 with an output luminance signal Y from processor 14. Matrix 18 supplies low level r' , g' and b' color image representative signals to respective gain controllable amplifiers 20, 21 and 22, which in turn respectively provide amplified r , g and b color signals to video output kinescope driver amplifiers 24, 25 and 26. The kinescope driver amplifiers produce high level R, G and B color signals suitable for driving intensity control cathode electrodes 36a, 36b and 36c of a color kinescope 35. The respective output signals from the kinescope driver amplifiers are coupled to kinescope cathodes 36a, 36b and 36c via current sensing networks 30, 31 and 32.

Kinescope 35 is for example of the self-converging, "in-line" gun type with a single control grid electrode 38 commonly biased with respect to

each of cathodes 36a, 36b and 36c, which comprise separate red, green and blue kinescope electron guns with grid 38. A high operating voltage for the anode electrode of kinescope 35 is provided from a high voltage supply 40 in response to horizontal flyback pulses derived from deflection circuits of the receiver. Kinescope beam resupply currents are supplied to high voltage network 40 via a resistor 42 associated with a DC operating potential (B+).

The receiver also includes an automatic kinescope beam current limiter control circuit 50 for limiting the magnitude of video signals applied to kinescope 35 to thereby limit excessive kinescope beam currents when the kinescope is sensed as conducting excessive beam currents (cathode currents) above a given threshold level. During image scanning (trace) intervals of the video signal, the magnitudes of the video image representative kinescope cathode currents are respectively sensed by networks 30, 31 and 32, and the sensed currents are combined in a network 45 to produce a total sensed current related to the total kinescope cathode current. The magnitude of this current is sensed by beam limiter control circuit 50, which develops and stores (e.g., by means of a capacitor) an output control signal related to the amount by which the sensed kinescope current exceeds the given threshold level. This control signal is coupled via an electronic switch S1, the purpose of which will be described below, to chrominance processor 16 and luminance processor 14. The control signal has a polarity for limiting the magnitudes of the chrominance and luminance signals, to thereby limit the kinescope beam current to a prescribed safe level.

Beam current limiting is accomplished over a given range of excessive beam currents by reducing the peak-to-peak amplitudes of the luminance and chrominance signals. Many color television receivers include a circuit, e.g., comprising a viewer adjustable potentiometer, for simultaneously controlling the amplitudes of the luminance and chrominance signals. The beam limiter control signal can be applied to such circuit for the purpose of simultaneously controlling the amplitudes of the luminance and chrominance signals.

The operation of switch S1 is associated with the operation of an automatic white balance control system of the receiver, and an automatic kinescope bias (AKB) control system for maintaining a desired kinescope black current level. Switch S1 responds to an INHIBIT timing signal such that when switch S1 is in an open, non-conductive condition the beam limiter control voltage is decoupled from the control inputs of luminance processor 14 and chrominance processor 16. This occurs during intervals when the white balance system operates.

Switch S1 is caused to exhibit a conductive, closed condition during normal picture (image scanning) intervals whereby the beam limiter control voltage operates to limit excessive beam currents. Switch S1 is also caused to conduct during the AKB bias control intervals so that any bias offset errors which may appear at the Y output of luminance processor 14 and more importantly at the R-Y and B-Y outputs of chrominance processor 16, due to the action of the beam limiter-control voltage, can be sensed and compensated for by the AKB system. Otherwise, such bias offsets could produce disturbing color errors in a reproduced picture. The role of switch S1 will be better understood after considering the operation of the white balance control system and the AKB control system, as follows.

The white balance system automatically compensates for variations of the kinescope electron gun emission characteristics which relate to the gains of the electron guns, in order to maintain proper drive ratios for the electron guns. The gain characteristics of the electron guns are subject to change with temperature and aging for example. Thus, the ability of the kinescope to properly produce a white display in response to a white video drive signal is impaired unless compensation is provided such as by means of the white balance system.

The white balance system comprises plural drive control networks 60, 62 and 64 respectively associated with the red, green and blue kinescope cathode signal coupling paths, and a source of white drive reference signal 65 coupled to luminance processor 14. Except as otherwise noted, the functional elements of drive control networks 60, 62 and 64 are similar. Accordingly, only the functional elements of drive control network 64 for the blue kinescope electron gun are shown and will be discussed.

The following discussion of the operation of the white balance system is made with reference to the timing signal waveforms shown in FIGURES 2 and 2a. These timing signals are provided by a timing signal generator 55, which responds to vertical (V) and horizontal (H) image synchronizing signals derived from deflection circuits of the receiver, and which may include combinational logic circuits such as logic gates and sequential logic circuits such as binary counters.

At the end of each vertical field retrace interval during each vertical blanking interval, at which time video image information is absent, a reference signal (e.g., a DC voltage) representative of a significant white drive level luminance signal is coupled to luminance processor 14 from reference source 65. This coupling is enabled by a WHITE timing signal which occurs during an automatic white drive control interval encompassing a few horizontal line

intervals. The magnitude of the white reference signal applied to luminance processor 14 can be about 10% of a full white luminance signal, although some receiver systems may require a larger white reference signal approaching the magnitude of a normally expected 100% peak white luminance signal.

At this time a BLANK signal is applied to chrominance processor 16, and to circuits in luminance processor 14 which precede the circuits to which the white reference signal is applied. The BLANK signal renders the preceding circuits in luminance processor 14 non-conductive to assure that spurious signals and video signal synchronizing components do not disturb the operation of the white balance system. Also at this time, $\bar{R}$ and $\bar{G}$ signals are applied to red and green signal amplifiers 20 and 21 with an amplitude and sense for rendering these amplifiers non-conductive when the white balance system operates with respect to the blue kinescope electron gun signal path. That is, of the red, green and blue gain controllable amplifiers 20, 21 and 22, only blue amplifier 22 remains conductive when the white balance system operates with respect to the blue signal path and the associated blue kinescope electron gun.

As seen from FIGURES 2a, during a first vertical field blanking interval when the blue kinescope electron gun white current is sensed, negative-going signals $\bar{R}$ and $\bar{G}$ render amplifiers 20 and 21 non-conductive while the condition of signal $\bar{B}$ permits blue amplifier 22 to remain conductive during the white balance drive control interval. Negative-going signals $\bar{R}$ and $\bar{G}$ also encompass the AKB bias control interval, to facilitate the operation of the AKB system as will be described subsequently. The relative conditions of the $\bar{R}$, $\bar{G}$ and $\bar{B}$ signals during succeeding second and third field blanking intervals, when the green and red electron gun currents are respectively sensed, are also shown in FIGURE 2a.

The white reference signal is conducted via amplifier 22 and associated kinescope driver amplifier 26 to produce a white reference drive signal for the blue kinescope electron gun comprising cathode 36c. The corresponding white reference level current conducted by blue cathode 36c is sensed by sensor 32 and coupled via network 45 to the input of blue drive control network 64.

Blue drive control network 64 comprises an electronic switch S2 at its input, a source of reference current 66, a differential current comparator 67, and an output storage network 68. Both input switch S2 and comparator 67 are controlled in response to a DRIVE SENSE signal which occurs during the interval encompassed by the WHITE timing signal. The magnitude of the reference current from source 66 is preselected such that it

corresponds to the magnitude of the blue cathode current, as supplied to comparator 67, when the blue cathode current is correct as conducted in response to the white reference signal. Thus the magnitude of the white reference signal from source 65 and the magnitude of the reference current from source 66 are related and selected one with respect to the other.

During the white drive current sensing interval for the blue electron gun, switch S2 is rendered conductive and comparator 67 operates in response to the DRIVE SENSE signal. The comparator produces an output error correction signal if the blue gun current is too high or too low. The correction signal is stored by network 68 and is applied to a gain control input of amplifier 22 for changing the gain of amplifier 22 with a sense for producing a correct blue gun current. Storage network 68 maintains the error correction signal at the gain control input of amplifier 22 until the next blue gun current sensing interval, which occurs three vertical fields later. The gain correction output signal from comparator 67 remains unchanged if the currents sensed by comparator 67 are substantially equal, indicating that the current conduction level (gain) of the blue electron gun is correct.

Red and green drive control networks 60 and 62 operate in a similar fashion during subsequent field blanking intervals with respect to the red and green electron gun white balance measurements. The levels of the reference currents supplied by the reference current sources in red and green drive control networks 60 and 62 are selected in accordance with normally "correct" gain-related emission characteristics of the red and green electron guns. Also, the input switch and comparator associated with red and green drive control networks 60, 62 are rendered non-conductive during the white drive measuring interval for the blue electron gun. For such purpose the DRIVE SENSE signal applied to the input switch and comparator of networks 60, 62 exhibits a magnitude and polarity sufficient to maintain the input switch and comparator of networks 60, 62 non-conductive during the blue electron gun white drive measuring interval. That is, only that drive control network associated with the electron gun under test is rendered operative during a given field interval.

Each of sensors 30-32 may comprise a high voltage PNP emitter follower transistor included in the cathode signal coupling path, with a base input electrode coupled to the output of the associated kinescope driver amplifier, an emitter output electrode coupled to the associated kinescope cathode, and a collector electrode coupled to a current summing junction (comprising network 45 in FIGURE 1). Beam limiter control circuit 50 can incorporate circuitry of the type shown in U.S. patent 4,167,025

of D. H. Willis. Details of a circuit suitable for use as each of current sensors 30-32, as well as details of circuits suitable for use as beam limiter control circuit 50, are also shown in my aforementioned U.S. patent application Serial No. 497,157. (GB-A-2140652)

Automatic kinescope bias (AKB) control circuits 75 include plural control circuits each operatively associated with one of the red (R), green (G) and blue (B) kinescope electron guns respectively comprising cathodes 36a, 36b and 36c. Each bias control circuit has an input coupled to the output of current combining network 45 at node A. The plural bias control circuits operate in response to a BIAS SENSE timing signal which occurs during a bias control interval after the end of vertical retrace, but before the white drive control interval, as seen from FIGURE 2. The bias control circuits operate sequentially with respect to each of the R, G, B cathode signal paths, in a manner analogous to that of drive control circuits 60, 62 and 64, but for sensing the black level currents of the plural cathode signal paths. During automatic bias control intervals the BLANK signal is applied to luminance processor 14 and chrominance processor 16, and luminance processor 14 is caused to develop an output black reference level, e.g., in response to an input reference signal.

The bias control circuits develop output bias control signals C_R , C_G , and C_B respectively representative of the magnitude of the sensed black currents with respect to a reference level. These control signals are applied to bias control inputs of amplifiers 20, 21 and 22 for maintaining desired black current levels for each of the cathode signal paths. Bias control network 75 maintains proper biasing of the kinescope electron guns to maintain faithful reproduction of color images in the presence of kinescope aging and temperature effects, among other factors which could lead to incorrect kinescope biasing and incorrect image rendition.

Each of the bias control circuits in network 75 can include circuit elements of the type illustrated in connection with blue drive control network 64, for example. Thus each bias control network may include an input switch responsive to the BIAS SENSE timing signal, a differential comparator rendered operative by the BIAS SENSE signal to provide an output signal representative of the difference between a reference current and a sensed black current derived from the output of combiner 45, and a storage network coupled to the comparator output for developing a bias control signal.

In connection with the automatic drive control operation, the INHIBIT timing signal is such that switch S1 is rendered non-conductive (i.e., open as shown) for the duration of each WHITE timing signal. This prevents the beam limiter control volt-

age from network 50 from influencing the characteristics of chrominance processor 16, and luminance processor 14 in particular, during the white drive control intervals. Otherwise, the beam limiter control signal would undesirably influence the conduction characteristics of the luminance signal path during the white drive control intervals, thereby resulting in significant distortion of the sensed white drive current conducted by the kinescope.

It is noted that switch S1 is timed to operate so that it remains conductive during AKB bias control intervals. Thus the beam limiter control voltage remains coupled to the control input of luminance processor 14 and chrominance processor 16 during AKB control intervals. The latter coupling to the chrominance channel is particularly advantageous, as follows.

Gain control of chrominance processor 16 by the beam limiter control voltage can lead to associated bias offset errors in the R-Y and B-Y outputs of chrominance processor 16. Such bias errors, even if small, if uncorrected can produce noticeable color errors in a reproduced color image particularly in scenes of low luminance content, and can result in a false color tint in the case of a monochrome scene. These undesirable effects are avoided since the timing of switch S1 permits the beam limiter control voltage to be applied to chrominance processor 16 during AKB sensing intervals. Any existing bias errors are therefore sensed and corrected by the AKB system in the DC coupled kinescope cathode signal coupling paths.

Similarly, with this arrangement the AKB system can correct any bias errors produced at the output of luminance processor 14 in response to the gain controlling action of the beam limiter control voltage, since the timing of switch S1 is such that the beam limiter control voltage is also coupled to luminance processor 14 during AKB intervals. However, luminance output bias errors are less perceptible in a reproduced scene since such bias errors result in a relatively less noticeable small brightness change.

The chrominance bias offset errors can result from the effects of small spurious (parasitic) impedances associated with the circuits in chrominance processor 16 to which the beam limiter control signal is applied for gain control purposes. Such spurious impedances are usually unavoidable in both discrete and integrated circuit designs, and can be present in both analog and digital video signal processing circuits as a function of circuit layout and construction. An example of a digital television signal processing system is that recently introduced by the Worldwide Semiconductor Group of International Telephone and Telegraph Corpora-

tion, the "Digit 2000 VLSI Digital TV System" previously referred to. That system includes an MAA 2100 Video Codec integrated circuit which incorporates chrominance processing circuits of the type which may be utilized by chrominance processor 16 in FIGURE 1.

In such digital television signal processing system, demodulated color difference signals in digital (binary) form are converted to analog form by means of a digital-to-analog (D/A) converter arrangement associated with the outputs of the chrominance processor, before the demodulated color difference signals are applied to a matrix network such as matrix 18 in FIGURE 1. The D/A converter arrangement can be of the type shown in FIGURE 3, wherein R-Y and B-Y digital input signals are respectively applied to similar D/A converters 80 and 82 from which R-Y and B-Y analog output signals are respectively provided. The D/A converters are coupled to respective sources 84, 86 of positive, non-zero reference voltages V_{REF} , and are also connected to a point of ground potential.

As indicated by unit 80, each D/A converter comprises a resistive ladder network to which digital input signal components are applied, and from which a corresponding analog output signal is provided. In this example the signal gain of the chrominance channel is controlled for beam current limiting purposes by controlling the magnitude of (i.e., decreasing) positive reference voltages (V_{REF}). As each reference voltage is reduced in magnitude, the amplitudes of the analog output color difference signals are reduced accordingly. The presence of unpredictable and usually unavoidable small spurious impedances associated with the construction and layout of the circuitry comprising the D/A converters, such as in the ground connection for the D/A converters, can result in a less effective, i.e., less stable, ground potential connection for the D/A converters. This condition can lead to unpredictable output bias offset errors as the levels of the reference voltages are caused to vary with the beam limiter control voltage, which bias errors are permitted to be sensed and compensated for by the automatic bias control system as already discussed.

Apparatus according to the present invention can be used with video signal processing systems employing analog signal processing circuits, as well as digital signal processing circuits such as those included in the ITT "Digit 2000 VLSI Digital TV System" previously referred to, which includes an automatic beam current limited, an automatic white balance control network, and automatic bias control circuits of the type described with reference to circuits 75 as shown and described in connection with FIGURE 1.



Claims

1. In a system including a video channel comprising luminance (14) and chrominance (16) channels for processing a video signal containing image intervals and image blanking intervals, and an image display device responsive to video signals coupled thereto via said video channel; apparatus comprising
automatic drive control means (64) coupled to said video channel for monitoring the conduction of said image display device (35) during prescribed drive control intervals within image blanking intervals, to maintain a desired drive characteristic for said video channel;
automatic bias control means (75) coupled to said video channel for monitoring the conduction of said image display device during prescribed bias control intervals within image blanking intervals, to maintain a desired bias characteristic for said video channel; and
means (50) for automatically limiting excessive beam currents conducted by said image display device in response to video signal image information, said limiting means providing an output beam current limiting control signal; characterized by
channel control means (S1,55) for rendering said video channel responsive to said control signal during said image intervals; for rendering said chrominance channel responsive to said control signal during said bias control intervals; and for rendering said luminance channel non-responsive to said control signal during said drive control intervals.
2. Apparatus according to claim 1 characterized in that said channel control means includes
a source of timing signals (55); and
switching means (S1) coupled to said beam current limiting means (50) and to said luminance (14) and chrominance (16) channels and responsive to said timing signals for a) coupling said control signal to said luminance and chrominance channels during said image intervals, and to said chrominance channel during said bias control intervals; and b) decoupling said control signal from said luminance channel during said drive control intervals.
3. Apparatus according to claim 2, characterized in that said switching means (S1) also decouples said control signal from said chrominance channel during said drive control intervals.
4. Apparatus according to claim 3, characterized

in that said switching means (S1) comprises an electronic switch with an input for receiving said control signal and an output coupled to said luminance and chrominance channels, said switch being rendered conductive during said bias control intervals and non-conductive during said drive control intervals.

5. Apparatus according to claim 2,3 or 4 characterized in that a source of reference voltage (V_{REF}) is included in said chrominance channel, the magnitude of chrominance signals processed by said chrominance channel being a function of the magnitude of said reference voltage; and
said switching means (S1) couples said control signal to said source of reference voltage for varying the magnitude of said reference voltage to effect beam current limiting.
6. Apparatus according to any one of the preceding claims, characterized in that a reference signal (WHITE) is applied to said luminance channel during said drive control intervals, said reference signal being of a significant magnitude and white-going image sense for increasing the current conduction of said image display device during said drive control intervals; and
said automatic drive control means (64) senses the magnitude of currents conducted by said display device in response to said reference signal.
7. Apparatus according to claim 6 characterized in that said image display device comprises a kinescope (35) having an electron gun including a cathode intensity control electrode (36c);
said reference signal (WHITE) is applied to said cathode electrode via said luminance channel (14);
said automatic drive control means (64) senses the magnitude of cathode current during said drive control intervals; and
said automatic bias control means (75) senses the magnitude of cathode current during said bias control intervals.

Revendications

1. Dans un système comprenant un canal vidéo comportant des canaux de luminance (14) et de chrominance (16) pour traiter un signal vidéo contenant des intervalles d'images et des intervalles de suppression d'images, et un dispositif de visualisation l'images répondant aux signaux vidéo couplés à celui-ci par l'intermédiaire du canal vidéo ; dispositif comprenant



un moyen de contrôle d'attaque automatique (64) couplé au canal vidéo pour contrôler la conduction du dispositif de visualisation d'images (35) pendant des intervalles de contrôle d'attaque prescrits dans les intervalles de suppression d'images pour maintenir une caractéristique d'attaque souhaitée au canal vidéo ;

un moyen de contrôle de polarisation automatique (75) couplé au canal vidéo pour contrôler la conduction du dispositif de visualisation d'images pendant les intervalles de contrôle de polarisation prescrit dans les intervalles de suppression d'images pour maintenir une caractéristique de polarisation souhaitée au canal vidéo ;

un moyen (50) pour automatiquement limiter des courants de faisceau excessifs conduits par le dispositif de visualisation d'images en réponse à l'information d'image du signal vidéo, le moyen de limitation produisant un signal de commande de limitation de courant du faisceau de sortie ; caractérisé par

un moyen de commande de canal (S1,55) pour rendre le canal vidéo sensible audit signal de commande pendant les intervalles d'images ; pour rendre le signal de chrominance sensible au signal de commande pendant les intervalles de contrôle de polarisation ; et pour rendre le canal de luminance insensible au signal de commande pendant les intervalles de contrôle d'attaque.

2. Dispositif selon la revendication 1 caractérisé en ce que le moyen de commande de canal précité comprend

une source de signaux de synchronisation (55) ; et

un moyen de commutation (S1) couplé au moyen de limitation de courant de faisceau (50) et aux canaux de luminance (14) et de chrominance (16) précités et répondant aux signaux de synchronisation pour a) coupler le signal de commande précité au canaux de chrominance et de luminance pendant les intervalles d'images et au canal de chrominance pendant les intervalles de contrôle de polarisation ; et b) découpler le signal de commande du canal de luminance pendant les intervalles de contrôle d'attaque.

3. Dispositif selon la revendication 2, caractérisé en ce que le moyen de commutation précité

(S1) découple également le signal de commande précité du signal de chrominance pendant les intervalles de contrôle d'attaque.

4. Dispositif selon la revendication 3, caractérisé en ce que le moyen de commutation précité (S1) comprend un commutateur électronique à une entrée pour recevoir le signal de commande précité et une sortie couplée aux canaux de luminance et de chrominance précités, ledit commutateur étant rendu conducteur pendant les intervalles de contrôle de polarisation et non conducteur pendant les intervalles de contrôle d'attaque.

5. Dispositif selon la revendication 2, 3 ou 4 caractérisé en ce qu'une source de tension de référence (V_{ref}) est incluse dans le canal de chrominance précité, la grandeur des signaux de chrominance traités par le canal de chrominance étant une fonction de la grandeur de la tension de référence ; et

le moyen de commutation précité (S1) couple le signal de commande précité à la source de tension de référence pour varier la grandeur de la tension de référence pour effectuer une limitation du courant de faisceau.

6. Dispositif selon l'une des revendications précédentes, caractérisé en ce qu'un signal de référence (BLANC) est appliqué au canal de luminance précité pendant les intervalles de contrôle d'attaque, ledit signal de référence étant d'une grandeur significative et d'un sens d'image allant vers le blanc pour augmenter la conduction en courant du dispositif de visualisation d'images précité pendant les intervalles de contrôle d'attaque ; et

le moyen de contrôle d'attaque automatique (64) précité détecte la grandeur des courants conduits par le dispositif de visualisation en réponse au signal de référence.

7. Dispositif selon la revendication 6 caractérisé en ce que le dispositif de visualisation d'images comprend un tube image (35) ayant un canon à électrons comprenant une électrode de contrôle d'intensité de cathode (36C) ;

le signal de référence précité (BLANC) est appliqué à l'électrode de cathode via le canal de luminance (14) ;

le moyen de contrôle attaque automatique (64) détecte la grandeur du courant de cathode pendant les intervalles de contrôle d'attaque ;



et

le moyen de contrôle de polarisation automatique (75) détecte la grandeur du courant d'attaque pendant les intervalles de contrôle de polarisation.

Patentansprüche

1. Vorrichtung in einem System, das einen Videokanal mit Leuchtdichte- und Farbartkanälen (14 und 16) zur Verarbeitung eines Bildintervalle und Bildaustastintervalle enthaltenden Videosignals und ein Bildwiedergabegerät aufweist, welches auf Videosignale anspricht, die ihm über den Videokanal eingekoppelt werden, mit folgenden Einrichtungen:

einer selbsttätigen Aussteuerungs-Regel-einrichtung (64), die mit dem Videokanal gekoppelt ist, um die Stromleitung des Bildwiedergabegerätes (35) während vorgeschriebener Aussteuerungsregelungsintervalle innerhalb Bildaustastintervallen zur Aufrechterhaltung einer gewünschten Aussteuerungscharakteristik für den Videokanal zu regulieren;

einer selbsttätigen Vorspannungs-Regel-einrichtung (75), die mit dem Videokanal gekoppelt ist, um die Stromleitung des Bildwiedergabegerätes während vorgeschriebener Vorspannungsregelungsintervalle innerhalb Bildaustastintervallen zur Aufrechterhaltung einer gewünschten Vorspannungscharakteristik für den Videokanal zu regulieren, und einer Einrichtung (5), um übermäßige Strahlströme, die vom Bildwiedergabegerät geleitet werden, in Ansprache auf Bildinformation des Videosignals selbsttätig zu begrenzen, wobei diese Begrenzungseinrichtung ein ausgangsseitiges Strahlstrombegrenzungs-Steuersignal liefert,

gekennzeichnet durch

eine Kanalsteuereinrichtung (S1, 55), welche den Videokanal während der Bildintervalle auf das besagte Steuersignal ansprechen läßt und welche den Farbartkanal während der besagten Vorspannungssteuerintervalle auf das Steuersignal ansprechen läßt und welche das Ansprechen des Leuchtdichtekanals auf das Steuersignal während der besagten Aussteuerungsregelungsintervalle unterbindet.

2. Vorrichtung nach Anspruch 1, dadurch gekennzeichnet, daß die Kanalsteuereinrichtung eine Quelle für Zeitsteuersignale (55) und eine mit der Strahlstrom-Begrenzungseinrichtung (50) und mit den Leuchtdichte- und Farbartkanälen (14 und 16) gekoppelte Schalteinrichtung (S1) enthält und auf die Zeitsteuersignale anspricht,

um a) das Steuersignal während der Bildintervalle auf die Leuchtdichte- und Farbartkanäle zu koppeln und während der Vorspannungsregelungsintervalle auf den Farbartkanal zu koppeln und b) das Steuersignal während der Aussteuerungsregelungsintervalle vom Leuchtdichtekanal abzukoppeln.

3. Vorrichtung nach Anspruch 2, dadurch gekennzeichnet, daß die Schalteinrichtung (S1) das Steuersignal während der Aussteuerungsregelungsintervalle auch vom Farbartkanal abkoppelt.

4. Vorrichtung nach Anspruch 3, dadurch gekennzeichnet, daß die Schalteinrichtung (S1) einen elektronischen Schalter aufweist, der einen Eingang zum Empfang des Steuersignals und einen mit den Farbart- und Leuchtdichtekanälen gekoppelten Ausgang hat und der während der Vorspannungsregelungsintervalle leitend und während der Aussteuerungsregelungsintervalle nichtleitend gemacht wird.

5. Vorrichtung nach Anspruch 2, 3, oder 4, dadurch gekennzeichnet,

daß im Farbartkanal eine Quelle für eine Referenzspannung (V_{REF}) enthalten ist und der Betrag der vom Farbartkanal verarbeiteten Farbsignale eine Funktion des Betrags der Referenzspannung ist, und

daß die Schalteinrichtung (S1) das Steuersignal mit der Quelle der Referenzspannung koppelt, um den Betrag der Referenzspannung zur Bewirkung der Strahlstrombegrenzung zu verändern.

6. Vorrichtung nach einem der vorhergehenden Ansprüche, dadurch gekennzeichnet,

daß während der Aussteuerungsregelungsintervalle an den Leuchtdichtekanal ein Referenzsignal (WHITE) gelegt wird, das einen signifikanten Betrag und einen in Weißrichtung gehenden Bildsinn hat, um die Stromleitung des Bildwiedergabegerätes während der Aussteuerungsregelungsintervalle zu erhöhen, und

daß der selbsttätige Aussteuerungs-Regel-einrichtung (64) den Betrag von Strömen führt, die vom Bildwiedergabegerät in Ansprache auf das Referenzsignal geleitet werden.

7. Vorrichtung nach Anspruch 6, dadurch gekennzeichnet, daß das Bildwiedergabegerät eine Bildröhre (35) mit einem Strahlerzeugungssystem aufweist, welches eine Kathodenelektrode (36c) zur Intensitätssteuerung hat;

daß das Referenzsignal (WHITE) über den Leuchtdichtekanal (14) an die Kathodenelektro-

de gelegt wird;

daß die selbsttätige Aussteuerungs-Regel-
einrichtung (64) den Betrag des Kathoden-
stroms während der Aussteuerungsregelungs-
intervalle fühlt, und

daß die selbsttätige Vorspannungs-Regel-
einrichtung (75) den Betrag des Kathoden-
stroms während der Vorspannungsregelungs-
intervalle fühlt.



5

10

15

20

25

30

35

40

45

50

55

10