

TEST CIRCUIT FOR AN UNPROGRAMMED OTP MEMORY ARRAY

CROSS REFERENCE TO RELATED APPLICATIONS

[0001] This application claims the benefit of priority of U.S. Provisional Patent Application No. 61/042,052, filed on April 3, 2008, which is incorporated herein by reference in its entirety.

FIELD OF THE INVENTION

[0002] The present invention relates generally to non-volatile memory. More specifically, the invention is directed to one-time programmable (OTP) memories.

BACKGROUND OF THE INVENTION

[0003] Anti-fuse memory is one type of one-time programmable (OTP) memory in which the device can be permanently programmed (electrically) with data once. This data is programmed by an end user for a particular application. There are several types of OTP memory cells which can be used. OTP memories provide users with a level of flexibility since any data can be programmed.

[0004] Anti-fuse memory can be utilized in all one time programmable applications, including RF-ID tags. RF-ID tagging applications are gaining more acceptance in the industry, particularly in sales, security, transport, logistics, and military applications for example. The simplicity and full CMOS compatibility anti-fuse memory allows for application of the RF-ID tag concept to integrated circuit manufacturing and testing processes. Therefore, IC manufacturing productivity can be increased by utilizing anti-fuse memory in combination with an RF communication interface on every wafer and/or every die on the wafer allowing for contact-less programming and reading chip specific or wafer specific information during IC manufacturing and packaging, as well as during printed circuit board assembly.

[0005] Figure 1 is a circuit diagram of a known anti-fuse memory cell, while Figures 2 and 3 show the planar and cross-sectional views respectively of the anti-fuse memory cell shown in Figure 1. The anti-fuse memory cell of Figure 1 includes a pass, or access transistor **10** for coupling a bitline BL to a bottom plate of anti-fuse device **12**. Anti-fuse device **12** is considered a gate dielectric breakdown based anti-fuse devices. A wordline WL is coupled to the gate of access transistor **10** to turn it on, and a cell plate voltage Vcp is coupled to the top plate of anti-fuse device **12** for programming anti-fuse device **12**.

[0006] It can be seen from Figures 2 and 3 that the layout of access transistor **10** and anti-fuse device **12** is very straight-forward and simple. The gate **14** of access transistor **10** and the top plate **16** of anti-fuse device **12** are constructed with the same layer of polysilicon, which extend across active area **18**. In the active area **18** underneath each polysilicon layer, is formed a thin gate oxide **20**, also known as a gate dielectric, for electrically isolating the polysilicon from the active area underneath. On either side of gate **14** are diffusion regions **22** and **24**, where diffusion region **24** is coupled to a bitline. Although not shown, those of skill in the art will understand that standard CMOS processing, such as sidewall spacer formation, lightly doped diffusions (LDD) and diffusion and gate silicidation, can be applied. While the classical single transistor and capacitor cell configuration is widely used, a transistor-only anti-fuse cell is further desirable due to the semiconductor array area savings that can be obtained for high-density applications. Such transistor-only anti-fuses should be reliable while simple to manufacture with a low cost CMOS process.

[0007] Figure 4a shows a cross-sectional view of an anti-fuse transistor that can be manufactured with any standard CMOS process. This anti-fuse transistor and its variants are disclosed in commonly owned U.S. Patent Application No. 10/553,873 filed on October 21, 2005, and commonly owned U.S. Patent Application No. 11/762,552 filed on June 13, 2007, the contents of which are incorporated by reference. In the presently shown example, the anti-fuse transistor is almost identical to a simple thick gate oxide, or input/output MOS transistor with one floating diffusion terminal. The disclosed anti-fuse transistor, also termed a split-channel capacitor or a half-transistor, can be reliably programmed such that the fuse link between the polysilicon gate and the substrate can be predictably localized to a particular region of the device. The cross-section view of Figure 4a is taken along the channel length of the device. The channel is generally understood to be the area underneath an overlying polysilicon gate, having a length defined by edges of the polysilicon gate adjacent respective diffusion regions.

[0008] Anti-fuse cell **30** includes a variable thickness gate oxide **32** formed on the substrate channel region **34**, a polysilicon gate **36**, sidewall spacers **38**, a field oxide region **40** a diffusion region **42**, and an LDD region **44** in the diffusion region **42**. A bitline contact **46** is shown to be in electrical contact with diffusion region **42**. The variable thickness gate oxide consists of a thick gate oxide **32** and a thin gate oxide **33** such that a portion of the channel length is covered by the thick gate oxide and the remaining portion of the channel length is covered by the thin gate oxide. Generally, the thin gate oxide is a region where oxide breakdown can occur. The thick gate oxide edge meeting diffusion

region **42** on the other hand, defines an access edge where gate oxide breakdown is prevented and current between the gate **36** and diffusion region **42** is to flow for a programmed anti-fuse transistor. While the distance that the thick oxide portion extends into the channel region depends on the mask grade, the thick oxide portion is preferably formed to be at least as long as the minimum length of a high voltage transistor formed on the same chip.

[0009] In this example, the diffusion region **42** is connected to a bitline through a bitline contact **46**, or other line for sensing a current from the polysilicon gate **36**, and can be doped to accommodate programming voltages or currents. This diffusion region **42** is formed proximate to the thick oxide portion of the variable thickness gate oxide. To further protect the edge of anti-fuse cell **30** from high voltage damage, or current leakage, a resistor protection oxide (RPO), also known as a salicide protect oxide, can be introduced during the fabrication process to further space metal particles from the edge of sidewall spacer **38**. This RPO is preferably used during the salicidation process for preventing only a portion of diffusion region **42** and a portion of polysilicon gate **36** from being salicided. It is well known that salicided transistors are known to have higher leakage and therefore lower breakdown voltage. Thus having a non-salicided diffusion region **42** will reduce leakage. Diffusion region **42** can be doped for low voltage transistors or high voltage transistors or a combination of the two resulting in same or different diffusion profiles.

[0010] A simplified plan view of the anti-fuse cell **30** is shown in Figure 4b. Bitline contact **46** can be used as a visual reference point to orient the plan view with the corresponding cross-sectional view of Figure 4a. The active area **48** is the region of the device where the channel region **34** and diffusion region **42** is formed, which is defined by an OD mask during the fabrication process. The dashed outline **50** defines the areas in which the thick gate oxide is to be formed via an OD2 mask during the fabrication process. More specifically, the area enclosed by the dashed outline **50** designates the regions where thick oxide is to be formed. OD simply refers to an oxide definition mask that is used during the CMOS process for defining the regions on the substrate where the oxide is to be formed, and OD2 refers to a second oxide definition mask different than the first. According to an embodiment of the present invention, the thin gate oxide area bounded by edges of the active area **48** and the rightmost edge of the OD2 mask, is minimized. In the presently shown embodiment, this area can be minimized by shifting the rightmost OD2 mask edge towards the parallel edge of active area **48**. Commonly owned U.S. Patent Application No. 11/762,552 filed on June 13, 2007, the contents of which are

incorporated by reference, describes alternate single transistor anti-fuse memory cells which can be used in a non-volatile memory array.

[0011] Figure 5 is a plan view layout of a single transistor anti-fuse memory cell memory array according to an embodiment of the present invention. In the present example, only four wordlines and four bitlines are shown. Each single transistor anti-fuse cell **30** in memory array **60** has one polysilicon gate **62**, and have the same structure as anti-fuse cell **30** of Figures 4a and 4b. In memory array **60**, the polysilicon line forming polysilicon gates **62** of each anti-fuse memory cell are common to all the anti-fuse memory cells of the row. Memory array **60** is shown to include sixteen anti-fuse memory cells, where four are arranged in each of first row **64**, second row **66**, third row **68** and fourth row **70**. Wordlines WLi , $WLi+1$, $WLi+2$ and $WLi+3$ are connected to the polysilicon gates **62** of rows **64**, **66**, **68** and **70** respectively. The dashed outlines **72** define the areas in the memory array in which a thick gate oxide is to be formed via a thick gate oxide definition mask during the fabrication process. In the configuration shown in Figure 5, each pair of memory cells from rows **64** and **66** share a common diffusion region **74** and a common bitline contact **76**. Each bitline contact is connected to a different bitline, such as bitlines BLn , $BLn+1$, $BLn+2$ and $BLn+3$. Connected to each of the bitlines is a precharge circuit **78**, and a column decoder and sense amplifier circuit block **80**. The precharge circuit **78** is responsible for precharging all the bitlines to a predetermined voltage for a read operation, while the column decoder and sense amplifier circuit block **80** includes multiplexing devices for sharing one sense amplifier with one or more bitlines. The actual layout of a memory array using the architecture of Figure 5 can have the precharge circuit **78** located at one end of the bitlines opposite to the column decoder and sense amplifier circuit block **80**, or adjacent or integrated with the column decoder and sense amplifier circuit block **80**.

[0012] An overview of the program and read operations is now discussed with reference to the anti-fuse cell **30** of Figure 4a and 4b, and memory array **60** of Figure 5. Generally, the anti-fuse transistors are programmed by rupturing the gate oxide, preferably at one of the thin/thick gate oxide boundary and the thin gate oxide/source diffusion edge. This is accomplished by applying a high enough voltage differential between the gate and the channel of the cells to be programmed and a substantially lower voltage differential, if any, on all other cells. Therefore, once a permanent conductive link is formed, a current applied to the polysilicon gate will flow through the link and the channel to the diffusion region, which can be sensed by conventional sense amplifier circuits. In the present example, programming of anti-fuse cell **30** is achieved by grounding selected bitlines to

0V, and driving a selected row to a programming voltage level (VPP) that is typically greater than the VDD voltage supply provided to other circuits. Under these conditions, the thin gate oxide **33** is intended to breakdown in the presence of the large electrical field formed between the channel region **34** and the wordline, thereby creating an electrically conductive connection between channel region **34** and polysilicon gate **36**. This electrically conductive connection can be referred to as a conductive link or anti-fuse. In Figure 5 for example, if BL_n is grounded and WL_i is selected to be driven to VPP, then the anti-fuse cell **30** at the intersection of BL_n and WL_i will be programmed once its conductive link is formed. Hence any anti-fuse transistor connected to WL_i can be programmed if its corresponding bitline is grounded. On the other hand, inhibiting programming of any anti-fuse transistor connected to WL_i is done by biasing the bitlines connected to them to VDD. The reduced electric field is insufficient for the conductive link to be formed.

[0013] To read a programmed or unprogrammed anti-fuse transistor with a formed conductive link, all the bitlines are precharged to VSS followed by driving a selected wordline to VDD. Any programmed anti-fuse transistor having a conductive link will drive its corresponding bitline to VDD through its VDD driven wordline via the conductive link. The increased bitline voltage can then be sensed. Any unprogrammed anti-fuse transistor having an absence of a conductive link will have no effect on its corresponding bitline, which means that it remains at the VSS precharge level.

[0014] It should be appreciated by those skilled in the art that OTP memories are programmed by the end customer, not by the manufacturer or the vendor. Accordingly, there should be some qualification provided by the manufacturer that the provided OTP memories have been tested to operate properly before use by the end customer. More specifically, the manufacturer should qualify that the circuits of the OTP memory function properly. Defective cells can be replaced with extra rows or columns of cells after unsuccessful programming by the end user, using well known redundancy techniques. In particular, this testing should ensure that fabricated circuits such as the row decoders and column decoders function as designed, and that there are no manufacturing defects during formation of wordlines and bitlines.

[0015] It is difficult to test the functionality of the previously described OTP memory device because the bitlines are precharged to a voltage level that corresponds to that of an unprogrammed cell, and driving wordlines to a read voltage will have no effect as the cells are unprogrammed. For the described OTP memory device, the bitlines will rise towards VDD only when a programmed OTP memory cell is activated.

[0016] It is, therefore, desirable to provide circuits for testing an unprogrammed OTP memory array, without programming any of the OTP memory cells.

SUMMARY OF THE INVENTION

[0017] It is an object of the present invention to obviate or mitigate at least one disadvantage of previous OTP testing methods and systems.

[0018] In a first aspect, the present invention provides a one time programmable (OTP) memory. The OTP memory includes a memory array, decoding circuits, a test circuit, and sense circuitry. The memory array includes unprogrammed OTP cells, while the decoding circuits are located at a first end of the memory array. The test circuit is located at a second and opposite end of the memory array for coupling at least one bitline towards a first voltage in response to an activated wordline during a testing operation. The at least one bitline is precharged to a second voltage during a normal read operation. The sense circuitry senses the voltage of the at least one bitline. According to one embodiment of the present aspect, the first voltage of the at least one bitline corresponds to a read voltage provided by a programmed OTP cell.

[0019] In another embodiment, the test circuit couples a plurality of bitlines connected to the unprogrammed OTP cells to the first voltage, and the decoding circuits include column circuits connected to the plurality of bitlines. In this embodiment, the test circuit includes a row of test cells having their gate terminals formed by the activated wordline, and each of the test cells is connected to one of the plurality of bitlines. Each of the test cells are mask programmed to couple the first voltage to a corresponding bitline in response to the activated wordline. Alternately, each of the test cells is identical in structure and layout to one of the unprogrammed OTP cells, and programmable for coupling the first voltage of the activated wordline to a corresponding bitline. The unprogrammed OTP cells and the test cells can be single transistor anti-fuse cells having identical layouts, or two-transistor anti-fuse cells having identical layouts.

[0020] In yet another embodiment of the present aspect, the decoding circuits include row circuits connected to a plurality of wordlines, the activated wordline being one of the plurality of wordlines, and the plurality of wordlines being connected to rows of the unprogrammed OTP cells. In the present embodiment, the test circuit includes a column of test cells having their gate terminals formed by the plurality of wordlines, where each of the test cells is connected to the at least one bitline. Each of the test cells can be mask programmed to couple the first voltage to the at least one bitline in response to the activated wordline. Alternately, each of the test cells is identical in structure and layout to

one of the unprogrammed OTP cells, and programmable for coupling the first voltage of the activated wordline to a corresponding bitline. Furthermore, the sense circuitry is a dedicated test sense amplifier for sensing the first voltage of the at least one bitline, and the test circuit includes a test coupling device for selectively connecting the at least one bitline to a bitline connected to a column of unprogrammed OTP cells.

[0021] In second aspect, the present invention provides a one time programmable (OTP) memory. The OTP memory includes a memory array, a row test circuit, a column test circuit, and sense circuitry. The memory array has unprogrammed OTP cells connected to wordlines and bitlines. The row test circuit is connected to the wordlines for charging a test bitline to a first voltage in response to activation of one of the wordlines. The column test circuit couples the bitlines to the first voltage in response to activation of a test wordline during a testing operation, where the bitlines are precharged to a second voltage during a normal read operation. The sense circuitry senses the voltage of the bitlines and the test bitline. According to embodiments of the second aspect, the row test circuit is connected to a first end of the wordlines, and row circuits for driving the wordlines are connected to a second end of the wordlines opposite to the first end. The row test circuit includes a column of row test cells having their gate terminals formed by the wordlines, each of the row test cells being connected to the test bitline. The column test circuit is connected to a first end of the bitlines, and column circuits are connected to a second end of the bitlines opposite to the first end. The column test circuit includes a row of column test cells connected to the bitlines and have their gates formed by the test wordline. The row test cells and the column test cells include mask programmable cells having a first diffusion region connected to the first voltage and a second diffusion region connected to one of the bitlines and the test bitline.

[0022] In a third aspect, the present invention provides a method for testing an unprogrammed one time programmable (OTP) memory array. The method includes activating a test circuit and sensing the at least one bitline. The step of activating includes coupling at least one bitline to a first voltage level, the at least one bitline being precharged to a second voltage level during a normal read operation. The step of sensing includes providing a logic state corresponding to one of a presence and absence of the voltage level. According to an embodiment of the third aspect, activating includes driving a wordline coupled to a row of programmed test memory cells, the programmed test memory cells coupling a plurality of bitlines to the first voltage level. The method can include a further step of iteratively changing a column address and sensing a different bitline of the plurality of bitlines. The programmed test memory cells can include mask

programmed memory cells. Prior to the step of activating, unprogrammed OTP memory cells are programmed to be the programmed test memory cells.

[0023] In another embodiment of the third aspect, the at least one bitline includes a test bitline connected to a column of programmed test memory cells, and activating includes driving a wordline coupled to one of the programmed test memory cells for coupling the test bitline to the first voltage level. This embodiment further includes precharging the test bitline to the second voltage level after the step of sensing, and changing a row address for driving another wordline coupled to another one of the programmed test memory cells. The programmed test memory cells can include mask programmed memory cells, or prior to activating, unprogrammed OTP memory cells are programmed to be the programmed test memory cells.

[0024] Other aspects and features of the present invention will become apparent to those ordinarily skilled in the art upon review of the following description of specific embodiments of the invention in conjunction with the accompanying figures.

BRIEF DESCRIPTION OF THE DRAWINGS

[0025] Embodiments of the present invention will now be described, by way of example only, with reference to the attached Figures, wherein:

Fig. 1 is a circuit diagram of a DRAM-type anti-fuse cell;

Fig. 2 is a planar layout of the DRAM-type anti-fuse cell of Figure 1;

Fig. 3 is a cross-sectional view of the DRAM-type anti-fuse cell of Figure 2 along line A-A;

Fig. 4a is a cross-sectional view of a variable thickness gate oxide anti-fuse transistor;

Fig. 4b is a planar layout of the variable thickness gate oxide anti-fuse transistor of Figure 4a;

Fig. 5 is a plan view of a single-transistor anti-fuse memory array using the variable thickness gate oxide memory cell of Fig. 4a;

Fig. 6 is a block diagram of an OTP memory device according to an embodiment of the present invention;

Fig. 7 is a plan view of a single-transistor anti-fuse memory array with row and column test circuits, according to an embodiment of the present invention;

Fig. 8 is a circuit schematic of the single-transistor anti-fuse memory array of Figure 7;

Fig. 9 is a plan view of a single-transistor anti-fuse memory array with row and column test circuits, according to an alternate embodiment of the present invention;

Fig. 10 is a circuit schematic of the single-transistor anti-fuse memory array of Figure 9;

Fig. 11 is a flow chart showing a method for testing an OTP memory array using row and column test circuits; and,

Fig. 12 is a plan view of a two-transistor anti-fuse memory array with row and column test circuits, according to an alternate embodiment of the present invention.

DETAILED DESCRIPTION

[0026] Generally, the present invention provides a method and system for testing unprogrammed OTP memories to ensure that wordline and bitline connections, column decoders, wordline drivers, correctness of decoding, sensing and multiplexing operate properly. The OTP testing system includes one or both of column test circuitry and row test circuitry. The column test circuitry couples all the bitlines to a voltage level similar to that provided by a programmed OTP memory cell during a read operation, in response to activation of a test wordline. The bitline voltages can be sensed, thereby allowing for testing of the column decoding and sense amplifier circuits. The row test circuitry couples a test bitline to a voltage level similar to that provided by a programmed OTP memory cell during a read operation, in response to activation of a wordline of the OTP memory array. The voltage of the test bitline can be sensed, thereby allowing for testing of the row decoding and driver circuits. Hence the continuity of signal lines such as wordlines and bitlines can be tested, as can the logic relied upon for driving these signal lines.

[0027] Figure 6 is a block diagram illustrating an embodiment of the present invention. OTP memory device **100** includes an OTP memory array **102** consisting of OTP memory cells connected to wordlines and bitlines, where the wordlines extend horizontally and the bitlines extend vertically within the OTP memory array **102**. Connected to a first end of the wordlines is a row circuit block **104** that includes row related circuits such as row decoders and row drivers for example. Connected to a first end of the bitlines is a column circuit block **106** that includes column related circuits such as column decoders and sense amplifiers for example. Connected to a second and opposite end of the wordlines is a row test circuit block **108** that is used for testing the functionality of the row circuits and the physical condition of each wordline. Connected to a second and opposite end of

the bitlines is a column test circuit block **110** that is used for testing the functionality of the column circuits and the physical condition of each bitline. It is noted that only the memory array and relevant memory array circuits are shown for OTP memory device **100**, as persons skilled in the art will understand that there are other circuits and logic that are required to enable proper operation. The physical placement of the row test circuits **108** and the column test circuits **110** enables testing of the physical integrity, or continuity, of the wordlines and the bitlines. To minimize circuit area overhead, the row test circuits **108** and the column test circuits **110** are formed as memory cells having the same physical layout and substantially the same construction as the memory cells of OTP memory array **102**. These test cells thus emulate the electrical behaviour of the OTP memory array memory cells. Further details of the row test circuits **108** and the column test circuits **110** according to one embodiment are shown in Figure 7.

[0028] Figure 7 is a plan view transistor level layout showing an example embodiment of the OTP memory device **100** of Figure 6. In particular, transistor level examples of the OTP memory array **102**, the row test circuit **108** and the column test circuit **110** are illustrated, while the column circuit block **106** represents known column circuits, such as precharge circuits, column decoders and sense amplifiers. The row circuit block **104** is not shown in Figure 7, however persons of skill in the art will understand that such circuits are well known in the art. All the transistors shown in Figure 7 are n-channel transistors. The OTP memory array **102** is an array of anti-fuse cells **30**, such as the single-transistor anti-fuse memory cells shown and described in Figures 4a, 4b and 5. In the present example, only four wordlines WL_i to WL_i+3 and four bitlines BL_n to BL_n+3 are shown for the OTP memory array **102**. These wordlines and bitlines are now referred to as normal wordlines and normal bitlines. The features of the single-transistor anti-fuse memory cell have been previously described, and are therefore not described again for the present embodiment.

[0029] The column test circuit **110** is connected to a second end of the normal bitlines opposite to the first end, which are connected to the column circuit block **106**. The purpose for this placement is to test the physical integrity of the entire bitline length. The column test circuit **110** includes a row of column test cells, such as mask programmed read only memory (MROM) cells, where there is a one-to-one ratio of MROM cells to normal bitlines. As shown in Figure 7, MROM cells **200**, **202**, **204** and **206** have a polysilicon gate that corresponds to test wordline WL_{test}, where each of the MROM cells has a drain terminal **208** connected to a corresponding normal bitline via a bitline contact, and a source terminal **210** connected to voltage supply VDD. According to the

present embodiment, each MROM cell is similar in construction to the anti-fuse transistor devices and are subjected to the same process steps, except that they do not have a variable thickness gate oxide. In the example of Figure 7, a thick gate oxide definition mask **212** identical to the thick gate oxide definition mask **72** in the OTP memory array **102**, is used to define a thick gate oxide over the channel regions underneath the polysilicon gate of WL_test. In otherwords, MROM cells **200**, **202**, **204** and **206** function similarly to either core logic transistors or I/O transistors formed on the same substrate as OTP memory device **100**.

[0030] In operation, each of the MROM cells charges its corresponding normal bitline to about $VDD - V_{tn}$, where V_{tn} is a threshold voltage of an n-channel transistor, in response to WL_test being activated or driven to a positive voltage level such as VDD or VREF. If there is a defect in the column decoding logic, or a physical defect such as a break in the bitline anywhere between the column test circuit **110** and the column circuits **106**, then that bitline will not have the $VDD - V_{tn}$ voltage level. Accordingly, the failure to sense the $VDD - V_{tn}$ voltage on a normal bitline indicates some type of failure related to that bitline or the column decoding for that bitline.

[0031] The row test circuit **108** is connected to a second end of the normal wordlines opposite to the first end, which are connected to row circuit block **104** (not shown). The purpose for this placement is to test the physical integrity of the entire wordline length. The row test circuit **108** includes a column of row test cells, such as MROM cells, where there is a one-to-one ratio of MROM cells to normal wordlines. As shown in Figure 7, MROM cells **214**, **216**, **218** and **220** each have a polysilicon gate corresponding to one of the normal wordlines, where each of the MROM cells has a shared drain terminal **222** connected to a test bitline BL_test via a bitline contact, and a shared or dedicated source terminal **224** connected to voltage supply VDD or VREF. Although the test bitline BL_test is connected to a test sense amplifier **226**, alternatively it can be selectively coupled to one of the normal sense amplifiers in block **106** during testing, as will be shown later in Figure 10. According to the present embodiment, each MROM cell is similar in construction to the anti-fuse transistor devices, except that they do not have a variable thickness gate oxide. In the example of Figure 7, the thick gate oxide definition mask **72** is extended to define a thick gate oxide over the channel regions underneath each polysilicon gate. In otherwords, MROM cells **214**, **216**, **218** and **220** function similarly to either core logic transistors or I/O transistors formed on the same substrate as OTP memory device **100**.

[0032] In operation, each of the MROM cells charges the test bitline BL_test to about $VDD - V_{tn}$, where V_{tn} is a threshold voltage of an n-channel transistor, in response to a normal wordline being activated or driven to a positive voltage level such as VDD. Provided there are no physical defects in the bitlines, all the normal bitlines and the test bitline BL_test are driven to the full VDD level if WL_test and each of the normal wordlines WLi to WLi+3 are driven to a voltage level above VDD. If there is a defect in the row decoding logic, or a physical defect such as a break in the normal wordline anywhere between the row test circuit **108** and the row circuits **104** (not shown), then the test bitline will not have the $VDD - V_{tn}$ voltage level. Accordingly, the failure to sense the $VDD - V_{tn}$ voltage on BL_test indicates some type of failure related to that row.

[0033] Figure 8 shows the equivalent circuit schematic of the OTP memory array **102**, row test circuit **108** and column test circuit **110**. The anti-fuse cells **30** used in Figure 8 are represented by a distinct transistor symbol that is different than the well known symbol for n-channel transistors. In particular, the presently used anti-fuse transistor symbol designates that the anti-fuse transistor has a variable thickness gate oxide. The column circuit block **106** is shown as a generic box as in Figure 7. Figure 8 clearly shows how the column testing circuit **110** can coupling the normal bitlines to a voltage level that can be sensed by column circuit block **106**, and how the row testing circuit **108** can couple the test bitline to a voltage level that can be sensed by test sense amplifier **226**. Because these bitline voltages can be sensed, the row circuits **104** and the column circuits **106** can be tested before shipment to the end user who will be programming the OTP memory array **102**. As will be described later, a testing algorithm can be developed to automatically cycle through the column and row addresses to check if the expected sensed data from the bitlines is read out properly or not.

[0034] In the embodiments of Figures 7 and 8, the row test circuit **108** and column test circuit **110** are considered part of the OTP memory array **102**, since the MROM cells are fabricated with substantially the same dimensions and process used for fabricating the anti-fuse memory cells. Accordingly, the circuit area overhead for implementing these test circuits is minimal. Figure 9 is an alternate embodiment of OTP memory device **100** that further minimizes circuit area overhead of a row test circuit and a column test circuit, according to an embodiment of the present invention.

[0035] In Figure 9, OTP memory device **300** includes the same OTP memory array **102** and column circuit block **106** shown in Figure 7. In the present embodiment, the column test circuit **302** includes a row of column test cells, such as anti-fuse transistors identical to anti-fuse cells **30** in OTP memory array **102**. This row of column test cells will be

programmed in a first test cycle. The row test circuit **304** is identical to the row test circuit **108** except that it does not include a test sense amplifier. Alternatively, the row test circuit **304** may include a column of row test cells, such as anti-fuse transistors (not shown) identical to anti-fuse cells **30** in OTP memory array **102**. This column of row test cells will be programmed in a first test cycle. Both test circuits have at least the same functionality as the corresponding test circuits shown in Figure 7. The column test circuit **302** includes anti-fuse transistors **306**, **308**, **310** and **312**, each having a gate formed by the polysilicon test wordline WL_test. Each of the anti-fuse transistors **306**, **308**, **310** and **312** has a drain diffusion region **314** with a bitline contact connected to a corresponding normal bitline. A thick gate oxide definition mask **316** delineates the thick and thin gate oxide portions of the variable thickness gate oxide of the anti-fuse transistors, such that the part of the active area not covered by the thick gate oxide definition mask **316** underneath the polysilicon wordline WL_test is covered by a thin gate oxide. Accordingly, the structure of the anti-fuse transistors **306**, **308**, **310** and **312** should be the same as the anti-fuse cells **30** formed in the OTP memory array **102**. The anti-fuse transistors **306**, **308**, **310** and **312** do not consume as much substrate area as MROM cells **200**, **202**, **204** and **206**, thereby reducing the circuit area overhead of column test circuit **302** relative to column test circuit **110**. In the row test circuit **304**, a test coupling device shown as an n-channel transistor **318** selectively connects the test bitline BL_test to the adjacent normal bitline BL_n+3 in response to a test control signal TEST.

[0036] Figure 10 shows the equivalent circuit schematic of the OTP memory array **102**, row test circuit **304** and column test circuit **302**. In order to illustrate the programmed status of anti-fuse transistors **306**, **308**, **310** and **312**, a resistor symbol is connected between the gate terminal and the source terminal of each anti-fuse transistor **306**, **308**, **310** and **312**. The absence of this resistor indicates the unprogrammed status of the anti-fuse transistor. Accordingly, once successfully programmed, the column test circuit **302** can be used to couple the normal bitlines to VDD.

[0037] The general operation of column test circuit **302** is now described. Prior to testing the functionality of the column circuits **106**, the anti-fuse transistors **306**, **308**, **310** and **312** are programmed. This is done by biasing the normal bitlines to VSS while driving the test wordline WL_test to VPP. If programming is successful, conductive links **320** will be formed in each of anti-fuse transistors **306**, **308**, **310** and **312**. Hence any program verify logic can be tested as part of the programming operation for the anti-fuse transistors of column test circuit **302**. In a fabricated device, there can be redundant test rows and test columns so that if one is defective for any reason, the other can be used instead.

Assuming that programming is successful, the column circuits **106** can be tested by driving WL_test to a read voltage level, such as VDD for example. Because each of anti-fuse transistors **306**, **308**, **310** and **312** has a conductive link formed therein, WL_test couples the normal bitlines to VDD.

[0038] The general operation of row test circuit **304** is now described. During the test mode, signal TEST is driven to VDD to turn on test coupling device **318** and connect BL_test to BLn+3. The column decoding logic within column circuit block **106** then routes the voltage of BL_test to an existing sense amplifier, which then provides a logic state corresponding to the voltage of BL_test. Hence an existing sense amplifier is reused, thereby obviating the need to include an extra dedicated sense amplifier for row test circuit **304**.

[0039] It is noted that different combinations of the row test circuit and the column test circuit embodiments shown in Figures 7 and 9 can be used together with an OTP memory array. For example, the MROM cells of the row test circuit **304** can be replaced with anti-fuse cells. Accordingly, prior to executing any testing of the rows, these anti-fuse cells are first subjected to programming. Alternately, just one of the row test circuit and the column test circuit can be used with an OTP memory array. While the data can be read out of the memory device for assessment by external testing apparatus, self test logic can be included on-chip for comparing the sensed data logic levels against expected logic levels.

[0040] Figure 11 is a flow chart showing a method for testing the OTP memory array using the previously described row and column test circuits, according to an embodiment of the present invention. The method steps can be automated and designed as a built-in-self-test (BIST) algorithm executable by an on-chip controller, or executed automatically via an external computing device. If the column test circuit **302** embodied in Figure 9 is used, then it is assumed that all the anti-fuse cells of column test circuit **302**, such as cells **306**, **308**, **310** and **312**, have been successfully programmed. The test method begins at step **400**, where a first row is activated, or driven to a voltage level effective for turning on the transistor devices it is connected to. This first row can include either the test wordline WL_test of the column test circuits **110** or **302** for turning on the MROM cells or the anti-fuse cells therein, or one of the normal wordlines WLi to WLi+3 for turning on the MROM cells of the row test circuits **108** or **304**. This results in coupling of the normal bitlines BLn to BLn+3 or of the test bitline BL_test to VDD. Following at step **402**, sensing of the normal bitlines or the test bitline occurs and the result of the sensing is provided to the test system or tester for determination of a pass or fail result.

[0041] It should be noted that the column decoding circuits typically couple a predetermined number of the bitlines to a limited number of sense amplifier circuits. In such a memory architecture, a decision is made at step **404** to determine if there are further columns to sense. In the situation where there are further columns to sense, the column address is changed at step **406**, and other bitlines are sensed at step **402**. The iteration of steps **402**, **404** and **406** are executed when the column test circuit is used to test column decoding for all the column addresses. For row testing, step **402** is executed once for the test bitline. In such a case, the method proceeds to step **408**.

[0042] A determination is made at step **408** if there are further wordlines to drive or not. If the current test is for testing the column circuits, then there are no further wordlines to drive. Accordingly, the test ends at step **410**. On the other hand, if the current test is for testing the row circuits, then other wordlines remain to be driven. In this situation, the method proceeds to step **412** where the test bitline is discharged, and the row address is changed at step **414**. The row address can be changed according to any pattern, such as a sequential pattern for example. Once the new row address has been latched, then the method returns to step **400** where a new wordline corresponding to the new row address is driven. Steps **400**, **402**, **404**, **408**, **412** and **414** iterate until there are no further wordlines to be driven. The number of iterations can be reduced by having the system terminate the test if a fail result is received after any iteration. Therefore, the steps outlined in Figure 11 can be used for column circuit testing or row circuit testing using the column and row test circuit embodiments respectively. If both the column test circuit and the row test circuit are included in the memory device, then testing for both the column circuits and the row circuits can be executed in any order.

[0043] The previously described embodiments of the OTP memory device **100** and the OTP memory device **300** of Figures 7 and 9 use single transistor anti-fuse cells shown in Figures 4a and 4b. The embodiments of the present invention are not limited to single transistor anti-fuse transistors, and alternate embodiments where the memory array consists of two-transistor anti-fuse cells can be used. For example, the two-transistor anti-fuse cell of Figures 2 and 3 can be used in an OTP memory array **102**, a column test circuit and a row test circuit, according to the present alternate embodiment.

[0044] Figure 12 is a plan view of a two-transistor anti-fuse memory array with row and column test circuits, according to an alternate embodiment of the present invention. OTP memory device **500** includes an OTP memory array **502**, column circuits **504**, a column test circuit **506** and a row test circuit **508**. The row circuits are not shown in Figure 12, and the column circuits **504** can be the same as column circuits **106** shown and

described in the previous embodiments. The OTP memory array **502** is shown to include two rows of two-transistor anti-fuse cells. Each of the two-transistor anti-fuse cells has the structure shown in Figures 2 and 3, where an access transistor **510** is formed in series with an anti-fuse device **512**. The first row includes wordline WL0 and VCP0, while the second row includes wordline WL1 and VCP1. A thick gate oxide definition mask **514** defines the areas within which thick oxide is to be formed. As shown in Figure 12, the two-transistor cells in the first row and the second row of the same column share a common diffusion region **516** having a bitline contact connected to a corresponding bitline.

[0045] In the alternate embodiment of Figure 12, the column test circuit **506** includes two-transistor anti-fuse cells which are identical in layout dimensions to those in the OTP memory array **502**. The gate terminal of the access transistor **520** is formed by a polysilicon line WL_test, and the gate terminal of the anti-fuse device **522** is formed by a polysilicon line VCP_test. A diffusion region **524** of the access transistor **520** is coupled to a corresponding normal bitline. These anti-fuse cells differ from those in the OTP memory array **502**. First, the thick oxide definition mask **518** covers both the access transistor **520** and the anti-fuse device **522**, meaning that the anti-fuse device is formed with a thick gate oxide. Second, the anti-fuse device **522** has an additional diffusion region that is coupled to the VDD supply. Therefore, when both VCP_test and WL_test are driven to at least VDD, both the access transistor **520** and the anti-fuse device **522** turn on to couple the normal bitline to VDD, thereby coupling the normal bitline to VDD. Accordingly, the two-transistor anti-fuse cells of the column test circuit **506** are fabricated as MROM cells. Alternately, the thick oxide definition mask **518** can be sized to exclude the anti-fuse device **522**, and the additional diffusion region coupled to VDD can be omitted, thereby configuring these anti-fuse cells to be identical to those in the OTP memory array **502**. In such an alternate configuration, the anti-fuse cells are programmed before any testing operations are to be executed.

[0046] The row test circuit **508** includes two-transistor anti-fuse cells which are identical in layout dimensions to those in the OTP memory array **502**. The gate terminal of the access transistor **526** is formed by the polysilicon wordline of the corresponding row (ie. WL1), and the gate terminal of the anti-fuse device **528** is formed by the polysilicon line of the same corresponding row (ie. VCP1). A diffusion region **530** of the access transistor **526** is coupled to a test bitline BL_test via a bitline contact. The test bitline BL_test is connected to a dedicated test sense amplifier **532**, but as shown in the previous embodiments, BL_test can be routed to a normal bitline for sensing by an existing sense

amplifier. The two-transistor anti-fuse cells of row test circuit **508** are the same as those in column test circuit **506**, in that the anti-fuse device **528** has an additional diffusion region coupled to VDD, and has a thick gate oxide as defined by the area covered by the thick gate oxide definition mask **514**. Therefore, BL_test is coupled to VDD when a wordline and its corresponding VCP are driven to at least VDD. As for anti-fuse devices in the row test circuit **508**, they can be configured as true anti-fuse cells which are programmed before any testing operations are executed.

[0047] According to a further alternate embodiment, either the anti-fuse device or access transistor can be omitted from one or both of the column test circuit **506** and the row test circuit **508** to further minimize circuit area overhead.

[0048] The previously described embodiments permit testing of an unprogrammed OTP memory array, and in particular the physical conductor lines that extend across the memory array and corresponding logic circuitry associated with these conductor lines. As shown in the previous embodiments, the physical conductor lines are the bitlines and the corresponding logic circuitry is the column decoding logic. Alternately, the physical conductor lines are the wordlines and the corresponding logic circuitry is the row decoding logic. Of course, other circuits related to the physical conductor lines can be tested for proper functionality using the previously described embodiments simply by executing read and/or program operations.

[0049] In the preceding description, for purposes of explanation, numerous details are set forth in order to provide a thorough understanding of the embodiments of the invention. However, it will be apparent to one skilled in the art that these specific details are not required in order to practice the invention. In other instances, well-known electrical structures and circuits are shown in block diagram form in order not to obscure the invention. For example, specific details are not provided as to whether the embodiments of the invention described herein are implemented as a software routine, hardware circuit, firmware, or a combination thereof.

[0050] Embodiments of the invention can be represented as a software product stored in a machine-readable medium (also referred to as a computer-readable medium, a processor-readable medium, or a computer usable medium having a computer-readable program code embodied therein). The machine-readable medium can be any suitable tangible medium, including magnetic, optical, or electrical storage medium including a diskette, compact disk read only memory (CD-ROM), memory device (volatile or non-volatile), or similar storage mechanism. The machine-readable medium can contain various sets of instructions, code sequences, configuration information, or other data,

which, when executed, cause a processor to perform steps in a method according to an embodiment of the invention. Those of ordinary skill in the art will appreciate that other instructions and operations necessary to implement the described invention can also be stored on the machine-readable medium. Software running from the machine-readable medium can interface with circuitry to perform the described tasks.

[0051] The above-described embodiments of the invention are intended to be examples only. Alterations, modifications and variations can be effected to the particular embodiments by those of skill in the art without departing from the scope of the invention, which is defined solely by the claims appended hereto.

CLAIMS:

1. A one time programmable (OTP) memory comprising:
 - 5 a memory array having unprogrammed OTP cells;
 - decoding circuits located at a first end of the memory array;
 - a test circuit located at a second and opposite end of the memory array for coupling at least one bitline towards a first voltage in response to an activated wordline during a testing operation, the at least one bitline being precharged to a second voltage
 - 10 during a normal read operation; and
 - sense circuitry for sensing the voltage of the at least one bitline.
2. The OTP memory of claim 1, wherein the first voltage of the at least one bitline corresponds to a read voltage provided by a programmed OTP cell.
- 15 3. The OTP memory of claim 1, wherein the test circuit couples a plurality of bitlines connected to the unprogrammed OTP cells to the first voltage, and the decoding circuits include column circuits connected to the plurality of bitlines.
- 20 4. The OTP memory of claim 3, wherein the test circuit includes a row of test cells having their gate terminals formed by the activated wordline, each of the test cells being connected to one of the plurality of bitlines.
5. The OTP memory of claim 4, wherein each of the test cells is mask programmed to
- 25 couple the first voltage to a corresponding bitline in response to the activated wordline.
6. The OTP memory of claim 4, wherein each of the test cells is identical in structure and layout to one of the unprogrammed OTP cells, and programmable for coupling the first voltage of the activated wordline to a corresponding bitline.
- 30 7. The OTP memory of claim 4, wherein each of the unprogrammed OTP cells and each of the test cells are single transistor anti-fuse cells having identical layouts.
8. The OTP memory of claim 4, wherein each of the unprogrammed OTP cells and each
- 35 of the test cells are two-transistor anti-fuse cells having identical layouts.

9. The OTP memory of claim 1, wherein the decoding circuits include row circuits connected to a plurality of wordlines, the activated wordline being one of the plurality of wordlines, and the plurality of wordlines being connected to rows of the unprogrammed OTP cells.

10. The OTP memory of claim 9, wherein the test circuit includes a column of test cells having their gate terminals formed by the plurality of wordlines, each of the test cells being connected to the at least one bitline.

11. The OTP memory of claim 10, wherein each of the test cells is mask programmed to couple the first voltage to the at least one bitline in response to the activated wordline.

12. The OTP memory of claim 10, wherein each of the test cells is identical in structure and layout to one of the unprogrammed OTP cells, and programmable for coupling the first voltage of the activated wordline to a corresponding bitline.

13. The OTP memory of claim 10, wherein the sense circuitry is a dedicated test sense amplifier for sensing the first voltage of the at least one bitline.

14. The OTP memory of claim 13, wherein the test circuit includes a test coupling device for selectively connecting the at least one bitline to a bitline connected to a column of unprogrammed OTP cells.

15. A one time programmable (OTP) memory comprising:
a memory array having unprogrammed OTP cells connected to wordlines and bitlines;
a row test circuit connected to the wordlines for charging a test bitline to a first voltage in response to activation of one of the wordlines;
a column test circuit for coupling the bitlines to the first voltage in response to activation of a test wordline during a testing operation, the bitlines being precharged to a second voltage during a normal read operation; and
sense circuitry for sensing the voltage of the bitlines and the test bitline.

16. The OTP memory of claim 15, wherein the row test circuit is connected to a first end

of the wordlines, and row circuits for driving the wordlines are connected to a second end of the wordlines opposite to the first end.

17. The OTP memory of claim 16, wherein the column test circuit is connected to a first end of the bitlines, and column circuits are connected to a second end of the bitlines opposite to the first end.

18. The OTP memory of claim 17, wherein the row test circuit includes a column of row test cells having their gate terminals formed by the wordlines, each of the row test cells being connected to the test bitline.

19. The OTP memory of claim 18, wherein the column test circuit includes a row of column test cells connected to the bitlines and having their gates formed by the test wordline.

20. The OTP memory of claim 19, wherein the row test cells and the column test cells include mask programmable cells having a first diffusion region connected to the first voltage and a second diffusion region connected to one of the bitlines and the test bitline.

21. A method for testing an unprogrammed one time programmable (OTP) memory array comprising:

activating a test circuit for coupling at least one bitline to a first voltage level, the at least one bitline being precharged to a second voltage level during a normal read operation; and,

sensing the at least one bitline to provide a logic state corresponding to one of a presence and absence of the voltage level.

22. The method of claim 21, wherein activating includes driving a wordline coupled to a row of programmed test memory cells, the programmed test memory cells coupling a plurality of bitlines to the first voltage level.

23. The method of claim 22, further including iteratively changing a column address and sensing a different bitline of the plurality of bitlines.

24. The method of claim 23, wherein the programmed test memory cells include mask programmed memory cells.

5 25. The method of claim 23, wherein prior to activating, unprogrammed OTP memory cells are programmed to be the programmed test memory cells.

26. The method of claim 21, wherein the at least one bitline includes a test bitline connected to a column of programmed test memory cells, and activating includes driving
10 a wordline coupled to one of the programmed test memory cells for coupling the test bitline to the first voltage level.

27. The method of claim 26, further including precharging the test bitline to the second voltage level after the step of sensing, and changing a row address for driving another
15 wordline coupled to another one of the programmed test memory cells.

28. The method of claim 26, wherein the programmed test memory cells include mask programmed memory cells.

20 29. The method of claim 26, wherein prior to activating, unprogrammed OTP memory cells are programmed to be the programmed test memory cells.