

DESCRIPTION

Title of Invention

ENCODING RATIO SETTING METHOD AND RADIO
COMMUNICATION DEVICE

5

Technical Field

[0001] The present invention relates to a coding rate setting
method and a radio communication apparatus used for a radio
communication system using adaptive modulation and the multiple
10 input multiple output (MIMO) technology.

Background Art,

[0002] For an uplink channel of 3rd generation partnership
project radio access network long term evolution (3GPP RAN
15 LTE, hereinafter referred to as "LTE"), single-carrier
transmission is adapted to achieve a low peak to average power
ratio (PAPR).

[0003] Further, for an LTE uplink channel, to achieve high
throughput, adaptive modulation (AMC: adaptive modulation and
20 coding) is used so as to select the modulation and coding scheme
(MCS) pattern for each user depending on the channel quality
indicator (CQI) of each user.

[0004] Further, introduction of the MIMO system is being
considered to achieve higher transmission rate and to further
25 improve the efficiency of use of frequency. Introduction of a
rank transmission technique is also considered such as rank
adaptation with which the rank indication (the number of rank) is

adaptively switched depending on the status of a spatial propagation path to further improve transmission rate.

[0005] Under these circumstances, an agreement is made to time-multiplex control information and user data using the physical uplink shared channel (PUSCH) of the same subframe so as to maintain low PAPR even when both control information and user data are transmitted at the same time in an LTE uplink channel (see Non-Patent Literature 1).

[0006] The number of coded symbols, Q' , of control information to be multiplexed with user data is set based on equation 1.

[0007]

[1]

$$Q' = \min \left(\left\lceil \frac{O}{10^{\frac{-\Delta_{offset}^{PUSCH}}{10}} \cdot R_{data}} \right\rceil, 4 \cdot M_{sc} \right) = \min(Q1, Q2)$$

... (Equation 1)

where $\lceil x \rceil$ is an integer not greater than x , and $\min(x, y)$ is the value of the smaller one of x and y .

[0008] In equation 1, M_{sc} is the number of subcarriers per PUSCH subframe, and $\Delta_{PUSCHoffset}$ is a PUSCH offset which varies per control information such as ACK/NACK, rank indicator (RI), or CQI. $\Delta_{PUSCHoffset}$ is reported from a higher layer (see Non-Patent Literature 1).

[0009] O is the number of control information bits, and R_{data} is represented by equation 2.

[0010]

[2]

$$R_{data} = \frac{\sum_{r=0}^{C-1} K_r}{M_{sc} \cdot N_{symb}} \dots \text{(Equation 2)}$$

In equation 2, K_r is the number of bits on r -th block, C is the number of blocks per PUSCH subframe, and N_{symb} is the number of symbols per PUSCH subcarrier. The actual coding rate of user data is obtained by dividing R_{data} in equation 2 by the number of bits per symbol, and is in proportion to R_{data} in equation 2. Accordingly, R_{data} in equation 2 will be hereinafter referred to as “user data coding rate.”

[0011] In equation 1, $Q1$ is the number of coded symbols of control information that is set based on the number of control information bits O , user data coding rate R_{data} , and PUSCH offset $\Delta PUSCH_{offset}$, per control information. $Q2$ is the upper limit value of the number of coded symbols of control information. As shown in equation 1, the number of coded symbols of control information, Q' , is set by the smaller one of the number of symbols $Q1$ and upper limit value $Q2$.

[0012] Here, equation 1 is modified to provide equation 3. As is the case with R_{data} in equation 2, the actual coding rate of control information is obtained by dividing $R_{control}$ in equation 3 by the number of bits per symbol, and is in proportion to $R_{control}$ in equation 3. Accordingly, $R_{control}$ in equation 3 will be hereinafter referred to as “control information coding rate (coding rate of control information).”

[0013]

[3]

$$R_{control} = \frac{O}{Q'} = \max \left(\left\lfloor \frac{O}{\frac{O}{10^{\frac{-\Delta_{offset}^{PUSCH}}{10}}} \cdot R_{data}}} \right\rfloor, \frac{O}{4 \cdot M_{sc}} \right) = \max(R1, R2)$$

... (Equation 3)

where $\lceil x \rceil$ is an integer not greater than x, and $\max(x, y)$ is the
5 value of the greater one of x and y. In equation 3, R1 is the
coding rate that is set based on user data coding rate R_{data} and
PUSCH offset, $\Delta_{PUSCHoffset}$, per control information. R2 is the
lower limit value of control information coding rate $R_{control}$. As
is shown in equation 3, control information coding rate $R_{control}$ is
10 set to the value of the greater value of coding rate R1 and lower
limit value R2. A case will be described below where coding
rate R1 is greater than lower limit value R2, and control
information coding rate $R_{control}$ is set as coding rate R1.

[0014] In this case, in equation 3, when PUSCH offset
15 $\Delta_{PUSCHoffset}$ is greater than 0, control information coding rate
 $R_{control}$ is set lower than user data coding rate R_{data} . Generally,
unlike user data, control information is not retransmitted.
Therefore, by setting PUSCH offset $\Delta_{PUSCHoffset}$, to be greater
than 0 and using equation 3, it is possible to lower control
20 information coding rate $R_{control}$ than user data coding rate R_{data} to
enhance the capability of error correction of control information.

Citation List

Non-Patent Literature

[0015]

NPL1

- 5 3GPP TS 36.212 v8.4.0, "Uplink transport channels and control information"

Summary of Invention

Technical Problem

10 [0016] However, when control information coding rate R_{control} is set simply by using only user data coding rate R_{data} and PUSCH offset $\Delta\text{PUSCHoffset}$, per control information, there is a possibility that adaptive modulation is applied depending on a channel quality indicator of user, and efficiency of control
15 information transmission is decreased when rank indication of a data channel (hereinafter referred to as "data CH") in which user data is transmitted, is transmitted.

[0017] For example, when rank 2 is applied to a data CH and reception quality is deteriorated due to interference between
20 streams (inter-stream interference), in adaptive modulation, user data MCS is lowered and user data coding rate R_{data} is set lower to prevent the decrease in the efficiency of transmission due to deteriorated reception quality.

[0018] In such a case where user data MCS is lowered by
25 adaptive modulation, if control information coding rate R_{control} is set based on equation 3, control information coding rate R_{control} may be set excessively low. As a result of this, for example,

even when the rank indication of a control channel (hereinafter referred to as "control CH"), in which control information is transmitted, is not transmitted, and the control CH is not subject to the influence of interference between streams, control
5 information is encoded at a lower coding rate to have excessively high quality, therefore lowering the efficiency of control information transmission.

[0019] In view of the above, it is therefore an object of the present invention to provide a coding rate setting method and a
10 radio communication apparatus that can prevent control information from being encoded at an excessively low coding rate and can suppress the decrease in the efficiency of control information transmission.

15 Solution to Problem

[0020] A coding rate setting method according to the present invention sets a user data coding rate to be adaptively set according to a channel quality indicator of a user as a reference value, corrects the reference value based on a type of control
20 information to be time-multiplexed with the user data and a rank indication of a data channel in which the user data is transmitted, and

sets the corrected reference value as a control information coding rate.

25 [0021] A radio communication apparatus according to the present invention comprises a coding rate obtaining section that sets a user data coding rate to be adaptively set according to a

channel quality indicator of a user as a reference value, obtains the reference value corrected based on a type of control information to be time-multiplexed with the user data and a rank indication of a data channel in which the user data is transmitted, as a the control information coding rate, and an encoding section that encodes the control information based on the control information coding rate.

Advantageous Effects of Invention

[0022] According to the present invention, it is possible to prevent control information from being encoded at an excessively low coding rate, and suppress the decrease in the efficiency of control information transmission.

Brief Description of Drawings

[0023]

FIG.1 is a block diagram showing a main configuration of a terminal according to Embodiment 1 of the present invention;

FIG.2 is a block diagram showing a main configuration of a coding rate setting section according to Embodiment 1 of the present invention;

FIG.3 shows an example of a rank information offset table according to Embodiment 1 of the present invention;

FIG.4 shows another example of a rank information offset table according to Embodiment 1 of the present invention;

FIG.5 is a block diagram showing a main configuration of a terminal according to Embodiment 2 of the present invention;

FIG.6 is a block diagram showing a main configuration of a coding rate setting section according to Embodiment 2 of the present invention;

FIG.7 shows an example of a rank information offset table according to Embodiment 2 of the present invention;

FIG.8 shows another example of a rank information offset table according to Embodiment 2 of the present invention; and

FIG.9 shows yet another example of a rank information offset table according to Embodiment 2 of the present invention.

Description of Embodiments

[0024] Now, embodiments of the present invention will be described in detail with reference to the accompanying drawings.

[0025] (Embodiment 1)

A case will be described here with the present embodiment where a control information coding rate is set by a offset corresponding to a rank indication of a data CH in which user data is transmitted, when adaptive modulation is applied according to a channel quality indicator of a user. Control information may include ACK/NACK, RI, and CQI, for example, and is time-multiplexed with user data to be transmitted from a terminal apparatus (hereinafter referred to as "terminal") to a base station apparatus (hereinafter referred to as "base station").

[0026] The control information coding rate can be set either at a base station or at a terminal. A case will be described below where the control information coding rate is set at a terminal.

[0027] FIG.1 is a block diagram showing a main configuration

of a terminal according to the present embodiment. In FIG.1, receiving section 110 of terminal 100 comprises radio receiving section 111, cyclic prefix (CP) removing section 112, fast Fourier transform (FFT) section 113, propagation path estimation section 114, demodulation section 115, and decoding section 116. Further, in FIG.1, transmission section 120 of terminal 100 comprises coding rate setting section 121, coding rate setting section 122, coding modulation section 123, coding modulation section 124, channel multiplexing section 125, discrete Fourier transform-spread-OFDM (DFT-s-OFDM) section 126, CP adding section 127, and radio transmission section 128.

[0028] Radio receiving section 111 converts a received signal received via an antenna to a baseband signal, and outputs the baseband signal to CP removing section 112.

[0029] CP removing section 112 removes a cyclic prefix (CP) from the baseband signal output from radio receiving section 111 and outputs, as a time domain signal, the baseband signal without a CP to FFT section 113.

[0030] FFT section 113 obtains a frequency domain signal by performing a fast Fourier transform on the time domain signal output from CP removing section 112, and outputs the obtained frequency domain signal to propagation path estimation section 114 and demodulation section 115.

[0031] Propagation path estimation section 114 estimates the propagation path environment of the received signal by using a pilot signal contained in the frequency domain signal output from FFT section 113, and outputs the estimation result, which is the

estimated propagation path environment of the received signal, to demodulation section 115.

[0032] Demodulation section 115 applies a propagation path compensation with respect to the frequency domain signal which is output from FFT section 113, and from which the pilot signal is removed, based on the estimation result output from propagation path estimation section 114. Further, demodulation section 115 demodulates the frequency domain signal after propagation path compensation based on the same MCS as used at the base station, i.e. the same modulation scheme and coding rate, etc. to obtain a demodulated signal, and outputs the obtained demodulated signal to decoding section 116.

[0033] Decoding section 116 corrects errors with respect to the demodulated signal output from demodulation section 115, to obtain a decoded signal. Then, decoding section 116 extracts, from the obtained decoded signal, information such as an information data sequence, the number of bits per block K_r , the number of subcarriers per subframe M_{sc} , the number of symbols per subcarrier N_{symb} , a PUSCH offset, and a data CH rank indication (the number of a rank for a data CH). Information about M_{sc} and N_{symb} are set at favorable values at a base station by being adaptively modulated according to the CQI transmitted from terminal 100. Decoding section 116 outputs the extracted information on K_r , M_{sc} and N_{symb} to coding rate setting section 121, and outputs the extracted information on the PUSCH offset and the data CH rank indication to coding rate setting section 122.

[0034] Coding rate setting section 121 sets user data coding rate R_{data} based on information on K_r , M_{sc} , and N_{symb} input from decoding section 116, based on equation 2. Coding rate setting section 121 outputs the set user data coding rate R_{data} to coding rate setting section 122 and coding modulation section 123.

[0035] Coding rate setting section 122 sets control information coding rate $R'_{control}$ based on information on user data coding rate R_{data} , the PUSCH offset, and the data CH rank indication. The internal configuration of coding rate setting section 122 and the method of setting control information coding rate $R'_{control}$ will be described later. Coding rate setting section 122 outputs the set control information coding rate $R'_{control}$ to coding modulation section 124.

[0036] Coding modulation section 123 generates encoded data by encoding the input user data based on information on user data coding rate R_{data} output from coding rate setting section 121, and generates data CH transmission data by modulating the generated encoded data. Coding modulation section 123 outputs the generated data CH transmission data to channel multiplexing section 125.

[0037] Coding modulation section 124 generates encoded data by encoding control information based on coding rate $R'_{control}$ output from coding rate setting section 122, and generates control CH transmission data by modulating the generated encoded data. Coding modulation section 124 outputs the generated control CH transmission data to channel multiplexing section 125.

[0038] Channel multiplexing section 125 time-multiplexes the

data CH transmission data output from coding modulation section 123 and the control CH transmission data output from coding modulation section 124, to generate multiplexed transmission data. Channel multiplexing section 125 outputs the multiplexed transmission data to DFT-s-OFDM section 126.

[0039] DFT-s-OFDM section 126 obtains a frequency domain signal by performing a discrete Fourier transform (DFT) on the multiplexed transmission data output from channel multiplexing section 125. DFT-s-OFDM section 126 maps the frequency domain signal on a transmission subcarrier, performs an inverse fast Fourier transform (IFFT) on the mapped frequency domain signal to obtain a transmission data sequence, and outputs the obtained transmission data sequence to CP adding section 127.

[0040] CP adding section 127 adds a CP to the transmission data sequence output from DFT-s-OFDM section 126 by duplicating the data in the end of a frame and inserting the duplicated data in the head of the frame, in each frame of the transmission data sequence, and outputs the transmission data sequence with a CP as the baseband signal, to radio transmission section 128.

[0041] Radio transmission section 128 converts the frequency with respect to the baseband signal output from CP adding section 127 into radio frequency bandwidth to obtain a transmission signal, and transmits the obtained transmission signal via an antenna.

[0042] FIG.2 is a block diagram showing an internal configuration of coding rate setting section 122 according to the present embodiment.

[0043] Rank information offset obtaining section 1221 stores rank information offset table 1222 inside, and obtains rank offset $\Delta RANK_{offset}$ from rank information table 1222 corresponding to the data CH rank indication. Rank information offset table 1222 will be explained later. Rank information offset obtaining section 1221 outputs the obtained rank offset $\Delta RANK_{offset}$ to coding rate calculating section 1223.

[0044] Coding rate calculating section 1223 sets control information coding rate $R'_{control}$ based on user data coding rate R_{data} , PUSCH offset $\Delta PUSCH_{offset}$ and rank offset $\Delta RANK_{offset}$, corresponding to the data CH rank indication, based on equation 4.

[0045]

[4]

$$R'_{control} = \frac{O}{Q'} = \max \left(\left\lceil \frac{O}{\frac{O}{10^{\frac{-\Delta PUSCH_{offset} + \Delta RANK_{offset}}{10}}} \cdot R_{data}} \right\rceil, \frac{O}{4 \cdot M_{sc}} \right) = \max(R'1, R'2)$$

... (Equation 4)

where $\lceil x \rceil$ is an integer not greater than x , and $\max(x, y)$ is the value of the greater one of x and y .

In equation 4, $R'1$ is a coding rate that is set based on user data coding rate R_{data} , PUSCH offset per control information which is defined as $\Delta PUSCH_{offset}$, and rank offset corresponding to the

data CH rank indication which is defined as $\Delta RANK_{offset}$. $R'2$ is the lower limit value of control information coding rate $R'_{control}$. A case will be described below where coding rate $R'1$ is greater than lower limit value $R'2$, and control information coding rate $R_{control}$ is set as coding rate $R'1$.

[0046] Further, in equation 4, O is the number of control information bits and Q' is the number of coded symbols of control information. The number of coded symbols of control information Q' is represented by equation 5.

[0047]

[5]

$$Q' = \min \left(\left\lceil \frac{O}{10^{\frac{-\Delta_{offset}^{PUSCH} + \Delta_{offset}^{RANK}}{10}} \cdot R_{data}} \right\rceil, 4 \cdot M_{sc} \right)$$

... (Equation 5)

where $\lceil x \rceil$ is an integer not greater than x , and $\min(x,y)$ is the value of the smaller one of x and y . As is obvious in equation 4, according to the present embodiment, by correcting user data coding rate R_{data} using PUSCH offset $\Delta PUSCH_{offset}$, corresponding to a type of control information and rank offset $\Delta RANK_{offset}$, corresponding to a data CH rank indication, it is possible to set the corrected user data coding rate as control information coding rate $R'_{control}$. In other words, by setting the user data coding rate R_{data} , to be adaptively set according to the user CQI, as a reference value, and by correcting the reference value based on PUSCH offset $\Delta PUSCH_{offset}$, corresponding to the

type of control information, and rank offset $\Delta\text{RANKoffset}$, corresponding to the data CH rank indication, it is possible to set the corrected reference value as control information coding rate R'_{control} .

5 [0048] As PUSCH offset $\Delta\text{PUSCHoffset}$ corresponding to the type of control information, $\Delta\text{HARQ-ACK}$ is used when control information is HARQ-ACK, ΔRI is used when control information is RI, and ΔCQI is used when control information is CQI, for example. An offset corresponding to the type of control
10 information such as $\Delta\text{HARQ-ACK}$, ΔRI , and ΔCQI is reported from a base station via a higher layer (see Non-Patent Literature 1).

[0049] FIG.3 shows an example of rank information offset table 1222 stored inside the rank information offset obtaining section
15 1221. According to the present embodiment, rank information offset table 1222 stores rank offset, $\Delta\text{RANKoffset}$, of a greater value for a data CH rank indication of a greater value. For example, in rank information offset table 1222 in FIG.3, rank offsets $\Delta\text{RANKoffset}$, are set at from a to z in ascending order of
20 data CH rank indications, and $\Delta\text{RANKoffset}$ values of from a to z are set to satisfy $z > \dots > b > a$.

[0050] As described above, by setting rank offset $\Delta\text{RANKoffset}$ of a greater value for the data CH rank indication of a greater value, it is possible to correct control information coding rate
25 R'_{control} , to be obtained based on equation 4, to become higher when the data CH rank indication is greater.

[0051] Generally, the influence of interference between streams

becomes greater when a rank indication is greater. Therefore, when a data CH rank indication is large, in adaptive modulation, user data MCS is lowered to ensure reception quality. That is, in adaptive modulation, user data coding rate R_{data} is set lower, when a data CH rank indication is greater and the influence of interference between streams is greater.

[0052] Therefore, in the case where user data coding rate R_{data} is set lower in adaptive modulation, when the control information coding rate is set using only PUSCH offset, $\Delta PUSCH_{offset}$, per control information, based on equation 3, for example, the control information coding rate is set further lower than user data coding rate R_{data} . Accordingly, there is a possibility that control information is encoded at an excessively low coding rate.

[0053] In contrast, according to the present embodiment, the control information coding rate is set by equation 4 using rank offset, $\Delta RANK_{offset}$, of a greater value for a data CH rank indication of a greater value, in addition to an offset per control information. By this means, the control information coding rate is corrected higher when the data CH rank indication is greater, and it is possible to prevent the control information coding rate from being set excessively low. In this way, according to the present embodiment, it is possible to obtain the control information coding rate by correcting the user data coding rate, based on the difference of the influence of interference between streams that a data CH suffers and the influence of interference between streams that a control CH suffers.

[0054] As described above, according to the present

embodiment, coding rate setting section 122 corrects the value of the user data coding rate to be adaptively set according to a channel quality indicator of a user, based on the type of control information to be time-multiplexed with user data and the rank indication of a data CH in which user data is transmitted, and sets the corrected value of the coding rate as the control information coding rate. That is, coding rate setting section 122 sets the user data coding rate to be adaptively set according to a channel quality indicator of a user, as a reference value, corrects the reference value based on the type of control information to be time-multiplexed with user data and the rank indication of a data CH in which user data is transmitted, and sets the corrected reference value as the control information coding rate. For example, coding rate setting section 122 sets control information coding rate R'_{control} to be time-multiplexed with user data, based on user data coding rate R_{data} , PUSCH offset $\Delta\text{PUSCHoffset}$, per control information, and rank offset $\Delta\text{RANKoffset}$, corresponding to a data CH rank indication, based on equation 4.

[0055] In this way, according to the present embodiment, the value of the user data coding rate is corrected based on the type of control information and the data CH rank indication, and the corrected value of the coding rate is set as the control information coding rate. By this means, even when the rank indication of a data CH in which user data is transmitted is greater and the user data coding rate is set lower in adaptive modulation, it is possible to prevent the control information coding rate from being set excessively low and suppress the

decrease in the efficiency of control information transmission.

[0056] Further, by correcting the control information coding rate to become higher when a data CH rank indication is greater, it is possible to correct the value of the user data coding rate, based on the difference of the influence of interference between streams that the data CH suffers and the influence of interference between streams that a control CH suffers, so as to set the user data coding rate as the control information coding rate. As a result of this, even when the user data coding rate is extremely low, it is possible to prevent the control information coding rate from being set excessively low and suppress the decrease in the efficiency of control information transmission.

[0057] A case has been described with the above embodiment as an example where rank information offset obtaining section 1221 stores rank information offset table 1222, in which the rank offset is defined separately for each rank indication, for example, from a to z. Rank information offset obtaining section 1221, however, may not store rank information offset table 1222, and may calculate rank offset $\Delta\text{RANKoffset}$ based on the equation shown as equation 6.

[6]

$$\Delta\text{RANKoffset} = (\text{rank indication} - 1) \times a \text{ (a is a constant)}$$

... (Equation 6)

[0058] Further, it is not necessary to define the rank offset at a different value for each rank indication, and it is possible to define the same rank offset for a plurality of rank indications. For example, it is possible to divide data channel rank indications

into a plurality of groups by comparing the data channel rank indications with a predetermined threshold value, and define a rank offset so that the control information coding rate is set higher when a data CH rank indication in each group is greater.

5 As shown in FIG.4, for example, it is possible to define all rank offsets at $a(a>0)$ for the rank indication of 2 or greater.

[0059] (Embodiment 2)

A case has been described with Embodiment 1 where, when a data CH rank indication is transmitted, the control information coding rate is set based on a rank offset corresponding to the data CH rank indication. A case will be described here with the present embodiment where, when a data CH rank indication and a control CH rank indication (the number of a rank for a control CH) are transmitted, the control information coding rate is set

10 coding rate is set based on a rank offset corresponding to the data CH rank indication. A case will be described here with the present embodiment where, when a data CH rank indication and a control CH rank indication (the number of a rank for a control CH) are transmitted, the control information coding rate is set

15 based on the rank offset based on the combination of the data CH rank indication and the control CH rank indication.

[0060] FIG.5 is a block diagram showing a main configuration of a terminal according to the present embodiment. In a terminal according to the present embodiment in FIG.5, parts that are the same as in FIG.1 will be assigned the same reference numerals as in FIG.1 and overlapping explanations will be omitted. In FIG.5, terminal 100a is provided with decoding section 116a and coding rate setting section 122a instead of decoding section 116 and coding rate setting section 122 in terminal 100 in FIG.1.

25 [0061] As is the case with Embodiment 1, the control information coding rate can be set either at a base station or at a terminal. A case will be described below where the control

information coding rate is set at a terminal.

[0062] Decoding section 116a obtains a decoded signal by correcting errors with respect to a demodulated signal output from demodulation section 115. Then, decoding section 116a extracts,
5 from the obtained decoded signal, information including an information data sequence, the number of bits per block K_r , the number of subcarriers per subframe M_{sc} , the number of symbols per subcarrier N_{symb} , the PUSCH offset, the data CH rank indication, and the control CH rank indication.

10 [0063] Decoding section 116a outputs the extracted information on K_r , M_{sc} , and N_{symb} to coding rate setting section 121, and outputs information on the PUSCH offset, the data CH rank indication and the control CH rank indication to coding rate setting section 122a.

15 [0064] Coding rate setting section 122a sets control information coding rate $R'_{control}$ based on information on user data coding rate R_{data} , the PUSCH offset, and the combination of the data CH rank indication and the control CH rank indication. The internal configuration of coding rate setting section 122 and the method of
20 setting control information coding rate $R'_{control}$ will be explained later. Coding rate setting section 122a outputs the set control information coding rate $R'_{control}$ to coding modulation section 124.

[0065] FIG.6 is a block diagram showing an internal configuration of coding rate setting section 122a according to the
25 present embodiment.

[0066] Rank information offset obtaining section 1221a stores rank information offset table 1222a inside, and obtains a rank

offset $\Delta\text{RANKoffset}$, corresponding to the combination of the data CH rank indication and the control CH rank indication, from rank information table 1222a. Rank information offset table 1222a will be explained later. Rank information offset obtaining section 1221a outputs the obtained rank offset $\Delta\text{RANKoffset}$, to coding rate calculating section 1223a.

[0067] Coding rate calculating section 1223a sets control information coding rate R'_{control} based on user data coding rate R_{data} , PUSCH offset $\Delta\text{PUSCHoffset}$, and rank offset $\Delta\text{RANKoffset}$, corresponding to the combination of the data CH rank indication and the control CH rank indication, based on equation 4.

[0068] FIG.7 shows an example of rank information offset table 1222a stored inside the rank information offset obtaining section 1221a. FIG.7 shows a case where the maximum rank indication is 2. According to the present embodiment, rank information offset table 1222a stores rank offsets $\Delta\text{RANKoffset}$, corresponding to the combinations of a data CH rank indication and a control CH rank indication. The relationship between rank offsets $\Delta\text{RANKoffset}$ and the combinations of a data CH rank indication and a control CH rank indication will be described below.

[0069] As shown in case #1 in FIG.7, when both the data CH rank indication and the control CH rank indication are 1, both the data CH and the control CH do not suffer interference between streams. Therefore, when obtaining the control information coding rate by correcting the user data coding rate, it is not necessary to consider the difference of the influence of

interference between streams that the data CH suffers and the influence of interference between streams that the control CH suffers. Accordingly, as shown in case #1, when both the data CH rank indication and the control CH rank indication are 1, rank offset $\Delta\text{RANKoffset}$ is set at 0. When rank offset $\Delta\text{RANKoffset}$ is 0, the control information coding rate coincides with the coding rate that is set based on equation 3.

[0070] As shown in case #2 in FIG.7, when the data CH rank indication is 1 and the control CH rank indication is 2, only control information suffers reception quality deterioration due to interference between streams. In this case, rank offset $\Delta\text{RANKoffset}$ is set at a ($a < 0$). By setting $\Delta\text{RANKoffset}$ smaller than 0, it is possible to set the control information coding rate obtained based on equation 4 lower than the control information coding rate obtained based on equation 3. By this means, it is possible to enhance the capability of error correction of control information.

[0071] As shown in case #3 in FIG.7, when the data CH rank indication is 2 and the control CH rank indication is 1, only user data suffers reception quality deterioration due to interference between streams. In this case, rank offset $\Delta\text{RANKoffset}$ is set at b ($b > 0$). By setting $\Delta\text{RANKoffset}$ greater than 0, it is possible to set the control information coding rate obtained based on equation 4 higher than the control information coding rate obtained based on equation 3. By this means, it is possible to prevent control information from being encoded at an excessively low coding rate and suppress the decrease in the efficiency of control information

transmission.

[0072] As shown in case #4 in FIG.7, when the data CH rank indication and the control CH rank indication are 2, both the data CH and the control CH suffer interference between streams. In this case, the influence of interference between streams is considered to be approximately equal between user data and control information. Accordingly, as shown in case #4, when both the data CH rank indication and the control CH rank indication are 2, the value (c), corresponding to the slight difference of the influence of interference between streams that the data CH suffers and the influence of interference between streams that the control CH suffers in the communication status between a base station and a terminal, is set as rank offset $\Delta\text{RANKoffset}$. When the influence of interference between streams that a data CH suffers and the influence of interference between streams that a control CH suffers are equal, rank offset $\Delta\text{RANKoffset}$ may be set at 0, as is the case with case #1.

[0073] FIG.8 shows another example of rank information offset table 1222a stored inside the rank information offset obtaining section 1221a. FIG.8 shows a case where the maximum rank indication is 4. The relationship between rank offset values $\Delta\text{RANKoffset}$ and the combinations of a data CH rank indication and a control CH rank indication will be described below. The explanation for cases #1 to 4 in FIG.8 are the same as for cases #1 to 4 in FIG.7, therefore the explanation will be omitted.

[0074] As shown in cases # 5 and 9 in FIG.8 and as is the case with case #2 in FIG.7, when the control CH rank indication is

greater than the data CH rank indication, control information reception quality deteriorates more severely than user data reception quality, due to the difference of the influence of interference between streams. In this case, rank offset
5 $\Delta\text{RANKoffset}$ is set smaller than 0. By setting $\Delta\text{RANKoffset}$ smaller than 0, it is possible to set the control information coding rate obtained based on equation 4 lower than the control information coding rate obtained based on equation 3. By this means, it is possible to enhance the capability of error correction
10 of control information. In this case, for example, when the greater absolute value of rank offset $\Delta\text{RANKoffset}$ is set as the data CH rank indication is smaller than the control CH rank indication, the control information coding rate becomes lower as the data CH rank indication is smaller than the control CH rank
15 indication. Therefore, it is possible to prevent the control information reception quality from being deteriorated.

[0075] As shown in cases # 6, 7, and 10-12 in FIG.8 and as is the case with case #3 in FIG.7, when the data CH rank indication is greater than the control CH rank indication, the user data
20 reception quality deteriorates more severely than the control information reception quality due to the difference of the influence of interference between streams. In this case, rank offset $\Delta\text{RANKoffset}$ is set greater than 0. By setting $\Delta\text{RANKoffset}$ greater than 0, it is possible to set the control
25 information coding rate obtained based on equation 4 higher than the control information coding rate obtained based on equation 3.

By this means, it is possible to prevent control information from

being encoded at an excessively low coding rate and suppress the decrease in the efficiency of control information transmission. In this case, for example, when the greater absolute value of rank offset $\Delta RANK_{offset}$ is set as the data CH rank indication is greater than the control CH rank indication, the control information coding rate becomes higher as the data CH rank indication is greater than the control CH rank indication. As a result of this, it is possible to prevent control information from being encoded at an excessively low coding rate and suppress the decrease in the efficiency of control information transmission.

[0076] As shown in cases # 8 and 13 in FIG.8 and as is the case with case #4 in FIG.7, when the data CH rank indication and the control CH rank indication are equal, the influence of interference between streams that the data CH suffers and the influence of interference between streams that the control CH suffers are considered to be approximately equal. In this case, as shown in case #4, when both the data CH rank indication and the control CH rank indication are equal, the value (g and l), corresponding to the slight difference of the influence of interference between streams that a data CH suffers and the influence of interference between streams that a control CH suffers in the communication status between a base station and a terminal, is set as rank offset $\Delta RANK_{offset}$. When the influence of interference between streams that the data CH and the influence of interference between streams that the control CH suffers are equal, rank offset $\Delta RANK_{offset}$ may be set at 0, as is the case with case #1.

[0077] FIG.9 shows yet another example of rank information offset table 1222a stored inside rank information offset obtaining section 1221a. In FIG.9, an identical rank offset $\Delta\text{RANKoffset}$ is defined for a plurality of combinations of a data CH rank indication and a control CH rank indication at rank information offset obtaining section 1221a. More specifically, an identical rank offset $\Delta\text{RANKoffset}$ is set for the combination where the data CH rank indication and the control CH rank indication are equal. The relationship between the combinations of a data CH rank indication and a control CH rank indication and rank offset $\Delta\text{RANKoffset}$ will be described below. FIG.9 shows a case where the maximum rank indication is 4, as is the case with FIG.8.

[0078] As shown in case #1 in FIG.9, when both the data CH rank indication and the control CH rank indication are 1, both the data CH and the control CH do not suffer interference between streams. Further, when both the data CH rank indication and the control CH rank indication are equal and are 2 or greater, the influence of interference between streams that the data CH suffers and the influence of interference between streams that the control CH suffers are considered to be approximately equal.

[0079] In this case, when the data CH rank indication and the control CH rank indication are equal, rank offset $\Delta\text{RANKoffset}$ is set at 0 assuming that the influence of interference between streams is equal between the data CH and the control CH.

[0080] As shown in cases #2-6 in FIG.9, when the data CH rank indication is greater than the control CH rank indication, the user

data reception quality deteriorates more severely than the control information reception quality due to the difference of the influence of interference between streams. In this case, rank offset $\Delta\text{RANKoffset}$ is set greater than 0. By setting
5 $\Delta\text{RANKoffset}$ greater than 0, it is possible to set the control information coding rate obtained based on equation 4 higher than the control information coding rate obtained based on equation 3. By this means, it is possible to prevent control information from being encoded at an excessively low coding rate and suppress the
10 decrease in the efficiency of control information transmission.

[0081] In this case, rank offset $\Delta\text{RANKoffset}$ of a greater value is set when the ratio of the data CH rank indication to the control CH rank indication (the data CH rank indication /the control CH rank indication) is greater. For example, in FIG.9, when the
15 relationship $p > n > m > o > q$ holds, the control information coding rate becomes higher as the data CH rank indication is greater than the control CH rank indication. Accordingly, it is possible to prevent control information from being encoded at an excessively low coding rate and suppress the decrease in the
20 efficiency of control information transmission.

[0082] As described above, according to the present embodiment, coding rate setting section 122a corrects the value of the user data coding rate to be adaptively set according to a channel quality indicator of a user, based on the type of control
25 information to be time-multiplexed with user data and the combination of the data CH rank indication and the control CH rank indication, and sets the corrected value of the coding rate as

the control information coding rate. That is, coding rate setting section 122a sets the user data coding rate to be adaptively set according to a channel quality indicator of a user as a reference value, corrects the reference value based on the type of control information to be time-multiplexed with user data and the combination of the data CH rank indication and the control CH rank indication, and sets the corrected reference value as the control information coding rate. For example, control information coding rate, R'_{control} , to be time-multiplexed with user data is set based on user data coding rate R_{data} , PUSCH offset $\Delta\text{PUSCHoffset}$ per control information, and rank offset, $\Delta\text{RANKoffset}$, corresponding to the combination of the data CH rank indication and the control CH rank indication, based on equation 4.

[0083] Further, by correcting the control information coding rate to be higher when the data CH rank indication is greater than the control CH rank indication, it is possible to correct the user data coding rate based on the difference of the influence of interference between streams that a data CH suffers and the influence of interference between streams that a control CH suffers, and set the control information coding rate. As a result of this, even when the user data coding rate is low, it is possible to prevent the control information coding rate from being set excessively low and suppress the decrease in the efficiency of control information transmission.

[0084] Although cases have been described above as examples where the control information coding rate is set at a terminal, the

present invention is by no means limited to this, and it is equally possible that a base station sets the control information coding rate and reports the set control information coding rate to a terminal, so that the terminal can obtain the reported control information coding rate.

[0085] Further, it is also possible that a base station sets rank offset $\Delta RANKoffset$ instead of the control information coding rate, and report the set rank offset $\Delta RANKoffset$ to a terminal so that the terminal can obtain the control information coding rate using the reported rank offset $\Delta RANKoffset$.

[0086] Further, it is also possible that a base station reports a rank information offset table to a terminal via a higher layer.

[0087] Further, the present invention is not limited to a data CH and a control CH, and is also applicable to other two channels having the different reception qualities required for the present invention.

[0088] Although cases have been described with the above embodiment as examples where the present invention is configured by hardware, the present invention can also be realized by software in combination with hardware.

[0089] Each function block employed in the description of each of the aforementioned embodiments may typically be implemented as an LSI constituted by an integrated circuit. These may be individual chips or partially or totally contained on a single chip.

LSI is adopted here but this may also be referred to as "IC", "system LSI", "super LSI", or "ultra LSI" depending on differing extents of integration.

[0090] Further, the method of circuit integration is not limited to LSI's, and implementation using dedicated circuitry or general purpose processors is also possible. After LSI manufacture, utilization of a programmable field programmable gate array (FPGA) or a reconfigurable processor where connections and settings of circuit cells within an LSI can be reconfigured is also possible.

[0091] Further, if integrated circuit technology comes out to replace LSI's as a result of the advancement of semiconductor technology or a derivative other technology, it is naturally also possible to carry out function block integration using this technology. Application of biotechnology is possible, for example.

[0092] The disclosure of Japanese Patent Application No. 2008-307658, filed on December 2, 2008, including the specification, drawings and abstract, is incorporated herein by reference in its entirety.

Industrial Applicability

[0093] The present invention is useful as a coding rate setting method and a radio communication apparatus used for the radio communication system using adaptive modulation and MIMO technology.

Reference Signs List

100, 100a Terminal

110 Receiving section

	111	Radio receiving section
	112	CP removing section
	113	FFT section
	114	Propagation path estimation section
5	115	Demodulation section
	116, 116a	Decoding section
	120	Transmission section
	121, 122, 122a	Coding rate setting section
	123, 124	Coding modulation section
10	125	Channel multiplexing section
	126	DFT-s-OFDM section
	127	CP adding section
	128	Radio transmission section
	1221, 1221a	Rank information offset obtaining section
15	1222, 1222a	Rank information offset table
	1223, 1223a	Coding rate calculating section

CLAIMS

Claim 1 A coding rate setting method:

 setting a coding rate of user data to be adaptively set
according to a channel quality indicator of a user as a reference
5 value;

 correcting the reference value based on a type of control
information to be time-multiplexed with the user data and a rank
indication of a data channel in which the user data is transmitted;
and

10 setting the corrected reference value as a coding rate of the
control information.

Claim 2 The coding rate setting method according to claim 1,
wherein:

15 a rank indication of a control channel in which the control
information is transmitted is 1; and

 the reference value is corrected so that the control
information coding rate becomes higher when the data channel
rank indication is greater.

20

Claim 3 The coding rate setting method according to claim 1,
wherein:

 a rank indication of a control channel in which the control
information is transmitted is 1;

25 the data channel rank indications are divided into a
plurality of groups by comparing the data channel rank
indications with a predetermined threshold value; and

the reference value is corrected so that the control information coding rate becomes higher when the data channel rank indication in each group is greater.

5 Claim 4 The coding rate setting method according to claim 1, wherein the reference value is corrected based on a combination of the data channel rank indication and a rank indication of a control channel in which the control information is transmitted.

10 Claim 5 The coding rate setting method according to claim 4, wherein the reference value is corrected so that the control information coding rate becomes higher when the data channel rank indication is greater than the control channel rank indication.

15

Claim 6 The coding rate setting method according to claim 4, wherein the reference value is corrected so that the control information coding rate becomes higher when a ratio of the data channel rank indication to the control channel rank indication is
20 greater.

Claim 7 The coding rate setting method according to claim 1, wherein control information coding rate R'_{control} , is set based on a PUSCH offset, $\Delta\text{PUSCHoffset}$, corresponding to the type of the
25 control information, and a rank offset, $\Delta\text{RANKoffset}$, corresponding to the data channel rank indication, based on equation 1.

[1]

$$R'_{control} = \max \left(\frac{O}{\left[\frac{O}{10^{\frac{-\Delta_{offset}^{PUSCH} + \Delta_{offset}^{RANK}}{10}}} \cdot R_{data} \right]}, \frac{O}{4 \cdot M_{sc}} \right) \quad \dots \text{ (Equation 1)}$$

where, in equation 1, max(x,y) is the value of the greater one of x
 5 and y, O is a number of symbols of control information, R_{data} is
 the user data coding rate, and M_{sc} is a number of subcarriers per
 PUSCH subframe.

Claim 8 The coding rate setting method according to claim 7,
 10 wherein:

the rank indication of a control channel in which the
 control information is transmitted is 1; and

the rank offset $\Delta RANK_{offset}$ of a greater value is set for
 the data channel rank indication of a greater value.

Claim 9 The coding rate setting method according to claim 7,
 wherein:

a rank indication of a control channel in which the control
 information is transmitted is 1;

20 the data channel rank indications are divided into a
 plurality of groups by comparing the data channel rank

indications with a predetermined threshold value; and

the rank offset $\Delta\text{RANKoffset}$ of a greater value is set for the data channel rank indication of a greater value in each group.

5 Claim 10 The coding rate setting method according to claim 7, wherein the control information coding rate R'_{control} is calculated based on the rank offset, $\Delta\text{RANKoffset}$, corresponding to a combination of the data channel rank indication and a rank indication of a control channel in which the control information is
10 transmitted.

Claim 11 The coding rate setting method according to claim 10, wherein an absolute value of the rank offset $\Delta\text{RANKoffset}$ becomes greater when a difference between the data channel rank
15 indication and the control channel rank indication is greater.

Claim 12 The coding rate setting method according to claim 10, wherein the rank offset $\Delta\text{RANKoffset}$ is set greater than 0 when the data channel rank indication is greater than the control
20 channel rank indication.

Claim 13 The coding rate setting method according to claim 10, wherein the rank offset $\Delta\text{RANKoffset}$ is set smaller than 0 when the data channel rank indication is smaller than the control
25 channel rank indication.

Claim 14 The coding rate setting method according to claim

10, wherein the rank offset $\Delta\text{RANKoffset}$ becomes greater when a ratio of the data channel rank indication to the control channel rank indication is greater.

5 Claim 15 A radio communication apparatus comprising:

 a coding rate obtaining section that sets a user data coding rate to be adaptively set according to a channel quality indicator of a user as a reference value, obtains the reference value corrected based on a type of control information to be time-
10 multiplexed with the user data and a rank indication of a data channel in which the user data is transmitted, as a control information coding rate; and

 an encoding section that encodes the control information based on the control information coding rate.