



G00002

- 1 -

TITLE OF THE INVENTION

METHOD AND APPARATUS FOR TURBO CODING AND DECODING IN
READ AND WRITE CHANNEL OF DISK DRIVE

BACKGROUND OF THE INVENTION

5 The present invention relates to the field of
data recording and reproduction of a disk drive, and
in particular, to a data recording and reproducing
technique to which a turbo coding/decoding method is
applied.

10 In general, a disk drive, represented by a hard
disk drive, is provided with a signal processing
circuit (hereinafter referred to as a "read/write
channel") to process a read signal (reproduced data
signal) read by a head from a disk as a recording
15 medium or a write signal (record data signal) written
to the disk.

 The read/write channel employs a so-called PRML
(Partial Response Maximum Likelihood) method,
a combination of a partial response (PR) method and
20 a Viterbi decoding method.

 In recent years, much attention has been paid to
a turbo coding/decoding method, which is expected to
provide better characteristics than the PRML method.
Prior art documents on this method include, for
25 example, "CODING AND ITERATIVE DETECTION FOR MAGNETIC
RECORDING CHANNELS", (Zinning Wu, Kluwer Academic
Publishers).

Specifically, a serial concatenated turbo coding and iterative decoding method has been proposed for the read/write channel of the disk drive. This method uses a recursive systematic convolutional (RSC) code
5 to generate a systematic code sequence consisting of an information sequence and a parity sequence. The information sequence corresponds to a recorded data sequence (input information sequence) used for the disk drive. Further, the parity sequence corresponds
10 to an error correction sequence (check bit sequence).

On the other hand, for a decoding system, an APP decoder is used which executes a posteriori probability (APP) decoding based on a soft-output Viterbi algorithm that achieves soft output decoding
15 on the basis of the Viterbi algorithm.

When the concatenated turbo coding/decoding method is applied to the read/write channel, an RSC encoder is used to generate a systematic code sequence consisting of an information sequence and a parity
20 sequence. This systematic code sequence has a coding rate of $1/2$, so that if it is directly written to the disk, processing efficiency may decrease. Thus, the capability of correcting errors may be relatively degraded. However, to increase the coding rate, a
25 decimation process called "puncture" is normally executed on the parity sequence.

However, with the concatenated turbo

coding/decoding method, improvement of the error
correction capability based on iterative decoding may
fail under certain combinations of puncture method and
RSC sequence as an outer code. This may result in a
5 failure to obtain a good error rate characteristic
(bit error rate characteristic).

BRIEF SUMMARY OF THE INVENTION

In accordance with one embodiment of the present
invention, there is provided a disk drive comprising a
10 read/write channel to which a concatenated turbo
coding and iterative decoding method is applied,
wherein the read/write channel has a puncture function
suitable for concatenated coding.

The disk drive comprises:

15 a head to read and write data from and to a disk
medium; and

a read/write channel that operates as a signal
processing unit and processes a record data signal or
a reproduction data signal transmitted to and from the
20 head, the read/write channel having a concatenated
turbo codec, and

wherein the concatenated turbo codec includes an
RSC encoder which encodes a recorded data sequence
into a recursive systematic code sequence for data
25 recording and a puncture unit which executes a
decimation process on the recursive systematic code
sequence at such a decimation rate that

a predetermined error rate is ensured in a decoding system.

Additional embodiments and advantages of the invention will be set forth in the description which follows, and in part will be obvious from the description, or may be learned by practice of the invention. The embodiments and advantages of the invention may be realized and obtained by means of the instrumentalities and combinations particularly pointed out hereinafter.

BRIEF DESCRIPTION OF THE SEVERAL VIEWS OF THE DRAWING

The accompanying drawings, which are incorporated in and constitute a part of the specification, illustrate presently preferred embodiments of the invention, and together with the general description given above and the detailed description of the embodiments given below, serve to explain the principles of the invention.

FIG. 1 is a block diagram showing an essential part of a disk drive according to an embodiment of the present invention;

FIGS. 2A and 2B are block diagrams showing an essential part of a turbo codec according to this embodiment;

FIG. 3 is a block diagram showing an example of an RSC encoder according to this embodiment;

FIG. 4 is a diagram useful in describing

an operation of a PUMUX according to this embodiment;

FIG. 5 is a diagram useful in describing an example of an error event that can be corrected by an APP decoder according to this embodiment;

5 FIG. 6 is a diagram useful in describing the error correction capability of a concatenated turbo codec according to this embodiment; and

FIG. 7 is a diagram useful in describing an operation of a PUMUX according to a variation of this
10 embodiment.

DETAILED DESCRIPTION OF THE INVENTION

An embodiment of the present invention will be described with reference to the drawings.

(Configuration of Disk Drive)

15 FIG. 1 is a block diagram showing an essential part of a disk drive according to this embodiment.

This disk drive has a disk 1 as a data recording medium, a preamplifier circuit 4, a read/write channel 5, and a disk controller (HDC) 6.

20 The disk 1 is rotated by a spindle motor (SPM) 2. The head 3 includes a read head and a write head and uses the read head to read data from the disk 1. The head 3 also uses the write head to write data to the disk 1. The preamplifier circuit 4 has a read
25 amplifier 40 that amplifies a read signal (reproduced data signal) from the read head and then sends it to the read/write channel 5. Further, the preamplifier

circuit 4 has a write amplifier 41 that converts a write signal (recorded data signal) output by the read/write channel 5, into a write current and then supplies it to the write head.

5 The read/write channel 5 includes an encoder/decoder (sometimes referred to as a "turbo codec") to which a turbo coding/decoding method is applied. The write channel is composed of a turbo encoder and a write signal processing circuit 51. The
10 write signal processing circuit 51 includes a recording compensation (precompensation) circuit.

 The read channel has a turbo decoder, an AGC circuit 52, a low pass filter (LPF) 53, an A/D converter 54, and an equalizer 55.

15 The AGC circuit 52 controls the amplitude of a read signal from the read amplifier 40 to a fixed value. The LPF 53 removes high-frequency noise from the read signal. The A/D converter 54 converts the analog read signal into a digital signal. The
20 equalizer 55 normally includes an FIR (Finite Impulse Response) type digital filter to execute a waveform equalization process.

 In this case, the read/write channel 5 is a PR channel in which its part starting with an input of
25 the write amplifier 41 and ending with an output of the equalizer 55 exhibits a desired PR (Partial Response) characteristic during digital magnetic

recording and reproduction. This part is considered to be a kind of convolution code and corresponds to an inner code for concatenated turbo coding.

(Configuration of Turbo Codec)

5 The turbo codec 50 is composed of a turbo encoder 20, shown in FIG. 2A, and a turbo decoder 21, shown in FIG. 2B. The turbo encoder 20 has an RLL (Run Length Limited) encoder 200, an interleaver 201, an RSC (Recursive Systematic Convolutional) code encoder 202, a PUMUX 203, and a precoder 204.

10 The RLL encoder 200 converts recorded data WD into an RLL code sequence. The interleaver 201 executes a process of disturbing (randomizing) the RLL code sequence. The RSC encoder 202 executes a recursive systematic coding process as an outer code on the RLL code sequence.

15 The PUMUX 203 is a combination of puncture and multiplex circuits. The PUMUX 203 multiplexes an information sequence and a parity sequence together to output the resulting systematic code sequence. The precoder 204 is installed to provide the PR channel with a recursive characteristic.

20 On the other hand, the turbo decoder 21 has an APP decoder 210 that executes an APP (A Posteriori Probability) decoding process on the PR channel (inner code), a DE-PUMUX 211, an interleaver 212, an APP decoder 213 that executes an APP decoding process on

an RSC sequence (outer code), a PUMUX 214 used to execute an iterative decoding process, and a deinterleaver 215.

5 The DE-PUMUX 211 is a circuit composed of a combination of a depuncture circuit and a demultiplexer to execute a conversion process inverse to the one executed by the PUMUX 203. Further, the deinterleaver 215 executes a conversion process inverse to the one executed by the interleaver 212.

10 Furthermore, the turbo decoder 21 includes a hard decision unit 216 and an RLL decoder 217. The hard decision unit 216 makes a binary decision using a log likelihood ratio output by the APP decoder 213, as a threshold value to determine a final turbo decoding sequence. The RLL decoder 217 executes an RLL decoding process on a turbo decoding sequence to output a reproduced data sequence (RD) corresponding to the original data. Then, the APP decoder 213 outputs external information on the outer code
15 excluding an LLR, to the PUMUX 214.
20

(Operation of Turbo Codec)

An operation of the turbo codec 50 will be described below.

25 To record data, the HDC 6 sends record data WD (information sequence) received from a host system (for example, a personal computer), to the read/write channel 5, as shown in FIG. 1. In the read/write

channel 5, the turbo encoder 20 executes a turbo coding process to output the resulting data to the write amplifier 41 via the write signal processing circuit 51.

5 In the turbo encoder 20, the RSC encoder 202 executes an RSC coding process on an RLL code sequence of the recorded data sequence WD. In this case, the RSC encoder 202 is composed of a one-bit delay element (D) and a mod 2 adder (exclusive logical OR gate (+)) as shown in, for example, FIG. 3.

FIG. 3 shows a specific example of the RSC encoder 202 having a restricted length of 3. In this case, the RLL code sequence is expressed as an input information sequence (U_k). Further, a parity sequence (P_k) generated by the RSC encoder 202 can be expressed by an internal sequence (Z_k).

In this case, the characteristics of the RSC encoder 202 can be expressed by Equation (1) using a one-bit delay operator D.

20

$$G(D) = \begin{bmatrix} 1 & \frac{1 + D^2}{1 + D + D^2} \end{bmatrix}_{\text{mod } 2} \quad \dots (1)$$

That is, with the RSC encoder 202 having such characteristics, when an input error sequence has a Hamming weight of 2 and is divisible by a generation matrix " $1 + D + D^2$ ", i.e. if the input error sequence is expressed by " $1 + D^{3i}$ (i is a natural number)",

an output error parity sequence is finite. This matrix is defined as a dominant error event.

Then, the PUMUX 203 executes a process of decimating the parity sequence according to a
5 predetermined coding rate (puncture rate), while inserting the decimated bits into the information sequence, and then outputs the resultant information sequence as a systematic code sequence. In this case, if, for example, the coding rate is assumed to be
10 33/34, the PUMUX 203 adds an arbitrary one bit from the parity sequence to the information sequence every 33 bits as shown in FIG. 4. In this case, if the n-th parity from the leading one is left, the point in time k at which the parity bit is left is expressed by
15 Equation (2).

$$k = 33j + n (j = \text{integer}) \quad \cdots (2)$$

In short, in terms of a general relationship, the point in time k at which the parity bit is left is expressed by $k = mj + d$ where d is a constant and j is
20 an integer equal to or larger than zero.

The precoder 204 executes a predetermined inverse conversion process on the systematic code sequence from the PUMUX 203 and then sends the processed systematic code sequence to the write signal
25 processing circuit 51. The write signal processing circuit 51 executes a recording compensation process on the systematic code sequence to dispatch the

resultant systematic code sequence to the write
amplifier 41. Accordingly, the write head records a
turbo coded recorded data signal on the disk 1 on the
basis of a write current supplied by the write
5 amplifier 41.

Then, when read from the disk 1 by the read head,
the reproduced data signal (DS) is amplified by the
read amplifier 40 and then transmitted to the
read/write channel 5. The reproduced data signal is
10 transmitted to the turbo decoder 21 through a series
of signal processing systems in the read channel.

In the turbo decoder 21, the APP decoder 210
decodes the inner code in the PR channel to output
external information on the inner code. The external
15 information on the inner code is transmitted to the
APP decoder 213 through the DE-PUMUX 211 and the
interleaver 212. The APP decoder 213 executes an APP
decoding process on the RSC sequence (outer code).

The APP decoder 213 can correct the matrix
20 " $1 + D^{3i}$ ", previously defined as a dominant error
event, if it meets a certain relationship with the
point in time at which the parity bit is left. That
is, if an RSC code is subjected to APP decoding, for
example, the matrix " $1 + D^{36}$ ", an error event, can be
25 corrected at the points of time shown by the circles
in FIG. 5 (here, the time zero indicates the point in
time at which the parity bit is left). Further, the

points of time at which the error event cannot be corrected can be collectively expressed as "3m".

Accordingly, to allow the error event to be corrected even at the points of time at which the error event otherwise cannot be corrected, the point in time at which the parity bit is left may be shifted from 3m. Specifically, the predetermined coding rate (puncture rate) in the PUMUX 203 may be set at, for example, 34/35.

FIG. 6 shows the points of time at which errors can be corrected at a puncture rate of 34/35. That is, FIG. 6 indicates that a parity bit A enables errors to be corrected at the points of time in the upper stage, while a parity bit B enables errors to be corrected at the points of time in the lower stage. Consequently, either parity bit enables correction at any point of time.

In short, for the RSC sequence of the matrix " $1 + D^c i$ (c is a constant, and i is a natural number)", a dominant error event, the predetermined coding rate (puncture rate) in the PUMUX 203 may be set according to the general relation " $m / (m + 1)$ ". In this case, $m = cn - b$, n is a natural number, and $b = (1, 2, \dots, c-1)$.

Then, in a variation of this embodiment, if the predetermined coding rate (puncture rate) in the PUMUX 203 is set at, for example, 33/34, the parity to be

left is varied for each puncture block. Specifically, as shown in FIG. 7, error correction is prevented from being disabled by setting the point in time at which the parity is left, as shown in Equation 3.

$$5 \quad k = 33j + n + (j \bmod 3) \quad \cdots (3)$$

In short, the point in time k at which the parity bit is left can be expressed by " $k = mj + d + (j \bmod c)$ " where d is a constant and j is an integer equal to or larger than zero.

10 As described above, according to this embodiment, in the turbo encoder 20, when the PUMUX 203 decimates a parity sequence of an RSC sequence output by the RSC encoder 202, the decimation is carried out at a coding rate (puncture rate) set in view of a dominant error
15 event, e.g. 33/34. This improves the error correction capability of the turbo decoder 21 when a turbo decoded sequence is determined by an iterative decoding process executed on the RSC sequence (outer code) and including an APP decoding process.
20 Consequently, in the read/write channel 5, to which a concatenated turbo coding/decoding method is applied, a good error rate characteristic (bit error characteristic) for a data decoding process is obtained.

25 As described above in detail, according to this embodiment, the error correction capability for data reproduction is improved to provide a good error rate

characteristic, particularly in a disk drive using a read/write channel to which a serial concatenated turbo coding/iterative decoding method is applied.

Additional advantages and modifications will
5 readily occur to those skilled in the art. Therefore, the invention in its broader aspects is not limited to the specific details and representative embodiments shown and described herein. Accordingly, various
modifications may be made without departing from the
10 spirit or scope of the general inventive concept as defined by the appended claims and their equivalents.

WHAT IS CLAIMED IS:

1. A disk drive comprising:

a head to read and write data from and to a disk medium; and

5 a read/write channel that operates as a signal processing unit and processes a record data signal or a reproduction data signal transmitted to or from the head, the read/write channel having a concatenated turbo codec, and

10 wherein the concatenated turbo codec includes an RSC encoder which encodes a record data sequence into a recursive systematic convolutional code sequence for data recording and a puncture unit which executes a decimation process on the recursive systematic
15 convolutional code sequence at such a decimation rate that a predetermined error rate is ensured in a decoding system.

2. A disk drive according to claim 1, further comprising:

20 an APP decoder to execute soft output decoding on the recursive systematic code sequence for data reproduction; and

a unit which executes a process inverse to the process executed by the puncture unit.

25 3. A disk drive according to claim 1, further comprising:

an APP decoder to execute soft output decoding on

the recursive systematic convolutional code sequence
for data reproduction;

a unit which executes a process inverse to the
process executed by the puncture unit; and

5 a turbo iterative decoder which determines a
decoding sequence that ensures the predetermined error
rate.

4. A disk drive according to claim 1, wherein
the puncture unit is configured so that for an RSC
10 code sequence of a matrix " $1 + D^c i$ " (c is a constant
and i is a natural number)" as a dominant error event,
a predetermined coding rate (puncture rate) is set
according to a general relation " $m / (m + 1)$ " where
 $m = cn - b$, n is a natural number, and $b = (1, 2, \dots,$
15 $c-1)$.

5. A disk drive according to claim 1, wherein
the puncture unit is configured so that for the RSC
code sequence of the matrix " $1 + D^c i$ " (c is a constant
and i is a natural number)" as a dominant error event,
20 the predetermined coding rate (puncture rate) is set
according to the general relation " $m / (m + 1)$ " where
 $m = cn - b$, n is a natural number, and $b = (1, 2, \dots,$
 $c-1)$, and a point in time k at which a parity bit is
left is set according to " $k = mj + d$ " where d is a
25 constant and j is an integer equal to or larger than
zero.

6. A disk drive according to claim 1, wherein

the puncture unit is configured so that for the RSC
code sequence of the matrix " $1 + D^c i$ " (c is a constant
and i is a natural number)" as a dominant error event,
the predetermined coding rate (puncture rate) is set
5 according to the general relation " $m / (m + 1)$ " where
 $m = cn - b$, n is a natural number, and $b = (1, 2, \dots,$
 $c-1)$, and the point in time k at which the parity bit
is left is set according to " $k = mj + d + (j \bmod c)$ "
where d is a constant and j is an integer equal to or
10 larger than zero.

7. A data recording and reproduction method
applied to a disk drive which records and reproduces
data on and from a disk medium, the data recording and
reproducing method using a concatenated turbo
15 coding/decoding method, the data recording and
reproduction method comprising:

coding a record data sequence into an RSC code
sequence on the basis of a turbo coding method when
data is written to said disk medium; and
20 carrying out puncture on the RSC code sequence at
such a decimation rate that a predetermined error rate
is ensured in a decoding system.

8. A method according to claim 7, wherein at the
step of executing the puncture, for an RSC code
25 sequence of a matrix " $1 + D^c i$ " (c is a constant and i
is a natural number)" as a dominant error event,
a predetermined coding rate (puncture rate) is set

according to a general relation " $m / (m + 1)$ " where $m = cn - b$, n is a natural number, and $b = (1, 2, \dots, c-1)$.

5 9. A method according to claim 7, wherein, at the step of executing the puncture, for the RSC code sequence of the matrix " $1 + D^i$ " (c is a constant and i is a natural number)" as a dominant error event, the predetermined coding rate (puncture rate) is set according to the general relation " $m / (m + 1)$ " where
10 $m = cn - b$, n is a natural number, and $b = (1, 2, \dots, c-1)$, and a point in time k at which a parity bit is left is set according to " $k = mj + d$ " where d is a constant and j is an integer equal to or larger than zero.

15 10. A method according to claim 7, wherein at the step of executing the puncture, for the RSC code sequence of the matrix " $1 + D^i$ " (c is a constant and i is a natural number)" as a dominant error event, the predetermined coding rate (puncture rate) is set
20 according to the general relation " $m / (m + 1)$ " where $m = cn - b$, n is a natural number, and $b = (1, 2, \dots, c-1)$, and the point in time k at which the parity bit is left is set according to " $k = mj + d + (j \bmod c)$ " where d is a constant and j is an integer equal to or
25 larger than zero.

 11. A method according to claim 7, further comprising:

executing an iterative decoding process based on a turbo decoding method, on the RSC code sequence decimated by the puncture, when data is reproduced from the disk medium.

5 12. A method according to claim 7, further comprising:

 executing soft output decoding on the recursive systematic convolutional code sequence when data is reproduced from the disk medium; and

10 executing a conversion process inverse to the puncture.

 13. A method according to claim 7, further comprising:

 executing soft output decoding on the recursive systematic convolutional code sequence when data is reproduced from the disk medium;

 executing a conversion process inverse to the puncture; and

 determining a decode sequence that ensures the predetermined error rate.

20