

5

IMPLANTABLE PULSE GENERATOR HAVING RECTANGULAR SHOCK WAVEFORM

The present invention relates to an implantable pulse generator.

10

Presently, capacitor discharges are always used in implantable defibrillators (ICDs) for defibrillation, wherein the entire shock energy is taken from a constant capacitance over the course of the defibrillation. The exponentially dropping voltage waveform is characteristic of this.

15

Shock waveforms that support a minimized shock voltage are already being used in external defibrillators.

20

The disadvantage of the exponential shock waveform is the high peak voltages that are needed to carry out effective defibrillation. In particular in the case of non-transvenous defibrillators (for example, subcutaneous ICDS such as S-ICD™), this results in peak voltages in excess of 1300 V, which, in turn, require appropriate high voltage components and compliance with aligned design rules.

25

Based thereon, it is an object of the present invention to provide an implantable pulse generator, which can provide a therapeutically effective shock using a lower shock voltage.

30

This object is achieved by an implantable pulse generator having the features of claim 1 and by a method having the features of claim 11. Suitable embodiments are provided in the dependent claims and in the following description.

According to claim 1, an implantable pulse generator comprising an electric circuit is provided. The electric circuit comprises:

- a primary energy store;
- at least one secondary energy store; and
- 5 – a control unit, wherein the control unit is configured
 - to activate an electric switch in the electric circuit in such a way that, in a first interval of a first phase of a pulse delivery, the primary energy store is discharged via a therapeutic current path, and
 - to activate an electric switch in the electric circuit in such a way that, in a
10 second interval of the first phase of a pulse delivery, the at least one secondary energy store is discharged via the therapeutic current path, wherein the primary energy store and the at least one secondary energy store are fixedly connected, or connectable, in series, and wherein the implantable pulse generator is designed to deliver a shock having an
15 approximately rectangular pulse waveform, wherein the implantable pulse generator comprises multiple secondary energy stores, and the control unit is further configured to activate an electric switch in the electric circuit in such a way that, in the second interval, the primary energy store and, consecutively, all secondary energy stores are discharged via the therapeutic
20 current path, or the primary energy store and in each case one of the multiple secondary energy stores are discharged via the therapeutic current path.

In particular, the therapeutic current path is used to deliver a therapeutic electrical pulse to
25 a target tissue, preferably the cardiac tissue of the patient, preferably for the delivery of a therapeutic electric shock for the defibrillation of the cardiac tissue.

Furthermore, in particular the primary energy store and the at least one secondary energy store are discharged, in the second interval of the first phase of the pulse delivery, via the
30 therapeutic current path.

Advantageously, a shock delivery having an approximately rectangular pulse waveform can be achieved by the pulse generator according to the invention, and in particular a substantially rectangular voltage or current waveform during the pulse delivery. In this way, it is possible to deliver a therapeutically effective (defibrillating) pulse over a defined
5 time, while reducing the maximum required shock voltage. The approach according to the invention advantageously allows a more cost-effective design for implantable defibrillators, and the use of existing high voltage components and platforms, in particular by reducing the maximum required shock voltage.

10 The implantable pulse generator according to the invention is therefore suitable, in particular, for use as a cardioverter defibrillator, so that it is possible to achieve therapy voltages of up to 1200 V having the above-described rectangular pulse waveform by way of the electric circuits according to the invention. In this way, the pulse generator according to the invention can be arranged as one electrode pole, and the end of an
15 electrode lead connected to the pulse generator can be arranged as the other electrode pole, outside the patient's thorax (subcutaneous ICD). Due to the possible more compact design, a pulse generator configured as a subcutaneous ICD advantageously has a volume of 70 cm³ or less.

20 Of course, it is also possible to achieve a lower therapy voltage with the pulse generator according to the invention, for example 600 V, which allows a use as a conventional ICD, wherein the end of the electrode lead is arranged inside the thorax, and the pulse generator is located outside the thorax. The aforementioned lower therapy voltage can be implemented by smaller energy stores. Due to the possible more compact design, a pulse
25 generator configured as a conventional ICD can accordingly have a volume of 35 cm³ or less.

The pulse generator according to the invention can also be used in an ICD in which both the end of the electrode lead and the pulse generator are located inside the thorax. In this
30 case, a therapy voltage of approximately 550 V is preferably used, which are implemented with the pulse generator according to the invention comprising smaller energy stores, so that in particular a device volume of 35 cm² or less can be achieved.

According to one embodiment of the implantable pulse generator according to the invention, it is provided that the primary energy store and the at least one secondary energy store are connected in series, in particular fixedly or inalterably in series, that is, the
5 aforementioned energy stores are not disconnected by a switch. As a result of this fixed series connection, the electric circuit according to the invention is advantageously less prone to faults.

According to an alternative embodiment of the implantable pulse generator, it is provided
10 that the primary energy store and the at least one secondary energy store can be connected in series.

According to one embodiment of the implantable pulse generator according to the invention, it is provided that the activation for the discharge of the at least one secondary
15 energy store takes place in a time-controlled or signal-controlled manner.

The control signal can be derived in the process from an analysis of one or more measuring voltages or currents, which are measured directly at the energy stores or at the delivered pulse, for example in the therapeutic current path.

20 Accordingly, according to one embodiment of the implantable pulse generator according to the invention, a device for voltage monitoring is included, which is in particular configured to determine the voltage of each of the energy stores of the implantable pulse generator according to the invention, preferably continuously or at predefined intervals.

25 The device for voltage monitoring is preferably further configured to transmit a first signal to the control unit when the voltage of one of the energy stores of the implantable pulse generator according to the invention drops below a predefined threshold value. The first signal can advantageously trigger the discharge of a further energy store via the therapeutic
30 current path.

The device for voltage monitoring is preferably also configured to transmit a second signal to the control unit when the voltage of one of the energy stores of the implantable pulse generator according to the invention does not drop below a predefined threshold value within a predefined time. The second signal can advantageously suppress a discharge of a further energy store via the therapeutic current path. In this design, the device for voltage monitoring and the control unit can implement an overvoltage protection system, in particular for the electric circuit according to the invention. It is established via the voltage measurement whether a load is present on the therapeutic current path (voltage drop) or no load is present (no voltage drop). If no load is detected, no further energy stores are discharged via the therapeutic current path so as not to further increase the voltage, for example in the therapeutic current path.

According to a further embodiment, the implantable pulse generator according to the invention comprises a device for measuring the impedance of the surrounding tissue (body tissue). The device for the impedance measurement is preferably configured to determine the resistance that causes the discharge (observed by the voltage drop) from a voltage ascertained after the start of the discharge of the primary energy store and/or of the at least one secondary energy store. The voltage can be the therapy voltage, the voltage of an individual energy store, or any voltage within the electric circuit according to the invention. The voltage can be ascertained in the process by the aforementioned device for voltage monitoring.

According to a further embodiment of the implantable pulse generator according to the invention, it is provided that the point in time for the start of the second interval of the first phase is determined from the discharge behavior of the first energy store and/or of the at least one secondary energy store. The aforementioned point in time is selected in such a way that the voltage of the particular energy store does not drop below a predefined threshold value, for example 80% of the output voltage.

According to a further embodiment of the implantable pulse generator according to the invention, it is provided that the electric circuit comprises multiple secondary energy stores, wherein the control unit is configured to activate one or more electric switches of

the electric circuit in such a way that the secondary energy stores are sequentially or consecutively discharged via the therapeutic current path in the second interval of the first phase of the pulse delivery.

- 5 According to a further embodiment of the implantable pulse generator according to the invention, it is provided that the primary energy store and the multiple secondary energy stores are connected in series, in particular fixedly or inalterably, that is, in particular without disconnectable switches between the energy stores.
- 10 According to an alternative embodiment of the implantable pulse generator, it is provided that the primary energy store and each of the multiple secondary energy stores can be connected in series, wherein in particular the secondary energy stores can be connected in parallel with one another.
- 15 In particular, the multiple secondary energy stores can essentially have identical capacitances (that is, within a tolerance of no more than 20%) and/or nominal voltages (that is, within a tolerance of no more than 10%) or different capacitances and/or nominal voltages. In the case of multiple secondary energy stores, these are in each case preferably of the same or an identical type.
- 20 According to a further embodiment of the implantable pulse generator according to the invention, it is provided that in each case one of the secondary energy stores is discharged in the second interval at a respective point in time (either alternately or all consecutively) via the therapeutic current path. Again, the respective point in time is preferably selected in
- 25 such a way that the voltage of the particular energy store does not drop below a predefined threshold value, for example 80% of the output voltage. Likewise, the respective points in time may be selected in such a way that the therapy voltage does not drop by more than 20% of the maximum voltage or output voltage.
- 30 The discharge of the secondary energy store, or energy stores, in the therapeutic current path preferably takes place in such a way that the variation of the actual pulse waveform (peak therapy voltage/current) from the desired ideal rectangular pulse waveform is less

than 50%, and preferably less than 20%. Such variations are also referred to as ripple. This is apparent as a spike in the voltage waveform.

The variation (ripple), or variations, can, as described above, be maintained within the
5 aforementioned boundaries by voltage monitoring, wherein the dropping voltage of the
exponential partial discharge of the particular energy store is observed. If the voltage drops
below a predefined threshold value, the charge of another energy store is called up,
wherein the therapy voltage increases to the desired maximum voltage and decreases again
with the discharge of the other energy store. This is also apparent by a further spike, or
10 ripple, in the voltage waveform.

The variation (ripple), or variations, can also be controlled in a time-controlled manner as
described above. The last secondary energy store whose charge is called up is preferably
discharged up to a polarity reversal with a biphasic shock (the last spike in the therapy
15 voltage “decays” until polarity reversal of the shock).

The point in time of the switch to the next energy store can, for example, be ascertained
from the exponential law of the energy store discharge, with the time constant being
known, having a known capacitance C , and the resistance R determined as described above
20 in such a way that the charge of the activated energy store is equal to the first polarity ($\pm 20\%$).

The variation (ripple), or variations, from the ideal pulse waveform can be controlled in
such a way that the therapy voltage, each time a switch is made to the next energy store,
25 essentially ($\pm 20\%$) increases to the same voltage, that is, the peaks of the ripples are at
the same level ($\pm 20\%$).

As an alternative, the variation, or the variations, from the ideal pulse waveform can be
monitored in such a way that the therapy voltage drops each a switch is made to the next
30 energy store, for example by a maximum of 20% each time.

The aforementioned control of the variation, or variations, can be time-controlled or voltage-controlled as described above.

According to a further embodiment of the implantable pulse generator according to the invention, it is provided that the control unit is further configured to activate at least one electric switch, preferably multiple switches of a bridge circuit (H-bridge), of the electric circuit in a second phase of the pulse delivery in such a way that the direction of current in the therapeutic current path is reversed. In this way, a steep voltage drop of the pulse can advantageously be achieved at the end of the first phase, and a biphasic therapeutic pulse can be generated. Moreover, areas in the target tissue that were not sufficiently stimulated in the first phase can advantageously be stimulated in the second phase. At the same time, charge equalization can advantageously be achieved in the target tissue, preferably the cardiac tissue.

According to a further embodiment of the implantable pulse generator according to the invention, it is provided that the control unit is further configured, in a second phase of the pulse delivery:

- to activate an electric switch in the electric circuit in such a way that the primary energy store is discharged via the therapeutic current path, or
- to activate an electric switch in the electric circuit in such a way that the primary energy store and the secondary energy store, or energy stores, are discharged via the therapeutic current path.

According to an alternative embodiment of the implantable pulse generator according to the invention, it is provided that the control unit is further configured, at the end of the first phase of the pulse delivery, to activate one or more electric switches in such a way that the primary energy store and/or the secondary energy store, or the multiple secondary energy stores, are disconnected from the therapeutic current path, and/or discharged in one or more bleeder resistors connected thereto. Advantageously, a steep voltage drop of the pulse at the end of the first phase can also be achieved with this embodiment, wherein a monophasic pulse can be generated in the process.

According to a further embodiment of the implantable pulse generator according to the invention, it is provided that the primary energy store is composed of a plurality of individual energy stores, which are connected in series or in parallel with one another. The number of the individual energy stores is preferably adapted to the required or desired
5 charging capacitance. The primary energy store preferably comprises at least two individual energy stores, three individual energy stores being preferred.

According to a further embodiment of the implantable pulse generator according to the invention, it is provided that the individual energy stores of the primary energy store are
10 fixedly connected in series.

In particular, the individual energy stores of the primary energy store can essentially have identical capacitances (that is, within a tolerance of no more than 20%) and/or nominal voltages (that is, within a tolerance of no more than 10%) or different capacitances and/or
15 nominal voltages.

According to a further embodiment of the implantable pulse generator according to the invention, it is provided that the switch, or the switches, of the electric circuit is or are electronic switches or semiconductor switches, in particular selected from: insulated-gate
20 bipolar transistor (IGBT), anode gated thyristor (AGT), or a combination of the aforementioned electronic switches.

According to a further embodiment of the implantable pulse generator according to the invention, it is provided that at least one of the switches described above is in electrical
25 connection with a diode, wherein the diode is arranged between one of the energy stores and the switch. The diode is preferably configured to block the current in the direction of the energy store. A diode is preferably arranged between each switch and the associated energy store, except for the switch by way of which the last secondary energy store is discharged via the therapeutic current path. Here as well, each of the diodes is preferably
30 configured to block the current in the direction of the particular energy store. In this way, the switches can advantageously be protected against polarity reversal.

According to a further embodiment of the implantable pulse generator according to the invention, it is provided that the multiple secondary energy stores comprise between two and four secondary energy stores, preferably three secondary energy stores.

- 5 According to one embodiment of the implantable pulse generator according to the invention, it is provided that the energy stores are capacitors or coils. Multiple energy stores, for example multiple secondary energy stores, can be formed by a capacitor in the process, which includes multiple capacitances, which are formed by multiple anodes, for example, wherein the multiple capacitances can be discharged independently of one
10 another.

- According to a further embodiment of the implantable pulse generator according to the invention, it is accordingly provided that the multiple secondary energy stores are formed by a capacitor comprising at least one first electrode having a first polarity, and at least two
15 second electrodes having a second polarity, wherein the first electrode and the at least two second electrodes can be electrically contacted separately from one another from the outside of the capacitor.

- According to a further embodiment of the implantable pulse generator according to the invention, it is provided that the primary energy store and/or the second energy store, or
20 energy stores, are a capacitor comprising at least one cathode and at least two anodes, preferably comprising three anodes, wherein the cathode and the at least two anodes can be electrically contacted separately from one another from the outside of the capacitor. The capacitor preferably comprises an electrically conductive housing, in which the cathode
25 and the anodes are arranged, wherein the housing is in electrical connection with the cathode, and the anodes can be electrically contacted by the housing and one another, via at least one electrical feedthrough from the outside of the capacitor or the capacitor housing. The cathode is preferably formed by an electrolyte, wherein the anodes are preferably formed of a valve metal, preferably aluminum, tantalum or niobium. In
30 particular, each of the anode can form a dedicated capacitance with the cathode (the

electrolyte), which is preferably in the range of 200 μF to 300 μF , and in particular approximately 241 μF .

According to a further embodiment of the implantable pulse generator according to the invention, it is provided that the electric circuit comprises a primary energy store, which comprises three of the capacitors described in the preceding paragraph comprising multi-electrodes, and a secondary energy store, which is formed by a capacitor described in the preceding paragraph, wherein in particular the capacitor configured as the secondary energy store comprises at least two, and preferably three, anodes, which can be electrically contacted independently of one another from the outside of the capacitor, and correspondingly can form at least two, and preferably three, capacitances that can be discharged independently of one another.

According to a further embodiment of the implantable pulse generator according to the invention, it is provided that the capacitor, or the capacitors, forming the primary energy store, the individual energy stores, or one of the aforementioned secondary energy stores, are electrolytic capacitors or ceramic capacitors or film capacitors, preferably aluminum or tantalum electrolytic capacitors, preferably having an energy density of at least $5 \text{ J} \cdot \text{cm}^3$.

According to one embodiment of the energy store according to the invention, it is provided that

- the primary energy store has a capacitance in the range of 150 μF to 300 μF and/or a nominal voltage in the range of 250 V to 300 V, and/or
- the secondary energy store has, or the secondary energy stores have, a capacitance in the range of 180 μF to 36 μF and/or a nominal voltage in the range of 250 V to 255 V, independently of one another.

If the primary energy store is formed of multiple individual energy stores, for example two or three, the primary energy store preferably has an overall capacitance in the range of 150 μF to 300 μF .

According to claim 11, a method for delivering an electrical pulse having a substantially rectangular pulse waveform is provided. The method comprises the following steps:

- connecting a charged primary energy store to a discharge current path in a first interval of a first phase of a pulse delivery; and
- 5 – connecting at least one charged secondary energy store to the discharge current path in a second interval of the first phase of the pulse delivery, wherein the primary energy store and the at least one secondary energy store are fixedly connected, or connectable, in series, and wherein
 - in the second interval, the primary energy store and, consecutively, all
 - 10 secondary energy stores are discharged via the therapeutic current path, or
 - the primary energy store and in each case one of the multiple secondary energy stores are discharged via the therapeutic current path.

The method according to the invention can advantageously be carried out by way of the implantable pulse generator according to the invention according to claim 1 or one of the
15 embodiments described above.

According to one embodiment of the method according to the invention, it is provided that the charged primary energy store and the at least one charged secondary energy store are
20 fixedly connected in series, that is, in particular not disconnected by switches.

According to an alternative embodiment of the method according to the invention, it is provided that the charged primary energy store and the at least one charged secondary energy store can be connected in series.
25

According to one embodiment of the method according to the invention, it is provided that the connection of the at least one secondary energy store to the discharge current path is signal-controlled or time-controlled.

30 According to one embodiment of the method according to the invention, it is provided that, in the second interval of the first phase of the pulse delivery, multiple charged secondary energy stores are sequentially or consecutively connected to the discharge current path.

According to one embodiment of the method according to the invention, it is provided that the charged primary energy store and the multiple charged secondary energy stores are fixedly connected in series, that is, in particular not disconnected by switches.

5

According to an alternative embodiment of the method according to the invention, it is provided that the charged primary energy store and the multiple charged secondary energy stores can be connected in series.

- 10 According to one embodiment of the method according to the invention, it is provided that only one charged secondary energy store at a time is connected to the discharge current path, wherein in particular the multiple charged secondary energy stores are in each case consecutively connected to the discharge current path. This can, in particular, be achieved by an electric circuit in which the secondary energy stores can be connected in parallel
- 15 with one another. In this way, only one secondary energy store at a time and the primary energy store are connected to the discharge current path.

- According to one embodiment of the method according to the invention, it is provided that the multiple charged secondary energy stores are sequentially connected to the discharge
- 20 current path, wherein in particular all secondary energy stores are consecutively connected to the discharge current path. This can, in particular, be achieved by an electric circuit in which the primary energy store and the secondary energy stores are connected in series with one another. In this way, the primary energy store, a first secondary energy store, and every further secondary energy store are consecutively connected in series with the
- 25 discharge current path.

- According to a further embodiment of the method according to the invention, it is provided that the connection of the primary energy store and of the at least one secondary energy store, or of the multiple secondary energy stores, is carried out in each case by way of a
- 30 switch, in particular by way of an electronic switch.

According to a further embodiment of the method according to the invention, it is provided that the direction of current in the current path is reversed in a second phase of the pulse delivery. Such a reversal in the direction of current can advantageously be implemented by way of a bridge circuit.

5

According to a further embodiment of the method according to the invention, it is provided that, in the second phase of the pulse delivery,

- only the primary energy store is connected to the discharge current path, or
 - the primary energy store and the secondary energy store, or energy stores, are
- connected to the discharge current path.

10

Further features and advantages of the invention are described hereafter based on the description of the figures of exemplary embodiments. In the drawings:

15 FIG. 1 shows various shock waveforms of implantable defibrillators and the effect on the transmembrane voltage of cardiac muscle cells;

FIG. 2 (A) shows an embodiment of a circuit according to the invention comprising primary and secondary energy stores that can be connected in series;

20 (B) shows the associated voltage waveform of the therapy voltage and of the energy stores (top), and the effect thereof on the transmembrane voltage of the cardiac muscle cells (bottom); and

 (C) shows a detailed representation of the embodiment shown in (A);

25 FIG. 3 (A) shows an alternative embodiment of a circuit according to the invention comprising primary energy stores connectable in series and secondary energy stores connectable in parallel; and

 (B) shows the associated voltage waveform of the therapy voltage and of the energy stores (top), and the effect thereof on the transmembrane voltage of the cardiac muscle cells (bottom); and

30

FIG. 4 shows an alternative embodiment of a circuit according to the invention, using capacitors comprising multi-anodes contactable from the outside.

FIG. 1 shows the state of the art (top graph, blue) of the shock waveform of an implantable defibrillator (applicable both to transvenous and subcutaneous ICDs). The therapy voltage results from the discharge of effectively only one capacitor and therefore drops exponentially. This has the disadvantage that the process has to begin with considerably higher starting voltages so as to generate the same effect in the heart. For comparison, the ideal waveform of a shock having a rectangular first phase is shown (red), as well as the shock waveforms of the approach according to the invention, which approximate the rectangular waveform.

FIG. 2A shows a preferred embodiment of the circuit according to the invention, in which the energy stores C_1 to C_6 are capacitors that are connected, or can be connected, in series. The capacitors C_1 to C_3 , which form the primary energy store according to the present invention, can also be implemented as a capacitance C_0 . All capacitors C_1 to C_6 can essentially be charged simultaneously by a charging circuit. The switches S_1 to S_4 are switched consecutively in ascending order for delivering the therapy. Switch i is opened again in the process before switch $i+1$ is closed. This circuit further feeds the H-bridge for the generation of the second phase (not shown). One of the switches, preferably S_4 , is closed in the second phase. Instead of switch S_4 , it is also possible for a diode to be arranged, which blocks the current in the direction C_0/C_4 . FIG. 2B shows the voltage waveform of the therapy voltage (blue) achievable with this electric circuit, as well as the capacitors C_0 (red), C_4 (yellow), C_5 (purple), C_6 (green) in the top illustration, and the corresponding effect on the transmembrane voltage of the cardiac muscle cells in the bottom illustration. The primary energy store C_0 , which is formed of three individual energy stores C_1 to C_3 , preferably has an overall capacitance in the range of 150 μF to 300 μF , and each of the secondary energy stores C_4 to C_6 preferably has a capacitance in the range of 180 μF to 360 μF .

FIG. 2C shows an implementation of the embodiment shown in FIG. 2A comprising electronic switches and up to 6 capacitors as energy stores C_1 to C_6 of the pulse generator

according to the invention. Of these, 3 capacitors C_1 , C_2 , C_3 ensure the sufficiently high starting voltage, and the remaining 3 capacitors C_4 , C_5 , C_6 generate the desired approximately rectangular pulse waveform (saw tooth curve), which in the present case can have up to 4 spikes. So as to render the shock biphasic, an H-circuit comprising the electronic switches (IGBTs) Q05 to Q08 is conventionally used. This circuit is fed via the electronic switches (IGBTs) Q01 to Q04, which activate the capacitors C_4 , C_5 , C_6 . The IGBTs Q02 to Q04 are preferably protected against polarity reversal by way of the diodes D7 to D9. The shock is conducted into the body via the terminals HV1 to HV2. The capacitors are charged via a high voltage source, which is connected to HVin and ground.

10

FIG. 3A shows a further preferred embodiment of the electric circuit according to the invention comprising capacitors C_1 to C_6 as energy stores, wherein the activated, or activatable, energy stores C_4 to C_6 are connected, or connectable, in parallel with one another. The capacitors C_1 to C_3 can also be implemented as a capacitance C_0 here. All capacitors are essentially charged simultaneously by a charging circuit. The switches S_1 to S_4 are switched consecutively in ascending order for delivering the therapy. Switch i is opened again in the process before switch $i+1$ is closed. This circuit further feeds the H-bridge for the generation of the second phase. One of the switches, preferably S_1 , is closed in the second phase. FIG. 3B shows the voltage waveform of the therapy voltage (blue) achievable with the electric circuit, as well as at the capacitors C_0 (red), C_4 (yellow), C_5 (purple), C_6 (green) in the top illustration, and the corresponding effect on the transmembrane voltage of the cardiac muscle cells in the bottom illustration.

20

FIG. 4 shows a preferred embodiment of the electric circuit according to the invention comprising a parallel approach, using capacitors comprising multi-anodes K, A_1 , A_2 , A_3 as the primary energy stores C_0 , C_1 , C_2 , C_3 and multiple secondary energy stores C_4 to C_6 . In particular, capacitors are used in the process which each comprise a cathode K and, for example, three anodes A_1 , A_2 , A_3 , wherein the cathode K can advantageously be contacted from the outside by an electrically conductive housing, and the anodes can be contacted from the outside separately from one another, and electrically insulated from one another and from the housing G, for example via feedthroughs D_1 , D_2 , D_3 . The multiple secondary energy stores according to the invention are thus implemented as a capacitor, which

30

provides three capacitances that can be discharged separately from one another with the three separately contactable anodes A_1 , A_2 , A_3 thereof

5 However, it would also be conceivable that the capacitors C_1 to C_3 , which form the primary energy store according to the present invention, are designed in such a way that the anodes A_1 , A_2 , A_3 are electrically connected in the interior of the housing G, and can be electrically contacted from the outside via a shared anode wire, which is routed to the outside via a feedthrough, for example.