

Description

The present invention relates to light beam positioning systems and, in particular, to such a system having light beam position error correction capabilities.

A conventional automated light beam positioning system typically includes a light beam positioner and a system control computer. The light beam positioner, which typically includes optical components having movable light-directing surfaces, receives beam position and velocity command data ("command data") processed by the system control computer. The optical components have either reflective or refractive light-directing properties. The light beam positioner determines, in response to the command data, the propagation path of an incident light beam to direct it to a predetermined position on a workpiece.

To change the path the light beam travels along the workpiece, the light beam positioner changes, in response to different command data, the orientations of the movable light-directing surfaces of the optical components. One example of such a device is a galvanometer beam positioner, which employs a pair of selectively pivotable mirrors that cooperate in response to the command data to direct an incident light beam to a desired position on a target surface.

Figs. 1A and 1B are diagrams of a prior art light beam positioning system 10 that employs a galvanometer beam positioner 12 to direct an incident light beam 14 emanating from a laser source 16 to a desired position on a planar target surface 18. Fig. 1A is a block diagram of the data processing modules for controlling galvanometer beam positioner 12, and Fig. 1B is a pictorial diagram of the optical components of light beam positioning system 10.

With reference to Figs. 1A and 1B, a peripheral storage medium 20, such as a magnetic disk, provides the command data to a system control computer 22. System control computer 22 typically performs multiple tasks, at least some of which do not pertain to a light beam positioning operation. The command data represent "tables" of start and end positions of possible paths and their associated speeds of light beam travel along the workpiece. System control computer 22 acquires electrical measurement data and, in response to such data, selects one of each of the possible paths and speeds for the light beam. For example, command data for a laser-based resistor trimmer represents a series of respective start and end positions from which and to which laser beam 14 moves to carry out a trimming operation on a particular resistor network with a known pattern.

System control computer 22 delivers the command data to a position data generator 24, which develops an X position coordinate digital word signal ("X signal") and a Y position coordinate digital word signal ("Y signal"). The X and Y signals represent digital words that are converted to DC voltages that are delivered to different ones of two galvanometer motors (not shown). A galvanometer motor is a DC motor whose shaft is operatively connected to a mirror for movement about a pivot axis. Galvanometer beam positioner 12 employs a pair of separate mirrors 26 and 28 mounted to brackets that are operatively connected to the galvanometer motors for pivotal movement about orthogonally aligned pivot axes. Mirrors 26 and 28 receive the incident laser beam 14 and pivotally move about their respective pivot axes in response to the X and Y signals to direct beam 14 to a desired position on target surface 18. Galvanometer beam positioner 12 also includes a lens of the F- θ type for focusing beam 14 and a mirror 32 for directing beam 14 toward target surface 18. The pivotal movements of mirrors 26 and 28 describe a generally circular addressable imaging area 33 on target surface 18.

One of the problems associated with light beam positioning system 10 is that the system optical components can cause unit pivotal movements of the galvanometer mirrors to not result in unit linear movements of laser beam 14 on target surface 18. A primary source of such nonlinear beam movement is the nonlinear distortion that results whenever the system optical components inaccurately convert pivotal motion to linear motion. For example, whenever it is positioned off the optic axis, galvanometer mirror 26 misdirects beam 14 as it propagates toward galvanometer mirror 28 and lens 30. The galvanometer positioning error results in "pincushion" distortion, which represents nonequidistant spacing between adjacent positions near the periphery of target surface 18 as beam 14 moves toward them in response to corresponding unit angular displacements of galvanometer mirrors 26 and 28.

Fig. 2 is a map of an exemplary addressable field 34 showing the light beam grid pattern described on target surface 18 by unit angular displacements of galvanometer mirrors 26 and 28 in response to unit changes in command data position values. For purposes of the following description, galvanometer mirrors 26 and 28 pivotally move about the X and Y axes, respectively. Fig. 2 shows that addressable field 34 of target surface 18 is of pincushion shape with equidistant spacing of 2.5 mm between adjacent positions in the vicinity of the center 36 of the target surface, an outwardly directed contour with a "keystone" shape at the periphery portions 40 in the X direction, and an inwardly directed contour at the periphery portions 38 in the Y direction. The resulting beam positioning nonlinearity is typically a few percent near the periphery of

the target surface.

There are several techniques employed in an attempt to deal with the nonlinear beam positioning introduced by the galvanometer beam positioner optical components. One technique is simply to ignore the problem and tolerate the resulting pincushion distortion. A second technique entails visual feedback in which an operator uses a joystick manually to position the laser beam at the desired start position. This technique suffers from the obvious disadvantage of being labor intensive and does not correct the problem of positioning nonlinearity that occurs as the laser beam moves from a start position near the periphery of the target surface. The use of visual feedback to direct the laser beam in the correct start position cannot, therefore, result in straight line beam positioning along the target surface.

A third technique for correcting beam positioning errors entails correcting the command data processed by system control computer 22. This is accomplished by providing in the system control computer 22 a calibration map in the form of a look-up table having correction data corresponding to the desired target surface positions to which the command data correspond. System control computer 22 uses the correction data to modify the command data to eliminate beam position errors. This error correction technique is disadvantageous because software files located in system control computer 22 must be changed each time a different beam positioner 12 is used in conjunction with system control computer 22. Another disadvantage is that the system control computer response time to a change in command data is inherently long because system control computer 22 performs many other unrelated tasks that are assigned priorities. The desired change in beam position may take place, therefore, after significant time has elapsed from the receipt of command data.

A fourth technique for correcting positioning errors, described by Takahashi in Patent Abstracts of Japan, Vol. 8, No. 80 (M-289)[1517] JP-A-58 224 088 (12 April 1984), involves the use of a closed loop control system. After traversing the beam positioner, the light beam is split into two parts: one part striking the target surface and a second part striking a two dimensional self-scanning photoelectric transducer. The photoelectric transducer provides real time feedback about the positioning of the light beam to a system controller and driver to allow correction of the light beam position.

An object of the invention is, therefore, to provide a beam position error correcting light beam positioning system.

Another object of the invention is to provide such a system that performs beam position error correction in real time.

A further object of the invention is to provide such a system that does not necessitate changes in system control computer software files with the use of different light beam positioners.

Still another object of the invention is to provide a computer-controlled light beam positioning system that has good beam positioning linearity properties over the entire addressable imaging area of a target surface.

Yet another object of the invention is to provide such a system that employs a galvanometer light beam positioner.

The present invention is described only by way of example with reference to a laser-based resistor trimmer system that employs a galvanometer laser beam positioner. The invention corrects in real time positioning errors of a galvanometer laser beam positioner and, therefore, has the capability of generating accurately positioned straight lines at programmed velocities between any two points on a target surface.

The invention employs an error correction processor that receives the X signal and the Y signal produced by a conventional position data generator and develops a compensated X digital word signal ("X_c signal") and a compensated Y digital word signal ("Y_c signal"), respectively, for delivery to the galvanometer beam positioner. The use of the error correction processor in association with the position data generator and the galvanometer beam positioner allows the use of common trim position data files in the system control computer in systems capable of using different light beam positioners. A facility having multiple computer-controlled beam positioning systems implemented in accordance with the invention is, therefore, capable of processing the same resistor network workpiece on different beam positioning systems having the same command data in the system control computer.

The error correction processor performs the correction steps in real time, thereby providing the X_c and Y_c signals in less time than the response time of the pivotally movable galvanometer mirrors of the light beam positioner. The error correction processor can be adapted for use in different laser trimming systems of the same model type simply by loading the error correction processor with the pertinent correction factors for the particular light beam positioner in use. Such flexibility is achievable with no changes to the software files in the system control computer.

Additional objects and advantages of the present invention will be apparent from the detailed description of a preferred embodiment thereof, which proceeds with reference to the accompanying drawings.

Figs. 1A and 1B are respective block and pictorial diagrams of a prior art computer-controlled beam positioning system.

Fig. 2 is a map of an exemplary addressable field having the beam position pincushion distortion inherent in an error uncompensated prior art galvanometer beam positioning system of the type shown in Figs. 1A and 1B.

Fig. 3 is a block diagram of a computer-controlled light beam positioning system with beam position error correction in accordance with the present invention.

Fig. 4 is a flow diagram of the calibration processing steps carried out to derive field correction coefficients of the polynomial terms representing the X_c and Y_c signals.

Fig. 5 is a diagram showing the locations of thirteen calibration points used in deriving the field correction coefficients in accordance with the flow diagram of Fig. 4.

Fig. 6A shows pincushion distortion in the X-direction only of an addressable field pattern of the character shown in Fig. 2, and Figs. 6B and 6C represent the wedge shape component and parabolic shape component, respectively, that can be superimposed to form the addressable field pattern of Fig. 6A.

Fig. 7 is a simplified block diagram of the error correction processor implemented in the system of Fig. 3.

Fig. 8 is a map of an exemplary addressable field showing the effect of the position error correction techniques of the invention in eliminating beam position pincushion distortion.

Fig. 3 is a block diagram of a computer-controlled light beam positioning system 50 with beam position error correction in accordance with the present invention. Beam positioning system 50 is described herein only by way of example as having a galvanometer laser beam positioner 12 of the type typically employed in resistor trimming systems. Beam positioning system 50 is capable of correcting laser beam positioning errors introduced by different galvanometer laser beam positioners 12 of the same model type. This can be accomplished by providing to an error correction processor 52 a set of correction coefficients that characterize the light directing properties of the specific galvanometer beam positioner employed in the beam positioning system. Beam positioning system 50 is capable of correcting for errors resulting from 1) nonlinear distortion caused by mirror pivotal motion and lens characteristics, 2) alignment errors caused by a deviation from the orthogonal relationship of the X-Y coordinate axes, 3) scale factor and origin deviation errors for the X-axis and Y-axis, and 4) rotational misalignment of the imaging field with respect to the target surface 18. In a preferred embodiment, target surface 18 is planar and represents the working surface of any laser-based micromachining device.

With reference to Fig. 3, beam positioning system 50 differs in part from the prior art beam positioning system 10 in that the former includes an error correction processor 52 that is positioned between position data generator 24 and galvanometer beam positioner 12. Error correction processor 52 executes a correction formula the results of which are inscribed in a memory to calculate the X_c and Y_c signals for delivery to galvanometer beam positioner 12. The error correction processor 52 performs the corrections in real time during the laser trimming operation. Error correction processing is performed at least as quickly as the response time of the galvanometer mirror that is driven.

Corrections to the command data are implemented in software whose processing steps manipulate the terms in predetermined equations representing the X_c and Y_c signals. These equations correct for position errors in each of the X- and Y-axes for each command data point. The equations are matched to a particular beam positioner 12 by means of a calibration process that generates a specific set of field correction coefficients ("coefficients") for the terms in the equations.

The calibration process that generates the coefficients is executed only as required to compensate for long term system drift or changes resulting from adjustment or repair. The coefficients are stored in a calibration data file 54 that is used in data communication with system control computer 22 and are delivered by way of a data bus 56 to error correction processor 52 each time electrical power is applied to beam positioning system 50. The contents of calibration data file 54 are identified by the serial number of the particular beam positioning system 50 to ensure that the correct set of coefficients is associated with the galvanometer beam positioner 12 employed in such system. It will be appreciated that the coefficients could also be stored in a nonvolatile memory in direct data communication with error correction processor 52.

Error correction processor 52 receives the X and Y signals representing a command data point and performs the pertinent mathematical operations to calculate the X_c and Y_c signals in accordance with the following transform equations:

$$\begin{aligned} X_c &= A_1 + B_1 X + C_1 X^2 + D_1 X^3 + E_1 Y + F_1 Y^2 + G_1 XY + H_1 XY^2 \\ Y_c &= A_2 + B_2 Y + C_2 Y^2 + D_2 Y^3 + E_2 X + F_2 X^2 + G_2 YX + H_2 YX^2 \end{aligned}$$

accomplished by performing a third order polynomial least-squares curve fit to the variables $IX_{1,2}$ and $DY_{1,2}$, $IX_{3,2}$ and $DY_{3,2}$, $IX_{7,2}$ and $DY_{7,2}$, $IX_{1,1}$ and $DY_{1,1}$, and $IX_{2,1}$ and $DY_{2,1}$. The coefficients derived from the least-squares curve fit are such that the zero order coefficient becomes A_2 , which is equivalent to the Y-axis offset; the first order coefficient becomes B_2 , which is equivalent to the Y-axis scale factor; the second order coefficient becomes C_2 ; and the third order coefficient becomes D_2 . It will be appreciated that the zero order coefficient, which represents Y-axis offset, should equal the dependent variable DY_7 . A difference between A_2 and DY_7 of greater than about five galvanometer motor increments could be indicative of questionable data.

Substep 64e indicates the derivation of the E_2 and F_2 coefficients. This derivation is accomplished by solving the Y_c transform equation as a function of the X terms in it. The E_2 and F_2 coefficients are derived from the five calibration points located along the horizontal or $Y=0$ axis by performing a second order polynomial least-squares fit to the variables IX_5 and DY_5 , IX_6 and DY_6 , IX_7 and DY_7 , IX_8 and DY_8 , and IX_9 and DY_9 . The coefficients derived from the second order polynomial least-squares curve fit are such that the zero order coefficient is unused except for error checking purposes. The first order coefficient becomes E_2 , and the second order coefficient becomes F_2 . It will be appreciated that the zero order coefficient should be approximately equal to DY_7 and the A_2 coefficient. The difference between the otherwise unused zero order coefficient and A_2 (or DY_7) of greater than about five galvanometer motor increments again could be indicative of questionable data.

Substep 64f indicates the computation of the G_2 and H_2 coefficients. The G_2 and H_2 coefficients are derived directly from six of the measured values in accordance with the following equations:

$$\begin{aligned} P_y &= DY_3 - DY_{1,3} \\ Q_y &= DY_1 - DY_{1,1} \\ R_y &= DY_2 - DY_{1,2} \end{aligned}$$

where, P_y , Q_y , and R_y are nominally positive numbers approximately equal to the vertical width of the data field. The G_2 and H_2 coefficients can be computed from the above expressions for P_y , Q_y , and R_y as follows:

$$\begin{aligned} G_2 &= (P_y - Q_y)/(4 \times IX_3 \times IX_3) \\ H_2 &= (P_y + Q_y - 2 \times R_y)/(4 \times IX_3 \times IX_3 \times IX_3) \end{aligned}$$

The G_2 coefficient can be of positive or negative value, and the magnitude of G_2 will be typically less than 1×10^{-8} . The H_2 coefficient will always be negative, and the magnitude of H_2 will be typically about 5×10^{-11} . The equations for the G_2 and H_2 coefficients are empirically derived from the addressable field pattern having pincushion distortion in a manner analogous to that recited above with reference to Figs. 6A-6C. It will be appreciated that substeps 64a-64c and substeps 64d-64f can be performed in parallel, as the flow diagram in Fig. 5 indicates.

Process block 66 indicates the normalizing and prescaling of the A_1 - H_1 and A_2 - H_2 coefficients. These operations are performed because the coefficients can be either much smaller or much greater than one. A wide range of possible coefficient values could cause an overflow condition for higher order terms because the preferred error correction processor 52 operates in 16-bit integer mathematics. To prevent such an overflow condition, the derived coefficients undergo a prescaling process that entails multiplying each term in the X_c and Y_c transform equations by $(32768)^n/(32768)^n$, where n represents the order of the term minus one. This prescaling process is advantageous in that it prevents the higher order terms from growing beyond 16-bits, scales up the smaller coefficient to a size that is greater than zero at 16-bits, and tends to keep intermediate products at a size yielding a maximum number of significant digits in 16-bit two's complement format.

Table I summarizes the prescaling factors computed for the coefficients.

where $A_1, B_1, C_1, D_1, E_1, F_1, G_1$, and H_1 and $A_2, B_2, C_2, D_2, E_2, F_2, G_2$, and H_2 represent the coefficients. The coefficients are derived from a set of measured data obtained from scans of the workpiece at thirteen predetermined locations in an addressable field bounded by a rectangle.

Fig. 4 is a flow diagram showing the calibration processing steps for deriving the coefficients for the X_c and Y_c signals. The calibration process entails six principal processing steps, which include 1) selecting a regular array of thirteen calibration points centered in the addressable field, 2) determining the command data required to position the laser beam precisely at each one of the thirteen selected calibration points, 3) deriving the sixteen required coefficients A_1-H_1 and A_2-H_2 for the respective transform equations X_c and Y_c , 4) normalizing and scaling the derived coefficients to prevent numeric overflow in a 16-bit integer mathematical operation carried out by error correction processor 52, 5) adjusting certain ones of the coefficients to compensate for an inherent divide-by-two operation performed whenever a multiplication operation is carried out, and 6) converting the coefficients to fractional binary format. The following detailed explanation of each of the above six steps is given with reference to Fig. 4.

Process block 60 indicates the selection of the thirteen calibration points. Each of the calibration points is bounded by a rectangle whose borders are about 5 percent inside the limits of the addressable field so that centering errors and aberrations caused by pincushion distortion do not place any of the calibration points outside the addressable field. The calibration points are referred to herein as "independent variables" for substitution into the X_c and Y_c equations and are arranged in thirteen ordered pairs denominated (IX_1, IY_1) through (IX_{13}, IY_{13}) . For example, IX_1 and IY_1 represent the respective X-coordinate and the Y-coordinate of calibration point 1.

Fig. 5 is a diagram showing the locations of the thirteen field calibration points identified in accordance with the above-described notation. Each increment of the galvanometer motors for galvanometer mirrors 26 and 28 represents, for example, 0.0025 millimeter movement of the laser beam along either the X-axis or the Y-axis of the target surface. The size of incremental movement depends upon the particular implementation of galvanometer beam positioner 12. The galvanometer motor counts are computed with reference to the center point (IX_7, IY_7) of the addressable field.

The thirteen calibration points include five points positioned along the horizontal ($Y=0$) axis, centered on $X=0$, and spaced according to the approximate proportions -10, -6, 0, 6, 10; five points positioned along the vertical ($X=0$) axis, centered on $Y=0$ and spaced according to the approximate proportions -10, -6, 0, 6, 10; and four corner points of the rectangle, which in the preferred embodiment is a square. In particular, the five points positioned along the horizontal axis include the ordered pairs (IX_5, IY_5) , (IX_6, IY_6) , (IX_7, IY_7) , (IX_8, IY_8) , and (IX_9, IY_9) . The five points positioned along the vertical axis include the ordered pairs (IX_2, IY_2) , (IX_4, IY_4) , (IX_7, IY_7) , (IX_{10}, IY_{10}) , and (IX_{12}, IY_{12}) . The four corner points of the square include the ordered pairs (IX_1, IY_1) , (IX_3, IY_3) , (IX_{11}, IY_{11}) , and (IX_{13}, IY_{13}) . It will be appreciated that the center point (IX_7, IY_7) , is common to the two sets of five points positioned along the horizontal and vertical axes.

Process block 62 indicates the determination of the X and Y signals required to position laser beam precisely at each one of the thirteen calibration points established in the manner described with reference to process block 60. The measurement can be accomplished, for example, by means of a scanning routine that locates a target, which represents any one of the thirteen calibration points. The targets can be either thirteen target locations on a fixed calibration plate or a single target location on a plate movable to thirteen different positions by a step-and-repeat mechanism. The thirteen measured positions are referred to herein as the "dependent variables" for substitution into the X_c and Y_c transform equations and are denominated (DX_1, DY_1) through (DX_{13}, DY_{13}) . For example, DX_1 and DY_1 represent the respective X and Y signals delivered to error correction processor 52 to position the beam at the center of target 1, which is located at (IX_1, IY_1) .

Process block 64 indicates the derivation of the coefficients from the independent variables IX and IY and the dependent variables DX and DY . The process of deriving all of the coefficients from the independent and dependent variables entails six substeps, some of which requiring the use of a conventional least-squares curve fitting algorithm. The requirements of the algorithm are that it 1) be sufficiently accurate to maintain at least six significant digits of resolution for floating point numbers as small as 1×10^{-12} , 2) be capable of fitting selectively either a second or third order curve to five calibration points, and 3) generate the desired coefficients and a figure of merit indicative of the quality of fit obtained. The figure of merit is useful for error checking purposes.

Substep 64a indicates the derivation of the A_1, B_1, C_1 , and D_1 coefficients. This derivation is accomplished by solving the X_c transform equation as a function of X . The A_1, B_1, C_1 , and D_1 coefficients are derived from the five calibration points located along the horizontal or $Y=0$ axis and is accomplished by performing a third order polynomial least-squares curve fit to the variables IX_5 and DX_5 , IX_6 and DX_6 , IX_7

and DX_7 , IX_3 and DX_3 , and IX_5 and DX_5 . The coefficients derived from the least-squares curve fit are such that the zero order coefficient becomes A_1 , which is equivalent to the X-axis offset; the first order coefficient becomes B_1 , which is equivalent to the X-axis scale factor; the second order coefficient becomes C_1 ; and the third order coefficient becomes D_1 . It will be appreciated that the zero order coefficient, which represents the X-axis offset, should equal the dependent variable DX_7 . A difference between A_1 and DX_7 of greater than about five galvanometer motor increments could be indicative of questionable data.

Substep 64b indicates the derivation of the E_1 and F_1 coefficients. This derivation is accomplished by solving the X_c transform equation as a function of Y . The E_1 and F_1 coefficients are derived from the five calibration points located along the vertical or $X=0$ axis by performing a second order polynomial least-squares fit to the variables $IX_{1,2}$ and $DY_{1,2}$, $IX_{1,3}$ and $DY_{1,3}$, IX_7 and DY_7 , IX_5 and DY_5 , and IX_2 and DY_2 . The coefficients derived from the second order polynomial least-squares curve fit are such that the zero order coefficient is unused except for error checking purposes, the first order coefficient becomes E_1 , and the second order coefficient becomes F_1 . It will be appreciated that the zero order coefficient should be approximately equal to DX_7 and to the A_1 coefficient. The difference between the otherwise unused zero order coefficient and A_1 (or DX_7) of greater than about five galvanometer motor increments again could be indicative of questionable data.

Substep 64c indicates the computation of the G_1 and H_1 coefficients. The G_1 and H_1 coefficients are derived directly from six of the measured values in accordance with the following equations:

$$\begin{aligned} P_x &= DX_3 - DX_1 \\ Q_x &= DX_{1,3} - DX_{1,1} \\ R_x &= DX_9 - DX_5 \end{aligned}$$

where P_x , Q_x , and R_x are nominally positive numbers approximately equal to the horizontal width of the data field. The G_1 and H_1 coefficients can be computed from the above expressions for P_x , Q_x , and R_x as follows:

$$\begin{aligned} G_1 &= (P_x - Q_x)/(4 \times IX_3 \times IX_5) \\ H_1 &= (P_x + Q_x - 2 \times R_x)/(4 \times IX_3 \times IX_5 \times IX_7) \end{aligned}$$

The G_1 coefficient can be of positive or negative value, and the magnitude of G_1 will be typically less than 1×10^{-8} . The H_1 coefficient will always be positive, and the magnitude of H_1 will be typically about 5×10^{-11} .

The equations for the G_1 and H_1 coefficients are empirically derived from the addressable field pattern having pincushion distortion. Fig. 6A represents an enlarged portion of an uncorrected addressable field pattern of the character shown in Fig. 2. Fig. 6A shows pincushion distortion only in the X direction. During his formulation of the error correction transform equations, one of the inventors determined that the pattern of Fig. 6A can be represented as the superposition of a wedge shape component, which is shown in Fig. 6B, and a parabolic shape component, which is shown in Fig. 6C. Fig. 6B indicates that the wedge increases in angular displacement as a function of distance from the Y-axis, and Fig. 6C indicates that the parabolic curvature increases as a function of distance from the Y-axis.

The term G_1XY in the X_c transform equation corrects for the wedge shape shown in Fig. 6B. The term $(P_x - Q_x)$ of the G_1 coefficient represents four times the average X-axis component of the lines extending from the X-axis to points (DX_1, DY_1) , (DX_3, DY_3) , $(DX_{1,1}, DY_{1,1})$, and $(DX_{1,3}, DY_{1,3})$. The division by four in the G_1 equation is, therefore, required to calculate G_1 . The G_1 coefficient is computed at the point (IX_3, IX_5) because it resides in the first quadrant of the addressable field, but the point (IX_1, IX_7) could also be used.

The term H_1XY^2 in the X_c transform equation corrects for the parabolic shape, the term $(P_x + Q_x - 2 \times R_x)$ of the H_1 coefficient represents four times the X-axis component of parabolas at the points (DX_1, DY_1) , (DX_3, DY_3) , $(DX_{1,1}, DY_{1,1})$, and $(DX_{1,3}, DY_{1,3})$. One of the parabolas passes through the points (DX_1, DY_1) , (DX_5, DY_5) , and $(DX_{1,1}, DY_{1,1})$; and the other parabola passes through the set of points (DX_3, DY_3) , (DX_9, DY_9) , and $(DX_{1,3}, DY_{1,3})$.

The division by four in the H_1 equation is, therefore, required to calculate H_1 . The H_1 coefficient is computed at the point (IX_3, IX_5) because it resides in the first quadrant, but the points (IX_1, IX_7) , $(IX_{1,1}, IX_{1,3})$, and $(IX_{1,3}, IX_5)$ could also be used. It will be appreciated that the terms G_1XY and H_1XY^2 nonlinearly increase as the beam position moves away from the Y-axis.

Substep 64d indicates the derivation of the A_2 , B_2 , C_2 , and D_2 coefficients. This derivation is accomplished by solving the Y_c transform equation as a function of the Y terms in it. The A_2 , B_2 , C_2 , and D_2 coefficients are derived from the five calibration points located on the vertical or $X=0$ axis and is

TABLE I

COEFFICIENTS	TYPICAL VALUES	MULTIPLIER	TYPICAL RESULTS
A ₁ , A ₂	+ - 1000	1	+ - 1000
B ₁ , B ₂	+ - 1	1	+ - 1
C ₁ , C ₂	+ - 4 x 10 ⁻⁸	32768	+ - 1.3 x 10 ⁻³
D ₁ , D ₂	+ - 5 x 10 ⁻¹²	1073741824	+ - 5.5 x 10 ⁻²
E ₁ , E ₂	+ - 3 x 10 ⁻³	1	+ - 3 x 10 ⁻³
F ₁ , F ₂	+ - 30 x 10 ⁻³	32768	+ - 1 x 10 ⁻³
G ₁ , G ₂	+ - 1 x 10 ⁻⁸	32768	+ - 3.3 x 10 ⁻⁴
H ₁ , H ₂	+ - 50 x 10 ⁻¹²	1073741824	+ - 5.3 x 10 ⁻²

The typical results listed in the rightmost column of Table 1 indicate that after multiplication by the prescaling factor, each of the coefficients is of manageable size in fractional binary notation.

Process block 68 indicates the adjustment of certain coefficients to compensate for inherent divide-by-two operation after a multiplication has been carried out. This step is necessary because a problem exists in the organization of the Model TMC 2010 multiplier-accumulator integrated circuit manufactured by TRW, Inc. and employed in the preferred embodiment. This integrated circuit provides the result of a multiplication/accumulation operation as two separate 16-bit words. Since this integrated circuit is chosen to operate in the fractional two's complement round mode, two 15-bit plus one sign bit numbers provide a 30-bit product and a sign bit. The lower order 16-bit output represents the lower 16 bits of the result, and the upper 16-bit output represents the upper fourteen bits of the result. The sign bit is provided as part of a separate 3-bit word. The effect of this bit arrangement is that, whenever the higher order 16-bit outputs are used, two 15-bit plus one sign bit numbers are multiplied to provide a 14-bit plus one sign bit output. A consequence of this arrangement is that the one significant bit of resolution is lost each time a product is provided or fed back to an input. This loss of data is fatal to accuracy. The problem could be avoided if it were possible to use the most significant bit (MSB) of the lower 16 bits in conjunction with the 14 bits from the upper 16 bits. Unfortunately, this cannot be done when the "round" option is selected for the multiplier because the "round" option always adds a logic 1 to the MSB of the lower 16 bits.

A solution to the problem is to use the higher order 15-bits (14-bit and one sign bit) and thereby cause an implicit divide-by-two operation on the output. This can be compensated for by pre-multiplying by two one of the factors one time for each multiplication operation needed to develop the term. In the preferred embodiment, this pre-multiplication is performed on the coefficients, provided that they remain less than one after pre-multiplication. The A₁, A₂, B₁, and B₂ coefficients are typically greater than one. The A₁ and B₁ coefficients are used as integer numbers and, therefore, do not suffer from the requirement that they be less than one. The B₁ and B₂ coefficients have a typical magnitude of about one. The pre-multiplication factor for the B₁ and B₂ coefficients is two; therefore, the magnitudes of the B₁ and B₂ coefficients are about two. Ensuring a value of less than one is accomplished by dividing the pre-multiplied B₁ and B₂ coefficients by three and performing the B₁ x X and B₂ x Y operations three times each. Manipulating the B₁ and B₂ coefficients in this manner accommodates unscaled values of such coefficients of up to 1.5.

Another instance in which an implicit divide-by-two operation is carried out occurs whenever error correction processor 52 recalls a previous result from a "scratch pad memory" and multiplies the result by one to deliver it to the accumulator. To compensate for the divide-by-two effect, it is necessary to recall the result from scratch pad memory twice, multiply the result by one each time, and add the result to the accumulator contents.

Table II shows the pre-multiplication factors computed for each of the A₁-H₁ and A₂-H₂ coefficients. It will be appreciated that the pre-multiplication process and the normalization and pre-scaling process described with reference to process blocks 66 and 68 may be combined and performed in one operation.

TABLE II

COEFFICIENTS	TYPICAL VALUES	MULTIPLIER	TYPICAL RESULTS
A ₁ , A ₂	+ - 1000	2	+ - 2000
B ₁ , B ₂	1	2 3	2 3
C ₁ , C ₂	+ - 1.3 x 10 ⁻³	4	+ - 5.2 x 10 ⁻³
D ₁ , D ₂	+ - 5.5 x 10 ⁻³	8	+ - 4.4 x 10 ⁻²
E ₁ , E ₂	+ - 3.0 x 10 ⁻³	2	+ - 6 x 10 ⁻³
F ₁ , F ₂	+ - 1.0 x 10 ⁻³	4	+ - 4.0 x 10 ⁻³
G ₁ , G ₂	+ - 3.3 x 10 ⁻⁴	4	+ - 1.3 x 10 ⁻³
H ₁ , H ₂	+ - 5.3 x 10 ⁻²	8	+ - 4.2 x 10 ⁻¹

Process block 70 indicates the conversion of the coefficients from fractional binary format to a binary integer format. The coefficients produced in accordance with the processes described with reference to process blocks 66 and 68 are numbers that will be interpreted as fractional binary numbers by the multiplier/accumulator but need to be presented as binary integers for storage in the error correction processor memory. This is not true, however, for the A₁ and A₂ coefficients because they are directly stored as two's complement integers. The conversion of the B₁-H₁ and B₂-H₂ coefficients to binary integer format entails multiplying the selected coefficient by 32768, rounding the result to the nearest whole number, and storing the number as a two's complement integer in 16-bits.

Fig. 7 is a simplified block diagram of error correction processor 52. With reference to Fig. 7, error correction processor 52 receives the X and Y signals in the form of 16-parallel bit digital words transmitted by way of an X input latch 82 and a Y input latch 84, respectively. The X signal data and Y signal data are stored in the respective input latches 82 and 84 at the appropriate times by a latch and output control signal provided on an output conductor 86 of a sequence controller 88. Sequence controller 88 develops the clock and timing signals in the proper sequence to coordinate and control the various functions of processor 52 to compute and accumulate the terms of the X_c and Y_c transform equations.

A random access memory (RAM) 90 stores the coefficients carried by data bus 56 from calibration data file 54 through system control computer 22 (Fig. 3). The coefficients are read into and read out of RAM 90 in response to a read/write control signal produced on output 92 of sequence controller 88 and an 8-parallel bit address word carried from sequence controller 88 by an address bus 93. The calibration data read out of RAM 90 appear on its output conductors and are delivered on an internal processor bus 94 to the "R" input of a multiplier/accumulator 98. Multiplier/accumulator 98 receives on its "S" input the X and Y signal data provided at different times on the outputs of the respective input latches 82 and 84. Multiplier/accumulator 98 operates in response to the arithmetic function control signals provided on outputs 100 of sequence controller 88 to multiply the data applied to the "R" and "S" inputs and to store the product in an internal "scratch pad" memory. The result of the arithmetic operations of multiplier/accumulator 98 appears on its "P" output, which is connected to processor bus 94. The "P" output and "R" input of multiplier/accumulator 98 are connected to provide an accumulator feedback path.

Processor bus 94 and the outputs of input latches 82 and 84 are connected to different inputs of a tri-state two-way switch 102. Tri-state switch 102 functions in response to a two-way switch control signal produced on output 104 of controller 88 to deliver during calibration raw X and Y position signal data from input latches 82 and 84 to output latches 106 and 108, respectively.

Sequence controller 88 provides on its outputs 86, 92, 100, and 104 control signals in the proper time sequence to deliver the X and Y signal data and coefficients to multiplier/accumulator 98 and to control its mathematical operations so that it can perform the multiplication and addition functions necessary to synthesize the X_c and Y_c transform equations. For example, sequence controller 88 develops the necessary signals to deliver the B₁ coefficient from RAM 90 and the X signal information from input latch 82 to the respective "R" and "S" inputs of multiplier/accumulator 98, which multiplies them and holds the product. Sequence controller 88 next develops the necessary control signals to deliver the A₁ coefficient from RAM 90 to the "R" input of multiplier/accumulator 98, which adds A₁ to the previously computed product, B₁ x X. Error correction processor 52 has a scratch pad memory that forms a part of RAM 90. The manner in which the expansion of the terms of the transform equations is performed and the architecture of error correction processor 52 require that the scratch pad memory store only one intermediate value computed during the expansion. Error correction processor 52 can be configured, however, to store more than one intermediate value, if necessary. All other values are stored in the accumulator.

The synthesis of the X_c transform equation proceeds on each term of the polynomial in an analogous manner until each of the A-H coefficients has been read out of RAM 90 and all of the required algebraic operations have been carried out in accordance with the X_c transform equation. The processing order of the terms during such synthesis is that which is most efficient without overflowing the value limits of multiplier accumulator 98. The synthesis of the Y_c transform equation is similarly carried out in an analogous manner.

The computed results appearing on the "P" output of multiplier accumulator 98 are delivered to the inputs of the respective X_c output latch 108 and Y_c output latch 106, which store the X_c and Y_c signals in response to a store signal provided on output 110 of sequence controller 88. The X_c and Y_c signals appearing on the outputs of the respective output latches 106 and 108 are applied to the inputs of galvanometer beam positioner 12 (Fig. 3), which directs laser beam 14 to the commanded position on target surface 18.

Fig. 8 is a map of an exemplary addressable field 120 showing the light beam grid pattern described on target surface 18 by unit angular displacements of galvanometer mirrors 26 and 28 in response to unit changes in command data position values. Fig. 8 shows that the addressable field 120 of target surface 18 exhibits equidistant spacing of 2.5 mm between adjacent positions over virtually the entire addressable field. This is in contrast to addressable field 34 (Fig. 2) produced in accordance with the prior art. The operation of error correction processor 52 eliminates, therefore, the pincushion distortion and thereby eliminates the beam positioning nonlinearity that is characteristic of prior art light beam positioning systems.

It will be obvious to those having skill in the art that many changes may be made in the above-described details of the preferred embodiment of the present invention without departing from the underlying principles thereof. The scope of the invention should, therefore, be determined only with reference to the following claims.

Claims

1. A light beam position error correction system (50) comprising:

beam positioning means (12) for receiving a light beam (14) from light source means (16), said positioning means (12) being arranged to direct the light beam (14) towards a position on a target surface (18);

position data generating means (24) receiving from a system control computer (22) beam position command data corresponding to a preselected position on said target surface (18) to generate position coordinate signals to direct said light beam (14) to the preselected position on said target surface (18), characterized by:

calibration data file means (54) for selectively delivering calibration data relative of light beam positioning errors of said beam positioning means (12); and

error correction processing means (52) receiving said position coordinate signals from said position data generating means (24) and receiving calibration data from said calibration data file means (54) to develop compensated position coordinate signals corrected for light beam positioning errors introduced by said beam positioning means (12) and delivering said compensated position control signals to said beam positioning means (12) so that said beam positioning means (12) directs the light beam (14) to the preselected position on the target surface (18).

2. The system of claim 1 in which the compensated position coordinate signals comprise an X_c signal and a Y_c signal and in which the beam positioning means (12) comprises a pair of first and second independently movable light reflecting surfaces (26, 28) that receive the light beam, the first and second light reflecting surfaces (26, 28) receive the X_c and Y_c signals to move the light beam (14) in respective first and second orthogonal directions along the target surface (18) to position the light beam (14) at the preselected position.

3. The system of claim 2 in which the beam positioning means further comprises a lens (30).

4. The system of claim 3 in which the lens (30) is of the F- θ type.

5. The system of claim 1 in which the light source means (16) comprises a laser.

6. The system of claim 1 in which the position coordinate signals comprise an X signal and a Y signal that indicate the instantaneous commanded position of the light beam (14), and the compensated position

coordinate signals include an X_c signal and a Y_c signal, the X_c signal being a function of polynomial

$$B \cdot X + C \cdot X^2 + D \cdot X^3 + E \cdot Y + F \cdot Y^2 + G \cdot XY + H \cdot XY^2$$

and the Y_c position signal being a function of the polynomial

$$B_2 Y + C_2 Y^2 + D_2 Y^3 + E_2 X + F_2 X^2 + G_2 XY + H_2 YX^2.$$

where $B_1, C_1, D_1, E_1, F_1, G_1, H_1, B_2, C_2, D_2, E_2, F_2, G_2$, and H_2 represent field correction coefficients of constant values that correspond to the light directing optical properties of the beam positioning means (12).

7. The system of claim 6 in which the term A_1 is added to the polynomial of which X_c is a function and the term A_2 is added to the polynomial of which Y_c is a function, the A_1 and A_2 terms representing respective X- and Y-axis offsets in an X-Y coordinate system.

8. The system of claim 1 in which the position coordinate signals comprise an X signal and a Y signal that indicate the instantaneous commanded position of the light beam (14), and the compensated position coordinate signals include an X_c signal and a Y_c signal, the X_c and Y_c signals being proportional to polynomials that include the respective terms $G_1 XY$ and $G_2 YX$ to correct position errors resulting from wedge angle distortion and the respective terms $H_1 XY^2$ and $H_2 X^2 Y$ to correct for position errors resulting from parabolic curvature distortion.

9. The system of claim 1, further comprising calibration data generating means to develop the previously acquired calibration data at system initialization by determining an actual beam position on the target surface (18) and the corresponding position coordinate signals.

10. A method of positioning a light beam (14), comprising:

providing beam position command data from a system computer (22), the beam position command data corresponding to an intended position to which a light beam (14) is to be directed on a target surface (18);

converting the beam position command data into position coordinate signals that correspond to the intended position on the target surface (18) so that the position signals can be used by a beam positioner (12), characterized by:

acquiring calibration data that are characteristic of the optical properties of a light beam positioning system (12) such that the acquisition of the calibration data includes selecting an array of calibration points in an addressable field of a target surface (18), scanning the field until the light beam (14) strikes each one of the calibration points, and determining the position coordinate signals required to position the light beam (14) at the calibration points;

storing said calibration data in a calibration data file means (54);

using the stored calibration data to transform the beam position command data into compensated position coordinate signals; and

providing the compensated position coordinate signals to a beam positioner (12) to direct the light beam (14) to the intended position on the target surface (18).

11. The method of claim 10, in which the compensated position coordinate signals comprise an X_c signal and a Y_c signal and in which the beam positioner (12) comprises a pair of first and second independently movable light reflecting surfaces (26, 28) that receive the light beam (14), the first and second light reflecting surfaces (26, 28) receiving the X_c and Y_c signals to move the light beam (14) in respective first and second orthogonal directions along the target surface (18) to position the light beam (14) at the intended position.

12. The method of claim 10, in which the light beam (14) is generated from a laser source (16) and in which the beam position command data is obtained from read only memory.

Patentansprüche

1. Lichtstrahlpositionsfehler-Korrektursystem (50), welches umfaßt:

- eine Strahlpositioniereinrichtung (12), zum Empfangen eines Lichtstrahls (14) von einer Lichtquelleinrichtung (16), wobei die Positioniereinrichtung (12) so angeordnet ist, daß sie den Lichtstrahl (14) zu einer Stelle auf einer Zieloberfläche (18) lenkt.

5 eine Positionsdaten-Erzeugungseinrichtung (24), welche von einem Systemsteuercomputer (22) Strahlpositions-Befehlsdaten empfängt, die einer vorgewählten Stelle auf der Zieloberfläche (18) entsprechen, zum Erzeugen von Positionskoordinatensignalen, um den Lichtstrahl (14) zu der vorgewählten Stelle auf der Zieloberfläche (18) zu lenken, gekennzeichnet durch

- eine Kalibrierdaten-Fileeinrichtung (54) zur selektiven Abgabe von Kalibrierdaten bezüglich von Lichtstrahlpositionierfehlern der Strahlpositioniereinrichtung (12) und
- einen Fehlerkorrektur-Prozessor (52), welcher die Positionskoordinatensignale von der Positionsdaten-Erzeugungseinrichtung (24) und Kalibrierdaten von der Kalibrierdaten-Fileeinrichtung (54) empfängt, um kompensierte Positionskoordinatensignale zu erzeugen, die bezüglich der Lichtstrahlpositionierfehler korrigiert sind, die durch die Strahlpositioniereinrichtung (12) erzeugt werden, und welcher kompensierte Positionssteuersignale an die Strahlpositioniereinrichtung (12) abgibt, so daß die Strahlpositioniereinrichtung (12) den Lichtstrahl (14) zu der vorgewählten Stelle auf der Zieloberfläche (18) lenkt.

2. System nach Anspruch 1, bei welchem die kompensierten Positionskoordinatensignale ein X_c -Signal und ein Y_c -Signal umfassen und bei dem die Strahlpositioniereinrichtung (12) ein Paar aus ersten und zweiten unabhängig voneinander beweglichen lichtreflektierenden Flächen (26, 28) umfaßt, welche den Lichtstrahl empfangen, und die ersten und zweiten lichtreflektierenden Flächen (26, 28) die X_c und Y_c -Signale empfangen, um den Lichtstrahl (14) in entsprechenden ersten und zweiten orthogonalen Richtungen auf der Zieloberfläche (18) zu bewegen, um den Lichtstrahl (14) an der vorgewählten Stelle zu positionieren.

3. System nach Anspruch 2, bei welchem die Strahlpositioniereinrichtung weiterhin eine Linse (30) enthält.

4. System nach Anspruch 3, bei welchem die Linse (30) von F- θ -Typ ist.

5. System nach Anspruch 1, bei welchem die Lichtquelle (16) einen Laser umfaßt.

6. System nach Anspruch 1, bei welchem die Positionskoordinatensignale ein X-Signal und ein Y-Signal umfassen, welche die momentane befohlene Position des Laserstrahls (14) angeben, und die kompensierten Positionskoordinatensignale ein X_c -Signal und ein Y_c -Signal umfassen, wobei das X_c -Signal eine Funktion des Polynoms

$$B_1 X + C_1 X^2 + D_1 X^3 + E_1 Y + F_1 Y^2 + G_1 XY + H_1 XY^2$$

ist und das Y_c -Positionssignal eine Funktion des Polynoms

$$B_2 Y + C_2 Y^2 + D_2 Y^3 + E_2 X + F_2 X^2 + G_2 XY + H_2 YX^2$$

ist, wobei $B_1, C_1, D_1, E_1, F_1, G_1, H_1, B_2, C_2, D_2, E_2, F_2, G_2$ und H_2 Feldkorrekturkoeffizienten mit konstantem Wert darstellen, welche den optischen Lichtlenkeigenschaften der Strahlpositioniereinrichtung (12) entsprechen.

7. System nach Anspruch 6, bei welchem der Term A_1 zu dem Polynom addiert wird, von welchem X_c eine Funktion ist, und der Term A_2 zu dem Polynom addiert wird, von welchem Y_c eine Funktion ist, wobei die A_1 - und A_2 -Terme den jeweiligen Versatz der X- bzw. Y-Achse in einem X-Y-Koordinatensystem darstellen.

8. System nach Anspruch 1, bei welchem die Positionskoordinatensignale ein X-Signal und ein Y-Signal umfassen, welche die momentane befohlene Position des Lichtstrahls (14) angeben, und die kompensierten Positionskoordinatensignale ein X_c -Signal und ein Y_c -Signal umfassen, wobei die X_c - und Y_c -Signale proportional zu Polynomen sind, die den Term $G_1 XY$ bzw. $G_2 YX$ zum Korrigieren der Positionfehler, die aus der Keilwinkel-Verzerrung herrühren, und den Term $H_1 XY^2$ bzw. $H_2 X^2 Y$ zum Korrigieren der Positionfehler, die aus einer Parabelkurven-Verzerrung herrühren, enthalten.

9. System nach Anspruch 1, welches weiterhin eine Kalibrierdaten-Erzeugungseinrichtung enthält, um die vorher gewonnenen Kalibrierdaten bei der Systeminitialisierung zu erzeugen, indem eine tatsächliche Strahlposition auf der Zieloberfläche (18) und die zugehörigen Positionskoordinatensignale bestimmt werden.

5

10. Verfahren zum Positionieren eines Lichtstrahls (14), welches umfaßt:

- Bereitstellen von Strahlpositions-Befehlsdaten aus einem Systemcomputer (22), wobei die Strahlpositions-Befehlsdaten einer angestrebten Position entsprechen, zu welcher ein Lichtstrahl (14) auf einer Zieloberfläche (18) gelenkt werden soll,
- Konvertieren der Strahlpositions-Befehlsdaten in Positionskoordinatensignale, die der angestrebten Position auf der Zieloberfläche (18) entsprechen, so daß die Positionssignale von einem Strahlpositionierer (12) verwendet werden können,

10

gekennzeichnet durch

- Ermitteln von Kalibrierdaten, die charakteristisch für die optischen Eigenschaften eines Lichtstrahlpositioniersystems (12) sind, derart, daß das Ermitteln der Kalibrierdaten das Auswählen einer Gruppe von Kalibrierpunkten in einem ansteuerbaren Feld einer Zieloberfläche (18), das Abtasten des Feldes, bis der Lichtstrahl (14) jeden Kalibrierpunkt trifft, und das Bestimmen der Positionskoordinatensignale, die erforderlich sind, um den Lichtstrahl (14) an den Kalibrierpunkten zu positionieren, umfaßt,
- Speichern der Kalibrierdaten in einer Kalibrierdaten-Fileinrichtung (54)
- Verwenden der gespeicherten Kalibrierdaten, um die Strahlpositions-Befehlsdaten in kompensierte Positionskoordinatensignale umzuwandeln, und
- Abgeben der kompensierten Positionskoordinatensignale an einen Strahlpositionierer (12), um den Lichtstrahl (14) zu der beabsichtigten Position auf der Zieloberfläche (18) zu lenken.

15

20

25

11. Verfahren nach Anspruch 10, bei dem die kompensierten Positionskoordinatensignale ein X_c -Signal und ein Y_c -Signal umfassen und bei dem der Strahlpositionierer (12) ein Paar aus ersten und zweiten unabhängig voneinander beweglichen lichtreflektierenden Flächen (26, 28) umfaßt, welche den Lichtstrahl (14) empfangen, wobei die ersten und zweiten lichtreflektierenden Flächen (26, 28) die X_c - und Y_c -Signale empfangen, um den Lichtstrahl (14) in entsprechende erste und zweite orthogonale Richtungen auf der Zieloberfläche (18) zu bewegen, um den Lichtstrahl (14) an der beabsichtigten Stelle zu positionieren.

30

12. Verfahren nach Anspruch 10, bei dem der Lichtstrahl (14) durch eine Laserquelle (16) erzeugt wird und bei dem die Strahlpositions-Befehlsdaten von einem ROM geliefert werden.

35

Revendications

1. Un système de correction d'erreur de position de faisceau lumineux (50) comprenant :

40

un moyen de positionnement de faisceau (12) pour recevoir un faisceau lumineux (14) depuis un moyen de source lumineuse (16), ledit moyen de positionnement (12) étant disposé pour diriger le faisceau lumineux (14) vers une position sur une surface de cible (18) ;

45

un moyen de génération de données de position (24) recevant d'un ordinateur de contrôle de système (22) des données de commande de position de faisceau correspondant à une position présélectionnée sur ladite surface de cible (18) pour générer des signaux de coordonnées de position pour diriger ledit faisceau lumineux (14) vers la position présélectionnée sur ladite surface de cible (18), caractérisé par :

50

un moyen de fichier de données d'étalonnage (54) pour délivrer sélectivement des données d'étalonnage relatives aux erreurs de positionnement du faisceau lumineux dudit moyen de positionnement de faisceau (12) ; et

55

un moyen de traitement de correction d'erreur (52) recevant lesdits signaux de coordonnées de position depuis ledit moyen de génération de données de position (24) et recevant des données d'étalonnage depuis ledit moyen de fichier de données d'étalonnage (54) pour développer des signaux de coordonnées de position compensées corrigés pour les erreurs de positionnement de faisceau lumineux introduites par ledit moyen de positionnement de faisceau (12) et délivrant lesdits signaux de contrôle de position compensée audit moyen de positionnement de faisceau (12), de telle sorte que ledit moyen de positionnement de faisceau (12) dirige le faisceau lumineux (14) vers la position présélectionnée sur la surface de cible (18).

2. Le système de la revendication 1, dans lequel les signaux de coordonnées de position compensée comprennent un signal X_c et un signal Y_c et dans lequel le moyen de positionnement de faisceau (12) comprend une paire de première et seconde surfaces réfléchissant la lumière déplaçables indépendamment (26, 28) qui reçoivent le faisceau lumineux, les première et seconde surfaces réfléchissant la lumière (26, 28) reçoivent les signaux X_c et Y_c pour déplacer le faisceau lumineux (14) dans des première et seconde directions orthogonales respectives le long de la surface de cible (18) pour positionner le faisceau lumineux (14) à la position présélectionnée.

3. Le système de la revendication 2, dans lequel le moyen de positionnement de faisceau comprend en outre une lentille (30).

4. Le système de la revendication 3, dans lequel la lentille (30) est du type F- θ .

5. Le système de la revendication 1, dans lequel le moyen de source lumineuse (16) comprend un laser.

6. Le système de la revendication 1, dans lequel les signaux de coordonnées de position comprennent un signal X et un signal Y qui indiquent la position commandée instantanée du faisceau lumineux (14), et les signaux de coordonnées de position compensée incluent un signal X_c et un signal Y_c , le signal X_c étant une fonction du polynôme :

$$B_1 X + C_1 X^2 + D_1 X^3 + E_1 Y + F_1 Y^2 + G_1 XY + H_1 XY^2$$

et le signal de position Y_c étant une fonction du polynôme :

$$B_2 Y + C_2 Y^2 + D_2 Y^3 + E_2 X + F_2 X^2 + G_2 XY + H_2 YX^2$$

où B_1 , C_1 , D_1 , E_1 , F_1 , G_1 , H_1 , B_2 , C_2 , D_2 , E_2 , F_2 , G_2 et H_2 représentent les coefficients de correction de champ de valeurs constantes qui correspondent aux propriétés optiques de direction de la lumière du moyen de positionnement de faisceau (12).

7. Le système de la revendication 6, dans lequel le terme A_1 est ajouté au polynôme duquel X_c est une fonction et le terme A_2 est ajouté au polynôme duquel Y_c est une fonction, les termes A_1 et A_2 représentant des décalages respectivement d'axes X et Y dans un système de coordonnées X-Y.

8. Le système de la revendication 1, dans lequel les signaux de coordonnées de position comprennent un signal X et un signal Y qui indiquent la position commandée instantanée du faisceau lumineux (14), et les signaux de coordonnées de position compensée incluent un signal X_c et un signal Y_c , les signaux X_c et Y_c étant proportionnels à des polynômes qui incluent les termes respectifs $G_1 XY$ et $G_2 XY$ pour corriger des erreurs de position résultant de distorsion d'angle de coin et les termes respectifs $H_1 XY^2$ et $H_2 X^2 Y$ pour corriger des erreurs de position résultant de distorsion de courbure parabolique.

9. Le système de la revendication 1, comprenant en outre un moyen de génération de données d'étalonnage pour développer les données d'étalonnage précédemment acquises à l'initialisation du système en déterminant une position de faisceau réelle sur la surface cible (18) et les signaux de coordonnées de position correspondant.

10. Un procédé de positionnement d'un faisceau lumineux (14), comprenant :

la fourniture des données de commande de position de faisceau à partir d'un ordinateur de système (22), les données de commande de position de faisceau correspondant à une position désirée vers laquelle un faisceau lumineux (14) doit être dirigé sur une surface de cible (18) ;

la conversion des données de commande de position de faisceau en des signaux de coordonnées de position qui correspondent à la position désirée sur la surface de cible (18), de telle sorte que les signaux de position peuvent être utilisés par un élément de positionnement de faisceau (12), caractérisé par :

l'acquisition des données d'étalonnage qui sont caractéristiques des propriétés optiques d'un système de positionnement de faisceau lumineux (12), telle que l'acquisition des données d'étalonnage inclut le choix d'un ensemble de points d'étalonnage dans un domaine accessible d'une surface de cible (18), le balayage du domaine jusqu'à ce que le faisceau lumineux (14) rencontre chacun des

points d'étalonnage, et la détermination des signaux de coordonnées de position requis pour positionner le faisceau lumineux (14) aux points d'étalonnage ;

le stockage desdites données d'étalonnage dans un moyen de fichier de données d'étalonnage (54) ;

5 l'utilisation des données d'étalonnage stockées pour transformer les données de commande de position de faisceau en des signaux de coordonnées de position compensée ; et

la fourniture des signaux de coordonnées de position compensée à un élément de positionnement de faisceau (12) pour diriger le faisceau lumineux (14) vers la position désirée sur la surface de cible (18).

10

11. Le procédé de la revendication 10, dans lequel les signaux de coordonnées de position compensée comprennent un signal X_c et un signal Y_c et dans lequel l'élément de positionnement de faisceau (12) comprend une paire de première et seconde surfaces réfléchissant la lumière déplaçables indépendamment (26, 28) qui reçoivent le faisceau lumineux (14), les première et seconde surfaces réfléchissant la lumière (26, 28) recevant les signaux X_c et Y_c pour déplacer le faisceau lumineux (14) dans des première et seconde directions orthogonales respectives le long de la surface de cible (18) pour positionner le faisceau lumineux (14) à la position désirée.

15

12. Le procédé de la revendication 10, dans lequel le faisceau lumineux (14) est généré à partir d'une source laser (16) et dans lequel les données de commande de position de faisceau sont obtenues à partir d'une mémoire morte.

20

25

30

35

40

45

50

55