Apparatus and Method for Filtering in Video Coding

~~CROSS-REFERENCE TO RELATED APPLICATIONS~~

~~This application claims the benefit of U.S. Provisional Application No. 62/693,441, filed on July 02, 2018, entitled "Apparatus and Method for Filtering in Video Coding", U.S. Provisional Application No. 62/725,845, filed on August 31, 2018, entitled "Apparatus and Method for Filtering in Video Coding", U.S. Provisional Application No. 62/731,967, filed on September 16, 2018, entitled "Apparatus and Method for Filtering in Video Coding", U.S. Provisional Application No. 62/731,972, filed on September 17, 2018, entitled "Apparatus and Method for Filtering in Video Coding", U.S. Provisional Application No. 62/735,722, filed on September 24, 2018, entitled "Filtering In Video Coding", U.S. Provisional Application No. 62/757,732, filed on November 08, 2018, entitled "Apparatus and Method for Filtering in Video Coding", U.S. Provisional Application No. 62/793,866, filed on January 17, 2019, entitled "Apparatus and Method for Filtering in Video Coding", all of which applications are incorporated herein by references.~~

TECHNICAL FIELD

[0001] Generally, the present invention relates to the field of video coding. More specifically, the present invention relates to a filter for video coding, method for filtering reconstructed video frames, and method for filtering video blocks as well as an encoding apparatus and a decoding apparatus comprising such the filter for video coding.

BACKGROUND

[0002] Digital video has been widely used since the introduction of DVD-discs. Before transmission the video is encoded and transmitted using a transmission medium. The viewer receives the video and uses a viewing device to decode and display the video. Over the years the quality of video has improved, for example, because of higher resolutions, color depths and frame rates. This has lead into larger data streams that are nowadays commonly transported over internet and mobile

[0036] FIG. 10 as an example, shows undesirable gap in filter transfer function;

[0037] FIG. 11 as an example, represents same table with table entries being plot one-by-one;

[0038] FIG. 12 as an example, illustrates the method how gap can be eliminated using auxiliary function;

[0039] FIG. 13 illustrates the example of eliminating gap by taken maximum from two values while generating the LUT;

[0040] FIG. 14, as an example, illustrates filter transfer function after applying ~~descibed~~described above method;

[0041] FIG. 15 illustrates example of filter transfer functions depending on five QPs in the set;

[0042] FIG. 16 illustrates example of filter transfer functions for five QPs in the set based on corresponding tables;

[0043] FIG. 17 illustrates example of filter transfer functions for five QPs in the set based on corresponding tables; and

[0044] FIG. 18 is a schematic diagram illustrating an exemplary structure of an apparatus according to an embodiment.

[0045] In the various figures, identical reference signs will be used for identical or functionally equivalent features.

DETAILED DESCRIPTION OF EMBODIMENTS

[0046] In the following description, reference is made to the accompanying drawings, which form part of the disclosure, and in which are shown, by way of illustration, specific aspects in which the present invention may be placed. It is understood that other aspects may be utilized and structural or logical changes may be made without departing from the scope of the present invention. The following detailed description, therefore, is not to be taken in a limiting sense, as the scope of the present invention is defined by the appended claims.

[0047] For instance, it is understood that a disclosure in connection with a described method may also hold true for a corresponding device or system configured to perform the method and vice versa. For example, if a specific method step is described, a corresponding device may include a unit to perform the described method step, even if such unit is not explicitly described or illustrated in the figures. Further, it

transformation unit 212. As in the case of the encoding apparatus 100, the reconstructed block can be provided to a line buffer 216 used for intra prediction and the filtered block/frame can be provided to a decoded picture buffer 230 by the filter 220 for inter prediction.

[0056] As shown in Fig. 2B, the prediction signal in the hybrid ~~encoder~~ decoder embodiment shown in Fig. 2B obtain from intra or inter prediction is further filtered by filter 264.

[0057] As already described above, the filter 120, 220 may be used at a frame level, for example, the filter 120, 220 may be configured to process a reconstructed frame from a decoded reconstructed video stream for generating a filtered reconstructed frame, where the reconstructed frame includes a plurality of blocks. The filter 120, 220 may be also used at a block level immediately after block reconstruction without waiting for a whole frame, for example, the filter 120, 220 may be configured to process a reconstructed block for generating a filtered reconstructed block, where the reconstructed block includes a plurality of pixels.

[0058] The filter 120, 220, 145 or 264 comprises one or more processor (or one or more processing unit). As will be explained in more detail below, the one or more processor (or one or more processing unit) is configured to: load a current pixel and its neighboring pixels to a linear buffer according to a predefined scan template (in other words, scan order, or scan pattern); obtain spectrum components by performing 1D transform for each pixel in the linear buffer; obtain filtered spectrum components by multiplying each spectrum component with a gain coefficient, wherein the gain coefficient depends on a corresponding spectrum component and a filtering parameter; obtain filtered pixels by performing inverse 1D transform for filtered spectrum; and generate a filtered reconstructed block based on the filtered pixels estimated on previous processing steps. In an example, the gain coefficient depends on a corresponding spectrum component and a filtering parameter. In another example, the gain coefficient depends on one or more filtering parameters and one or more corresponding spectrum components. In other example, the respective gain coefficient may depend on one or more filtering parameters and the corresponding spectrum component as well as neighboring spectral components to the left and to the right of the spectrum component.

[0059] The disclosure describes in-loop filter for lossy video codec which

performs local and/or non-local filtering of reconstructed block from reconstructed frame. According to an example, the reconstructed frame is divided into set of small non-overlapped rectangular blocks (CU blocks). On the next step each reconstructed block (reconstructed CU block) is filtered in frequency domain independently from other reconstructed blocks. The filter can also be applied after transform and reconstruction, and the filtered result is used both for output as well as for spatial and temporal prediction.

[0060] As another example, the disclosure describes prediction filter for lossy video codec which performs local and/or non-local filtering of prediction block of reconstructed frame.

[0061] At the first step of processing all pixels inside reconstructed block can be processed independently from each other. For processing of pixel r(0), neighboring pixels are used. For example, as illustrated on Figure 3A, pixels r(1) to r(7) are used, and pixels r(0) to r(7) form one processing group.

[0062] Fig. 3A or 3B shows a schematic diagram 300, 300' illustrating aspects of a filtering process implemented in a filter according to an embodiment. At step 302, 302', a current pixel and its neighboring pixels from a block are loaded to a linear buffer according to a predefined scan template. As an example, the block may be a predicted block. As another example, the block may be a reconstructed block.

[0063] At step 304, 304', 1D transform is performed for pixel r(0) and its neighboring pixels r(1) to r(7) in the linear buffer to obtain spectrum components R:

$$\boldsymbol{R = 1D_Transform(r)}$$

[0064] As an example, the 1D transform may be a Hadamard transform.

[0065] It should be understood that whether to perform 1D transform on 4 pixels in the ~~raw~~ row (e.g. pixels A,B,C,D as in example on Fig. 3B) or perform 2D transform to spatially located pixels A,B,C,D relates to implementation specific. Applying 2D transform on 4 pixels A,B,C,D located in 2x2 block can lead to same result as applying 1D transform to 4 pixels A,B,C,D being taken as a ~~raw~~row. At step 306, 306', filtering is performed in frequency domain based on multiplication of each spectrum component $\boldsymbol{R(i)}$ by a corresponding gain coefficient $\boldsymbol{G(i,\sigma)}$ to obtain a filtered spectrum components $\boldsymbol{F(i)}$:

[0066] The set of gain coefficients for all spectrum components is frequency

$$\boldsymbol{F(i) = R(i) * G(i,\sigma)} \qquad \textbf{(1)}$$

[00154] In some implementation keeping LUT size limited and having THR in order to keep of equation from para [0077} maybe contradictory. Indeed at high QP values (which leads to high σ value) keeping LUT size limited by e.g. 16 entries may lead to undesirable gap in filter transfer function (which is represented by LUT) around value 120 as depicted on FIG. 10 (which also includes method of LUT subsampling by dropping of 3 least significant bits off).

[00155] FIG. 11 represents same table with table entries being plot one-by-one without consideration LUT subsampling effect illustrating gap between last LUT entry at index 15 and next point in filter transfer function at index 16.

[00156] FIG. 12 illustrates the method how gap can be eliminated using auxiliary function coming through THR value at the argument of corresponding to last LUT entry + 1, e.g. by using straight line equation (pointed by green color), coming through point THR=128 at argument 16 that corresponds to argument of last LUT entry (which is 15) increased by 1 or in other words LUT size (which is 16) and crossing x-axis at some point (e.g. at a value of 11 like in given example). It should be noted that other types of auxiliary functions can be used based on same principle, e.g. exponential, logarithmic, parabolic etc. or combination of them.

[00157] FIG. 13 Illustrates the example of eliminating gap by taken maximum from two values while generating the LUT, where the first value is LUT entry as described above $LUT(R_i, \sigma) = \frac{R_i^3}{R_i^2 + m * \sigma^2}$; and the second is a value of AuxiliaryFunction (straight line in this example) at the same argument i:

$$LUT(R_i, \sigma) = \max\left(\frac{R_i^3}{R_i^2 + m * \sigma^2}, AuxiliaryFunc_\sigma(i)\right);$$

where $AuxiliaryFunc_\sigma(i)$ represents the auxiliary function, and the auxiliary function has a value equal to THR at *i* corresponding to an argument of last LUT + 1.

[00158] FIG. 14 illustrates filter transfer function after applying ~~descibed~~described above method of using auxilary straight line equation and LUT subsampling by dropping 3 least significant bits.

[00159] As ~~descibed~~described in para [00144] one LUT can used for group of QPs. To cover the possible QP range the predefined QP set is used and one LUT is generated for each QP from the set. The FIG.15 illustrates example of filter transfer functions depending on five QPs in the set and corresponding tables (from 0 to 4). In this

example the table 4 is generated using method described in paras [00156]-[00157] with straight-line auxiliary function crossing x-axis at the value of 11; and table 3 is generated using same method with straight-line auxiliary function crossing x-axis at the value of 9. The tables used in this ~~exampe~~example have values according to:

table0 = { 0, 2, 10, 19, 28, 36, 45, 53, 61, 70, 78, 86, 94, 102, 110, 118, },

table1 = { 0, 0, 5, 12, 20, 29, 38, 47, 56, 65, 73, 82, 90, 98, 107, 115, },

table2 = { 0, 0, 1, 4, 9, 16, 24, 32, 41, 50, 59, 68, 77, 86, 94, 103, },

table3 = { 0, 0, 0, 1, 3, 5, 9, 14, 19, 25, 32, 40, 55, 73, 91, 110, },

table4 = { 0, 0, 0, 0, 0, 1, 2, 4, 6, 8, 11, 14, 26, 51, 77, 102, },

[00160] As described above in paras [00150]-[00153] the method of table subsampling can drop N bits from table values to reduce table size. As also mentioned in these paras N may be different depending on QP used for certain table generation and selected THR value for this table. For example for lower QP values the filtering parameter σ is relatively lower than for higher QPs. Thus the absolute value of THR can be reduced without sacrificing of performance. Furthermore to keep table size same for all QPs in the set (that is beneficial for simplifying implementation) and reduce subsampling rate for lower QPs (which correspond for less compression level and better reconstructed picture quality) it may be beneficial to reduce the amount of dropped bits N in comparison to other QP tables, e.g. by setting N for lover QP equal to 2 and setting THR to 64. The FIG. 16 illustrates example of filter transfer functions for five QPs in the set based on corresponding tables (from 0 to 4) with N set to 2 for first table (corresponding to lover QP range) and N set to 3 for other tables. This example also includes method of using *AuxiliaryFunction* for table 3 and table 4 generation as ~~descibed~~described in paras [00159]-[00160]. For table 4 straight-line auxiliary function crosses the x-axis at the value of 11. For table 4 straight-line auxiliary function crosses the x-axis at the value of 9. The tables used in this ~~exampe~~example have values according to:

table0 = { 0, 0, 2, 6, 10, 14, 19, 23, 28, 32, 36, 41, 45, 49, 53, 57, },

table1 = { 0, 0, 5, 12, 20, 29, 38, 47, 56, 65, 73, 82, 90, 98, 107, 115, },

table2 = { 0, 0, 1, 4, 9, 16, 24, 32, 41, 50, 59, 68, 77, 86, 94, 103, },

table3 = { 0, 0, 0, 1, 3, 5, 9, 14, 19, 25, 32, 40, 55, 73, 91, 110, },

table4 = { 0, 0, 0, 0, 0, 1, 2, 4, 6, 8, 11, 14, 26, 51, 77, 102, },

[00161] As described above in paras [00150]-[00153] the method of table

subsampling can drop N bits from table values to reduce table size. As also mentioned in these paras N may be different depending on QP used for certain table generation and selected THR value for this table. For example for higher QP values the filtering parameter σ is relatively higher than for lower QPs that may require on increase THR value to keep equation from para [0077] closer to 1. At the same time to keep LUT size same for all QPs in the set (which is beneficial due to simplification of implementation) and also considering that for higher QP values reconstructed picture has more distortions and increasing subsampling of LUT is acceptable due to subjectively unnoticeable effect of LUT subsampling in presence of strong compression artifacts the value N of least significant bitts dropped may be increased to 4 e.g. for last and for second last table in the set. FIG. 17 illustrates example of filter transfer functions for five QPs in the set based on corresponding tables (from 0 to 4) with N set to 2 for first table (table 0 corresponding to lover QP range), N set to 4 for last and second last table (table 3 and table 4) and N set to 3 for other tables. In this example TRH is set to 64 for first table generation, set to 256 for last end second last table and set to 128 for rest tables. This example also includes method of using *AuxiliaryFunction* for table 3 and table 4 generation as ~~descibed~~described in paras [00159]-[00160]. For table 4 straight-line auxiliary function crosses the x-axis at the value of 6. For table 4 straight-line auxiliary function crosses the x-axis at the value of 8. The tables used in this ~~exampe~~example have values according to:

table0 = { 0, 0, 2, 6, 10, 14, 19, 23, 28, 32, 36, 41, 45, 49, 53, 57, },
table1 = { 0, 0, 5, 12, 20, 29, 38, 47, 56, 65, 73, 82, 90, 98, 107, 115, },
table2 = { 0, 0, 1, 4, 9, 16, 24, 32, 41, 50, 59, 68, 77, 86, 94, 103, },
table3 = { 0, 0, 3, 9, 19, 32, 47, 64, 81, 99, 117, 135, 154, 179, 205, 230, },
table4 = { 0, 0, 0, 2, 6, 11, 18, 27, 38, 51, 64, 96, 128, 160, 192, 224, },

[00162] FIG. 18 is a block diagram of an apparatus 600 that can be used to implement various embodiments. The apparatus 600 may be the encoding apparatus as shown in FIG.1 and the decoding apparatus as shown in FIG. 2. Additionally, the apparatus 600 can host one or more of the described elements. In some embodiments, the apparatus 600 is equipped with one or more input/output devices, such as a speaker, microphone, mouse, touchscreen, keypad, keyboard, printer, display, and the like. The apparatus 600 may include one or more central processing units (CPUs) 610, a memory 620, a mass storage 630, a video adapter 640, and an

CLAIMS

1. A method for processing a reconstructed block, wherein the reconstructed block comprises a plurality of pixels, wherein the method comprises:

scanning a current pixel of the reconstructed block and its neighboring pixels of the current pixel according to a predefined scan template;

obtaining spectrum components by performing transform for the current pixel and its neighboring pixels;

obtaining filtered spectrum components based on a filtering parameter and the spectrum components;

obtaining filtered pixels by performing inverse transform for the filtered spectrum components; and

generating a filtered reconstructed block based on the filtered pixels.

2. The method of claim 1, wherein the obtaining the filtered spectrum components by using a look up table (LUT).

3. The method of claim 2, a filtered spectrum component $F(i,\sigma)$ is derived by:

$$F(i,\sigma) = \begin{cases} R(i) \ , \ Abs(R(i)) \geq THR \\ LUT(R(i),\sigma), \ R(i) > 0 \\ -LUT(-R(i),\sigma), \ R(i) \leq 0 \end{cases}$$

wherein (i) is an index of a spectrum component, R(i) is the spectrum component corresponding to (i) index, σ is the filtering parameter, $LUT(R(i),\sigma)$ is an array in the look up table, and THR is a threshold.

4. The method of claim 3, wherein $LUT(R(i),\sigma) = \frac{R(i)^3}{R(i)^2+\mathrm{m}*\sigma^2}$, m is normalization constant equal to number of spectrum components.

5. The method of any one of claims 2-4, wherein the filtering parameter is derived based on a codec quantization parameter (QP).

6. The method of claim 5, wherein the filtering parameter σ is derived by

$$\sigma = k * 2^{(n*(QP-s))}$$

, wherein QP is the codec quantization parameter, k, n and s are constants.

7. The method of claim 6, wherein $k = 2.64, n = 0.1296$ and $s = 11$.

8. The method of claim 6 or 7, wherein k is modified based on bit depth of pixels $k_{mod} = k*(1 << (bit_depth - 8))$.

9. The method of claim 5, wherein the filtering parameter σ is equal to zero if QP <= 17, and the reconstructed block is bypassed without filtering.

10. The method of any one of claims 2-9, THR is dependent of QP value.

11. The method of claim 10, THR is derived by:

$$\frac{THR^2}{THR^2 + m*\sigma^2} = C$$

Wherein C is a value close to 1.

12. The method of any one of claims 1-11, wherein the predefined scan template is defined as set of spatial or raster offsets relative to a position of the current pixel inside the reconstructed block.

13. The method of claim 12, wherein the predefined scan template is defined as follows: scanTmpl[4] (y, x) ={ (0,0), (0,1), (1,0), (1,1) }

14. The method of claim 12, wherein when the predefined scan template is defined as set of raster offsets relative to the position of the current pixel inside the reconstructed block, offsets point to neighbour pixels are inside the reconstructed block.

15. The method of any one of claims 1-14, wherein at least one filtered pixel is placed to its original position according to the predefined scan template.

16. The method of any one of claims 1-15, wherein all filtered pixels are added to an accumulation buffer according to the predefined scan template, and wherein the accumulation buffer is initialized by zero before the obtaining filtered spectrum components.

17. The method of claim 16, wherein final filtered pixels are obtained as accumulated values in the accumulation buffer divided by number of pixels adding to a current position of the accumulation buffer; and

wherein the generating the filtered reconstructed block based on the filtered pixels comprises: generating the filtered reconstructed block based on the final filtered pixels.

18. The method of any one of claims 1-17, wherein differences between all filtered and corresponding unfiltered pixels are added to an accumulation buffer according to the predefined scan template, and wherein the accumulation buffer is initialized by unfiltered pixels multiplied by maximum number of pixel values to be added in the block.

19. The method of claim 18, wherein final filtered pixels are obtained as accumulated values in the accumulation buffer divided by maximum number of pixel values to be added in the block.

20. The method of any one of claims 1-19, wherein the method is applied depending on conditions, wherein the conditions comprises at least one of:

the block has non-zero residual signal;
a size of the block;
an aspect ratio of the block;
a prediction mode of the block;
a prediction mode of the block in intra; or
a prediction mode of the block in inter.

21. The method of claim 20, wherein the filter parameter and/or the predefined scan template are depending on the conditions.

22. The method of claim 20, where the method is applied if size of the block obtained as block width multiplied by block height is greater than 4x4.

23. The method of claim 20, where the method is not applied if the prediction mode of the block is inter and the block width and the block height is greater or equal to 32.

24. The method of claim 20, where the method is applied if the prediction mode of the block is inter and the block has non-zero residual signal.

25. The method of claim 20, where the method is applied if the prediction mode of the block is intra.

26. The method of any one of claims 1-25, scanning the current pixel of the reconstructed block and its neighboring pixels of the current pixel according to the predefined scan template to an accumulation buffer;and
obtaining spectrum components by performing transform for pixels in the accumulation buffer.

27. The method of any one of claims 1-26, wherein the transform is a Hadamard transform.
28. The method of any one of claims 1-27, wherein the transform is a 1D transform.

29. A method for processing a predicted block, wherein the predicted block comprises a plurality of pixels, wherein the method comprises:

scanning a current pixel of the predicted block and its neighboring pixels of the current pixel according to a predefined scan template;

obtaining spectrum components by performing transform for the current pixel and its neighboring pixels;

obtaining filtered spectrum components based on a filtering parameter and the spectrum components;

obtaining filtered pixels by performing inverse transform for the filtered spectrum components; and

generating a filtered predicted block based on the filtered pixels.

30. The method of claim 29, wherein the obtaining the filtered spectrum components by using a look up table (LUT).

31. The method of claim 30, a filtered spectrum component $F(i,\sigma)$ is derived by:

$$F(i,\sigma) = \begin{cases} R(i) \ , \ Abs(R(i)) \geq THR \\ LUT(R(i),\sigma), \ R(i) > 0 \\ -LUT(-R(i),\sigma), \ R(i) \leq 0 \end{cases}$$

wherein (i) is an index of a spectrum component, R(i) is the spectrum component corresponding to (i) index, σ is the filtering parameter, $LUT(R(i),\sigma)$ is an array in the look up table, and THR is a threshold.

32. The method of claim 31, wherein $LUT(R(i),\sigma) = \frac{R(i)^3}{R(i)^2+\mathrm{m}*\sigma^2}$, m is normalization constant equal to number of spectrum components.

33. The method of any one of claims 30-32, wherein the filtering parameter is derived based on a codec quantization parameter (QP).

34. The method of claim 33, wherein the filtering parameter σ is derived by

$$\boldsymbol{\sigma} = k * \mathbf{2}^{(n*(QP-s))}$$

, wherein QP is the codec quantization parameter, k, n and s are constants.

35. The method of claim 33, wherein the filtering parameter σ is equal to zero if QP <= 17, and the predicted block is bypassed without filtering.

36. The method of any one of claims 31-35, THR is dependent of QP value.

37. The method of claim 36, THR is derived by:

$$\frac{THR^2}{THR^2+m*\sigma^2}=\mathrm{C}$$

Wherein C is a value close to 1.

38. The method of any one of claims 29-37, wherein the predefined scan template is defined as set of spatial or raster offsets relative to a position of the current pixel inside the predicted block.

39. The method of claim 38, wherein the predefined scan template is defined as follows: scanTmpl[4] (y, x) ={ (0,0), (0,1), (1,0), (1,1) }

40. The method of any one of claims 29-39, wherein at least one filtered pixel is placed to its original position according to the predefined scan template.

41. The method of any one of claims 29-40, wherein all filtered pixels are added to an accumulation buffer according to the predefined scan template, and wherein the accumulation buffer is initialized by zero before the obtaining filtered spectrum components.

42. The method of claim 41, wherein final filtered pixels are obtained as accumulated values in the accumulation buffer divided by number of pixels adding to a current position of the accumulation buffer; and

wherein the generating the filtered predicted block based on the filtered pixels comprises: generating the filtered predicted block based on the final filtered pixels.

43. The method of any one of claims 29-42, wherein the method is applied depending on conditions, wherein the conditions comprises at least one of:

the block has non-zero residual signal;
a size of the block;
an aspect ratio of the block;
a prediction mode of the block;
a prediction mode of the block in intra; or
a prediction mode of the block in inter.

44. The method of claim 43, wherein the filter parameter and/or the predefined scan template are depending on the conditions.

45. The method of claim 43, where the method is applied if size of the block obtained as block width multiplied by block height is greater than 4x4, or if the prediction mode of the block is intra, or if the prediction mode of the block is inter and the block has non-zero residual signal.

46. The method of any one of claims 29-45, wherein the transform is a Hadamard

transform.

47. A decoder comprising processing circuitry for carrying out the method according to any one of claims 1-46.

48. An encoder comprising processing circuitry for carrying out the method according to any one of claims 1-46.

49. A decoder comprising a filter for carrying out the method according to any one of claims 1-46.

50. An encoder comprising a filter for carrying out the method according to any one of claims 1-46.

51. A decoder, comprising:

a memory storage comprising instructions; and

one or more processors in communication with the memory, wherein the one or more processors execute the instructions to carry out the method according to any one of claims 1-46.

52. An encoder, comprising:

a memory storage comprising instructions; and

one or more processors in communication with the memory, wherein the one or more processors execute the instructions to carry out the method according to any one of claims 1-46.

53. A computer program product comprising program code for performing the method of claims 1-46 when executed on a computer or a processor.

CLAIMS

1. A method for processing a block for an image or a video, wherein the block comprises a plurality of pixels, wherein the method comprises:

scanning, according to a predefined scan template, to obtain a current pixel of the block and its neighboring pixels of the current pixel, wherein the block is a reconstructed block or a predicted block;

obtaining spectrum components by performing a transform for the current pixel and the neighboring pixels of the current pixel;

obtaining filtered spectrum components based on a filtering parameter and the spectrum components when an absolute value of at least one of the spectrum components is less than a threshold;

obtaining filtered pixels by performing inverse transform for the filtered spectrum components; and

generating a filtered block based on the filtered pixels.

2. The method of claim 1, wherein the obtaining the filtered spectrum components is performed by using a look up table (LUT).

3. The method of claim 2, wherein a filtered spectrum component $F(i,\sigma)$ is derived by:

$$F(i,\sigma)=\begin{cases} R(i) \ , \ Abs\big(R(i)\big)\geq THR \\ LUT(R(i),\sigma),\ R(i)>0 \\ -LUT(-R(i),\sigma),\ R(i)\leq 0 \end{cases}$$

wherein i is an index of a spectrum component, R(i) is the spectrum component corresponding to index i, σ is the filtering parameter, LUT is an array representing the look up table, and THR is thethreshold.

4. The method of claim 3, wherein $LUT(R(i),\sigma)=\frac{R(i)^3}{R(i)^2+\mathrm{m}*\sigma^2}$, and *m* is a normalization constant equal to a number of spectrum components.

5. The method of any one of claims 2-4, wherein the filtering parameter is derived based on a codec quantization parameter (QP).

6. The method of claim 5, wherein the filtering parameter σ is derived by

$$\sigma = k * 2^{(n*(QP-s))}$$

, wherein QP is the codec quantization parameter, and k, n and s are constants.

7. The method of claim 6, wherein $k = 2.64, n = 0.1296$ and $s = 11$.

8. The method of claim 6 or 7, wherein k is modified based on bit depth of pixels $k_{mod} = k$*(1 << (bit_depth - 8)) and k_{mod} is used to replace k to derive the filtering parameter σ.

9. The method of claim 5, wherein the filtering parameter σ is equal to zero if QP <= 17, and the block is bypassed without filtering.

10. The method of claim 3, wherein the THR is dependent of QP value.

11. The method of claim 10, wherein the THR is derived by:

$$\frac{THR^2}{THR^2+m*\sigma^2}=C$$

wherein C is a constant value close to 1, and C is 0.8 or 0.9.

12. The method of any one of claims 1-11, wherein the predefined scan template is defined as a set of spatial or raster offsets relative to a position of the current pixel inside the reconstructed block.

13. The method of claim 12, wherein the predefined scan template is defined as follows: scanTmpl[4] (y, x) ={ (0,0), (0,1), (1,0), (1,1) }

14. The method of claim 12, wherein when the predefined scan template is defined as a set of raster offsets relative to the position of the current pixel inside the reconstructed block, the set of raster offsets point to neighbour pixels that are inside the reconstructed block.

15. The method of any one of claims 1-14, wherein at least one filtered pixel is placed to an original position of the at least one filtered pixel before filtering according to the predefined scan template.

16. The method of any one of claims 1-15, wherein the filtered pixels are added to an accumulation buffer according to the predefined scan template, and wherein the accumulation buffer is initialized by zero before the obtaining filtered spectrum components.

17. The method of claim 16, wherein final filtered pixels are obtained as accumulated values in the accumulation buffer divided by respective numbers of pixels added to respective positions of the accumulation buffer; and

wherein the generating the filtered block based on the filtered pixels comprises: generating the filtered block based on the final filtered pixels.

18. The method of any one of claims 1-17, wherein differences between the filtered pixels and corresponding unfiltered pixels are added to an accumulation buffer according to the predefined scan template, and wherein the accumulation buffer is initialized by unfiltered pixels multiplied by the maximum number of pixel values to be added in the block.

19. The method of claim 18, wherein final filtered pixels are obtained as accumulated values in the accumulation buffer divided by the maximum number of pixel values to be added in the block; and

wherein the generating the filtered block based on the filtered pixels comprises: generating the filtered block based on the final filtered pixels.

20. The method of any one of claims 1-19, wherein the method is applied when conditions are satisfied, wherein the conditions depend on at least one of:

the block has a non-zero residual signal;
a size of the block;
an aspect ratio of the block;
a prediction mode of the block;
a prediction mode of the block in intra; or
a prediction mode of the block in inter.

21. The method of claim 20, wherein the filter parameter and/or the predefined scan template are depending on the conditions.

22. The method of claim 20, wherein the method is applied if size of the block obtained as block width multiplied by block height is greater than 4x4.

23. The method of claim 20, wherein the method is not applied if the prediction mode of the block is inter and the block width and the block height is greater or equal to 32.

24. The method of claim 20, wherein the method is applied if the prediction mode of the block is inter and the block has non-zero residual signal.

25. The method of claim 20, wherein the method is applied if the prediction mode of the block is intra.

26. The method of any one of claims 1-25, wherein the method comprises: scanning the current pixel of the reconstructed block and its neighboring pixels of the current pixel according to the predefined scan template to an accumulation buffer; and

obtaining spectrum components by performing a transform for pixels in the accumulation buffer.

27. The method of any one of claims 1-26, wherein the transform is a Hadamard transform.

28. The method of any one of claims 1-27, wherein the transform is a 1D transform.

29. An apparatus comprising processing circuitry when used in carrying out the method according to any one of claims 1-28, wherein the apparatus is an encoder or a decoder.

30. An apparatus comprising a filter when used in carrying out the method according to any one of claims 1-28, wherein the apparatus is an encoder or a decoder.

31. An apparatus, comprising:

a memory storage comprising instructions; and

one or more processors in communication with the memory, wherein the one or more processors execute the instructions to carry out the method according to any one of claims 1-28, wherein the apparatus is an encoder or a decoder.

32. A computer program product comprising program code for performing the method of claims 1-28 when executed on a computer or a processor.