

NEAR FIELD COMMUNICATION IMPLEMENTATION METHOD AND SYSTEM

TECHNICAL FIELD

[0001] The present disclosure relates to a field of modulating and demodulating sound waves, and more particularly to a method and a system for implementing near field communication technology.

BACKGROUND

[0002] A near field communication (NFC), which is also called as a short-range wireless communication, is a short-range high frequency wireless communication technology and allows electronic devices to implement contactless point-to-point data transmission between them for exchanging data within a short distance such as 10 centimeters. An NFC chip is mainly applied to a mobile communication device, so the mobile communication device can implement electronic micropayments and read information of other NFC devices or tags. Short-range interactions with the NFC greatly simplify the overall authentication and identification processes. Through the NFC, wireless connections can be conveniently and quickly established between plural devices such as computers, digital cameras, mobile phones, PDAs and so on.

[0003] The conventional NFC technology becomes an industry standard and has incomparable advantages on security and communication efficiency. However, it can be seen that methods of the standard NFC depend on specific hardware such as NFC chips. However, most mobile communication devices currently do not have the NFC chips equipped. Therefore, hardware requirements by utilizing schemes of the NFC standard are relatively hard to meet, and current application ranges are limited narrow.

SUMMARY OF THE DISCLOSURE

[0004] The present disclosure provides a method and a system for implementing near field communication (NFC) which is capable of implementing NFC between mobile communication devices not having NFC chips equipped, thereby solving the problems that hardware requirements by utilizing schemes of the NFC standard are higher, and current application ranges are narrow.

[0005] Some technical schemes may be implemented as follows.

[0006] An embodiment method for implementing near field communication comprises:

[0007] modulating a digital signal to generate an audio signal and playing the modulated audio signal by a transmitting device; and

[0008] sampling the audio signal and demodulating the sampled audio signal for obtaining the digital signals by a receiving device.

[0009] An embodiment system for implementing near field communication comprises:

[0010] a transmitting device for modulating a digital signal to generate an audio signal and playing the modulated audio signal; and

[0011] a receiving device for sampling the audio signal and demodulating the sampled audio signal for obtaining the digital signal.

[0012] Apparently, the embodiments of the method and the system for implementing the NFC of the present disclosure adopt speakers and microphones disposed in the general mobile communication devices and technologies of modulating and demodulating sound waves for implementing the NFC between the mobile communication devices, thereby solving the problems in the existing art that hardware requirements by utilizing schemes of the NFC standard are higher and the

current application ranges are narrow.

BRIEF DESCRIPTION OF THE DRAWINGS

[0013] To clarify embodiments of the present disclosure or technical schemes in the prior arts, appended drawings required in the descriptions of the embodiments and the prior arts are briefly described as follows. Apparently, the following drawings merely illustrate some embodiments of the present disclosure. For those skilled in the art, other drawings may be acquired according to the drawings without devoting effort.

[0014] FIG. 1 is a schematic diagram illustrating constitute of a system for implementing the near field communication (NFC) in accordance with the present disclosure.

DETAILED DESCRIPTION OF THE DISCLOSURE

[0015] The technical scheme provided in embodiments of the present disclosure will be clearly and completely described below with reference to accompanying drawings, it should be appreciated that the embodiments described herein are merely part of, but not all of, the possible embodiments of the present disclosure, and that other embodiments devised by those of ordinary skill in the art based on the embodiments herein without making creative efforts are within the protection scope of the present disclosure.

[0016] The present disclosure discloses a method for implementing near field communication (NFC), and the NFC is implemented by utilizing a speaker and a microphone disposed in a mobile communication device. FIG. 1 is a schematic diagram illustrating constitute of a system for implementing the NFC in accordance with the present disclosure. Amongst, a mobile communication device A is a

transmitting device, and a mobile communication device is a receiving device.

[0017] The system as shown in FIG. 1 implementing the NFC comprises:

[0018] the transmitting device modulates a digital signal and plays the modulated audio signal; and

[0019] the receiving device samples the audio signal and demodulates the sampled audio signal for obtaining the digital signal.

[0020] A specific embodiment is described in detailed as follows.

[0021] In the present embodiment, modulating the digital signal by the transmitting device comprises: implementing to modulate a sound wave by utilizing a binary frequency shift keying (2FSK) technique. A sampling frequency of the audio signal is 48 KHz. A channel number is a single channel. A quantization bit is 8 bits.

[0022] According to the sampling theorem: $f_0 \geq 2f$, that is, the sampling frequency f_0 must be greater than or equal to twice a maximum frequency of sampled wave. In the present embodiment, when the digital signal are modulated, a modulating frequency f_1 of a binary digital signal "0" is set as 12 KHz, while a modulating frequency f_2 of a binary digital signal "1" is set as 16 KHz.

[0023] Due to the above-mentioned settings, the audio signal may be represented as: $y = 128 + 127 \cdot \sin(2 \pi f x)$.

[0024] Amongst, y is an amplitude quantization value, and x is represented as time.

[0025] Because the sampling frequency is f_0 , $x = N/f_0$. The audio signal may be further represented as: $y = 128 + 127 \cdot \sin(2 \pi f N/f_0)$.

[0026] Amongst, f is a modulating frequency. N is a number of sampling points.

[0027] When the modulated signal is "0", $f = f_1 = 12$ KHz; when the modulated signal is "1", $f = f_2 = 16$ KHz.

[0028] Furthermore, a modulating width is required to be set. The sampling frequency is 48 KHz, that is, 48000 points per second can be sampled. If a

modulating width is set to have 1000 points, a modulating time $t = 1000/f_0 = 0.02s$. That is, an audio frequency in the time period is fixed to be a frequency corresponding to the modulated signal.

[0029] According to a transmitting rate = sampling frequency / modulating width, it can be obtained that 48-bit data can be transmitted per second. That is, the transmitting rate of the data is 48 bps.

[0030] According to the above-mentioned settings, the binary digital signal is modulated firstly. A 96-bit binary signal

"10100110101010011010101001101010100110101010011010101001101010100110101010011010101001101010100110101010011010000000" including 96 bits may be modulated as an audio signal of 2 seconds. After testing, the transmitting device plays the audio signal.

[0031] The receiving device samples the audio signal and utilizes a software algorithm for demodulating the sampled audio signal. Specifically, the sampled audio signal is analyzed by utilizing a Fast Fourier Transform (FFT). Every 64 points are used as an analyzing period, and spectral characteristics thereof are served as frequency characteristics in a middle period for analyzing a frequency signal having a maximum power in the spectrum. If a frequency of one point having the maximum power is closest to 12 KHz, then an output result is "0". If a frequency of one point having the maximum power is closest to 16 KHz, then an output result is "1". If the frequency is not closest to 12 KHz or 16 KHz, then it is an environmental audio sound and there is no output result. There is no output result, and it is represented as "". The frequency spectrum of one analyzing period is shown in the following table.

frequency	amplitude	frequency	amplitude
0 KHz	39	11.0250 KHz	510
0.68906 KHz	562	11.7141 KHz	828
1.37813 KHz	382	12.4031 KHz	651

0000__1111111111__00000000000000__111111111111__000000000000__111111
1111__01000000000000000000000000__1111111111111111111111__000000
00000__111111111111__00_000000000__111111111111__00000000000000__111111
11111__0000000000000000000000000000__1111111111111111111111__0000000
0000000__11111111111100000000000000__1_11111111__00000000000__11111
1111111__0000000000000000000000000000__1111111111111111111111__0000
000000000__111111111111__00000000000000__1111111111110000000000000000__
11111111111__1000000000000000000000000000__1111111111111111111111__10
000000000000__1_11111111__000000000000__1_11111111__00000000000000
__11111111111__0000000000000000000000000000__1_1111111111111111111111
_010000000000__111111111111__000000000000__11_11111111__100000000000
00__111111111111000000000000000000000000000000__11111111111111111111
1__000000000000__111111111111000000000000000000000000000000000000000
00____
_____”.

[0033] Since a modulating period includes 1000 sampling points and one analyzing period includes 64 points herein, 15.625 analyzing periods constitute a modulating period. 16 bits are set as a length of a window for performing a statistical analysis on the output result. If “1” in the window occurs more, then the obtained modulated digital signal is “1”. Otherwise, the obtained modulated digital signal is “0”. Then, the window is shifted by a displacement for analyzing the next one. A distance of the displacement is determined by the content of the current window. A count value FLAG is set and an initial value thereof is 0. When the window is traversed from left to right, FLAG is increased by 1 on the situation that “1” is met; FLAG is decreased by 1 on the situation that “0” is met; FLAG is unchanged in other situations. A position of a maximum absolute value of FLAG (the position of the maximum absolute value is

subject to a right side position if equal) is a position required to be shifted. If the current window is "1111111111__0_0", then the position of the maximum absolute value (11) of FLAG is 13. Accordingly, the window should be shifted to the right by 13 positions for continual analysis, so on and so forth. The rest can be done in the same manner to obtain a final modulated result as:

"10100110101010011010101001101010100110101010011010101001101010100110101010011010101001101010100110101010011010000000". The final demodulated result is the same as the originally modulated binary digital signal, thereby successfully implementing the demodulating process.

[0034] In the above-mentioned embodiment, the sampling frequency f_0 , the specific values of the modulating frequencies f_1 , f_2 , the modulating method, the modulating width and the width of the analyzing window are only exemplary rather than limiting the present disclosure. The technical schemes by simply modifying the specific values are within the protection scope of the present disclosure.

[0035] The present disclosure further discloses a system for implementing NFC, which comprises:

[0036] a transmitting device for modulating a digital signal and playing the modulated audio signal; and

[0037] a receiving device for sampling the audio signal and demodulating the sampled audio signal for obtaining the digital signal.

[0038] In the above-mentioned system, the transmitting device is specifically utilized for modulating the digital signal by utilizing a 2FSK modulation. A modulating frequency f_1 of a binary digital signal "0" is set as 12 KHz, while a modulating frequency f_2 of a binary digital signal "1" is set as 16 KHz. A modulating width includes 1000 sampling points.

[0039] The receiving device samples the audio signal in a sampling frequency of 48

KHz. A channel number is a single channel. A quantization bit is 8 bits.

[0040] A method for demodulating the sampled audio signal by the receiving device comprises the following steps.

[0041] The sampled audio signal is transformed from a time domain signal to a frequency domain signal.

[0042] 64 points are used as an analyzing period. The sampled audio signal in the frequency domain is analyzed. If a frequency of one point having the maximum power is closest to 12 KHz, then an output result is "0". If a frequency of one point having the maximum power is closest to 16 KHz, then an output result is "1".

[0043] 16 bits are set as a length of a window for performing a statistical analysis on the above-mentioned output result. If "1" in the output result of the window occurs more, then the modulated digital signal is "1". If "0" in the output result of the window occurs more, then the modulated digital signal is "0". The window is shifted for continuing to perform the above-mentioned statistical analysis on the above-mentioned output result until all of the digital signals are demodulated.

[0044] A distance to traverse the window is set by the following steps. An initial count value is set as 0. The output result in the window is traversed. The count value is increased by 1 when traversing to "1". The count value is decreased by 1 when traversing to "0". A position of a maximum absolute value of the count value is the distance to traverse the window.

[0045] In conclusion, the method and the system for implementing the NFC of the present disclosure adopts the speaker and the microphone in the mobile communication devices, utilizes the software algorithm for modulating the digital signal, and then plays the modulated audio signal through the speaker. The other mobile communication device samples the audio signal through the microphone and performs an algorithm analysis on the sampled data for implementing to demodulate.

The interactive method can implement little data between two mobile communication devices in the NFC and can be applied to offline payments and similar conditions.

[0046] It is noted that the above-mentioned embodiments of the methods are described as combinations of a series of actions for simplifying descriptions. However, those skilled in the art should appreciate that the present disclosure is not limited to sequences of the described actions because some steps may be performed in different sequences or at the same time in accordance with the present disclosure. Next, those skilled in the art should appreciate that the embodiments described in the specifications are preferred embodiments, and the related actions and modules are not necessary in the present disclosure.

[0047] In the above-mentioned embodiments, emphases on descriptions of each embodiment are different. Portions which are not described in detail in one embodiment can be referred to related descriptions of other embodiments.

[0048] It should be appreciated by those skilled in the art that all or part of the steps of the method described in the embodiments above may be executed by relevant hardware instructed by a program that may be stored in a computer-readable memory medium. When the program is performed, the steps of the method described in the embodiments are performed. The readable memory medium may include various media capable of storing codes of the program, such as a read-only memory (ROM), a random access memory (RAM), a magnetic disk, a compact disc and so on.

[0049] It should be noted that the embodiments described above are merely preferred ones of the present disclosure but are not limitations to the protection scope of the present disclosure, and any variations or substitutions easily devised by those skilled in the art without departing from the spirit of the present disclosure fall within the scope of the protection. Therefore, the protection scope of the present disclosure

shall be subject to that specified by the appended claims.

What is claimed is:

1. A method for implementing near field communication (NFC), characterized in that, the method comprises:

modulating a digital signal by utilizing a binary frequency shift keying (2FSK) modulation to generate an audio signal and playing the modulated audio signal by a transmitting device; and

sampling the audio signal and demodulating the sampled audio signal for obtaining the digital signal by a receiving device,

wherein a modulating frequency of a binary digital signal "0" is set as f_1 and a modulating frequency of a binary digital signal "1" is set as f_2 ,

wherein demodulating the sampled audio signal comprises:

transforming the sampled audio signal from a time domain signal to a frequency domain signal;

analyzing the sampled audio signal in the frequency domain by an analyzing period by comparing frequency of one point having a maximum power with f_1 and f_2 ; and

performing a statistical analysis on the result of the analysis of the sampled audio signal using a window to generate a modulated digital signal.

2. The method according to claim 1, characterized in that, f_1 is set as 12 KHz, f_2 is set as 16 KHz, and a modulating width is set to have 1000 sampling points.

3. The method according to claim 1, characterized in that, a sampling frequency for sampling the audio signal by the receiving device is 48 KHz, a channel number is a single channel, a quantization bit is 8 bits;

64 points are used as the analyzing period, and if a frequency of one point having a maximum power is closest to f_1 , then an output result is "0"; if a frequency of one point having a maximum power is closest to f_2 , then an output result is "1"; and

16 bits are set as a length of the window for performing a statistical analysis on the above-mentioned output result, if "1" in the output result of the window occurs more, then the modulated digital signal is "1"; if "0" in the output result of the window occurs more, then the modulated digital signal is "0"; the window is shifted for continuing to perform the above-mentioned statistical analysis on the above-mentioned output result until all of the digital signals are demodulated.

4. The method according to claim 3, characterized in that, the step of shifting the window comprises:

an initial count value is set as 0, the output result in the window is traversed, the count value is increased by 1 when traversing to "1 "; the count value is decreased by 1 when traversing to "0"; a position of a maximum absolute value of the count value is a distance to shift the window, and the window is shifted in accordance with the distance.

5. The method according to one of claims 1-4, characterized in that, the transmitting device comprises a speaker, and the receiving device comprises a microphone.

6. A system for implementing near field communication (NFC), characterized in that, the system comprises:

a transmitting device for modulating a digital signal by utilizing a binary frequency shift keying (2FSK) modulation to generate an audio signal and playing the modulated audio signal; and

a receiving device for sampling the audio signal and demodulating the sampled audio signal for obtaining the digital signal,

wherein a modulating frequency of a binary digital signal "0" is set as f_1 and a modulating frequency of a binary digital signal "1" is set as f_2 ,

wherein a method for demodulating the sampled audio signal by the receiving device comprises:

transforming the sampled audio signal from a time domain signal to a frequency domain signal;

analyzing the sampled audio signal in the frequency domain by an analyzing period by comparing frequency of one point having a maximum power with f_1 and f_2 : and

performing a statistical analysis on the result of the analysis of the sampled audio signal using a window to generate a modulated digital signal.

7. The system according to claim 6, characterized in that, f_1 is set as 12 KHz, f_2 is set as 16 KHz, and a modulating width includes 1000 sampling points.

8. The system according to claim 6, characterized in that, the receiving device samples the audio signals in a sampling frequency of 48 KHz, a channel number is a single channel, a quantization bit is 8 bits;

64 points are used as an analyzing period, if a frequency of one point having a maximum power is closest to f_1 , then an output result is "0"; if a frequency of a point having a maximum power is closest to f_2 , then an output result is "1"; and

16 bits are set as the length of a window for performing a statistical analysis on the above-mentioned output result, if "1" in the output result of the window occurs more, then the modulated digital signal is "1"; if "0" in the output result of the window occurs more, then the modulated digital signal is "0"; the window is shifted for continuing to perform the above-mentioned statistical

analysis on the above-mentioned output result until all of the digital signals are demodulated.

9. The system according to claim 8, characterized in that, the receiving device is utilized for setting a count value having an initial value of 0, the output result in the window is traversed, the count value is increased by 1 when traversing to "1 "; the count value is decreased by 1 when traversing to "0"; a position of a maximum absolute value of the count value is a distance to shift the window, and the window is shifted in accordance with the distance.

10. The system according to one of claims 6-9, characterized in that, the transmitting device comprises a speaker, and the receiving device comprises a microphone.