

DESCRIPTION

SEQUENCE ALLOCATING METHOD, TRANSMITTING METHOD AND WIRELESS MOBILE STATION DEVICE

5 Technical Field

[0001] The present invention relates to a sequence allocating method, transmitting method and radio mobile station apparatus that are used in a cellular radio communication system.

10 Background Art

[0002] In 3GPP LTE (3rd Generation Partnership Project Long Term Evolution), a Zadoff-Chu sequence ("ZC sequence") is adopted as a reference signal ("RS") that is used in uplink. The reason for adopting a ZC sequence as an RS is that a ZC sequence has a uniform frequency characteristic and has good auto-correlation and cross-correlation characteristics. A ZC sequence is a kind of CAZAC (Constant Amplitude and Zero Auto-correlation Code) sequence and represented by following equation 1 or equation 2.

[1]

$$a_r(k) = \begin{cases} e^{-j\frac{2\pi r}{N}(k^2/2+qk)} & , N: \text{even} \\ e^{-j\frac{2\pi r}{N}(k(k+1)/2+qk)} & , N: \text{odd} \end{cases} \dots (\text{Equation 1})$$

$$a_r(k) = \begin{cases} e^{j\frac{2\pi r}{N}(k^2/2+qk)} & , N: \text{even} \\ e^{j\frac{2\pi r}{N}(k(k+1)/2+qk)} & , N: \text{odd} \end{cases} \dots (\text{Equation 2})$$

[0003] In equation 1 and equation 2, "N" is the sequence length, "r" is the ZC sequence number, and "N" and "r" are coprime. Also, "q" is an arbitrary integer. It is possible to generate N-1 quasi-orthogonal sequences of good cross-correlation characteristics from a ZC sequence having the sequence length N of a prime number. In this case, the cross-correlation is constant at $\sqrt{N}$ between the N-1 quasi-orthogonal sequences generated.

[0004] Here, in the RS's that are used in uplink, the reference signal for channel estimation used to demodulate data (i.e. DM-RS (Demodulation Reference Signal)) is transmitted in the same band as the data

transmission bandwidth. That is, when the data transmission bandwidth is narrow, a DM-RS is also transmitted in a narrow band. For example, if the data transmission bandwidth is one RB (Resource Block), the DM-RS transmission bandwidth is also one RB. Likewise, if the data transmission bandwidth is two RB's, the DM-RS transmission bandwidth is also two RB's. Also, in 3GPP LTE, one RB is comprised of twelve subcarriers. Consequently, a ZC sequence having a sequence length N of 11 or 13 is used as a DM-RS that is transmitted in one RB, and a ZC sequence having a sequence length N of 23 or 29 is used as a DM-RS that is transmitted in two RB's. Here, when a ZC sequence having a sequence length N of 11 or 23 is used, a DM-RS of 12 subcarriers or 24 subcarriers is generated by cyclically expanding the sequence, that is, by copying the head data of the sequence to the tail end of the sequence. On the other hand, when a ZC sequence having a sequence length N of 13 or 29 is used, a DM-RS of 12 subcarriers or 24 subcarriers is generated by performing truncation, that is, by deleting part of the sequence.

[0005] As a method of allocating ZC sequences, to reduce the interference between DM-RS's that are used between different cells, that is, to reduce the inter-cell interference of DM-RS, in each RB, ZC sequences of different sequence numbers are allocated to adjacent cells as DM-RS's. The data transmission bandwidth is determined by the scheduling in each cell, and therefore DM-RS's of different transmission bandwidths are multiplexed between cells. However, if ZC sequences of different transmission bandwidths, that is, ZC sequences of different sequence lengths, are multiplexed, a specific combination of ZC sequence numbers has a high cross-correlation.

[0006] FIG.1 is a diagram illustrating cross-correlation characteristics between ZC sequences in combinations of different sequence numbers, which are acquired by computer simulation,. To be more specific, FIG.1 illustrates the cross-correlation characteristics between a ZC sequence of a sequence length $N=11$ and sequence number $r=3$, and ZC sequences of a sequence length $N=23$ and sequence numbers $r=1$ to 6. In FIG.1, the horizontal axis represents the delay time using the number of symbols, and the vertical axis represents the normalized cross-correlation values, that is, the values dividing the cross-correlation values by N . As shown in FIG.1, the maximum cross-correlation value is very high with the combination of a ZC sequence of $r=3$ and $N=11$ and a ZC sequence of $r=6$

and $N=23$, and is about three times higher than the cross-correlation value in the single transmission bandwidth, $1/\sqrt{N}$, that is, $1/\sqrt{11}$.

[0007] FIG.2 is a diagram illustrating the inter-cell interference of DM-RS in a case where specific combinations of ZC sequences that increase cross-correlation are allocated to adjacent cells. To be more specific, a ZC sequence of $r=a$ and $N=11$ and a ZC sequence of $r=b$ and $N=23$ are allocated to cell #A, and a ZC sequence of $r=c$ and $N=23$ and a ZC sequence of $r=d$ and $N=11$ are allocated to cell #B. In this case, the combination of the ZC sequence of $r=a$ and $N=11$ allocated to cell #A and the ZC sequence of $r=c$ and $N=23$ allocated to cell #B, or the combination of the ZC sequence of $r=b$ and $N=23$ allocated to cell #A and the ZC sequence of $r=d$ and $N=11$ allocated to cell #B, increases the inter-cell interference of DM-RS, and, consequently, degrades the accuracy of channel estimation and degrades the data demodulation performance significantly.

[0008] To avoid such problems, the ZC sequence allocating method disclosed in Non-Patent Document 1 is used in a cellular radio communication system. To reduce inter-cell interference, Non-Patent Document 1 suggests allocating a combination of ZC sequences of high cross-correlation and different sequence lengths, to a single cell.

[0009] FIG.3 is a diagram illustrating the ZC sequence allocating methods disclosed in Non-Patent Document 1 and Non-Patent Document 2. In FIG.3, the example shown in FIG.2 is used. As shown in FIG.3, a combination of ZC sequences of high cross-correlation, that is, a combination of a ZC sequence of $r=a$ and $N=11$ and a ZC sequence of $r=c$ and $N=23$, is allocated to a single cell (cell #A in this case). Also, another combination of ZC sequences of high cross-correlation, that is, a combination of a ZC sequence of $r=d$ and $N=11$ and a ZC sequence of $r=b$ and $N=23$, is allocated to a single cell (cell #B in this case). In the single cell, transmission bands are scheduled by one radio base station apparatus, and, consequently, ZC sequences of high correlation allocated to the same cell, are not multiplexed. Therefore, inter-cell interference is reduced.

[0010] Also, Non-Patent Document 2 proposes a method of finding a combination of ZC sequence numbers, which are used in RB's (hereinafter referred to as a "sequence group"). ZC sequences have a feature of having higher cross-correlation when the difference of r/N , that is, the

difference of sequence number / sequence length is smaller. Therefore, based on a sequence of an arbitrary RB (e.g. one RB), ZC sequences that make the difference of r/N equal to or less than a predetermined threshold, are found from the ZC sequences of each RB, and the multiple
 5 ZC sequences found are allocated to a cell as one sequence group.

[0011] FIG.4 is a diagram illustrating a sequence group generation method disclosed in Non-Patent Document 2. In FIG.4, the horizontal axis represents r/N , and the vertical axis represents the ZC sequence of each RB. First, the reference sequence length N_b and reference sequence number rb are set. Hereinafter, a ZC sequence having the reference sequence length N_b and reference sequence number rb is referred to as a "reference sequence." For example, if N_b is 13 (which is the sequence length associated with one RB) and rb is 1 (which is selected between 1 and N_b-1), rb/N_b is $1/13$. Next, ZC sequences that make the difference
 10 of r/N from the reference rb/N_b equal to or less than a predetermined threshold, are found from the ZC sequences of each RB to generate a sequence group. Also, the reference sequence number is changed, and, in the same process as above, other sequence groups are generated. Thus, it is possible to generate different sequence groups for the number of
 20 reference sequence numbers, that is, it is possible to generate N_b-1 different sequence groups. Here, if ranges for selecting ZC sequences, in which a difference from rb/N_b is equal to or less than a predetermined threshold, overlap between adjacent sequence groups, the same ZC sequences are included in the plurality of sequence groups, and therefore
 25 the sequence numbers overlap between cells. Therefore, to prevent ranges for selecting ZC sequences in adjacent sequence groups from overlapping, the above predetermined threshold is set to, for example, a value less than $1/(2N_b)$.

[0012] FIG.5A and FIG.5B illustrate examples of sequence groups generated by the sequence group generation method disclosed in Non-Patent Document 2. Here, the sequence length N is set to the prime number that is larger than the maximum possible size of transmission in the transmission bandwidth and that is the closest to this size, and, furthermore, the sequence length N is uniquely determined from the
 30 number of RB's. FIG.5A and FIG.5B illustrate sequence groups (ZC sequence group 1 and ZC sequence group 2) comprised of ZC sequences that satisfy following equation 3 in a case where the reference sequence

length N_b is 13 and the reference sequence number r_b is 1 or 2. In equation 3, the threshold X_{th} is, for example, $1/(2N_b)$, (i.e. $1/26$) to prevent the same sequence from being included in a plurality of sequence groups.

$$|r_b/N_b - r/N| \leq X_{th} \quad \dots (\text{Equation 3})$$

[0013] Thus, according to the sequence allocating methods disclosed in Non-Patent Document 1 and Non-Patent Document 2, a sequence group comprised of ZC sequences that make a difference of r/N equal to or less than a predetermined threshold, that is, a sequence group comprised of ZC sequences having greater cross-correlation than a predetermined threshold, is generated, and the generated sequence group is allocated to the single cell. By this means, it is possible to allocate a combination of ZC sequences of large cross-correlation and different sequence lengths to the single cell, and reduce inter-cell interference.

Non-Patent Document 1: Huawei, R1-070367, "Sequence Allocating method for E-UTRA Uplink Reference Signal", 3GPP TSG RAN WG1Meeting #47bis, Sorrento, Italy 15 -19 January, 2007
 Non-Patent Document 2: LG Electronics, R1-071542, "Binding method for UL RS sequence with different lengths", 3GPP TSG RAN WG1Meeting #48bis, St. Julians, Malta, March 26 – 30, 2007

Disclosure of Invention

Problems to be Solved by the Invention

[0014] However, with the sequence allocating method disclosed in Non-Patent Document 2, the threshold X_{th} related to a difference of r/N is a fixed value regardless of the number of RB's, and, consequently, the following problem arises.

[0015] FIG.6 is a diagram illustrating a problem that arises when the threshold X_{th} is set higher. As shown in FIG.6, if the threshold X_{th} is set higher, ZC sequences located near the boundary of adjacent sequence groups have a smaller difference of r/N , and therefore cross-correlation increases. That is, the cross-correlation between sequence groups increases.

[0016] FIG.7A and FIG.7B illustrate problems that arise when the threshold X_{th} is set higher, using specific examples of sequence groups. In FIG.7A and FIG.7B, the sequence group examples shown in FIG.5A and

FIG.5B are used. In the ZC sequences included in the two sequence groups (i.e. ZC sequence group 1 and ZC sequence group 2) shown in FIG.7A and FIG.7B, the hatched ZC sequences have a smaller difference of r/N from and larger cross-correlation with ZC sequences of other sequence groups. Here, as shown in FIG.4, the number of ZC sequences in each RB is $N-1$ at $1/N$ intervals in the range of $r/N=0$ to 1. Therefore, as shown in FIG.7A and FIG.7B, when the number of RB's is larger, the number of ZC sequences increases that make a difference of r/N from a reference ZC sequence smaller than a threshold. Also, when the number of RB's is larger, that is, when the sequence length N is longer, the number of hatched ZC sequences increases.

[0017] By contrast, when the threshold X_{th} is set smaller, the number of ZC sequences forming a sequence group decreases. Especially, when the number of RB's is smaller, that is, when the sequence length N is shorter, the number of sequences that are present in the range of $r/N=0$ to 1 at $1/N$ intervals, $N-1$, decreases, and, consequently, when the threshold is further smaller, the number of ZC sequences forming a sequence group further decreases. Also, to randomize the influence of interference, if sequence hopping to switch sequence numbers at predetermined time intervals is adapted and there are few candidates of sequence numbers to be switched, the randomization of interference provides no effect.

[0018] It is therefore an object of the present invention to provide a sequence allocating method that can reduce cross-correlation between different sequence groups while maintaining the number of ZC sequences forming a sequence group that are allocated, in a cellular radio communication system.

Means for Solving the Problem

[0019] The sequence allocating method of the present invention for Zadoff-Chu sequences represented by equation 1 in a cellular radio communication system, includes: a reference setting step of setting a reference sequence length N_b and a reference sequence number r_b ; a first threshold setting step of setting a first threshold based on the sequence length N ; a selecting step of selecting a plurality of Zadoff-Chu sequences, in which a first difference representing a difference between r_b/N_b and r/N is equal to or less than the first threshold, from the Zadoff-Chu sequences generated according to the equation 1; and an allocating

step of allocating the plurality of Zadoff-Chu sequences selected, to a same cell.

[0020] The radio mobile station of the present invention that transmits Zadoff-Chu sequences represented by equation 1 as a reference signal,
 5 employs a configuration having: a setting section that sets a threshold based on a sequence length N signaled from a radio base station apparatus; a selecting section that selects a Zadoff-Chu sequence, in which a difference between r_b/N_b and r/N is equal to or less than the threshold, from the Zadoff-Chu sequences generated according to equation
 10 1, using a reference sequence number r_b and a reference sequence length N_b signaled from the radio base station apparatus; and a transmitting section that transmits the selected Zadoff-Chu sequence as the reference signal.

[0021] The transmitting method of the present invention whereby a radio
 15 mobile station apparatus transmits Zadoff-Chu sequences represented by equation 1 as a reference signal, in which the radio mobile station apparatus receives a sequence length N and a reference sequence number r_b signaled from the radio base station apparatus; selects a Zadoff-Chu sequence, which satisfies a condition that a difference between r_b/N_b
 20 (where N_b is a reference sequence length) and r/N is equal to or less than a threshold associated with the sequence length N , using the received sequence length N and the received reference sequence number r_b ; and transmits the selected Zadoff-Chu sequence as the reference signal.

25 Advantageous Effect of Invention

[0022] According to the present invention, it is possible to reduce cross-correlation between different groups while maintaining the number of ZC sequences forming sequence groups.

30 Brief Description of Drawings

[0023]

FIG.1 is a diagram illustrating cross-correlation characteristics between ZC sequences in combinations of different sequence numbers, which are acquired by computer simulation, according to the prior art;

35 FIG.2 is a diagram illustrating inter-cell interference between DM-RS's in a case where specific combinations of ZC sequences that increase cross-correlation are allocated to adjacent cells, according to the

prior art;

FIG.3 is a diagram illustrating a method of allocating ZC sequences according to the prior art;

5 FIG.4 is a diagram illustrating a method of generating sequence groups according to the prior art;

FIG.5A is a diagram illustrating an example of a sequence group generated by a sequence group generation method according to the prior art (ZC sequence group 1);

10 FIG.5B is a diagram illustrating an example of a sequence group generated by a sequence group generation method according to the prior art (ZC sequence group 2);

FIG.6 is a diagram illustrating a problem with the prior art that arises when the threshold Xth is set higher;

15 FIG.7A is a diagram illustrating a problem with the prior art that arises when the threshold Xth is set higher, using a detailed example of a sequence group (ZC sequence group 1);

FIG.7B is a diagram illustrating a problem with the prior art that arises when the threshold Xth is set higher, using a detailed example of a sequence group (ZC sequence group 2);

20 FIG.8 is a flowchart showing the process of a sequence allocating method in a cellular radio communication system, according to Embodiment 1 of the present invention;

25 FIG.9 is a diagram illustrating a method of setting a threshold in a sequence allocating method according to Embodiment 1 of the present invention;

FIG.10A is a diagram illustrating an example of a sequence group acquired by a sequence allocating method according to Embodiment 1 of the present invention (ZC sequence group 1);

30 FIG.10B is a diagram illustrating an example of a sequence group acquired by a sequence allocating method according to Embodiment 1 of the present invention (ZC sequence group 2);

FIG.11 is a diagram illustrating a method of setting a threshold according to a sequence allocating method according to Embodiment 1 of the present invention;

35 FIG.12A is a diagram illustrating an example of a sequence group acquired by a sequence allocating method according to Embodiment 1 of the present invention (ZC sequence group 1);

FIG.12B is a diagram illustrating an example of a sequence group acquired by a sequence allocating method according to Embodiment 1 of the present invention (ZC sequence group 2);

5 FIG.13 is a block diagram showing the configuration of a radio base station apparatus to which a sequence group is allocated, according to Embodiment 1 of the present invention;

FIG.14 is a block diagram showing the configuration inside a ZC sequence setting section according to Embodiment 1 of the present invention;

10 FIG.15 is a block diagram showing the configuration of a radio mobile station apparatus according to Embodiment 1 of the present invention;

FIG.16 is a diagram illustrating the cross-correlation characteristic ascertained by computer simulation according to
15 Embodiment 2 of the present invention;

FIG.17 is a flowchart showing the process of a sequence allocating method in a cellular radio communication system according to Embodiment 2 of the present invention;

FIG.18 is a diagram illustrating a method of generating sequence
20 groups based on the process of a sequence allocating method according to Embodiment 2 of the present invention;

FIG.19A is a diagram illustrating an example of a sequence group acquired by a sequence allocating method according to Embodiment 2 of the present invention (ZC sequence group 1);

25 FIG.19B is a diagram illustrating an example of a sequence group acquired by a sequence allocating method according to Embodiment 2 of the present invention (ZC sequence group 8);

FIG.20A is a diagram illustrating an example of a sequence group acquired when the number of RB's allowing sequences to be deleted, is
30 set 10 or greater (ZC sequence group 1); and

FIG.20B is a diagram illustrating an example of a sequence group acquired when the number of RB's allowing sequences to be deleted, is set 10 or greater (ZC sequence group 8).

35 Best Mode for Carrying Out Invention

[0024] Embodiments of the present invention will be explained below in detail with reference to the accompanying drawings. Here, in these

embodiments, components providing the same functions will be assigned the same reference numerals and overlapping explanations will be omitted.

[0025] (Embodiment 1)

5 FIG.8 is a flowchart showing the process of a sequence allocating method in a cellular radio communication system according to Embodiment 1 of the present invention.

[0026] First, in step (hereinafter "ST") 101, the reference sequence length Nb and the reference sequence number rb are set for a generated
10 sequence group. Here, the sequence number rb corresponds to the sequence group number and is lower than Nb.

[0027] In ST 102, the number of RB's, m, is initialized to 1.

[0028] In ST 103, the threshold Xth(m) associated with the number of RB's m is set. Here, the method of setting the threshold Xth(m) will be
15 described later.

[0029] In ST 104, the ZC sequence length N associated with the number of RB's m is set. The number of RB's "m" and the sequence length N are uniquely associated. For example, N is a prime number that is larger than the maximum possible size of transmission with the number of RB's,
20 m, and that is the closest to this size.

[0030] In ST 105, the sequence number r is initialized to 1.

[0031] In ST 106, whether or not r and N satisfy following equation 4 is decided.

$$|r/N - rb/Nb| \leq Xth(m) \dots (\text{Equation 4})$$

25 [0032] Following equation 5 is acquired from equation 4. Given that equation 4 and equation 5 are equivalent, in ST 106, whether or not r and N satisfy equation 5 may be decided.

$$(rb/Nb - Xth(m)) \times N \leq r \leq (rb/Nb + Xth(m)) \times N \dots (\text{Equation 5})$$

[0033] In ST 106, if r and N are decided to satisfy equation 4 ("YES" in
30 ST 106), the process of ST 107 is performed.

[0034] In ST 107, a ZC sequence having a sequence number of r is determined as one of ZC sequences associated with the number of RB's m in the sequence group rb.

[0035] In ST 106, when r and N are decided not to satisfy equation 4
35 ("NO" in ST 106), the process of ST 108 is performed.

[0036] In ST 108, whether or not $r < N$ is decided.

[0037] In ST 108, if $r < N$ is decided ("YES" in ST 108), the process of

ST 109 is performed.

[0038] In ST 109, the sequence number r is incremented by 1 like $r=r+1$, and the process moves to ST 106.

[0039] In ST 108, if $r < N$ is not decided ("NO" in ST 108), the process
5 of ST 110 is performed.

[0040] In ST 110, whether or not $m < M$ is decided. Here, M is the maximum value of the number of RB's in the sequence group rb and corresponds to the maximum value of the transmission bandwidth.

[0041] In ST 110, if $m < M$ is decided ("YES" in ST 110), the process of
10 ST 111 is performed.

[0042] In ST 111, the number of RB's m is incremented by one, like $m=m+1$, and the process moves to ST 103.

[0043] In ST 110, if $m < M$ is not decided ("NO" in ST 110), the process of ST 112 is performed.

15 [0044] In ST 112, the generated sequence group rb is allocated to a single cell, that is, a single radio base station apparatus.

[0045] Next, the method of setting the threshold $Xth(m)$ will be explained using two different cases. In above ST 103, it is possible to use either of following setting method 1 and setting method 2.

20 [0046] <threshold $Xth(m)$ setting method 1>

FIG.9 is a diagram illustrating threshold $Xth(m)$ setting method 1 in a sequence allocating method according to the present embodiment. As shown in FIG.9, the threshold $Xth(m)$ is set smaller when an RB is greater. For example, as shown in following equation 6, the $Xth(m)$ is
25 set to decrease by a predetermined value every time the number of RB's m increases.

$$Xth(m) = 1/(2Nb) - (m-1) \times 0.0012 \quad \dots (\text{Equation 6})$$

[0047] By setting the threshold $Xth(m)$ in this way, ZC sequences located near the boundary of adjacent sequence groups have a greater
30 difference of r/N , so that it is possible to suppress an increase of cross-correlation. Also, by increasing the threshold $Xth(m)$ associated with a smaller number of RB's, it is possible to increase the number of ZC sequences and maintain it above a predetermined number.

[0048] FIG.10A and FIG.10B illustrate examples of sequence groups
35 acquired by the sequence allocating methods shown in FIG.8 and FIG.9. To be more specific, the sequence groups shown in FIG.10A and FIG.10B are acquired according to the following conditions and process. For

example, to generate ZC sequence group 1 shown in FIG.10A, in ST 101, Nb=13 and rb=1 are set. Here, Nb=13 represents the sequence length associated with the number of RB's m=1, and the sequence number rb=1 corresponds to the sequence group number. Next, in the process of ST 102, the threshold Xth(m) associated with the number of RB's is set using above equation 6, and, in the process of ST 104 to ST 107, the sequence number r that makes the difference between rb/Nb and r/N equal to or less than the threshold Xth(m) is selected, to generate ZC sequence group 1. The conditions and process for generating ZC sequence group 2 shown in FIG.10B differ from those in the case of ZC sequence group 1, only in setting the reference sequence number rb to 2 in ST 101.

[0049] <threshold Xth(m) setting method 2>

FIG.11 is a diagram illustrating threshold Xth(m) setting method 2 in a sequence allocating method according to the present embodiment. As shown in FIG.11, a threshold for the number of RB's "m" is set, and threshold Xth(m) is set higher below the threshold for the number of RB's than above the threshold for the number of RB's. For example, as shown in following equation 7, the threshold for the number of RB's m is 10, and, if the number of RB's m is equal to or lower than 10, Xth(m) is set to 1/2 Nb, and, if the number of RB's m is higher than 10, Xth(m) is set to 1/4 Nb. That is, the threshold Xth(m) is switched between two fixed values across the sequence length N associated with the number of RB's of 10, and the fixed value associated with the sequence lengths N's associated with the numbers of RB's equal to or less than 10 is set lower than the fixed value associated with the sequence lengths N's associated with the numbers of RB's greater than 10.

$$Xth(m)=1/(2Nb) \text{ (in the case of } 1 \leq m \leq 10)$$

$$Xth(m)=1/(4Nb) \text{ (in the case of } m \geq 11) \quad \dots \text{ (Equation 7)}$$

[0050] By setting the threshold Xth(m) in this way, ZC sequences located near the boundary of adjacent sequence groups have a grater difference of r/N, so that it is possible to suppress an increase of cross-correlation. Also, by increasing the threshold Xth(m) associated with the numbers of RB's lower than the threshold for the number of RB's m, it is possible to increase the number of ZC sequences and maintain it above a predetermined number.

[0051] FIG.12A and FIG.12B illustrate examples of sequence groups acquired by the sequence allocating methods shown in FIG.8 and FIG.11.

To be more specific, the conditions and process for acquiring the sequence groups shown in FIG.12A and FIG.12B (i.e. ZC sequence group 1 and ZC sequence group 2) differ from the conditions and process for acquiring the sequence groups shown in FIG.10A and FIG.10B (i.e. ZC sequence group 1 and ZC sequence group 2), only in using equation 7, instead of equation 6, for the method of setting the threshold $X_{th}(m)$.

[0052] Next, the operations of a radio base station apparatus that is present in a cell, to which sequence groups generated based on the sequence allocating method according to the present embodiment are allocated, will be explained.

[0053] FIG.13 is a block diagram showing the configuration of radio base station apparatus 100, to which sequence groups are allocated, according to the present embodiment.

[0054] Encoding section 101 encodes transmission data and control signal for a radio mobile station apparatus that is present in the same cell as that of radio base station apparatus 100, and outputs the encoded data to modulating section 102. Here, the control signal includes the reference sequence length N_b and the reference sequence number r_b associated with the sequence group number, and the reference sequence length N_b and the reference sequence number r_b are transmitted to, for example, radio mobile station apparatus 200, which will be described later, via a broadcast channel. The control signal also includes scheduling information showing the transmission bandwidth including, for example, the number of RB's for transmission allocated to radio mobile station 200 and the sequence length N , and this scheduling information is transmitted to radio mobile station apparatus 200 via a control channel.

[0055] Modulating section 102 modulates the encoded data received as input from encoding section 101 and outputs the modulated signal to RF (Radio Frequency) transmitting section 103.

[0056] RF transmitting section 103 performs transmission processing such as A/D conversion, up-conversion and amplification on the modulated signal received as input from modulating section 102, and transmits the signal subjected to transmission processing via antenna 104.

[0057] RF receiving section 105 performs reception processing such as down-conversion and A/D conversion on a signal received via antenna 104, and outputs the signal subjected to reception processing to demultiplexing section 106.

[0058] Demultiplexing section 106 demultiplexes the signal received as input from RF receiving section 105 into a reference signal, data signal and control signal, outputs the reference signal to DFT (Discrete Fourier Transform) section 107 and outputs the data signal and control signal to DFT section 114.

[0059] DFT section 107 transforms the time domain reference signal received as input from demultiplexing section 106 into a frequency domain signal by performing DFT processing, and outputs the transformed, frequency domain reference signal to demapping section 109 in channel estimating section 108.

[0060] Channel estimating section 108 is provided with demapping section 109, dividing section 110, IFFT section 111, mask processing section 112 and DFT section 113, and estimates the channel based on the reference signal received as input from DFT section 107.

[0061] Demapping section 109 extracts, from the frequency band reference signal received as input from DFT section 107, a ZC sequence corresponding to the transmission band of each radio mobile station apparatus 200, and outputs the extracted ZC sequences to dividing section 110.

[0062] ZC sequence setting section 1000 calculates the ZC sequences used in radio mobile station apparatuses 200, based on the reference sequence length N_b , the reference sequence number r_b and the number of RB's assigned to each radio mobile station apparatus 200, which are included in control information received as input, and outputs the results to dividing section 110. Here, the internal configuration and operations of ZC sequence setting section 1000 will be described later.

[0063] Dividing section 110 divides the ZC sequences corresponding to each radio mobile station apparatus 200, calculated in ZC sequence setting section 1000, by the ZC sequences actually used in each radio mobile station apparatus 200 and received as input from demapping section 109, and outputs the division result to IFFT (Inverse Fast Fourier Transform) section 111.

[0064] IFFT section 111 performs IFFT processing on the division result received as input from dividing section 110, and outputs the signal subjected to IFFT processing to mask processing section 112.

[0065] Mask processing section 112 extracts the correlation value in the region in which the correlation value of the desired cyclic shift sequence

is present, that is, extracts the correlation value in the window part, by performing mask processing on the signal received as input from IFFT section 111, and outputs the extracted correlation value to DFT section 113.

5 [0066] DFT section 113 performs DFT processing on the correlation value received as input from mask processing section 112, and outputs the correlation value subjected to DFT processing to frequency domain equalization section 116. Here, the signal subjected to DFT processing outputted from DFT section 113, represents the frequency response of the
10 channel.

[0067] DFT section 114 transforms the time domain data signal and control signal received as input from demultiplexing section 106, into the frequency domain by performing DFT processing, and outputs the transformed, frequency domain data signal and control signal to
15 demapping section 115.

[0068] Demapping section 115 extracts the data signal and control signal corresponding to the transmission band of each radio mobile station apparatus 200, from signals received as input from DFT section 114, and outputs the extracted signals to frequency domain equalization section
20 116.

[0069] Frequency domain equalization section 116 performs equalization processing on the data signal and control signal received as input from demapping section 115, using a signal which is received as input from DFT section 113 in channel estimating section 108 and which represents
25 the frequency response of the channel, and outputs the signals subjected to equalization processing to IFFT section 117.

[0070] IFFT section 117 performs IFFT processing on the data signal and control signal received as input from frequency domain equalization section 116, and outputs the signals subjected to IFFT processing to
30 demodulating section 118.

[0071] Demodulating section 118 performs demodulation processing on the signals subjected to IFFT processing received as input from IFFT section 117, and outputs the signals subjected to demodulation processing to decoding section 119.

35 [0072] Decoding section 119 performs decoding processing on the signals subjected to demodulation processing received as input from demodulating section 118, and extracts received data.

[0073] FIG.14 is a block diagram showing the configuration inside ZC sequence setting section 1000.

[0074] Threshold calculating section 1001 calculate the threshold $X_{th}(m)$ according to above equation 6 or equation 7, using the number of RB's m included in control information received as input, and outputs the result to sequence number calculating section 1002.

[0075] Sequence number calculating section 1002 calculates the sequence length N of a ZC sequence that can be used as a reference signal, based on the number of RB's m included in control information received as input, and outputs the result to ZC sequence generating section 1004. Also, sequence number calculating section 1002 calculates the sequence number r of a ZC sequence that can be used as a reference signal, based on the calculated sequence length N , the reference sequence number r_b and the reference sequence length N_b included in the control information received as input, and the threshold $X_{th}(m)$ received as input from threshold calculating section 1001, and outputs the result to parameter determining section 1003.

[0076] Parameter determining section 1003 selects one of usable r 's received as input from sequence number calculating section 1002, and outputs the result to ZC sequence generating section 1004. To be more specific, parameter determining section 1003 selects r corresponding to the remainder acquired by dividing the frame number or slot number by the number of usable r 's, that is, corresponding to the result of performing a modulo operation of the frame number or slot number by the number of usable r 's. For example, upon receiving as input four usable r 's of $r=a, b, c$ and d from sequence number calculating section 1002, parameter determining section 1003 selects $r=a$ when a result of performing a modulo operation on the frame number or slot number by 4 is 0, selects $r=b$ when the result is 1, selects $r=c$ when the result is 2, and selects $r=d$ when the result is 3. By this means, it is possible to realize sequence hopping.

[0077] ZC sequence generating section 1004 generates a ZC sequence according to equation 1 or equation 2, using " r " received as input from parameter determining section 1003 and " N " received as input from sequence number calculating section 1002, and outputs the result to dividing section 110.

[0078] As described above, radio base station apparatus 100 signals the

reference sequence number rb , the reference sequence length Nb and the number of RB's, to radio mobile station apparatus 200.

[0079] Next, radio mobile station apparatus 200 that generates a ZC sequence used as a reference signal will be explained, using the reference sequence number rb , the reference sequence length Nb and the number of RB's signaled from radio base station apparatus 100.

[0080] FIG.15 is a block diagram showing the configuration of radio mobile station apparatus 200 according to the present embodiment. Here, in FIG.15, the receiving system of radio mobile station apparatus 200 will be omitted, and the transmitting system alone will be shown.

[0081] In FIG.15, similar to ZC sequence setting section 1000 provided in radio base station apparatus 100, ZC sequence setting section 1000 provided in radio mobile station apparatus 200 calculates a ZC sequence based on the reference sequence number rb , the reference sequence length Nb and the number of RB's m included in control information transmitted from radio base station apparatus 100, and outputs the result to mapping section 201.

[0082] Mapping section 201 maps the ZC sequence received as input from ZC sequence setting section 1000, to the transmission band of radio mobile station apparatus 200, and outputs the mapped ZC sequence to IFFT section 202.

[0083] IFFT section 202 performs IFFT processing on the ZC sequence received as input from mapping section 201, and outputs the ZC sequence subjected to IFFT processing to RF transmitting section 203.

[0084] RF transmitting section 203 performs transmission processing such as D/A conversion, up-conversion and amplification on the ZC sequence received as input from IFFT section 202, and transmits the signal subjected to transmission processing, via antenna 204.

[0085] Thus, according to the present embodiment, when the number of RB's increases, that is, when the ZC sequence length N is longer, a sequence group is generated using sequences that make the difference between r/N and rb/Nb smaller, and allocated to the single cell. By this means, it is possible to maintain a predetermined number of sequences in each RB while reducing cross-correlation between different sequence groups, thereby reducing inter-cell interference.

[0086] Also, although an example case has been described above with the present embodiment where the sequence length of one RB is used as

the reference sequence length N_b in ST 101, the present invention is not limited to this, and it is equally possible to set the reference sequence length N_b adaptively. For example, taking into account that, amongst ZC sequences forming a certain sequence group, the reference ZC sequence
 5 has the lowest cross-correlation with other sequence groups, the reference sequence length N_b is the sequence length associated with the number of RB's used in a radio mobile station apparatus in the cell edge of the poorest received quality. By this means, it is further possible to reduce inter-cell interference.

10 [0087] Also, in a cellular communication system, it is equally possible to set the reference sequence length N_b based on the number of sequence groups required to reduce inter-cell interference. For example, when the number of sequence groups required is 100, the sequence length that is the closest to 100, that is, a sequence length of 109, associated with nine
 15 RB's, is set as the reference sequence length N_b . It is possible to generate 108 ZC sequences from nine RB's, that is, from a sequence length of 109, so that it is possible to select 100 reference sequence number r 's from 108 reference sequence number r 's and generate 100 different sequence groups.

20 [0088] Also, an example case has been described above with the present embodiment where the number of ZC sequences associated with a larger number of RB's is limited by setting the threshold $X_{th}(m)$ smaller when the number of RB's is larger. However, the present invention is not limited to this, and it is equally possible to find predetermined ZC
 25 sequences arranged in ascending order of the difference between r/N and rb/N_b , and form a sequence group. That is, ZC sequences that make the difference between r/N and rb/N_b smaller are preferentially selected until the number of ZC sequences reaches a predetermined number. If the sequences are arranged based on the magnitude of r/N , the interval
 30 between sequences is $1/N$, and the interval between sequences is smaller when an RB is larger (i.e. N is larger). Therefore, by the process of limiting the number of sequences, it is possible to provide the same effect as provided in the process of making the threshold $X_{th}(m)$ smaller when an RB is larger. That is, even if sequence groups are generated in the
 35 above way, it is equally possible to provide an effect of reducing cross-correlation between sequence groups.

[0089] Also, an example case has been described above with the present

embodiment where the reference sequence length N_b signaled from radio base station apparatus 100 to radio mobile station apparatus 200, with an assumption that the reference sequence length N_b varies between cells. However, the present invention is not limited to this, and, if a reference sequence length N_b that is common between all cells is determined in advance, signaling is not necessary. Alternatively, it is equally possible to determine in advance the reference number of RB's instead of the reference sequence length N_b . The numbers of RB's and sequence lengths are uniquely associated, so that it is possible to derive the reference sequence length N_b from the reference number of RB's.

[0090] Also, an example case has been described above with the present embodiment where sequence number calculating section 1002 calculates the usable sequence number r using the reference sequence number r_b , the reference sequence length N_b and the number of RB's m . However, the present invention is not limited to this, and, if radio base station apparatus 100 and radio mobile station apparatus 200 hold the sequence groups shown in FIG.10A and FIG.10B or the sequence groups shown in FIG.12A and FIG.12B in the form of tables, sequence number calculating section 1002 may calculate the usable sequence number r by looking up these tables. An example method of determining the sequence number r using these tables will be explained below. For example, with an assumption that the reference sequence length N_b is fixed, tables are prepared for the two parameters of sequence length N and reference sequence number r_b , and selectable r 's are described therein. In this example, radio mobile station apparatus 100 receives the sequence length N and reference sequence number r_b signaled from radio base station apparatus 200, refers to the tables associated with these items and determines a Zadoff-Chu sequence that should be used as a reference signal by selecting in a random manner one of the described values that r might assume.

[0091] Also, an example case has been described above with the present embodiment where parameter determining section 1003 selects one of usable sequence numbers r 's based on the frame number or slot number. However, the present invention is not limited to this, and parameter determining section 1003 may select the minimum or maximum sequence number from usable sequence number r 's.

[0092] (Embodiment 2)

The sequence allocating method according to Embodiment 2 of the present invention is based on the cross-correlation characteristic of ZC sequence ascertained by computer simulation by the present inventors.

[0093] FIG.16 is a diagram illustrating the cross-correlation characteristic of ZC sequence ascertained by computer simulation by the present inventors.

[0094] In FIG.16, the horizontal axis represents the difference of r/N between ZC sequences of different transmission bandwidths or different sequence lengths, and the vertical axis represents the cross-correlation characteristic. As shown in FIG.16, if the difference of r/N between ZC sequences of different transmission bandwidths or different sequence lengths is 0.0, the cross-correlation between ZC sequences is the largest, and, if the difference of r/N is 0.5, the cross-correlation between ZC sequences forms a peak. That is, the cross-correlation between ZC sequences of different transmission bandwidths or different sequence lengths increases when the difference of r/N is closer to 0.5.

[0095] The sequence allocating method according to the present embodiment has a feature of excluding a ZC sequence that makes a difference of r/N from the reference ZC sequence close to 0.5, from a sequence group.

[0096] FIG.17 is a flowchart showing the process of the sequence allocating method in a cellular radio communication system according to the present embodiment. Here, in the process in FIG.17, the same process as in FIG.8 will be omitted.

[0097] In ST 201, as an existing sequence group, a sequence group formed with ZC sequences, in which the difference between r/N and r_b/N_b is equal to or less than $1/26$ regardless of the number of RB's, is inputted.

[0098] In ST 202, according to following equation 8, the threshold $X_{th2}(m)$ is set in a case where the number of RB's is m . That is, $X_{th2}(m)$ is set higher by a predetermined value every time the number of RB's increases.

$$X_{th2}(m) = (m-1) \times 0.0012 \quad \dots (\text{Equation 8})$$

[0099] In ST 203, whether or not r and N satisfy following equation 9 is decided.

$$||r/N - r_b/N_b| - 0.5| \leq X_{th2}(m) \quad \dots (\text{Equation 9})$$

[0100] In ST 203, if r and N are decided to satisfy equation 9 ("YES" in ST 203), the process of ST 204 is performed.

[0101] In ST 204, the ZC sequence having r as a sequence number is deleted from the existing sequence group inputted in ST 201

[0102] By contrast, if r and N are decided not to satisfy equation 9 ("NO" in ST 203), the process of ST 108 is performed.

5 [0103] FIG.18 is a diagram illustrating a method of generating sequence groups according to the process of the sequence allocating method in FIG.17.

[0104] In FIG.18, group X represents a sequence group including a reference sequence, and group Y represents an existing sequence group
 10 inputted in ST 201. Here, the hatched region represents ZC sequences in which the difference between r/N and rb/Nb in group X is close to 0.5, for example, in which the r/N difference stays within a range of $(0.5 - Xth2(m))$ to $(0.5 + Xth2(m))$. As shown in FIG.18, in the sequence allocating method according to the present embodiment, ZC sequences, in
 15 which the difference between r/N and rb/Nb in group X stays within the range of $(0.5 - Xth2(m))$ to $(0.5 + Xth2(m))$, are deleted from the existing sequence group Y. By this means, cross-correlation between sequence groups is reduced. Also, according to equation 8, by setting the threshold $Xth2(m)$ smaller when the number of RB's decreases and by
 20 reducing the number of sequences deleted, the number of ZC sequences deleted from a sequence group is limited.

[0105] FIG.19A and FIG.19B illustrate examples of sequence groups acquired by the sequence allocating method according to the present embodiment. To be more specific, the sequence groups shown in
 25 FIG.19A and FIG.19B (ZC sequence group 1 and ZC sequence group 8) are acquired according to the following conditions and process. For example, to generate ZC sequence group 1 shown in FIG.19A, in ST 101, the reference sequence length Nb is set to 13, and the reference sequence number rb is set to 1. Here, an existing sequence group is comprised of
 30 sequences in which the difference from rb/Nb is equal to or less than $1/26$, regardless of the number of RB's. In ST 202, using equation 8, the threshold $Xth2(m)$ associated with the number of RB's is set, and a ZC sequence that satisfies equation 9 in ST 204 is deleted from the existing sequence group.

35 [0106] Thus, according to the present embodiment, upon generating sequence groups, the threshold $Xth2(m)$ is set smaller when the number of RB's is smaller, and a ZC sequence, in which the difference between r/N

and rb/Nb stays within a range of $(0.5-Xth2(m))$ to $(0.5+Xth2(m))$, is deleted from an existing sequence group. By this means, it is possible to reduce the cross-correlation between sequence groups and reduces inter-cell interference while maintaining the number of sequences forming sequence groups.

[0107] Also, an example case has been described above with the present embodiment where a sequence group comprised of ZC sequences, in which the difference between r/N and rb/Nb is equal to or less than $1/26$, regardless of the number of RB's, is inputted as an existing sequence group in ST 201. However, the present invention is not limited to this, and it is equally possible to input a sequence group acquired in Embodiment 1 as an existing sequence group.

[0108] Also, although an example case has been described above with the present embodiment where a ZC sequence, in which the difference between r/N and rb/Nb stays within a range of $(0.5-Xth2(m))$ to $(0.5+Xth2(m))$, is deleted from an existing sequence group, the present invention is not limited to this, and, it is equally possible to further add conditions for deleting ZC sequences from a sequence group and delete only sequences associated with the numbers of RB's equal to or greater than a predetermined value, for example, 10. By this means, it is possible to prevent ZC sequences associated with smaller numbers of RB's from being deleted excessively and limit the number of ZC sequences deleted.

[0109] FIG.20A and FIG.20B show examples of sequence groups acquired when the number of RB's allowing a sequence to be deleted, is set 10 or more. Here, other conditions for acquiring the sequence groups shown in FIG.20A and FIG.20B (i.e. ZC sequence group 1 and ZC sequence group 8) are the same as the conditions for acquiring the sequence groups shown in FIG.19A and FIG.19B.

[0110] Also, an example case has been described above with the present embodiment where whether or not r and N satisfy equation 9 is decided in ST 203, the present invention is not limited to this, and it is equally possible to use following equation 10. By this means, it is possible to delete the same sequences as in the case of using equation 9, from a sequence group.

$$||r/N-rb/Nb|-(0.5/Nb)|\leq Xth2(m) \quad \dots(\text{Equation 10})$$

[0111] Also, an example case has been described above with the present

embodiment where one sequence length, that is, one kind of the number of RB's is used as a reference in equation 9. However, the present invention is not limited to this, and it is equally possible to provide a plurality of reference sequence lengths used for a decision in equation 9, that is, a plurality of the reference numbers of RB's. For example, using three references of $Nb_1=13$, $Nb_2=29$ and $Nb_3=37$ associated with one RB, two RB's and three RB's, all sequences in which $||r/N-rb_1/Nb_1|-0.5|$ is lower than a threshold, $||r/N-rb_2/Nb_2|-0.5|$ is lower than a threshold and $||r/N-rb_3/Nb_3|-0.5|$ is lower than a threshold, are deleted. Here, a plurality of the reference numbers of RB's need not be consecutive. For example, it is possible to set one RB and three RB's (i.e. $N=13$ and $N=37$) as the reference sequence length Nb .

[0112] Also, an example case has been described above with the present embodiment where ZC sequences, in which the difference between r/N and rb/Nb stays within a range of $(0.5-Xth2(m))$ to $(0.5+Xth2(m))$, are deleted from an existing sequence group. However, the present invention is not limited to this, and it is equally possible to further add the conditions of maintaining (leaving) predetermined sequences based on each number of RB's. To be more specific, the number of sequences $p(m)$ to be maintained is set in advance in each RB, sequences are deleted in order from the sequence in which the difference between r/N and rb/Nb is the closest to 0.5, and deletion processing is stopped when the number of remaining sequences is $p(m)$. By this means, it is possible to maintain required sequences in each RB.

[0113] Embodiments of the present invention have been explained above.

[0114] The sequence allocating method according to the present invention is not limited to the above embodiments, and can be implemented with various changes. For example, the above embodiments can be implemented with adequate combinations.

[0115] Also, in the above embodiments, as further conditions for generating sequence groups, sequences, in which CM (Cubic Metric) or PAPR is greater than a predetermined value, such as CM or PAPR in QPSK, may not be used and may be deleted from a sequence group. In this case, the magnitude of CM or PAPR is less biased between sequence groups, so that, even if such conditions are added, it is possible to make the number of sequences substantially equal between sequence groups,

and the number of sequences that can be used in each sequence group is not biased.

[0116] Also, although an example case has been described above with embodiments where sequence groups are formed using frequency domain ZC sequences, the present invention is not limited to this, and it is equally possible to form sequence groups using ZC sequences that are generated in the time domain. Here, time domain ZC sequences and frequency domain ZC sequences satisfy the relationship represented by following equation 11.

$$(u \times r) \bmod(N) = N-1 \quad \dots(\text{Equation 11})$$

[0117] In equation 11, N represents the ZC sequence length, r represents the sequence number of time domain ZC sequence, and u represents the sequence number of frequency domain ZC sequence. Therefore, when a sequence group is formed using time domain ZC sequences, ZC sequences, in which the difference of u/N from the reference sequence is less than a predetermined threshold, are found. Time domain ZC sequences and frequency domain ZC sequences share the same characteristics, and therefore the same effect is acquired.

[0118] Also, although an example case has been described above with embodiments where a ZC sequence is used as a reference signal for channel estimation, the present invention is not limited to this, and it is equally possible to use a ZC sequence as, for example, a reference signal for CQI estimation (i.e. sounding RS), synchronization channel, random access preamble signal, CQI signal or ACK/NACK signal.

[0119] Also, although an example case has been described above with embodiments where a ZC sequence is used as a reference signal from a radio mobile station apparatus to a radio base station apparatus, the present invention is not limited to this, and it is equally possible to apply the present invention to a case where a ZC sequence is used as a reference signal from a radio base station apparatus to a radio mobile station apparatus.

[0120] Also, although an example case has been described above with embodiments where a ZC sequence is used as a reference signal, it is equally possible to use, for example, a GCL (Generalized Chirp-Like) sequence $c(k)$ represented by following equation 12, as a reference signal.

$$c(k) = a(k)b(k \bmod m), k=0,1,\dots,N-1 \quad \dots(\text{Equation 12})$$

[0121] In equation 12, N represents the sequence length, and the

relationship of $N=sm^2$ (where s and m are integers) or $N=tm$ (where t and m are integers) holds. Here, $a(k)$ is the ZC sequence represented by equation 1 or equation 2, and $b(k)$ is a DFT sequence represented by following equation 13.

5 [3]

$$b_i(k) = W_m^{ik}, \quad i, k = 0, 1, \dots, m-1 \dots (\text{Equation 13})$$

[0122] Also, although the above embodiments use the condition “equal to or less than a threshold” as a decision condition, it is equally possible to use the condition “less than a threshold” as a decision condition.

10 [0123] Also, the above embodiments have been described using Zadoff-Chu sequences. However, Zadoff-Chu sequences are not limited to the sequences represented by the above equations, and include a sequence generated by repeating part of a Zadoff-Chu sequence, a sequence generated by truncating part of a Zadoff-Chu sequence and a sequence
15 generated by removing part of a Zadoff-Chu sequence.

[0124] Although a case has been described above with embodiments as an example where the present invention is implemented with hardware, the present invention can be implemented with software.

[0125] Furthermore, each function block employed in the description of
20 each of the aforementioned embodiments may typically be implemented as an LSI constituted by an integrated circuit. These may be individual chips or partially or totally contained on a single chip. “LSI” is adopted here but this may also be referred to as “IC,” “system LSI,” “super LSI,” or “ultra LSI” depending on differing extents of integration.

25 [0126] Further, the method of circuit integration is not limited to LSI’s, and implementation using dedicated circuitry or general purpose processors is also possible. After LSI manufacture, utilization of an FPGA (Field Programmable Gate Array) or a reconfigurable processor where connections and settings of circuit cells in an LSI can be
30 reconfigured is also possible.

[0127] Further, if integrated circuit technology comes out to replace LSI’s as a result of the advancement of semiconductor technology or a derivative other technology, it is naturally also possible to carry out function block integration using this technology. Application of
35 biotechnology is also possible.

[0128] The disclosure of Japanese Patent Application No.2007-160348, filed on June 18, 2007, including the specification, drawings and abstract,

is incorporated herein by reference in its entirety.

Industrial Applicability

- [0129] The sequence allocating method, transmitting method and radio
5 mobile station apparatus according to the present invention can reduce
cross-correlation between different sequence groups while maintaining the
number of ZC sequences forming a sequence group, and are applicable to
a cellular radio communication system.

CLAIMS

1. A transmission apparatus comprising:
 - a receiving section configured to receive control information related to transmission bandwidth of a reference signal;
 - a generating section configured to generate the reference signal using one of sequence(s) which are grouped into a group, wherein N_b is a reference sequence length which is common to all cells, and a predefined number of the sequence(s) with sequence number(s) r in ascending order of absolute value of difference between r_b/N_b and r/N are grouped into the group with a group number r_b for a sequence length N which depends on the transmission bandwidth based on the control information; and
 - a transmitting section configured to transmit the reference signal.

2. A transmission apparatus comprising:
 - a receiving section configured to receive control information related to transmission bandwidth of a reference signal;
 - a generating section configured to generate the reference signal using one of sequence(s) which are grouped into a group, wherein N_b is a reference sequence length which is common to all cells, and the sequence(s) with sequence number(s) r , by which absolute value of difference between r_b/N_b and r/N is less than or equal to a predetermined value, are grouped into the group with a group number r_b for a sequence length N which depends on the transmission bandwidth based on the control information; and
 - a transmitting section configured to transmit the reference signal,
 - wherein the predetermined value for the wide transmission bandwidth is smaller than that for the narrow transmission bandwidth.

3. The transmission apparatus according to claim 2, wherein the wider the transmission bandwidth is, the smaller the predetermined value is.

4. The transmission apparatus according to claim 2, wherein a definition of the predetermined value is different across a threshold value.

5. The transmission apparatus according to any of claims 1-4, wherein the sequence is a Zadoff-Chu sequence $a_r(k)$ defined by

$$a_r(k) = e^{-j \frac{2\pi r}{N} (k(k+1)/2 + qk)}$$

wherein k and q are arbitrary integers.

6. The transmission apparatus according to any of claims 1-5, wherein the sequence length N corresponds to the transmission bandwidth uniquely.

7. The transmission apparatus according to any of claims 1-6, wherein said generating section groups sequence(s) with sequence number(s) r by which the absolute value for the sequence length N is smaller as the transmission bandwidth is wider.

8. The transmission apparatus according to claim 1, wherein said generating section limits a number of the sequence(s) available for the sequence length N by grouping the predefined number of the sequence(s).

9. The transmission apparatus according to any of claims 1-8, further comprising a receiving section configured to receive control information related to the group number rb , wherein said generating section generates the reference signal using one of the grouped sequence(s) based on the control information.

10. The transmission apparatus according to any of claims 1-9, wherein said generating section generates the reference signal using one of the grouped sequence(s) according to a cell.

11. The transmission apparatus according to any of claims 1-10, wherein the reference signal is a sounding reference signal (sounding RS).

12. The transmission apparatus according to any of claims 1-11, wherein said generating section generates the reference signal using one sequence which is selected among the grouped sequence(s) with sequence hopping.

13. The transmission apparatus according to any of claims 1-12, wherein said generating section generates the reference signal using one sequence which is selected among the grouped sequence(s) with sequence hopping based on a frame number or slot number.

14. A method for generating reference signal comprising:

receiving control information related to transmission bandwidth of a reference signal; and

generating the reference signal using one of sequence(s) which are grouped into a group, wherein N_b is a reference sequence length which is common to all cells, and a predefined number of the sequence(s) with sequence number(s) r in ascending order of absolute value of difference between r_b/N_b and r/N are grouped into the group with a group number r_b for a sequence length N which depends on the transmission bandwidth based on the control information.

15. A method for generating reference signal comprising:

receiving control information related to transmission bandwidth of a reference signal; and

generating the reference signal using one of sequence(s) which are grouped into a group, wherein N_b is a reference sequence length which is common to all cells, and the sequence(s) with sequence number(s) r , by which absolute value of difference between r_b/N_b and r/N is less than or equal to a predetermined value, are grouped into the group with a group number r_b for a sequence length N which depends on the transmission bandwidth based on the control information,

wherein the predetermined value for the wide transmission bandwidth is smaller than that for the narrow transmission bandwidth.

16. A reception apparatus comprising:

a transmitting section configured to transmit control information related to transmission bandwidth of a reference signal and control information related to a group number r_b , where N_b is a reference sequence length which is common to all cells, and a predefined number of sequence(s) with sequence number(s) r in ascending order of absolute value of difference between r_b/N_b and r/N are grouped into group with the group number r_b for a sequence length N which depends on the transmission bandwidth; and

a receiving section configured to receive the reference signal,

wherein the reference signal is generated using one of the sequence(s) which are grouped based on the control information related to the transmission bandwidth of the reference signal and the control information related to the group number r_b .

17. A reception apparatus comprising:

a transmitting section configured to transmit control information related to transmission bandwidth of a reference signal and control information related to a group number r_b , where N_b is a reference sequence length which is common to all cells, and sequence(s) with sequence number(s) r , by which absolute value of difference between r_b/N_b and r/N is less than or equal to a predetermined value, are grouped into group with the group number r_b for a sequence length N which depends on the transmission bandwidth based on the control information related to the transmission bandwidth; and

a receiving section configured to receive the reference signal,

wherein: the reference signal is generated using one of the sequence(s) which are grouped based on the control information related to the transmission bandwidth of the reference signal and the control information related to the group number r_b ; and

the predetermined value for the wide transmission bandwidth is smaller than that for the narrow transmission bandwidth.

18. A method for receiving reference signal comprising:

transmitting control information related to transmission bandwidth of a reference signal;

transmitting control information related to a group number r_b , where N_b is a reference sequence length which is common to all cells, and a predefined number of sequence(s) with sequence number(s) r in ascending order of absolute value of difference between r_b/N_b and r/N are grouped into group with the group number r_b for a sequence length N which depends on the transmission bandwidth; and

receiving the reference signal generated using one of the sequence(s) which are grouped based on the control information related to the transmission bandwidth of the reference signal and the control information related to the group number r_b .

19. A method for receiving reference signal comprising:

transmitting control information related to transmission bandwidth of a reference signal;

transmitting control information related a group number rb , where Nb is a reference sequence length which is common to all cells, and sequence(s) with sequence number(s) r , by which absolute value of difference between rb/Nb and r/N is less than or equal to a predetermined value, are grouped into group with the group number rb for a sequence length N which depends on the transmission bandwidth based on the control information related to the transmission bandwidth; and

receiving the reference signal generated using one of sequence(s) which are grouped based on the control information related to the transmission bandwidth of the reference signal and the control information related to the group number rb ,

wherein the predetermined value for the wide transmission bandwidth is smaller than that for the narrow transmission bandwidth.

20. An integrated circuit for controlling a process comprising:

receiving control information related to transmission bandwidth of a reference signal; and

generating the reference signal using one of sequence(s) which are grouped into a group, wherein Nb is a reference sequence length which is common to all cells, and a predefined number of the sequence(s) with sequence number(s) r in ascending order of absolute value of difference between rb/Nb and r/N are grouped into the group with a group number rb for a sequence length N which depends on the transmission bandwidth based on the control information.

21. An integrated circuit for controlling a process comprising:

receiving control information related to transmission bandwidth of a reference signal; and

generating the reference signal using one of sequence(s) which are grouped into a group, wherein Nb is a reference sequence length which is common to all cells, and the sequence(s) with sequence number(s) r , by which absolute value of difference between rb/Nb and r/N is less than or equal to a predetermined value, are grouped into the group with a group number rb for a sequence length N which depends on the transmission bandwidth based on the control information,

wherein the predetermined value for the wide transmission bandwidth is smaller than that for the narrow transmission bandwidth.

22. An integrated circuit for controlling a process comprising:

transmitting control information related to transmission bandwidth of a reference signal;

transmitting control information related to a group number rb , where N_b is a reference sequence length which is common to all cells, and a predefined number of sequence(s) with sequence number(s) r in ascending order of absolute value of difference between rb/N_b and r/N are grouped into group with the group number rb for a sequence length N which depends on the transmission bandwidth; and

receiving the reference signal generated using one of the sequence(s) which are grouped based on the control information related to the transmission bandwidth of the reference signal and the control information related to the group number rb .

23. An integrated circuit for controlling a process comprising:

transmitting control information related to transmission bandwidth of a reference signal;

transmitting control information related a group number rb , where N_b is a reference sequence length which is common to all cells, and sequence(s) with sequence number(s) r , by which absolute value of difference between rb/N_b and r/N is less than or equal to a predetermined value, are grouped into group with the group number rb for a sequence length N which depends on the transmission bandwidth based on the control information related to the transmission bandwidth; and

receiving the reference signal generated using one of sequence(s) which are grouped based on the control information related to the transmission bandwidth of the reference signal and the control information related to the group number rb ,

wherein the predetermined value for the wide transmission bandwidth is smaller than that for the narrow transmission bandwidth.