

Description

The present invention relates to transceivers used for communicating over a common communication channel.

Description of the Prior Art

When communicating between two transceivers over metallic conductors, optical fibers, or other media, there often is provided a defined relationship between the transceivers. That is, one of the transceivers is designated as the "master", and the other as the "slave". This designation is useful when prescribing the protocol for establishing communications between the transceivers. For example, the master may send out a pulse or other signal to activate the slave when communications are desired. This allows bidirectional communications over a single channel, by time sharing the channel between the two transceivers. If a suitable protocol were not established, there is the possibility that a transceiver will attempt to transmit while data is incoming, which can result in lost information.

One early technique for allocating communication time slots among stations was the "Aloha net", wherein a station desiring to transmit would broadcast a burst of digital data to a number of other stations. The address of the intended station was included in the transmission, and the transmitting frequency was then monitored by the transmitting station to determine whether another station had transmitted at the same time. If so, the transmission to the desired location was repeated, to ensure that the information was not lost due to interference.

The use of two transceivers in a time-shared manner over a single communication channel is usually referred to as "half-duplex" operation. Transmitting digital signals in time-shared groups is also referred to as the "burst mode" or "ping-pong" technique. It is possible to avoid the time-sharing requirements of these techniques, but at the cost of an additional channel, resulting in "full-duplex" operation.

In the half-duplex technique, the slave is maintained in a state receptive to the signal transmitted from the master at least during the approximate time period during which communications are expected. Normally, transmissions from the slave unit are inhibited during this waiting period. For these and possibly other reasons, the master and slave units are required to be differentiated in some manner. This differentiation is accomplished by a change in the characteristics of the transceivers during manufacture or use. For example, in one current half-duplex transceiver implemented in an

integrated circuit chip, both the master and slave transceiver chips are initially formed identically. That is, their time bases, transmitter, and receiver portions are initially identical as formed on the chip. However, during a latter phase of the production process, a different metalization pattern designates one unit as the master, and the other as the slave. It is also possible for the user to perform the designation, as by the appropriate connection of an integrated circuit terminal. The designation by whatever technique then causes the slave transceiver to remain in the receive state until the signaling pulse is received from the master. That is, only the master can initiate communications over the channel. This arrangement has the disadvantage that the flexibility of use of a given transceiver is reduced, since it can perform only as a master or slave after a given designation.

Another prior art technique that allows for bidirectional communications over a single channel utilizes a collision detection scheme. For example, the Ethernet (a trademark of Xerox Corp.) networking technique uses transceivers that monitor the common channel for incoming messages and traffic between other units. A given transceiver transmits only when the channel is not busy. It is possible for transmission to begin just as traffic is detected, resulting in a "collision", wherein data from two (or more) transceivers are simultaneously present on the channel. The two (or more) colliding transceivers then wait a random time period before attempting transmission again. If re-transmission is not then successful because of a second collision, the time period is again changed. Note however that in the Ethernet technique each transceiver on the network must still be designated in some manner to specify its address to other units. Furthermore, the collision avoidance technique must be practiced every time a transmission is to begin. Also, relatively sophisticated control circuitry is required to detect and avoid collisions. Hence, this networking technique is overly complicated than is desirable for implementing a low-cost two-transceiver communication link over a single channel.

JP-A-56117455 discloses a master/slave communications system wherein the station that transmits a message discontinues receiving action for a time period equal to the round-trip propagation delay. This helps ensure proper message acknowledgement over long-delay transmission paths.

PROCEEDINGS OF THE 1982 INTERNATIONAL SYMPOSIUM ON SUBSCRIBER LOOPS AND SERVICES, Toronto, 20th-24th September 1982, Catalog No. 82CH1686-5, pages 169-173, IEEE, New York, US; B.S. BOSIK et al.: "A loop access system for a circuit switched digital capability" discloses a master/slave communications system wherein a framing algorithm appends extra bits to

every burst of data. When the system recognizes an out of frame condition exists, as when starting up the system or recovering from a loss of synchronization, input data is blocked, and a specific pattern is sent for each burst. During this time, only the master transmits, and the slave is instructed to receive only, until the slave has established frame synchronization. Then, the slave is allowed to transmit. This technique insures that overlapping bursts never occur.

According to this invention there is provided a transceiver as claimed in claim 1.

To initially establish communications between two transceivers over a common channel, each transceiver is adapted to transmit a start signal, and then listen for a start signal from the other transceiver. Each transceiver is designed to transmit the start signal again if no start signal is received from the other transceiver within a listening time period. A random time difference between the periodic transmissions by the transceivers provides that the start signal transmitted from one of the transceivers will eventually get through to the other during its listening period. This difference may be due to the small difference between the frequencies of each transceiver's local time base. In a preferred embodiment, the difference is predominantly due to a circuit that substantially increases the randomness of the listening period, without affecting the frequency of the transceiver's local time base. The present technique allows the transceivers to be identical (within normal tolerances) in manufacture and use if desired.

The invention will now be described with reference to the accompanying drawings, in which:

FIG. 1 shows a time sequence for establishing synchronization;

FIG. 2 shows an exemplary protocol for establishing communications, and also provides for reflections to be ignored;

FIG. 3 shows a diagram of a transceiver embodying the invention; and

FIG. 4 shows a circuit suitable for randomizing the listening period.

The following detailed description relates to a technique for communicating between two transceivers having a peer relationship, whereby designating one the master and the other the slave is avoided. The transceivers transmit (and receive) at different times due to a start-up procedure using time variations that are statistically random (or pseudo-random) in nature. By detecting an incoming start signal during a listening period, the two transceivers are synchronized for communication without the necessity of collision detection. Furthermore, the transceivers can be identical within normal tolerances as manufactured.

The present invention provides for a "start-up" procedure whereby each transceiver periodically transmits a "start" signal, usually a defined sequence of bits in a packet, and then listens for the start signal from the other transceiver. The time periods between transmissions of the start signal are at least slightly different for the two transceivers. The minimum length of the "listening period" is typically chosen to allow for the maximum specified round-trip propagation delay time over the channel, plus the time to receive the start signal (typically equal to the duration of a packet). Using terms as defined below, the minimum listening period is then typically $2A + P$. During start-up, the difference between the transmission time periods ensures that one of the start signals will eventually arrive at the other transceiver when that other transceiver is listening for it, thereby establishing the link. Once the link is established, the information signals, typically multi-bit data packets, maintain the synchronism between the transceivers. The time difference between the transmission periods during start-up is typically due to random differences in component values within desired manufacturing tolerances. The time difference may be enhanced by changes in temperature, operating voltage, component aging, or other factors that tend to independently affect the transceivers in a random manner.

A typical startup sequence that illustrates the present invention is shown in FIG. 1. At time T_0 the first transceiver is activated, and transmits a start signal, typically a multi-bit data packet having a time duration P . This packet traverses the communication channel and arrives at the second transceiver after a propagation delay of A . Following this transmission, the first transceiver activates its receiver, which listens for an incoming start signal for a listening period having duration L . (For simplicity of illustration, no waiting period to allow reflections to die out is included prior to activating the receiver). The start signal is the combination of the "start" and "stop" bits of the packet in this illustrative case, but may be any desired sequence of bits in the packet. As shown, since no start signal is incoming during the first listening period, the first transceiver again transmits a packet at time T_2 . The second transceiver is activated at time T_1 , which is S_1 later than the activation of the first transceiver. After the transmission of its packet, the second transceiver also listens for a listening period. As shown, no start signal is received during this time either. Hence, the second transceiver again transmits a packet at time T_3 .

Due to the random difference in the period between transmissions, eventually a start signal will be received by one of the transceivers during its listening period. At that time, the transceiver de-

tests the start signal, terminates the listening period and (after the optional waiting period R) starts transmitting a packet to the other transceiver. When both transceivers have recognized the start signal within their listening periods, the transceivers are synchronized. Thereafter, a number of packets containing a fixed bit pattern may be exchanged between the transceivers, to verify proper synchronization. Each transceiver then switches to a state receptive to transmit and receive the user data. In a presently preferred embodiment, each transceiver also switches to a shorter listening period once synchronization is initially achieved, to reduce the time required to detect the loss of data, as due to noise, or a break in the channel, etc. For example, if $L=1$ millisecond during the start-up sequence, then changing to $L=50$ microseconds after synchronization is achieved allows for rapidly detecting loss of data. The transceivers are typically designed to reset L to the longer period when power is lost.

For an example of the time required for start-up, if the local time base of each transceiver uses a crystal oscillator having a design frequency of 1 megahertz and a tolerance of 0.01 percent, the time bases will differ in frequency by no more than 200 hertz. However, there is some difference, due to the inevitable statistical variations in the component values or operating conditions (e.g., temperature or power supply voltage) of the two transceivers. Because of this relatively small but inevitable difference in frequency, after a certain time period the transmissions from one of the transceivers will diverge sufficiently from the transmissions from the other transceiver that the transmissions will not overlap. (A resistance-capacitance type oscillator may be used to provide a larger tolerance, and shorter start-up time). Thus, as indicated in FIG. 1, the transmission of the start signal from transceiver one will eventually arrive at transceiver two during transceiver two's listening period. As noted, the listening period is a random variable that is chosen to be greater than a desired minimum time. However, it is desirable that it not be excessively long, in order to minimize the time required for start-up. We recommend a listening period having a value less than 1000 times the duration of the start signal, which duration is typically the same as the duration of a data packet. In most cases, particularly in local area transmission systems, the listening period is less than 100 milliseconds, and typically less than 10 milliseconds.

In a preferred embodiment, rather than relying solely on the relatively small differences in the time base oscillators, a "randomizing" circuit is used that produces relatively larger variations in the listening period without affecting the frequency of the time base oscillator. This is effective because a

change in the listening period also produces a change in the time interval between the periodic transmissions of the start signal. Hence, the statistical difference between the transmission intervals for the two transceivers is increased. In this manner, the average time required for start-up is reduced, while allowing for ease of maintaining synchronization of a high data rate after start-up is achieved. If the communications channel is broken or otherwise interfered with, the startup sequence will again be initiated, since a given transceiver will not then have received a signal within its listening time period. Hence, communication may again be established.

If a data buffer (optional) is provided in each transceiver, the communication can appear to be full duplex to the user. For example, the actual half-duplex data rate may be about 600 kilobits per second in each direction, which will allow each end user to send and receive at a constant 19 kilobit rate, allowing for oversampling the user data, the inclusion of control bits, and propagation delays. If the data buffer has sufficient capacity, even momentary breaks in the communication channel need not be apparent to the users, since the transceivers can automatically re-initiate the above startup procedure until synchronization is again achieved, and re-transmit the missing data.

Also, as is known in the art, an additional waiting period may be provided by each transceiver to allow reflections to die out in the channel before the transceiver transmits after receiving a transmission from the other end. Reflections are commonly present on a communication channel due to irregularities in the transmission medium at various points, usually including splices and equipment terminations. The irregularities include impedance mis-matches in the case of electrical conductors, and differences in the index of refraction in the case of optical conductors. Any reflections of a transmitted signal (from the near end) tend to mask the signal received from the far end. However, this additional waiting period is optional insofar as the present invention is concerned. That is, the reflections may not be of sufficient magnitude to interfere with the desired signal, or may be removed by echo-cancelers or dealt with otherwise.

Referring to FIG. 2, a sequence of operations for implementing the present invention in a given transceiver is shown. The "begin" step may occur when power is applied to the transceiver, and normally occurs independently for the two transceivers at opposite ends of a given channel. The transmitter then sends out the start signal (e.g., a multi-bit packet), while the receiver is disabled. The inclusion of an optional waiting period to allow reflections to be ignored is provided by adding a time period R before enabling the receiver. The waiting

period is typically of duration $2A$, wherein A is the propagation time of a signal over the maximum length communication channel with which the transceiver is designed to operate. For a local area type transmission system, the length is typically less than 10 kilometers. However, the present technique may be practiced with channels of any length. The round trip time ($2A$) then allows for a reflection from the far end of a channel having the maximum length (or less) to be ignored by the receiver. However, other waiting periods may be suitable. For example, a shorter waiting period may be acceptable if it is known that the far end reflection is relatively small in magnitude, or if the channel actually used is less than the maximum design length. Alternately, the waiting period R may be longer than $2A$ if additional attenuation of reflections is desired. Typically, the waiting period allows for an integral number of round-trips for the signal, over a channel having the maximum design length, and hence typically $R = nA$, where n is an even integer.

Upon enabling the receiver after this first optional waiting period, the listening period begins. If a start signal is not detected during the listening period, the transmitter again transmits a start signal. However, when a start signal is detected during the listening period, synchronization (i.e., "link-up") is achieved. Note that if the first optional waiting period is included, then a second waiting period, typically also of duration R , may be provided after detecting the start signal and before enabling the transmitter. The second waiting period allows for communicating over channels of less than the maximum length. Otherwise data could be lost, since the transceiver at the other end of the channel is then disabled from receiving during its first optional waiting period, in order to allow the reflection to be ignored at the far end in a comparable manner as above. By making the second optional waiting period to be equal to the first, it is not necessary to specify a minimum length for the channel.

An exemplary embodiment of the present technique using optical transceivers is shown in FIG. 3. In this embodiment, each transceiver utilizes a single light emitting diode (the "diode") for both transmitting optical signals, and also for receiving optical signals, by employing the diode as a photodetector, according to principles known in the art. Alternately, a separate optical source (e.g., laser or light emitting diode) may be used with a separate photodetector (e.g., pin diode, avalanche diode, phototransistor, etc.) by means of an optical coupler, according to principles known in the art. The two transceivers communicate via an optical fiber channel.

The analog receiver amplifies the electrical signals from the diode during reception of optical signals, and supplies the amplified signal to the digital receiver, which is under the control of the protocol controller. The digital receiver operates on the data packets received, and converts the packets to a form suitable to the user via the "data out" line, along with a control signal to indicate the reception of the word. For example, if the user data is oversampled and encoded, then the digital receiver may convert the data back to its original form.

A digital transmitter, also under the control of the protocol controller, receives data and control signals from a desired data source, and provides suitably formatted data packets to the analog transmitter. The analog transmitter provides sufficient current amplification to drive the diode so as to generate the optical signal for transmission. A time base oscillator provides timing signals, and a randomizer circuit increases the randomness of the listening period over the randomness of the local time base, as discussed below. As indicated, in a typical case, all of the circuitry, with the exception of the diode (and quartz crystal - not shown), is located on a single integrated circuit. However, it may be advantageous in some cases to integrate the analog portions of the circuitry on one integrated circuit, and the digital portions on another integrated circuit, to allow for optimized processing for each.

In order to implement a RS232 transceiver, suitable system parameters to obtain a 19.2 kilobit/second user data rate are as follows:

1. User data (at 19.2 kilobits/second) is sampled at 397.7 kilobits/second.
2. A group of 31 samples is encoded into each packet.
3. Optical coding is non return to zero (NRZ).
4. Packet size is 13 bits, including a start bit, a stop bit, 2 control bits, and 9 data bits.
5. The optical transmission and reception rates are 596.59 kilobits/second.
6. The time base oscillator operates at 14.31818 MHz.
7. The maximum optical fiber propagation delay (A) is assumed to be 5 microseconds, providing for a maximum fiber length of about 1 kilometer.
8. The waiting time (R) for echo suppression is 10.057 microseconds (i.e., about $2A$).
9. The duration of an optical packet is 21.79 microseconds.

The protocol controller implements the protocol shown in FIG. 2 by control signals as follows:

ARS Analog Receive Set: When this line is high the receiver is in its active state ready to receive data from the diode. When ARS is low then the receiver is in a state where it holds the receive

detection threshold to avoid having it upset by the much larger transmit signals.

Link Status: This line goes high to signify that communications has been established. When Link Status is high then it will go low if a packet is not received within the listening period.

RC Receive Control: This line goes high to enable the Digital Receiver. When low, it clears the circuitry of the Digital Receiver. When the Protocol Controller sees that RO has gone high (signifying that the Digital Receiver has received a data packet from the fiber) then RC will go low after about 10 μ S. This delay allows sufficient time for the packet to be decoded and loaded into the 31 bit receiver register.

RO Receive Over: The Digital Receiver causes this line to go high immediately after it has received a valid packet from the fiber. RO can only go high when RC is high.

XC Transmit Control: This line goes high to enable the Digital Transmitter. It is actually the clear control for the blocks within the Digital Transmitter. When the Protocol Controller sees that XO has gone high (signifying that the Digital Transmitter is finished) then XC will go low after a period defined by the time base (139.7 nanoseconds).

XO Transmit Over: The Digital Transmitter causes this line to go high only after it has finished sending a packet of data onto the fiber. XO can only go high when XC is high.

According to the preferred embodiment, each transceiver includes a randomizer circuit. This substantially increases the random variation of the listening time from one transceiver to another, as compared to the random variation due to the local time base, but without affecting the frequency of the local time base. A suitable circuit is shown in FIG. 4, wherein the well-known variability of the characteristics of field effect transistors is used for this purpose. The power supply voltage is imposed across series connected devices M1 and M2, which are gate-drain shorted. Transistors M2-M3 and M4-M5 form a current mirror that divides the current I1 to a smaller value. When the "control line", under the control of a clock referenced to the time base, goes high, the listening period is initiated, and M6 is turned off. This allows the small current through M5 to charge the capacitor C1 (about 20 picofarads), causing the voltage on node S to decrease. When node S reaches the switching threshold of inverter INV3, the "out" line goes high, which terminates the listening period. (A clock derived from the time base provides for the above-noted minimum delay of $2A + P$ if the random delay is less than this minimum value). The randomness of the delay from control line high to out high is due in part to the variation in the capacitance of C1, and especially the variability of the transcon-

ductances of transistors M1 and M2. This variability is relatively large in standard integrated circuit manufacturing processes. In addition, the circuit provides a high variability of delay due to changes in the power supply voltage, and also temperature. The delay ranges from about 100 microseconds to 2 milliseconds over expected variations in manufacturing tolerances, temperature, and power supply voltage. Other randomizing circuits may be used, or a pseudo-random number generator may be used for the randomizing function. Additionally, relying on electrical noise (e.g., a noisy diode) may provide this function, with still other techniques possible.

Note that although the exemplary embodiment has illustrated signals in multiple-bit packets having equal bit lengths, it is alternately possible to employ packets having different bit lengths. For example, if information traffic is heavier in a given direction, then a larger transmit packet (i.e., having more bits) may be used in that direction. It is also possible to dynamically alter the packet length, to optimize the information carrying capacity of the system as the information load changes. On the other hand, in very simple, low-cost systems, the transceivers may employ only a single bit packet. For example, pulse width modulation may be used, wherein a logic "1" is represented by a signal having a given duration (e.g., one microsecond), and a logic "0" is represented by a signal having another duration (e.g., two microseconds). In this manner, the absence of any signal on the channel can be recognized by either transceiver as the "link down" condition. The next received signal (either a "1" or "0") may then be used as the start signal in the startup procedure noted above. It is also possible that the startup signal may be a multiple-bit packet having a different number of bits than an information bit packet. For example, if the information packet has a large number of bits, it may be more efficient to use a start packet having fewer bits, to reduce the average required startup time. Furthermore, the use of a fixed length start packet may be useful in facilitating start-up when the information packets are of variable length, as noted above. Although the start signal illustrated above includes start and stop bits in a packet, the start signal may be readily implemented with Manchester encoded data by recognizing a 0 to 1 transition, without the inclusion of a stop bit. Other start signal schemes are also possible.

Means may also be included in the transceiver to determine the actual propagation time (a) for the channel in use (as opposed to the assumed maximum time A), and adjust the length of the information packet, or period between packets accordingly, after start-up is achieved. Also, once the link is established, a measure of the actual propagation

time (a) may advantageously be used to keep the receiver of a given transceiver disabled following a transmission by its transmitter until just prior to the time a return packet (from the other transceiver) is expected. This reduces the possibility that noise will be mistaken for an information signal. While a given transceiver may be designated to work with a channel having a given maximum propagation time (A), this need not be the case. For example, a channel of arbitrary length may be used, with the transceiver data rate from the user being reduced accordingly as the channel length (and propagation time) increases. This may be accommodated automatically if desired by sending a signal to the near-end user when a return packet is received from the far end. Finally, on long channels, it is possible for two or more packets to be propagating simultaneously on the channel. This is useful, for example, when the propagation delay is long compared to the packet duration (P), and/or long compared to the time required for a transceiver to switch between transmit and receive. For such long channels, the minimum listening period is then desirably less than $2A + P$.

Claims

1. A transceiver adapted to communicate over a channel, said transceiver comprising a transmitter ("DIGITAL TRANSMITTER"; "ANALOG TRANSMITTER") adapted to transmit information at a rate controlled by a local time base ("TIME BASE"), a receiver ("DIGITAL RECEIVER"; "ANALOG RECEIVER") adapted to receive information, and optional means for providing an optional waiting period (R) that allows for at least one reflection due to the transmitted information to be ignored, CHARACTERISED BY means for transmitting an outgoing start signal, means for determining whether an incoming start signal is received within a listening period having a duration L that follows said transmitting and optional waiting period, means for terminating said listening period prior to L if an incoming start signal is received, and means for causing said transmitter to again transmit an outgoing start signal if an incoming start signal is not received within said listening period, wherein said listening period is a random variable that ranges within desired limits.
2. A transceiver as claimed in claim 1 comprising means for deriving from said local time base a minimum value for said listening period.
3. A transceiver as claimed in claim 2 wherein said minimum value is at least the duration of said incoming start signal.

4. A transceiver as claimed in claim 3 adapted to communicate over a channel having a maximum propagation time (A), and wherein said minimum value is the duration of said incoming start signal plus twice said maximum propagation time of said channel.
5. A transceiver as claimed in claim 1, 2, 3 or 4 comprising a randomizing means ("RANDOMIZER") that substantially increases the randomness of the listening period without affecting the frequency of said local time base.
6. A transceiver as claimed in claim 1, 2, 3 or 4 wherein said listening period depends primarily on the frequency of said local time base.
7. A transceiver as claimed in any preceding claim wherein said means for transmitting a start signal is adapted to transmit a multi-bit packet having a given bit pattern, and said means for determining whether an incoming start signal is received is adapted to recognize said given bit pattern.
8. A transceiver as claimed in any preceding claim wherein the duration of said outgoing start signal is equal to the duration of said incoming start signal.

Patentansprüche

1. Sendeempfänger zur Kommunikation über einen Kanal mit einem Sender ("Digitaler Sender", "Analoger Sender") zur Übertragung von Informationen mit einer Rate, die durch eine örtliche Zeitbasis ("Zeitbasis") gesteuert wird, einem Empfänger ("Digitaler Empfänger", "Analoger Empfänger") zum Empfang von Informationen und als Option einer Einrichtung zur Bereitstellung einer optionalen Warteperiode (R), die die Möglichkeit gibt, wenigstens eine Reflexion aufgrund der ausgesendeten Informationen nicht zu beachten, gekennzeichnet durch eine Einrichtung zur Aussendung eines abgehenden Startsignals, eine Einrichtung zur Feststellung, ob ein ankommendes Startsignal innerhalb einer Empfangsbereitschaftsperiode mit einer Dauer L empfangen wird, die der Aussendung und der optionalen Warteperiode folgt, eine Einrichtung zur Beendigung der Empfangsbereitschaftsperiode vor der Dauer L, wenn ein ankommendes Startsignal empfangen wird und eine Einrichtung, die den Sender veranlaßt, erneut ein abgehendes Startsignal auszusenden.



time (a) may advantageously be used to keep the receiver of a given transceiver disabled following a transmission by its transmitter until just prior to the time a return packet (from the other transceiver) is expected. This reduces the possibility that noise will be mistaken for an information signal. While a given transceiver may be designated to work with a channel having a given maximum propagation time (A), this need not be the case. For example, a channel of arbitrary length may be used, with the transceiver data rate from the user being reduced accordingly as the channel length (and propagation time) increases. This may be accommodated automatically if desired by sending a signal to the near-end user when a return packet is received from the far end. Finally, on long channels, it is possible for two or more packets to be propagating simultaneously on the channel. This is useful, for example, when the propagation delay is long compared to the packet duration (P), and/or long compared to the time required for a transceiver to switch between transmit and receive. For such long channels, the minimum listening period is then desirably less than $2A + P$.

Claims

1. A transceiver adapted to communicate over a channel, said transceiver comprising a transmitter ("DIGITAL TRANSMITTER"; "ANALOG TRANSMITTER") adapted to transmit information at a rate controlled by a local time base ("TIME BASE"), a receiver ("DIGITAL RECEIVER"; "ANALOG RECEIVER") adapted to receive information, and optional means for providing an optional waiting period (R) that allows for at least one reflection due to the transmitted information to be ignored, CHARACTERISED BY means for transmitting an outgoing start signal, means for determining whether an incoming start signal is received within a listening period having a duration L that follows said transmitting and optional waiting period, means for terminating said listening period prior to L if an incoming start signal is received, and means for causing said transmitter to again transmit an outgoing start signal if an incoming start signal is not received within said listening period, wherein said listening period is a random variable that ranges within desired limits.
2. A transceiver as claimed in claim 1 comprising means for deriving from said local time base a minimum value for said listening period.
3. A transceiver as claimed in claim 2 wherein said minimum value is at least the duration of said incoming start signal.

4. A transceiver as claimed in claim 3 adapted to communicate over a channel having a maximum propagation time (A), and wherein said minimum value is the duration of said incoming start signal plus twice said maximum propagation time of said channel.
5. A transceiver as claimed in claim 1, 2, 3 or 4 comprising a randomizing means ("RANDOMIZER") that substantially increases the randomness of the listening period without affecting the frequency of said local time base.
6. A transceiver as claimed in claim 1, 2, 3 or 4 wherein said listening period depends primarily on the frequency of said local time base.
7. A transceiver as claimed in any preceding claim wherein said means for transmitting a start signal is adapted to transmit a multi-bit packet having a given bit pattern, and said means for determining whether an incoming start signal is received is adapted to recognize said given bit pattern.
8. A transceiver as claimed in any preceding claim wherein the duration of said outgoing start signal is equal to the duration of said incoming start signal.

Patentansprüche

1. Sendeempfänger zur Kommunikation über einen Kanal mit einem Sender ("Digitaler Sender", "Analoger Sender") zur Übertragung von Informationen mit einer Rate, die durch eine örtliche Zeitbasis ("Zeitbasis") gesteuert wird, einem Empfänger ("Digitaler Empfänger", "Analoger Empfänger") zum Empfang von Informationen und als Option einer Einrichtung zur Bereitstellung einer optionalen Warteperiode (R), die die Möglichkeit gibt, wenigstens eine Reflexion aufgrund der ausgesendeten Informationen nicht zu beachten, gekennzeichnet durch
eine Einrichtung zur Aussendung eines abgehenden Startsignals,
eine Einrichtung zur Feststellung, ob ein ankommendes Startsignal innerhalb einer Empfangsbereitschaftsperiode mit einer Dauer L empfangen wird, die der Aussendung und der optionalen Warteperiode folgt,
eine Einrichtung zur Beendigung der Empfangsbereitschaftsperiode vor der Dauer L, wenn ein ankommendes Startsignal empfangen wird und
eine Einrichtung, die den Sender veranlaßt, erneut ein abgehendes Startsignal auszusenden.



den, wenn kein ankommendes Startsignal innerhalb der Empfangsbereitschaftsperiode empfangen wird, wobei die Empfangsbereitschaftsperiode eine Zufallsvariable ist, die sich innerhalb gewünschter Grenzen bewegt.

2. Sendeempfänger nach Anspruch 1 mit einer Einrichtung, die aus der örtlichen Zeitbasis einen Minimalwert für die Empfangsbereitschaftsperiode ableitet. 10
3. Sendeempfänger nach Anspruch 2, bei dem der Minimalwert wenigstens gleich der Dauer des ankommenden Startsignals ist. 15
4. Sendeempfänger nach Anspruch 3 zur Kommunikation über einen Kanal mit einer maximalen Laufzeit (A), wobei der Minimalwert gleich der Dauer des ankommenden Startsignals zuzüglich der doppelten maximalen Laufzeit des Kanals ist. 20
5. Sendeempfänger nach Anspruch 1, 2, 3 oder 4 mit einer Einrichtung zur Zufallsverteilung ("Zufallsverteiler"), die die Zufallsverteilung der Empfangsbereitschaftsperiode wesentlich erhöht, ohne die Frequenz der örtlichen Zeitbasis zu beeinflussen. 25
6. Sendeempfänger nach Anspruch 1, 2, 3 oder 4, bei dem die Empfangsbereitschaftsperiode in erster Linie von der Frequenz der örtlichen Zeitbasis abhängt. 30
7. Sendeempfänger nach einem der vorhergehenden Ansprüche, bei dem die Einrichtung zur Aussendung eines Startsignals ein Mehrbitpaket mit einem gegebenen Bitmuster aussenden kann und die Einrichtung zur Feststellung, ob ein ankommendes Startsignal empfangen wird, das gegebene Bitmuster erkennen kann. 40
8. Sendeempfänger nach einem der vorhergehenden Ansprüche, bei dem die Dauer des abgehenden Startsignals gleich der Dauer des ankommenden Startsignals ist. 45

Revendications

1. Un émetteur-récepteur conçu pour communiquer au moyen d'un canal, cet émetteur-récepteur comprenant un émetteur ("EMETTEUR NUMERIQUE"; "EMETTEUR ANALOGIQUE") conçu pour émettre de l'information avec un débit qui est commandé par une base de 55

temps locale ("BASE DE TEMPS"), un récepteur ("RECEPTEUR NUMERIQUE"; "RECEPTEUR ANALOGIQUE") conçu pour recevoir de l'information, et des moyens facultatifs pour établir une période d'attente facultative (R) qui permet de ne pas prendre en compte au moins une réflexion qui résulte de l'information émise, CARACTERISE PAR des moyens pour émettre un signal ce début sortant, des moyens pour déterminer si un signal de début entrant est reçu pendant une période d'écoute ayant une durée L qui suit la période d'émission et d'attente facultative, des moyens pour mettre fin à la période d'attente avant L si un signal de début entrant est reçu, et des moyens pour faire en sorte que l'émetteur émette à nouveau un signal de début sortant si un signal de début entrant n'est pas reçu pendant la période d'attente, cette période d'attente étant une variable aléatoire qui est comprise entre des limites désirées.

2. Un émetteur-récepteur selon la revendication 1, comprenant des moyens pour élaborer, à partir de la base de temps locale, une valeur minimale pour la période d'attente.
3. Un émetteur-récepteur selon la revendication 2, dans lequel la valeur minimale est au moins égale à la durée du signal de début entrant.
4. Un émetteur-récepteur selon la revendication 3, conçu pour communiquer au moyen d'un canal ayant un temps de propagation maximal (A), et dans lequel la valeur minimale précitée est la durée du signal de début entrant, plus deux fois le temps de propagation maximal de ce canal.
5. Un émetteur-récepteur selon la revendication 1, 2, 3 ou 4, comprenant des moyens de randomisation ("CIRCUIT DE RANDOMISATION") qui augmentent notablement le caractère aléatoire de la période d'écoute, sans affecter la fréquence de la base de temps locale.
6. Un émetteur-récepteur selon la revendication 1, 2, 3 ou 4, dans lequel la période d'écoute dépend essentiellement de la fréquence de la base de temps locale.
7. Un émetteur-récepteur selon l'une quelconque des revendications précédentes, dans lequel les moyens destinés à émettre un signal de début sont conçus pour émettre un paquet à plusieurs bits ayant une configuration de bits donnée, et les moyens destinés à déterminer si un signal de début entrant est reçu, sont



conçus pour reconnaître cette configuration de bits données.

8. Un émetteur-récepteur selon l'une quelconque des revendications précédentes, dans lequel la durée du signal de début sortant est égale à la durée du signal de début entrant.

5

10

15

20

25

30

35

40

45

50

55