

A Method of Fabricating Tunnel Transistors with Abrupt Junctions

CROSS-REFERENCE TO RELATED APPLICATIONS

0001 The present application claims the benefits of United States patent application S/N: 13/459278 entitled "A Method of Fabricating Tunnel Transistors with Abrupt Junctions", filed April 30, 2012, the content of which is incorporated herein by reference in its entirety.

FIELD OF THE INVENTION

0002 The present invention relates to semiconductor devices, and more particularly, to junction tunnel transistors (TFETs) with controllable gate overlap and abrupt junctions as part of a replacement gate process flow and a method of manufacturing the same.

BACKGROUND OF THE INVENTION

0003 Tunnel FETs have shown to be an alternative transistor design applicable to very low voltage operations. TFETs are a different type of transistor than conventional, thermal MOSFETs, because in TFETs a tunnel energy barrier is modulated at the source region, as opposed to a thermal barrier at the source region. It is the modulation of this tunnel barrier (in particular, a band-to-band tunnel (BTBT) barrier) which results in a drain-current-to-gate-voltage sensitivity (i.e., sub-threshold swing or SS) which can be superior to that in thermal MOSFETs. In thermal MOSFETs, the thermal limit for SS is defined as $n \cdot k \cdot T \cdot \ln(10)$, where k is Boltzman's constant, T is the temperature (in Kelvin scale), and n is the ideality factor (greater than or equal to 1, but ideally 1). Under ideal conditions at room temperature, the SS limit for thermal MOSFETs is 60 mV/decade, i.e., the minimum change in gate bias needed to increase the drain current by a factor of 10 is 60 mV. Any device that can offer a room temperature SS limit below 60 mV/decade will permit scaling down the transistor threshold voltage (V_t), and therefore the power supply voltage (V_{DD}) without increasing the off-state leakage current. This is desirable from a circuit design standpoint, since V_{DD} scaling reduces dynamic power

consumption while keeping the off-state leakage constant results in no increase in standby power consumption.

- 0004 TFETs of various designs have achieved both in theory and in practice SS values below 60 mV/dec. This is accomplished by leveraging the energetic distribution of tunnel carriers between the conduction and valence band edges. In order to obtain BTBT, the conduction band of one portion of the device must exist at a lower energy than the valence band of another portion. This is referred to as band edge overlap. The extent of this band edge overlap defines the energy range over which carriers can tunnel between the conduction and valence bands in these regions. The energetic distribution of the tunnel carriers plays a major role in determining SS, since the low SS achieved in TFETs is defined by the transition between zero or negative band edge overlap (i.e., zero BTBT) and some finite band edge overlap (i.e., finite BTBT). This can be engineered through the use of different materials (e.g., Si, Ge, III-V) and/or geometries (e.g., 1-D, 2-D, or 3-D density of states).
- 0005 A conventional Ge source region achieving sub-60 mV/dec SS in a TFET structure has been empirically demonstrated and shown to significantly improve the performance over prior work due to a reduced bandgap of Ge relative to Si or SiGe. The placement of the Ge source under the gate electrode has been shown by performing an isotropic etch to undercut the gate followed by a Ge deposition to fill the etched region. The limitation of the improvement is mainly related to the use of an isotropic etch to undercut the gate electrode. Since it is desirable to place the Ge directly under the gate dielectric, the gate dielectric ends up being exposed to the isotropic etch, exposing to damage the gate dielectric and lead to high gate leakage. Additionally, there is also a challenge of accurately controlling the undercut etch, since the extent of gate overlap of the Ge source region will determine how much BTBT can be modulated. This tends to occur when the design is a “vertical” TFET (also referenced to a transverse TFET) due to most of the BTBT current flowing in a direction that is transverse to the gate electrode over the source region. In such a design, the total BTBT current is linearly proportional to the extent of gate overlap of the source region.

0006 The concept of a broken-gap TFET has been introduced to effectively engineer the materials on both sides of the BTBT barrier such that a band edge offset exists in equilibrium (i.e., without any gate bias-induced band edge offset), known as a type-III junction. In this particular design, the broken gap region exists at a distance sufficiently away from the gate electrode such that it is not under the influence of the gate electrode. The purpose thereof is to create a TFET structure wherein SS is independent of gate bias, unlike the aforementioned illustration wherein SS changes with the gate bias. Engineering the BTBT barrier effectively is not easily achieved in order to obtain that the tunnel probability in the band edge overlap region be effectively 100%. The remainder of the device is preferably a conventional thermal MOSFET, and such that the structure as a whole is basically a source-limited thermal MOSFET, wherein the thermal barrier modulated by the gate electrode controls the portion of the energetic distribution of carriers injected at the source BTBT barrier. This achieves a very steep SS over several decades of current when compared to the performance of similarly-scaled thermal MOSFETs. The limitation of this embodiment is that no integration scheme is forthcoming for actually building the device.

0007 Conventional TFETs with doped regions have been shown to be formed vertically rather than laterally, (horizontally) as known, for instance in typical MOSFETs, with the gate electrode wrapping around the sidewall regions. A delta-doped p⁺ SiGe layer exists between the p⁺ Si source and undoped body regions to facilitate a BTBT injection, and therefore improving the performance. An advantage is that the doped regions can be arbitrarily thick or thin and defined precisely by epitaxial growth. The limitation with this device structure is the same as with all other “vertical” transistor designs, wherein the gate-to-source parasitic capacitance is very high, due to the gate electrode and source regions both covering the same, large, area.

0008 The use of a raised Ge source in a TFET structure is known. The operational concept is the same as previously described except that here, employing a raised source offers a few advantages. Firstly, the presence of the bottom gate corner adjacent to the raised source improves the device electrostatics by suppressing drain field penetration into the gate-induced depletion region in the source (wherein BTBT occurs). Secondly, by using a raised source, precludes the need to use of a required isotropic etch, and so the gate-to-source overlap can be

more accurately controlled with epitaxy. However, this structure is limited by the described integration scheme, wherein the Ge epitaxy is formed against the dielectric sidewall region. It is well-known that semiconductor epitaxy against a dielectric sidewall (e.g., raised source/drain epitaxy in conventional MOSFETs) results in faceting and reduced epitaxial film quality along the dielectric sidewall. In the context of a TFET, this will lead to a significant degradation in performance due to the presence of crystalline defects in the epitaxial region.

- 0009 Referring to FIG. 1a, a planar TFET structure is illustrated operating in a “vertical” (also referred to as transverse) mode. The source and drain regions can be oppositely doped, and the body region doped to the same polarity as the source region. For example, for an n-type TFET, the source and body can be p-type and the drain, n-type. If the source is doped “low” (e.g., $1\text{E}19\text{ cm}^{-3}$), and the body is doped “high” (e.g., $1\text{E}18\text{ cm}^{-3}$), then the dominant BTBT direction will be vertical, or transverse to the gate dielectric boundary to the source.
- 0010 Referring to FIG. 1b, if the source is doped heavily (e.g., $1\text{E}20\text{ cm}^{-3}$) and the body is doped lightly, (e.g., $1\text{E}16\text{ cm}^{-3}$), then the dominant BTBT direction will be “lateral” (also referenced as longitudinal), or in the direction of the current flow in the channel under the gate dielectric. This is caused by the relative doping levels in the source and body regions that determine which BTBT mode turns on first. With high source doping and low body doping, the lateral BTBT threshold voltage (V_t) will be lower, while the vertical BTBT V_t will be higher, leading to a lateral-BTBT dominated mode of operation, and vice versa.
- 0011 The lateral and vertical terminologies are only accurate for simple, planar structures. However, when the source region becomes elevated, the orientation of BTBT is altered, since now it is the gate sidewall that controls the BTBT current. This is illustrated with reference to FIG. 1c, wherein the tunnel mode is transverse (as in FIG. 1a), but the tunnel direction is lateral (as in FIG. 1b). The tunnel mode being an essential feature of the type of the TFET, the mode of operation is therefore defined as either transverse (i.e., “vertical” in a planar structure) or longitudinal (i.e., “lateral” in a planar structure).

0012 Although TFETs are known in the art, there is a need for a structure provided with an intrinsic epitaxial layer bridging the source, body and drain regions (p-i-n junctions) of the device structure.

BRIEF DESCRIPTION OF THE DRAWINGS

- 0013 The accompanying drawings, which are incorporated in and which constitute part of the specification, illustrate the presently preferred embodiments of the invention which, together with the general description given above and the detailed description of the preferred embodiments given below serve to explain the principles of the, wherein like reference numerals denote like elements and parts, in which:
- 0014 FIG. 1a is cross-sectional view illustrating a prior art BTBT occurring “vertically” i.e., transverse to the gate dielectric boundary to the source of the TFET;
- 0015 FIG. 1b shows a cross-sectional side view illustrating a prior art BTBT occurring “laterally” i.e., in the longitudinal current flow direction;
- 0016 FIG. 1c shows a cross-sectional side view depicting a prior art BTBT occurring “laterally” but transverse to the gate dielectric;
- 0017 FIG 2 is a side cross-sectional view depicting a p-type substrate superimposed by an epitaxial growth of p⁺ source material;
- 0018 FIG. 3 is a side cross-sectional view showing a dummy gate stack surrounded by a spacer on top of the epitaxial layer;
- 0019 FIGs. 4a – 4c show side cross-sectional views illustrating the drain region etched away and filled with in-situ doped n⁺ epitaxial material;
- 0020 FIG. 5 shows a cross-sectional view depicting an interlayer dielectric (ILD) deposited and planarized;
- 0021 FIGs. 6a-6d depict side cross-sectional views illustrating the removal of the dummy gate stack followed by etching a cavity, and more particularly, showing four examples respectively depicting anisotropic, isotropic, and two sigma-shaped cavities;
- 0022 FIGs. 7a-7d are side cross-sectional views of the channel epitaxially grown within the etch cavity.

- 0023 FIGs. 8a-8d show side cross-sectional diagrams of an embodiment showing a final view of the device, wherein in the last step, a high-k/metal gate stack is first deposited and subsequently planarized, wherein the direction of the BTBT current is shown transverse to the gate electrode over the source region.
- 0024 FIGs. 9a-9d illustrate side cross-sectional diagrams of the final views of the device shown in FIGs. 8a-8d that include each current flow vector -- shown by arrows from the source to the channel region in a direction transverse to the gate electrode.

SUMMARY

- 0025 In one aspect, an embodiment of the invention provides a method of forming a TFET device having a thin epitaxial layer bridging the source, body and drain regions (p-i-n junctions) that provides a thin barrier between the N⁺ and P⁺ regions, with the thin epitaxial layer being modulated by the gate.
- 0026 In another aspect, an embodiment of the invention provides two types of TFET designs, i.e., "vertical" TFETs and "lateral" TFETs, respectively referenced to the more accurate terminology of "transverse" TFETs and "longitudinal" TFETs.
- 0027 In a further aspect, an embodiment of the invention provides leveraging the replacement gate, or "gate last" process flow forming a self-aligned etch cavity directly under the gate electrode, wherein an epitaxial layer is formed along the source/drain sidewall.
- 0028 In still another aspect, an embodiment describes tuning the crystal direction in which BTBT takes place by varying the shapes of the self-aligned etch cavity, and wherein in view of different crystal directions having a different effective tunnel mass, the crystal direction can be tuned depending on the materials used in the BTBT region.
- 0029 In yet a further aspect, in an embodiment, P⁺ and N⁺ regions and intrinsic/lightly-doped regions are formed defining the TFET source, body, and drain regions using epitaxy, implant, or any combination thereof, abutting to a structure having the intrinsic/lightly-doped region separating the P⁺ from the N⁺ regions.

- 0030 In still a further aspect, in an embodiment, a MESA etch defines the shape of the TFET channel region, preferably during a replacement gate process, e.g., metal replacement, wherein the dummy gate region determines the length and width of the MESA etch cavity.
- 0031 In yet a further aspect, a channel region is grown epitaxially over the TFET structure, covering at least the source region (i.e, the P+ region for an N-type TFET, or the N+ region for a P-type TFET). The epitaxial channel region can be doped or undoped.
- 0032 In another aspect, an embodiment provides a method of manufacturing a TFET that includes forming on a substrate covered by an epitaxial growth of source material a dummy gate stack surrounded by sidewall spacers; forming doped source and drain regions followed by an inter-layer dielectric surrounding the sidewall spacers; removing the dummy gate stack, etching a self-aligned cavity; epitaxially growing a thin channel region within the self-aligned etch cavity; and conformally depositing gate dielectric and metal gate materials within the self-aligned etch cavity.
- 0033 In still another aspect, an embodiment of the invention provides a tunnel field effect transistor (TFET) that includes a p+ source region for n-type TFET or n+ source region for p-type TFET; an n+ drain region for n-type TFET or p+ drain region for p-type TFET; a body region that is either intrinsic or doped, with a doping concentration less than that of the source region, separating the p+ and n+ source/drain regions; a self-aligned etch cavity separating the p+ and n+ source/drain regions; a thin epitaxial channel region that is grown within the self-aligned etch cavity, covering at least the source region; a replacement gate stack comprising a high-k gate dielectric and one or a combination of metals; and sidewall spacer regions adjacent to the replacement gate stack.

DETAILED DESCRIPTION

- 0034 Detailed embodiments of the methods and structures of the present disclosure are described herein; however, it is to be understood that the disclosed embodiments are merely illustrative of the described methods and structures that can be embodied in various forms. In addition,

each of the examples given in connection with the various embodiments of the disclosure is intended to be illustrative, and not restrictive. Further, the FIGs. are not necessarily to scale, some features can be exaggerated to show details of particular components. Therefore, specific structural and functional details disclosed herein are not to be interpreted as limiting, but merely as a representative basis for teaching one skilled in the art to variously employ the methods and structures of the present disclosure. For purposes of the description hereinafter, the terms "upper", "lower", "top", "bottom", and derivatives thereof shall relate to the disclosed structures, as they are oriented in the drawing FIGs.

- 0035 The process described herein illustrates an n-type TFET process flow (i.e, NMOS-like). However, p-type TFETs (i.e, PMOS like) can be formed in the same manner, with the exception of using different bandgap engineered materials for the source, channel, and drain regions.
- 0036 Referring to FIG. 2, a substrate (200) is shown upon which an epitaxial layer (220) is grown that ultimately defines the source material. For an n-type TFET, the preferable source material has a valence band edge offset to the channel material such that the valence band edge energy in the source material is higher than that in the channel, wherein a conduction band edge offsets such that the conduction band edge energy in the channel material is lower than that in the source material. An illustrative material of choice includes silicon germanium (SiGe) or pure germanium. Pure germanium has an electron affinity of 4 eV and a bandgap of 0.66 eV. SiGe has an electron affinity between 4 eV and 4.05 eV and a bandgap between 0.66 eV and 1.12 eV (depending on the Ge content). The thickness of the epitaxial layer ranges from 5 to 20nm.
- 0037 Referring to FIG. 3, a dummy gate stack (310) and sidewall spacers (320) are obtained by first growing or depositing a dummy gate dielectric (e.g., silicon dioxide with a preferred thickness of 3nm, sufficient to act as an etch stop layer or endpoint detection layer when the dummy gate stack is patterned). This is followed by a deposition of the dummy gate material (typically polysilicon, with a thickness of the order of 50nm). Next, the aforementioned step is followed by the deposition of a capping layer over the dummy gate material (typically silicon nitride,

with a thickness on the order of 30nm). All three layers described thus far are shown for illustrative purposes only as one layer. The dummy gate stack is then patterned by lithography, and subsequently etched in conformity with the lithographically defined pattern. Then, sidewall spacer material (typically silicon nitride, with a thickness on the order of 10nm) is deposited and anisotropically etched.

- 0038 Referring to FIGs. 4a-4c, the drain region is formed in one embodiment, using conventional ion implant/anneal processing, or alternatively, the drain region selectively etched away and filled in with in-situ doped n⁺ epitaxial material. The latter approach is preferred and is shown to avoid excessive thermal processing which can otherwise relax any strain between the epitaxial layers and the underlying substrate (which could lead to crystalline defects). The recess etch shape of the drain region can take any shape by undercutting the drain-side sidewall spacer that protrudes under the dummy gate stack. In view of the self-aligned cavity etching (hereinafter in the process flow), the drain region is exposed, extending from under the dummy gate stack and ending into the source region.
- 0039 Referring to FIG. 4a, an etch mask (410) (e.g., silicon dioxide) is deposited and patterned such that the source side of the TFET is covered, leaving the drain side (430) of the TFET exposed. Subsequently, a recess etch is performed into the drain side of the TFET. The recess etch is shown in FIG. 4b as having preferably the same depth (440) as the epitaxial source material, but can be any depth greater or equal thereto. To achieve an undercut (450) in the recess etch profile such that the bottom of the dummy gate partially overlaps the recess etch profile, an isotropic reactive ion etch (RIE) or a wet etch or a combined thereof can be performed, using a chlorine-based or fluorine based plasma as reactive species.
- 0040 Still referring to FIG. 4b, the drain region is preferably epitaxially grown. The thickness of the layer (460) can be greater than or equal to the thickness of the recess etch depth. In an embodiment of an n-type TFET, in-situ doped SiP or SiCP can be used to form the n⁺ drain region.

- 0041 Referring to FIG. 4c, the etch mask is removed from the structure. If the etch mask (410) is made of silicon dioxide, the etch mask can be removed selectively using a wet HF etch.
- 0042 Referring now to FIG. 5, an interlayer dielectric (ILD) layer (510) is deposited and planarized. The ILD material preferably used includes silicon dioxide and/or silicon nitride. A chemical mechanical planarization (CMP) is preferably employed to planarize both the ILD and the gate stack, exposing the dummy gate material (polysilicon in this example) within the gate stack. Also shown, are the source region (530) and the drain region (520).
- 0043 Referring to FIGs. 6a-6d, the dummy gate (310, FIG. 3) is preferably removed by a combination of wet and/or dry etching (e.g., anisotropic RIE selective to polysilicon, followed by an ammonium hydroxide wet etch to remove residual polysilicon), and forming a cavity. Four non-limiting examples are depicted in FIG. 6a, for an anisotropic recess etch, an isotropic recess etch (FIG. 6b), and sigma-shaped (i.e, sigma etch 1 and sigma etch 2) cavities (FIGs. 6c and 6d). Each etch shape results in an etch surface with different exposed crystal planes. Depending on the materials used and the direction of effective mass anisotropy, a different set of crystal planes will be optimal for maximizing BTBT current and therefore TFET drive current. Moreover, corner regions in the anisotropic and sigma recess etches confine the drain voltage drop to take place between the corner regions and the drain terminal. This results in a uniform surface potential along the BTBT perimeter at the source/channel junction caused at the corner regions, the inversion charge is at a lower concentration than in the “planar” regions due to electric field dilution from the inside of the corner region and extending outward toward the channel. This creates regions of higher resistance wherein some or a majority of the drain voltage is dropped, reducing the drain voltage drop across the source region. If this effect does not take place (e.g., for a planar TFET, FIGs. 1a-1c), then there will be a drain-bias-induced potential distribution throughout the source, which leads to a non-uniform transverse electric field distribution within the source. This, in turn, leads to an operational mode wherein some fraction of the BTBT is transverse while the other fraction is longitudinal. Since the transverse and longitudinal modes have a different V_t , the net result is a degradation in SS and therefore drive current at the same off-state leakage. Thus, the anisotropic and sigma etches are preferred for maximizing the TFET performance.

- 0044 Referring to FIG. 6a, anisotropic etching can be realized by using a HBr (hydrogen bromide) based RIE. The depth of the recess cavity is preferably greater than the thickness of the epitaxial source material, and can be on the order of 50nm.
- 0045 Referring to FIG. 6b, a chlorine-based plasma etch can be utilized to form the isotropic etch cavity. Again, the depth of the etch cavity is preferably greater than the thickness of the epitaxial source material.
- 0046 Referring to FIG. 6c, the sigma shape can be formed by a combination of RIE and wet etching. For example, HBr-based RIE can be performed to create an initial etch cavity, similar to the anisotropic etch cavity in FIG. 6a but with a smaller etch depth. Alternately, a Chlorine or Fluorine based isotropic RIE can be performed to create an initial etch cavity, similar to the isotropic etch cavity (FIG. 6b), but with a smaller etch depth. Either one of these can have an etch depth on the order of 5-10nm, and followed by a wet etch in ammonium hydroxide to form the final sigma shape shown. The depth of the initial RIE etch profile determines the placement of the sigma corner regions extending under/past the sidewall spacers and into the doped source/drain regions. The sigma corner regions do not need to terminate within the doped source/drain regions, however. The initial RIE can be sufficiently deep that the final sigma profile results in the corner regions extending below the source/drain regions.
- 0047 Referring to FIG. 6d, the process of forming the sigma shape is such that the sigma corner regions extending into the source/drain regions do not extend to a depth below the surface. This can be achieved by performing an ammonium hydroxide wet etch, wherein the wet etch undercuts the sidewall spacers to result in some lateral protrusion of the sigma corner regions.
- 0048 Referring to FIG. 7, channel material is epitaxially grown within the etch cavity. This is an optional, albeit preferred, step and can be used to create a BTBT junction with larger band edge offset within the junction (e.g., a broken gap tunnel junction). It is noteworthy that one could forego the epitaxial growth and proceed straight to the next step (i.e., gate stack

formation), such that BTBT takes place purely within the source material and not across a junction between the source and the channel.

- 0049 Referring now to FIGs. 7a and 7b, an epitaxial channel material is grown over all the exposed semiconducting regions within the self-aligned etch cavity. The optimal thickness of the material depends on the material used, and the implications for quantum confinement within this material, as well as stress relaxation over the underlying material/s. The epitaxial channels (710,720) thickness can be on the order of 5-10nm. For illustrative purposes, example of materials include but are not limited to InP, InSb, InAs, and other III-V semiconductors, as well as Ge or graphene.
- 0050 Referring to FIGs. 7c and 7d, the epitaxial channels (730, 740) material is grown over all the exposed semiconductor regions in the self-aligned etch cavity. In the example illustrated herein, the interface between the channel material and the source material exists on a (111) crystal plane.
- 0051 Still referring to FIG. 7d, since the etch cavity cuts through the source/drain regions and the epitaxial channel is grown 'over' the source/drain regions, the effective channel width is independent of the epitaxial channel thickness (as opposed to a longitudinal mode TFET, wherein the channel thickness plays a role in determining the BTBT cross-sectional area). This implies that relatively thin epitaxial regions can be employed, permitting the usage of materials with a larger lattice mismatch over the source/drain and substrate regions without relaxing the interface strain (that can otherwise occur if the epitaxial layer is too thick). Also, as the thickness of the epitaxial channel layer is reduced, the transverse electric field increases, which leads to higher BTBT current in the on-state (assuming that the material is not so thin that quantum confinement increases the effective tunnel bandgap and reduces the availability of tunnel carriers over the energy range within which BTBT occurs).
- 0052 Referring to FIGs. 8a-8d, high-k/metal gate stacks are respectively deposited and planarized. The respective high-k materials are initially deposited conformally, covering the entire channel region. Typical choices for high-k dielectrics include HfO₂, Al₃O₂, and Ta₂O₅. The high-k

dielectric thickness is preferably on the order of 1-2nm. To reduce the presence of interface states at the channel-to-high-k interface, the high-k deposition can be preceded by some form of interface passivation using any or a combination of fluorine, oxygen, selenium, sulfur, carbon, hydrogen, and the like, and/or a thin oxide deposition or growth step. After depositing the respective high-k materials, metal gate stacks are then respectively deposited into the self-aligned etch cavity. Each metal gate stack can be formed using any metal needed to meet the gate workfunction and gate leakage specifications required by the source and channel materials to achieve optimal performance. This can include one or a combination of TiN, TaN, TiAl, Ti, Ta, W, Al, Dy, Er, and the like. Following the deposition of the each metal gate stack, CMP is then performed to remove the metal residuals from the top of each structure (i.e, on top of the spacer and ILD regions), resulting in respective electrically isolated metal gate stacks.

- 0053 Referring to FIG. 8a, the direction of BTBT current flow in the on-state from the source to the channel can be in the lateral direction but transverse to the gate electrode. Referring to the thin epitaxial channel layer over the source region described in embodiments of the invention, the gate electrode forms an inversion layer over the source region inducing the BTBT current flow from the source region to the channel region in a direction transverse to the gate electrode.
- 0054 Referring to FIG. 8b, the shape of the interface between the source region and the gate region is curved, indicative that the direction of the BTBT current flow in the on-state is neither lateral nor vertical. However, for each current flow vector (shown by arrows), the flow of the current from the source to the channel region is transverse to the gate electrode. Thus, for both FIGs. 8a and 8b, despite the different absolute directions of the BTBT current flow (i.e., FIG. 8a has a 1-D interface and FIG. 8b has a 2-D curved interface between the source region and gate region), the BTBT current flows nonetheless in a direction transverse to the gate electrode in both cases.
- 0055 Referring to FIGs. 8c and 8d, the interface between the source region and the gate region exists along the (111) crystal plane, but the principle of operation is the same as shown in FIGs. 8a and 8b, wherein throughout the interface between source region and the gate electrode, the BTBT current flows in the on-state is in a direction that is transverse to the gate electrode, as

depicted by the arrows in FIGs. 8c and 8d. Alternatively, in FIGs. 8c and 8d, the direction of BTBT current flow is in the $\langle 111 \rangle$ direction. For materials which possess effective mass anisotropy, the effective carrier tunneling mass may be lower in the $\langle 111 \rangle$ direction than in any other crystal plane direction, such as the $\langle 100 \rangle$ direction. Using the sigma shape as described in FIGs. 8c and 8d should result in an increase in BTBT current compared to the structures in FIGs. 8a and 8b.

0056 While the present invention has been particularly shown and described with respect to preferred embodiments thereof, it will be understood by those skilled in the art that the foregoing and other changes in forms and details can be made without departing from the spirit and scope of the present invention. It is therefore intended that the present invention not be limited to the exact forms and details described and illustrated, but fall within the scope of the appended claims.

INDUSTRIAL APPLICABILITY

0057 The present invention finds industrial applicability in the design and fabrication of high-performance semiconductor Tunnel Field Effect Transistors (FET) incorporated in integrated circuit chips that find application in a large variety of electronic and electrical apparatus.

CLAIMS

1. A method of manufacturing a tunnel field effect transistor (TFET), comprising:
 - a) forming a dummy gate stack (310) surrounded by sidewall spacers (320) on a substrate (200) covered by epitaxially grown source material (220);
 - b) forming doped source (510) and drain (520) regions followed by an inter-layer dielectric (ILD) (510) surrounding the sidewall spacers (320);
 - c) removing the dummy gate stack (310) followed by etching a self-aligned cavity (710);
 - d) epitaxially growing a thin channel within the self-aligned etch cavity; and
 - e) depositing gate dielectric and gate materials within the self-aligned etch cavity.
2. The method of claim 1, wherein step b) is followed by exposing dummy gate materials by planarizing said dummy gate stack.
3. The method as recited in claim 2 wherein the planarizing extends over both the ILD and the dummy gate stack, exposing the dummy gate material within the gate stack.
4. The method of claim 1, further comprising forming the self-aligned etch cavity directly under the gate electrode by leveraging replacement gate.
5. The method of claim 1, wherein step e) is followed by planarizing a top surface of the replacement stack, removing residues of said gate dielectric and said metal gate materials.
6. The method of claim 3, further comprising removing said dummy gate stack and forming a self aligned etch cavity.
7. The method of claim 6, wherein said etch is performed during a replacement gate process, and wherein the dummy gate region defines the length and width of said etch cavity.
8. The method of claim 1 further comprising forming P+ and, N+ regions and intrinsic and lightly-doped regions separating the P+ and N+ regions, defining the source, body, and the drain regions.

9. The method of claim 8, wherein forming the P⁺ and N⁺ regions is performed by epitaxy, implant, or any combination thereof with an intrinsic or a lightly-doped region separating said P⁺ and N⁺ regions.
10. The method of claim 1, wherein said epitaxially grown channel extends over at least the source region, and wherein said epitaxially grown channel is doped or undoped.
11. The method of claim 1, wherein forming the replacement gate stack comprises the gate dielectric, and metal gate electrode over the epitaxially grown channel.
12. The method of claim 1 further comprises forming a TFET with predominantly transverse or longitudinal tunneling.
13. The method of claim 1 further comprising forming a thin epitaxial layer bridging the source, body and drain regions.
14. The method of claim 13, wherein said thin epitaxial layer between the N⁺ and P⁺ regions is modulated by said gate.
15. The method of claim 1, wherein removing the dummy gate to achieve the etch cavity is performed by any combination of wet and dry etching.
16. The method of claim 1, wherein the etch cavity comprises one of anisotropic, isotropic, or a sigma-shaped configuration.
17. The method of claim 16, wherein each etch results in an etch surface having different exposed crystal planes.
18. The method of claim 17 wherein the different exposed crystal planes maximize the TFET drive current, depending on materials and direction of an effective mass anisotropy.

19. The method of claim 17 wherein corner regions in the anisotropic and sigma recess etches confine the drain voltage drop to take place between corner regions and drain terminal, resulting in a uniform surface potential along BTBT perimeter at the source to the channel junction.
20. A tunnel field effect transistor (TFET) device, comprising:
- a first doped source region for a first type TFET or a second doped source region (530) for a second type TFET;
 - a second doped drain region for the first type TFET or a first doped drain region (520) for the second type TFET;
 - a body region that is either intrinsic or doped, with a doping concentration less than that of the first or second source region, separating the first or second source from the first or second drain regions;
 - a self-aligned etch cavity (710) separating the first or second doped source (530) and drain (520) regions;
 - a thin epitaxial channel region that is grown within the self-aligned etch cavity (710), covering at least the first or the second source region;
 - a replacement gate stack (310) comprising a high-k gate dielectric and one or a combination of metals and polysilicon; and
 - sidewall spacers (320) adjacent to the replacement gate stack.
21. The TFET device of claim 20 further comprising a p⁺ source region of an n-type TFET or an n⁺ source region of a p-type TFET; an n⁺ drain region for the n-type TFET or a p⁺ drain region for the p-type TFET; a body region that is either intrinsic or doped, with a doping concentration less than that of the source region, separating the p⁺ and n⁺ source and drain regions; a self-aligned etch cavity separating the p⁺ and n⁺ source and drain regions; a thin epitaxial channel region grown within the self-aligned etch cavity, covering at least the source region; a replacement gate stack comprising a high-k gate dielectric and one or a combination of metals; and sidewall spacer regions adjacent to the replacement gate stack.