

METHOD AND APPARATUS FOR ALLOCATING CONTROL CHANNEL CANDIDATES

TECHNICAL FIELD

[0001] The present invention relates to the communications field, and in particular, to a
5 method and an apparatus for allocating control channel candidates.

BACKGROUND

[0002] In an LTE (Long Term Evolution, long term evolution) Rel-8/9/10 communication
system, a dynamic scheduling technology is used to improve performance of the system. In
other words, an eNB (evolved Node Base, evolved base station) schedules and allocates
10 resources according to channel conditions of each UE (User Equipment, user equipment), so
that each scheduled UE performs transmission on an optimal channel of the UE. In downlink
transmission, the eNB sends a PDSCH (Physical Downlink Shared Channel, physical
downlink shared channel) and a corresponding PDCCH (Physical Downlink Control
Channel, physical downlink control channel) to each scheduled UE according to a dynamic
15 scheduling result, where the PDSCH carries data sent by the eNB to the scheduled UE, and
the PDCCH is mainly used to indicate a transport format of the corresponding PDSCH,
including scheduling information such as resource allocation, transport block size,
modulation and coding scheme, transport rank, and precoding matrix information.

[0003] In a subframe, each PDCCH used for downlink and uplink scheduling is multiplexed
20 in N ($N > 1$) CCEs numbered $n = 0, 1, \dots, N-1$ in a PDCCH region. Each PDCCH has 4
aggregation levels in total, namely, 1, 2, 4, and 8, which means, the PDCCH may be formed
by aggregation of 1, 2, 4, or 8 consecutive CCEs. The aggregation level corresponding to
each PDCCH is determined by the size of information blocks in the PDCCH and a channel of
a UE corresponding to the PDCCH. Information in each PDCCH is mapped through the N

CCEs to REs reserved for the PDCCH and is sent to a UE.

[0004] At a receiving end, the UE needs to blindly detect the N CCEs to obtain a PDCCH needed by the UE. The number of PDCCH candidates at each aggregation level is limited. A smaller number of PDCCH candidates indicate a smaller number of times of blind detections.

5 For example, when aggregation level l is 8, there are only two PDCCH candidates, which means, CCEs 0 to 7 and CCEs 8 to 15 are detected. Although this PDCCH candidate allocation principle can reduce the number of times of blind detections, the number of times of blind detections needed at each aggregation level is still approximately in direct proportion to the number N of CCEs in the PDCCH region. To further reduce complexity of blind
10 detections, the maximum number of PDCCH candidates to be blindly detected, namely, a search space, is limited at each aggregation level. The search space is classified into a common search space and a UE-specific search space. The difference between the two search spaces lies in that a start CCE of the common search space is in a fixed position, while a start CCE of the UE-specific search space is determined by a UE identity and a subframe number
15 of a PDCCH, where the common search space and the UE-specific search space may overlap. After the number of PDCCH candidates included in the search space is set, the UE may start to perform a specified number of times of blind detections from the start CCE according to an aggregation level supported by the PDCCH candidates, thereby reducing the complexity of blind detections. For example, the number of CCEs in a PDCCH region is $N = 18$, a start
20 CCE of a UE-specific search space is 0, and the numbers of PDCCH candidates at aggregation levels $l = 1, 2, 4$, and 8 are 6, 6, 2, and 2 respectively; then, when $l = 1$, there are 6 PDCCH candidates, and there is one aggregated CCE in each PDCCH, and therefore, the UE needs to perform only 6 blind detections for 6 consecutive CCEs starting from the start CCE; when $l = 4$, there are 2 PDCCH candidates, and there are 4 aggregated CCEs in each
25 PDCCH, and therefore, the UE needs to perform only 2 blind detections for $2 * 4 = 8$ consecutive CCEs starting from the start CCE.

[0005] In LTE Rel-11, an existing PDCCH is enhanced, in other words, a part of resources are divided from an original PDSCH region to transmit an enhanced PDCCH to form an ePDCCH (enhance Physical Downlink Control Channel, enhanced physical downlink control
30 channel), so that capacity of the PDCCH and the number of simultaneously scheduled UEs

are increased. The ePDCCH may be formed by aggregation of one or more eCCEs (enhance Control Channel Elements, enhanced control channel elements), and an aggregation level may be obtained according to CSI feedback information. According to whether the ePDCCH is transmitted in consecutive time-frequency resource positions, in other words, whether
5 eCCEs are located in one physical resource block pair (corresponding to a localised transmission mode) or located in multiple distributed physical resource block pairs (corresponding to a distributed transmission mode), a transmission mode of the ePDCCH may be classified into a localised mode and a distributed mode.

[0006] Given a Normal subframe and a Normal CP or special subframe configurations 3, 4,
10 and 8 (Normal CP), when the number of valid resource elements in each PRB Pair is less than a threshold, aggregation levels used by the localised transmission mode are 2, 4, 8, and 16, and aggregation levels used by the distributed transmission mode are 2, 4, 8, 16, and 32. In all other cases, aggregation levels used by the localised transmission mode are 1, 2, 4, and 8, and aggregation levels used by the distributed transmission mode are 1, 2, 4, 8, and 16. In a
15 subframe, the UE may simultaneously detect control channel candidates of the localised transmission mode and distributed transmission mode. At the 3GPP RAN1#70, a conclusion on the design of a search space for an ePDCCH mainly includes: configuring K sets for a search space, where each set is made up of N PRB pairs, where N is equal to one of 1, 2, 4, 8, and 16, and the PRB pairs in each set may completely overlap or partially overlap. The
20 maximum value of K is one of {2, 3, 4, 6}, where there are K_L localised sets and K_D distributed sets (K_L and K_D may be equal to 0), and the total number of times of blind detections is 32 or 48 and does not change according to the value of K.

[0007] When the UE performs blind detections for the search space of the K sets, the total number of times of blind detections is fixed. To reduce the complexity of blind detections,
25 some limitations to the number of control channel candidates allocated in the K ePDCCH sets need to be made for each aggregation level; however, the prior art does not provide a method for allocating control channel candidates.

SUMMARY

[0008] Embodiments of the present invention provide a method and an apparatus for allocating control channel candidates, which can allocate control channel candidates at different aggregation levels to K ePDCCH sets and reduce complexity of blind detections performed by a UE.

[0009] To achieve the foregoing objectives, the embodiments of the present invention adopt the following technical solutions:

[0010] According to a first aspect, a method for allocating control channel candidates is provided and includes:

determining K sets for transmitting a control channel, where each set in the K sets includes at least one physical resource block pair, and K is a positive integer greater than 0; and

allocating each control channel candidate to at least one set in the K sets according to at least one of aggregation levels supported by the control channel, the number of control channel candidates corresponding to each aggregation level, the K sets for transmitting the control channel, and types of the sets.

[0011] In a first possible implementation manner, the K sets for transmitting the control channel include a set of a localised transmission mode and a set of a distributed transmission mode, where the number of sets of the localised transmission mode is K_L , and the number of sets of the distributed transmission mode is K_D , $K_L + K_D = K$, and K_L and K_D are integers greater than or equal to 0; and

the aggregation levels supported by the control channel include one or more of the following levels:

aggregation levels supported by the localised transmission mode, aggregation levels supported by the distributed transmission mode, and common aggregation levels supported by both the localised transmission mode and the distributed transmission mode.

[0012] In a second possible implementation manner, with reference to the first possible implementation manner of the first aspect, the allocating control channel candidates at each

aggregation level to at least one set in the K sets according to the aggregation levels supported by the control channel to be transmitted, the number of control channel candidates corresponding to each aggregation level and determined according to a preset rule, the K sets for transmitting the control channel, and the types of the sets, includes:

5 when K_L is a positive integer, allocating all control channel candidates at the aggregation levels supported by the localised transmission mode to at least one of the K_L sets; or

 when K_D is a positive integer, allocating all control channel candidates at the aggregation levels supported by the distributed transmission mode to at least one of the K_D sets; or

10 sets; or

 when both K_L and K_D are positive integers, allocating all control channel candidates at each aggregation level in the aggregation levels supported by both the localised transmission mode and the distributed transmission mode to at least one of the K_D sets and at least one of the K_L sets.

15 **[0013]** In a third possible implementation manner, both K_L and K_D are positive integers, all control channel candidates at each aggregation level in the aggregation levels supported by both the localised transmission mode and the distributed transmission mode are allocated to at least one of the K_D sets and at least one of the K_L sets,

 at least one half of all control channel candidates at each first aggregation level in the aggregation levels supported by both the localised transmission mode and the distributed transmission mode are allocated to at least one of the K_L sets; and

20 transmission mode are allocated to at least one of the K_L sets; and

 at least one half of all control channel candidates at each second aggregation level in the aggregation levels supported by both the localised transmission mode and the distributed transmission mode are allocated to at least one of the K_D sets.

25 **[0014]** In a fourth possible implementation manner, the allocating all control channel candidates at an aggregation level supported by only the distributed transmission mode or the

localised transmission mode to at least one set in the K_D sets of the distributed transmission mode or in the K_L sets of the localised transmission mode, includes:

determining, according to the number of sets used for the aggregation level in K_D or K_L , the number of control channel candidates allocated to each set in the K_D or K_L sets, at the aggregation level; or

determining, according to a ratio of the number of physical resource blocks of each set in sets used for the aggregation level in K_D or K_L , the number of control channel candidates allocated to each set in the K_D or K_L sets, at the aggregation level.

[0015] In a fifth possible implementation manner, both K_L and K_D are positive integers, all control channel candidates at each aggregation level in the aggregation levels supported by both the localised transmission mode and the distributed transmission mode are allocated to at least one of the K_D sets and at least one of the K_L sets,

according to a ratio between the numbers of sets used for the aggregation level in K_D and K_L , the numbers of control channel candidates allocated to the K_L and K_D sets are determined, at each aggregation level; or

according to a ratio between the total numbers of physical resource blocks in sets used for the aggregation level in K_D and K_L , the numbers of control channel candidates allocated to the K_L and K_D sets are determined, at each aggregation level; or

according to a ratio of the number of physical resource blocks of each set in sets used for the aggregation level in K_D and K_L , the number of control channel candidates allocated to each set in the K_L and K_D sets is determined, at each aggregation level.

[0016] Optionally, at each aggregation level, when the number of control channel candidates configured for the K_L (greater than 1) sets is greater than 1, the number of control channel candidates in each set is determined according to the number of physical resource blocks included in each set that can support the aggregation level in the K_L sets or

the number of sets that can support the aggregation level in the K_L sets, or

when the number of control channel candidates configured for the K_D (greater than 1) sets is greater than 1, the number of control channel candidates in each set is determined according to the number of physical resource blocks included in each set that can support the aggregation level in the K_D sets or the number of sets that can support the aggregation level in the K_D sets.

[0017] Optionally, at each aggregation level supported by the control channel to be transmitted, the number of control channel candidates allocated to the K_L sets of the localised transmission mode and the number of control channel candidates allocated to the K_D sets of the distributed transmission mode are functions of at least one of the number of control channel candidates at the aggregation level, the number K_L of sets of the localised transmission mode, and the number K_D of sets of the distributed transmission mode.

[0018] Optionally, when the number of control channel candidates corresponding to the aggregation levels supported by both the localised transmission mode and the distributed transmission mode is an even number, the number of control channel candidates allocated to the K_L sets of the localised transmission mode meets the following formula:

$M^{(L)}/2 + \left\lfloor \frac{K_L}{K_L + K_D} \cdot M^{(L)}/2 \right\rfloor$; and the number of control channel candidates allocated to the

K_D sets of the distributed transmission mode meets the following formula:

$M^{(L)}/2 - \left\lfloor \frac{K_L}{K_L + K_D} \cdot M^{(L)}/2 \right\rfloor$;

when the number of control channel candidates corresponding to the lower aggregation levels is an odd number, the number of control channel candidates allocated to the K_L sets of the localised transmission mode meets the following formula:

$(M^{(L)} + 1)/2 + \left\lfloor \frac{K_L}{K_L + K_D} \cdot (M^{(L)} - 1)/2 \right\rfloor$; and the number of control channel candidates

allocated to the K_D sets of the distributed transmission mode meets the following formula:

$$(M^{(L)} - 1)/2 - \left\lfloor \frac{K_L}{K_L + K_D} \cdot (M^{(L)} - 1)/2 \right\rfloor; \text{ and}$$

an allocation ratio of all candidates at aggregation levels where the number of control channel candidates is 2, is 1:1 between the K_L sets of the localised transmission

5 mode and the K_D sets of the distributed transmission mode.

[0019] Optionally, at least one set in the determined K sets for transmitting the control channel is used to allocate control channel candidates at one or two aggregation levels.

[0020] A rule for determining aggregation levels that can be supported by the control channel to be transmitted includes:

10 when the total number of aggregation levels that can be supported by the control channel is N, obtaining, according to the number of valid physical resource elements included in each physical resource block pair, k ($k \leq N$) aggregation levels in the N aggregation levels as aggregation levels of the control channel to be transmitted, or

15 configuring, semi-statically through RRC signaling, k ($k \leq N$) aggregation levels in the N aggregation levels as aggregation levels that can be supported by the control channel to be transmitted.

[0021] A form of semi-static configuration through RRC signaling is a bitmap (Bitmap).

[0022] If the number of aggregation levels of the control channel to be transmitted is N, the numbers of control channel candidates corresponding to any p ($p \leq 4$) aggregation levels in 20 4 aggregation levels (1, 2, 4, 8) in an original protocol are respectively configured for corresponding aggregation levels in the N aggregation levels of the control channel to be transmitted, and the numbers of control channel candidates corresponding to remaining (4-p) aggregation levels in the 4 aggregation levels (1, 2, 4, 8) in the original protocol are correspondingly configured for remaining N-p aggregation levels in the N aggregation levels 25 of the control channel to be transmitted.

[0023] When the aggregation levels supported by the control channel to be transmitted include 32, and the number of available resource elements in each physical resource block pair except resource elements of other signals, such as a CRS, a DMRS, a CSI-RS, a

PDCCH, is greater than or equal to 72, a user terminal does not detect control channel candidates at aggregation level 32; otherwise, the user terminal detects the control channel candidates at aggregation level 32;

or, when the aggregation levels supported by the control channel to be transmitted do not include 32, and the number of available resource elements in each physical resource block pair except resource elements of other signals, such as a CRS, a DMRS, a CSI-RS, a PDCCH, is less than 72, a user terminal detects control channel candidates at aggregation level 8.

[0024] When the control channel to be transmitted is transmitted with an extended cyclic prefix, and the supported aggregation levels include 16, and the number of available resource elements in each physical resource block pair except resource elements of other signals, such as a CRS, a DMRS, a CSI-RS, a PDCCH, is greater than or equal to 72, a user terminal does not detect control channel candidates at aggregation level 16; otherwise, the user terminal detects the control channel candidates at aggregation level 16;

or, when the control channel to be transmitted is transmitted with an extended cyclic prefix, and the supported aggregation levels do not include 16, and the number of available resource elements in each physical resource block pair except resource elements of other signals, such as a CRS, a DMRS, a CSI-RS, a PDCCH, is less than 72, a user terminal detects PDCCH candidates at aggregation level 8.

[0025] The K_L and K_D for transmitting the control channel are configured, and the number of physical resource block pairs included in each set is configured; or the K_L and K_D for transmitting the control channel are fixed, the number of physical resource block pairs included in each set is configured, and allocation of all control channel candidates at each aggregation level to the K_L and K_D sets is fixed.

[0026] In a second aspect, an apparatus for allocating control channel candidates is provided and includes:

a determining unit, configured to determine K sets for transmitting a control channel, where each set in the K sets includes at least one physical resource block pair, and K is a positive integer greater than 0; and

an allocating unit, configured to allocate, according to at least one of aggregation levels supported by the control channel, the number of control channel candidates corresponding to each aggregation level, the K sets for transmitting the control channel, and types of the sets, each control channel candidate to at least one set in the K sets determined by the determining unit.

[0027] In a first possible implementation manner, the K sets for transmitting the control channel include a set of a localised transmission mode and a set of a distributed transmission mode, where the number of sets of the localised transmission mode is K_L , and the number of sets of the distributed transmission mode is K_D , $K_L + K_D = K$, and K_L and K_D are integers greater than or equal to 0; and

the aggregation levels supported by the control channel include one or more of the following levels:

aggregation levels supported by the localised transmission mode, aggregation levels supported by the distributed transmission mode, and common aggregation levels supported by both the localised transmission mode and the distributed transmission mode.

[0028] The allocating unit is specifically configured to: when K_L is a positive integer, allocate all control channel candidates at the aggregation levels supported by the localised transmission mode to at least one of the K_L sets; or when K_D is a positive integer, allocate all control channel candidates at the aggregation levels supported by the distributed transmission mode to at least one of the K_D sets; or when both K_L and K_D are positive integers, allocate all control channel candidates at each aggregation level in the aggregation levels supported by both the localised transmission mode and the distributed transmission mode to at least one of the K_D sets and at least one of the K_L sets.

[0029] Optionally, the allocating unit being configured to allocate all control channel candidates at each aggregation level in the aggregation levels supported by both the localised transmission mode and the distributed transmission mode to at least one of the K_D sets and at least one of the K_L sets when both K_L and K_D are positive integers, includes:

allocating at least one half of all control channel candidates at each first aggregation level in the aggregation levels supported by both the localised transmission mode and the distributed transmission mode to at least one of the K_L sets; and allocating at least one half of all control channel candidates at each second aggregation level in the aggregation levels supported by both the localised transmission mode and the distributed transmission mode to at least one of the K_D sets.

[0030] Optionally, when the number of control channel candidates at the aggregation level is 2, remaining control channel candidates are not placed in any set corresponding to a transmission mode of a first control channel candidate.

10 [0031] Optionally, the allocating unit being configured to allocate all control channel candidates at an aggregation level supported by only the distributed transmission mode or the localised transmission mode to at least one set in the K_D sets of the distributed transmission mode or in the K_L sets of the localised transmission mode, includes:

determining, according to the number of sets used for the aggregation level in K_D or K_L , the number of control channel candidates allocated to each set in the K_D or K_L sets, at the aggregation level; or

determining, according to a ratio of the number of physical resource blocks of each set in sets used for the aggregation level in K_D or K_L , the number of control channel candidates allocated to each set in the K_D or K_L sets, at the aggregation level.

20 [0032] Optionally, the allocating unit being configured to allocate all control channel candidates at each aggregation level in the aggregation levels supported by both the localised transmission mode and the distributed transmission mode to at least one of the K_D sets and at least one of the K_L sets when both K_L and K_D are positive integers, includes:

determining, according to a ratio between the numbers of sets used for the aggregation level in K_D and K_L , the numbers of control channel candidates allocated to the K_L and K_D sets, at each aggregation level; or

determining, according to a ratio between the total numbers of physical resource blocks in sets used for the aggregation level in K_D and K_L , the numbers of control channel candidates allocated to the K_L and K_D sets, at each aggregation level; or

determining, according to a ratio of the number of physical resource blocks of each set in sets used for the aggregation level in K_D and K_L , the number of control channel candidates allocated to each set in the K_L and K_D sets, at each aggregation level.

[0033] Optionally, at each aggregation level, the numbers of control channel candidates allocated to the K_L and K_D sets are configured. The configuration is a higher-layer semi-static configuration.

[0034] At each aggregation level, when the number of control channel candidates configured for the K_L (greater than 1) sets is greater than 1, the allocating unit is configured to determine the number of control channel candidates in each set according to the number of physical resource blocks included in each set that can support the aggregation level in the K_L sets or the number of sets that can support the aggregation level in the K_L sets, or

when the number of control channel candidates configured for the K_D (greater than 1) sets is greater than 1, the allocating unit is configured to determine the number of control channel candidates in each set according to the number of physical resource blocks included in each set that can support the aggregation level in the K_D sets or the number of sets that can support the aggregation level in the K_D sets.

[0035] At each aggregation level supported by the control channel to be transmitted, the number of control channel candidates allocated to the K_L sets of the localised transmission mode and the number of control channel candidates allocated to the K_D sets of the distributed transmission mode are functions of at least one of the number of control channel candidates at the aggregation level, the number K_L of sets of the localised transmission mode, and the number K_D of sets of the distributed transmission mode.

[0036] When the number of control channel candidates corresponding to the aggregation levels supported by both the localised transmission mode and the distributed transmission mode is an even number, the number of control channel candidates allocated to the K_L sets of the localised transmission mode meets the following formula:

$$5 \quad M^{(L)} / 2 + \left\lfloor \frac{K_L}{K_L + K_D} \cdot M^{(L)} / 2 \right\rfloor; \text{ and the number of control channel candidates allocated to the}$$

K_D sets of the distributed transmission mode meets the following formula:

$$M^{(L)} / 2 - \left\lfloor \frac{K_L}{K_L + K_D} \cdot M^{(L)} / 2 \right\rfloor;$$

when the number of control channel candidates corresponding to the lower aggregation levels is an odd number, the number of control channel candidates allocated to the K_L sets of the localised transmission mode meets the following formula:

$$(M^{(L)} + 1) / 2 + \left\lfloor \frac{K_L}{K_L + K_D} \cdot (M^{(L)} - 1) / 2 \right\rfloor; \text{ and the number of control channel candidates}$$

allocated to the K_D sets of the distributed transmission mode meets the following formula:

$$(M^{(L)} - 1) / 2 - \left\lfloor \frac{K_L}{K_L + K_D} \cdot (M^{(L)} - 1) / 2 \right\rfloor; \text{ and}$$

an allocation ratio of all candidates at aggregation levels where the number of control channel candidates is 2, is 1:1 between the K_L sets of the localised transmission mode and the K_D sets of the distributed transmission mode.

[0037] Optionally, the allocating unit is configured to determine that at least one set in the K sets for transmitting the control channel is used to allocate control channel candidates at one or two aggregation levels.

[0038] Optionally, a rule for determining aggregation levels that can be supported by the control channel to be transmitted includes:

when the total number of aggregation levels that can be supported by the control channel is N , obtaining, according to the number of valid physical resource elements included in each physical resource block pair, k ($k \leq N$) aggregation levels in the N aggregation

levels as aggregation levels of the control channel to be transmitted, or

configuring, semi-statically through RRC signaling, k ($k \leq N$) aggregation levels in the N aggregation levels as aggregation levels that can be supported by the control channel to be transmitted.

5 [0039] A form of semi-static configuration through RRC signaling is a bitmap (Bitmap).

[0040] If the number of aggregation levels of the control channel to be transmitted is N , the numbers of control channel candidates corresponding to any p ($p \leq 4$) aggregation levels in 4 aggregation levels (1, 2, 4, 8) in an original protocol are respectively configured for corresponding aggregation levels in the N aggregation levels of the control channel to be transmitted, and the numbers of control channel candidates corresponding to remaining ($4-p$) aggregation levels in the 4 aggregation levels (1, 2, 4, 8) in the original protocol are correspondingly configured for remaining $N-p$ aggregation levels in the N aggregation levels of the control channel to be transmitted.

[0041] Optionally, the apparatus further includes a detecting unit, where: when the aggregation levels supported by the control channel to be transmitted include 32, and the number of available resource elements in each physical resource block pair except resource elements of other signals, such as a CRS, a DMRS, a CSI-RS, a PDCCH, is greater than or equal to 72, the detecting unit does not detect control channel candidates at aggregation level 32; otherwise, the detecting unit detects the control channel candidates at aggregation level 32; or, when the aggregation levels supported by the control channel to be transmitted do not include 32, and the number of available resource elements in each physical resource block pair except resource elements of other signals, such as a CRS, a DMRS, a CSI-RS, a PDCCH, is less than 72, the detecting unit detects control channel candidates at aggregation level 8.

25 [0042] Optionally, when the control channel to be transmitted is transmitted with an extended cyclic prefix, and the supported aggregation levels include 16, and the number of available resource elements in each physical resource block pair except resource elements of other signals, such as a CRS, a DMRS, a CSI-RS, a PDCCH, is greater than or equal to 72, the detecting unit does not detect control channel candidates at aggregation level 16; otherwise, the detecting unit detects the control channel candidates at aggregation level 16;

or, when the control channel to be transmitted is transmitted with an extended cyclic prefix, and the supported aggregation levels do not include 16, and the number of available resource elements in each physical resource block pair except resource elements of other signals, such as a CRS, a DMRS, a CSI-RS, a PDCCH, is less than 72, the detecting unit detects PDCCH candidates at aggregation level 8.

[0043] Optionally, the K_L and K_D for transmitting the control channel are configured, and the number of physical resource block pairs included in each set is configured; or the K_L and K_D for transmitting the control channel are fixed, the number of physical resource block pairs included in each set is configured, and allocation of all control channel candidates at each aggregation level to the K_L and K_D sets is fixed.

[0044] In a third aspect, an apparatus for allocating control channel candidates is provided and includes: a receiver, a transmitter, a memory, and a processor that is connected to the receiver, the transmitter, and the memory, where the memory stores a group of program codes, and the processor invokes the program codes in the memory to perform the method provided by the first aspect.

[0045] In the method and apparatus for allocating control channel candidates according to the above technical solutions, K sets for transmitting a control channel are determined, and control channel candidates at each aggregation level are allocated to at least one set in the K sets according to at least one of aggregation levels supported by the control channel to be transmitted, the number of control channel candidates corresponding to each aggregation level, the K sets for transmitting the control channel, and types of the sets. Therefore, control channel candidates at different aggregation levels can be allocated to K ePDCCH sets, and a search space of a UE is defined, thereby reducing complexity of blind detection performed by the UE.

BRIEF DESCRIPTION OF DRAWINGS

[0046] To describe the technical solutions in the embodiments of the present invention or in the prior art more clearly, the following briefly introduces the accompanying drawings

required for describing the embodiments or the prior art. Apparently, the accompanying drawings in the following description show merely some embodiments of the present invention, and a person of ordinary skill in the art may still derive other drawings from these accompanying drawings without creative efforts.

5 [0047] FIG. 1 is a schematic flowchart of a method for allocating control channel candidates according to an embodiment of the present invention;

[0048] FIG. 2 is a structural block diagram of an apparatus for allocating control channel candidates according to an embodiment of the present invention; and

10 [0049] FIG. 3 is a structural block diagram of another apparatus for allocating control channel candidates according to an embodiment of the present invention.

DESCRIPTION OF EMBODIMENTS

[0050] The following clearly and completely describes the technical solutions in the embodiments of the present invention with reference to the accompanying drawings in the embodiments of the present invention. Apparently, the described embodiments are merely a
15 part rather than all of the embodiments of the present invention. All other embodiments obtained by a person of ordinary skill in the art based on the embodiments of the present invention without creative efforts shall fall within the protection scope of the present invention.

[0051] An embodiment of the present invention provides a method for allocating control
20 channel candidates (EPDCCH candidates). As shown in FIG. 1, the method includes the following:

[0052] 101. Determine K sets for transmitting a control channel, where each set in the K sets includes at least one physical resource block pair, and K is a positive integer greater than 0.

25 [0053] There are two transmission modes for an ePDCCH, namely, localised transmission and distributed transmission. The localised transmission means that each eCCE aggregated into the ePDCCH is mapped to a PRB pair, and the distributed transmission means that each eCCE aggregated into the ePDCCH may be mapped to several non-consecutive PRB pairs in

the frequency domain.

[0054] For a UE, ePDCCH resources used for the localised transmission and distributed transmission are configured by an eNB. This configuration may be dynamic or semi-static allocation. For ease of description, without loss of generality, in the embodiment of the present invention, configurations of resources are described by using sets, and ePDCCH resources allocated by the eNB to the UE may be configured as K sets, where K is an integer greater than 0. Therefore, the set is also referred to as a resource set or an ePDCCH set (EPDCCH set). The K sets include two types: a set of a localised transmission mode and a set of a distributed transmission mode. The K sets for transmitting the control channel include

K_L sets of the localised transmission mode and K_D sets of the distributed transmission mode, where $K_L + K_D = K$, and K_L and K_D are integers greater than or equal to 0.

[0055] Each set includes N ($N \geq 1$) PRB pairs. When ePDCCH resources are configured, according to values of K_L and K_D , there may be the following cases: $K = K_L$, and $K_D = 0$, which means, the eNB allocates only $K_L \geq 1$ sets of the localised transmission mode to the UE; $K = K_D$, and $K_L = 0$, which means, the eNB allocates only $K_D \geq 1$ sets of the distributed transmission mode to the UE; $K = K_L + K_D$, where both K_L and K_D are not 0, which means, the eNB simultaneously allocates $K_L \geq 1$ sets of the localised transmission mode and $K_D \geq 1$ sets of the distributed transmission mode to the UE, where the number of PRB pairs in different sets may be the same or different, which is not limited by the embodiment of the present invention.

[0056] When control channel candidates are allocated to the K sets (the control channel candidates may also be referred to as candidates), values of K, K_L , and K_D need to be determined first. The K_L and K_D for transmitting the control channel are configured, and the number of physical resource block pairs included in each set is configured; or the K_L and K_D for transmitting the control channel are fixed, the number of physical resource block pairs included in each set is configured, and allocation of all control channel candidates

at each aggregation level to the K_L and K_D sets is fixed.

[0057] Herein the configuration refers to parameters configured by the base station for the UE through higher-layer signaling, which means, values of the K_L and K_D and the number of physical resource block pairs included in each set may all be configured by the
5 base station for the UE.

[0058] 102. Allocate control channel candidates at each aggregation level to at least one set in the K sets according to at least one of aggregation levels supported by the control channel to be transmitted, the number of control channel candidates corresponding to each aggregation level, the K sets for transmitting the control channel, and types of the sets.

10 [0059] To facilitate blind detections performed by the UE, an ePDCCH search space needs to be defined in all the configured K ePDCCH sets. For example, ePDCCH sets configured for a UE include a set of the localised transmission mode and a set of the distributed transmission mode, and the number of PRB pairs in the configured set of the localised transmission mode is 8 and the number of PRB pairs in the configured set of the distributed
15 transmission mode is 4, and 4 eCCEs may be transmitted in each PRB pair. Therefore, the set of the localised transmission mode and the set of the distributed transmission mode include 32 eCCEs and 16 eCCEs respectively, 48 eCCEs in total. The ePDCCH search space of the UE needs to be defined on the 48 eCCEs. Specifically, on the 48 eCCEs, eCCE positions of the control channel candidates at different aggregation levels are determined, in the other
20 words, the number and eCCE positions of control channel candidates at different aggregation levels in the set of the localised transmission mode and the set of the distributed transmission mode are determined.

[0060] For the localised transmission mode and distributed transmission mode, generally when the base station can obtain accurate CSI feedback of a transmission channel of the UE,
25 the base station can obtain a frequency scheduling gain and a beamforming gain by using the localised transmission mode. Therefore, a lower aggregation level may be used for an ePDCCH, for example, aggregation levels 1 and 2 can satisfy performance requirements. Otherwise, when the base station cannot obtain accurate or timely CSI feedback, the base station cannot obtain the frequency scheduling gain and beamforming gain. To ensure

transmission performance of the ePDCCH, the distributed transmission mode needs to be used. Therefore, generally a higher aggregation level is used for transmission, for example, aggregation level 8, 16, or 32. Therefore, in the embodiment of the present invention, in common aggregation levels supported by both the localised transmission mode and the distributed transmission mode, at least one half of candidates at a lower aggregation level are placed in the region of the set of the localised transmission mode, and at least one half of candidates at a higher aggregation level are placed in the region of the set of the distributed transmission mode.

[0061] After obtaining the value of K configured by the eNB for the UE, the UE may allocate the control channel candidates to at least one set in the K sets. The allocation method may include the following three cases: When the K_L is a positive integer, the UE may allocate all control channel candidates at an aggregation level supported by only the localised transmission mode in the aggregation levels supported by the control channel to be transmitted to at least one set in the K_L sets of the localised transmission mode; and when the K_D is a positive integer, allocate all control channel candidates at an aggregation level supported by only the distributed transmission mode to at least one set in the K_D sets of the distributed transmission mode. When both the K_L and K_D are positive integers, all control channel candidates at the aggregation levels supported by both the localised transmission mode and the distributed transmission mode are allocated to at least one of the K_D sets of the distributed transmission mode and at least one of the K_L sets of the localised transmission mode; and allocate all control channel candidates at the aggregation level supported by only the distributed transmission mode or the localised transmission mode to at least one of the K_D sets of the distributed transmission mode or at least one of the K_L sets of the localised transmission mode.

[0062] The allocating all control channel candidates at the aggregation levels supported by both the localised transmission mode and the distributed transmission mode to at least one of the K_D sets of the distributed transmission mode and at least one of the K_L sets of the

localised transmission mode includes: allocating at least one half of all control channel candidates corresponding to a lower aggregation level in the aggregation levels supported by both the localised transmission mode and the distributed transmission mode to at least one of the K_L sets of the localised transmission mode; and allocating at least one half of all control channel candidates corresponding to a higher aggregation level in the aggregation levels supported by both the localised transmission mode and the distributed transmission mode to at least one of the K_D sets of the distributed transmission mode. As discussed at the 3GPP RAN1#70, for ePDCCH, given a Normal subframe and a Normal CP or special subframe configuration 3, 4 and 8 (Normal CP), when the number of valid resource elements in each PRB Pair is less than a threshold, the aggregation levels supported by the localised transmission mode are 2, 4, 8, and 16, and the aggregation levels supported by the distributed transmission mode are 2, 4, 8, 16, and 32. The aggregation levels supported by both the localised transmission mode and the distributed transmission mode are 2, 4, 8, and 16. In this case, the lower aggregation levels (namely, the first aggregation levels) are 2 and 4, and the higher aggregation levels (namely, the second aggregation levels) are 8 and 16. In all other cases, the aggregation levels used by the localised transmission mode are 1, 2, 4, and 8, and the aggregation levels used by the distributed transmission mode are 1, 2, 4, 8, and 16. The aggregation levels supported by both the localised transmission mode and the distributed transmission mode are 1, 2, 4, and 8. In this case, the lower aggregation levels are 1 and 2, and the higher aggregation levels are 4 and 8.

[0063] After completion of allocating at least one half of control channel candidates at each aggregation level in the aggregation levels supported by the control channel to be transmitted, remaining control channel candidates at each aggregation level are allocated to different sets according to a predefined sequence of control channel sets and a position of a start set at the aggregation level. The position of a start set at each aggregation level is related to the number of control channel candidates at the aggregation level and configuration of K_L and K_D . For example, for a lower aggregation level, at least one half of control channel candidates at the aggregation level are allocated to K_L sets of the localised transmission mode, and the

position of the start set at the aggregation level may be set in a set of the localised transmission mode in K_L sets of the localised transmission mode according to the number of control channel candidates at the aggregation level and K_L and K_D .

[0064] Optionally, the UE may also allocate each control channel candidate to at least one set in the K sets according to the number of control channel candidates corresponding to each aggregation level and types of the sets. When the number of control channel candidates at the aggregation level is 2, remaining control channel candidates are allocated to all sets different from the type of the set to which the first control channel candidate is allocated. For example, if the numbers of all control channel candidates corresponding to the aggregation levels supported by both the localised transmission mode and the distributed transmission mode are 2, the first control channel candidate is first allocated to a set in the K_L sets of the localised transmission mode, and the remaining one control channel candidate will be allocated to a set in the K_D sets of the distributed transmission mode.

[0065] According to the above method, for a lower aggregation level in the aggregation levels supported by both the localised transmission mode and the distributed transmission mode, the UE may evenly allocate a half of the control channel candidates corresponding to the lower aggregation level to the K_L sets of the localised transmission mode, and allocate the remaining half to different sets according to the predefined sequence of control channel sets and the position of a start set at the aggregation level.

[0066] In the existing protocol, the aggregation levels supported by both the localised transmission mode and the distributed transmission mode may be 1, 2, 4, and 8, or 2, 4, 8, and 16. Herein, assuming that the aggregation levels supported by both the localised transmission mode and the distributed transmission mode are 1, 2, 4, and 8, for lower aggregation levels 1 and 2, one half of control channel candidates corresponding to the aggregation levels 1 and 2 are first allocated to at least one set in the K_L sets, and the remaining half are allocated to different sets according to the predefined sequence of control channel sets and the position of the start set at the aggregation levels.

[0067] Assuming that aggregation level 1 or 2 corresponds to 6 control channel candidates,

the UE may allocate the first 3 control channel candidates in the 6 control channel candidates corresponding to aggregation level 1 or 2 to at least one set in the K_L sets. In this embodiment, the allocating the first 3 control channel candidates to at least one set in the K_L sets includes evenly allocating the 3 control channel candidates to the K_L sets, which means, a control channel candidate is allocated to each set sequentially in an incremental cyclic manner. The remaining 3 control channel candidates are allocated to different sets according to the predefined sequence of control channel sets and the position of the start set at the aggregation level. In the embodiment of the present invention, K_L sets of the localised transmission mode are marked with 1, 2, ..., and K_L , and K_D sets of the distributed transmission mode are marked with 1, 2, ..., and K_D . The allocating the remaining half of the control channel candidates at the lower aggregation level 1 or 2 to different sets according to the predefined sequence of control channel sets and the position of the start set at the aggregation level includes: allocating a control channel candidate to each set sequentially from the start set according to the sequence from K_L sets 1, 2, ..., and K_L of the localised transmission mode to K_D sets 1, 2, ..., and K_D of the distributed transmission mode, where the cyclic allocation is performed until the remaining half of the control channel candidates are allocated completely.

[0068] For $K = 4$, $K_L = 2$, and $K_D = 2$, when the start ePDCCH set is set 1 of the localised transmission mode, the result of allocating 6 control channel candidates at aggregation level 1 or 2 to 4 ePDCCH sets is:

Set 1 of the Localised Transmission Mode	Set 2 of the Localised Transmission Mode	Set 1 of the Distributed Transmission Mode	Set 2 of the Distributed Transmission Mode
3	2	1	0

[0069] The first 3 control channel candidates are allocated to sets 1 and 2 of the localised transmission mode, where 2 control channel candidates are in set 1 of the localised

transmission mode, and 1 control channel candidate is in set 2 of the localised transmission mode. The last 3 control channel candidates are sequentially allocated to sets 1 and 2 of the localised transmission mode and set 1 of the distributed transmission mode from set 1 of the localised transmission mode. Therefore, the final result of allocating the 6 control channel candidates to the 4 ePDCCH sets is: 3 control channel candidates are in set 1 of the localised transmission mode, 2 control channel candidates are in set 2 of the localised transmission mode, and 1 control channel candidate is in set 1 of the distributed transmission mode.

[0070] Likewise, for $K = 4$, $K_L = 1$, and $K_D = 3$, when the start ePDCCH set is set 1 of the localised transmission mode, the result of allocating 6 candidates at aggregation level 1 or

2 to 4 ePDCCH sets is:

Set 1 of the Localised Transmission Mode	Set 1 of the Distributed Transmission Mode	Set 2 of the Distributed Transmission Mode	Set 3 of the Distributed Transmission Mode
4	1	1	0

[0071] For $K = 4$, $K_L = 3$, and $K_D = 1$, when the start ePDCCH set is set 3 of the localised transmission mode, the result of allocating 6 candidates at aggregation level 1 or 2 to 4 ePDCCH sets is:

Set 1 of the Localised Transmission Mode	Set 2 of the Localised Transmission Mode	Set 3 of the Localised Transmission Mode	Set 1 of the Distributed Transmission Mode
1	2	2	1

[0072] For $K = 4$, $K_L = 4$, and $K_D = 0$, when the start ePDCCH set is set 1 of the localised transmission mode, the result of allocating 6 candidates at aggregation level 1 or 2 to 4 ePDCCH sets is:

Set 1 of the Localised	Set 2 of the Localised	Set 3 of the Localised	Set 4 of the Localised
---------------------------	---------------------------	---------------------------	---------------------------

Transmission Mode	Transmission Mode	Transmission Mode	Transmission Mode
2	2	1	1

[0073] For $K = 4$, $K_L = 0$, and $K_D = 4$, when the start ePDCCH set is set 1 of the distributed transmission mode, the result of allocating 6 candidates at aggregation level 1 or 2 to 4 ePDCCH sets is:

Set 1 of the Distributed Transmission Mode	Set 2 of the Distributed Transmission Mode	Set 3 of the Distributed Transmission Mode	Set 4 of the Distributed Transmission Mode
2	2	1	1

5

[0074] For $K = 2$, $K_L = 1$, and $K_D = 1$, assuming that the start ePDCCH set is set 1 of the localised transmission mode, the result of allocating 6 candidates at aggregation level 1 or 2 to 2 ePDCCH sets is:

Set 1 of the Localised Transmission Mode	Set 1 of the Distributed Transmission Mode
5	1

10 [0075] For $K = 2$, $K_L = 2$, and $K_D = 0$, assuming that the start ePDCCH set is set 2 of the localised transmission mode, the result of allocating 6 candidates at aggregation level 1 or 2 to 2 ePDCCH sets is:

Set 1 of the Localised Transmission Mode	Set 2 of the Localised Transmission Mode
3	3

[0076] For $K = 2$, $K_L = 0$, and $K_D = 2$, assuming that the start ePDCCH set is set 1 of

the distributed transmission mode, the result of allocating 6 candidates at aggregation level 1 or 2 to 2 ePDCCH sets is:

Set 1 of the Distributed Transmission Mode	Set 2 of the Distributed Transmission Mode
3	3

[0077] In the above method, after the UE allocates at least one half of the control channel candidates corresponding to a lower aggregation level to at least one set in K_L sets of the localised transmission mode, the UE allocates a control channel candidate to each set sequentially from the start set according to the sequence from K_L sets 1, 2, ..., and K_L of the localised transmission mode to K_D sets 1, 2, ..., and K_D of the distributed transmission mode, where the cyclic allocation is performed until the remaining control channel candidates are allocated completely. Optionally, the allocating the remaining control channel candidates to different sets according to the predefined sequence of control channel sets and the position of a start set at the aggregation level may also include: allocating a control channel candidate in the sets of the localised transmission mode and the sets of the distributed transmission mode from the start set in a head/tail alternation manner according to the sequence of K_L sets 1, 2, ..., and K_L of the localised transmission mode and K_D sets 1, 2, ..., and K_D of the distributed transmission mode, until the remaining half of the control channel candidates are allocated completely.

[0078] For $K = 4$, $K_L = 1$, and $K_D = 3$, when the start ePDCCH set is set 1 of the localised transmission mode, the result of allocating 6 candidates at aggregation level 1 or 2 to 4 ePDCCH sets is:

Set 1 of the Localised Transmission Mode	Set 1 of the Distributed Transmission Mode	Set 2 of the Distributed Transmission Mode	Set 3 of the Distributed Transmission Mode

2	1	1	2
---	---	---	---

[0079] For $K = 4$, $K_L = 1$, and $K_D = 3$, when the start ePDCCH set is set 2 of the localised transmission mode, the result of allocating 6 candidates at aggregation level 1 or 2 to 4 ePDCCH sets is:

Set 1 of the Localised Transmission Mode	Set 1 of the Distributed Transmission Mode	Set 2 of the Distributed Transmission Mode	Set 3 of the Distributed Transmission Mode
1	2	1	2

5

[0080] For a higher aggregation level in the aggregation levels supported by both the localised transmission mode and the distributed transmission mode, the UE may allocate at least one half of the control channel candidates corresponding to the higher aggregation level to at least one set in the K_D sets of the distributed transmission mode, and allocate the

10 remaining control channel candidates to different sets according to the predefined sequence of control channel sets and the position of a start set at the aggregation level. In the embodiment of the present invention, the allocating at least one half of the control channel candidates corresponding to the higher aggregation level to at least one set in the K_D sets of the distributed transmission mode includes: allocating a control channel candidate to each set

15 in the K_D sets of the distributed transmission mode sequentially according to the sequence 1, 2, ..., and K_D , where the cyclic allocation is performed until at least one half of the control channel candidates are allocated completely. The allocating the remaining control channel candidates to different sets according to the predefined sequence of control channel sets and the position of a start set at the aggregation level includes: allocating one of the

20 remaining control channel candidates to each set sequentially from the start set according to the reverse sequence from K_L sets 1, 2, ..., and K_L of the localised transmission mode to K_D sets 1, 2, ..., and K_D of the distributed transmission mode, where the cyclic allocation

is performed until the remaining half of the control channel candidates are allocated completely. Preferably, when the number of control channel candidates at the aggregation level is 2, remaining control channel candidates are allocated to all sets different from the type of the set to which the first control channel candidate is allocated. In other words, when the number of candidates at the aggregation level is 2, two control channel candidates are respectively allocated to a set in a region of the distributed transmission mode and a set in a region of localised transmission mode.

[0081] Herein, still assuming that the aggregation levels supported by both the localised transmission mode and the distributed transmission mode are 1, 2, 4, and 8, for the higher aggregation levels 4 and 8, a half of the control channel candidates corresponding to aggregation levels 4 and 8 are first allocated to at least one set in the K_D sets of the distributed transmission mode. In this embodiment, the first control channel candidate is allocated to one of the K_D sets, for example, a control channel candidate is allocated to each set sequentially in an incremental cyclic manner. The remaining half may be allocated to all sets different from the type of the set to which the first control channel candidate is allocated, namely, to a set in the K_L sets of the localised transmission mode.

[0082] For $K = 4$, $K_L = 2$, and $K_D = 2$, when two control channel candidates are respectively allocated to a set in the region of the distributed transmission mode and a set in the region of the localised transmission mode, the result of allocating 2 control channel candidates at aggregation level 4 or 8 to 4 ePDCCH sets is:

Set 1 of the Localised Transmission Mode	Set 2 of the Localised Transmission Mode	Set 1 of the Distributed Transmission Mode	Set 2 of the Distributed Transmission Mode
0	1	1	0

[0083] For $K = 4$, $K_L = 2$, and $K_D = 2$, when the start set is set 1 of the distributed transmission mode, the result of allocating 2 control channel candidates at aggregation level 4 or 8 to 4 ePDCCH sets is:

Set 1 of the Localised Transmission Mode	Set 2 of the Localised Transmission Mode	Set 1 of the Distributed Transmission Mode	Set 2 of the Distributed Transmission Mode
1	0	1	0

[0084] For $K = 2$, $K_L = 1$, and $K_D = 1$, the result of allocating 2 control channel candidates at aggregation level 4 or 8 to 2 ePDCCH sets is:

Set 1 of the Localised Transmission Mode	Set 1 of the Distributed Transmission Mode
1	1

- 5 [0085] In the above method, after the UE allocates at least one half of the control channel candidates corresponding to a higher aggregation level to at least one set in K_D sets of the distributed transmission mode, the UE allocates a control channel candidate to each set sequentially from the start set according to the sequence from K_L sets 1, 2, ..., and K_L of the localised transmission mode to K_D sets 1, 2, ..., and K_D of the distributed
- 10 transmission mode, where the cyclic allocation is performed until the remaining control channel candidates are allocated completely. Optionally, the allocating the remaining control channel candidates to different sets according to the predefined sequence of control channel sets and the position of a start set at the aggregation level may also include: allocating a control channel candidate in the sets of the localised transmission mode and the sets of the
- 15 distributed transmission mode from the start set in a head/tail alternation manner according to the sequence of K_L sets 1, 2, ..., and K_L of the localised transmission mode and K_D sets 1, 2, ..., and K_D of the distributed transmission mode, until the remaining half of the control channel candidates are allocated completely.

[0086] For $K = 4$, $K_L = 2$, and $K_D = 2$, when two control channel candidates are

respectively allocated to a set in the region of the distributed transmission mode and a set in the region of the localised transmission mode, the result of allocating 2 control channel candidates at aggregation level 4 or 8 to 4 ePDCCH sets is:

Set 1 of the Localised Transmission Mode	Set 2 of the Localised Transmission Mode	Set 1 of the Distributed Transmission Mode	Set 2 of the Distributed Transmission Mode
1	0	0	1

- 5 [0087] After obtaining the value of K configured by the eNB for the UE, the UE may allocate the control channel candidates to at least one set in the K sets. The allocation method may include 3 cases. In the third case, the allocating all control channel candidates at the aggregation levels supported by both the localised transmission mode and the distributed transmission mode to at least one set in the K_D sets of the distributed transmission mode
- 10 and at least one set in the K_L sets of the localised transmission mode when both the K_L and K_D are positive integers, may also include:

determining, according to a ratio between the numbers of sets used for the aggregation levels in K_D and K_L , the number of control channel candidates allocated to the K_L and K_D sets, at each aggregation level; or determining, according to a ratio

15 between the total numbers of physical resource blocks in sets used for the aggregation levels in K_D and K_L , the number of control channel candidates allocated to the K_L and K_D sets, at each aggregation level; or determining, according to a ratio of the number of physical resource blocks of each set in sets used for the aggregation levels in K_D and K_L , the number of control channel candidates allocated to each set in the K_L and K_D sets, at each

20 aggregation level.

[0088] After allocating all control channel candidates at the aggregation levels supported by both the distributed transmission mode and the localised transmission mode to at least one set in the K_D sets of the distributed transmission mode and at least one set in the K_L sets of

the localised transmission mode, all control channel candidates at the aggregation level supported by only the distributed transmission mode or the localised transmission mode are allocated to at least one set in the K_D sets of the distributed transmission mode or in the K_L sets of the localised transmission mode, which includes: determining, according to the

5 number of sets used for the aggregation level in K_D or K_L , the number of control channel candidates allocated to each set in the K_L or K_D sets, at the aggregation level; or determining, according to a ratio of the number of physical resource blocks of each set in sets used for the aggregation level in K_D or K_L , the number of control channel candidates allocated to each set in the K_L or K_D sets, at the aggregation level. For example,

10 aggregation levels supported by the control channel to be transmitted may be 1, 2, 4, 8, and 16, and may also be 2, 4, 8, 16, and 32, where an aggregation level supported by only the distributed transmission mode is 16 or 32, and the UE may allocate all control channel candidates at aggregation level 16 or 32 to at least one set in the K_D sets of the distributed transmission mode. Generally, the UE may allocate all control channel candidates at

15 aggregation level 16 or 32 to one set in the K_D sets of the distributed transmission mode. Optionally, the UE also determines, according to the number of sets used for the aggregation level 16 or 32 in K_D , the number of control channel candidates allocated to each set, at the aggregation level 16 or 32, for example, when the number of sets used for the aggregation level 16 or 32 is 2, and the number of control channel candidates is also 2, allocation is

20 performed sequentially in a manner of placing one candidate in each set. Otherwise, allocation is performed by using the following methods:

[0089] Method 1: Firstly, assuming that the number of control channel candidates corresponding to the aggregation level is $M^{(L)}$, and the number of sets is K , perform allocation, according to the number $\lfloor M^{(L)} / K \rfloor$, for each set of the sets supporting

25 the aggregation level, then place one of the remaining $M^{(L)} - \lfloor M^{(L)} / K \rfloor$ candidates cyclically to each set sequentially until all candidates are completely allocated.

" $\lceil \cdot \rceil$ " means rounding up.

[0090] Method 2: According to a ratio of the number of physical resource blocks of each set supporting the aggregation level to the total number of physical resource blocks in all sets that support the aggregation level, first perform the following allocation in the set of the highest or lowest ratio: $\lfloor M^{(L)} \cdot (N_i / N_{total}) \rfloor$, where N_i is the number of physical resource blocks in set i , and N_{total} is the total number of physical resource blocks in all the sets. Secondly, according to this method, place the remaining $M^{(L)} - \lfloor M^{(L)} \cdot (N_i / N_{total}) \rfloor$ candidates in a set of a next higher or next lower ratio in a recursive manner until all candidates are allocated completely.

10 [0091] Method 3: Mark each set supporting the aggregation level L with $s_1, s_2, s_3, \dots$, and s_T . Firstly, allocate c_i control channel candidates to set s_i according to the following formula, where the number c_i may be indicated by:

$$c_i = \left\lfloor \frac{C_L \times N_i}{\sum_{j=1}^T N_j} \right\rfloor.$$

[0092] Place the remaining $R = C_L - \sum_{j=1}^T c_j$ control channel candidates in R sets according

15 to a preset rule. Herein C_L is the number of control channel candidates corresponding to the aggregation level L .

[0093] The preset rule may be: sorting the R sets according to the number of physical resource block pairs included in each set, marking the sorted R sets with $s_1, s_2, s_3, \dots$, and s_R , where assuming that the number of physical resource block pairs included in the set s_i is N_i , the sorted sets satisfy $N_i \geq N_j$ and $i \leq j$, and placing one control channel candidate in

20 each set of the R sets sequentially according to the sequence of $s_1, s_2, \dots$, and s_R .

[0094] In the above method, the UE allocates all control channel candidates at the aggregation levels supported by both the localised transmission mode and the distributed transmission mode in the aggregation levels supported by the control channel to be

transmitted to at least one set in the K_D sets of the distributed transmission mode and at least one set in the K_L sets of the localised transmission mode; and allocates all control channel candidates at the aggregation level supported by only the distributed transmission mode or localised transmission mode to at least one set in the K_D sets of the distributed transmission mode or K_L sets of the localised transmission mode. Optionally, at each aggregation level supported by the control channel to be transmitted, the numbers of control channel candidates allocated to the K_L sets of the localised transmission mode and the K_D sets of the distributed transmission mode may be configured, and may also be obtained by calculation, which means, the allocation is a function of at least one of the number of control channel candidates at the aggregation level, the number K_L of sets of the localised transmission mode, and the number K_D of sets of the distributed transmission mode.

[0095] Optionally, the UE may receive the number of control channel candidates at each aggregation level, which is higher-layer semi-statically configured by RRC signaling, in the K_L sets of the localised transmission mode and the K_D sets of the distributed transmission mode. Preferably, when the number of available resource elements included in each PRB pair is greater than or equal to a threshold (such as 104), one configuration, as shown in the following tables, is semi-statically configured by RRC signaling for the UE:

Aggregation Level	Set of the Localised Transmission Mode	Set of the Distributed Transmission Mode
1	3	1
2	4	2
4	1	1
8	1	1
16	0	2

Aggregation Level	Set of the Localised Transmission Mode	Set of the Distributed Transmission Mode
-------------------	--	--

1	3	1
2	3	3
4	1	1
8	1	1
16	0	2

Aggregation Level	Set of the Localised Transmission Mode	Set of the Distributed Transmission Mode
1	3	1
2	5	1
4	1	1
8	1	1
16	0	2

Aggregation Level	Set of the Localised Transmission Mode	Set of the Distributed Transmission Mode
1	3	1
2	6	0
4	1	1
8	1	1
16	0	2

Aggregation Level	Set of the Localised Transmission Mode	Set of the Distributed Transmission Mode
1	2	2
2	3	3
4	1	1
8	1	1
16	0	2

Aggregation Level	Set of the Localised Transmission Mode	Set of the Distributed Transmission Mode
1	2	2
2	4	2
4	1	1
8	1	1
16	0	2

Aggregation Level	Set of the Localised Transmission Mode	Set of the Distributed Transmission Mode
1	2	2
2	5	1
4	1	1
8	1	1
16	0	2

Aggregation Level	Set of the Localised Transmission Mode	Set of the Distributed Transmission Mode
1	2	2
2	6	0
4	1	1
8	1	1
16	0	2

5

Aggregation Level	Set of the Localised Transmission Mode	Set of the Distributed Transmission Mode
1	4	1

2	4	2
4	1	1
8	1	1
16	0	1

Aggregation Level	Set of the Localised Transmission Mode	Set of the Distributed Transmission Mode
1	4	1
2	3	3
4	1	1
8	1	1
16	0	1

Aggregation Level	Set of the Localised Transmission Mode	Set of the Distributed Transmission Mode
1	4	1
2	5	1
4	1	1
8	1	1
16	0	1

Aggregation Level	Set of the Localised Transmission Mode	Set of the Distributed Transmission Mode
1	4	1
2	6	0
4	1	1
8	1	1
16	0	1

Aggregation Level	Set of the Localised Transmission Mode	Set of the Distributed Transmission Mode
1	4	1
2	6	0
4	1	1
8	1	1
16	0	1

Aggregation Level	Set of the Localised Transmission Mode	Set of the Distributed Transmission Mode
1	3	2
2	3	3
4	1	1
8	1	1
16	0	1

Aggregation Level	Set of the Localised Transmission Mode	Set of the Distributed Transmission Mode
1	3	2
2	4	2
4	1	1
8	1	1
16	0	1

Aggregation Level	Set of the Localised Transmission Mode	Set of the Distributed Transmission Mode
1	3	2
2	5	1
4	1	1

8	1	1
16	0	1

Aggregation Level	Set of the Localised Transmission Mode	Set of the Distributed Transmission Mode
1	3	2
2	6	0
4	1	1
8	1	1
16	0	1

Aggregation Level	Set of the Localised Transmission Mode	Set of the Distributed Transmission Mode
1	5	0
2	6	0
4	1	1
8	1	1
16	0	1

Aggregation Level	Set of the Localised Transmission Mode	Set of the Distributed Transmission Mode
1	4	0
2	6	0
4	1	1
8	1	1
16	0	2

- 5 [0096] When the number of available resource elements included in each PRB pair is less than a threshold (such as 104), one configuration, as shown in the following tables,

semi-statically configured by RRC signaling for the terminal:

Aggregation Level	Set of the Localised Transmission Mode	Set of the Distributed Transmission Mode
2	3	1
4	4	2
8	1	1
16	1	1
32	0	2

Aggregation Level	Set of the Localised Transmission Mode	Set of the Distributed Transmission Mode
2	3	1
4	3	3
8	1	1
16	1	1
32	0	2

Aggregation Level	Set of the Localised Transmission Mode	Set of the Distributed Transmission Mode
2	3	1
4	5	1
8	1	1
16	1	1
32	0	2

Aggregation Level	Set of the Localised Transmission Mode	Set of the Distributed Transmission Mode
2	3	1
4	6	0

8	1	1
16	1	1
32	0	2

Aggregation Level	Set of the Localised Transmission Mode	Set of the Distributed Transmission Mode
2	2	2
4	3	3
8	1	1
16	1	1
32	0	2

Aggregation Level	Set of the Localised Transmission Mode	Set of the Distributed Transmission Mode
2	2	2
4	4	2
8	1	1
16	1	1
32	0	2

Aggregation Level	Set of the Localised Transmission Mode	Set of the Distributed Transmission Mode
2	2	2
4	5	1
8	1	1
16	1	1
32	0	2

Aggregation Level	Set of the Localised Transmission Mode	Set of the Distributed Transmission Mode
2	2	2
4	6	0
8	1	1
16	1	1
32	0	2

Aggregation Level	Set of the Localised Transmission Mode	Set of the Distributed Transmission Mode
2	4	1
4	4	2
8	1	1
16	1	1
32	0	1

Aggregation Level	Set of the Localised Transmission Mode	Set of the Distributed Transmission Mode
2	4	1
4	3	3
8	1	1
16	1	1
32	0	1

Aggregation Level	Set of the Localised Transmission Mode	Set of the Distributed Transmission Mode
2	4	1
4	5	1
8	1	1

16	1	1
32	0	1

Aggregation Level	Set of the Localised Transmission Mode	Set of the Distributed Transmission Mode
2	4	1
4	6	0
8	1	1
16	1	1
32	0	1

Aggregation Level	Set of the Localised Transmission Mode	Set of the Distributed Transmission Mode
2	4	1
4	6	0
8	1	1
16	1	1
32	0	1

Aggregation Level	Set of the Localised Transmission Mode	Set of the Distributed Transmission Mode
2	3	2
4	3	3
8	1	1
16	1	1
32	0	1

Aggregation Level	Set of the Localised Transmission Mode	Set of the Distributed Transmission Mode
-------------------	---	---

2	3	2
4	4	2
8	1	1
16	1	1
32	0	1

Aggregation Level	Set of the Localised Transmission Mode	Set of the Distributed Transmission Mode
2	3	2
4	5	1
8	1	1
16	1	1
32	0	1

Aggregation Level	Set of the Localised Transmission Mode	Set of the Distributed Transmission Mode
2	3	2
4	6	0
8	1	1
16	1	1
32	0	1

Aggregation Level	Set of the Localised Transmission Mode	Set of the Distributed Transmission Mode
2	5	0
4	6	0
8	1	1
16	1	1
32	0	1

Aggregation Level	Set of the Localised Transmission Mode	Set of the Distributed Transmission Mode
2	4	0
4	6	0
8	1	1
16	1	1
32	0	2

[0097] Optionally, according to the allocation shown in the above tables, the UE may perform proportional allocation of the candidates between different sets according to the number of PRB pairs included in each set of a set type, for example, when the number of control channel candidates allocated to the $K_L = 2$ sets of the localised transmission mode is 3, and the numbers of PRB Pairs included in two sets are 2 and 4 respectively, the 3 control channel candidates are respectively allocated to each set according to the ratio of the number of included PRB Pairs, namely, 1:2. Of course, when the number of control channel candidates is 4, and allocation cannot be performed according to the ratio 1:2, allocation may be performed according to the ratio $\text{ceil}(4/(1 + 2)) - 1 = 1:\text{ceil}(4 * 2/(1 + 2)) = 3$. Ceil means rounding up.

[0098] Optionally, the UE may also obtain, by calculation, the number of control channel candidates allocated to the K_L sets of the localised transmission mode and the K_D sets of the distributed transmission mode. Preferably, for a lower aggregation level supported by the control channel to be transmitted, when the number of control channel candidates corresponding to the lower aggregation level is an even number, the number of control channel candidates allocated to the K_L sets of the localised transmission mode meets the

following formula: $M^{(L)}/2 + \left\lfloor \frac{K_L}{K_L + K_D} \cdot M^{(L)}/2 \right\rfloor$; and the number of control channel

candidates allocated to the K_D sets of the localised transmission mode meets the following

formula: $M^{(L)}/2 - \left\lfloor \frac{K_L}{K_L + K_D} \cdot M^{(L)}/2 \right\rfloor$; when the number of control channel candidates

corresponding to the lower aggregation level is an odd number, the number of control channel candidates allocated to the K_L sets of the localised transmission mode meets the following

formula: $(M^{(L)} + 1)/2 + \left\lfloor \frac{K_L}{K_L + K_D} \cdot (M^{(L)} - 1)/2 \right\rfloor$; and the number of control channel

5 candidates allocated to the K_D sets of the localised transmission mode meets the following

formula: $(M^{(L)} - 1)/2 - \left\lfloor \frac{K_L}{K_L + K_D} \cdot (M^{(L)} - 1)/2 \right\rfloor$; and an allocation ratio of all candidates at

aggregation levels supported by the control channel to be transmitted, except the lower aggregation level, is 1:1 between the K_L sets of the localised transmission mode and the K_D sets of the distributed transmission mode. When the aggregation levels supported by the

10 control channel to be transmitted are 1, 2, 4, 8, and 16, the lower aggregation levels are 1 and 2; when the aggregation levels supported by the control channel to be transmitted are 2, 4, 8, 16, and 32, the lower aggregation levels are 2 and 4.

[0099] Based on the higher-layer semi-statically configured or the calculated number of control channel candidates at each aggregation level in the K_L sets of the localised

15 transmission mode and K_D sets of the distributed transmission mode, for each aggregation

level, when the number of control channel candidates configured for the K_L sets of the localised transmission mode is greater than 1, the number of control channel candidates in each set is determined according to the number of physical resource blocks included in each set of the localised transmission mode; or when the number of control channel candidates

20 configured for the K_D sets of the distributed transmission mode is greater than 1, the number of control channel candidates in each set is determined according to the number of physical resource blocks included in each set of the distributed transmission mode.

[0100] Optionally, the UE may perform proportional allocation of the above candidates between different sets according to the number of PRB pairs included in each set of a set type,

for example, when the number of control channel candidates allocated to the $K_L = 2$ sets of the localised transmission mode is 3, and the numbers of PRB Pairs included in two sets are 2 and 4 respectively, the 3 control channel candidates are respectively allocated to each set according to the ratio of the number of included PRB Pairs, namely, 1:2. Of course, when the number of control channel candidates is 4, and allocation cannot be performed according to the ratio 1:2, allocation may be performed according to the ratio $\text{ceil}(4/(1 + 2)) - 1 = 1:\text{ceil}(4 * 2/(1 + 2)) = 3$. Ceil means rounding up.

[0101] Further, there may be a binding relationship between the number of PRB Pairs specific to the aggregation level and control channel candidates. For example, when the aggregation level is 4 (the corresponding number of control channel candidates is 2), and the number of sets is 4, 2 sets may be first selected from the 4 sets and then allocation and binding of the control channel candidates are performed according to the number of PRB pairs included in the 2 sets. Herein the sets may be selected sequentially according to the ascending order of PRB Pair numbers.

[0102] Optionally, the allocating the control channel candidates at each aggregation level to at least one set in the K sets according to aggregation levels supported by the control channel to be transmitted, the number of control channel candidates corresponding to each aggregation level, the K sets for transmitting the control channel, and types of the sets, includes: allocating all control channel candidates at one or two aggregation levels to at least one set in the K sets.

[0103] Optionally, the UE may bind aggregation levels with the K sets, which means, all candidates at each aggregation level are allocated to at least one specific set, and all candidates at each aggregation level in a transmission mode correspond to one or more ePDCCH sets in the region of the set of the transmission mode. When 4 control channel candidates of the localised transmission mode and 2 control channel candidates of the distributed transmission mode at aggregation levels 1 and 2 are allocated, the UE may allocate the corresponding 4 control channel candidates of the localised transmission mode to the first set of the localised transmission mode in the K_L sets of the localised transmission mode, and allocate the corresponding 2 control channel candidates of the distributed

transmission mode to the first set of the distributed transmission mode in the K_D sets of the distributed transmission mode. When 1 candidate of the localised transmission mode and 1 candidate of the distributed transmission mode at aggregation levels 4 and 8 are allocated, the UE may allocate the corresponding 1 candidate of the localised transmission mode to the second set in the K_L sets of the localised transmission mode, and allocate the corresponding 1 candidate of the distributed transmission mode to the second set in the K_D sets of the distributed transmission mode. All control channel candidates at aggregation levels 16 and 32 are allocated to the third specific set in the region of the distributed transmission mode, where the number of PRB Pairs included in the specific set is at least 4 or 8.

[0104] Binding between the aggregation levels and the K sets may reduce reservations of PUCCH ACK/NCK resource positions, because the number of reserved PUCCH ACK/NCK resources in each set may be determined according to the bound aggregation levels. For example, a set includes 8 PRB pairs, and 32 eCCEs are specially used for placing candidates at aggregation level 16 or/and 32; therefore, when ACK/NACK resources are reserved, only two ACK/NACK resources, instead of 32 resources, need to be reserved.

[0105] Control channel candidates at each aggregation level are placed in each set according to a sequence and a reverse sequence alternately. For example, for candidates at aggregation level 1, one candidate is placed in each PRB Pair according to the ascending order of the PRB Pair numbers, and for candidates at aggregation level 2, one candidate is placed in each PRB Pair according to the descending order of the PRB Pair numbers. Likewise, by analogy, all control channel candidates at aggregation levels 4, 8, and 16 may be placed in the corresponding sets.

[0106] The K_L and K_D for transmitting the control channel are configured, and the number of physical resource block pairs included in each set is configured; or the K_L and K_D for transmitting the control channel are fixed, the number of physical resource block pairs included in each set is configured, and allocation of all control channel candidates at each aggregation level to the K_L and K_D sets is fixed.

[0107] Optionally, a rule for determining the number of control channel candidates corresponding to the aggregation levels that are supported by the control channel to be transmitted is as follows:

[0108] When only the sets of the localised transmission mode exist, namely, $K_L > 0$ and

5 $K_D = 0$, there may be the following two cases for the number of control channel candidates corresponding to each aggregation level.

[0109] 1. Given an extended cyclic prefix and a normal cyclic prefix, and normal subframe/special subframe configurations 3, 4, and 8, when n_{EPDCCH} , the number of available resource elements in each PRB Pair, is greater than or equal to 104 ($n_{\text{EPDCCH}} \geq 104$),

10 the number of control channel candidates corresponding to each aggregation level is shown in the following table:

Type	Search Space $S_k^{(L)}$		Number $M^{(L)}$ of ePDCCH Candidates
	Aggregation Level L	Size [in eCCEs]	
UE-Specific	1	6	6
	2	12	6
	4	8	2
	8	16	2

[0110] 2. Given a normal cyclic prefix and normal subframe/special subframe configurations 3, 4, and 8, when n_{EPDCCH} , the number of available resource elements in each

15 PRB Pair, is less than 104 ($n_{\text{EPDCCH}} < 104$), the number of control channel candidates corresponding to each aggregation level is shown in the following table:

Type	Search Space $S_k^{(L)}$		Number $M^{(L)}$ of ePDCCH Candidates
	Aggregation Level L	Size [in eCCEs]	
UE-Specific	2	12	6
	4	24	6

	8	16	2
	16	32	2

[0111] When only the sets of the distributed transmission mode exist, namely, $K_L = 0$ and $K_D > 0$, there may be the following cases for the number of control channel candidates corresponding to each aggregation level:

- 5 [0112] Given an extended cyclic prefix and a normal cyclic prefix, and normal subframe/special subframe configurations 3, 4, and 8, when n_{EPDCCH} , the number of available resource elements in each PRB Pair, is greater than or equal to 104 ($n_{\text{EPDCCH}} \geq 104$), the number of control channel candidates corresponding to each aggregation level is shown in the following tables:

Type	Search Space $S_k^{(L)}$		Number $M^{(L)}$ of ePDCCH Candidates
	Aggregation Level L	Size [in eCCEs]	
UE-Specific	1	4	4
	2	12	6
	4	8	2
	8	16	2
	16	32	2

10

Type	Search Space $S_k^{(L)}$		Number $M^{(L)}$ of ePDCCH Candidates
	Aggregation Level L	Size [in eCCEs]	
UE-Specific	1	5	5
	2	12	6
	4	8	2
	8	16	2
	16	16	1

[0113] Given a normal cyclic prefix and normal subframe/special subframe configurations 3, 4, and 8, when n_{EPDCCH} , the number of available resource elements in each PRB Pair, is less than 104 ($n_{\text{EPDCCH}} < 104$), the UE blindly detects EPDCCH candidates.

Type	Search Space $S_k^{(L)}$		Number $M^{(L)}$ of ePDCCH Candidates
	Aggregation Level L	Size [in eCCEs]	
UE-Specific	2	8	4
	4	24	6
	8	16	2
	16	32	2
	32	64	2

Type	Search Space $S_k^{(L)}$		Number $M^{(L)}$ of ePDCCH Candidates
	Aggregation Level L	Size [in eCCEs]	
UE-Specific	2	10	5
	4	24	6
	8	16	2
	16	32	2
	32	32	1

5

[0114] The allocation solution considers that control information corresponding to main transmission modes in Rel-11 is usually large and that one purpose of introducing the ePDCCH is to enhance coverage. Therefore, after a new higher aggregation level is introduced for the ePDCCH, the numbers of candidates at other aggregation levels remain unchanged, and 1 or 2 candidates at aggregation level 1 are transferred to the added higher aggregation level.

10

[0115] When the sets of the localised transmission mode and the sets of the distributed transmission mode exist, namely, $K_L > 0$ and $K_D > 0$, there may be the following cases for the number of control channel candidates corresponding to each aggregation level.

[0116] Given an extended cyclic prefix and a normal cyclic prefix, and normal subframe/special subframe configurations 3, 4, and 8, when n_{EPDCCH} , the number of available resource elements in each PRB Pair, is greater than or equal to 104 ($n_{\text{EPDCCH}} \geq 104$), the number of control channel candidates corresponding to each aggregation level is shown in the

5 following table:

Type	Search Space $S_k^{(L)}$		Number $M^{(L)}$ of ePDCCH Candidates
	Aggregation Level L	Size [in eCCEs]	
UE-Specific	1	6	6L
	2	12	6L
	4	1	1L
	8	16	2(1L+1D)
	16	16	1D

[0117] Given a normal cyclic prefix and normal subframe/special subframe configurations 3, 4, and 8, when n_{EPDCCH} , the number of available resource elements in each PRB Pair, is less than 104 ($n_{\text{EPDCCH}} < 104$), the number of control channel candidates corresponding to each

10 aggregation level is shown in the following table:

Type	Search Space $S_k^{(L)}$		Number $M^{(L)}$ of ePDCCH Candidates
	Aggregation Level L	Size [in eCCEs]	
UE-Specific	2	12	6L
	4	24	6L
	8	16	1L
	16	32	2(1L+1D)
	32	32	1L

[0118] Optionally, the maximum value of the number K of sets of all UEs may be fixed to one of 2, 3, 4, and 6, and the number of PRB pairs included in each set changes according to

scenarios. For example, when the number of users in a cell or the number of multiplexed users in each set increases, the number of PRB pairs included in each set also increases. In this case, the UE may cyclically map the corresponding number of control channel candidates corresponding to each aggregation level sequentially according to the sequence of the K sets
5 until the corresponding number of control channel candidates corresponding to each aggregation level are allocated completely.

[0119] This solution may simplify the allocation of all control channel candidates at each aggregation level among K sets (especially in a case where both a set of the localised transmission mode and a set of the distributed transmission mode exist). For example, when
10 the maximum number K of sets is 2, one is a set of the localised transmission mode, and the other is a set of the distributed transmission mode. In this case, all candidates at each aggregation level may be allocated to the two sets respectively according to one half of the number.

[0120] An embodiment of the present invention further provides an apparatus for allocating
15 control channel candidates. As shown in FIG. 2, the apparatus includes a determining unit 201 and an allocating unit 202.

[0121] The determining unit 201 is configured to determine K sets for transmitting a control channel, where each set in the K sets includes at least one physical resource block pair, and K is a positive integer greater than 0; and the allocating unit 202 is configured to allocate,
20 according to at least one of aggregation levels supported by the control channel, the number of control channel candidates corresponding to each aggregation level, the K sets for transmitting the control channel, and types of the sets, each control channel candidate to at least one set in the K sets determined by the determining unit 201.

[0122] The K sets for transmitting the control channel include a set of a localised
25 transmission mode and a set of a distributed transmission mode, where the number of sets of the localised transmission mode is K_L , and the number of sets of the distributed transmission mode is K_D , where $K_L + K_D = K$, and K_L and K_D are integers greater than or equal to 0; and the aggregation levels supported by the control channel include one or more of the following levels: aggregation levels supported by the localised transmission

mode, aggregation levels supported by the distributed transmission mode, and common aggregation levels supported by both the localised transmission mode and the distributed transmission mode.

[0123] Optionally, the allocating unit 202 is specifically configured to: when K_L is a positive integer, allocate all control channel candidates at the aggregation levels supported by the localised transmission mode to at least one of the K_L sets; or when K_D is a positive integer, allocate all control channel candidates at the aggregation levels supported by the distributed transmission mode to at least one of the K_D sets; or when both K_L and K_D are positive integers, allocate all control channel candidates at each aggregation level in the aggregation levels supported by both the localised transmission mode and the distributed transmission mode to at least one of the K_D sets and at least one of the K_L sets.

[0124] The allocating unit 202 being configured to allocate all control channel candidates at each aggregation level in the aggregation levels supported by both the localised transmission mode and the distributed transmission mode to at least one of the K_D sets and at least one of the K_L sets when both K_L and K_D are positive integers, includes: allocating at least one half of all control channel candidates at each first aggregation level in the aggregation levels supported by both the localised transmission mode and the distributed transmission mode to at least one of the K_L sets; and allocating at least one half of all control channel candidates at each second aggregation level in the aggregation levels supported by both the localised transmission mode and the distributed transmission mode to at least one of the K_D sets.

[0125] Herein, when the aggregation levels supported by both the localised transmission mode and the distributed transmission mode are 1, 2, 4, and 8, the first aggregation levels are 1 and 2, and the second aggregation levels are 4 and 8; and when the aggregation levels supported by both the localised transmission mode and the distributed transmission mode are 2, 4, 8, and 16, the first aggregation levels are 2 and 4, and the second aggregation levels are 8 and 16. Remaining control channel candidates at each aggregation level are allocated to

different sets according to a predefined sequence of control channel sets and/or a position of a start set at the aggregation level. The position of a start set at each aggregation level is related to the number of control channel candidates at the aggregation level and configuration of K_L and K_D .

5 [0126] Optionally, when the number of control channel candidates at the aggregation level is 2, remaining control channel candidates are not placed in any set corresponding to a transmission mode of a first control channel candidate.

[0127] The allocating unit 202 being configured to allocate all control channel candidates at an aggregation level supported by only the distributed transmission mode or the localised
10 transmission mode to at least one set in the K_D sets of the distributed transmission mode or in the K_L sets of the localised transmission mode, includes: determining, according to the number of sets used for the aggregation level in K_D or K_L , the number of control channel candidates allocated to each set in the K_D or K_L sets, at the aggregation level; or determining, according to a ratio of the number of physical resource blocks of each set in sets
15 used for the aggregation level in K_D or K_L , the number of control channel candidates allocated to each set in the K_D or K_L sets, at the aggregation level.

[0128] The allocating unit 202 being configured to allocate all control channel candidates at each aggregation level in the aggregation levels supported by both the localised transmission mode and the distributed transmission mode to at least one of the K_D sets and at least one
20 of the K_L sets when both K_L and K_D are positive integers, includes: determining, according to a ratio between the numbers of sets used for the aggregation level in K_D and K_L , the numbers of control channel candidates allocated to the K_L and K_D sets, at each aggregation level; or determining, according to a ratio between the total numbers of physical resource blocks in sets used for the aggregation level in K_D and K_L , the numbers of
25 control channel candidates allocated to the K_L and K_D sets, at each aggregation level; or

determining, according to a ratio of the number of physical resource blocks of each set in sets used for the aggregation level in K_D and K_L , the number of control channel candidates allocated to each set in the K_L and K_D sets, at each aggregation level.

[0129] At each aggregation level, the numbers of control channel candidates allocated to the K_L and K_D sets are configured. The configuration is a higher-layer semi-static configuration.

[0130] At each aggregation level, when the number of control channel candidates configured for the K_L (greater than 1) sets is greater than 1, the allocating unit 202 is configured to determine the number of control channel candidates in each set according to the number of physical resource blocks included in each set that can support the aggregation level in the K_L sets or the number of sets that can support the aggregation level in the K_L sets, or when the number of control channel candidates configured for the K_D (greater than 1) sets is greater than 1, the allocating unit 202 is configured to determine the number of control channel candidates in each set according to the number of physical resource blocks included in each set that can support the aggregation level in the K_D sets or the number of sets that can support the aggregation level in the K_D sets.

[0131] At each aggregation level supported by the control channel to be transmitted, the number of control channel candidates allocated to the K_L sets of the localised transmission mode and the number of control channel candidates allocated to the K_D sets of the distributed transmission mode are functions of at least one of the number of control channel candidates at the aggregation level, the number K_L of sets of the localised transmission mode, and the number K_D of sets of the distributed transmission mode.

[0132] When the number of control channel candidates corresponding to the aggregation levels supported by both the localised transmission mode and the distributed transmission mode is an even number, the number of control channel candidates allocated to the K_L sets

of the localised transmission mode meets the following formula:

$M^{(L)}/2 + \left\lfloor \frac{K_L}{K_L + K_D} \cdot M^{(L)}/2 \right\rfloor$; and the number of control channel candidates allocated to the

K_D sets of the distributed transmission mode meets the following formula:

$M^{(L)}/2 - \left\lfloor \frac{K_L}{K_L + K_D} \cdot M^{(L)}/2 \right\rfloor$. When the number of control channel candidates

5 corresponding to the lower aggregation levels is an odd number, the number of control channel candidates allocated to the K_L sets of the localised transmission mode meets the

following formula: $(M^{(L)} + 1)/2 + \left\lfloor \frac{K_L}{K_L + K_D} \cdot (M^{(L)} - 1)/2 \right\rfloor$; and the number of control

channel candidates allocated to the K_D sets of the distributed transmission mode meets the

following formula: $(M^{(L)} - 1)/2 - \left\lfloor \frac{K_L}{K_L + K_D} \cdot (M^{(L)} - 1)/2 \right\rfloor$. An allocation ratio of all

10 candidates at aggregation levels where the number of control channel candidates is 2, is 1:1 between the K_L sets of the localised transmission mode and the K_D sets of the distributed transmission mode.

[0133] The allocating unit 202 is configured to determine that at least one set in the K sets for transmitting the control channel is used to allocate control channel candidates at one or
15 two aggregation levels.

[0134] A rule for determining aggregation levels that can be supported by the control channel to be transmitted includes:

when the total number of aggregation levels that can be supported by the control channel is N, obtaining, according to the number of valid physical resource elements included
20 in each physical resource block pair, k ($k \leq N$) aggregation levels in the N aggregation levels as aggregation levels of the control channel to be transmitted, or

configuring, semi-statically through RRC signaling, k ($k \leq N$) aggregation levels in the N aggregation levels as aggregation levels that can be supported by the control channel to be transmitted.

[0135] A form of semi-static configuration through RRC signaling is a bitmap (Bitmap).

[0136] If the number of aggregation levels of the control channel to be transmitted is N, the numbers of control channel candidates corresponding to any p ($p \leq 4$) aggregation levels in 4 aggregation levels (1, 2, 4, 8) in an original protocol are respectively configured for corresponding aggregation levels in the N aggregation levels of the control channel to be transmitted, and the numbers of control channel candidates corresponding to remaining (4-p) aggregation levels in the 4 aggregation levels (1, 2, 4, 8) in the original protocol are correspondingly configured for remaining N-p aggregation levels in the N aggregation levels of the control channel to be transmitted.

[0137] Optionally, the apparatus includes a detecting unit. When the aggregation levels supported by the control channel to be transmitted include 32, and the number of available resource elements in each physical resource block pair except resource elements of other signals, such as a CRS, a DMRS, a CSI-RS, a PDCCH, is greater than or equal to 72, the detecting unit does not detect control channel candidates at aggregation level 32; otherwise, the detecting unit detects the control channel candidates at aggregation level 32; or, when the aggregation levels supported by the control channel to be transmitted do not include 32, and the number of available resource elements in each physical resource block pair except resource elements of other signals, such as a CRS, a DMRS, a CSI-RS, a PDCCH, is less than 72, the detecting unit detects control channel candidates at aggregation level 8.

[0138] When the control channel to be transmitted is transmitted with an extended cyclic prefix, and the supported aggregation levels include 16, and the number of available resource elements in each physical resource block pair except resource elements of other signals, such as a CRS, a DMRS, a CSI-RS, a PDCCH, is greater than or equal to 72, the detecting unit does not detect control channel candidates at aggregation level 16; otherwise, the detecting unit detects the control channel candidates at aggregation level 16; or, when the control channel to be transmitted is transmitted with an extended cyclic prefix, and the supported aggregation levels do not include 16, and the number of available resource elements in each physical resource block pair except resource elements of other signals, such as a CRS, a DMRS, a CSI-RS, a PDCCH, is less than 72, the detecting unit detects PDCCH candidates at aggregation level 8.

[0139] The K_L and K_D for transmitting the control channel are configured, and the number of physical resource block pairs included in each set is configured; or the K_L and K_D for transmitting the control channel are fixed, the number of physical resource block pairs included in each set is configured, and allocation of all control channel candidates at each aggregation level to the K_L and K_D sets is fixed.

[0140] Herein the configuration refers to parameters configured by the base station for the UE through higher-layer signaling, which means, values of the K_L and K_D and the number of physical resource block pairs included in each set may all be configured by the base station for the UE.

[0141] An embodiment of the present invention further provides an apparatus for allocating control channel candidates. As shown in FIG. 3, the apparatus includes a receiver 32, a transmitter 31, a memory 33, and a processor 34 that is connected to the receiver 31, the transmitter 32, and the memory 33, where the receiver may be configured to receive higher-layer signaling sent by a base station. The memory stores a group of program codes, and the processor invokes the program codes in the memory to perform operations.

[0142] The processor 34 is configured to determine K sets for transmitting a control channel, where each set in the K sets includes at least one physical resource block pair, and K is a positive integer greater than 0; the processor 34 is configured to allocate, according to at least one of aggregation levels supported by the control channel, the number of control channel candidates corresponding to each aggregation level, the K sets for transmitting the control channel, and types of the sets, each control channel candidate to at least one set in the K sets determined by the processor 34.

[0143] The K sets for transmitting the control channel include a set of a localised transmission mode and a set of a distributed transmission mode, where the number of sets of the localised transmission mode is K_L , and the number of sets of the distributed transmission mode is K_D , where $K_L + K_D = K$, and K_L and K_D are integers greater than or equal to 0; and the aggregation levels supported by the control channel include one or

more of the following levels: aggregation levels supported by the localised transmission mode, aggregation levels supported by the distributed transmission mode, and common aggregation levels supported by both the localised transmission mode and the distributed transmission mode.

- 5 [0144] Optionally, the processor 34 is specifically configured to: when K_L is a positive integer, allocate all control channel candidates at the aggregation levels supported by the localised transmission mode to at least one of the K_L sets; or when K_D is a positive integer, allocate all control channel candidates at the aggregation levels supported by the distributed transmission mode to at least one of the K_D sets; or when both K_L and K_D are positive integers, allocate all control channel candidates at each aggregation level in the aggregation levels supported by both the localised transmission mode and the distributed transmission mode to at least one of the K_D sets and at least one of the K_L sets.

- [0145] The processor 34 being configured to allocate all control channel candidates at each aggregation level in the aggregation levels supported by both the localised transmission mode and the distributed transmission mode to at least one of the K_D sets and at least one of the K_L sets when both K_L and K_D are positive integers, includes: allocating at least one half of all control channel candidates at each first aggregation level in the aggregation levels supported by both the localised transmission mode and the distributed transmission mode to at least one of the K_L sets; and allocating at least one half of all control channel candidates at each second aggregation level in the aggregation levels supported by both the localised transmission mode and the distributed transmission mode to at least one of the K_D sets.

- [0146] Herein, when the aggregation levels supported by both the localised transmission mode and the distributed transmission mode are 1, 2, 4, and 8, the first aggregation levels are 1 and 2, and the second aggregation levels are 4 and 8; and when the aggregation levels supported by both the localised transmission mode and the distributed transmission mode are 2, 4, 8, and 16, the first aggregation levels are 2 and 4, and the second aggregation levels are 8 and 16. Remaining control channel candidates at each aggregation level are allocated to

different sets according to a predefined sequence of control channel sets and/or a position of a start set at the aggregation level. The position of a start set at each aggregation level is related to the number of control channel candidates at the aggregation level and configuration of K_L and K_D .

5 [0147] Optionally, when the number of control channel candidates at the aggregation level is 2, remaining control channel candidates are not placed in any set corresponding to a transmission mode of a first control channel candidate.

[0148] The processor 34 being configured to allocate all control channel candidates at an aggregation level supported by only the distributed transmission mode or the localised
10 transmission mode to at least one set in the K_D sets of the distributed transmission mode or in the K_L sets of the localised transmission mode, includes: determining, according to the number of sets used for the aggregation level in K_D or K_L , the number of control channel candidates allocated to each set in the K_D or K_L sets, at the aggregation level; or determining, according to a ratio of the number of physical resource blocks of each set in sets
15 used for the aggregation level in K_D or K_L , the number of control channel candidates allocated to each set in the K_D or K_L sets, at the aggregation level.

[0149] The processor 34 being configured to allocate all control channel candidates at each aggregation level in the aggregation levels supported by both the localised transmission mode and the distributed transmission mode to at least one of the K_D sets and at least one of the
20 K_L sets when both K_L and K_D are positive integers, includes: determining, according to a ratio between the numbers of sets used for the aggregation level in K_D and K_L , the numbers of control channel candidates allocated to the K_L and K_D sets, at each aggregation level; or determining, according to a ratio between the total numbers of physical resource blocks in sets used for the aggregation level in K_D and K_L , the numbers of
25 control channel candidates allocated to the K_L and K_D sets, at each aggregation level; or

determining, according to a ratio of the number of physical resource blocks of each set in sets used for the aggregation level in K_D and K_L , the number of control channel candidates allocated to each set in the K_L and K_D sets, at each aggregation level.

[0150] At each aggregation level, the numbers of control channel candidates allocated to the K_L and K_D sets are configured. The configuration is a higher-layer semi-static configuration.

[0151] At each aggregation level, when the number of control channel candidates configured for the K_L (greater than 1) sets is greater than 1, the processor 34 is configured to determine the number of control channel candidates in each set according to the number of physical resource blocks included in each set that can support the aggregation level in the K_L sets or the number of sets that can support the aggregation level in the K_L sets, or when the number of control channel candidates configured for the K_D (greater than 1) sets is greater than 1, the processor 34 is configured to determine the number of control channel candidates in each set according to the number of physical resource blocks included in each set that can support the aggregation level in the K_D sets or the number of sets that can support the aggregation level in the K_D sets.

[0152] At each aggregation level supported by the control channel to be transmitted, the number of control channel candidates allocated to the K_L sets of the localised transmission mode and the number of control channel candidates allocated to the K_D sets of the distributed transmission mode are functions of at least one of the number of control channel candidates at the aggregation level, the number K_L of sets of the localised transmission mode, and the number K_D of sets of the distributed transmission mode.

[0153] When the number of control channel candidates corresponding to the aggregation levels supported by both the localised transmission mode and the distributed transmission mode is an even number, the number of control channel candidates allocated to the K_L sets

of the localised transmission mode meets the following formula:

$M^{(L)}/2 + \left\lfloor \frac{K_L}{K_L + K_D} \cdot M^{(L)}/2 \right\rfloor$; and the number of control channel candidates allocated to the

K_D sets of the distributed transmission mode meets the following formula:

$M^{(L)}/2 - \left\lfloor \frac{K_L}{K_L + K_D} \cdot M^{(L)}/2 \right\rfloor$. When the number of control channel candidates

5 corresponding to the lower aggregation levels is an odd number, the number of control channel candidates allocated to the K_L sets of the localised transmission mode meets the

following formula: $(M^{(L)} + 1)/2 + \left\lfloor \frac{K_L}{K_L + K_D} \cdot (M^{(L)} - 1)/2 \right\rfloor$; and the number of control

channel candidates allocated to the K_D sets of the distributed transmission mode meets the

following formula: $(M^{(L)} - 1)/2 - \left\lfloor \frac{K_L}{K_L + K_D} \cdot (M^{(L)} - 1)/2 \right\rfloor$. An allocation ratio of all

10 candidates at aggregation levels where the number of control channel candidates is 2, is 1:1 between the K_L sets of the localised transmission mode and the K_D sets of the distributed transmission mode.

[0154] The processor 34 is configured to determine that at least one set in the K sets for transmitting the control channel is used to allocate control channel candidates at one or two
15 aggregation levels.

[0155] A rule for determining aggregation levels that can be supported by the control channel to be transmitted includes:

when the total number of aggregation levels that can be supported by the control channel is N, obtaining, according to the number of valid physical resource elements included
20 in each physical resource block pair, k ($k \leq N$) aggregation levels in the N aggregation levels as aggregation levels of the control channel to be transmitted, or

configuring, semi-statically through RRC signaling, k ($k \leq N$) aggregation levels in the N aggregation levels as aggregation levels that can be supported by the control channel to be transmitted.

[0156] A form of semi-static configuration through RRC signaling is a bitmap (Bitmap).

[0157] If the number of aggregation levels of the control channel to be transmitted is N, the numbers of control channel candidates corresponding to any p ($p \leq 4$) aggregation levels in 4 aggregation levels (1, 2, 4, 8) in an original protocol are respectively configured for corresponding aggregation levels in the N aggregation levels of the control channel to be transmitted, and the numbers of control channel candidates corresponding to remaining (4-p) aggregation levels in the 4 aggregation levels (1, 2, 4, 8) in the original protocol are correspondingly configured for remaining N-p aggregation levels in the N aggregation levels of the control channel to be transmitted.

[0158] Optionally, the apparatus includes a detecting unit. When the aggregation levels supported by the control channel to be transmitted include 32, and the number of available resource elements in each physical resource block pair except resource elements of other signals, such as a CRS, a DMRS, a CSI-RS, a PDCCH, is greater than or equal to 72, the detecting unit does not detect control channel candidates at aggregation level 32; otherwise, the detecting unit detects the control channel candidates at aggregation level 32; or, when the aggregation levels supported by the control channel to be transmitted do not include 32, and the number of available resource elements in each physical resource block pair except resource elements of other signals, such as a CRS, a DMRS, a CSI-RS, a PDCCH, is less than 72, the detecting unit detects control channel candidates at aggregation level 8.

[0159] When the control channel to be transmitted is transmitted with an extended cyclic prefix, and the supported aggregation levels include 16, and the number of available resource elements in each physical resource block pair except resource elements of other signals, such as a CRS, a DMRS, a CSI-RS, a PDCCH, is greater than or equal to 72, the detecting unit does not detect control channel candidates at aggregation level 16; otherwise, the detecting unit detects the control channel candidates at aggregation level 16; or, when the control channel to be transmitted is transmitted with an extended cyclic prefix, and the supported aggregation levels do not include 16, and the number of available resource elements in each physical resource block pair except resource elements of other signals, such as a CRS, a DMRS, a CSI-RS, a PDCCH, is less than 72, the detecting unit detects PDCCH candidates at aggregation level 8.

[0160] The K_L and K_D for transmitting the control channel are configured, and the number of physical resource block pairs included in each set is configured; or the K_L and K_D for transmitting the control channel are fixed, the number of physical resource block pairs included in each set is configured, and allocation of all control channel candidates at each aggregation level to the K_L and K_D sets is fixed.

[0161] Herein the configuration refers to parameters configured by the base station for the UE through higher-layer signaling, which means, values of the K_L and K_D and the number of physical resource block pairs included in each set may all be configured by the base station for the UE.

[0162] In the method and apparatus for allocating control channel candidates according to the embodiments of the present invention, K sets for transmitting a control channel are determined, and control channel candidates at each aggregation level are allocated to at least one set in the K sets according to at least one of aggregation levels supported by the control channel to be transmitted, the number of control channel candidates corresponding to each aggregation level, the K sets for transmitting the control channel, and types of the sets. Therefore, control channel candidates at different aggregation levels can be allocated to K ePDCCH sets, and a search space of a UE is defined, thereby reducing complexity of blind detection performed by the UE.

[0163] The foregoing descriptions are merely specific embodiments of the present invention, but are not intended to limit the protection scope of the present invention. Any variation or replacement readily figured out by a person skilled in the art within the technical scope disclosed in the present invention shall fall within the protection scope of the present invention. Therefore, the protection scope of the present invention shall be subject to the protection scope of the claims.

CLAIMS

What is claimed is:

1. A method for allocating control channel candidates, comprising:

determining K sets for transmitting a control channel, wherein each set in the K sets
5 comprises at least one physical resource block pair, and K is an integer greater than 0; and

allocating control channel candidates at each aggregation level to at least one set in the K sets according to the following factors: aggregation levels supported by the control channel, the number of control channel candidates corresponding to each aggregation level, the K sets for transmitting the control channel, and types of the sets, which comprises:

10 when K_L is a positive integer, allocating all control channel candidates at the aggregation levels supported by the localised transmission mode to at least one of the K_L sets; or

when K_D is a positive integer, allocating all control channel candidates at the aggregation levels supported by the distributed transmission mode to at least one of the K_D
15 sets; or

when both K_L and K_D are positive integers, allocating all control channel candidates at each aggregation level in the aggregation levels supported by both the localised transmission mode and the distributed transmission mode to at least one of the K_L sets and at least one of the K_D sets;

20 wherein: the K sets for transmitting the control channel comprise one or both of a set of a localised transmission mode and a set of a distributed transmission mode, wherein the number of sets of the localised transmission mode is K_L , and the number of sets of the distributed transmission mode is K_D , $K_L + K_D = K$, and K_L and K_D are integers greater than or equal to 0; and

25 the aggregation levels supported by the control channel comprise one or more of the

following levels:

aggregation levels supported by the localised transmission mode, aggregation levels supported by the distributed transmission mode, and common aggregation levels supported by both the localised transmission mode and the distributed transmission mode.

5

2. The method according to claim 1, wherein when both K_L and K_D are positive integers, the allocating all control channel candidates at each aggregation level in the aggregation levels supported by both the localised transmission mode and the distributed transmission mode to at least one of the K_L sets and at least one of the K_D sets

10 comprises:

allocating at least one half of all control channel candidates at each first aggregation level in the aggregation levels supported by both the localised transmission mode and the distributed transmission mode to at least one of the K_L sets; and

15 allocating at least one half of all control channel candidates at each second aggregation level in the aggregation levels supported by both the localised transmission mode and the distributed transmission mode to at least one of the K_D sets.

3. The method according to claim 2, wherein:

20 when the aggregation levels supported by both the localised transmission mode and the distributed transmission mode are 1, 2, 4, and 8, the first aggregation levels are 1 and 2, and the second aggregation levels are 4 and 8; and

when the aggregation levels supported by both the localised transmission mode and the distributed transmission mode are 2, 4, 8, and 16, the first aggregation levels are 2 and 4, and the second aggregation levels are 8 and 16.

4. The method according to claim 2 or 3, wherein:

25 remaining control channel candidates at each aggregation level are allocated to different sets according to a predefined sequence of control channel sets and/or a position of a start set at the aggregation level.

5. The method according to claim 1, wherein all control channel candidates at an

aggregation level supported by only the distributed transmission mode or the localised transmission mode are allocated to at least one set in the K_D sets of the distributed transmission mode or in the K_L sets of the localised transmission mode.

6. The method according to claim 5, wherein allocating all control channel candidates at an aggregation level supported by only the distributed transmission mode or the localised transmission mode to at least one set in the K_D sets of the distributed transmission mode or in the K_L sets of the localised transmission mode comprises:

determining, according to the number of sets used for the aggregation level in K_D or K_L sets, the number of control channel candidates allocated to each set in the K_D or K_L sets, at the aggregation level; or

determining, according to a ratio of the number of physical resource blocks of each set in sets used for the aggregation level in K_D or K_L sets, the number of control channel candidates allocated to each set in the K_D or K_L sets, at the aggregation level.

7. The method according to claim 6, wherein the determining, according to a ratio of the number of physical resource blocks of each set in sets used for the aggregation level in K_D or K_L sets, the number of control channel candidates allocated to each set in the K_D or K_L sets, at the aggregation level comprises:

allocating c_i control channel candidates to set s_i supporting an aggregation level L ,

wherein the number c_i is indicated by $c_i = \left\lfloor \frac{C_L \times N_i}{\sum_{j=1}^T N_j} \right\rfloor$, L is the aggregation level supported by

only the distributed transmission mode or the localised transmission mode, C_L is the number of control channel candidates at the aggregation level L ; s_i is a set supporting the aggregation level L , c_i is the number of control channel candidates allocated to the set s_i , $i \in [1, T]$, and T is a positive integer;

allocating remaining R control channel candidates to R sets according to a preset rule,
wherein the number R is indicated by $R = C_L - \sum_{j=1}^T c_j$,

and the preset rule comprises: allocating one control channel candidate to each set of the
R sets according to a descending order of the number of physical resource block pairs
5 included in each set.

8. The method according to claim 1, wherein when both K_L and K_D are positive
integers, the allocating all control channel candidates at each aggregation level in the
aggregation levels supported by both the localised transmission mode and the distributed
transmission mode to at least one of the K_L sets and at least one of the K_D sets,
10 comprises:

determining, according to a ratio between the numbers of sets used for the aggregation
level in K_D and K_L , the numbers of control channel candidates allocated to the K_L and
 K_D sets at each aggregation level; or

determining, according to a ratio between the total numbers of physical resource blocks
15 in sets used for the aggregation levels in K_D and K_L , the numbers of control channel
candidates allocated to the K_L and K_D sets at each aggregation level; or

determining, according to a ratio of the number of physical resource blocks of each set
in sets used for the aggregation level in K_D and K_L , the number of control channel
candidates allocated to each set in the K_L and K_D sets at each aggregation level.

20 9. The method according to claim 1, wherein:

at each aggregation level, when the number of control channel candidates configured for
the K_L sets is greater than 1, the number of control channel candidates in each set is
determined according to the number of physical resource blocks comprised in each set that
can support the aggregation level in the K_L sets or the number of sets that can support the
25 aggregation level in the K_L sets, wherein K_L is greater than 1; or

when the number of control channel candidates configured for the K_D sets is greater than 1, the number of control channel candidates in each set is determined according to the number of physical resource blocks comprised in each set that can support the aggregation level in the K_D sets or the number of sets that can support the aggregation level in the K_D sets, wherein K_D is greater than 1.

10. The method according to claim 9, wherein when the number of control channel candidates configured for the K_L or K_D sets is greater than 1, determining the number of control channel candidates in each set according to the number of physical resource blocks comprised in each set that can support the aggregation level in the K_L or K_D sets comprises:

allocating c_i control channel candidates to set s_i supporting an aggregation level L ,

wherein the number c_i is indicated by $c_i = \left\lfloor \frac{C_L \times N_i}{\sum_{j=1}^T N_j} \right\rfloor$, L is an aggregation level, C_L is the

number of control channel candidates at the aggregation level L ; s_i is a set supporting the aggregation level L , c_i is the number of control channel candidates allocated to the set s_i , $i \in$

$\{1, T\}$, and T is a positive integer;

allocating remaining R control channel candidates to R sets according to a preset rule,

wherein the number R is indicated by $R = C_L - \sum_{j=1}^T c_j$,

and the preset rule comprises: allocating one control channel candidate to each set of the R sets according to a descending order of the number of physical resource block pairs included in each set.

11. An apparatus for allocating control channel candidates, comprising:

a determining unit, configured to determine K sets for transmitting a control channel, wherein each set in the K sets comprises at least one physical resource block pair, and K is an integer greater than 0; and

an allocating unit, configured to allocate, according to the following factors: aggregation

levels supported by the control channel, the number of control channel candidates corresponding to each aggregation level, the K sets for transmitting the control channel, and types of the sets, control channel candidates at each aggregation level to at least one set in the K sets determined by the determining unit, wherein the allocating unit is configured to:

5 allocate, when K_L is a positive integer, all control channel candidates at the aggregation levels supported by the localised transmission mode to at least one of the K_L sets; or

allocate, when K_D is a positive integer, all control channel candidates at the aggregation levels supported by the distributed transmission mode to at least one of the K_D

10 sets; or

allocate, when both K_L and K_D are positive integers, all control channel candidates at each aggregation level in the aggregation levels supported by both the localised transmission mode and the distributed transmission mode to at least one of the K_L sets and at least one of the K_D sets; wherein: the K sets for transmitting the control channel comprise one or both of a set of a localised transmission mode and a set of a distributed transmission mode, wherein the number of sets of the localised transmission mode is K_L , and the number of sets of the distributed transmission mode is K_D , $K_L + K_D = K$, and K_L and K_D are integers greater than or equal to 0; and

20 the aggregation levels supported by the control channel comprise one or more of the following levels:

aggregation levels supported by the localised transmission mode, aggregation levels supported by the distributed transmission mode, and common aggregation levels supported by both the localised transmission mode and the distributed transmission mode.

25 12. The apparatus according to claim 11, wherein the allocating unit being configured to allocate all control channel candidates at each aggregation level in the aggregation levels supported by both the localised transmission mode and the distributed transmission mode to

at least one of the K_L sets and at least one of the K_D sets when both K_L and K_D are positive integers, comprises:

allocating at least one half of all control channel candidates at each first aggregation level in the aggregation levels supported by both the localised transmission mode and the distributed transmission mode to at least one of the K_L sets; and

allocating at least one half of all control channel candidates at each second aggregation level in the aggregation levels supported by both the localised transmission mode and the distributed transmission mode to at least one of the K_D sets.

13. The apparatus according to claim 12, wherein:

when the aggregation levels supported by both the localised transmission mode and the distributed transmission mode are 1, 2, 4, and 8, the first aggregation levels are 1 and 2, and the second aggregation levels are 4 and 8; and

when the aggregation levels supported by both the localised transmission mode and the distributed transmission mode are 2, 4, 8, and 16, the first aggregation levels are 2 and 4, and the second aggregation levels are 8 and 16.

14. The apparatus according to claim 12 or 13, wherein:

remaining control channel candidates at each aggregation level are allocated to different sets according to a predefined sequence of control channel sets and/or a position of a start set at the aggregation level.

15. The apparatus according to claim 11, wherein the allocating unit is configured to allocate all control channel candidates at an aggregation level supported by only the distributed transmission mode or the localised transmission mode to at least one set in the K_D sets of the distributed transmission mode or the K_L sets of the localised transmission mode.

16. The apparatus according to claim 25, wherein the allocating unit being configured to allocate all control channel candidates at an aggregation level supported by only the distributed transmission mode or the localised transmission mode to at least one set in the K_D sets of the distributed transmission mode or the K_L sets of the localised transmission

mode, comprises:

determine, according to the number of sets used for the aggregation level in K_D or K_L sets, the number of control channel candidates allocated to each set in the K_D or K_L sets, at the aggregation level; or

- 5 determine, according to a ratio of the number of physical resource blocks of each set in sets used for the aggregation level in K_D or K_L sets, the number of control channel candidates allocated to each set in the K_D or K_L sets, at the aggregation level.

17. The apparatus according to claim 16, wherein when the the number of control channel candidates allocated to each set in the K_D or K_L sets is determined according to a
10 ratio of the number of physical resource blocks of each set in sets used for the aggregation level in K_D or K_L sets, the allocating unit is configured to:

allocate c_i control channel candidates to set s_i supporting an aggregation level L ,

wherein the number c_i is indicated by $c_i = \left\lfloor \frac{C_L \times N_i}{\sum_{j=1}^T N_j} \right\rfloor$, L is the aggregation level supported by

only the distributed transmission mode or the localised transmission mode, C_L is the
15 number of control channel candidates at the aggregation level L ; s_i is a set supporting the aggregation level L , c_i is the number of control channel candidates allocated to the set s_i , $i \in [1, T]$, and T is a positive integer;

allocate remaining R control channel candidates to R sets according to a preset rule,

wherein the number R is indicated by $R = C_L - \sum_{j=1}^T c_j$,

20 and the preset rule comprises: allocating one control channel candidate to each set of the R sets according to a descending order of the number of physical resource block pairs included in each set.

18. The apparatus according to claim 11, wherein the allocating unit being configured to allocate all control channel candidates at each aggregation level in the aggregation levels

supported by both the localised transmission mode and the distributed transmission mode to at least one of the K_L sets and at least one of the K_D sets when both K_L and K_D are positive integers, comprises:

determining, according to a ratio between the numbers of sets used for the aggregation level in K_D and K_L , the numbers of control channel candidates allocated to the K_L and K_D sets, at each aggregation level; or

determining, according to a ratio between the total numbers of physical resource blocks in sets used for the aggregation level in K_D and K_L , the numbers of control channel candidates allocated to the K_L and K_D sets, at each aggregation level; or

determining, according to a ratio of the number of physical resource blocks of each set in sets used for the aggregation level in K_D and K_L , the number of control channel candidates allocated to each set in the K_L and K_D sets, at each aggregation level.

19. The apparatus according to claim 11, wherein:

at each aggregation level, when the number of control channel candidates configured for the K_L sets is greater than 1, the allocating unit is configured to determine the number of control channel candidates in each set according to the number of physical resource blocks comprised in each set that can support the aggregation level in the K_L sets or the number of sets that can support the aggregation level in the K_L sets, wherein K_L is greater than 1; or

when the number of control channel candidates configured for the K_D sets is greater than 1, the allocating unit is configured to determine the number of control channel candidates in each set according to the number of physical resource blocks comprised in each set that can support the aggregation level in the K_D sets or the number of sets that can support the aggregation level in the K_D sets, wherein K_D is greater than 1.

20. The apparatus according to claim 19, wherein when the number of control channel candidates configured for the K_L or K_D sets is greater than 1, and the number of control

channel candidates in each set is determined according to the number of physical resource blocks comprised in each set that can support the aggregation level in the K_L or K_D sets, the allocating unit is configured to:

allocate c_i control channel candidates to set s_i supporting an aggregation level L ,

5 wherein the number c_i is indicated by
$$c_i = \left\lfloor \frac{C_L \times N_i}{\sum_{j=1}^T N_j} \right\rfloor$$
, L is an aggregation level, C_L is the

number of control channel candidates at the aggregation level L ; s_i is a set supporting the aggregation level L , c_i is the number of control channel candidates allocated to the set s_i , $i \in [1, T]$, and T is a positive integer;

allocate remaining R control channel candidates to R sets according to a preset rule,

10 wherein the number R is indicated by
$$R = C_L - \sum_{j=1}^T c_j$$
,

and the preset rule comprises: allocating one control channel candidate to each set of the R sets according to a descending order of the number of physical resource block pairs included in each set.