

Description

The invention relates to a circuit that generates a train of higher frequency pulses synchronized to input synchronization pulses, such as may be used in a television apparatus.

Recently there has been an interest in displaying an interlaced type video signal such as of the NTSC standard, in a non-interlaced scanning format for reducing the effects of artifacts. Such display format generally requires deflection current switching at a frequency which is a multiple of the horizontal frequency, f_H , of the horizontal sync pulses. In television systems using double-horizontal rate scanning format, for example, it may be required to generate two cycles of horizontal deflection current from each horizontal sync pulse. In comparison, in standard television systems, the correspondence is one cycle from each sync pulse.

In some prior art circuits, the doubling of the horizontal rate frequency is accomplished by a phase-lock-loop circuit that includes a voltage controlled oscillator (VCO). The output frequency of the VCO is equal to a multiple of the horizontal rate. In digital television, for example, it is desirable to generate the deflection current using signals that are derived from a common system clock, rather than from a VCO.

It is also known, see US-A-4,317,133, to provide an analog two-loop horizontal automatic frequency phase control system comprising a first loop responsive to input horizontal sync signals for producing an output signal in frequency and phase synchronism with the horizontal sync signal. A second loop is responsive to the output signal and to flyback pulses in order to adjust the phase of horizontal deflection drive signals, in order to centre the picture on a TV screen. It would be desirable to adopt such a known two-loop system to a digital system as described above with a double horizontal rate frequency.

In view of the above, the present invention provides a deflection apparatus responsive to a line synchronizing input signal for generating a deflection output signal that forms corresponding deflection cycles in a deflection circuit during a given period of said input signal such that the frequency of said deflection cycles is an integer multiple of said input signal, said apparatus comprising, a phase-lock-loop circuit responsive to said line synchronizing input signal for generating in said given period thereof a periodic signal at a frequency that is related to the frequency of said input signal; a line output stage of said line deflection circuit responsive to said output signal for generating said multiple frequency deflection cycles and for developing a deflection cycle indicative signal that contains phase information of said higher frequency deflection cycles; and a phase-control-loop having a phase detector that generates a control signal in accordance with said higher frequency deflection cycle indicative signal and in accordance with said periodic signal, said phase-control-loop being responsive to said periodic signal for generating said output signal that forms said deflection cycles at the frequency that is a multiple of said input signal and in a phase that is determined in accordance with said control signal of said phase detector.

In an apparatus embodying an aspect of the invention, a phase-lock-loop circuit responsive to a periodic line synchronizing input signal is used for generating, at the same relative times, respectively, to the input signal, and in each period of the input signal, synchronized first and second periodic signals respectively.

In accordance with an aspect of the invention, a phase control-loop circuit is responsive to a deflection cycle indicative signal of a deflection circuit and to at least one of said first and second periodic signals for generating first and second deflection output signals each period of the line synchronizing input signal. An output stage of the deflection circuit is used for generating a cycle of deflection current upon the occurrence of each one of the first and second deflection output signals.

In carrying out a specific embodiment of the invention, for example, the circuit doubles the frequency of the sync pulses to obtain, in the output stage, deflection current at the frequency of $2xf_H$.

The timings of each of the first and second periodic signals is defined with a resolution of a fraction of a common clock signal period. Each period of the synchronizing input signal results in a corresponding sequence of states in the phase-lock-loop circuit. Each state is produced synchronously with the common clock signal. The phase-lock-loop circuit supplies the first and second periodic signals that are indicative of a first and second periodic events, respectively, to a phase-control-loop circuit for generating the first and second deflection output signals, respectively, therefrom.

In accordance with another aspect of the invention, the phase-control-loop circuit receives a retrace signal from the deflection circuit output stage for correcting, illustratively, only once during a given period of the synchronizing input signal, and in accordance with the timings of one signal of the first and second signals, the timings of the output signals. The output signals timings are corrected, so as to make the timings of alternate deflection cycles correspond with the first and second periodic events, respectively.

In accordance with yet another aspect of the invention, the tracking response time, in the phase-control-loop circuit, with respect to phase variations of the retrace signal is faster than the corresponding tracking response, in the phase-lock-loop circuit, with respect to phase variations of the synchronizing input signal

that contains the sync pulses. This is so, because the phase-control-loop circuit is optimized to accommodate fast switching time variations in the output stage that may occur because of fast changing electron beam current; whereas the phase-lock-loop circuit is optimized to reject noise or jitter accompanying the sync pulses.

5 In the drawing:

FIGURE 1 illustrates a general block diagram of a deflection circuit that includes a phase-lock-loop circuit and a phase-control-loop circuit, embodying an aspect of the invention;

FIGURE 2 illustrates a detailed block diagram of the deflection circuit of FIGURE 1;

FIGURES 3a-3g illustrate timing diagrams useful in explaining the synchronization of the phase-lock-loop circuit of FIGURE 2;

FIGURES 4a-4r illustrate timing diagrams that are useful for explaining the operation of the circuit of FIGURE 2; and

FIGURE 5 illustrates an embodiment of a phase comparator of FIGURE 2.

FIGURE 1. illustrates a block diagram of a horizontal deflection circuit including a phase-lock-loop circuit 20. It includes a sequential counter 21 that has the analogous function of a VCO of a conventional phase-lock-loop circuit. Counter 21 is a programmable counter that is incremented after each leading edge of a clock pulse CK having a period t_{CK} , illustrated in the timing diagram of FIGURE 4a. It counts up, from an initial value of, for example, 1, until it is reset to the initial value by a reset pulse RESET at an input terminal 21a of FIGURE 1. Pulse RESET controls the number of clock CK periods t_{CK} that are included in a corresponding period, or sequence, N, of counter 21. Successions of sequences N produced by counter 21 define a recurring sequence. Each word CT, at an output port 21b of counter 21, supplies, in a given sequence N, the current count of counter 21.

Illustratively, a digital word herein is represented as a base 2 number that includes an integer, a fraction or a combination of an integer and a fraction. A negative number is represented as a 2's complement number.

Horizontal sync pulses H_s having a period H (1H sync pulses H_s), are coupled, illustratively, from a conventional sync separator 60 of a television receiver to a phase detector 202. When phase-lock-loop circuit 20 is phase-locked to sync pulses H_s , provided that they are accompanied by low level of noise, the leading edge of each pulse MS that is coupled to phase detector 202 occurs substantially coincidentally with the last clock CK edge that occurs before the center of the corresponding sync pulse H_s . Pulse MS is generated by a decoder 23 when a predetermined value of word CT is detected. Thus, the center of each sync pulse H_s occurs a variable fraction f of clock CK period t_{CK} of FIGURE 4a after the leading edge of pulse MS of FIGURE 1.

Variable fraction f is contained in a 1H skew word SK that is also coupled to phase detector 202. Phase detector 202 generates a period length adjusting word LPFO. Word LPFO is combined, in a horizontal period length generator 33, with a constant word PR to produce a word DPW. Word PR, for example, equals the value 910 where $910 \times t_{CK}$ is equal to the nominal, or free-running period, of phase-lock-loop circuit 20. Note that clock CK period t_{CK} is equal to

$$\frac{1}{4 \times f_{sc}}$$

where f_{sc} is the NTSC color subcarrier frequency.

Word DPW contains the calculated estimate, or computed, binary value of the actual period H of pulses H_s in the form of an integer number M of clock CK period t_{CK} and a fractional number k of clock CK period t_{CK} . Word DPW is coupled to a counter period and skew words generator 201 that generates 1H skew word SK and a period word PERIOD. Word PERIOD, that contains the number of clock CK cycles in a given counter 21 period N, is coupled to a comparator 200 that compares the current value of words CT and PERIOD and generates pulse RESET when word CT = word PERIOD. Pulse RESET initializes counter 21 to contain word CT=1 simultaneously with the next clock CK edge that, thereby, defines the end time of the current sequence N of counter 21 and the beginning time of the next sequence N.

Words CT are coupled through a programmable time shifter or delay 42 to provide delayed words Ca. The delay of programmable delay 42 is controlled by an external word NPW that is coupled from a source not shown in the FIGURES. A word CMa, defined to include words SK and Ca that provide the fraction and integer parts, respectively, of word CMa, is coupled to a programmable delay 203. A word CMao is defined as the state of word CMa in which word Ca = 0. Word CMao defines a periodic event e_{CMao} having a period that is equal to an estimated value of the actual period H, in accordance with word DPW. Event e_{CMao}

occurs $f \cdot t_{CK}$ after the leading edge of clock CK that causes word Ca to become zero, as described later on. Fraction f is the value contained in 1H skew word SK.

Horizontal period length word DPW is coupled to a divide-by-2 unit 46 that divides the value of word DPW by the factor 2 to produce word HDPW that is indicative of one-half the horizontal period length H. Word HDPW is coupled to the control port of programmable delay 203 that delays event e_{CMao} , defined by word CMao, by H/2 in accordance with the value of delay 203 control word HDPW.

A word Cmb, the output word of programmable delay 203 includes a skew word SKB and a word Cb, providing the fraction and integer parts, respectively, of word Cmb. A word CMbo is defined as the state of word Cmb in which word Cb = 0. Word CMbo defines a periodic event e_{CMbo} CMbo that occurs in the calculated estimate center of the interval between each pair of successive events e_{CMao} .

Words CMa and Cmb are coupled to ports 40a and 40b, respectively of a multiplexer 40. Multiplexer 40 couples, alternately, words CMa and Cmb to input port 51a of a programmable time shifter or delay 51 of a phase-control-loop circuit 120. Words CMI and CMP, at an output port 51c of programmable delay 51, represent an integer and a fraction, respectively, of clock CK period t_{CK} of FIGURE 4a. Words CMI are coupled to a horizontal drive pulse generator 253 that generates, each time word CMI=0, a pulse PGP having a width w that is controlled by an external word WIDTH. Pulse PGP is coupled from pulse generator 253 to an input terminal 54a of a gate delay 54. Gate delay 54 delays pulse PGP by a fraction q of clock CK period t_{CK} of FIGURE 4a, having a length that is determined in accordance with the value of word CMP of FIGURE 1, to produce a $2f_H$ rate signal HORDRIVE at an output terminal 54b of gate delay 54. Signal HORDRIVE is also coupled to a flip-flop unit 55. Each pulse of signal HORDRIVE causes the toggling of a signal TOGGLE at an output terminal 55a of flip-flop unit 55. Signal TOGGLE is coupled to a select terminal 40c of multiplexer 40. Signal TOGGLE causes, in accordance with its logical state, the alternate coupling of words CMa and Cmb, respectively, to input port 51a of programmable delay 51. Thus, the timings of the pulses of signal HORDRIVE are controlled, alternately, by the words in ports 40a and 40b, respectively, of multiplexer 40.

It should be understood that an arrangement similar to the arrangement of FIGURE 1 may be used for generating a signal analogous to signal HORDRIVE of FIGURE 1 having a different multiple of the frequency f_H such as, illustratively, $3f_H$ or $4f_H$.

Signal HORDRIVE is coupled to an input terminal 41a of a $2f_H$ horizontal deflection circuit output stage 41 to control the switching of a horizontal output transistor. A retrace interval is formed in response to a corresponding pulse of signal HORDRIVE. A resulting pulse FLYBACK, occurring during retrace, that is obtained, illustratively, from a flyback transformer, not shown in FIGURE 1, of output stage 41, is coupled to a phase detector 202'.

When phase-control-loop circuit 120 is perfectly phase-locked to flyback pulses FLYBACK, the leading edge of each pulse MS', that is also coupled to phase detector 202', occurs substantially coincidentally with the last clock CK edge before the center time of the respective pulse FLYBACK. Pulse MS' is generated by a decoder 23' when a predetermined value of word Ca is detected. The center of pulse FLYBACK occurs fraction f of clock CK period t_{CK} of FIGURE 4a after the leading edge of pulse MS' of FIGURE 1. Fraction f is contained in 1H skew word SK.

Phase detector 202' generates a word LPFO' that controls the delay time of programmable delay 51. Programmable delay 51 is capable of providing a positive or negative phase shift, or time delay, as explained later on. The center of $2f_H$ rate pulses FLYBACK occurs coincidentally with each corresponding event e_{CMao} or e_{CMbo} . Event e_{CMao} occurs during the time in which word Ca = 0; whereas event e_{CMbo} occurs when word Cb = 0, as described before. Therefore, the arrangement of FIGURE 1 generates the $2f_H$ rate pulses FLYBACK, delayed by corresponding constant delay times relative to the corresponding 1H sync pulse H_s .

FIGURE 2 illustrates a more detailed block diagram of the arrangement of FIGURE 1. Similar numerals and symbols in FIGURES 1 and 2 illustrate similar items or functions. FIGURES 4a-4r illustrate timing diagrams of a typical steady state example, showing three consecutive periods, or sequences, N_a , N_b and N_c of counter 21 of FIGURE 2, when phase-lock-loop circuit 20 is phase-locked to sync pulses H_s of FIGURE 4r. Similar numbers and symbols in FIGURES 1, 2 and 4a-4r represent similar items or functions.

Assume that word DPW, at an input port 34a of an adder 34 of FIGURE 2, contains the calculated estimate value of period H of horizontal sync pulses H_s of FIGURE 4r. Word DPW of FIGURE 2 includes, illustratively, 10-bit number, M, representative of an integer multiple of clock CK periods t_{CK} of FIGURE 4a, and 5-bit number, k, representative of a fraction of period t_{CK} . The value $(M+k) \cdot t_{CK}$ defines the updated estimate of period H.

Skew word SK, representing fraction f, at an output port 38b of a latch 38 of FIGURE 2, is coupled, right justified, to an input port 34b of adder 34, where it is summed up with right justified word DPW. A word

CNTPR appears at an output port 34c of adder 34 to represent the integer part of the addition result. Each bit of word CNTPR is at the same numerical weight as the corresponding bit of the integer part, M, of word DPW. Word CNTPR is coupled to an input port 35a of a latch 35. Latch 35 stores the value of word CNTPR, at a time T_1 of FIGURE 4f under the control of a pulse CL of decoder 23 of FIGURE 2, to form period length word PERIOD at an input port 36a of a subtractor 36. Subtractor 36 controls the total number of states in a given counter 21 period N. Decoder 23 decodes counter 21 words CT and generates timing control signals such as pulse CL, as well as other timing pulses that are mentioned later on, when a corresponding predetermined state of counter 21 occurs. Pulse CL is also coupled to a clock input terminal 38a of latch 38 for storing, at time T_1 of FIGURE 4e, a word SKIN of FIGURE 2 to produce 1H skew word SK that contains fraction f. The bits of fraction f appear at the same numerical scale, or weight, as the corresponding bits of fraction k of word DPW. Fraction f is representative of the fractional part of the addition result. Thus, adder 34 adds right justified latch 38 output word SK, that was formed by pulse CL during the immediately preceding period N of counter 21, to right justified word DPW, for updating words PERIOD and SK, respectively, at time T_1 of FIGURES 4f and 4e, respectively.

Counter 21 output word CT of FIGURE 2 is coupled to an input port 36b of subtractor 36 where it is subtracted from word PERIOD to form, in a port 36c, a word RS. Word RS is coupled to a zero detector 37. Zero detector 37 issues pulse RESET, as illustrated in FIGURE 4j, when word RS of FIGURE 2 is equal to zero. Thus, when counter 21 word CT is equal to counter 21 period word PERIOD, counter 21 is reset and the next counter 21 word CT is equal to 1, the initial counting state. Word PERIOD expresses, in multiples of clock CK periods t_{CK} of FIGURE 4a, the length of period N of counter 21 of FIGURE 2.

Word Ca, illustratively 10-bit wide, is obtained by subtracting, in a subtractor that represents programmable delay 42 of FIGURE 1, the current word CT of counter 21 of FIGURE 2 from constant word NPW. FIGURE 4c illustrates an example of the corresponding sequence that is represented by words Ca. When word CT is equal to word NPW, word Ca is equal to 0. Similarly, when word CT exceeds word NPW by 1, word Ca is equal to 1023, in accordance with conventional 2's complement arithmetic. In each counter 21 sequence N, the states $Ca=1$, $Ca=0$ and $Ca=1023$ occur, respectively, as counter 21 of FIGURE 2 is incremented sequentially. The time in which word Ca of FIGURE 4c becomes zero is defined as time t_{CTJ} . Time t_{CTJ} occurs (J-1) clock CK periods t_{CK} after sequence N beginning time, such as time T_0 of period N_a . During clock CK period t_{CK} that follows time T_0 , counter 21 word CT is equal to 1. Word CMao is defined as the state of word CMA in which word CA=0, as described before. Each word CMao thus defines periodic event e_{CMao} that occurs at time $t_{CMao} = t_{CTJ} + f_1 t_{CK}$, as illustrated by the corresponding short arrows in FIGURE 4d. Note that word SK of a given word CMao may have different values in corresponding counter 21 periods N. For example, during the interval t_{CK} that immediately follows time t_{CTJ} of FIGURE 4e, word SK is equal to f_1 . Thus, event e_{CMao} of FIGURE 4d occurs at time $t_{CMao} = t_{CTJ} + f_1 \times t_{CK}$. Note that fraction f_1 was computed during period N of counter 21 of FIGURE 2, not shown in FIGURE 4a-4r, that occurred immediately prior to period N_a .

The arrangement of FIGURE 2 computes the timing of the next event e_{CMao} of FIGURE 4d, such as time t_{CMao}' of event e_{CMao}' relative to time t_{CTJ} , by adding, in adder 34, old fraction f_1 of word SK of FIGURE 2, to fraction k of word DPW to produce new fraction f_2 . A binary carry C may be produced from such addition and the corresponding new period word PERIOD becomes (M+the value of carry C), at time T_1 of FIGURE 4f. The interval between successive events e_{CMao} of FIGURE 4d is equal to $(M+k) \times t_{CK}$, as shown by the examples below.

Assume, hypothetically, that prior to time T_1 of FIGURE 4e the fractional result, word SKIN of FIGURE 2 = $(f_1 + k)$, is <1 ; since no carry C is produced, word CNTPR is equal to M, the integer part of word DPW. After pulse CL of FIGURE 2 occurs, at time T_1 of FIGURE 4e, word SK is equal to $f_2 = (f_1 + k)$ and word PERIOD of FIGURE 4f is equal to M. Since reset pulse RESET of FIGURE 4j occurs when word CT of FIGURE 2 is equal to word PERIOD, the length of counter 21 period N_a is going to be equal to (M) clock CK periods t_{CK} of FIGURE 4a. The corresponding event e_{CMao} that occurs at time t_{CMao} of FIGURE 4d during counter 21 period N_a , occurs $(J-1 + f_1) \times t_{CK}$ after beginning time T_0 of period N_a of FIGURE 4b.

Assume, in a second hypothetical example, that prior to time T_1' of FIGURE 4e, the fractional result, word SKIN of FIGURE 2 = $f_2 + k$, is >1 ; consequently, carry C is produced in adder 34, and word CNTPR of is equal to (M+1). It follows that after pulse CL occurs, at time T_1' of FIGURE 4e, fraction f_3 , represented by word SK of FIGURE 4e, is equal to $(f_1 + k) + k - 1$, and word PERIOD of FIGURE 4f is equal to (M+1). Therefore, the length of counter 21 period N_b of FIGURE 4b is going to be equal to (M+1) clock CK periods t_{CK} . The corresponding event e_{CMao}' , during counter 21 period N_b , occurs $(J-1 + f_1 + k) \times t_{CK}$ after beginning time T_0' of period N_b of FIGURE 4b.

Assume, in a third hypothetical example, that prior to time T_1'' , the fractional result, word SKIN of FIGURE 2 = $(f_1 + 2k - 1) + k$, is <1 ; since no carry C is produced, word CNTPR is equal to M. It follows that

after pulse CL occurs, at time T_1 of FIGURE 4e, the corresponding word PERIOD of FIGURE 4f is equal to M. Therefore, the length of counter 21 period N_c of FIGURE 4b is going to be equal to (M) clock CK periods t_{CK} . The corresponding event e_{CMao} occurs $(J-1 + f_1 + 2k-1) \times t_{CK}$ after beginning time T_0 of period N_c of FIGURE 4b.

The above calculations lead to the conclusion that the interval $t'_{CMao}-t_{CMao}$ of FIGURE 4d, of successive events e_{CMao} , is equal to :

$$[T_0'-t_{CMao}] + [t_{CMao}'-T_0'] = [M-(J-1 + f_1)] + [J-1 + f_1 + k] = (M+k)$$

10 of clock CK periods t_{CK} . Likewise, the interval $t''_{CMao}-t'_{CMao}$ is equal to :

$$[T_0''-t'_{CMao}] + [t'_{CMao}-T_0''] = [(M+1)-(J-1 + f_1 + k)] + [J-1 + f_1 + 2k-1] = (M+k)$$

15 of clock CK periods t_{CK} . Thus, the length of the interval between successive events e_{CMao} of FIGURE 4d is expressed in the content, (M+k), of word DPW of FIGURE 2. The length of a given period N of FIGURE 4b may be, for example, either (M) or (M+1) clock CK periods t_{CK} ; however, the average length of period N, is equal to period H of horizontal sync pulses H_s of FIGURE 4r, as explained later on.

At time t_{CH} of FIGURE 4g, which occurs prior to time T_1 of period N_a , fraction f in latch 38 of FIGURE 2 is saved in a latch 45 to form a word SKD. The saving of word SK is done by a pulse CH from decoder 23. Word SKD is coupled, right adjusted, to an input port 47b of an adder 47 that is similar to adder 34. Word DPW, that contains (M+k), is coupled through divide-by-2 unit 46 that includes, for example, a right shifter, to the other input port of adder 47 to form there right adjusted word HDPW that is equal to $(1/2) \times (M+k)$. A word IHP, the integer part of the result of the addition in adder 47, is coupled to an input port 49a of an adder 49. Word Ca of programmable delay 42 is coupled to an input port 49b of adder 49 where it is added with word IHP to form word Cb. Skew words SKB of FIGURES 4g and 2 contains a fractional part g of the result of the addition of the respective fractions in adder 47.

Word Cb is equal to 0 during the length of clock CK period t_{CK} that immediately follows clock CK edge of a time t_{CTB} of FIGURE 4h. Word CMbo of FIGURE 2 that is defined as the state of word CMb in which word Cb=0, is thus defined in an analogous manner to the way word CMao was defined before. Similarly to words CMao, words CMbo define corresponding periodic events e_{CMbo} of FIGURE 4i, that are analogous to events e_{CMao} of FIGURE 4d. In an analogous manner, event e_{CMbo} of FIGURE 4i, for example, occurs $g \times t_{CK}$ after time t_{CTB} of FIGURE 4h.

As explained before, programmable delay 203 of FIGURE 1, that is controlled by word HDPW, delays the occurrence of event e_{CMao} of FIGURE 4d by a duration that is determined in accordance with the value of word HDPW of FIGURE 2 to define event e_{CMbo} of FIGURE 4i. Event e_{CMbo} is delayed by $H/2$ relative to the corresponding event e_{CMao} of FIGURE 4d. Each event e_{CMbo} of FIGURE 4i occurs at the center of the corresponding interval that lies between consecutive events e_{CMao} of FIGURE 4d, as shown by the example below.

During counter 21 period N_a of FIGURE 4g, prior to time t_{CH} , latch 45 of FIGURE 2 contains fraction f_1 . Since word HDPW is equal to $(1/2) \times (M+k)$, the addition result at port 47c of adder 47 is equal to $(1/2) \times (M+k) + f_1$. Assume, hypothetically, that M is an odd number that is equal to $2A+1$. The number A, an integer, is thus equal to

$$\frac{M-1}{2}.$$

It follows that $(1/2) \times (M+k) + f_1$ is equal to $(A+1/2+k/2+f_1)$. Further assume, hypothetically, that fraction g_1 of word SKB of FIGURE 4g, that is equal to $(1/2+k/2+f_1)$, is less than 1. Thus word IHP is equal to A, the integer part of word HDPW. Because of the summation of words IHP and Ca in adder 49, word Cb of FIGURE 4h will be equal to zero when (A) clock CK periods t_{CK} have elapsed after time t_{CTJ} of FIGURE 4c. Thus, event e_{CMbo} of FIGURE 4i of time t_{CMbo} occurs $(A) \times t_{CK} + (1/2+k/2+f_1) \times t_{CK}$ after time t_{CTJ} of FIGURE 4c. The total delay time, $T_{H/2a}$ in FIGURE 4i, from time t_{CTJ} to the corresponding time t_{CMbo} is equal to

$$\left[\frac{M-1}{2} + (1/2+k/2+f_1) \right] \times t_{CK} = \left(\frac{M+k}{2} + f_1 \right) \times t_{CK}.$$

Since event e_{CMao} occurs at time $t_{CMao} = t_{CTJ} + f_1 x t_{CK}$, it follows that event e_{CMbo} of FIGURE 4i occurs

$$\frac{(M+k)}{2} \times t_{CK}$$

after the immediately preceding event e_{CMao} of FIGURE 4d. It can be shown that the same result is obtained when other assumptions are made with respect to M or fraction g_1 . Since the period defined by successive events e_{CMao} is equal to (M+k), it follows that each event e_{CMbo} of FIGURE 4i lies at the center of the interval $t_{CMao} - t_{CMao}'$ between consecutive events e_{CMao} and e_{CMao}' , respectively, of FIGURE 4d. As described later on, and in accordance with an aspect of the invention, alternate retrace intervals, that are repeated every period H, occur in accordance with times t_{CMbo} of events e_{CMbo} of FIGURE 4i. The other alternate retrace intervals occur in accordance with times t_{CMao} of events e_{CMao} of FIGURE 4d.

Each f_H rate sync pulse H_s of FIGURE 2 is sampled by clock CK and the corresponding sample is digitized in a digitizer unit 61, such as an analog-to-digital converter, to form, in a conventional manner, a corresponding word 207. Successive digitized sync words 207 are coupled to an input port 25a of a digital low pass filter 25. Successive digitized sync words SY, at the output of filter 25 are coupled to an input port 22a of a sync phase comparator 22. As described below, sync words SY are used for synchronizing each event e_{CMao} of FIGURE 4d with the corresponding sync pulse H_s of FIGURE 4r, and for obtaining period length word DPW of FIGURE 2.

FIGURES 3a-3g illustrate schematically timing diagrams useful in explaining the synchronization of phase-lock-loop circuit 20 of FIGURE 2. Similar symbols and numerals in FIGURES 2, 3a-3g, and 4a-4r illustrate similar items or functions. FIGURE 3a illustrates an example of successive digitized sync words SY of FIGURE 2 that result from digitizing an idealized trapezoidal horizontal sync pulse H_s , defining a trapezoidal envelope 1, during interval T of FIGURES 4r and 3a. Envelope 1 of FIGURE 3a has a leading edge 72 and a trailing edge 73, illustrated by dashed lines. During entire interval T, between times T_b and T_e , respectively, each sync word SY appears after each leading edge of clock CK of FIGURE 3d. Words SY are illustrated schematically by the vertical arrows that reach up to envelope 1, representing the respective magnitude of words SY.

Decoder 23 of FIGURE 2 produces control pulse MS at time T_m of FIGURE 3c or 4i when a predetermined value of word CT of FIGURE 2 occurs, such as, for example when word CT is equal to 315. Control pulse MS is coupled to a terminal 22b of phase comparator 22 where it is phase-compared with a corresponding sync pulse H_s that forms words SY, as described below.

FIGURE 5 illustrates schematically a block diagram of phase comparator 22. Similar symbols and numerals in FIGURES 1, 2, 3a-3g, 4a-4r and 5 indicate similar items or functions. Phase comparator 22 of FIGURE 5 includes an accumulator 26 that subtractively accumulates, from an initial value of zero, successive sync words SY of FIGURE 3a from time T_b , at the beginning of interval T of FIGURE 3a, as controlled by a signal CAC of decoder 23 of FIGURE 2, through time T_m of FIGURE 3a. At time T_m associated with pulse MS of FIGURE 5, a signal FFO at an output terminal 27a of a flip-flop 27, toggles from a first logical level to a second logical level, as illustrated in FIGURE 3c. Flip-flop 27 signal FFO of FIGURE 5 toggles after receiving, at a clock input terminal 22b, the leading edge of control pulse MS. After time T_m , and until interval T end time T_e of FIGURE 3a, as controlled by signal CAC, individual sync words SY are additively accumulated in accumulator 26 to provide an output word ACW that contains the total accumulation of the subtractions and the subsequent additions.

In a second timing example of FIGURE 3a, sync words SY, referred to as sync words SY2, are illustrated schematically by vertical arrows that define an envelope 2. Envelope 2, that is illustrated by the dotted lines, has a leading edge 70 and a trailing edge 71, that are similar to the respective edges in envelope 1. Words SY2 are provided within an interval T_2 that is equal in length to interval T. A center point T_{c2} of interval T_2 is delayed relative to center point T_c of interval T. Note that each word SY2 is of a smaller value at leading edge 70 but of a larger value at trailing edge 71 of envelope 2 than the corresponding words SY1 of leading edge 72 and trailing edge 73, respectively, of envelope 1. Therefore, the sum total in word ACW, at an end time T_{c2} of period T_2 , is more positive than at end of time T_e of period T. Thus, the magnitude of word ACW is proportional to the length of the corresponding interval $T_{c2} - T_m$ or $T_c - T_m$. It follows that the magnitude and polarity values of word ACW correspond with the time difference, $(T_c - T_m)$, between actual center point T_c of interval T and time T_m that is defined by the leading edge of pulse MS of FIGURE 3b.

Output word ACW of accumulator 26 of FIGURE 5 is coupled to an input port 28a of a scaler 28. Scaler 28 generates from word ACW a word SCW that expresses the time difference, $(T_c - T_m)$ of FIGURE 3a as a

ratio n that is equal, illustratively, to $(T_c - T_m)/t_{CK}$. Ratio n has a resolution of time difference $(T_c - T_m)$, illustratively, of $1/32$ of clock CK period t_{CK} .

Word SK of FIGURE 2, that contains fraction f , is coupled to a port 22d of subtractor 30 of FIGURE 5 where it is subtracted from word SCW to form a word SCWD at an input port 22g of a register 31. Register 31 stores each word SCWD and transfers it to an output port 22e to provide a phase word PH of FIGURE 5. Phase word PH, that is, consequently, equal to $[(T_c - T_m)/t_{CK} - f]$, is clocked into and out of register 31 by a pulse CC of decoder 23 of FIGURE 2 that is coupled to a clock terminal 22c at instant T_r of FIGURE 3e following end time T_e of period T of FIGURE 3a.

A time $T_{cc} = T_m + f \cdot t_{CK}$, as described later on, represents the calculated, or expected, occurrence time of the center of period T of FIGURE 3a. The interval between time T_{cc} and the corresponding time t_{CMao} of event e_{CMao} is inherently equal to a predetermined integer multiple of clock CK periods t_{CK} of FIGURE 3d. It follows that time T_{cc} is also periodic with the same period length of $(M + k) \times t_{CK}$ as time t_{CMao} of event e_{CMao} of FIGURE 4d. Thus, in order to synchronize the occurrences of events e_{CMao} to the corresponding sync pulses H_s of FIGURE 4r, it is sufficient that the actual center point T_c of period T of FIGURE 3a coincides with the calculated time T_{cc} . Word PH of FIGURE 2 that is equal to $[(T_c - T_m)/t_{CK} - f]$, is thus indicative of the time difference between the actual center point T_c and the calculated center point T_{cc} of interval T of FIGURE 3a. When word PH of FIGURE 2 is positive, the actual center time T_c of FIGURE 3a is greater, or later, than the calculated center time T_{cc} . Conversely, when word PH of FIGURE 2 is negative, the actual center time T_c of FIGURE 3a is smaller, or earlier, than the calculated center time T_{cc} . When time T_{cc} is equal to time T_c , phase word PH of FIGURE 2 is zero.

Phase word PH is coupled through a conventionally built digital low pass filter 32 of FIGURE 2 to an input port 33b of an adder 33 to form filter 32 output word LPFO. Filter 32 may comprise an accumulator that additively accumulates individual phase words PH, under the control of a horizontal rate pulse CLPF generated by decoder 23 at a corresponding time T_s of FIGURE 3f. Time T_s appears after time T_r of pulse cc of FIGURE 3e. When phase word PH of FIGURE 2 is zero, in the steady state example, word LPFO of low pass filter 32 does not change. A negative phase word PH, for example, decreases the value of word LPFO; whereas a positive phase word PH increases it. The adder of generator 33 adds word PR that represents the nominal number of clock CK periods t_{CK} contained in a given period H of the NTSC composite television signal, to the integer part of word LPFO for forming deflection period word DPW at port 33a. As described before, period length word DPW is added with 1H skew word SK to produce updated words PERIOD and SK when pulse CL occurs at time T_t of FIGURE 3g. Time T_t occurs shortly after time T_s of FIGURE 3f.

Assume, hypothetically, that actual center time T_c of FIGURE 3a is later than calculated center time T_{cc} ; consequently, phase word PH of FIGURE 2 is a positive value. Word DPW becomes larger when phase word PH becomes more positive. In the subsequent interval T of FIGURE 3a, the larger word DPW produces calculated center time T_{cc} , representing a longer time interval from the previous time T_{cc} . Thus calculated center time T_{cc} becomes closer to actual center time T_c for achieving synchronization. In a steady, or synchronized, state, clock CK edge of FIGURE 3d at time T_m occurs a fraction of clock CK period t_{CK} , that is equal to f , prior to actual center point T_c of interval T of FIGURE 3a. In the steady, or synchronized, state, each of events e_{CMao} and e_{CMbo} of FIGURES 4d and 4i, respectively, that are associated with words CMA and CMB, respectively, of FIGURE 2, occurs a corresponding constant delay time, respectively, from the corresponding horizontal sync pulses H_s of FIGURE 4r.

When output signal TOGGLE, of flip-flop unit 55 at select terminal 40c of multiplexer 40 of FIGURE 2, is at the first logical state, words CMA in port 40a are coupled right adjusted to input port 51a of programmable delay 51 that comprises an adder. Phase shifting word LPFO' of phase-control-loop circuit 120 is coupled, right adjusted, to port 51b of the adder of programmable delay 51. Word CMI at output port 51c of delay 51, representing the integer part of the result of the addition in programmable delay 51, as illustrated schematically in FIGURE 4k, is coupled to a zero detector 52. Zero detector 52 generates a pulse START at time T_{CMIO} of FIGURE 4m, when word CMI of FIGURE 4k becomes zero. Pulse START of FIGURE 2 is coupled to pulse generator unit 53 causing it to generate, in a conventional manner, pulse PGP having a width w that is controlled by external controlling word WIDTH. Word WIDTH is coupled to an input port 53c of pulse generator 53. Pulse PGP is coupled to gate delay 54 that delays each individual pulse PGP by a fraction q of clock CK period t_{CK} , thus producing a corresponding individual pulse h_d component of signal HORDRIVE of FIGURE 4n. Fraction q of word CMP at output port 51c of delay 51 of FIGURE 2 represents the fractional part of the result of the summation at the adder of programmable delay 51. The width w of pulse h_{d1} of FIGURE 4h is, illustratively, wide enough to overlap the corresponding width of pulse f_{b1} of FIGURE 4q.

Gate delay 54 may include a delay line of t_{CK} time delay, having, for example, 32 uniformly distributed taps. A given 5-bit combination of word CMP of FIGURE 2 may select a corresponding tap of the 32 taps for delaying pulse PGP a fraction of clock CK period t_{CK} in accordance with its numerical value. For example, when fraction q of word CMP is equal to $(00101)_2$, the delay obtained is equal to $(5/32) \times t_{CK}$. Thus, an individual component pulse h_{d1} of signal HORDRIVE of Figure 4n occurs, for example, at time $(T_{CMIO} + q_1 \times t_{CK})$, where q_1 is the fraction contained in word CMP of FIGURE 2.

After, for example, the occurrence of the trailing edge of pulse h_{d1} component of signal HORDRIVE of FIGURE 4n, signal TOGGLE changes its state to be at a second state, as illustrated in FIGURE 4p. Now signal TOGGLE causes words CMB in port 40b of multiplexer 40 of FIGURE 2 to be coupled to input port 51a of programmable delay 51 in the form of words CMI and CMP at its output port 51c. Zero detector 52 now generates pulse START at time T_{CMIO}' of FIGURE 4m, when word CMI of FIGURE 4k at port 51c of programmable delay 51 of FIGURE 2, becomes zero. This is done in a manner similar to that described before with respect to time T_{CMIO} . Time T_{CMIO}' of FIGURE 4m is thus determined now by words Cb of FIGURE 4h. The ensuing trailing edge of pulse h_{d2} component of signal HORDRIVE of FIGURE 4n will cause flipflop unit 55 of FIGURE 2 to revert back to the first state, as illustrated in FIGURE 4p, for coupling, as explained before, words Ca and SK of each word CMA at port 40a to input port 51a of programmable delay 51 of FIGURE 2. Thus, in accordance with an aspect of the invention, the timings of alternate first and second component pulses h_d of signal HORDRIVE of FIGURE 4n, are controlled, alternately, by words CMA and CMB in ports 40a and 40b, respectively, of multiplexer 40 of FIGURE 2.

Each pulse FLYBACK of output stage 41 having illustratively, a trapezoidal shape, as illustrated in FIGURE 4q, and derived from horizontal flyback pulses, may be digitized in a digitizer unit 61', that is analogous to digitizer unit 61, to form successive digitized flyback words SY' at an input port 22a' of a phase comparator 22'. Flyback words SY' of phase-control-loop circuit 120 are analogous to sync words SY of phase-lock-loop circuit 20. Phase comparator 22' may be constructed similarly to phase comparator 22 of phase-lock-loop circuit 20. Thus, ports 22a'-22e' of phase comparator 22' respectively, are functionally equivalent to ports 22a-22e, respectively, of phase comparator 22. A decoder 23' decodes corresponding predetermined values of words Ca for generating pulses MS' CAC', CC' and CLPF', respectively, that are analogous to pulses MS, CAC, CC and CLPF, respectively, of decoder 23. Pulse CC', for example, is coupled to terminal 22c'. Skew word SK is similarly coupled to port 22d' of phase comparator 22'.

Assume that flyback words SY', representing a trapezoidal envelope that is similar to envelope 1 of sync words SY of FIGURE 3a, for example, are consecutively generated during a retrace interval T' of FIGURE 4q that has an actual center time T_c' . Interval T' and center time T_c' are analogous to interval T and center point T_c of FIGURE 3a, respectively. In the example of FIGURE 4q, the leading edge of pulse MS' of FIGURE 2, that is coupled to terminal 22b' of phase comparator 22', occurs at time t_{CTJ} of FIGURES 4d as illustrated in FIGURE 40. In an analogous manner to the operation of phase comparator 22, a phase word PH' at port 22e' of phase comparator 22' of FIGURE 2 is indicative of the corresponding time difference $(T_c' - t_{CMao})$. The term t_{CMao} in phase word PH', is analogous to the term T_{cc} in phase word PH of phase comparator 22. Using the same analogy, it follows that when center point T_c' of interval T' of an individual pulse f_{b1} of pulses FLYBACK of FIGURE 4q is greater than the corresponding time t_{CMao} of FIGURE 4d, phase word PH' of FIGURE 2 is positive. On the other hand, when time T_c' of FIGURE 4q is equal to time t_{CMao} , phase word PH' of FIGURE 2 is zero.

Phase word PH' of FIGURE 2 is coupled to a sign complementing unit 58 that provides a sign complemented word PHI. When word PH' is negative, for example, word PHI is positive and of, illustratively, the same absolute value as word PH'. Words PHI are coupled to a low pass digital filter 32' that is analogous to filter 32 of phase-lock-loop circuit 20. Filter 32' output word LPFO' has a shorter response time to phase variations of pulses FLYBACK of FIGURE 4q than the response time of low pass filter 32 to phase variations of pulses H_s of FIGURE 4r. In the steady state of phase-control-loop circuit 120 of FIGURE 2, occurring when phase word PH' is zero, word LPFO' is negative with such a value that causes center point T_c' of alternate flyback pulses f_{b1} and f_{b3} pulses FLYBACK of FIGURE 4q, to occur at times t_{CMao} and, t_{CMao}' respectively, of FIGURE 4d. It can be shown that component pulse h_{d1} , for example, of signal HORDRIVE of FIGURE 4n, occurs prior to the corresponding time t_{CMao} of FIGURE 4d by a period t_{LEAD} that is equal to $(Q + h) \times t_{CK}$, where Q and h are the integer and fractional parts respectively, of word LPFO' of FIGURE 2.

Word NPW of FIGURE 2, that is coupled to the adder of programmable delay 42, controls the relative timing between pulse MS' of decoder 23' and the corresponding pulse MS of decoder 23. By changing the value of word NPW a corresponding change of the duration between, for example, center times T_c , and T_c' of pulses f_{b1} and H_{sa} of FIGURES 4q and 4r, respectively, is obtained.

As a result of a beam current change in the picture tube, the ultor current changes. The change in ultor current drawn from the flyback transformer of output stage 41 causes the delay between pulse f_{b1} of FIGURE 4q and pulse h_{d1} of FIGURE 4n also to change because of the change in storage time of the horizontal output switching transistor. Assume that as a result of such change in delay, the interval ($T_c - t_{CMao}$) of pulse f_{b1} of FIGURE 4q deviates from zero and becomes positive. In this case, word PH' of FIGURE 1 becomes more positive and word LPFO' becomes more negative. Therefore, the next pulse h_{d3} of FIGURE 4n occurs earlier, causing pulse f_{b3} of pulses FLYBACK of FIGURE 4q to occur earlier. This leads to a decrease in the length of the subsequent interval ($T_c - t_{CMao}$) so as to correct for the assumed deviation caused by the corresponding beam current change.

In accordance with an aspect of the invention, the same value of word LPFO' of FIGURE 2 controls the timings of successive pulses h_d of FIGURE 4n that correspond with events e_{CMao} and e_{CMbo} , respectively. Because, for example, time t_{CMbo} of FIGURE 4i is spaced from time t_{CMao} of FIGURE 4d by a period length of $H/2$, as shown in FIGURE 4q and as described before, pulse f_{b2} of flyback pulses FLYBACK of FIGURE 4q that corresponds with time t_{CMbo} of FIGURE 4i, appears $H/2$ after the immediately preceding pulse f_{b1} of pulses FLYBACK of FIGURE 4q. Pulse f_{b1} corresponds with time t_{CMao} of FIGURE 4d. Thus, updating low pass filter 32' by pulse CLPF' of FIGURE 2 occurs once in each horizontal period H. It should be understood that decoder 23' may be designed so that updating low pass filter 32' occurs at a rate of, illustratively, $2f_H$ that corresponds with the rate of flyback pulses FLYBACK of FIGURE 2q.

When sync pulses H_s of FIGURE 2 are absent, causing word LPFO of filter 32 to be zero, word DPW, which is equal to word PR=910, causes the arrangement of FIGURE 1 to form retrace intervals separated by $910/2 \times t_{CK}$, that is equal to $1/2$ the nominal value of period H in an NTSC system.

Claims

1. A deflection apparatus responsive to a line synchronizing input signal (H_s) for generating a deflection output signal (HORDRIVE) that forms corresponding deflection cycles in a deflection circuit during a given period of said input signal such that the frequency of said deflection cycles is an integer multiple of said input signal, said apparatus comprising:
 - a phase-lock-loop circuit (20) responsive to said line synchronizing input signal (H_s) for generating in said given period thereof a periodic signal (Ca) at a frequency that is related to the frequency of said input signal (H_s);
 - a line output stage (41) of said line deflection circuit responsive to said output signal (HORDRIVE) for generating said multiple frequency deflection cycles and for developing a deflection cycle indicative signal (FLYBACK) that contains phase information of said higher frequency deflection cycles; and
 - a phase-control-loop (120) having a phase detector (202') that generates a control signal (LPFO') in accordance with said higher frequency deflection cycle indicative signal (FLYBACK) and in accordance with said periodic signal (Ca), said phase-control-loop being responsive to said periodic signal (Ca) for generating said output signal (HORDRIVE) that forms said deflection cycles at the frequency that is a multiple of said input signal (H_s) and in a phase that is determined in accordance with said control signal (LPFO') of said phase detector (202').
2. Apparatus as recited in claim 1, characterized in that:
 - said phase-lock loop circuit (20) generates first (CMa) and (CMB) periodic signals, said second signal being said first signal shifted in time; and
 - said phase-control loop circuit (12) is responsive to said first (CMa) and second (CMB) periodic signals for generating from said first periodic signal (CMa) a first component, and for generating from said second periodic signal (CMB) a second component of said deflection output signal (HORDRIVE) during said given period of said line synchronizing input signal (H_s).
3. An apparatus as recited in claim 2 characterized in that said phase-control-loop circuit (120) is responsive only to the deflection cycle indicative signal (FLYBACK) that corresponds to a cycle of line deflection current associated with only one of said first and second components of said deflection output signal (HORDRIVE).
4. An apparatus as recited in claim 2 characterized by means (40,51) for combining said first (CMa) and second (CMB) periodic signals to form a third periodic signal (CMI,CMP).

As a result of a beam current change in the picture tube, the ultor current changes. The change in ultor current drawn from the flyback transformer of output stage 41 causes the delay between pulse f_{b1} of FIGURE 4q and pulse h_{d1} of FIGURE 4n also to change because of the change in storage time of the horizontal output switching transistor. Assume that as a result of such change in delay, the interval ($T_c - t_{CMao}$) of pulse f_{b1} of FIGURE 4q deviates from zero and becomes positive. In this case, word PH' of FIGURE 1 becomes more positive and word LPFO' becomes more negative. Therefore, the next pulse h_{d3} of FIGURE 4n occurs earlier, causing pulse f_{b3} of pulses FLYBACK of FIGURE 4q to occur earlier. This leads to a decrease in the length of the subsequent interval ($T_c - t_{CMao}$) so as to correct for the assumed deviation caused by the corresponding beam current change.

In accordance with an aspect of the invention, the same value of word LPFO' of FIGURE 2 controls the timings of successive pulses h_d of FIGURE 4n that correspond with events e_{CMao} and e_{CMbo} , respectively. Because, for example, time t_{CMbo} of FIGURE 4i is spaced from time t_{CMao} of FIGURE 4d by a period length of $H/2$, as shown in FIGURE 4q and as described before, pulse f_{b2} of flyback pulses FLYBACK of FIGURE 4q that corresponds with time t_{CMbo} of FIGURE 4i, appears $H/2$ after the immediately preceding pulse f_{b1} of pulses FLYBACK of FIGURE 4q. Pulse f_{b1} corresponds with time t_{CMao} of FIGURE 4d. Thus, updating low pass filter 32' by pulse CLPF' of FIGURE 2 occurs once in each horizontal period H . It should be understood that decoder 23' may be designed so that updating low pass filter 32' occurs at a rate of, illustratively, $2f_H$ that corresponds with the rate of flyback pulses FLYBACK of FIGURE 2q.

When sync pulses H_s of FIGURE 2 are absent, causing word LPFO of filter 32 to be zero, word DPW, which is equal to word PR=910, causes the arrangement of FIGURE 1 to form retrace intervals separated by $910/2 \times t_{CK}$, that is equal to $1/2$ the nominal value of period H in an NTSC system.

Claims

1. A deflection apparatus responsive to a line synchronizing input signal (H_s) for generating a deflection output signal (HORDRIVE) that forms corresponding deflection cycles in a deflection circuit during a given period of said input signal such that the frequency of said deflection cycles is an integer multiple of said input signal, said apparatus comprising:
 - a phase-lock-loop circuit (20) responsive to said line synchronizing input signal (H_s) for generating in said given period thereof a periodic signal (Ca) at a frequency that is related to the frequency of said input signal (H_s);
 - a line output stage (41) of said line deflection circuit responsive to said output signal (HORDRIVE) for generating said multiple frequency deflection cycles and for developing a deflection cycle indicative signal (FLYBACK) that contains phase information of said higher frequency deflection cycles; and
 - a phase-control-loop (120) having a phase detector (202') that generates a control signal (LPFO') in accordance with said higher frequency deflection cycle indicative signal (FLYBACK) and in accordance with said periodic signal (Ca), said phase-control-loop being responsive to said periodic signal (Ca) for generating said output signal (HORDRIVE) that forms said deflection cycles at the frequency that is a multiple of said input signal (H_s) and in a phase that is determined in accordance with said control signal (LPFO') of said phase detector (202').
2. Apparatus as recited in claim 1, characterized in that:
 - said phase-lock loop circuit (20) generates first (CMa) and (Cmb) periodic signals, said second signal being said first signal shifted in time; and
 - said phase-control loop circuit (12) is responsive to said first (CMa) and second (Cmb) periodic signals for generating from said first periodic signal (CMa) a first component, and for generating from said second periodic signal (Cmb) a second component of said deflection output signal (HORDRIVE) during said given period of said line synchronizing input signal (H_s).
3. An apparatus as recited in claim 2 characterized in that said phase-control-loop circuit (120) is responsive only to the deflection cycle indicative signal (FLYBACK) that corresponds to a cycle of line deflection current associated with only one of said first and second components of said deflection output signal (HORDRIVE).
4. An apparatus as recited in claim 2 characterized by means (40,51) for combining said first (CMa) and second (Cmb) periodic signals to form a third periodic signal (CMI,CMP).



5. An apparatus as recited in claim 4 characterized in that said combining means comprises a multiplexer (40) that alternately couples said first (C_{Ma}) and second (C_{Mb}) periodic signals to form a combined periodic signal (C_{Ma},C_{Mb}).
6. An apparatus as recited in claim 4 characterized by a source of a clock signal (CK), wherein said third periodic signal forming means (40,51) is operative to form integer (C_{MI}) and fraction (C_{MP}) part signals of said third periodic signal, wherein said integer part signal (C_{MI}) is indicative of a corresponding cycle of said clock signal (CK) and wherein said fraction part signal (C_{MP}) is indicative of a corresponding fraction of a cycle of said clock signal (CK), and means (253,54) responsive to said integer (C_{MI}) and fraction part (C_{MP}) signals of said third periodic signal for generating said deflection output signal (HORDRIVE) in accordance with timing information contained therein.
7. An apparatus as recited in claim 4 characterized in that said combining means includes a time shifting means (51) of said phase-control-loop circuit (120) that time shifts the first and second periodic signals (C_{Ma},C_{Mb}) in accordance with an output (LPFO') of said phase detector (202').

Patentansprüche

1. Ablenkeinrichtung, die abhängig ist von einem zeilensynchron-Eingangssignal (H_s), zum Erzeugen eines Ablenk-Ausgangssignales (HORDRIVE), das entsprechende Ablenkzyklen in einer Ablenkschaltung während einer gegebenen Periode des Eingangssignales so bildet, daß die Frequenz der Ablenkzyklen ein ganzzahliges Vielfaches (integer multiple) des Eingangssignales ist, welche Einrichtung aufweist:
- eine PLL-Schaltung (20), die abhängig ist von dem Zeilensynchron-Eingangssignal (H_s), zum Erzeugen - in seiner gegebenen Periode - eines periodischen Signales (Ca) mit einer Frequenz, die zu der Frequenz des Eingangssignales (H_s) Bezug hat ;
 - eine Zeilen-Ausgangsstufe (41) der Zeilen-Ablenkschaltung, die abhängig ist von dem Ausgangssignal (HORDRIVE), zum Erzeugen der Ablenkzyklen mit vielfacher Frequenz und zum Bilden eines Anzeigesignales für den Ablenkzyklus (FLYBACK), der Phaseninformation der höherfrequenten Ablenkzyklen beinhaltet;
 - eine Phasensteuer-Schleife (120) mit einem Phasendetektor (202'), der ein Steuersignal (LPFO') erzeugt, in Übereinstimmung mit dem Anzeigesignal (FLYBACK) für die höherfrequenten Ablenkzyklen und in Übereinstimmung mit dem periodischen Signal (Ca), wobei die Phasensteuer-Schleife abhängig von dem periodischen Signal (Ca) ist zum Erzeugen des Ausgangssignales (HORDRIVE), das die Ablenkzyklen mit einer Frequenz bildet, die ein Vielfaches des Eingangssignales (H_s) ist und mit einer Phase, die in Übereinstimmung mit dem Steuersignal (LPFO') des Phasendetektors (202') bestimmt wird.
2. Einrichtung nach Anspruch 1, dadurch gekennzeichnet, daß die PLL-Schaltung (20) ein erstes (C_{Ma}) und ein zweites (C_{Mb}) periodisches Signal erzeugt, welches zweites Signal das zeitverschobene erste Signal ist;
- daß die Phasensteuer-Schleifenschaltung (12) abhängig von dem ersten (C_{Ma}) und zweiten (C_{Mb}) periodischen Signal ist zum Erzeugen einer ersten Komponente aus dem ersten periodischen Signal (C_{Ma}) und zum - aus dem zweiten periodischen Signal (C_{Mb}) - Erzeugen einer zweiten Komponente des Ablenk-Ausgangssignales (HORDRIVE) während der gegebenen Periode des Zeilensynchron-Eingangssignales (H_s).
3. Einrichtung nach Anspruch 2, dadurch gekennzeichnet, daß die Phasensteuerschleifen-Schaltung (120) nur abhängig ist von dem Ablenkzyklus-Anzeigesignal (FLYBACK), das mit einem Zyklus von Zeilen-Ablenkstrom korrespondiert, der nur mit einem der ersten und zweiten Komponenten des Ablenk-Ausgangssignales (HORDRIVE) assoziiert ist.
4. Einrichtung nach Anspruch 2, gekennzeichnet durch Mittel (40, 51) zum Kombinieren des ersten (C_{Ma}) und zweiten (C_{Mb}) periodischen Signales, um ein drittes periodisches Signal (C_{MI}, C_{MP}) zu bilden.



5. Einrichtung nach Anspruch 4,
dadurch gekennzeichnet,
daß die Kombiniermittel einen Multiplexer (40) aufweisen, der alternativ das erste (C_{Ma}) und das zweite (C_{Mb}) periodische Signal koppelt, um ein kombiniertes periodisches Signal (C_{Ma}, C_{Mb}) zu bilden.
6. Einrichtung nach Anspruch 4,
gekennzeichnet durch
- eine Quelle eines Taktsignales (CK), in welcher Bildungsmittel (40, 51) für das dritte periodische Signal arbeiten, um Signale für Ganzzahl (C_{MI}) und Bruchteil (C_{MP}) (integer and fraction part signals) des dritten periodischen Signales zu bilden, wobei das Ganzzahl-Teilsignal (C_{MI}) einen korrespondierenden Zyklus des Taktsignales (CK) anzeigt und wobei das Bruchteils-Teilsignal (C_{MP}) einen korrespondierenden Bruchteil eines Zyklusses des Taktsignales (CK) anzeigt und
 - Mittel (253, 54), die abhängig sind von den Ganzzahl- (C_{MI}) und Bruchteils- (C_{MP}) Teilsignalen des dritten periodischen Signales, zum Erzeugen des Ablenk-Ausgangssignales (HORDRIVE) in Übereinstimmung mit Zeitverlaufs-Informationen (timing information), die darin enthalten ist.
7. Einrichtung nach Anspruch 4,
dadurch gekennzeichnet,
daß die Kombiniermittel ein Zeitverschiebe-Mittel (51) der Phasensteuerschleifen-Schaltung (120) aufweist, das erste und zweite periodische Signale (C_{Ma}, C_{Mb}) in Übereinstimmung mit einem Ausgangssignal (LPFO') des Phasendetektors (202') zeitverschiebt.

Revendications

1. Dispositif de déviation sensible à un signal d'entrée de synchronisation horizontale (H_s) pour générer un signal de sortie de déviation (HORDRIVE) qui forme des cycles de déviation correspondants dans un circuit de déviation pendant une période donnée dudit signal d'entrée de telle sorte que la fréquence desdits cycles de déviation est un multiple entier dudit signal d'entrée, ledit dispositif comprenant :
- un circuit de boucle à verrouillage de phase (20) sensible audit signal d'entrée de synchronisation horizontale (H_s) pour produire dans ladite période donnée de celui-ci un signal périodique (Ca) à une fréquence qui est reliée à la fréquence dudit signal d'entrée (H_s) ;
 - un étage de sortie horizontale (41) dudit circuit de déviation horizontale sensible audit signal de sortie (HORDRIVE) pour générer lesdits cycles de déviation de fréquence multiple et pour développer un signal indicateur d'un cycle de déviation (FLYBACK) qui contient une information de phase desdits cycles de déviation de fréquence supérieure ; et
 - une boucle à réglage de phase (120) comportant un détecteur de phase (202') qui génère un signal de commande (LPFO') en conformité avec ledit signal (FLYBACK) indicateur de cycle de déviation de fréquence supérieure et en conformité avec ledit signal périodique (Ca), ladite boucle à verrouillage de phase étant sensible audit signal périodique (Ca) pour générer ledit signal de sortie (HORDRIVE) qui forme lesdits cycles de déviation à la fréquence qui est un multiple dudit signal d'entrée (H_s) et dans la phase qui est déterminée en conformité avec ledit signal de commande (LPFO') dudit détecteur de phase (202').
2. Dispositif selon la revendication 1, caractérisé en ce que :
- ledit circuit de boucle à verrouillage de phase (20) produit les premier (C_{Ma}) et second (C_{Mb}) signaux périodiques, ledit second signal étant ledit premier signal décalé en temps ; et
 - ledit circuit à réglage de phase (12) est sensible auxdits premier (C_{Ma}) et second (C_{Mb}) signaux périodiques pour générer à partir dudit premier signal périodique (C_{Ma}) une première composante et pour générer à partir du second signal périodique (C_{Mb}) une seconde composante dudit signal de sortie de déviation (HORDRIVE) pendant ladite période donnée dudit signal d'entrée de synchronisation horizontale (H_s).
3. Dispositif selon la revendication 2 caractérisé en ce que ledit circuit de boucle à réglage de phase (120) est seulement sensible au signal indicateur de cycle de déviation (FLYBACK) qui correspond à un cycle du courant de déviation horizontale associé avec l'une seulement desdites première et seconde composantes dudit signal de sortie de déviation (HORDRIVE).



4. Dispositif selon la revendication 2 caractérisé par un moyen (40, 51) de combinaison desdits premier (C_{Ma}) et second (C_{Mb}) signaux périodiques pour former un troisième signal périodique (C_{MI}, C_{MP}).
5. Dispositif selon la revendication 4 caractérisé en ce que ledit moyen de combinaison comprend un multiplexeur (40) qui couple alternativement lesdits premier (C_{Ma}) et second (C_{Mb}) signaux périodiques pour former un signal périodique combiné (C_{Ma}, C_{Mb}).
6. Dispositif selon la revendication 4 caractérisé par une source de signal d'horloge (CK), dans lequel ledit moyen de formation du troisième signal périodique (40, 51) est opérationnel pour former des signaux de la partie entière (C_{MI}) et de la partie fractionnaire (C_{MP}) dudit troisième signal périodique, dans lequel ledit signal de la partie entière (C_{MI}) est un indicateur d'un cycle correspondant dudit signal d'horloge (CK) et dans lequel ledit signal de la partie fractionnaire (C_{MP}) est un indicateur d'une fraction correspondante d'un cycle dudit signal d'horloge (CK) et un moyen (253, 54) sensible auxdits signaux des parties entière (C_{MI}) et fractionnaire (C_{MP}) dudit troisième signal périodique pour produire ledit signal de sortie de déviation (HORDRIVE) en conformité avec l'information de synchronisation contenu en lui.
7. Dispositif selon la revendication 4 caractérisé en ce que ledit moyen de combinaison inclut un moyen de décalage en temps (51) dudit circuit de boucle à réglage de phase (120) qui décale en temps les premier et second signaux périodiques (C_{Ma}, C_{Mb}) en conformité avec une sortie (LPFO') dudit détecteur de phase (202').

