

DIRECTION FINDER ANTENNA SYSTEM

TECHNOLOGICAL FIELD

The present invention is in the field of antenna systems and is particularly relevant for direction finding antenna systems.

5 BACKGROUND

Direction finding antenna systems are used in various fields. Such antenna systems are generally configured for collecting electromagnetic signals, such as radio frequency (RF) signal, and provide output data that enables determining direction from which the received signal was transmitted. Generally, direction finding antenna systems
10 include an array of two or more antenna elements, located at selected positions with predetermined arrangement. The different antenna elements collect input signal with different phases and amplitudes, thereby enabling to reconstruct data on the direction from which the signal was transmitted.

Various techniques have been described, providing broadband direction-finding
15 antenna system. Some of these techniques utilize conical antenna units, partial cone antenna as well as Vivaldi type antenna units. For example

US 6,346,920 describes a broadband partial fan cone direction finding antenna and array. The antenna includes a radiator having a partial cone shape. The radiator substantially occupies a spatial area defined by a portion of a cone and the cone is
20 defined by a cone axis, a cone height, and a cone angle. The cone has a base and an apex, and the portion of the cone is defined by a cone sweep angle. The cone sweep angle is determined as the angle subtended by a projection of the portion of the cone projected onto a plane that is perpendicular to the cone axis. The cone sweep angle is less than 360degrees so that the portion of the cone is bounded on its sides by edges
25 which extend radially from the apex of the cone outward to the base of the cone.

GENERAL DESCRIPTION

As indicated above, direction finding antenna systems are typically required to operate in diverse conditions and enable to determine direction of signals of various RF frequencies. A drawback in typical broadband direction-finding (DF) antenna systems
5 relates to variation in phase difference of signal portions collected by different antenna elements. Generally, for given locations of an array of antenna elements, phase difference between signal portions collected by the antenna elements are determined by frequency of the collected signals. Thus, for determining direction of origin for signals of lower frequency at given accuracy, the antenna array needs to be larger.

10 The present technique provides for direction finding (DF) antenna system that is capable of determining direction of origin from which collecting signals have been transmitted/arrived. Further, the DF antenna system is configured for enabling to determine direction of origin for wide frequency range (broadband) of signals. The antenna system of the present invention is configured to be of relatively small form
15 factor (with respect to bandwidth of operation) and enables high accuracy of direction finding for various frequencies.

To this end the present technique utilizes an antenna system comprising an array of antenna elements arranged in circular arrangement around a common/central axis. The antenna elements are configured as tapered dipole antenna elements each having a
20 pair of curved arms and configured such that effective phase center for collection of signals is dependent on signal frequency. More specifically, the tapered dipole antenna elements are configured such that for lower frequencies, phase center of each tapered dipole antenna element is located at periphery of the system with respect to phase centers for signals of higher frequency. Preferably, a ratio between wavelength of
25 collected signal and radial distance of the corresponding phase center is within predetermined range. For example, in some configurations of the system, an effective radius of the antenna system for collection of signals at frequency of 100MHz (wavelength of about 2.998m) is 1.5meters, while effective radius for collection of signals at frequency of 1000MHz (wavelength of about 29.98cm) is 15cm. In this
30 example, a ratio R/λ is about $R/\lambda \approx 0.5$. Generally, the numerical value of R/λ may differ between various configurations of the system relating to material, curvature of the antenna elements etc. In the general configuration according to the present invention the

values of R/λ may be vary by 50% within the frequency band for which the system is configures.

Thus, according to one broad aspect, the invention provides a direction finding antenna system comprising a plurality of tapered dipole antenna elements arranged in
5 circular array around a central axis; wherein each tapered dipole antenna element comprises a pair of rectangular elongated antenna elements mounted radially from said central axis and configured to be curved such that a distance between said pair of rectangular elongated antenna elements is larger at periphery of the system with respect to center thereof.

10 The rectangular elongated antenna elements may comprise at least one metal stripe sandwiched between two flexible dielectric stripes. Additionally, or alternatively, the rectangular elongated antenna elements of the dipole antenna elements may be configured with ratio between length dimension and width dimension thereof being greater than 10 ($L/W > 10$).

15 According to some embodiments, the rectangular elongated antenna elements may be configured with one or more chokes at selected location of the rectangular elongated antenna elements. To this end the rectangular elongated antenna elements may comprise one or more bent metal tips along length thereof. The at least one choke, or bent at least one metal tip, may be located at peripheral end of the rectangular
20 elongated antenna elements. The bent metal tips may comprise at least outward bent and inward bent of different lengths, providing outward and inward chokes.

According to some embodiments, the rectangular elongated antenna elements of said tapered dipole antenna elements may be curved such that phase center of the tapered dipole antenna elements is distal for signals of lower frequency and central for
25 signals of higher frequency.

The curvature of the rectangular elongated antenna elements may be selected to provide a ratio between wavelength of collected signal and radial distance of corresponding phase center of signal detection being within predefined range for a selected bandwidth. For example, R/λ may differ by no more than 50% within
30 bandwidth of operation of the system.

According to some embodiments, the plurality of dipole antenna elements may comprise dipole antenna elements of two groups configured for collection of signals of two orthogonal polarizations respectively.

The arrangement of the dipole antenna elements generally defines a general plane for determining signal direction, dipole antenna elements of said two groups may comprise dipole antenna mounted for collection of signals of polarities at +45 degrees and -45degrees with respect to said general plane.

5 According to some embodiments, dipole antenna elements may comprise dipole antenna elements mounted for collection of signals having vertical polarization with respect to said general plane. The direction-finding antenna system may further comprise a second circular array of antenna elements configured for collection of signal having horizontal polarization.

10 According to some embodiments, the DF antenna system may be configured for operation in RF frequencies between 20 MHz and 1200MHz, or between 20MHz and 1000MHz. In some configurations, the DF antenna system may be operable in frequency range between 80 MHz and 600MHz, or between 80 MHz and 250MHz, or between 80 MHz and 150MHz, or between 180 MHz and 250MHz, or between 400
15 MHz and 600MHz.

 According to some embodiments, the DF antenna system may be configured to be in mobile mode suitable for low form factor and high mobility and in operation mode configured to be deployed at a selected location for operating in determining direction of origin of collected signals.

20

BRIEF DESCRIPTION OF THE DRAWINGS

 In order to better understand the subject matter that is disclosed herein and to exemplify how it may be carried out in practice, embodiments will now be described, by way of non-limiting example only, with reference to the accompanying drawings, in
25 which:

Figs. 1A and 1B illustrate configuration of a DF antenna system according to some embodiments of the invention, Fig. 1A illustrates tapered dipole antenna elements using curved elongated antenna elements and Fig. 1B illustrates a top view of circular arrangement of the tapered dipole antenna elements;

30 **Fig. 2** exemplifies possible closed configuration of the DF antenna system according to some embodiments;

Fig 3 exemplifies tapered dipole antenna element utilizing peripheral chokes and external dielectric cover according to some embodiments of the invention;

Figs. 4A and 4B illustrate tapered dipole antenna elements' configuration for collection of signals with various polarizations;

5 **Figs. 5A to 5D** exemplify tapered dipole antenna elements (**Fig. 5A**), DF system configuration (**Fig. 5B**), simulated S11 parameter (**Fig. 5C**) and expected gain (**Fig. 5D**) for exponential curve profile according to some embodiments of the invention;

Figs. 6A to 6D show beam pattern maps for signals having frequencies of 30MHz, 150MHz 500MHz and 1000MHz respectively;

10 **Figs. 7A to 7C** exemplifies configuration of DF antenna system using exponential curved antenna elements and additional horizontal dipole antenna elements (**Fig. 7A**), corresponding simulated S11 (**Fig. 7B**) and expected gain (**Fig. 7C**);

Figs. 8A to 8D show beam pattern maps for signal frequencies of 88MHz, 96MHz, 100MHz and 108MHz respectively with horizontal polarization collected by
15 the horizontal dipole antenna elements of **Fig. 7A**;

Figs. 9A-9I illustrate DF antenna system with linear configuration of the tapered dipole antenna elements (**Fig. 9A**) and beam patterns for signal frequencies of 30MHz, 130MHz, 180MHz, 220MHz, 300MHz, 500MHz, 750MHz and 1000MHz in **Figs. 9B to 9I** respectively;

20 **Figs. 10A-10I** illustrate DF antenna system with bi-linear configuration of the tapered dipole antenna elements (**Fig. 10A**) and beam patterns for signal frequencies of 30MHz, 130MHz, 180MHz, 220MHz, 300MHz, 500MHz, 750MHz and 1000MHz in **Figs. 10B to 10I** respectively;

Figs. 11A-11I illustrate DF antenna system with tri-linear configuration of the
25 tapered dipole antenna elements (**Fig. 11A**) and beam patterns for signal frequencies of 30MHz, 130MHz, 180MHz, 220MHz, 300MHz, 500MHz, 750MHz and 1000MHz in **Figs. 11B to 11I** respectively;

Figs. 12A-12I illustrate DF antenna system with parabolic configuration of the tapered dipole antenna elements (**Fig. 12A**) and beam patterns for signal frequencies of
30 30MHz, 130MHz, 180MHz, 220MHz, 300MHz, 500MHz, 750MHz and 1000MHz in **Figs. 12B to 12I** respectively;

Figs. 13A to 13I illustrate DF antenna system with quarter-circle configuration of the tapered dipole antenna elements (**Fig. 13A**) and beam patterns for signal

frequencies of 30MHz, 130MHz, 180MHz, 220MHz, 300MHz, 500MHz, 750MHz and 1000MHz in Figs. **13B to 13I** respectively;

Figs. 14A to 14J illustrate DF antenna system with quarter-circle configuration of the tapered dipole antenna elements and additional of chokes in selected locations
5 **(Fig. 14A)** exemplify chokes configuration **(Fig. 14B)** and beam patterns for signal frequencies of 30MHz, 130MHz, 180MHz, 220MHz, 300MHz, 500MHz, 750MHz and 1000MHz in Figs. **14C to 14J** respectively;

Figs. 15A to 15I illustrate DF antenna system with general curvature configuration of the tapered dipole antenna elements determined by mechanical
10 constrains **(Fig. 15A)** and beam patterns for signal frequencies of 30MHz, 130MHz, 180MHz, 220MHz, 300MHz, 500MHz, 750MHz and 1000MHz in **Figs. 15B to 15I** respectively.

DETAILED DESCRIPTION OF EMBODIMENTS

15 Reference is made to **Figs. 1A and 1B** exemplifying direction finding antenna system **100**. **Fig. 1A** illustrates a portion of direction finding antenna system **100** according to some embodiments of the present invention along a horizontal plane; and **Fig. 1B** illustrates a top view of the DF antenna system **100**. In the example of **Fig. 1A**, the system **100** is illustrated with two dipole antenna elements **50a** and **50b**. Generally,
20 the DF antenna system **100** is configured with a plurality of three or more dipole antenna elements arranged in circular array about a common/central axis **CA**, while **Fig. 1A** illustrates two dipole elements **50a** and **50b** for simplicity and to illustrate the structure of the dipole elements. The dipole antenna elements **50a** and **50b** are configured as tapered dipole antenna elements having tapering directed away from
25 central axis of the system **100**.

Each of the dipole antenna elements **50a** and **50b** include a pair of rectangular elongated antenna elements **52** and **54** that are mounted radially from the common axis **CA**, and generally an adaptor/connector unit **56** providing electronic connection to the antenna elements for feed and readout. The rectangular elongated elements **52** and **54**
30 are mounted to be curved as illustrated in **Fig. 1A**. Effectively, a distance between the rectangular elongated antenna elements **52** and **54** grows from center (closer to axis

CA) toward periphery of the system **100**. Thus, a collection aperture of the antenna system **100** effectively increases as the frequency of collected signal decreases.

Fig. 1B illustrates a top view of DF antenna system **100** according to some examples of the invention. As shown, system **100** in this example includes eight dipole antenna elements, generally at **50**, arranged in circular array around a common axis **CA**. In this example, the dipole antenna elements **50** are connected to a central feed/readout box **58** providing electronic connection to the plurality of antenna elements. It should be generally noted that the DF antenna system of the invention may be configured with three or more dipole antenna elements **50**. More specifically, the system **100** may be configured with 4, 5, 6, 7, 8, 9 or more dipole antenna elements in circular array.

Generally, the DF antenna system **100** according to the present techniques is configured for collecting input electromagnetic signals and providing output data indicative of direction from which the collected signal has been transmitted from, or has arrived. To this end the different dipole antenna elements **50** of system **100** are located in a predetermined array configuration, such that phase and temporal variations of signals as collected by each dipole antenna element provide data about direction of propagation of the signal, and thus of direction to its source. As the collected signal is generally of unknown source, direction and frequency band, the DF antenna system is preferably capable for operating at wide bandwidth. To this end, the dipole antenna elements of the present technique are configured with selected curvature providing variation in phase center in accordance with signal frequency.

More specifically, electromagnetic signals of higher frequency are collected at central portions of the dipole antenna element, where the distance between the rectangular curved antenna elements is smaller. This is while electromagnetic signals of lower frequency (longer wavelength) are effectively collected at peripheral portion of the dipole antenna element, where the distance between the rectangular curved antenna elements is greater. Accordingly, the location of phase centers of each tapered dipole antenna element is shifted radially in accordance with frequency of collected signals providing effective variation in aperture of signal collection. The effective aperture (radius of the DF system circular arrangement) is increased for collection of signals of lower frequency, and reduced for collection of signals of higher frequency. This maintains phase center variations with respect to signal frequency, and enables the DF system to identify direction of origin of the collected signals within wide frequency

bandwidth. In some exemplary configurations, the curvature of the rectangular elongated antenna elements is selected to provide that radial location R (with respect to the central axis CA) of effective phase center for collection of signal of wavelength λ , provides a ratio R/λ being substantially constant, or varying within no more than 50% for different wavelengths within the frequency band that the antenna system is designed for. For example, some configurations provide radial location of phase center for collection of signal at frequency of 1000MHz at 15cm from the CA , and radial location of phase center for collection of signals at frequency of 100MHz to be at 150cm from the CA .

10 Additionally, the DF antenna system of the present invention may be configured to be partially portable and can be deployed at a selected region. To this end the antenna system 100 is preferably configured with relatively low form factor and reduced material weight. Reference is made to **Fig. 2** illustrating an exemplary configuration of DF antenna system **100** in a folded position. As shown, the antenna elements **52** and **54**
15 may be aligned along the central axis CA . The antenna elements may be aligned toward different direction as illustrated in **Fig. 2**, or toward a similar direction, i.e. both rectangular elongated antenna elements of each dipole antenna element are aligned upward or downward, or one rectangular elongated antenna element is aligned upward and the other one is aligned downward with respect to the central axis. Alternatively,
20 the antenna system **100** may be configured to be taken apart by disconnecting the rectangular elongated antenna elements from the central axis CA . In this connection, it should be noted that the DF antenna system **100** as described herein is preferably configured to be relatively mobile and having low form factor, with respect to size of antenna elements required for collection of electromagnetic signals of the respective
25 bandwidth. Accordingly, the use of rectangular elongated antenna elements is preferred over the fan-like elements as known in the art, for reducing weight and size of the antenna system, while maintaining effective collection of electromagnetic signals.

Reference is further made to **Fig. 3** illustrating a dipole antenna element **50** according to some embodiments of the invention. As shown, the dipole antenna element
30 **50** includes adapter/connector unit **56** located at vicinity of the central axis, and two rectangular elongated antenna elements **52** and **54** extending from the adaptor **56** toward periphery of the antenna system, while having selected curvature to provide tapered dipole antenna element **50**. The rectangular elongated antenna elements may be

configured by conducting (e.g. metallic) stripes, e.g. at **62**, located between two dielectric stripes **64** and **66**. Preferably, the dielectric stripes **64** and **66** are flexible, enabling bending of the elongated antenna elements **52** and **54** to the desired curvature.

Also, as illustrated in **Fig. 3**, the rectangular elongated antenna elements **52** and **54** may further include one or more chokes, illustrates herein as bent metal tips, along length thereof. The bent metal tips **72** and **74** of the chokes are exemplified at peripheral end of the elongated antenna elements **52** and **54**. However, it should be understood that the bent tips may be located at any point along the element **52** or **54**. Generally, the dipole antenna element **50** may include outward/external bents, e.g. **72**, directed outward from tapering of the dipole antenna element, and inward/internal bents, e.g. **74**, directed inward with respect to tapering of the dipole antenna element. Generally, the outward **72** and inward **74** bents may be of different length. Typically, bended tips in antenna units are provided for reducing interference of signals reflected from the material of the antenna element. The use of bended tips of different lengths may provide further elimination of signal interferences for signals of broad frequency range.

The DF antenna system **100** according to the present technique may also be configured for collecting signals of various polarization states for determining direction from which the signals originate. Reference is made to **Figs. 4A and 4B** exemplifying dipole antenna elements' configurations enabling collection of signals of different polarizations. **Fig. 4A** illustrates overlapping tapered dipole antenna elements arranged at $\pm 45^\circ$ with respect to a plane defined by the circular arrangement of the tapered dipole antenna elements, and **Fig. 4B** illustrates tapered dipole antenna element align vertically combined with additional dipole antenna element aligned horizontally, with respect to a plane defined by circular arrangement of the antenna system. **Fig. 4A and 4B** are illustrated as seen along radial axis of the antenna system, and the central axis **CA** is marked in **Fig. 4A** to simplify understanding. As shown in **Fig. 4A**, rectangular elongated antenna elements **52a** and **54a** form a dipole antenna element aligned at $+45^\circ$ and rectangular elongated antenna elements **52b** and **54b** for dipole antenna element aligned at -45° . This configuration enables detection of signals having generally any polarization. In the example of **Fig. 4B**, rectangular antenna elements **52** and **54** for dipole antenna element aligned vertical to plane defined by the circular array of the antenna system (perpendicular to the central axis), and configured for collecting signals with vertical polarization. In this example, the antenna system further includes

additional arrangement of dipole antenna element **55** configured for collecting signals of horizontal polarization. Such combined polarization dipole antenna elements provide for collecting input electromagnetic signals having any possible polarization state, such as linear polarization along horizontal, vertical axes or at an angle between them, as well as circular polarization states.

According to some examples, the DF antenna system was tested with several curvature profiles. **Figs. 5A to 5D** exemplify DF antenna system configured with an arrangement of seven (7) dipole antenna elements configured in a circular array. Each dipole antenna element includes a pair of exponentially curved rectangular elongated antenna elements providing radius of the circular arrangement of 1500mm. In some examples, the actual portion of the radius formed by the elongated antenna element **52** and **54** is about 1300mm resulting from the connections/adaptors connecting the antenna element and located around the central axis CA. The actual length of each antenna element may be greater along the curvature thereof.

Fig. 5A illustrates curvature of a pair of rectangular antenna elements **52** and **54**, curved to provide an Exponential curve described by a general formula $ae^{br}+c$ for antenna element **52**, and $-ae^{br}-c$ for antenna element **54** (where r is the radial coordinate indicating distance from the central axis along a plane defined by the circular array). **Fig. 5B** illustrates a three-dimensional representation of the antenna system **100** having 7 dipole antenna elements in circular array around central axis and where each of the dipole antenna elements include pair of exponentially curved antenna elements. **Fig. 5C** shows expected S11 data simulated for the antenna system of **Fig. 5B**, and **Fig. 5D** shows simulated expected gain.

Direction finding results of this exemplary antenna system are illustrates in **Figs. 6A to 6D** showing DF results for collected signals at frequencies of 30MHz, 150MHz, 500MHz and 1000MHz respectively. These results illustrate estimates angle of arrival (AOA) determined for collected signals of various angles of arrival (AOA). For each collected signal of certain AOA, the antenna system generates output data indicative of phase variations between signal portions as collected by each of the dipole antenna elements. This phase variation map enables determining an estimated AOA shown for each of the various AOA values. In the figures, bright color indicated high estimation values (the estimated AOA's). As seen, the diagonal line indicating

agreement between the estimated AOA and the actual AOA is bright, showing accurate direction finding data.

An additional example is illustrated in **Fig. 7A** with simulated S11 and gain results shown in **Figs. 7B and 7C**. This example is based on the configuration illustrated in **Fig. 4B** utilizing dipole antenna elements utilizing curved elongated antenna elements **52** and **54** in combination with a horizontal bent dipole antenna element **55**. This configuration provides for collecting electromagnetic signals having different polarizations where the linear vertical polarization components of signals are collected by antenna elements **52** and **54** provides wide bandwidth while collection of the horizontal polarization components has relatively narrow band, e.g. of 50MHz to 150MHz. **Figs. 7B and 7C** show estimated S11 and Gain values for the bandwidth of 80MHz to 110MHz (or 88MHz to 108MHz) indicating overall good performance.

Direction finding simulation results in the form of beam pattern graphs are shown in **Figs. 8A to 8D** corresponding with signal frequencies of 88MHz, 96MHz, 100MHz and 108MHz with horizontal polarization. These results show clear correspondence between the angle of arrival (AOA) and the estimated AOA determined based on signal collection using the DF antenna system and effective direction-finding performance by the dipole antenna elements **55** configured for collecting signals of horizontal polarization.

Additional exemplary configurations are illustrated in **Figs. 9A-9I, 10A-10I, 11A-11I and 12A-12I**. These configurations vary in structure of the tapered dipole antenna elements of the DF antenna system.

Figs. 9A to 9I illustrate configuration of DF antenna system utilizing linear elongated antenna elements of the tapered dipole antenna elements. **Fig. 9A** illustrates structure of the antenna system and **Figs. 9B to 9I** show beam pattern graphs indicative of operation of the direction-finding technique and accuracy thereof for signal frequencies of 30MHz, 130MHz, 180MHz, 220MHz, 300MHz, 500MHz, 750MHz and 1000MHz respectively. As shown in **Fig. 9A**, the tapered dipole antenna elements are formed by pairs of elongated stripes acting as antenna elements. The two elongated antenna elements are mounted at a selected angle between them such that the elements are close to each other at vicinity of the central axis and are further from each other at periphery of the system.

Figs. 10A to 10I illustrate a bi-linear configuration of the elongated antenna elements. **Fig. 10A** illustrates configuration of the DF antenna system including 7 tapered dipole antenna elements configured with pairs of bi-linear elongated antenna elements, and **Figs. 10B to 10I** show beam pattern graphs indicative of operation of the direction-finding technique and accuracy thereof for signal frequencies of 30MHz, 130MHz, 180MHz, 220MHz, 300MHz, 500MHz, 750MHz and 1000MHz respectively. As shown in Fig. 10A, the bi-linear elongated antenna elements are formed of pair of elongated antenna elements angled to distant from each other at a first angle between the central axis and certain radial position, and at a second, larger angle from the selected position toward periphery of the DF antenna system.

Figs. 11A to 11I illustrate a tri-linear configuration that is otherwise similar to the configurations shown in **Figs. 9A-9I and 10A-10I**. **Fig. 11A** illustrates structure of the DF antenna system using tri-linear elongated antenna elements, and **Figs. 11B to 11I** show beam pattern graphs indicative of operation of the direction-finding technique and accuracy thereof for signal frequencies of 30MHz, 130MHz, 180MHz, 220MHz, 300MHz, 500MHz, 750MHz and 1000MHz respectively.

Figs. 12A to 12I show a parabolic configuration of the DF antenna system. **Fig. 12A** illustrates a DF antenna system including 7 tapered dipole antenna elements having parabolic curved elongated antenna elements, generally having a curvature of the form ar^2+br+c and $-ar^2-br-c$ (where r is the radial coordinate indicating distance from the central axis along a plane defined by the circular array), and **Figs. 12B to 12I** show beam pattern graphs indicative of operation of the direction-finding technique and accuracy thereof for signal frequencies of 30MHz, 130MHz, 180MHz, 220MHz, 300MHz, 500MHz, 750MHz and 1000MHz respectively.

Additional curve configuration is exemplified in **Figs. 13A to 13I**. **Fig. 13A** illustrates DF antenna system including elongated antenna elements curved to the form for quarter circle, i.e. being curved according to the form $\sqrt{R^2 - r^2} - a$ (and $-\sqrt{R^2 - r^2} + a$) (where R is a selected curvature radius, a is a selected constant defining displacement between the antenna elements and r relates to radial coordinate), and **Figs. 13B to 13I** show beam pattern graphs indicative of operation of the direction-finding technique and accuracy thereof for signal frequencies of 30MHz, 130MHz, 180MHz, 220MHz, 300MHz, 500MHz, 750MHz and 1000MHz respectively.

Figs. 14A to 14J exemplify DF antenna system utilizing quarter circle antenna elements utilizing chokes at selected location along curvature of the antenna elements. **Fig. 14A** illustrates a single dipole antenna element in which the quarter wave ($\lambda/4$) chokes **152** and **154** are included along curvature of the antenna elements **52** and **54**,
5 **Fig. 14B** illustrates the chokes **152** on antenna element **52** in more details, and **Figs. 14C to 14J** show corresponding beam pattern graphs for signal frequencies of 30MHz, 130MHz, 180MHz, 220MHz, 300MHz, 500MHz, 750MHz and 1000MHz respectively.

As exemplified in **Fig. 14B**, the chokes are generally configured as bent tips of
10 conducting material extending from the antenna elements **52** or **54**, similarly to the example of **Fig. 3**. The chokes may be located at different positions along the antenna elements **52** and **54** and are used for reducing interference of signal portions reflected from the antenna element. The sue of choke may typically increase direction finding accuracy for signals of high frequency, generally by reducing signal interference that
15 causes estimation errors, as can be seen between **Figs. 13I and 14J** relating to 1000MHz frequency.

Generally, it can be seen from the above described examples, as well as the example of **Figs. 5A to 5B** and **Figs. 6A to 6D**, that tapering of the dipole antenna elements provides accurate direction-finding results over a broad band of frequencies.
20 Further, the examples of exponential curve of **Figs. 5A and 5B** and quarter circle of **Fig. 13A** and **Fig. 14A** typically show greater accuracy over wide bandwidth.

In addition to the above described configurations, the inventors of the present invention considered mechanical constrains as well as preferred wide band performance. In this connection reference is made to **Figs. 15A to 15I** illustrating a DF
25 antenna system configuration determined in according with mechanical constrains of the system and corresponding beam pattern graphs. In **Fig. 15A**, the DF antenna system is configured with dipole antenna elements formed by elongated curved antenna elements as described above. Curvature of the antenna elements is formed by mechanical tension provided by constructions of the system. More specifically, the
30 elongated antenna elements are mounted at vicinity of the central axis to corresponding connectors, where at the mounting location, the antenna elements are oriented parallel to each other extending along the radial direction. At a distal point, located between 0.6 of total length to the distal end of the antenna elements, each antenna element is

connected to a second mount, e.g. cable, providing tension toward higher (and lower) point on the central axis, thus bending the antenna element.

Generally, the rectangular elongated antenna elements may be formed from various materials, preferably including a conducting layer located between two sheets of dielectric material as illustrated in **Fig. 3**. More specifically the rectangular elongated antenna elements may be formed from any one of the following materials: Epoxy Glass, Polycarbonate, Bakelite, Fibber Glass/fiberglass, Plexiglas and Lexan. The electrically conducting layer may be provided as metal sheet and/or suitable doping of the dielectric material to provide sufficient conducting.

Thus, the present technique provides for a broad band direction finding antenna system. The system is configured to be of low form factor, being deployable and mobile. The antenna system is configured with a plurality of tapered dipole antenna element formed of rectangular elongate stripes.

CLAIMS:

1. A direction-finding antenna system comprising a plurality of tapered dipole antenna elements arranged in circular array around a central axis; wherein each tapered dipole antenna element comprises a pair of rectangular elongated antenna elements
5 mounted radially from said central axis and configured to be curved such that a distance between said pair of rectangular elongated antenna elements is larger at periphery of the system with respect to center thereof.
2. The direction-finding antenna system of claim 1, wherein said rectangular elongated antenna elements comprise at least one metal stripe sandwiched between two
10 flexible dielectric stripes.
3. The direction-finding antenna system of claim 1 or 2, wherein said rectangular elongated antenna elements of said dipole antenna elements are configured with ratio between length dimension and width dimension thereof being greater than 10 ($L/W > 10$).
- 15 4. The direction-finding antenna system of any one of claims 1 to 3, wherein said rectangular elongated antenna elements comprise one or more chokes along length thereof.
5. The direction-finding antenna system of claim 4, wherein said one or more chokes are located at peripheral end of the rectangular elongated antenna elements.
- 20 6. The direction-finding antenna system of claim 4 or 5, wherein said one or more chokes comprise at least outward choke and inward choke of different lengths.
7. The direction-finding antenna system of any one of claims 1 to 6, wherein the rectangular elongated antenna elements of said tapered dipole antenna elements are curved such that phase center of the tapered dipole antenna elements is distal for signals
25 of lower frequency and central for signals of higher frequency.
8. The direction-finding antenna system of claim 7, wherein curvature of the rectangular elongated antenna elements is selected to provide a ratio between wavelength of collected signal and radial distance of corresponding phase center of signal detection being within predefined range for a selected bandwidth.
- 30 9. The direction-finding antenna system of any one of claims 1 to 8, wherein said plurality of dipole antenna elements comprises dipole antenna elements of two groups configured for collection of signals of two orthogonal polarizations respectively.

- 10.** The direction-finding antenna system of claim 8, wherein arrangement of the dipole antenna elements defines a general plane for determining signal direction, dipole antenna elements of said two groups comprise dipole antenna mounted for collection of signals of polarities at +45degrees and -45degrees with respect to said general plane.
- 5 **11.** The direction-finding antenna system of any one of claims 1 to 8, wherein said plurality of tapered dipole antenna elements comprise dipole antenna elements mounted for collection of signals having vertical polarization with respect to general plane defined by the circular arrangement thereof.
- 12.** The direction-finding antenna system of claim 11, further comprising a second
10 circular array of antenna elements configured for collection of signal having horizontal polarization.
- 13.** The direction-finding antenna system of any one of claims 1 to 12, configured for operation in RF frequencies between 20 MHz and 1000MHz.
- 14.** The direction-finding antenna system of any one of claims 1 to 12, configured
15 for operation in RF frequencies between 80 MHz and 600MHz.
- 15.** The direction-finding antenna system of any one of claims 1 to 12, configured for operation in RF frequencies between 80 MHz and 250MHz.
- 16.** The direction-finding antenna system of any one of claims 1 to 12, configured for operation in RF frequencies between 80 MHz and 150MHz.
- 20 **17.** The direction-finding antenna system of any one of claims 1 to 12, configured for operation in RF frequencies between 180 MHz and 250MHz.
- 18.** The direction-finding antenna system of any one of claims 1 to 12, configured for operation in RF frequencies between 400 MHz and 600MHz.
- 19.** The direction-finding antenna element of any one of claims 1 to 18, wherein said
25 system being configured in mobile mode suitable for low form factor and high mobility and in operation mode configured to be deployed at a selected location for operating in determining direction of origin of collected signals.