

Description.

This invention relates to automatic gain control circuits and particularly, though not exclusively, to automatic gain control circuits for use in the demodulation of FM signals.

In the demodulation of FM signals in a SECAM television system using sampling techniques, e.g. switched capacitor filter techniques, non-linearity of the circuit results in the generation of frequency components higher than the Nyquist value which can cause beat notes in the system. For example, the frequency band in a SECAM system is 3.9—4.75 MHz and so the 3rd. harmonic (such as would be generated by a limiter as normally used in FM systems) of this frequency band is 11.7—14.25 MHz. Sampling at a frequency of approximately 17.73 MHz (i.e. four times the PAL sub carrier frequency, as is convenient in a TV receiver) generates a frequency band of approximately 3.5—6.0 MHz. Further non-linearity produces beating between this generated frequency band and the first-mentioned SECAM frequency band.

In order for the system to remain linear, an automatic gain control circuit must be used to remove amplitude variations in the FM signal. However, known automatic gain control circuits cannot readily be made to operate sufficiently fast to cope with amplitude variations resulting from the passage of such FM signals through tuned circuits, etc.

It is an object of the present invention to provide an automatic gain control circuit wherein the above disadvantage may be overcome, or at least alleviated.

In accordance with the invention an automatic gain control circuit comprises:

- an input node;
- an output node;
- controllable gain amplifier means having a signal input connected to the input node, a control input and an output; and
- automatic gain control means having an input coupled to the output of the controllable gain amplifier means and an output connected to the control input of the controllable gain amplifier means,

characterised in that the automatic gain control circuit further comprises divider means having a first signal input coupled to the output of the controllable gain amplifier means, a divide signal input coupled to the input of the automatic gain control means and an output connected to the output node of the circuit, whereby the signal produced at the output of the divider means is substantially independent of the signal level produced at the output of the controllable gain amplifier means.

Preferably the circuit further comprises multiplier means having first and second inputs each connected to the output of the controllable gain amplifier means and an output connected to the input of the automatic gain control means, and the divider means has a second signal input

connected to the output of the controllable gain amplifier means and includes means for multiplying the signals at its first and second signal inputs.

Preferably phase shifting filter means is provided in the signal path to the first signal input of the divider means so that the circuit is frequency discriminating and low-pass filter means is provided in the signal path to the divide signal input of the divider means, the delays produced by the two filter means being so matched as to minimise differential delay effects at the output of the divider means.

One frequency discriminating automatic gain control circuit in accordance with the invention will now be described, by way of example only, with reference to the accompanying drawings, in which:

Figure 1 shows a block-schematic diagram of the circuit; and

Figure 2 shows a more detailed circuit diagram of parts of the circuit of Figure 1.

Referring firstly to Figure 1, a frequency discriminating automatic gain control circuit for use in an FM decoder in a SECAM TV receiver includes an input node 2 connected to the signal input 4 of a variable gain amplifier 6. The output 8 of the amplifier 6 is connected to each of two inputs 10, 12 of a multiplier 14. The output 16 of the multiplier 14 is connected to the input 18 of a known automatic gain control (AGC) gain generator 20. The output 22 of the AGC gain generator 20 is connected to the control input 24 of the amplifier 6 to control the gain thereof.

The output 8 of the amplifier 6 is also connected, via a constant amplitude, phase-shifting filter 26, to a first multiply input 28 of a multiplier/divider 30. The output 8 of the amplifier 6 is also connected directly to a second multiply input 32 of the multiplier/divider 30. The output 16 of the multiplier 14 is also connected, via a low-pass filter 34, to a divide input 36 of the multiplier/divider 30. The output 38 of the multiplier/divider 30 is connected to an output node 40 of the circuit.

In use of the circuit of Figure 1 a SECAM FM signal V_1 applied to the input node 2 is amplified by amplifier 6 to produce a signal V_2 at its output 8. This signal is then rectified by the multiplier 14 to produce at its output 16 a signal kV_2^2 , k being the multiplication factor of the multiplier 14. The rectified signal at the multiplier output 16 is applied to the AGC gain generator 20, which accordingly controls the gain of the amplifier 6, and is also applied via the filter 34 to the divide input 36 of the multiplier/divider 30.

The signal V_2 produced at the output 8 of the amplifier 6 is phase-shifted by the filter 26 in dependence on the frequency of the signal V_2 to produce a phase shifted signal $(V_2)_\theta$ which is applied to the multiply input 28 of the multiplier/divider 30. The signal V_2 produced at the output 8 of the amplifier 6 is also applied directly to the multiply input 32 of the multiplier/divider 30. The multiplier/divider 30 produces at its output 30 a signal V_3 which is the product of the signals $(V_2)_\theta$

and V_2 at its inputs 28 and 32 divided by the signal kV_2^2 at its input 36.

It will be understood that the frequency dependent phase shift provided by the filter 26 produces frequency discrimination in the product of the signals $(V_2)_0$ and V_2 , as is well known, and so also in the signal V_3 .

It will, of course, be readily appreciated that the amplitude of the signal V_3 is independent of the amplitude of the signal V_2 and so is independent of any variations in amplitude which are not compensated by the AGC loop 6, 14, 20. It will also be appreciated that because the signal kV_2^2 is fed forward from the multiplier 14 to the multiplier/divider 30, the compensation provided by the multiplier/divider 30 is not limited by the response time of the AGC gain generator 20 and the variable gain amplifier 6. In practice the AGC loop 6, 14, 20 may typically compensate for relatively slow amplitude variations of wide range (e.g. up to 60 dB) whereas the multiplier/divider 30 may typically compensate for relatively fast amplitude variations of narrow range (e.g. up to 6 dB).

It will also be understood that the delays produced by the filters 26 and 34 are arranged to be substantially the same so as to minimise differential delay effects in the signal V_3 .

Referring now also to Figure 2, the multiplier/divider 30 includes a pair of pnp transistors 302, 304 each having their bases connected to a source of bias voltage V_{B1} and having their emitters connected respectively via resistors 306, 308 to a source of positive supply. A first pair of npn transistors 310, 312 have their emitters commonly connected to a first current source S_1 and have their collectors connected respectively to the collectors of the transistors 302 and 304. A second pair of npn transistors 314, 316 have their emitters commonly connected to a second current source S_2 and have their collectors respectively connected to the collectors of the transistors 304 and 302. The bases of the transistors 310 and 316 are connected via a diode 318 to a source of bias voltage V_{B2} , and the bases of the transistors 312 and 314 are connected via a diode 320 to the voltage V_{B2} . A third pair of npn transistors 322, 324 have their collectors connected respectively to the bases of the transistors 310, 316 and to the bases of the transistors 312, 314. The emitters of the transistors 324 and 322 are interconnected via a resistor 326. A fourth pair of npn transistors 328, 330 have their collectors connected respectively to the emitters of the transistors 322, 324, and have their emitters connected to ground via respective resistors 332, 334.

The emitters of the transistors 310, 312 and the emitters of the transistors 314, 316 are differentially connected as the multiply input 28 of the multiplier/divider 30. The bases of the transistors 322, 324 are differentially connected as the multiply input 32 of the multiplier/divider 30. The bases of the transistors 328, 330 are commonly connected as the divide input 36 of the multiplier/divider 30. The output 38 of the multiplier/divider

30 is taken differentially between the collectors of the transistors 312, 314 and 310, 316. It will be realised that the circuit of Figure 2 acts in known manner as a multiplier, the differential voltage at the output 38 being proportional to the product of the differential signals at the inputs 28 and 32. It will also be understood that the circuit additionally acts as a divider, the voltage at the output 38 being reduced in proportion to the voltage applied at input 36 to the bases of the transistors 328, 330.

It will be appreciated that a similar circuit to that of Figure 2 may be used for the multiplier 14, the voltage there applied to the bases of the transistors 328, 330 being chosen so as to produce a desired multiplication factor k .

It will be appreciated that the circuit described above may conveniently be fabricated in integrated circuit form.

Claims

1. An automatic gain control circuit comprising:
an input node;
an output node;

controllable gain amplifier means having a signal input connected to the input node, a control input and an output; and

automatic gain control means having an input coupled to the output of the controllable gain amplifier means and an output connected to the control input of the controllable gain amplifier means,

characterised in that the automatic gain control circuit further comprises divider means having a first signal input coupled to the output of the controllable gain amplifier means, a divide signal input coupled to the input of the automatic gain control means and an output connected to the output node of the circuit, whereby the signal produced at the output of the divider means is substantially independent of the signal level produced at the output of the controllable gain amplifier means.

2. An automatic gain control circuit according to claim 1 wherein the circuit further comprises multiplier means having first and second inputs each connected to the output of the controllable gain amplifier means and an output connected to the input of the automatic gain control means, and the divider means has a second signal input connected to the output of the controllable gain amplifier means and includes means for multiplying the signals at its first and second signal inputs.

3. An automatic gain control circuit according to claim 2 wherein phase shifting filter means is provided in the signal path to the first signal input of the divider means so that the circuit is frequency discriminating and low-pass filter means is provided in the signal path to the divide signal input of the divider means, the delays produced by the two filter means being so matched as to minimise differential delay effects at the output of the divider means.

and V_2 at its inputs 28 and 32 divided by the signal kV_2^2 at its input 36.

It will be understood that the frequency dependent phase shift provided by the filter 26 produces frequency discrimination in the product of the signals $(V_2)_0$ and V_2 , as is well known, and so also in the signal V_3 .

It will, of course, be readily appreciated that the amplitude of the signal V_3 is independent of the amplitude of the signal V_2 and so is independent of any variations in amplitude which are not compensated by the AGC loop 6, 14, 20. It will also be appreciated that because the signal kV_2^2 is fed forward from the multiplier 14 to the multiplier/divider 30, the compensation provided by the multiplier/divider 30 is not limited by the response time of the AGC gain generator 20 and the variable gain amplifier 6. In practice the AGC loop 6, 14, 20 may typically compensate for relatively slow amplitude variations of wide range (e.g. up to 60 dB) whereas the multiplier/divider 30 may typically compensate for relatively fast amplitude variations of narrow range (e.g. up to 6 dB).

It will also be understood that the delays produced by the filters 26 and 34 are arranged to be substantially the same so as to minimise differential delay effects in the signal V_3 .

Referring now also to Figure 2, the multiplier/divider 30 includes a pair of pnp transistors 302, 304 each having their bases connected to a source of bias voltage V_{B1} and having their emitters connected respectively via resistors 306, 308 to a source of positive supply. A first pair of npn transistors 310, 312 have their emitters commonly connected to a first current source S_1 and have their collectors connected respectively to the collectors of the transistors 302 and 304. A second pair of npn transistors 314, 316 have their emitters commonly connected to a second current source S_2 and have their collectors respectively connected to the collectors of the transistors 304 and 302. The bases of the transistors 310 and 316 are connected via a diode 318 to a source of bias voltage V_{B2} , and the bases of the transistors 312 and 314 are connected via a diode 320 to the voltage V_{B2} . A third pair of npn transistors 322, 324 have their collectors connected respectively to the bases of the transistors 310, 316 and to the bases of the transistors 312, 314. The emitters of the transistors 324 and 322 are interconnected via a resistor 326. A fourth pair of npn transistors 328, 330 have their collectors connected respectively to the emitters of the transistors 322, 324, and have their emitters connected to ground via respective resistors 332, 334.

The emitters of the transistors 310, 312 and the emitters of the transistors 314, 316 are differentially connected as the multiply input 28 of the multiplier/divider 30. The bases of the transistors 322, 324 are differentially connected as the multiply input 32 of the multiplier/divider 30. The bases of the transistors 328, 330 are commonly connected as the divide input 36 of the multiplier/divider 30. The output 38 of the multiplier/divider

30 is taken differentially between the collectors of the transistors 312, 314 and 310, 316. It will be realised that the circuit of Figure 2 acts in known manner as a multiplier, the differential voltage at the output 38 being proportional to the product of the differential signals at the inputs 28 and 32. It will also be understood that the circuit additionally acts as a divider, the voltage at the output 38 being reduced in proportion to the voltage applied at input 36 to the bases of the transistors 328, 330.

It will be appreciated that a similar circuit to that of Figure 2 may be used for the multiplier 14, the voltage there applied to the bases of the transistors 328, 330 being chosen so as to produce a desired multiplication factor k .

It will be appreciated that the circuit described above may conveniently be fabricated in integrated circuit form.

Claims

1. An automatic gain control circuit comprising:

an input node;

an output node;

controllable gain amplifier means having a signal input connected to the input node, a control input and an output; and

automatic gain control means having an input coupled to the output of the controllable gain amplifier means and an output connected to the control input of the controllable gain amplifier means,

characterised in that the automatic gain control circuit further comprises divider means having a first signal input coupled to the output of the controllable gain amplifier means, a divide signal input coupled to the input of the automatic gain control means and an output connected to the output node of the circuit, whereby the signal produced at the output of the divider means is substantially independent of the signal level produced at the output of the controllable gain amplifier means.

2. An automatic gain control circuit according to claim 1 wherein the circuit further comprises multiplier means having first and second inputs each connected to the output of the controllable gain amplifier means and an output connected to the input of the automatic gain control means, and the divider means has a second signal input connected to the output of the controllable gain amplifier means and includes means for multiplying the signals at its first and second signal inputs.

3. An automatic gain control circuit according to claim 2 wherein phase shifting filter means is provided in the signal path to the first signal input of the divider means so that the circuit is frequency discriminating and low-pass filter means is provided in the signal path to the divide signal input of the divider means, the delays produced by the two filter means being so matched as to minimise differential delay effects at the output of the divider means.



4. An automatic gain control circuit according to any preceding claim wherein the divider means comprises:

first and second transistors each having base, collector and emitter electrodes;

third and fourth transistors each having base, collector and emitter electrodes; and

a first resistance coupled between the emitter electrodes of the first and second transistors,

the emitter electrodes of the first and second transistors being coupled respectively to the collector electrodes of the third and fourth transistors,

the emitter electrodes of the third and fourth transistors being coupled to ground and the collector electrodes of the first and second transistors being adapted for coupling to a source of reference potential, whereby the base electrodes of the first and second transistors form the differential signal input of the divider, the bases of the third and fourth electrodes form the divide input of the divider and the output of the divider is coupled to the collector electrodes of the first and second transistors.

5. An integrated circuit incorporating an automatic gain control circuit according to any preceding claim.

6. A SECAM television receiver circuit including an automatic gain control circuit in accordance with any one of claims 1 to 4.

Patentansprüche

1. Automatische Verstärkungsregelungsschaltung, enthaltend:

einen Eingangsanschluß;

einen Ausgangsanschluß;

eine Verstärkereinrichtung mit regelbarer Verstärkung mit einem Signaleingang, der mit dem Eingangsanschluß verbunden ist, einem Regeleingang und einem Ausgang; und

eine automatische Verstärkungsregelungseinrichtung mit einem Eingang, der mit dem Ausgang der Verstärkereinrichtung mit regelbarer Verstärkung verbunden ist und mit einem Ausgang, der mit dem Regeleingang der Verstärkereinrichtung mit regelbarer Verstärkung verbunden ist,

dadurch gekennzeichnet, daß die automatische Verstärkungsregelungsschaltung weiterhin eine Teilereinrichtung enthält, die einen ersten Signaleingang hat, der mit dem Ausgang der Verstärkereinrichtung mit regelbarer Verstärkung verbunden ist, einen Teilsignaleingang hat, der mit dem Eingang der automatischen Verstärkungsregelungseinrichtung verbunden ist, und einen Ausgang hat, der mit dem Ausgangsanschluß der Schaltung verbunden ist, wodurch das Signal, das an dem Ausgang der Teilereinrichtung erzeugt wird, im wesentlichen unabhängig von dem Signalpegel ist, der an dem Ausgang der Verstärkereinrichtung mit regelbarer Verstärkung erzeugt wird.

2. Automatische Verstärkungsregelungsschaltung nach Anspruch 1, bei der die Schaltung

weiterhin eine Multipliziereinrichtung enthält, die erste und zweite Eingänge hat, die jeweils mit dem Ausgang der Verstärkereinrichtung mit regelbarer Verstärkung und mit einem Ausgang verbunden sind, der mit dem Eingang der automatischen Verstärkungsregelungseinrichtung verbunden ist, und bei der die Teilereinrichtung einen zweiten Signaleingang hat, der mit dem Ausgang der Verstärkereinrichtung mit regelbarer Verstärkung verbunden ist und eine Einrichtung enthält, um die Signale an ihren ersten und zweiten Signaleingängen zu multiplizieren.

3. Automatische Verstärkungsregelungsschaltung nach Anspruch 2, bei der eine Phasenschieberfiltereinrichtung in dem Signalweg zu dem ersten Signaleingang der Teilereinrichtung vorgesehen ist, so daß die Schaltung frequenzdiskriminierend ist, und wobei eine Tiefpaßfiltereinrichtung in dem Signalweg zu dem Teilsignaleingang der Teilereinrichtung angeordnet ist, wobei die Verzögerungen, die von den zwei Filtereinrichtungen erzeugt werden, so angepaßt sind, daß sie Verzögerungsdifferenzeffekte am Ausgang der Teilereinrichtung minimieren.

4. Automatische Verstärkungsregelungsschaltung nach einem der vorhergehenden Ansprüche, bei der die Teilereinrichtung enthält:

erste und zweite Transistoren, die jeweils Basis-, Kollektor- und Emittierelektroden haben;

dritte und vierte Transistoren, die jeweils Basis-, Kollektor- und Emittierelektroden haben; und

einen ersten Widerstand, der zwischen die Emittierelektroden der ersten und zweiten Transistoren geschaltet ist,

wobei die Emittierelektroden der ersten und zweiten Transistoren jeweils mit den Kollektorelektroden der dritten und vierten Transistoren verbunden sind,

die Emittierelektroden der dritten und vierten Transistoren mit Erde verbunden sind und die Kollektorelektroden der ersten und zweiten Transistoren dazu eingerichtet sind, mit einer Bezugspotentialquelle verbunden zu werden, wodurch die Basiselktroden der ersten und zweiten Transistoren den Differenzsignaleingang des Teilers bilden, die Basen der dritten und vierten Elektroden den Teileringang des Teilers bilden und der Ausgang des Teilers mit den Kollektorelektroden der ersten und zweiten Transistoren verbunden ist.

5. Integrierte Schaltung, die eine automatische Verstärkungsregelungsschaltung nach einem der vorhergehenden Ansprüche enthält.

6. Secam-Fernsehempfängerschaltung, die eine automatische Verstärkungsregelungsschaltung nach einem der Ansprüche 1 bis 4 enthält.

Revendications

1. Circuit à commande automatique de gain, comprenant:

un noeud d'entrée;

un noeud de sortie;

un moyen amplificateur de gain ajustable ayant



une entrée de signal i est connectée au noeud d'entrée, une entrée de commande et une entrée de sortie; et

un moyen de commande automatique de gain ayant une entrée couplée à la sortie du moyen amplificateur de gain ajustable et une sortie connectée à l'entrée de commande du moyen amplificateur de gain ajustable,

caractérisé en ce que le circuit à commande automatique de gain comprend en outre un moyen diviseur possédant une première entrée de signal qui est couplée à la sortie du moyen amplificateur de gain ajustable, une entrée de signal de division qui est couplée à l'entrée du moyen de commande automatique de gain et une sortie qui est connectée au noeud de sortie du circuit, de sorte que le signal produit à la sortie du moyen diviseur est sensiblement indépendant du niveau de signal produit sur la sortie du moyen amplificateur de gain ajustable.

2. Circuit à commande automatique de gain selon la revendication 1, où le circuit comprend en outre un moyen multiplicateur possédant une première et une deuxième entrée qui sont chacune connectées à la sortie du moyen amplificateur de gain ajustable et une sortie connectée à l'entrée du moyen de commande automatique de gain, et le moyen diviseur possède une deuxième entrée de signal connectée à la sortie du moyen amplificateur de gain ajustable et comporte un moyen servant à multiplier le signal présent sur ses première et deuxième entrées de signal.

3. Circuit à commande automatique de gain selon la revendication 2, où un moyen de filtrage à déphasage est prévu dans le trajet de signal allant à la première entrée de signal du moyen diviseur de sorte que le circuit effectue une discrimination de fréquence, et un moyen de filtrage passe-bas est prévu dans le trajet de

signal allant à l'entrée de signal de division du moyen diviseur, les retards produits par les deux moyens de filtrage étant adaptés de façon à minimiser les effets de différence de retard à la sortie du moyen diviseur.

4. Circuit à commande automatique de gain selon l'une quelconque des revendications précédentes, où le moyen diviseur comprend:

un premier et un deuxième transistor ayant chacun des électrodes de base, de collecteur et d'émetteur;

un troisième et un quatrième transistor ayant chacun des électrodes de base, de collecteur et d'émetteur; et

une première résistance couplée entre les électrodes d'émetteur des premier et deuxième transistors,

les électrodes d'émetteur des premier et deuxième transistors étant respectivement couplées aux électrodes de collecteur des troisième et quatrième transistors,

les électrodes d'émetteur des troisième et quatrième transistors étant couplées à la terre et les électrodes de collecteur des premier et deuxième transistors étant destinées à être couplées à une source de potentiel de référence, si bien que les électrodes de base des premier et deuxième transistors forment l'entrée de signal différentiel du diviseur, les bases des troisième et quatrième électrodes forment l'entrée de division du diviseur, et la sortie du diviseur est couplée aux électrodes de collecteur des premier et deuxième transistors.

5. Circuit intégré incorporant un circuit à commande automatique de gain selon l'une quelconque des revendications précédentes.

6. Circuit récepteur de télévision SECAM comportant un circuit à commande automatique de gain selon l'une quelconque des revendications 1 à 4.



* C L M S *