

SELF-INJECTION OPTICAL TRANSCEIVER MODULE AND WAVELENGTH DIVISION MULTIPLEXING PASSIVE OPTICAL NETWORK SYSTEM

FIELD OF THE INVENTION

5 The present invention relates to the field of communications technologies, and in particular, to a self-injection optical transceiver module and a wavelength division multiplexing passive optical network (Wavelength Division Multiplexing Passive Optical Network, WDM-PON) system based on the transceiver.

BACKGROUND OF THE INVENTION

10 As high-bandwidth fiber-optical communications technologies become more and more mature, and the application cost declines year by year, fiber access networks gradually become more competitive for next-generation broadband access networks. Among fiber access networks, passive optical networks (PONs) are especially competitive. Generally, a specific structure of a passive optical network system may be referred to FIG. 1, the passive optical network system includes an
15 OLT (Optical Line Terminal, optical line terminal) located at a central office, an ODN (Optical Distribution Network, optical distribution network) for branching/coupling or multiplexing/demultiplexing, and multiple ONUs (Optical Network Unit, optical network unit) located at user ends. The PONs may be categorized into different types according to different implementations, where WDM-PON systems using the WDM technology gain much attention
20 owing to advantages such as large bandwidth capacity, and information security of quasi-point-to-point communication. However, the WDM-PON has high cost compared with fiber access networks which use TDM (Time Division Multiplexing, TDM) technologies such as an EPON and a GPON, where the excessive cost of a light source is an important factor causing the excessive cost of the entire WDM-PON system.

25 The WDM-PON uses an AWG (Arrayed Waveguide Grating, arrayed waveguide grating) or a WGR (Waveguide Grating Router, waveguide grating router) at the user end, wavelengths on AWG ports or WGR ports connected to user end ONUs are different, and therefore, different ONUs need to use optical transceiver module with different wavelengths, which are named as colored optical

modules in the field of optical communications. The use of the colored optical modules in the ONUs may render the ONUs failed to be commonly used; and at the same time, bring difficulties to service distributions of an operator as well as a storage problems. In order to solve the problem of the colored ONUs, a proposal of WDM-PON colorless light source is raised in the industry, that is, an ONU transceiver module is independent of a wavelength, an emission wavelength may be automatically adapted to the wavelength of a connected AWG or WGR port, so that the ONU transceiver module can achieve plug-and-play on any AWG or WGR port.

In order to achieve the colorless ONU transceiver module of the WDM-PON, multiple solutions are proposed in the industry, including a self-seeding fiber laser. Referring to FIG. 2, a schematic diagram of a WDM-PON system using a self-seeding laser is illustrated. In the WDM-PON system, after a multi-longitudinal-mode optical signal emitted by a self-injection locking laser of a user end ONU is filtered by an AWG at a remote node (Remote Node, RN), only an optical signal of a corresponding wavelength may permeate the RN-AWG and enter a partial reflection mirror (Partial Reflection Mirror, PRM) disposed at a trunk fiber. Due to the partial reflection mirror, a part of light is reflected back and re-injected into the self-injection locking laser. A gain cavity of the self-injection locking laser amplifies the light reflected back again and then transmits the amplified light, and such round-trip oscillation is performed for multiple times. Accordingly, the self-injection locking laser and the partial reflection mirror cooperatively form an external cavity self-seeding laser, and a laser resonance oscillation cavity is formed in between and outputs a stable optical signal. After uplink data of the ONT being modulated to the optical signal, the uplink data of the ONU may further pass through the trunk fiber, and be demultiplexed by an AWG at a central office (Central Office, CO) and then output to a corresponding receiver (Rx) of an OLT. Similarly, a downlink optical signal emitted by the OLT is demultiplexed by the RN-AWG, and then output to a receiver of a corresponding ONU.

Although the foregoing solution may achieve the colorless optical transceiver, the AWG needs to undertake functions of intra-cavity filtering for a transmitting end and demultiplexing for a receiving end at the same time. As for the transmitting end, each channel of the AWG is used as an intra-cavity filter of the self-seeding laser, which requires that a filtering curve of the AWG channel has narrow bandwidth and has a maximum transmissivity at a central wavelength of the channel. As for the receiving end, the AWG functions as demultiplexing, which requires that the AWG channel has wide bandwidth and a transmission curve is flat in the channel. Due to the two contradictive requirements, the optical transceiver and the WDM-PON system that are based on the self-seeding laser have limited performances, and fail to meet the demand in practical application.

SUMMARY OF THE INVENTION

Embodiments of the present invention provide a self-injection optical transceiver module and a WDM-PON system based on the optical transceiver module, so as to solve the problem of poor performance in the existing techniques.

5 A self-injection optical transceiver mod includes a gain medium, a photoelectric converter, at least one arrayed waveguide grating AWG, and a partial reflection mirror, where the at least one AWG includes two common ports and a plurality of branch ports. One of the common ports functions as a signal sending port, and the other one of the common ports functions as a signal receiving port. Bandwidth of the signal sending port is less than that of the signal receiving port.

10 The gain medium and the photoelectric converter are connected to one of the branch ports of the AWG. The AWG and the partial reflection mirror are configured to cooperatively perform wavelength self-injection locking on an optical signal provided by the gain medium, and output the optical signal through the signal sending port. In addition, the AWG is further configured to demultiplex an optical signal received by the signal receiving port to a corresponding branch port.

15 A wavelength division multiplexing passive optical network system includes a self-injection optical transceiver module at a central office and a self-injection optical transceiver module at a user end, where the self-injection optical transceiver module at the central office and the self-injection optical transceiver module at the user end each include the above-mentioned self-injection optical transceiver module.

20 A wavelength division multiplexing passive optical network system includes an optical line terminal located at a central office and a plurality of optical network units located at a user end, where the optical line terminal is connected to the optical network units through fibers. The optical line terminal includes a plurality of self-injection optical transceiver modules at the central office, where the self-injection optical transceiver modules at the central office share a common arrayed

25 waveguide grating AWG at the central office. The AWG at the central office includes two common ports and a plurality of branch ports. Each self-injection optical transceiver module at the central office is correspondingly connected to one of the branch ports of the AWG at the central office respectively. One of the common ports of the AWG at the central office functions as a signal sending port at the central office, and the other one of the common ports of the AWG at the central office

30 functions as a signal receiving port at the central office. Bandwidth of the signal sending port at the central office is less than that of the signal receiving port at the central office.

It may be known from the foregoing technical solutions that the AWG of the self-injection optical transceiver module provided in embodiments of the present invention has two common ports,

that is, the signal sending port and the signal receiving port, and the bandwidth of the signal sending port is less than that of the signal receiving port, so that the AWG may use different common ports respectively in sending and receiving an optical signal. As the bandwidth of the signal sending port is narrow, a transmission peak of the signal sending port is identical to a central wavelength of an AWG channel, thereby effectively improving the performance of signal transmission. Channel bandwidth corresponding to the signal receiving port is wide, which may ensure that the quality of a signal received after demultiplexing is good. Therefore, compared with the prior art, the performance of the self-injection optical transceiver module and the WDM-PON system provided in embodiments of the present invention is improved.

BRIEF DESCRIPTION OF THE DRAWINGS

To illustrate the technical solutions according to the embodiments of the present invention or in the prior art more clearly, the accompanying drawings for describing the embodiments or the prior art are introduced briefly in the following. Apparently, the accompanying drawings in the following description are some embodiments of the present invention, and persons skilled in the art may derive other drawings from the accompanying drawings without creative efforts.

FIG. 1 is a schematic structural diagram of a passive optical network system;

FIG. 2 is a schematic structural diagram of a WDM-PON system;

FIG. 3 is a schematic structural diagram of a self-injection optical transceiver module according to an embodiment of the present invention;

FIG. 4 is a schematic structural diagram of a WDM-PON system according to an embodiment of the present invention;

FIG. 5 is a schematic structural diagram of a WDM-PON system according to another embodiment of the present invention;

FIG. 6 is a schematic structural diagram of a WDM-PON system according to yet another embodiment of the present invention;

FIG. 7 is a schematic structural diagram of a WDM-PON system according to yet another embodiment of the present invention; and

FIG. 8 is a schematic structural diagram of a WDM-PON system according to yet another embodiment of the present invention.

DETAILED DESCRIPTION OF THE EMBODIMENTS

The technical solution of the present invention is clearly and completely described in the following with reference to the accompanying drawings. It is obvious that the embodiments to be described are a part rather than all of the embodiments of the present invention. All other
5 embodiments obtained by persons skilled in the art based on the embodiments of the present invention without creative efforts shall fall within the protection scope of the present invention.

As described above, in a WDM-PON system shown in FIG. 2, an AWG undertakes the functions of forming an intra-cavity filter for a transmitting end and a demultiplexer for a receiving end. Since the two functions have contradictive requirements on bandwidth, for the applicability to
10 sending and receiving an optical signal at the same time, in the industry, a compromise should be made when selecting a bandwidth of a common port of the AWG, which causes poor performance of an optical transceiver module and a WDM-PON system based on a self-seeding laser at present.

In order to solve the problem of poor performance of the WDM-PON system in the prior art, an embodiment of the present invention provides a self-injection optical transceiver module, where the
15 optical transceiver module may include a transmitter and a receiver.

Referring to FIG. 3, the transmitter of the optical transceiver module includes a gain medium 11, an AWG 2, and a partial reflection mirror 12. The AWG 2 includes a branch port 22 connected to the gain medium 11, and a signal sending port 13 connected to the partial reflection mirror 12, where a wavelength channel of the branch port 22 is corresponding to a working wavelength of the
20 transmitter, and the signal sending port 13 is configured to send an optical signal provided by the gain medium 11 to a trunk fiber 4. The receiver of the optical transceiver module includes a photoelectric converter 21 and an AWG 2. The AWG 2 is connected to the photoelectric converter 21 through the branch port 22; and the AWG 2 may be further disposed with a signal receiving port 23 configured to receive the optical signal from the trunk fiber 4.

25 In the embodiment, the transmitter and the receiver may share the AWG 2, for example, the AWG 2 may function as a filter of the transmitter in one aspect, configured to limit a wavelength of the optical signal transmitted by the transmitter to the working wavelength of the optical transceiver module, and may function as a demultiplexer of the receiver in another aspect, configured to demultiplex the optical signal received from the trunk fiber 4 to the corresponding branch port 22,
30 so that the optical signal is received by the photoelectric converter 21.

In a specific embodiment, the optical transceiver module may further include a circulator 1. The signal sending port 13 and the signal receiving port 23 of the AWG 2 may be connected to the trunk fiber 4 through the circulator 1. Moreover, the partial reflection mirror 12 may be disposed

between the signal sending port 13 and the circulator 1. The circulator 1 may provide the optical signal from the signal sending port 13 to the trunk fiber 4, and provide the optical signal from the trunk fiber 4 to the signal receiving port 23. In other alternative embodiments, the circulator may be replaced by a wavelength division multiplexer.

Furthermore, bandwidth of the signal sending port 13 is less than that of the signal receiving port 23, for example, 3dB bandwidth of the signal sending port 13 may be relatively narrow, so as to improve the filtering function for the transmitter of the optical transceiver module, and 3dB bandwidth of the signal receiving port 23 may be relatively wide, so as to improve the demultiplexing function for the receiver of the optical transceiver module.

Specifically, taking an optical transceiver module of an OLT disposed at a central office of a WDM-PON system as an example, the self-injection optical transceiver module may send a downlink optical signal to a user end ONU through the trunk fiber 4 connected to the self-injection optical transceiver module, and receive an uplink optical signal from the user end ONU. In an embodiment of the present invention, two types of common ports are disposed in the AWG 2 of the self-injection optical transceiver module, namely, the signal sending port 13 and the signal receiving port 23. The signal sending port 13 is configured to send the downlink optical signal, and the signal receiving port 23 is configured to receive the uplink optical signal. As the signal sending port 13 and a corresponding branch port of the AWG 2 cooperatively form an intra-cavity filter of a self-injection laser, in order to ensure a relatively narrow spectrum of the downlink optical signal transmitted by the a self-injection optical transceiver module at the central office to improve the quality of the signal, in the embodiment of the present invention, the signal sending port 13 may be designed such that 3dB bandwidth of the signal sending port 13 is relative narrow and the signal sending port 13 have a maximum transmissivity at the central wavelength of the channel. Specifically, the signal sending port 13 may be a Gaussian-type port having narrow 3dB bandwidth.

For the signal receiving port 23 configured to receive the uplink optical signal, in the embodiment of the present invention, the signal receiving port 23 may be designed such that 3dB bandwidth of the signal receiving port 23 is relatively wide, that is, the pass band wavelength of the signal receiving port 23 has a small transmissivity variation in a wide range, so that the self-injection optical transceiver module has a good receiving performance when receiving the uplink optical signal. Specifically, the signal receiving port 23 may be a flat-type port having wide 3dB bandwidth. It should be understood that, the "wide 3dB bandwidth" and the "narrow 3dB bandwidth" are relative terms, and specific bandwidth may be configured according to the number of the wavelength channels of the AWG 2. In order to ensure the performance of the optical transceiver module, in the embodiment of the present invention, the 3dB bandwidth of the signal

sending port 13 is at least less than the 3dB bandwidth of the signal receiving port 23.

For better understanding of the embodiment of the present invention, an operation of the optical transceiver module is introduced briefly in the following.

Specifically, in an embodiment of the present invention, a transmitter may include the gain medium 11, the AWG 2, and the partial reflection mirror 12. A branch port 22 connected to the gain medium 11 and a signal sending port 13 connected to the partial reflection mirror 12 are disposed in the AWG 2. The signal sending port 13 is further connected to a circulator 1 or a wavelength division multiplexer, and the circulator 1 or the wavelength division multiplexer is further connected to a trunk fiber 4. In this way, when the self-injection optical transceiver module sends a downlink optical signal, the gain medium 11 is stimulated and starts to emits an ASE (Amplified Spontaneous Emission, amplified spontaneous emission) optical signal. After the ASE optical signal passes through a wavelength channel of the AWG 2, optical signals beyond the corresponding wavelength channel are filtered out or lost, and therefore, only an optical signal with wavelength within a pass band range determined by the branch port 22 and the signal sending port 13 of the AWG 2 can pass through the AWG 2. Then, the optical signal is transmitted to the partial reflection mirror 12 through the signal sending port 13, where a part of the optical signal is reflected back by the partial reflection mirror 12, injected into the gain medium 11, and amplified again. Such a round trip is performed for multiple times. In this way, the round trips of the optical signal between the gain medium 11 and the partial reflection mirror 12 for multiple times result in resonance oscillation amplification, and finally enable the optical signal generated by the transmitter to work at a transmission peak wavelength determined by the signal sending port 13 and the branch port 22, thereby forming a downlink optical signal that may be sent through the signal sending port 13. After passing through the signal sending port 13, the downlink optical signal is further sent to the trunk fiber 4 through the circulator 1 or the wavelength division multiplexer, and is transmitted by the trunk fiber 4 to a corresponding ONU at the user end.

In the embodiment of the present invention, the signal sending port 13 functions to form an intra-cavity filter in the transmitter, therefore, bandwidth design and optimization of the signal sending port 13 may be performed separately to enable the desired bandwidth to be relatively narrow, and a transmission peak is identical to a central wavelength of the corresponding AWG channel, thereby effectively improving the performance of signal transmission.

Subsequently, in an embodiment of the present invention, a receiver may include the photoelectric converter 21 and an AWG 2. The branch port 22 connected to the photoelectric converter 21 and a signal receiving port 23 are further disposed in the AWG 2. The signal receiving port 23 is connected to a circulator 1 or a wavelength division multiplexer, and the circulator 1 or

the wavelength division multiplexer is further connected to the trunk fiber 4. In this way, an uplink optical signal is transmitted from the trunk fiber 4 to the circulator 1 or the wavelength division multiplexer, and then is further conducted to the signal receiving port 23 by the circulator 1 or the wavelength division multiplexer. The AWG 2 demultiplexes the uplink optical signal to the branch port 22 corresponding to the receiver, and the optical signal is transmitted to the photoelectric converter 21 in the receiver through the branch port 22 of the AWG 2. Specifically, in the embodiment of the present invention, the photoelectric converter 21 may be a photoelectric diode.

For example, when the self-injection optical transceiver module receives the uplink optical signal, the uplink optical signal transmitted by the trunk fiber 4 may pass through the circulator 1, enter the flat-type signal receiving port 23 with 3dB bandwidth that is relatively wide, be demultiplexed by the AWG 2 to the corresponding branch port 22, and then provided by a wavelength division multiplexer to the photoelectric converter 21. As in the embodiment of the present invention, the signal receiving port 23 is configured separately and independent from the signal sending port 12, the channel bandwidth corresponding to the signal receiving port 23 may be designed to be relatively wide and a transmission curve of the signal receiving port 23 is flat, so that the quality of the signal received after demultiplexing is good.

In the embodiment of the present invention, two types of common ports are configured in the AWG in the self-injection optical transceiver module, namely, a signal sending port with 3dB bandwidth that is relatively narrow and a signal receiving port with 3dB bandwidth that is relatively wide, so that the AWG may use different common ports for optical signal transmission and reception respectively. Moreover, the 3dB bandwidth of the signal sending port is designed to be relatively narrow, and the 3dB bandwidth of the signal receiving port is designed to be relatively wide, the quality of the optical signal reception and transmission of the self-injection optical transceiver module is ensured. Accordingly, in the embodiment of the present invention, bandwidth optimization designs can be separately performed on the signal receiving port and the signal sending port of the self-injection optical transceiver module, which significantly improves the performance of the self-injection optical transceiver module.

Preferably, in an embodiment of the present invention, the gain medium in the receiver may specifically include an IL FP-LD (Injection-Locked Fabry-Perot Laser Diode, injection-locked Fabry-Perot laser diode) or an RSOA (Reflective Semiconductor Optical Amplifier, reflective semiconductor optical amplifier).

In an embodiment of the present invention, the partial reflection mirror may further be a Faraday rotator mirror. Specifically, a 45° one-way Faraday cup may be added before the partial reflection mirror, to form a faraday rotator mirror (FRM, Faraday Rotator Mirror). In this manner,

after the ASE optical signal transmitted by the transmitter is reflected by the Faraday rotator mirror, a polarization direction of the optical signal is rotated by 90° . In this way, a TE mode of the optical signal emitted from a laser transceiver becomes a TM mode after being reflected back by the FRM, and the emitted TM mode of the optical signal becomes the TE mode after being reflected back by the TE. Therefore, the correlation of polarization gain in a self-injection laser transceiver is diminished, which improves the ability of the self-injection fiber laser transceiver in resisting random polarization interference in the embodiment of the present invention.

The self-injection optical transceiver module provided in the embodiment of the present invention may be further applied in user end ONUs in the WDM-PON system, and a specific structure of the self-injection optical transceiver module is similar to that of the self-injection optical transceiver module at the central office. The difference only lies in that, for the self-injection optical transceiver module in the user end ONU, the receiver is configured to receive the downlink optical signal, and the transmitter is configured to send the uplink optical signal. Furthermore, the gain medium of the self-injection optical transceiver module at the central office has a gain amplification function for a downlink wave band, and the gain medium of the self-injection optical transceiver module at the user end has a gain amplification function for an uplink wave band. The wavelength division multiplexer has the functions of multiplexing the uplink wave band and demultiplexing the downlink wave band.

In the embodiment shown in FIG. 3, in order to ensure the 3dB bandwidth of the signal sending port 13 less than the 3dB bandwidth of the signal receiving port 23, specifically, a waveguide at a signal sending end of the AWG 2 is designed to have an inverted conical structure, that is, a waveguide close to a Roland circle of the AWG 2 is narrow, and a waveguide at an output end is wide, so that the 3dB bandwidth of the signal sending port is narrow. In addition, in the embodiment shown in FIG. 3, the bandwidth of the signal sending port 13 less than that of the signal receiving port 23 may be achieved through some other manners, for example, the 3dB bandwidth of the signal receiving port may be increased by disposing a conical waveguide structure, a Mach-Zehnder interferometer structure, or a multimode coupler at the signal receiving port 23, or by cascading multiple AWGs.

In addition, in the embodiment of the present invention, the signal sending port and the signal receiving port having different bandwidths may also be achieved by use of two AWGs with different 3dB bandwidth. That is, the two AWGs with different 3dB bandwidth respectively function as a signal receiving AWG and a signal sending AWG. Specifically, a common port of the AWG with 3dB bandwidth that is relatively narrow functions as the signal receiving port, and the AWG is referred to as the signal receiving AWG. A common port of the AWG with 3dB bandwidth that is

relatively wide functions as the signal sending port, and the AWG is referred to as the signal sending AWG.

In addition, in an embodiment of the present invention, the signal sending port and the signal receiving port having different bandwidths may also be achieved by use of two AWGs with the same 3dB bandwidth and one periodic filter with narrow bandwidth. Specifically, in the two AWGs with the same 3dB bandwidth, a common port of a signal sending AWG may be connected to the periodic filter with narrow 3dB bandwidth, for example, a Fabry-Perot etalon, so that the optical signal sent by the signal sending AWG has 3dB bandwidth that is relatively narrow. The other AWG may function as a signal receiving AWG, and 3dB bandwidth of the signal receiving AWG is greater than that of the signal sending AWG.

Based on the optical transceiver module, an embodiment of the present invention further provides a WDM-PON system. The WDM-PON system may include self-injection optical transceiver modules at a central office and self-injection optical transceiver modules at user ends. The optical transceiver modules provided in the above embodiments may be used as the self-injection optical transceiver modules at the central office and the self-injection optical transceiver modules at the user ends. The self-injection optical transceiver modules at the central office may be disposed at an OLT, and may function as optical transceiver modules of the OLT. The self-injection optical transceiver modules at the user ends may be separately disposed at user ends, and function as optical transceiver modules of the ONUs. Each optical transceiver module of the OLT corresponds to the optical transceiver module of a respective ONU, and the operation wavelength of the optical transceiver module of the OLT is the same as that of the corresponding one of the optical transceiver module of the ONU.

Specifically, referring to FIG. 4, the self-injection optical transceiver module at the central office may include an AWG 102 and a partial reflection mirror 112. The AWG 102 includes multiple branch ports 122 and two common ports, the two common ports are respectively configured as a signal receiving port 123 and a signal sending port 113. Each of the branch port 122 is connected to a gain medium 111 and a photoelectric converter 121 through a wavelength division multiplexer. The signal sending port 113 has a Gaussian-type or semi-Gaussian-type filtering curve, and has 3dB bandwidth that is relatively narrow. The signal receiving port 123 has a flat-type filtering curve, and has 3dB bandwidth that is relatively wide.

The self-injection optical transceiver module at the user end includes an AWG 202 and a partial reflection mirror 212. The AWG 202 includes multiple branch ports and two common ports, and the two common ports are respectively configured as a signal sending port 213 and a signal receiving port 223. Each of the branch ports 222 is connected to a gain medium 211 and a photoelectric

converter 221 through a wavelength division multiplexer. The signal sending port 213 has a Gaussian-type or semi-Gaussian-type filtering curve, and has 3dB bandwidth that is relatively narrow. The signal receiving port 223 has a flat filtering curve, and has 3dB bandwidth that is relatively wide.

5 In the self-injection optical transceiver module at the central office shown in FIG. 4, each of the branch ports 122 is connected to a gain medium 111 and a photoelectric converter 121 through a wavelength division multiplexer, that is, the branch ports of the AWG 102 are correspondingly connected to the gain mediums 111 and the photoelectric converters 121 one by one. In other words, a first gain medium and a first photoelectric converter are connected to a first branch port, a second
10 gain medium and a second photoelectric converter are connected to a second branch port, and the connection of other branch ports may be deduced by analogy. A location of the signal sending port 113 of the self-injection optical transceiver module 100 at the central office on a Roland circle of the AWG 102 is corresponding to a location of the signal receiving port 223 of the self-injection optical transceiver module 200 at the user end on the Roland circle of the AWG 202. A location of the
15 signal receiving port 123 of the self-injection optical transceiver module 100 at the central office on the Roland circle of the AWG 102 is corresponding to a location of the signal sending port 213 of the self-injection optical transceiver module 200 at the user end on the Roland circle of the AWG 202.

In this way, a downlink optical signal generated by the self-injection optical transceiver module
20 100 at the central office is sent from the signal sending port 113 to a trunk fiber via the partial reflection mirror 112, enters the signal receiving port 223 of the self-injection optical transceiver module 200 at the user end, and is demultiplexed by the AWG 202 to a corresponding branch port 222, and then is provided to and received by a photoelectric converter 221 of the corresponding optical transceiver module at the user end. Similarly, at the user end, the partial reflection mirror
25 212 is configured in the self-injection optical transceiver module 200 at the user end. An uplink optical signal generated by the self-injection optical transceiver module at the user end is transmitted from the signal sending port 213 to the trunk fiber via the partial reflection mirror 212, enters the signal receiving port 123 of the self-injection optical transceiver module 100 at the central office, and is demultiplexed by the AWG 102 to a corresponding branch port 122, and then is
30 provided to and received by a photoelectric converter 121 of the corresponding optical transceiver module at the central office.

FIG. 5 is a schematic structural diagram of another embodiment of a WDM-PON system based on a self-injection optical transceiver module of the present invention. In this embodiment, an AWG employed in the self-injection optical transceiver module is a non-wavelength 0-hop AWG. It is

assumed that both a self-injection optical transceiver module at a central office and a self-injection optical transceiver module at a user end include 32 receivers and transmitters, a location of a signal sending port 313 of an AWG 302 on a Roland circle of the AWG 302 corresponds to a location of a signal sending port 413 of an AWG 402 on a Roland circle of the AWG 402, and a location of a signal receiving port 323 on a Roland circle of the AWG 302 corresponds to a signal sending port 423 on the Roland circle of the AWG 402. In an embodiment, the signal receiving port 313 and the signal sending port 312 of the AWG 302 are spaced by a wavelength channel of the AWG 302, and the signal receiving port 413 and the signal sending port 412 of the AWG 402 are also spaced by a channel of the AWG 402; locations of the second to 33rd branch ports of the AWG 302 on the Roland circle of the AWG 302 are respectively corresponding to the first to 32nd branch ports of the AWG 402 on the Roland circle of the AWG 402. The first port of the AWG 302 is a previous port adjacent to the second port, and the 34th port is a next port adjacent to the 33rd port. Thus, when a downlink optical signal sent by a gain medium in the self-injection optical transceiver module at the central office, where the gain medium is connected to a k^{th} branch port ($k=1, 2, \dots, 32$) of the AWG 302 passes through the AWG 402 of the optical transceiver module at the user end, the downlink optical signal may not be demultiplexed to a k^{th} branch port (that is, a k^{th} user) of the AWG 402. In view of this, in this embodiment, to enable the downlink optical signal transmitted by the k^{th} gain medium in the self-injection optical transceiver module at the central office to enter the k^{th} branch port of the AWG 402 of the self-injection optical transceiver module at the user end, that is, to enable the downlink optical signal to be received by the k^{th} photoelectric converter in the self-injection optical transceiver module at the user end, fiber connections of the AWG 302 of the self-injection optical transceiver module at the central office can be modified. As for a specific fiber connection manner, reference may be made to FIG. 5.

In practice, a possible value of channel spacing between the signal receiving port and the signal sending port of the AWG 302 may be 1, 2, 3, or the like. In designing a manner of connection between the gain medium and the branch port of the AGW 302 in the self-injection optical transceiver module at the central office, it is assumed that the channel spacing between the signal receiving port and the signal sending port of the AWG302 is m . In this case, the k^{th} gain medium in the self-injection optical transceiver module at the central office only needs to be connected to the $(k+2m)^{\text{th}}$ branch port in the AWG 302. In order to ensure that the an uplink optical signal sent by the k^{th} user of the self-injection optical transceiver module at the user end can enter the k^{th} receiver at the central office, it is required that the location of the m^{th} port of the AWG 302 of the self-injection optical transceiver module at the central office on the Roland circle of the AWG 302 is corresponding to the location of the first port of the AWG 402 in the self-injection optical

transceiver module at the user end on the Roland circle of the AWG 402.

In this embodiment, with the modification of the connection between the gain medium and the branch port of the AWG 302 in the optical transceiver module at the central office, the branch ports of the AWG 402 and the gain media in the optical transceiver module at the user end only need to be
5 connected one by one correspondingly, as shown in FIG. 5.

Specifically, the downlink optical signal from the self-injection optical transceiver module at the central office enters the trunk fiber through the transmitting port 312 of the AWG 302, and then enters the signal receiving port 423 of the AWG 402 in the self-injection optical transceiver module at the user end. As in the embodiment of the present invention, the AWG employed in the
10 self-injection optical transceiver module is a non-wavelength 0-hop AWG, that is, the channel of the signal sending port of the AWG 302 is different from that of the signal receiving port of the AWG 402. Specifically, for example, in this embodiment, the channel spacing is 1; in this case, a downlink optical signal sent by the $(k+2)$ th branch port of the AWG 302 may be demultiplexed to the k th branch port of the AWG 402 in the self-injection optical transceiver module at the user end.

Therefore, in order to ensure that the self-injection optical transceiver module in the embodiment of the present invention can work normally, the k th gain medium in the self-injection optical transceiver module at the central office is further connected to the $(k+2)$ th branch port of the AWG 302. For example, the first gain medium of the self-injection optical transceiver module at the central office is connected to the third branch port of the AWG 302, the second gain medium is
20 connected to the fourth branch port of the AWG 302, and connection of the remaining gain media and branch ports of the AWG 302 can be deduced by analogy. With this configuration, the self-injection optical transceiver module at the user end may use a 32-channel AWG to form 32 receivers and transmitters, however, in the self-injection optical transceiver module at the central office, as the 32nd gain medium needs to be connected to the 34th branch port of the AWG 302, the
25 AWG 302 of the self-injection optical transceiver module at the central office needs to be disposed with at least 34 branch ports. In practice, a 40-channel AWG may be used.

Referring to FIG. 6, in another embodiment of the present invention, an AWG used by a WDM-PON system may also be a wavelength 0-hop AWG.

Specifically, the embodiment shown in FIG. 6 is similar to the embodiment corresponding to
30 FIG. 5. The difference lies in that the AWG of a self-injection optical transceiver module in the embodiment shown in FIG. 6 is wavelength 0-hop AWG. Assuming the wavelength 0-hop AWG has N branch ports in total, as the ports of the wavelength 0-hop AWG has a circulating characteristic, that is, a k^{th} wavelength and a $(k+N)^{\text{th}}$ wavelength may occur at the same port, a wavelength next to that of an N^{th} channel of the AWG may reoccur at a first channel, and then the circulation continues.

When both a self-injection optical transceiver module at a central office and a self-injection optical transceiver module at a user end employ the same wavelength 0-hop AWG, and two common ports of the AWG are two adjacent channels, in order to send a downlink optical signal provided by a first gain medium in the self-injection optical transceiver module at the central office to a photoelectric converter connected to a first branch port in an AWG 602, a first gain medium 511 in the self-injection optical transceiver module at the central office may be connected to a second branch port in an AWG 502. Connection manners of other gain mediums are similar to that of the first gain medium, except the last gain medium of the self-injection optical transceiver module at the central office. Specifically, a second gain medium needs to be connected to a third branch port in the AWG 502, and the rest may be deduced by analogy. The last gain medium in the self-injection optical transceiver module at the central office needs to be connected to the first branch port in the AWG 502. In this way, the photoelectric converters 621 in the self-injection optical transceiver modules at the user end respectively correspond to the gain mediums 511 of self-injection optical fiber laser transceivers 500 at the central office.

A second photoelectric converter in the self-injection optical transceiver module at the central office is connected to the first branch port of the AWG 502, so as to receive an uplink optical signal sent by the first gain medium in the self-injection optical transceiver module at the user end. Connection manners of other photoelectric converters are similar to that of the second photoelectric converter, except the first photoelectric converter of the self-injection optical transceiver module at the central office. Specifically, a third photoelectric converter of the self-injection optical transceiver module at the central office needs to be connected to the second branch port in the AWG 502, and the rest may be deduced by analogy. The first photoelectric converter in the self-injection optical transceiver module at the central office needs to be connected to a last branch port in the AWG 502.

In another embodiment of the present invention, two AWGs with different 3dB bandwidth may be combined, where a common port of the AWG with 3dB bandwidth that is relatively narrow serves as a signal sending port, and a common port with 3dB bandwidth that is relatively wide serves as a signal receiving port. In this way, a partial reflector is connected to the signal sending port of the AWG with 3dB bandwidth that is relatively narrow, and a received signal is connected to the signal receiving port of the AWG with 3dB bandwidth that is relatively wide.

Specifically, referring to FIG. 7, a self-injection optical transceiver module at a central office may include an AWG 31 and an AWG 41, and the two AWGs have different 3dB bandwidth respectively. A self-injection optical transceiver module at a user end may use an AWG 51 having two common ports with different 3dB bandwidth.

The AWG 31 includes a signal sending port 33 with 3dB bandwidth that is relatively narrow,

and the signal sending port 33 is configured to send a downlink optical signal. The AWG 41 includes a signal receiving port 43 with 3dB bandwidth that is relatively wide, and the signal receiving port 43 is configured to receive an uplink optical signal. The AWG 51 includes a signal sending port 53 with 3dB bandwidth that is relatively narrow and a signal receiving port 56 with 3dB bandwidth that is relatively wide.

In the embodiment of the present invention, specific operation of the self-injection optical transceiver module at the central office and the self-injection optical transceiver module at the user end is as follow. A first gain medium 32 of the self-injection optical transceiver module at the central office sends, through a first branch port 34, a downlink optical signal along the signal sending port 33 to a trunk fiber. After the signal receiving port 56 of the AWG 51 receives the downlink optical signal, the downlink optical signal enters a first branch port 54 of the self-injection optical transceiver module at the user end, and then enters a first photoelectric converter 52.

A first gain medium 52 of the self-injection optical transceiver module at the user end sends, through the first branch port 54, an uplink optical signal along the signal sending port 53 to the trunk fiber. After the signal receiving port 43 of the AWG 41 receives the downlink optical signal, the signal enters a first branch port 44 of the AWG 41, and then enters the first photoelectric converter 42.

In addition, in another embodiment of the present invention, the self-injection optical transceiver module at the central office and the self-injection optical transceiver module at the user end may be set to be formed by two AWGs. Specifically, referring to FIG. 8, a self-injection optical transceiver module at a central office may include an AWG 61 and an AWG 71, and the two AWGs have different 3dB bandwidth respectively. A self-injection optical transceiver module at a user end may include an AWG 81 and an AWG 91, and the two AWGs have different 3dB bandwidth respectively.

The AWG 61 includes a signal sending port 63 with 3dB bandwidth that is relatively narrow, and the signal sending port 63 is configured to send a downlink optical signal. The AWG 71 includes a signal receiving port 73 with 3dB bandwidth that is relatively wide, and the signal receiving port 73 is configured to receive an uplink optical signal. The AWG 81 includes a signal sending port 83 with 3dB bandwidth that is relatively narrow, and the signal sending port 83 is configured to send an uplink optical signal. The AWG 91 includes a signal receiving port 93 with 3dB bandwidth that is relatively wide, and the signal receiving port 93 is configured to receive a downlink optical signal.

In the embodiment of the present invention, a specific operation of the self-injection optical transceiver module at the central office and the self-injection optical transceiver module at the user

end is as follows. A first gain medium 62 of the self-injection optical transceiver module at the central office sends, through a first branch port 64, a downlink optical signal along the signal sending port 63 to a trunk fiber. After the signal receiving port 93 of the AWG 91 receives the downlink optical signal, the downlink optical signal enters a first branch port 94 of the AWG 91, and then enters a first photoelectric converter 92.

A first gain medium 82 of the self-injection optical transceiver module at the user end sends, through a first branch port 84 of the AWG 81, an uplink optical signal along the signal sending port 83 to the trunk fiber. After the signal receiving port 73 of the AWG 71 receives the downlink optical signal, the downlink optical signal enters a first branch port 74 of the AWG 71, and then enters a first photoelectric converter 72 of the self-injection optical transceiver module at the central office.

In all the embodiments according to the present invention, an uplink wave band and a downlink wave band may be an FSR (Free Spectral Range, free spectral range) wave band adjacent to the AWG, or an FSR wave band not adjacent to the AWG.

Embodiments in this specification are described in a progressive way. Each embodiment highlights the difference from other embodiments, and for the same or similar parts of the embodiments, reference may be made to each other. The description on the apparatus disclosed in the embodiments is simple because the apparatus is corresponding to the method disclosed in the embodiments, and reference may be made to the description in the method part.

The descriptions on the disclosed embodiments enable persons skilled in the art to implement or practice the present invention. Modifications made to the embodiments are apparent to persons skilled in the art, and the general principles defined here may be implemented in other embodiments without departing from the spirit and scope of the present invention. Therefore, the present invention is not limited to the embodiments exemplified here, but complies within a broadest scope consistent with the principle and novel characteristics disclosed here.

CLAIMS

What is claimed is:

1. A self-injection optical transceiver module, comprising a gain medium, a photoelectric converter, at least one arrayed waveguide grating AWG, and a partial reflection mirror,

5 wherein the at least one AWG comprises two common ports and a plurality of branch ports, one of the common ports functions as a signal sending port, the other one of the common ports functions as a signal receiving port, bandwidth of the signal sending port is less than that of the signal receiving port;

10 the gain medium and the photoelectric converter are connected to one of the branch ports of the AWG, the AWG and the partial reflection mirror are configured to cooperatively perform wavelength self-injection locking on an optical signal provided by the gain medium, and output the optical signal through the signal sending port; wherein the AWG is further configured to demultiplex an optical signal received by the signal receiving port to a corresponding branch port.

15 2. The self-injection optical transceiver module according to claim 1, further comprising a circulator or a wavelength division multiplexer, wherein the signal receiving port and the signal sending port of the AWG are coupled to a trunk fiber through the circulator or the wavelength division multiplexer, and the partial reflection mirror is connected between the circulator or the wavelength division multiplexer and the signal sending port.

20 3. The self-injection optical transceiver module according to claim 1, wherein the signal sending port is a Gaussian-type port, and the signal receiving port is a flat-type port.

4. The self-injection optical transceiver module according to claim 3, wherein a transmission peak of the signal sending port is identical to a central wavelength of a corresponding channel of the AWG, and a transmission curve of the signal receiving port is a flat-type transmission curve.

25 5. The self-injection optical transceiver module according to claim 1, wherein the signal receiving port comprises a Mach-Zehnder interferometer structure, a conical waveguide structure or a multimode coupler; and the signal sending port comprises an inverted conical waveguide structure.

6. The self-injection optical transceiver module according to claim 1, wherein the partial reflection mirror comprise a Faraday rotator mirror.

30 7. The self-injection optical transceiver module according to any one of claims 1 to 6, wherein the at least one AWG comprises a signal sending AWG and a signal receiving AWG; a common port of the signal receiving AWG functions as the signal receiving port, and a common port of the signal

sending AWG functions as the signal sending port.

8. The self-injection optical transceiver module according to claim 7, further comprising a periodic filter, wherein the periodic filter is connected to the common port of the signal sending AWG, and configured to reduce bandwidth of the common port of the signal sending AWG, so that
5 the bandwidth of the common port of the signal sending AWG is less than bandwidth of the common port of the signal receiving AWG.

9. A wavelength division multiplexing passive optical network system, comprising a self-injection optical transceiver module at a central office and a self-injection optical transceiver module at a user end, wherein the self-injection optical transceiver module at the central office and
10 the self-injection optical transceiver module at the user end comprise the self-injection optical transceiver module according to any one of claims 1 to 8.

10. A wavelength division multiplexing passive optical network system, comprising an optical line terminal located at a central office and a plurality of optical network units located at user ends, wherein the optical line terminal is connected to the optical network units through fibers; and
15 the optical line terminal comprises a plurality of self-injection optical transceiver modules at the central office, wherein the self-injection optical transceiver modules at the central office share an arrayed waveguide grating AWG at the central office, the AWG at the central office comprises two common ports and a plurality of branch ports, each self-injection optical transceiver module at the central office is correspondingly connected to one of the branch ports of the AWG at the central
20 office respectively, one of the common ports of the AWG at the central office functions as a signal sending port at the central office, and the other one of the common ports of the AWG at the central office functions as a signal receiving port at the central office, and bandwidth of the signal sending port at the central office is less than that of the signal sending port at the central office.

11. The wavelength division multiplexing passive optical network system according to claim
25 10, wherein each self-injection optical transceiver module at the central office comprises a gain medium, a partial reflection mirror, and a photoelectric converter, the gain medium and the photoelectric converter are connected to a corresponding one of the branch ports of the AWG at the central office, the AWG and the partial reflection mirror at the central office are configured to cooperatively perform wavelength self-injection locking on an optical signal provided by the gain
30 medium, and send the optical signal to a corresponding optical network unit through the signal sending port; wherein the AWG at the central office is further configured to demultiplex an optical signal received by the signal receiving port to a corresponding branch port.

12. The wavelength division multiplexing passive optical network system according to claim 10 or 11, wherein each optical network unit comprises a self-injection optical transceiver module at

the user end, the self-injection optical transceiver modules at the user end share an AWG at the user end, the AWG at the user end comprises two common ports and a plurality of branch ports, each self-injection optical transceiver module at the user end is correspondingly connected to one of the branch ports of the AWG at the user end respectively, one of the common ports of the AWG at the user end functions as a signal sending port at the user end, and the other one of the common ports of the AWG at the user end functions as a signal receiving port at the user end, and bandwidth of the signal sending port at the user end is less than that of the signal receiving port at the user end.