

Device for encoding/decoding n-bit source words into corresponding m-bit channel words, and vice versa.

The invention relates to a device for encoding a stream of databits of a binary source signal into a stream of databits of a binary channel signal, wherein the bitstream of the source signal is divided into n-bit source words, which device comprises converting means adapted to convert said source words into corresponding m-bit channel words, the converting means being adapted to convert a block of p consecutive n-bit source words into a corresponding block of p consecutive m-bit channel words, such that the conversion for each block of p consecutive n-bit source words is substantially parity preserving, where n, m and p are integers, $m > n \geq 1$, $p \geq 1$, and where p can vary. The invention also relates to a recording device comprising the encoding device, for recording the channel signal on a record carrier, to the record carrier itself, to an encoding method, and to a device for decoding a stream of data bits of a binary channel signal obtained by means of the encoding device, so as to obtain a stream of databits of a binary source signal.

15

An encoding device mentioned in the foregoing is known from USP 5,477,222 (PHN 14448). The document discloses a device for encoding a stream of databits of a binary source signal into a stream of databits of a binary channel signal, satisfying a (1,8) runlength constraint. That means that, in a serial datastream of the channel signal at minimum one 'zero' and at maximum eight 'zeroes' are present between two consecutive 'ones' in the channel signal. It should be noted in this respect that normally an additional precoding step, such as a 1T precoding, is applied to the (1,8) constrained sequence, resulting in a runlength limited sequence with minimum runlength 2 and maximum runlength 9.

25

The known conversion is parity preserving. 'Parity preserving' means that the parity of the n-bit source words to be converted equal the parity (after modulo-2 addition) of the corresponding m-bit channel words in which they are converted. As a result, the n-to-m conversion device as claimed does not influence the polarity of the signal.

As the conversion is parity preserving, an efficient DC control can be

applied, such as by inserting DC control bits in the datastream of the source words.

The invention has for its object to provide an improved device for
5 encoding n-bit source words into corresponding m-bit channel words.

The device in accordance with the invention is characterized in that the converting means is adapted to convert the 8-bit bit sequence '00010001' in the bitstream of the binary source signal into the 12-bit bit sequence '100010010010' of the binary channel signal.

10 The device in accordance with the invention is also characterized by one of the claims 2, 5, 6, 7 or 8.

The invention is based on the recognition that, encoding in accordance with the known encoding device relatively long sequences comprising only the minimum transition runlength may occur, leading to a deterioration of the bit detection in a bitdetector
15 in a receiver, following transmission and subsequent decoding of the channel signal in the receiver. In a channel signal satisfying a specific runlength constraint, such as (1,7) or (1,8), this means that relatively long sequences '.....0101010101.....' occur, resulting in relatively long sequences '.....001100110011.....' in the sequence after 1T precoding.

The devices in accordance with the invention restrict the lengths of those
20 sequences, so that an improved bitdetection in a receiver can be realized.

The encoding device in accordance with the invention can be used in combination with a bit-adder unit in which one bit is added to codewords of a certain length of the source signal. The signal obtained can be applied to the encoding device of the present invention. The channel signal of the encoding device is applied to a 1T-precoder. The
25 purpose of the bit-adder unit is to add a '0'- or a '1'-bit to the consecutive code words included in the input signal of the converter, so as to obtain a precoder output signal which is DC free, or includes a tracking pilot signal having a certain frequency. The precoder output signal is recorded on a record carrier. The adding of a '0'-bit in the input signal of the converter results in the polarity of the output signal of the 1T precoder remaining the same.
30 The adding of a '1'-bit results in a polarity inversion in the output signal of the 1T precoder. The converter therefore influences the output signal of the 1T precoder such that the running digital sum value of the output signal of the 1T precoder can be controlled so as to have a desired pattern as a function of time.

The invention will be further described in the following figure description,
in which

figure 1 shows a first embodiment of the encoding device,
figure 2 shows a second embodiment of the encoding device,
5 figure 3 shows a third embodiment of the encoding device,
figure 4 shows a fourth embodiment of the encoding device,
figure 5 shows the application of the device in an arrangement for
inserting one bit on equidistant positions in the serial source signal,
figure 6 shows a first embodiment of the decoding device, and
10 figure 7 shows a second embodiment of the decoding device.

Figure 1 shows an encoding device that is capable of converting 2-bit
source words into 3-bit channel words. The device described here is in fact the device also
15 disclosed in USP 5,477,222, with further modifications to realize the objectives of a
minimization of the repeated minimum transition runlength.

The device has an input terminal 1, for receiving a stream of databits of a
binary source signal S. The terminal 1 is coupled to an input of a shift register 2 having
eight cells X_1 to X_8 , in the present example, so as to receive eight consecutive source bits of
20 the source signal S. The shift register 2 functions as a serial-parallel converter. The outputs
of the cells are coupled to corresponding inputs i_1 to i_8 , respectively, of a logic circuit LC,
for supplying the logic values $(x_1, \dots, x_8)$ of the source bits present in the cells. The logic
circuit LC forms part of the conversion means CM.

The device further includes a second shift register 4 having twelve cells
25 Y_1 to Y_{12} . The logic circuit LC has twelve outputs o_1 to o_{12} . Those outputs of the logic
circuit LC are coupled to corresponding inputs of the twelve cells Y_1 to Y_{12} , respectively, of
the shift register 4. An output 6 of the shift register 4 is coupled to an output terminal 8. The
shift register 4 functions as a parallel-serial converter, so as to obtain the binary channel
signal C.

30 Further, a detector unit 10 is available for detecting specific sequences in
the serial datastream of the source signal S. To that purpose, the outputs of the eight cells X_1
to X_8 of the shift register 2 are coupled to corresponding inputs, denoted 12, of the detector
unit 10. In the present embodiment, the detector unit 10 has three outputs, denoted o_1 , o_2
and o_3 , for generating a first, second and third control signal, respectively. Those outputs are

coupled to corresponding control signal inputs c_1 , c_2 and c_3 , respectively, of the logic circuit LC.

The functioning of the logic circuit LC in response to the control signals applied to its inputs c_1 , c_2 and c_3 , is as follows.

- 5 The logic circuit LC is capable of converting 2-bit source words SW into 3-bit channel words, such that the conversion for each 2-bit source word is parity preserving. That means that the number of 'ones' in the source word to be converted equals the number of 'ones' in the corresponding channel word, a modulo-2 addition on the 'ones' in the channel word being carried out. Or, otherwise said: if the number of 'ones' in the source
- 10 word is even, the number of 'ones' in the channel word will be even. And: if the number of 'ones' in the source word is odd, the number of 'ones' in the channel word will be odd.

As an example, the converting means LC is adapted to convert the 2-bit source words SW into 3-bit channel words CW in accordance with the following table:

TABLE I

15

source word (x_1, x_2)		channel word (y_1, y_2, y_3)	
SW ₁	00	CW ₁	101
SW ₂	01	CW ₂	100
SW ₃	10	CW ₃	001
SW ₄	11	CW ₄	000

20

It should be noted here, that the first bit in the source word is applied first to the shift register 2 and that the first bit in the channel word is supplied first from the output 6 of the shift register 4.

- 25 It should be further noted here, that the logic circuit LC converts 2-bit source words stored in the cells X_1, X_2 into 3-bit channel words and stores those channel words in the cells Y_1, Y_2, Y_3 of the shift register 4, in response to an absence of any control signal at the control signal inputs c_1, c_2 and c_3 . Each conversion in this way, is followed by a shift over two positions to the left in the shift register 2, and a shift over three positions to the left in the shift register 4. The shift over two positions in the shift register 2 is required
- 30 so as to make the shift register 2, and thus the converter, ready for a subsequent conversion. The shift over three positions in the shift register 4 is required in order to output the 3-bit channel word generated.

The device of figure 1 can be used to generate a channel signal C in the

form of a (d,k) sequence satisfying the $d=1$ constraint. That means that at least one 'zero' is present between two subsequent 'ones' in the serial datastream of the channel signal. That is, that a concatenation of two or more 'ones' in the channel signal is prohibited.

It might occur that the unmodified conversion, such as by means of the device of figure 1, of combinations of two subsequent 2-bit source words might violate the $d=1$ constraint. Those combinations are the combinations; '00 00', which by unmodified conversion would lead to the two 3-bit channel words '101 101'; '00 01', which by unmodified conversion would lead to the two 3-bit channel words '101 100'; '10 00', which by unmodified conversion would lead to the two 3-bit channel words '001 101' and '10 01', which by unmodified conversion would lead to the two 3-bit channel words '001 100'.

The occurrence of such combinations should be detected so that a modified encoding of blocks of two 2-bit source words into blocks of two 3-bit channel words can take place. Therefore, the device of figure 1 is, in addition to the 'normal' encoding of 2-bit source words into 3-bit channel words, capable of detecting the above identified combinations, and is capable of realizing a modified encoding, such that the $d=1$ constraint in the channel signal is still satisfied.

Because of the fact that the outputs of the cells X_1 to X_4 of the shift register 2 are coupled to corresponding inputs of the detector unit 10, this detector unit 10 is capable of detecting the position in the serial bitstream of the source signal where unmodified encoding of single 2-bit source words in the bitstream into corresponding single 3-bit channel words would lead to a violation of the $d=1$ constraint in the channel signal C, and are adapted to supply a control signal at its output o_1 in response to such detection.

More specifically, the detector unit 10 detects whether the cells X_1 to X_4 comprise one of the 4-bit sequences that are given in table II, and generates a first control signal at its output o_1 .

As soon as the detector circuit 10 detects a combination of two 2-bit source words present in the four cell positions x_1, x_2, x_3, x_4 , which combination equals one of the combinations given in the left hand column of table 11, the logic circuit LC converts the combination in accordance with the modified coding as given in table II:

TABLE II

source words	unmodified coding	modified coding
00 00	101 101	100 010
00 01	101 100	101 010
10 00	001 101	000 010
10 01	001 100	001 010

As can be seen from the table, unmodified conversion of the single two 2-bit source words leads to a violation of the $d=1$ constraint, as two 'ones' occur at the boundary between the two channel words obtained. The logic circuit LC is therefore adapted to convert in a modified coding mode, the blocks of two 2-bit source words given in the left column of the above table into the blocks of two 3-bit channel words as given in the right column in the above table II. As can be seen, no violation of the $d=1$ constraint occurs anymore. Moreover, the modified encoding in the same way is parity preserving. Further, one of the two 2-bit source words, which is in the above table the second one, is encoded into a 3-bit channel word which is unequal to one of the four channel words of table I. The reason for this is that on the receiver side, a detection of this 3-bit channel word not belonging to the set of four 3-bit channel words of the table I is possible, so that a corresponding decoding, which is the inverse of the encoding as defined with reference to table II, can be realized.

The block of two 3-bit channel words obtained by means of the encoding in conformity with table II, is supplied by the logic circuit LC to its outputs o_1 to o_6 , which channel words are supplied to the six cells Y_1 to Y_6 of the shift register 4.

It will further be clear that, a conversion of two 2-bit source words into two 3-bit channel words by the converter unit LC, is followed by a shift over four positions to the left in the shift register 2 and a shift over six positions to the left in the shift register 4. The shift over four positions in the shift register 2 is required so as to make the shift register 2, and thus the converter, ready for a subsequent conversion. The shift over six positions in the shift register 4 is required in order to output the two 3-bit channel words generated.

The k -constraint in a (d,k) sequence means that a concatenation of at most k 'zeroes' between two subsequent 'ones' in the channel signal are allowed.

It might occur that the unmodified conversion of three subsequent 2-bit

source

words might violate the k-constraint.

As an example: the sequence of source words '11 11 11' would by unmodified conversion lead to the three 3-bit channel words '000 000 000'. If a (d,k) sequence should be obtained where k equals 6, 7 or 8, such combination of three 3-bit channel words should not occur.

Another example is the sequence of source words '11 11 10' which by unmodified conversion would lead to the three 3-bit channel words '000 000 001'. This combination of three 3-bit channel words does not satisfy a k=6 or k=7 constraint.

Moreover, this combination of three 3-bit channel words can follow a previous channel word that ends with a '0', so that it might lead to a violation of a k=8 constraint. Further, the combination ends with a '1', so that it might lead to a violation of the d=1 constraint, if the combination is followed by a 3-bit channel word that starts with a '1'. An equivalent reasoning is valid for the sequence of source words '01 11 11'.

A further example is the sequence of source words '01 11 10' which by unmodified conversion would lead to the three 3-bit channel words '100 000 001'. This combination can, in the same way as given above, lead to a violation of the d=1 constraint.

The occurrence of such combinations should be detected so that a modified encoding can take place. Therefore, the device of figure 1 is, in addition to the 'normal' encoding of 2-bit source words into 3-bit channel words, as well as the modified encoding in accordance with table II, capable of detecting the above identified combinations, and is capable of realizing a modified encoding, such that the k-constraint in the channel signal is still satisfied.

Because of the fact that the outputs of the cells X_1 to X_6 of the shift register 2 are coupled to corresponding inputs of the detector unit 10, this detector unit 10 is capable of detecting the position in the serial bitstream of the source signal where unmodified encoding would lead to a violation of the k-constraint in the channel signal C, and are adapted to supply a control signal at its output o_2 in response to such detection.

More specifically, the detector unit 10 detects whether the cells X_1 to X_6 comprise one of the 6-bit sequences that are given in table III, and generates a second control signal at its output o_2 .

As soon as the detector circuit 10 detects a combination of three 2-bit source words present in the six cell positions $x_1, x_2, x_3, x_4, x_5, x_6$, which combination equals one of the combinations given in the left hand column of table III, the logic circuit LC

converts the combination in accordance with the modified coding as given in table III:

TABLE III

source words	unmodified coding	modified coding
11 11 11	000 000 000	000 010 010
11 11 10	000 000 001	001 010 010
01 11 10	100 000 001	101 010 010
01 11 11	100 000 000	100 010 010

The logic circuit LC converts in the second modification of the coding mode, the blocks of three 2-bit source words given in the left column of the above table III into the blocks of three 3-bit channel words as given in the right column in the above table. By realizing the modified encoding as per table III, a channel signal has been obtained which satisfies the $k=8$ constraint. Moreover, the modified encoding in the same way is parity preserving. This means in the present situation that, if the number of 'ones' in the combination of three 2-bit source words is odd (even), the number of 'ones' in the combination of the three 3-bit channel words obtained is odd (even). Further, two of the three 2-bit source words, which is in the above table the second one and the third one, is encoded into a 3-bit channel word which is unequal to one of the four channel words of table I. The reason for this is that on the receiver side, a detection of these two consecutive 3-bit channel words not belonging to the set of four 3-bit channel words of the table I is possible, so that a corresponding decoding, which is the inverse of the encoding as defined with reference to table III, can be realized.

The block of three 3-bit channel words obtained by means of the encoding in conformity with table III, is supplied by the logic circuit LC to its outputs o_1 to o_9 , which channel words are supplied to the nine cells Y_1 to Y_9 of the shift register 4.

It will further be clear that, a conversion of three 2-bit source words into three 3-bit channel words by the converter unit LC, is followed by a shift over six positions to the left in the shift register 2 and a shift over nine positions to the left in the shift register 4. The shift over six positions in the shift register 2 is required so as to make the shift register 2, and thus the converter, ready for a subsequent conversion. The shift over nine positions in the shift register 4 is required in order to output the three 3-bit channel words

generated.

A further requirement for encoding the source signal is that the repeated minimum transition runlength in the channel signal should be limited. The repeated minimum transition runlength is defined as the length of the sequence of subsequent transitions between '0' and '1', or: a sequence '.....01010101010...', in the case where the d-constraint equals 1. As an example, the bit sequence '00 01 00 01' results, after modified conversion using table II, in the bit sequence '101 010 101 010'. In the same way, the bit sequence '10 01 00 01' results, after modified conversion using table II, in the bit sequence '001 010 101 010'. Such sequences deteriorate the bit detection in a receiver.

10 Restriction of the length of 01-sequences is thus required.

Because of the fact that the outputs of the cells X_1 to X_8 of the shift register 2 are coupled to corresponding inputs of the detector unit 10, this detector unit 10 is capable of detecting the position in the serial bitstream of the source signal where unmodified encoding would lead to a violation of the requirement that repeated minimum transition runlength is limited and is adapted to supply a control signal at its output o_3 in response to such detection.

More specifically, the detector unit 10 detects whether the cells X_1 to X_8 comprise one of the 8-bit sequences that are given in table IV, and generates a third control signal at its output o_3 .

20 As soon as the detector circuit 10 detects a combination of four 2-bit source words present in the eight cell positions $x_1, x_2, x_3, x_4, x_5, x_6, x_7, x_8$, which combination equals one of the combinations given in the left hand column of table IV, the logic circuit LC converts the combination in accordance with the modified coding as given in table IV into a 12-bit bitsequence as given in the right column of this table IV.

25

TABLE IV

8-bit bitsequence in source signal	12-bit bitsequence in channel signal
00 01 00 01	100 010 010 010
10 01 00 01	000 010 010 010

30

The modified conversion as per table IV is again parity preserving.

It should be noted that the bitstream of the channel words is in NRZI

(non-return to zero-inverse) notation, which means that a 'one' results in a transition in the write current for recording the channel signal on a magnetic record carrier.

In the foregoing, the situations where a modified encoding is required are detected by the detector unit 10 from the source words. It should however be noted that

5 detection could be carried out on the channel words generated. Reference is made in this respect to figure 2b in USP 5,477,222.

Figure 2 shows another embodiment of the encoding device in which detection of the situations where a modified encoding is required is done based on the channel words generated by an unmodified coding as per table I.

10 The device of figure 2 includes a detector 10' having 12 inputs for receiving the four subsequent 3-bit channel words obtained by means of an unmodified encoding as per table I in the circuit LC'. The detector 10' detects whether the two subsequent 3-bit channel words at the outputs o_1 to o_6 of the circuit LC', obtained using the unmodified coding, equal one of the four 6-bit sequences given in the middle column under
15 'unmodified coding' of table II. If so, the detector 10' issues a switching signal at its output 12 and an address signal AD at its output 12'. The switching signal is applied to a switching signal input 45 of the shift register 4'. The address signal AD is applied to an address signal input 46 of a ROM 47. The detector 10' generates one of four possible address signals AD1 to AD4, in response to the detection of a corresponding one of the four 6-bit sequences in
20 the middle column of table II. As an example, the address signal AD1 is generated when the detector 10' detects the sequence '101101' and generates the address signal AD4 upon detection of the 6-bit sequence '001100'. The ROM 47 has the 6-bit sequences shown in the right column of table II stored. Upon the receipt of the address signal AD1, the ROM supplies the 6-bit sequence '100 010' at its outputs o_1 to o_6 , and upon the receipt of the
25 address signal AD2, the ROM supplies the 6-bit sequence '101 010' at those outputs. Upon the receipt of the address signal AD3, the ROM supplies the 6-bit sequence '000 010' at those outputs, and upon the receipt of the address signal AD4, the ROM supplies the 6-bit sequence '001 010' at those outputs. Each memory location of the shift register 4' has now two inputs, one of them being coupled with a corresponding output of the logic circuit LC',
30 the other being coupled to a corresponding output of the ROM 47. In response to the switching signal applied to the input 45, the shift register accepts the information supplied to its lower inputs and shifts its contents over six positions to the left. As a result, a modified 6-bit sequence is supplied by the shift register 4' to the output 8.

The detector 10' also detects whether the three subsequent 3-bit channel

words at the outputs o_1 to o_9 of the circuit LC', obtained using the unmodified coding, equal one of the four 9-bit sequences given in the middle column under 'unmodified coding' of table III. If so, the detector 10' issues a switching signal at its output 12 and an address signal AD at its output 12'. The detector 10' generates one of four possible address signals

5 AD5 to AD8, in response to the detection of a corresponding one of the four 9-bit sequences in the middle column of table III. As an example, the address signal AD5 is generated when the detector 10' detects the sequence '000 000 000' and generates the address signal AD8 upon detection of the 9-bit sequence '100 000 000'. The ROM 47 has the 9-bit sequences shown in the right column of table III stored. Upon the receipt of the address signal AD5,

10 the ROM supplies the 9-bit sequence '000 010 010' at its outputs o_1 to o_9 , and upon the receipt of the address signal AD6, the ROM supplies the 9-bit sequence '001 010 010' at those outputs. Upon the receipt of the address signal AD7, the ROM supplies the 9-bit sequence '101 010 010' at those outputs, and upon the receipt of the address signal AD8, the ROM supplies the 9-bit sequence '100 010 010' at those outputs.

15 In response to the switching signal applied to the input 45, the shift register accepts the information supplied to its lower inputs and shifts its contents over nine positions to the left. As a result, a modified 9-bit sequence is supplied by the shift register 4' to the output 8.

The detector 10' further detects whether the four subsequent 3-bit channel

20 words at the outputs o_1 to o_{12} of the circuit LC', obtained using the unmodified coding, equal one of the following two 12-bit sequences: '101 010 101 010' or '001 010 101 010'. If so, the detector 10' issues a switching signal at its output 12 and an address signal AD at its output 12'. The detector 10' generates one of two possible address signals AD9 and AD10, respectively, in response to the detection of a corresponding one of the two 12-bit sequences

25 given above. As an example, the address signal AD9 is generated when the detector 10' detects the sequence '101 010 101 010' and generates the address signal AD10 upon detection of the 12-bit sequence '001 010 010 101'. The ROM 47 has the 12-bit sequences shown in the right column of table IV stored. Upon the receipt of the address signal AD9, the ROM supplies the 12-bit sequence '100 010 010 010' at its outputs o_1 to o_{12} , and upon

30 the receipt of the address signal AD10, the ROM supplies the 12-bit sequence '000 010 010 010' at those outputs.

In response to the switching signal applied to the input 45, the shift register accepts the information supplied to its lower inputs and shifts its contents over twelve positions to the left. As a result, a modified 12-bit sequence is supplied by the shift

register 4' to the output 8.

In the normal situation, when none of the constraints is violated, unmodified conversion is carried out in accordance with table I, and the switching signal is absent so that the shift register accepts the bits supplied by the logic circuit LC' via the upper inputs of the shift register 4'.

It has been said previously that other conversion rules for converting single 2-bit source words into single 3-bit channel words are possible. Those conversion rules are given in the following three tables.

TABLE IV

source word (x_1, x_2)		channel word (y_1, y_2, y_3)	
SW ₁	00	CW ₁	101
SW ₂	01	CW ₂	001
SW ₃	10	CW ₃	100
SW ₄	11	CW ₄	000

TABLE V

source word (x_1, x_2)		channel word (y_1, y_2, y_3)	
SW ₁	00	CW ₁	000
SW ₂	01	CW ₂	100
SW ₃	10	CW ₃	001
SW ₄	11	CW ₄	101

TABLE VI

source word (x_1, x_2)		channel word (y_1, y_2, y_3)	
SW ₁	00	CW ₁	000
SW ₂	01	CW ₂	001
SW ₃	10	CW ₃	100
SW ₄	11	CW ₄	101

It is evident that extensions of those conversion rules for encoding blocks

of two or three 2-bit source words into blocks of two or three 3-bit channel words can be obtained using the teachings given above.

Figure 3 shows a modification of the device of figure 1. The device of figure 3 is capable of generating a channel signal with a lower k-constraint, more specifically a k-constraint $k=7$. The modification lies in the addition of the a further shift register 70 having three storage locations 70.1, 70.2 and 70.3, which has an input 72 coupled to the output 6 of the shift register 4, and outputs 74.1, 74.2 and 74.3, being the outputs of the storage locations 70.1, 70.2 and 70.3, respectively. Further, a detector 76 is present having inputs 78.1, 78.2 and 78.3, coupled to the outputs 74.1, 74.2 and 74.3, respectively, of the shift register 70, and having an output 82. The output 74.1 of the shift register 70 is also coupled to a control input c_5 of the conversion circuit LC_m , and the output 82 of the detector 76 is coupled to a control input c_4 of the conversion circuit LC_m . Further, the detector 10 in figure 1 is slightly modified into the detector 80 in figure 3.

As far as the conversion of single 2-bit source words into 3-bit channel words, the conversion of two 2-bit source words into two 3-bit channel words, and the conversion of three 2-bit source words into three 3-bit channel words is concerned, this conversion is the same as explained above with reference to the device of figure 1.

The modification lies specifically in the conversion of 8-bit bitsequences of a specific form occurring in the source signal. The detector 80 is, in addition to detecting the 4-bit bitsequences of table II and the 6-bit bitsequences of table III (as explained with reference to the embodiment of figure 1), capable of detecting 8-bit bitsequences given in the table VII that follows below. In response to such detection, the detector 80 generates a control signal at its output o_3 , which control signal is applied to the control input c_3 of the logic circuit LC_m .

The shift register 70 has the last three bits of the channel signal generated up to now stored in its storage locations 70.1, 70.2 and 70.3, where the storage location 70.1 has the last bit of the channel signal generated up to now stored in it. This last bit of the channel signal, which is either a '0' or a '1' bit, is used as a further control signal for the logic circuit LC_m , and is supplied to the logic circuit LC_m via its control input c_4 . Further, the detector 76 is adapted to generate a control signal at its output 82, when the shift register 70 has the 3-bit bitsequence '010' stored in its storage locations 70.1, 70.2 and 70.3. This control signal is supplied to the logic circuit LC_m via its control input c_5 .

In accordance with the table VII, the logic circuit LC_m converts the 8-bit bitsequence '00 01 00 01' into its corresponding 12-bit bitsequence '100 010 010 010', in

response to the control signal applied to its control input c_3 , and irrespective of the control signals appearing at its inputs c_4 and c_5 . Further, the logic circuit LC_m converts the 8-bit bitsequence '10 01 00 01' into the 12-bit bitsequence '100 000 010 010', in response to the control signal at its input c_5 being equal to '0', and converts the said 8-bit bitsequence into the 12-bit bitsequence '000 010 010 010', in response to the control signal being equal to '1'. When the 8-bit bitsequence '11 10 00 00' appears at the inputs i_1 to i_8 of the logic circuit, a control signal is generated by the detector 80 at its output o_3 . Further, when the contents of the shift register 70 equals the 3-bit bitsequence '010', a control signal is generated by the detector 76. In response to both control signals, the logic circuit LC_m converts this 8-bit bitsequence into the 12-bit bitsequence '000 001 010 010', as shown in table VII. When the 8-bit bitsequence '11 10 00 10' appears at the inputs i_1 to i_8 of the logic circuit, a control signal is generated by the detector 80 at its output o_3 . Further, when the contents of the shift register 70 equals the 3-bit bitsequence '010', a control signal is generated by the detector 76. In response to both control signals, the logic circuit LC_m converts this 8-bit bitsequence into the 12-bit bitsequence '100 001 010 010', as shown in table VII. When the 8-bit bitsequence '11 10 00 01' appears at the inputs i_1 to i_8 of the logic circuit, a control signal is generated by the detector 80 at its output o_3 . Further, when the contents of the shift register 70 equals the 3-bit bitsequence '010', a control signal is generated by the detector 76. In response to both control signals, the logic circuit LC_m converts this 8-bit bitsequence into the 12-bit bitsequence '001 010 010 010', as shown in table VII. When the 8-bit bitsequence '11 10 00 11' appears at the inputs i_1 to i_8 of the logic circuit, a control signal is generated by the detector 80 at its output o_3 . Further, when the contents of the shift register 70 equals the 3-bit bitsequence '010', a control signal is generated by the detector 76. In response to both control signals, the logic circuit LC_m converts this 8-bit bitsequence into the 12-bit bitsequence '101 010 010 010', as shown in table VII.

TABLE VII

	8-bit bitsequence in source signal	last bit(s) in channel signal	12-bit bitsequence in channel signal
	00 01 00 01	don't care	100 010 010 010
5	10 01 00 01	0	100 000 010 010
	10 01 00 01	1	000 010 010 010
	11 10 00 00	010	000 001 010 010
	11 10 00 10	010	100 001 010 010
	11 10 00 01	010	001 010 010 010
10	11 10 00 11	010	101 010 010 010

With this conversion, the channel signal satisfies $k=7$ and limits the repeated minimum transition runlength to 6.

Figure 4 shows a modification of the embodiment of figure 2, modified so as to enable the conversion in accordance with the table VII above. The embodiment of figure 2 is modified into the embodiment of figure 4 by adding the shift register 70 and the detector unit 76, which supply their control signals to control inputs c_4 and c_5 of the ROM 47'. No further description of the embodiment will be given, as with the above description of the embodiment of figure 2, with the explanation of the modified encoding of a number of 8-bit bitsequences in the source signal, it is clear for the skilled man to develop an enabling construction for the embodiment of figure 4, without employing any inventive activity.

As has been said previously, the devices described above are very suitable for including in the encoding arrangement where one bit is inserted after each q bits in a serial datastream in order to realize a polarity conversion, or not. Such an encoding arrangement is schematically shown in figure 5, where the encoder 40 is followed by the encoding device in accordance with the present invention 41, and a 1T-precoder 42, well known in the art. The output signal of the 1T-precoder 42 is applied to a control signal generator 43, which generates the control signal for the converter 40, so as to control whether a '0' or a '1' is inserted in the serial datastream applied to the converter 40. The encoding device 41 can be inserted between the converter 40 and the 1T-precoder 42 without any modification, as the encoder 41 does not influence the polarity of the signal generated by the converter 40. By means of the arrangement shown in figure 5 it is possible to embed a tracking tone of a certain frequency in the serial datastream, or keep the DC content of the

datastream to zero. Further, when the encoding device 41 is adapted to generate a (d,k) sequence as explained above, it causes the output signal of the arrangement of figure 4 to be a (d,k) RLL output signal. Embodiments of the converter 40 are given in Bell System Technical Journal, Vol 53, No. 6, pp. 1103-1106.

5 The output signal of the 1T precoder 42 is supplied to a write unit 21 for writing the signal in a track on a record carrier 23. The record carrier 23 can be a magnetic record carrier in longitudinal or disk form. The record carrier could also be an optical record carrier, such as an optical disk 23'. The write unit 21 comprises a write head 25, which is a magnetic write head, when recording the signal on a magnetic record carrier or an optical
10 write head, when recording the signal on an optical record carrier.

Figure 6 shows an embodiment of a decoding device for decoding the serial datastream obtained by the encoding device of figure 1 or 2, so as to obtain a binary source signal. The decoding device has an input terminal 50 for receiving the channel signal, which input terminal 50 is coupled to an input 56 of a shift register 51, comprising twelve
15 cells Y_1 to Y_{12} . The shift register 51 functions as a serial-parallel converter so that blocks of four 3-bit channel words are applied to inputs i_1 to i_{12} of a logic circuit 52. The logic circuit 52 comprises the four tables I, II, III and IV. Outputs o_1 to o_8 of the logic circuit 52 are coupled to inputs of cells X_1 to X_8 of a shift register 54, which has an output 57 coupled to an output terminal 55. A detector circuit 53 is present having inputs i_1 to i_9 , schematically
20 indicated by the reference number 60, coupled to outputs of cells Y_4 to Y_{12} respectively of the shift register 51, and outputs o_1 , o_2 and o_3 coupled to control inputs c_1 , c_2 and c_3 , respectively, of the logic circuit 52. The detector circuit 53 is capable of

- (a) detecting a '010 010 010' bit pattern in the cells Y_4 to Y_{12} of the shift register 51,
- (b) detecting a bit pattern '010 010' in the cells Y_4 to Y_9 of the shift register 51, whilst the
25 bits in the cells Y_{10} , Y_{11} and Y_{12} are unequal to '010', and
- (c) detecting a '010' bit pattern in the cells Y_4 , Y_5 and Y_6 , whilst the bits in the bitcells Y_7 , Y_8 and Y_9 are unequal to '010'.

Upon detection of the '010 010 010' bitpattern, the detector circuit 53 generates a control signal on its output o_1 , upon detection of the '010 010' bit pattern in the
30 cells Y_4 to Y_9 , the detector circuit 53 generates a control signal on its output o_2 , upon detection of the '010' pattern in the cells Y_4 to Y_6 , the detector circuit 53 generates a control signal at its output o_3 , whilst, when there is no '010' bit pattern in the cells Y_4 to Y_{12} , it generates no control signal on its outputs.

In the absence of the control signals, the logic circuit 52 converts the 3-bit

channel word stored in the cells Y_1 , Y_2 and Y_3 into its corresponding 2-bit source word, as per the conversion table I, and supplies the 2-bit source word to the cells X_1 and X_2 . In the presence of the control signal at the input c_3 , the logic circuit 52 converts the block of two 3-bit channel words stored in the cells Y_1 to Y_6 into a block of two 2-bit source words, as per the conversion table II, and supplies the two 2-bit source words to the cells X_1 to X_4 . In the presence of the control signal at the input c_2 , the logic circuit 52 converts the block of three 3-bit channel words stored in the cells Y_1 to Y_9 into a block of three 2-bit source words, as per the conversion table III, and supplies the three 2-bit source words to the cells X_1 to X_6 . In the presence of the control signal at the input c_1 , the logic circuit 52 converts the block of four 3-bit channel words stored in the cells Y_1 to Y_{12} into a block of four 2-bit source words, as per the conversion table IV, and supplies the four 2-bit source words to the cells X_1 to X_8 .

In this way, the serial datastream of the channel signal is converted into the serial datastream of the source signal.

The encoded information supplied to the input 50 could have been obtained from reproducing the information from a record carrier, such as a magnetic record carrier 23 or an optical record carrier 23'. The device in figure 6 thereto comprises a read unit 62 for reading the information from a track on the record carrier, where the unit 62 comprises a read head 64 for reading the information from said track.

Figure 7 shows an embodiment of the decoder for decoding the channel signal generated by the encoders of the figures 3 or 4. From the table VII, it is clear that the specific 12-bit bitsequences in the channel signal that should be decoded in accordance with the table VII cannot all be detected by the sequence '010 010 010'. Therefore, the detector 53' requires inputting of the 12-bit bitsequence in order to identify all the seven 12-bit bitsequences included in the table VII.

Whilst the invention has been described with reference to preferred embodiments thereof, it is to be understood that these are not limitative examples. Thus, various modifications may become apparent to those skilled in the art, without departing from the scope of the invention, as defined in the claims. As an example, the decoding device of figure 6 could be modified into a device in which the detector 53 detects the various modified decoding situations from the decoded information, instead of from the encoded information, as disclosed in figure 6.

Further, the invention lies in each and every novel feature or combination of features.

CLAIMS


1. A device for encoding a stream of databits of a binary source signal into a stream of databits of a binary channel signal, wherein the bitstream of the source signal is divided into n -bit source words, which device comprises converting means adapted to convert said source words into corresponding m -bit channel words, the converting means being
5 adapted to convert a block of p consecutive n -bit source words into a corresponding block of p consecutive m -bit channel words, such that the conversion for each block of p consecutive n -bit source words is substantially parity preserving, where n , m and p are integers, $m > n \geq 1$, $p \geq 1$, and where p can vary, characterized in that the converting means is adapted to convert the 8-bit bit sequence '00010001' in the bitstream of the binary source signal into the
10 12-bit bit sequence '100010010010' of the binary channel signal.
2. A device for encoding a stream of databits of a binary source signal into a stream of databits of a binary channel signal, wherein the bitstream of the source signal is divided into n -bit source words, which device comprises converting means adapted to convert said source words into corresponding m -bit channel words, the converting means being
15 adapted to convert a block of p consecutive n -bit source words into a corresponding block of p consecutive m -bit channel words, such that the conversion for each block of p consecutive n -bit source words is substantially parity preserving, where n , m and p are integers, $m > n \geq 1$, $p \geq 1$, and where p can vary, characterized in that the converting means is adapted to convert the 8-bit bit sequence '10010001' in the bitstream of the binary source signal into the
20 12-bit bit sequence '000010010010' of the binary channel signal.
3. A device as claimed in claim 2, characterized in that the converting means is adapted to convert the 8-bit bit sequence '10010001' in the bitstream of the binary source signal into the 12-bit bit sequence '000010010010' of the binary channel signal in the case that the last bit of the channel signal generated up to this bit sequence is a '1' bit.
- 25 4. A device as claimed in claim 3, characterized in that the converting means is adapted to convert the 8-bit bit sequence '10010001' in the bitstream of the binary source signal into the 12-bit bit sequence '100000010010' of the binary channel signal in the case that the last bit of the channel signal generated up to this bit sequence is a '0' bit.
5. A device for encoding a stream of databits of a binary source signal into a

stream of databits of a binary channel signal, wherein the bitstream of the source signal is divided into n -bit source words, which device comprises converting means adapted to convert said source words into corresponding m -bit channel words, the converting means being adapted to convert a block of p consecutive n -bit source words into a corresponding block of p consecutive m -bit channel words, such that the conversion for each block of p consecutive n -bit source words is substantially parity preserving, where n , m and p are integers, $m > n \geq 1$, $p \geq 1$, and where p can vary, characterized in that the converting means is adapted to convert the 8-bit bit sequence '11100000' in the bitstream of the binary source signal into the 12-bit bit sequence '000001010010' of the binary channel signal in the case that the last three bits of the channel signal generated up to this bit sequence is '010'.

6. A device for encoding a stream of databits of a binary source signal into a stream of databits of a binary channel signal, wherein the bitstream of the source signal is divided into n -bit source words, which device comprises converting means adapted to convert said source words into corresponding m -bit channel words, the converting means being adapted to convert a block of p consecutive n -bit source words into a corresponding block of p consecutive m -bit channel words, such that the conversion for each block of p consecutive n -bit source words is substantially parity preserving, where n , m and p are integers, $m > n \geq 1$, $p \geq 1$, and where p can vary, characterized in that the converting means is adapted to convert the 8-bit bit sequence '11100010' in the bitstream of the binary source signal into the 12-bit bit sequence '100001010010' of the binary channel signal in the case that the last three bits of the channel signal generated up to this bit sequence is '010'.

7. A device for encoding a stream of databits of a binary source signal into a stream of databits of a binary channel signal, wherein the bitstream of the source signal is divided into n -bit source words, which device comprises converting means adapted to convert said source words into corresponding m -bit channel words, the converting means being adapted to convert a block of p consecutive n -bit source words into a corresponding block of p consecutive m -bit channel words, such that the conversion for each block of p consecutive n -bit source words is substantially parity preserving, where n , m and p are integers, $m > n \geq 1$, $p \geq 1$, and where p can vary, characterized in that the converting means is adapted to convert the 8-bit bit sequence '11100001' in the bitstream of the binary source signal into the 12-bit bit sequence '001010010010' of the binary channel signal in the case that the last three bits of the channel signal generated up to this bit sequence is '010'.

8. A device for encoding a stream of databits of a binary source signal into a stream of databits of a binary channel signal, wherein the bitstream of the source signal is



divided into n -bit source words, which device comprises converting means adapted to convert said source words into corresponding m -bit channel words, the converting means being adapted to convert a block of p consecutive n -bit source words into a corresponding block of p consecutive m -bit channel words, such that the conversion for each block of p consecutive n -bit source words is substantially parity preserving, where n , m and p are integers, $m > n \geq 1$, $p \geq 1$, and where p can vary, characterized in that the converting means is adapted to convert the 8-bit bit sequence '11100011' in the bitstream of the binary source signal into the 12-bit bit sequence '101010010010' of the binary channel signal in the case that the last three bits of the channel signal generated up to this bit sequence is '010'.

9. A device as claimed in anyone of the preceding claims, characterized in that, $m=n+1$.

10. A device as claimed in claim 9, characterized in that, $n=2$.

11. Device as claimed in claim 10, characterized in that, the device is adapted to convert single source words into corresponding single channel words in accordance with

the following table:

source word		channel word	
SW ₁	00	CW ₁	101
SW ₂	01	CW ₂	100
SW ₃	10	CW ₃	001
SW ₄	11	CW ₄	000



12. A device as claimed in claim 10 or 11, wherein the converting means are adapted to convert 2-bit source words into corresponding 3-bit channel words, so as to obtain a channel signal in the form of a (d,k) sequence, where $d=1$, the device further comprising means for detecting the position in the bitstream of the source signal where encoding of single 2-bit source words into corresponding single channel words would lead to a violation of the d -constraint at the channel word boundaries and for supplying a control signal in response to said detection, characterized in that, in the absence of the control signal, the converting means are adapted to convert single 2-bit source words into corresponding single 3-bit channel words, such that the conversion for each 2-bit source word is parity preserving.

13. Device as claimed in claim 12, wherein, in the presence of the control signal, occurring during the conversion of two consecutive source words, the converting

means are adapted to convert a block of said two consecutive 2-bit source words into a block of two corresponding 3-bit channel words, such that one of the two source words in the block of source words is converted into a 3-bit channel word which is not identical to one of the four channel words CW_1 to CW_4 , in order to preserve the $d=1$ constraint, characterized in that, in the presence of said control signal, the converting means are further adapted to convert the block of said two subsequent 2-bit source words into a corresponding block of two subsequent 3-bit channel words, such that the conversion for said block of two subsequent 2-bit source words is parity preserving.

14. Device as claimed in claim 13, characterized in that, the converting means are adapted to convert the blocks of two consecutive 2-bit source words into the blocks of two consecutive 3-bit channel words in accordance with the coding given in the following table:

block of 2 source words	block of 2 channel words
00 00	100 010
00 01	101 010
10 00	000 010
10 01	001 010

15. Device as claimed in claim 13 or 14, where k has a value larger than 5, the device being further provided with means for detecting the position in the bitstream of the source signal where encoding of single 2-bit source words into single 3-bit channel words would lead to a violation of the k -constraint and for supplying a second control signal in response to said detection, characterized in that, in the presence of the second control signal, occurring during the conversion of three consecutive 2-bit source words, the converting means are adapted to convert a block of said three consecutive 2-bit source words into a block of corresponding three consecutive 3-bit channel words, such that the conversion for said block of three 2-bit source words is parity preserving, the converting means are further adapted to convert two of the three source words in the block into corresponding 3-bit channel words not identical to the four channel words CW_1 to CW_4 , in order to preserve the k constraint.

16. Device as claimed in claim 15, characterized in that, the converting means are adapted to convert blocks of three consecutive 2-bit source words into blocks of three



consecutive 3-bit channel words in accordance with the coding given in the following table:

block of 3 source words	block of 3 channel words
11 11 11	000 010 010
11 11 10	001 010 010
01 11 10	101 010 010
01 11 11	100 010 010

17. Device as claimed in anyone of the preceding claims, characterized in that the device further comprising means for detecting 8-bit bitsequences '00010001' and '10010001' in the bitstream of the source signal and means for detecting the value of the last bit of the channel signal generated from the binary source signal up to the 8-bit bitsequence, the converting means being adapted to convert the 8-bit bitsequences into the 12-bit bitsequences in the channel signal in accordance with the coding given in the following table, in dependence of the value of the said last channel bit:

8-bit bitsequence in source signal	12-bit bitsequence in channel signal
00 01 00 01	100 010 010 010
10 01 00 01 (last channel bit='0')	100 000 010 010
10 01 00 01 (last channel bit='1')	000 010 010 010

so as to limit a repeated minimum transition runlength in the channel signal.

18. Device as claimed in anyone of the preceding claims, characterized in that the device further comprises means for detecting an 8-bit bitsequence in the bitstream of the binary source signal and means for detecting the value of the last three bits of the channel signal generated from the binary source signal up to the said 8-bit bitsequence to be equal to '010', the converting means being adapted to convert the 8-bit bit sequences as given in the following table into 12-bit bitsequences in the channel signal upon detection of said three bit sequence '010' in the channel signal, in accordance with the coding given in the said following table:



8-bit bit sequence in source signal	12-bit bitsequence in channel signal
11 10 00 00	000 001 010 010
11 10 00 10	100 001 010 010
11 10 00 01	001 010 010 010
11 10 00 11	101 010 010 010

19. Device as claimed in claim 18, the converting means being adapted to convert the 8-bit sequences in accordance with the said table so as to limit the k-constraint to

10 7.

20. Recording device for recording a channel signal in a track on a record carrier, the recording device comprising the encoding device as claimed in anyone of the preceding claims and comprising writing means for writing the channel signal in said track on the record carrier.

15 21. Recording device as claimed in claim 20, characterized in that the writing means comprise precoding means for carrying out a precoding step on the channel signal prior to recording in the track on the record carrier.

22. Record carrier obtained with the recording device as claimed in claim 20 or 21.

20 23. Record carrier as claimed in claim 22, the record carrier being an optical record carrier.

24. Device for decoding a stream of data bits of a binary channel signal into a stream of databits of a binary source signal, wherein the bitstream of the channel signal is divided into m-bit channel words, which device comprises deconverting means adapted to
 25 deconvert m-bit channel words into corresponding n-bit source words, the deconverting means being adapted to deconvert a block of p consecutive m-bit channel words into a corresponding block of p consecutive n-bit source words, such that the conversion for each block of p consecutive m-bit channel words is parity preserving, where n, m and p are integers, $m > n$, $p \geq 1$, and where p can vary, characterized in that the converting means is
 30 adapted to convert at least one of the 12-bit bit sequences in the following table that appear in the bitstream of the binary channel signal into a corresponding 8-bit bit sequence of the binary source signal in accordance with the said table:



	12-bit bitsequence in the channel signal	corresponding 8-bit bitsequence in the binary source signal
5	100 010 010 010	00 01 00 01
	100 000 010 010	10 01 00 01
	000 010 010 010	10 01 00 01
	000 001 010 010	11 10 00 00
	100 001 010 010	11 10 00 10
	001 010 010 010	11 10 00 01
10	101 010 010 010	11 10 00 11

25. Device as claimed in claim 24, characterized in that the device further comprising means for detecting the said 12-bit bitsequences as given in the table.

26. A method of encoding a stream of databits of a binary source signal into a stream of databits of a binary channel signal, wherein the bitstream of the source signal is divided into n-bit source words, the method comprising the step of converting said source words into corresponding m-bit channel words, such that upon converting a block of p consecutive n-bit source words into a corresponding block of p consecutive m-bit channel words, the conversion for each block of p consecutive n-bit source words is substantially parity preserving, where n, m and p are integers, $m > n \geq 1$, $p \geq 1$, and where p can vary, characterized in that the conversion step comprises the substep of converting the 8-bit bit sequence '00010001' in the bitstream of the binary source signal into the 12-bit bit sequence '100010010010' of the binary channel signal.

27. A method of encoding a stream of databits of a binary source signal into a stream of databits of a binary channel signal, wherein the bitstream of the source signal is divided into n-bit source words, the method comprising the step of converting said source words into corresponding m-bit channel words, such that upon converting a block of p consecutive n-bit source words into a corresponding block of p consecutive m-bit channel words, the conversion for each block of p consecutive n-bit source words is substantially parity preserving, where n, m and p are integers, $m > n \geq 1$, $p \geq 1$, and where p can vary, characterized in that the conversion step comprises the substep of converting the 8-bit bit sequence '10010001' in the bitstream of the binary source signal into the 12-bit bit sequence '000010010010' of the binary channel signal.



28. The method as claimed in claim 27, characterized in that the substep of converting the 8-bit bit sequence '10010001' in the bitstream of the binary source signal into the 12-bit bit sequence '000010010010' of the binary channel signal is carried out in the case that the last bit of the channel signal generated up to this bit sequence is a '1' bit.

5 29. The method as claimed in claim 28, characterized in that the substep of converting the 8-bit bit sequence '10010001' in the bitstream of the binary source signal into the 12-bit bit sequence '100000010010' of the binary channel signal is carried out in the case that the last bit of the channel signal generated up to this bit sequence is a '0' bit.

30. A method of encoding a stream of databits of a binary source signal into a
10 stream of databits of a binary channel signal, wherein the bitstream of the source signal is divided into n-bit source words, the method comprising the step of converting said source words into corresponding m-bit channel words, such that upon converting a block of p consecutive n-bit source words into a corresponding block of p consecutive m-bit channel words, the conversion for each block of p consecutive n-bit source words is substantially
15 parity preserving, where n, m and p are integers, $m > n \geq 1$, $p \geq 1$, and where p can vary, characterized in that the conversion step comprises the substep of converting the 8-bit bit sequence '11100000' in the bitstream of the binary source signal into the 12-bit bit sequence '000001010010' of the binary channel signal in the case that the last three bits of the channel signal generated up to this bit sequence is '010'.

20 31. A method of encoding a stream of databits of a binary source signal into a stream of databits of a binary channel signal, wherein the bitstream of the source signal is divided into n-bit source words, the method comprising the step of converting said source words into corresponding m-bit channel words, such that upon converting a block of p consecutive n-bit source words into a corresponding block of p consecutive m-bit channel
25 words, the conversion for each block of p consecutive n-bit source words is substantially parity preserving, where n, m and p are integers, $m > n \geq 1$, $p \geq 1$, and where p can vary, characterized in that the conversion step comprises the substep of converting the 8-bit bit sequence '11100010' in the bitstream of the binary source signal into the 12-bit bit sequence '100001010010' of the binary channel signal in the case that the last three bits of
30 the channel signal generated up to this bit sequence is '010'.

32. A method of encoding a stream of databits of a binary source signal into a stream of databits of a binary channel signal, wherein the bitstream of the source signal is divided into n-bit source words, the method comprising the step of converting said source



words into corresponding m-bit channel words, such that upon converting a block of p consecutive n-bit source words into a corresponding block of p consecutive m-bit channel words, the conversion for each block of p consecutive n-bit source words is substantially parity preserving, where n, m and p are integers, $m > n \geq 1$, $p \geq 1$, and where p can vary, characterized in that the converting step comprises the substep of converting the 8-bit bit sequence '11100001' in the bitstream of the binary source signal into the 12-bit bit sequence '001010010010' of the binary channel signal in the case that the last three bits of the channel signal generated up to this bit sequence is '010'.

33. A method of encoding a stream of databits of a binary source signal into a

stream of databits of a binary channel signal, wherein the bitstream of the source signal is divided into n-bit source words, the method comprising the step of converting said source words into corresponding m-bit channel words, such that upon converting a block of p consecutive n-bit source words into a corresponding block of p consecutive m-bit channel words, the conversion for each block of p consecutive n-bit source words is substantially parity preserving, where n, m and p are integers, $m > n \geq 1$, $p \geq 1$, and where p can vary, characterized in that the converting step comprises the substep of converting the 8-bit bit sequence '11100011' in the bitstream of the binary source signal into the 12-bit bit sequence '101010010010' of the binary channel signal in the case that the last three bits of the channel signal generated up to this bit sequence is '010'.

34. The method as claimed in anyone of the claims 26 to 33, further comprising the step of recording the channel signal in a track on a record carrier.

35. The method as claimed in claim 34, characterized in that the record carrier is an optical record carrier.

36. The method as claimed in claim 34 or 35, characterized in that the

method further comprises a precoding step on the channel signal prior to recording the channel signal on the record carrier.

