

DESCRIPTION

POSITION DETECTOR AND POSITION DETECTION METHOD

Field of the Invention

5 [0001]

The present invention relates to a position detector for detecting positions of a moving object such as a traveling vehicle, a transfer apparatus, a head of a working machine or a workpiece. Further, the present invention relates to a position detection method.

10

Background Art

[0002]

The applicant developed a sensor for measuring positions of a moving object such as a traveling vehicle, a transportation apparatus, a transfer apparatus, a head of a working machine or a workpiece (e.g., Patent Publication 1: JP2009-2660A). This position detector uses a combination of magnetizable material and non-magnetizable material or a magnet or the like as a mark, and uses coil arrays to determine positions based on the mark. That is, phases of signals outputted from coil arrays are different depending on the relative position to the mark, and the difference are used to determine the position based on the mark. Further, in the case where a plurality of marks are present, an offset is stored for each of the marks, and the offset is added to the position based on the mark to determine an absolute position.

20

[0003]

Next, for example, a case where a range of measuring the position is large will be considered. It is assumed that a movement stroke of a moving object, or the entire length of a travel route is large. In order to continuously detect the position in the case where the measurement range is large, it is effective to provide a pair of position detectors at

25

least on left and right sides of the moving object, provide the marks on left and right sides of the moving route of the moving object, and detect the marks using any of the position detectors all the time (Patent Publication 2: JP2008-140144A). However, the inventor found that, at the time of switching between a pair of left and right position detectors, the indicator value indicating the position of the moving object changes discontinuously. If the position changes discontinuously, large noises will be inputted to a servo system operated based on the indicator value from the position detectors disadvantageously.

Summary of the Invention

10 [0004]

In the present invention, a plurality of sensor units are provided for continuously detecting positions, and an object of the present invention is to prevent discontinuous changes of outputs of the position in a segment where two or more sensor units each outputting positions are present.

15 [0005]

The present invention relates to a position detector having a plurality of sensor units each configured to determine positions. The position detector selectively uses the sensor units for outputting positions of a moving object.

The position detector includes a smoothing unit for generating positional outputs by combining outputs from a plurality of the sensor units in a segment where the plurality of sensor units output positions together, for allowing the positional outputs to change continuously from a start to an end of the segment.

[0006]

Further, the present invention relates to a position detection method using a position detector having a plurality of sensor units each configured to determine positions. The position detector selectively uses the sensor units for outputting positions of a moving object. The method includes the step of generating positional outputs using

a smoothing unit of the position detector by combining outputs from a plurality of the sensor units in a segment where the plurality of sensor units output positions together, for allowing the positional outputs to change continuously from a start to an end of the segment. In this specification, description regarding the position detector is directly applicable to the position detection method, and conversely, description regarding the position detection method is directly applicable to description regarding the position detector.

[0007]

In this manner, at the time of switching the sensor units, in a segment where outputs from a plurality of sensor units are obtained, the outputs (indicator values) of the position does not change discontinuously. Therefore, no excessive burden is applied to the servo system or the like using the signal from the position detector. The position detector may be mounted in the moving object to detect marks on the ground.

Alternatively, marks may be provided on the moving object, and the position detector on the ground may detect the marks of the moving object to determine the position of the moving object.

[0008]

Preferably, in the segment, an outputs D of the position detector is determined based on an equation of $D = DL - (DL - DR) \times X/L1$, where DL denotes positions based on outputs from a first sensor unit of the plurality of sensor units, DR denotes positions based on outputs from a second sensor unit of the plurality of sensor units, $L1$ denotes length of the segment in a moving direction of the moving object, X denotes a relative position of the moving object in the segment, $X = 0$ on a side where only the first sensor unit is valid, and $X = L1$ on a side where only the second sensor unit is valid. In this manner, the position of the moving object can be determined by simple interpolation computation. Further, the difference between outputs of the sensor units are dispersed over the entire length of the segment. It should be noted that any one of, e.g., a pair of

the sensor units may be referred to as L or R. In the above equation, the suffixes L and R may not correspond to left and right sides physically. L may be the sensor unit on the right side, and R may be the sensor unit on the left side. However, in this approach, at the position where $X = 1$ and the position where $X = L1$, though the position is continuous, it does not change smoothly. For the purpose of smoothing of the position, for example, assuming that $y = X/L1 - 0.5$ and $DL - DR = C$, a function of $C(y) = 1/(1 + \exp(-n \times y))$, $D = DL + C$ or the like may be used. This is a sigmoid function used in neural network where n is a positive number, e.g., in a range of 5 to 100. If $y = -0.5$, this function has a value of about 0. If $y = 0$, this function has a value of $1/2$. If $y = 0.5$, this function has a value of about 1. However, since an exponential function is required for computation, it is not possible to suitably determine the position at high speed. Errors are compressed in an area where y is about 0.5. Therefore, the burden applied to the external servo system becomes large.

[0009]

More preferably, each of the plurality of sensor units is a coil array. The position detector includes a common power supply for driving a plurality of coil arrays, a detection circuit for converting the outputs from the coil array into outputs of the detection circuit, and a switch for selectively inputting outputs from the plurality of coil arrays to use the detection circuit as a common detection circuit shared between the plurality of coil arrays. The switch is switched in the segment to convert the outputs from the plurality of coil arrays alternately into the outputs of the common detection circuit. In this manner, not only the detection circuit can be shared but also the difference in the indicator value of the position due to variation of the detection circuit can be eliminated. The difference in the indicator value of the position is due to the use of different detection circuits in addition to installation precision of marks and variation of each sensor unit. Therefore, by using the common detection circuit, the difference resulting from the use of detection circuits can be eliminated from the beginning.

[0010]

Particularly preferably, in the segment, a prediction computation unit is provided for performing extrapolation of time series data of positions based on an output from each coil array to positions at current time to determine a temporal current position of each coil array. In the smoothing unit, respective outputs of the temporal current positions of the coil arrays are combined to generate the position of the moving object. By sharing the detection circuit, since the sensor units are used alternately, in each of the individual sensor units, the cycle of obtaining the outputs from the sensor unit is doubled. In the meanwhile, in order to determine the position, it is necessary to obtain the indicator values from the plurality of sensor units at the same time. Therefore, by extrapolation of the indicator values from the sensor units to determine temporal current positions, the position of the moving object can be determined all the time without being affected by the influence resulting from sharing of the detection circuit.

Brief Description of the Drawings

[0011]

[FIG. 1]

FIG. 1 is a diagram showing magnetic marks, coil arrays, a detection circuit, and a smoothing unit according to an embodiment.

[FIG. 2]

FIG. 2 is a block diagram showing the coil array according to the embodiment.

[FIG. 3]

FIG. 3 is a block diagram showing the detection circuit and the smoothing unit according to the embodiment.

[FIG. 4]

FIG. 4 includes graphs showing smoothing at the time of switching the coil arrays and the weight w of each coil array.

[FIG. 5]

FIG. 5 includes graphs showing prediction of the current position based on signals from coil arrays and smoothing.

[FIG. 6]

5 FIG. 6 is a flow chart showing an algorithm of smoothing.

[FIG. 7]

FIG. 7 is a block diagram showing detection circuits and a smoothing unit according to a modified embodiment.

[0012]

10 Hereinafter, an embodiment in the most preferred form for carrying out the present invention will be described. The scope of the invention shall be determined according to understanding of a person skilled in the art based on the description of the claims in consideration of the description of the specification and techniques known in this technical field.

15

Most preferred embodiment

[0013]

FIGS. 1 to 7 show the embodiment. In the drawings, reference numerals m1, m2 denote magnetic marks provided along left and right sides of a travel rail for moving
20 objects (not shown), e.g., overhead traveling vehicles in the embodiment. For example, the mark is a combination of magnetizable material and non-magnetizable material, or a permanent magnet or the like. A position detector 2 is attached to a moving object (not shown), and made up of a pair of left and right coil arrays L, R (left and right sensor units), a common alternating current power supply circuit for driving the coil arrays L, R,
25 a common detection circuit 6, and a smoothing unit 8.

[0014]

The coil arrays L, R have the same structure. A layout of coils of the coil arrays

L, R is shown in FIG. 2. For example, four coils C1-1 to C1-4 are arranged in one set, and likewise, coils C2-1 to C2-4 are arranged in one set, and coils C3-1 to C3-4 are arranged in one set. The other coils are arranged in the same manner. Two outputs are collected from four coils of each set as outputs P1, P2 of the coil arrays. Further, the
5 coils C1-1 to C3-4 are arranged in series in the order of C1-1, C1-2, C1-3, C1-4, C2-1, C2-2, ... etc.

[0015]

FIG. 3 shows structure of a detection circuit 6 or the like. An alternating current power supply circuit 4 includes a timer 12 having a clock circuit, a table 13 for reading a
10 signal corresponding to $\sin\omega t$ from the timer 12, and a D/A converter 14 for performing D/A conversion of the outputs of the table 13 to output a signal $a \times \sin\omega t$ corresponding to the alternating current waveform voltage. In the detection circuit 6, timing where the alternating current signal $\sin\omega t$ becomes 0 is important. At this timing, the counter 22 as described later is reset. In the detection circuit 6, when $\sin(\omega t + \alpha)$ becomes 0, the clock
15 outputs from the timer 12 are latched, and the time t_i is outputted. α denotes a phase relative to the mark, and denotes displacement based on the mark. The value obtained by adding an offset to α is an indicator value of positions of each sensor unit.

[0016]

As shown in FIG. 2, a pair of signals P1, P2 are obtained from the coil arrays L,
20 R. Since there are two sets of the coil arrays, two sets of signals (P1L, P2L), (P1R, P2R) are outputted to the detection circuit 6. In the detection circuit 6, the signals (P1L, P2L) and (P1R, P2R) are switched alternately by a switch 16 for processing. Reference numerals 18, 19 denote a pair of operational amplifiers. The operation amplifier 18 obtains a signal corresponding to $b \times \cos\alpha \times \sin\omega t$, and the operational amplifier 19
25 obtains a signal corresponding to $b \times \sin\alpha \times \sin\omega t$. A phase shifter 20 advances the phase of ωt of the operational amplifier 19 by 90° to output a signal corresponding to $b \times \sin\alpha \times \cos\omega t$. For this purpose, for example, the signal is delayed by $\pi/2$ of ωt , and negative to

positive conversion or positive to negative conversion is performed. An adder 21 adds the signal of $b \times \cos\alpha \times \sin\omega t$ from the operational amplifier 18 to the signal of $b \times \sin\alpha \times \cos\omega t$ from the phase shifter 20, and outputs a signal corresponding to $b \times \sin(\omega t + \alpha)$ using addition theorem.

5 [0017]

α denotes a position of the coil array relative to the magnetic mark in the phase in a range of 0 to 2π , i.e., α is a position based on the magnetic mark. Each time $\sin\omega t$ becomes 0, the counter 22 is reset by a signal from the timer 12. Then, the time until $\sin(\omega t + \alpha)$ becomes 0 is counted. Conversely, the time until $\sin\omega t$ becomes 0 after $\sin(\omega t + \alpha)$ became 0 may be counted. Data of α is obtained from the counter 22. Since this data is based on the magnetic mark, an offset correction unit 30 performs offset correction of the data, and converts the data into an indicator value D_i of positions of the moving object. The series of processing as described above is performed for left and right magnetic marks m_1 , m_2 alternately. For the left magnetic mark m_1 , an indicator value D_{iL} and time series data of the detection time t_{iL} are obtained. For the right magnetic mark m_2 , an indicator value D_{iR} and time series data of the detection time t_{iR} are obtained. These two types of time series data are stored in a memory 31.

[0018]

A prediction computation unit 32 performs prediction computation of the current position D_{iL} based on the coil array L using the time series data from the coil array L in the memory 31. Likewise, the prediction computation unit 32 performs prediction computation of the current position D_{iR} based on the coil array R using the time series data from the coil array R. In a segment where only the coil array L is valid, prediction computation for only the current position based on the coil array L is performed. Likewise, in a segment where only the coil array R is valid, prediction computation for only the current position based on the coil array R is performed. Prediction computation is at least performed in a segment where both of the coil array L and the coil array R are

valid (overlapping area). In the embodiment, weighted averaging is performed as smoothing. As shown in FIG. 4, a smoothing unit 8 averages prediction computation values of two current values regarding the coil array L and the coil array R using $X/L1$ as a weight, and outputs an indicator value D of the current position. The meaning of $X/L1$ is shown in FIG. 4.

[0019]

FIG. 4 shows smoothing of indicator values from the coil arrays L, R. On the left side in FIG. 4, only the coil array L is valid. On the right side in FIG. 4, only the coil array R is valid. A segment where both of the coil array L and the coil array R are valid is present between the left side and right side of FIG. 4. This segment is a target of smoothing. The length of the segment is $L1$. In this segment, smoothing is performed as shown by a double line in FIG. 4. In this segment, indicator values are outputted from the coil arrays L, R at timings of vertical lines in FIG. 4. Prediction computation of these indicator values are performed by the prediction computation unit to convert the indicator values into a continuous indicator value. The weight of the signal of the coil array L is 100% at the start of a segment where $X=0$, and the weight of the signal of the coil array R is 100% at the end of a segment where $X=L1$. For example, the weight changes linearly between these points.

[0020]

FIG. 5 schematically shows processing from prediction computation to calculation of the indicator value after smoothing. A graph in an upper portion of FIG. 5 shows the indicator value DL from the left coil array L. For example, the indicator value DL is generated in a cycle of about 10Hz of the alternating current power supply signal. Likewise, the indicator value DR from the right coil array R is generated in a cycle of about 10kHz. In the area where both of the two coil arrays are valid, since the detection circuit is switched alternately, the time interval of obtaining the indicator value is twice as large as the time interval in the other segment. Further, the indicator values from the

pair of coils L, R cannot be obtained at the same time. Therefore, indicator values at arbitrary points are temporarily determined. Then, as shown in a graph in a lower portion of FIG. 5, the temporarily determined indicator values are averaged using the weight w to generate the indicator value $D(t)$ at the time t . The weight w is $X/L1$.

5 [0021]

FIG. 6 shows a processing algorithm in the overlapping segment where both of the coil arrays L and R are valid. In step 1, an indicator value from the coil array L and the time series data of the detection time are stored. In step 2, outputs DR from the coil array R and time series data of the detection time are stored. Step 1 and step 2 are performed alternately. In step 3, with respect to the coil array L, the indicator value DR at the current time r is determined by extrapolation of the time series data obtained from the coil array L. Likewise, in step 4, with respect to the coil array R, the indicator value DR at the current time is determined by extrapolation. Step 3 and Step 4 are performed alternately as well. In step 5, the two extrapolated values are weight averaged to determine the current position. Determination of the relative position X in the overlapping segment is substantially equal to determination of indicator value D . For example, a value calculated from the previous indicator value D is used as X . In the case of carrying out processing more precisely, X is determined from the previous indicator value, and the current indicator value D is determined from X . Then, X is determined again based on the current indicator value D , and then, the current indicator value D is determined again.

20

[0022]

FIG. 7 shows detection circuits according to a modified embodiment. A pair of coil arrays L, R are driven by a common alternating current power supply circuit made up of the timer 12, the table 13, and the D/A converter 14. In this respect, the circuit of FIG. 7 is the same as that shown in FIG. 3. In the circuit of FIG. 7, a pair of detection circuits are provided, and outputs from the separate detection circuits are smoothed by a

25

smoothing unit 8 in accordance with the manner shown in FIG. 4. Therefore, in an offset correction unit 30', offset correction of only one indicator value from one coil is performed. Further, since the indicator values from left and right coil arrays can be obtained substantially at the same time, prediction computation is omitted. In the circuit shown in FIG. 7, the pair of detection circuits are required. Additionally, since the signals from the left and right coil arrays L, R are processed by the separate detection circuits, errors based on the variation in the characteristics of the detection circuits occur. In other respect, the detection circuit of FIG. 7 are the same as the detection circuit 6 shown in FIG. 3.

10 [0023]

In the embodiment, the following advantages are obtained.

- (1) In the overlapping segment where signals are obtained from both of the pair of coils, the outputs from the position detector do not change discontinuously. Therefore, no excessive load is applied to the servo system or the like using the signal from the position detector for control.
- (2) By determining the positional outputs as $D = DL - (DL - DR) \times X/L1$, the position can be determined by simple computation. Further, the errors can be dispersed over the entire overlapping segment.
- (3) Sharing of the detection circuit is advantageous in terms of cost, and no errors due to variation of the detection circuit occur.
- (4) By predicting the current position based on the prediction computation unit, since the detection circuit is shared, it becomes possible to solve the problem that the left and right indicator values cannot be obtained at the same time. Further, the current indicator value can be predicted substantially at any position. Further, also in segments other than the overlapping segment, the indicator value can be outputted regardless of the alternating current cycle of driving the coil arrays.

25

[0024]

The components such as the offset correction unit 30, the memory 31, the prediction computation unit 32, the smoothing unit 8, the timer 12, the table 13, the D/A converter 14 may be provided as discrete circuits. Alternatively, these components may be provided as computer structure made up of hardware and software.

5

Description of the numerals

[0025]

2: position detector

4: alternating current power supply circuit

10 6: detection circuit

8: smoothing unit

10, 11: signal line

12: timer

13: table

15 14: D/A converter

16: switch

18, 19: operational amplifier

20: phase shifter

21: adder

20 22: counter

30: offset correction segment

31: memory

32: prediction computation segment

25 m1, m2: magnetic mark

L, R: coil array

C1-1 to C3-4: coil

D: indicator value

t: time

P1, P2: outputs of coil array

L1: length of overlapping portion

5 X: relative coordinate in overlapping portion

WHAT IS CLAIMED IS:

1. A position detector having a plurality of sensor units each configured to determine positions, the position detector selectively using the sensor units for outputting
5 positions of a moving object, being characterized in

that the plurality of sensor units each comprise a coil array;

that the position detector further includes

a common power supply for driving the plurality of coil arrays;

a detection circuit for converting the outputs from the coil arrays into the

10 positional outputs; and

a switch for selectively inputting outputs from the plurality of coil arrays to the

detection circuit in such a way that the detection circuit is shared between the

plurality of coil arrays;

that, in a segment where the plurality of sensor units output positions together, the

15 switch is switched to convert the outputs from the plurality of coil arrays alternately into the positional outputs by the detection circuit; and

that the position detector further includes a smoothing unit for generating

positional outputs of the detector by combining the outputs positions from the plurality of

the sensor units in such a way that the positional outputs change continuously from a start

20 to an end of the segment.

2. The position detector according to claim 1, being characterized in that means for extrapolating output positions from each coil array to provisional current positions for each coil array is provided; and that the smoothing unit combines the provisional current
25 positions for the coil arrays to the positional outputs of the detector.