



POS copy

PRINthead WITH REDUCED INTERCONNECTIONS TO A PRINTER

BACKGROUND OF THE INVENTION

This invention relates generally to thermal inkjet printing. More particularly, this invention relates to a novel printhead design for increasing the number of inkjet nozzles on the printhead while minimizing the number of electrical interconnections between the printer and printhead. The term "printhead" as used herein includes an ink source as well as an ink drop generating mechanism attached to the source and is also known as a cartridge or pen.

Print quality and throughput are important objectives in the design of thermal inkjet printers. Print quality is a function of, among other things, the distance between the inkjet nozzles on the printhead. Higher print quality produces crisper output and more colors through better dithering. Throughput is a function of the width of the printed swath. The wider the swath, the fewer passes the printhead must to print a page.

Both of these objectives can be met by increasing the number of inkjet nozzles on the printhead. By placing nozzles closer together, the print quality can be improved. By placing more nozzles on the printhead, the width of the printing swath is increased. However, adding nozzles requires adding associated drivers, which comprise heater resistors, control logic and power and control interconnections. These interconnections are flexible wires or equivalent conductors that electrically connect the drivers on the printhead to printhead interface circuitry in the printer. They may be contained in a ribbon cable that connects on one end to control circuitry within the printer and on the other end to driver circuitry on the printhead.

Interconnections are a major source of cost in printer design, and adding them to increase the number of drivers increases the cost. Interconnections also affect the reliability of the printer, with more interconnections increasing the likelihood that the printer will fail.



Thus as the number of drivers on a printhead has increased over the years, there have been attempts to reduce the number of interconnections per driver. One approach that is presently being investigated is called "integrated drive head" or IDH multiplexing. In IDH, the drivers are split into groups known as primitives. Each primitive has its own power supply interconnection ("primitive select") and return interconnection ("primitive return"). In addition, a number of control lines are used to enable particular drivers. These control or address lines are shared among all primitives. This approach can be thought of as an XY matrix where X is the number of primitives (rows) and Y is the number of drivers per primitive (columns). The energizing ("firing") of each driver resistor is controlled by a primitive select and by a transistor such as a MOSFET that acts as a switch connected in series with each resistor. By powering up one or more primitive selects (X1, X3, etc.) and driving the associated gate of the transistor (Y2, for example), multiple heater resistors may be fired simultaneously. The number of interconnections required for such a matrix is fewer than one per driver. This is markedly fewer than in a direct drive approach, wherein each driver has its own primitive select and shares a primitive common with the other drivers.

The matrix approach in IDH multiplexing offers an improvement over the direct drive approach. Yet as presently contemplated the matrix approach has its drawbacks. The primitive select interconnection for each primitive must be driven by a switching power supply that can rapidly switch between on and off states. Such supplies are more expensive and more prone to failure than constant, i.e., static, power supplies. Furthermore, the number of interconnections with such a matrix is still large, on the order of $3\sqrt{n}$, where n is the number of drivers. Thus increasing the number of drivers significantly, even with the matrix, still results in an undesirable increase in the number of interconnections.

SUMMARY OF THE INVENTION

An object of the invention, therefore, is to increase the number of inkjet nozzles on a printhead without increasing the number of interconnections between the printhead and printer.

Another object of the invention is to minimize the number of interconnections required per driver on the printhead.

Yet another object of the invention is to reduce the cost or complexity of printer control circuitry by shifting control functions from the printer to the printhead.

In one embodiment, a printhead according to the invention includes a power interconnection for providing constant power to the printhead and a control interconnection for providing a print command to the printhead. A plurality of heater resistors are each operably connected to the power interconnection. A switching device is also provided for selectively energizing each heater resistor with power from the power interconnection. Each switching device is responsive to a print command from the control interconnection for energizing the heater resistor.

In another embodiment, the printhead includes a plurality of groups of heater resistors and a power interconnection for selectively providing power to each group when the interconnection is enabled. Switching devices are also provided in a plurality of groups for selectively energizing each heater resistor within a group. A control interconnection operates each group of switching devices when the interconnection is enabled. A heater resistor on the printhead is energized if both the power interconnection and control interconnection for the resistor are enabled.

Variations on the inventive printhead include multiplexed interconnections, energy control, gray scale modulation and other features described more particularly below.



The foregoing and other objects, features, and advantages of the invention will become more apparent from the following detailed description of several preferred embodiments as shown in the accompanying drawings.

5

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a block diagram showing a conventional printer and printhead and the interconnections between them.

FIG. 2 is a schematic diagram of a conventional driver matrix in the printhead of FIG. 1.

FIG. 3 is a block diagram of printhead driver circuitry according to the invention.

FIGS. 4A and 4B are diagrams of possible drivers for use in the driver circuitry of FIG. 3.

FIG. 5 is a schematic diagram of one embodiment of the energy control circuit shown in the driver design of FIG. 4B.

FIG. 6 is a schematic diagram of one embodiment of the address generating device shown in FIG. 3.

FIG. 7 is a schematic diagram of one embodiment of the print enable register shown in FIG. 3.

FIG. 8 is a block diagram of another embodiment of the printhead driver circuitry that includes a pulse width modulation (PWM) converter.

FIG. 9 is a schematic diagram of another embodiment of printhead driver circuitry that includes gray scale modulation.

FIG. 10 is a schematic diagram of a multiplexing scheme for reducing the number of control interconnections between the printer and printhead.

DESCRIPTION OF PREFERRED EMBODIMENTS

FIG. 1 shows printhead interface circuitry 10 with an inkjet printer 12 and an IDH inkjet printhead 14. Printing commands are transmitted from the interface circuitry 10, which is conventional in design, to driver circuitry on the printhead 14 through multiple interconnections 18. These interconnections 18 include primitive selects, primitive commons and control



interconnections. The interconnections 18 are operably connected to the driver circuitry on the printhead 14 through various connecting pads for controlling the energizing of heater resistors.

5 The Basic Embodiment

FIG. 2 illustrates a driver matrix (rectangular array) within driver circuitry 16 on the printhead 14 for selecting which drivers to fire in response to print commands from the printer. While the matrix will be
10 described in terms of rows and columns, it should be understood that these terms are not meant to imply physical limitations on the arrangement of drivers within the matrix or on the printhead. Drivers may be arranged in any manner so long as they can be identified in the
15 matrix by two enable signals within the print command. Each driver generally comprises a heater resistor (R_0) 20, a switching device 22, a primitive select 24, a primitive common 26 and a control interconnection 28 (parasitic resistances (R_p) are also shown). The switching device 22
20 is connected in series with the resistor 20 between the primitive select 24 and primitive common 26. The control interconnection 28 is also connected to the switching device 22 for switching the device 22 between a conductive state and a nonconductive state. In the conductive state,
25 the device 22 completes a circuit from the primitive select 24 through the resistor 20 to the primitive common 26 to energize the heater resistor.

Each row of drivers in the matrix is a primitive and may be selectively fired by powering the associated
30 primitive select ("power") interconnection 24, such as PS1 for the top row shown in FIG. 2. To provide uniform energy per heater resistor 20, the parasitic resistances R_p of the primitive select and common interconnections are carefully balanced as shown and only one resistor 20 is
35 energized at a time per primitive. However, any number of the primitive selects may be enabled concurrently. Each enabled primitive select 24 such as PS1, PS2, etc., thus delivers both power and one of the enable signals to the



driver circuitry 16. The other enable signal for the driver matrix is an address signal provided by each control interconnection 28, such as A1, A2, etc., only one of which is preferably active at a time. Each control
5 interconnection 28 is tied to all of the switching devices 22 in a matrix column so that all such switching devices are conductive when the interconnection is enabled or "active," i.e., at a voltage level which turns on the switching devices 22. Where a primitive select
10 interconnection 24 and a control interconnection 28 for a heater resistor R_p 20 are both active concurrently, that resistor 20 is energized. Alternatively, each matrix column could be a primitive or other defined group of drivers and each row could be a column or other defined
15 group of drivers tied to a single control interconnection 28. "Matrix" as used herein refers to an electrical, not physical, relationship.

The interconnections for controlling the printhead driver circuitry of FIG. 2 include separate
20 primitive select and primitive common interconnections for each primitive and separate control interconnections for each matrix column. A typical driver matrix comprises an array of 8 primitives and 13 columns, requiring 29 interconnections. Increasing the number of drivers to 300
25 with a similar matrix would only increase the number of interconnections to 49.

The Advanced Embodiment

FIG. 3 shows an advanced embodiment of printhead driver circuitry 30 for minimizing the number of
30 interconnections 24, 26 and 28. Primitive select interconnection 24 and common interconnection 26 provide constant power to an array 32 of drivers 31. "Array," like matrix, as used herein refers to an electrical, not physical, relationship. At a minimum, one of each
35 interconnections 24 and 26 is required for the entire array of drivers, assuming the parasitic resistances R_p in the array 32 are balanced throughout. Because such balancing may be difficult to achieve in practice, it may



be desirable to have the array 32 divided into primitives each with interconnections 24, 26 connected in the manner shown in FIG. 2. Alternatively, an energy control circuit may be incorporated into the driver circuitry 30, as will
5 be discussed.

Control interconnection 28 provides a print command from the printer interface circuitry 10 to the driver circuitry 30. The print command includes an address generating signal such as a clock signal and a
10 print enable signal. These two signals may be carried on separate interconnections 28 or combined using known data compression techniques in a signal on a single interconnection, as will be described. Whichever way the two signals arrive at the printhead 14, they are directed
15 to different components of circuitry 30 for selecting one or more drivers 31 from a driver array 32 have n-by-m drivers.

One of these components is an address generator 34 which receives the print command and in response
20 generates a address signals for the drivers 31 of array 32. The address generator 34 has an input for receiving the address generating signal and a plurality of address lines as outputs for transmitting address signals to the drivers of the array 32. Preferably only one of the
25 address lines is active at one time, although it may be possible to have generator 34 produce concurrent address signals if desired. Each of these lines is interconnected to a row of drivers in the array 32 such that each driver in the row receives the address. The address generator 34
30 may be a state machine, circular shift register or other equivalent device that can receive an address generating signal and in response generate multiple address signals. FIG. 6 shows a shift register embodiment of such a generator 34 comprising a number of D flip flops 36
35 connected from output to input. The address generating signal in this example is a clock signal 37 within the print command which is applied to a clock input on each of the flip flops 36. The outputs of the generator 34, A(1),

191148



- 8 -

A(2), ..., A(n) are active individually in sequential order. A reset input may also be provided for receiving an reset signal 38 from the printer. A reset of generator 34 to an initial state may be desired at power up of the printer or other appropriate times in the printing process.

Returning to FIG. 3, another of the components of the driver circuitry 30 for selecting a driver 31 to fire is a print control device such as print enable data register 40. Register 40 receives the print command and in response generates one or more print enable signals. The function of these print enable signals is analogous to the enabling function provided by primitive select interconnections 24, 26 in the embodiment of FIG. 2. Specifically, register 40 converts a serial stream of print enable signals it receives from the printer 12 into a format for applying the print enable signals concurrently to one or more columns of drivers in array 32. FIG. 7 shows one embodiment of the register 40 in the form of a serial-to-parallel shift register comprising a row of connected D flip flops 42. The print command data is applied serially to the D input of the first flip flop and clocked through to the output of the mth flip flop, which corresponds to the mth column in the array 32. The outputs of the flip flops 42 are provided in parallel. A clock signal for clocking the D flip flops 42 may be the same clock signal that forms the address generating signal for address generator 34 or may be a separate signal.

The drivers D_{1,1} through D_{n,n} may be constructed in a number of ways. A preferred design is shown in FIG 4A, where each driver 31 comprises a heater resistor 44, an associated switching device 46 such as a MOSFET in series with the resistor, and a logic gate 48 such as a two-input AND gate connected for controlling the switching device 46. The resistor 44 and switching device 46 are operably connected between a power interconnection 24 and a common interconnection 26. The inputs to the gate 48 are an address signal from the generator 34, such as



signal Ax (where x indicates the xth row of the array 32),
and a print enable signal PEy from register 40 (where y
represents the yth column of the array 32). The switching
device 46 is driven between conductive and nonconductive
5 states by the presence or absence of these two signals at
the logic gate 48. Thus in response to a print command
from the printer 12 to fire a particular driver, the
switching device 46 energizes the associated heater
resistor 44 by allowing current to flow from the power
10 interconnection 24 through the resistor to the common
interconnection 26.

Of course, it will be appreciated by those
skilled in the art that a number of equivalent devices
could be substituted for the components described above.
15 For example, in this particular embodiment, a circuit is
completed through the heater resistor 44 when the
switching device 46 is switched to a conductive state.
Alternative arrangements such as switching the device 46
to a nonconductive state are possible.

20 Driver Circuitry with Energy Control

The number of power interconnections 24, 26 may
be reduced to a minimum if the firing energy per resistor
can be equalized without the use of primitives in array
32. In the ideal case, the power interconnections could
25 be reduced to one power interconnection 24 and one common
interconnection 26. This arrangement would allow more
than one driver to be fired per row in the array 32 of
FIG. 3 if desired.

To make this possible, a mechanism for
30 controlling the energy provided to each heater resistor 44
is provided. FIG. 4B shows one example of such a
mechanism in the form of an energy control circuit 50.
The circuit 50 monitors the voltage across each heater
resistor 44 and compares the monitored voltage to a
35 reference voltage. The output of that comparison controls
the strength of the drive signal applied to the gate of
switching device 46 so that the switch is driven to
conduct sufficiently to achieve the desired voltage across



resistor 44. One form of circuit 50 is illustrated in FIG. 5. An instrument amplifier 52 measures the voltage drop across the resistor 44. The magnitude of this voltage is compared at a comparator 54 to a reference voltage REF that is the same reference voltage for each heater resistor 44 in the array 32. The output signal of the comparator 54 is applied to a level shift circuit 56 that shifts the level of voltage applied to the gate of switching device 46 in an appropriate direction. Circuit 50 and several equivalents are more fully shown and described in U.S. Patent No. 5,083,137, commonly owned by the present assignee and hereby incorporated by reference.

Driver Circuitry with Data Decoding and Compression

FIG. 8 is a partial view of the embodiment in FIG. 3 in which a data converter 58 is placed between the interconnections from the printer 12 and the driver circuitry 30. The data converter 58 decodes an encoded electrical signal and, if the data has also been compressed, uncompresses the data as well. Any of a number of encoding schemes maybe used, including but not limited to pulse code modulation, pulse width modulation, run length limited encoding and time division multiplexing. By using such a scheme, the print command may be carried on a single interconnection or at least fewer interconnections than if no encoding is used. Data converter 58, of conventional design, converts the print command into the print enable signal and address generating signal (or address signal if address generation is not performed on the printhead).

30 Driver Circuitry with Gray Scale Modulation

The intensity of the ink (multi-color or black) printed by the printer 12 is a function of ink drop volume and drop velocity. This intensity can be scaled by varying the control voltage applied to the gate of switching device 46 (or switching device 22 in FIG. 2.) This voltage controls the amount of energy delivered to the heater resistor by power interconnections 24 and 26,



as described above. One approach for providing for such gray scale printing is shown in FIG. 9.

A number of analog voltage levels $GL_1, \dots, GL_n$ are generated by an on- or off-printhead voltage reference and are provided as signal inputs to a selection device such as a multiplexer 60 that connects to the input of each switching device 46. PE.LVL is an m bit bus ($m = \log_2 n$) which is connected to the selection inputs of multiplexer 60 and controls the selection of the analog voltage level in the multiplexer. Ax is an address signal to an enable input of multiplexer 60. This scheme requires a group of m bits of print enable data for each row of drivers in array 32. A particular driver fires when its address signal and its PE.LVL bus are both active. The analog voltage GL selected depends upon the data on the PE.LVL print enable bus.

Row Sub-Multiplexing

Referring to FIG. 10, an alternative approach to reducing the interconnections to the printhead 14 is multiplexing the control interconnections to the drivers in the circuitry 16 of FIG. 2. This approach is called "row sub-multiplexing" (RSM). By multiplexing the control interconnections into a square (or nearly square) array, the number of interconnections is twice the number of columns plus twice the square root of the number of rows. With RSM, the total number of interconnections n when optimized is reduced from $3\sqrt{n}$ to $3\sqrt[3]{n}$.

Although the reduction in interconnections with RSM is not as dramatic as in the advanced embodiment and its variations, RSM has advantages in simplicity and the small number of active devices, e.g., transistors, required for implementation. RSM also permits fabricating the required printhead circuitry using a simple NMOS process. For example, the additional number of active devices required for RSM compared to the driver circuit 16 in FIG. 2 is equal to the number of rows in the matrix. Therefore RSM has only a negligible effect on the size of the driver circuit. In fact, depending on the specific



layout of the driver circuit, RSM may actually reduce the circuit size because of the reduced number of interconnection pads. If RSM is implemented using resistor-transistor logic (RTL) structures as shown in
5 FIG. 10, a simple NMOS process can be used to fabricate the structures.

FIG. 10 shows a simple example of RSM. Structurally, the multiplexer 70 is located on printhead 14 and comprises groups of X and Y inputs serially
10 connected through resistors R_b 71 and logic gates 72. A control line A_i is connected at one location to a node between each resistor R_b and gate 72 and at another location to a switching device 22 within driver circuitry 16. Each input group has a single X input and multiple
15 paths each through a resistor R_b , gate and Y input as desired. The Y inputs are common to multiple groups. A control line A_i is enabled if the X_i input signal is enabled and the Y_i input signal is disabled.

In RSM operation, the control lines $A_1, \dots, A_i$ to
20 the switching devices 22 are sequentially enabled one at a time. To enable line A_1 for example, inputs X_1 and Y_2 are enabled and inputs X_2 and Y_1 are disabled. In similar fashion, control lines $A_2, \dots, A_i$ are sequentially enabled.

25 The power consumed by the row multiplexer 70 depends inversely on the resistance of resistors R_b . The resistors must have enough resistance that the power consumed does not contribute to excessive printhead temperature, which can degrade print quality. However,
30 the switching time for turning on the drivers 31 within driver circuitry 16 is proportional to the value of the resistors R_b . The desire for low printhead temperature and fast switching time are thus in conflict. One way of reducing switching time, power consumption and temperature
35 is to increase the number of X inputs and decrease the number of Y inputs. But this option increases both the number of interconnections and the number of active devices from the minimum set forth above.

Having described and illustrated the principles of the invention with reference to a preferred embodiment and several variations thereon, it should be readily apparent to those skilled in the art that the embodiment
5 can be modified without departing from such principles. We recognize that the principles of this invention can be applied to a wide variety of equivalent embodiments. For example, the address signals may come directly from the printer over interconnections rather than being generated
10 within driver circuitry 30, if desired. Components such as logic gates 48 and switching devices 46 may be interchanged with analog or software-based equivalent structure such as look up tables, comparison operations, etc. Therefore, the illustrated embodiments should be
15 considered as an examples only of our preferred forms of the invention and not as limitations on the scope of the invention. We claim as the invention all embodiments of the invention that come within the scope and spirit of the following claims.

This Sheet Has Been Replaced



We claim:

1. A thermal inkjet printhead (14) for interconnection to a printer (12), comprising:
 - a power interconnection (24) for providing
5 constant power to the printhead;
 - a control interconnection (28) for providing a print command to the printhead;
 - a plurality of heater resistors (44), each operably connected to the constant power
10 interconnection (24); and
 - a switching device (46) for selectively energizing each heater resistor (44) with power from the power interconnection,
each switching device (46) responsive to a
15 print command from the control interconnection (28) for energizing the heater resistor (44).
2. The printhead (14) of claim 1 wherein the switching device (46) is interconnected in a circuit (30) including the heater resistor (44), the power
20 interconnection (24) source and a return path (26) to complete the circuit (30), the switching device (46) switchable between a conductive state and a nonconductive state.
3. The printhead (14) of claim 1 including an
25 energy control circuit (50) for controlling the energy provided to the heater resistor (44).
4. The printhead (14) of claim 1 including an address generating device (34) for receiving the print command and in response generating address signals for
30 the switching devices (46).
5. The printhead (14) of claim 1 wherein the print command includes an address generating signal and a print enable signal, the printhead further including:
 - an address generating device (34) for
35 generating address signals in response to the address generating signal; and



191148



- 15 -

a print control device (40) for applying print enable signals to the switching devices (46),

wherein the switching devices (46) are organized into a matrix (32), one matrix group of
5 switching devices (46) receiving a same print signal and another matrix group of switching devices (46) receiving a same address signal.

6. The printhead (14) of claim 1 wherein the print command includes an address generating signal and
10 a print enable signal, the printhead further including:

a data converter (58) for receiving a print command from the printer (12) and converting the print command into a print enable signal and an address generating signal;

15 an address generating device (34) for generating a pattern of address signals in response to an address generating signal; and

a print control device (40) for applying print enable signals to the switching devices (46).

20 7. A method of selectively energizing heater resistors (44) on a printhead (14) interconnected to a printer (12), comprising:

providing constant power to the heater resistors (44);

25 sending an address signal to a first group of heater resistors (44);

sending a print enable signal to a second group of heater resistors (44); and

30 energizing a heater resistor (44) that receives an address signal and a print enable signal.

8. A thermal inkjet printhead (14) for interconnection to a printer (12), comprising:

a power interconnection (24) for providing power to the printhead;

35 a control interconnection (28) for providing a print enable signal and an address generating signal to the printhead (14);



191148

- 16 -

a plurality of heater resistors (44), each operably connected to the power interconnection (24);

a switching device (46) for selectively energizing the heater resistor (44) with power from the
5 power interconnection (24);

a register (40) for receiving a print enable signal from a control interconnection (28) and applying the print enable signal to a first group of switching devices (46); and

10 an address generating device (34) for receiving an address generating signal from a control interconnection (28) and generating an address signal for a second group of switching devices (46),

each switching device (46) responsive to the
15 address signal and a print enable signal for energizing the heater resistor.

9. The printhead (14) of claim 18 wherein the power interconnection (24) provides constant power to the printhead (14).

20 10. The printhead (14) of claim 18 wherein a single control interconnection (28) provides the address generating signal and the print enable signal.

This Sheet Has Been Replaced



* C L M S *



FIG. 1




FIG. 2






FIG. 3






FIG. 4A




FIG. 4B










FIG. 5





This Sheet Has Been Replaced
 111111 111111 1111 1111




191148

- 17 -

PRINthead WITH REDUCED INTERCONNECTIONS TO A PRINTER**ABSTRACT**

The interconnections (24, 26, 28) for transmitting print commands from a printer (12) to a printhead (14) are reduced by the use of on-printhead circuitry (16, 30). In a basic embodiment, the printhead driver circuitry (16) includes a matrix of drivers (31) controlled by gates, power and control interconnections. Interconnections are reduced by enabling rows and columns of drivers with the power and control interconnections. A multiplexer (70) may also be added to further reduce control interconnections. In an advanced embodiment, the printhead driver circuitry (30) includes a register (40) for converting a serial stream of print enable signals from the printer (12) into a format for applying such signals concurrently to switching devices (46) for one or more heater resistors (44). An address generator (34) on the printhead (14) generates address signals in response to an address generating signal from the printer (12). The printer (12) provides constant power to the printhead (14) so that energizing of the heater resistors (44) is a function of the address and print enable signals and not of the power. Variations on the basic and advanced embodiments are also shown and described.

(Fig. 3)





PRINTHEAD WITH REDUCED INTERCONNECTIONS TO A PRINTER

BACKGROUND OF THE INVENTION

This invention relates generally to thermal inkjet printing. More particularly, this invention relates to a novel printhead design for increasing the number of inkjet nozzles on the printhead while minimizing the number of electrical interconnections between the printer and printhead. The term "printhead" as used herein includes an ink source as well as an ink drop generating mechanism attached to the source and is also known as a cartridge or pen.

Print quality and throughput are important objectives in the design of thermal inkjet printers. Print quality is a function of, among other things, the distance between the inkjet nozzles on the printhead. Higher print quality produces crisper output and more colors through better dithering. Throughput is a function of the width of the printed swath. The wider the swath, the fewer passes the printhead must to print a page.

Both of these objectives can be met by increasing the number of inkjet nozzles on the printhead. By placing nozzles closer together, the print quality can be improved. By placing more nozzles on the printhead, the width of the printing swath is increased. However, adding nozzles requires adding associated drivers, which comprise heater resistors, control logic and power and control interconnections. These interconnections are flexible wires or equivalent conductors that electrically connect the drivers on the printhead to printhead interface circuitry in the printer. They may be contained in a ribbon cable that connects on one end to control circuitry within the printer and on the other end to driver circuitry on the printhead.

Interconnections are a major source of cost in printer design, and adding them to increase the number of drivers increases the cost. Interconnections also affect the reliability of the printer, with more interconnections increasing the likelihood that the printer will fail.

REPLACEMENT SHEET

04 JUL 1996

S-6781233

Thus as the number of drivers on a printhead has increased over the years, there have been attempts to reduce the number of interconnections per driver. One approach that is presently being investigated is called "integrated drive head" or IDH multiplexing. In IDH, the drivers are split into groups known as primitives. Each primitive has its own power supply interconnection ("primitive select") and return interconnection ("primitive return"). In addition, a number of control lines are used to enable particular drivers. These control or address lines are shared among all primitives. This approach can be thought of as an XY matrix where X is the number of primitives (rows) and Y is the number of drivers per primitive (columns). The energizing ("firing") of each driver resistor is controlled by a primitive select and by a transistor such as a MOSFET that acts as a switch connected in series with each resistor. By powering up one or more primitive selects (X1, X3, etc.) and driving the associated gate of the transistor (Y2, for example), multiple heater resistors may be fired simultaneously. The number of interconnections required for such a matrix is fewer than one per driver. This is markedly fewer than in a direct drive approach, wherein each driver has its own primitive select and shares a primitive common with the other drivers.

The matrix approach in IDH multiplexing offers an improvement over the direct drive approach. Yet as presently contemplated the matrix approach has its drawbacks. The primitive select interconnection for each primitive must be driven by a switching power supply that can rapidly switch between on and off states. Such supplies are more expensive and more prone to failure than constant, i.e., static, power supplies. Furthermore, the number of interconnections with such a matrix is still large, on the order of $3\sqrt{n}$, where n is the number of drivers. Thus increasing the number of drivers significantly, even with the matrix, still results in an undesirable increase in the number of interconnections.

SUMMARY OF THE INVENTION

An object of the invention, therefore, is to increase the number of inkjet nozzles on a printhead without increasing the number of interconnections between the printhead and printer.

Another object of the invention is to minimize the number of interconnections required per driver on the printhead.

Yet another object of the invention is to reduce the cost or complexity of printer control circuitry by shifting control functions from the printer to the printhead.

In one embodiment, a printhead according to the invention includes a power interconnection for providing constant power to the printhead and a control interconnection for providing a print command to the printhead. A plurality of heater resistors are each operably connected to the power interconnection. A switching device is also provided for selectively energizing each heater resistor with power from the power interconnection. Each switching device is responsive to a print command from the control interconnection for energizing the heater resistor.

In another embodiment, the printhead includes a plurality of groups of heater resistors and a power interconnection for selectively providing power to each group when the interconnection is enabled. Switching devices are also provided in a plurality of groups for selectively energizing each heater resistor within a group. A control interconnection operates each group of switching devices when the interconnection is enabled. A heater resistor on the printhead is energized if both the power interconnection and control interconnection for the resistor are enabled.

Variations on the inventive printhead include multiplexed interconnections, energy control, gray scale modulation and other features described more particularly below.





The foregoing and other objects, features, and advantages of the invention will become more apparent from the following detailed description of several preferred embodiments as shown in the accompanying drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a block diagram showing a conventional printer and printhead and the interconnections between them.

FIG. 2 is a schematic diagram of a conventional driver matrix in the printhead of FIG. 1.

FIG. 3 is a block diagram of printhead driver circuitry according to the invention.

FIGS. 4A and 4B are diagrams of possible drivers for use in the driver circuitry of FIG. 3.

FIG. 5 is a schematic diagram of one embodiment of the energy control circuit shown in the driver design of FIG. 4B.

FIG. 6 is a schematic diagram of one embodiment of the address generating device shown in FIG. 3.

FIG. 7 is a schematic diagram of one embodiment of the print enable register shown in FIG. 3.

FIG. 8 is a block diagram of another embodiment of the printhead driver circuitry that includes a pulse width modulation (PWM) converter.

FIG. 9 is a schematic diagram of another embodiment of printhead driver circuitry that includes gray scale modulation.

FIG. 10 is a schematic diagram of a multiplexing scheme for reducing the number of control interconnections between the printer and printhead.

DESCRIPTION OF PREFERRED EMBODIMENTS

FIG. 1 shows printhead interface circuitry 10 with an inkjet printer 12 and an IDH inkjet printhead 14. Printing commands are transmitted from the interface circuitry 10, which is conventional in design, to driver circuitry on the printhead 14 through multiple interconnections 18. These interconnections 18 include primitive selects, primitive commons and control

REPLACEMENT SHEET

04 JUL 1996

THIS SHEET HAS BEEN
REPLACED

- 5 - Substitute sheet - 28 June 1996

interconnections. The interconnections 18 are operably connected to the driver circuitry on the printhead 14 through various connecting pads for controlling the energizing of heater resistors.

The Basic Embodiment

FIG. 2 illustrates a driver matrix (rectangular array) within driver circuitry 16 on the printhead 14 for selecting which drivers to fire in response to print commands from the printer. While the matrix will be described in terms of rows and columns, it should be understood that these terms are not meant to imply physical limitations on the arrangement of drivers within the matrix or on the printhead. Drivers may be arranged in any manner so long as they can be identified in the matrix by two enable signals within the print command. Each driver generally comprises a heater resistor (R_h) 20, a switching device 22, a primitive select 24, a primitive common 26 and a control interconnection 28 (parasitic resistances (R_p) are also shown). The switching device 22 is connected in series with the resistor 20 between the primitive select 24 and primitive common 26. The control interconnection 28 is also connected to the switching device 22 for switching the device 22 between a conductive state and a nonconductive state. In the conductive state, the device 22 completes a circuit from the primitive select 24 through the resistor 20 to the primitive common 26 to energize the heater resistor.

Each row of drivers in the matrix is a primitive and may be selectively fired by powering the associated primitive select ("power") interconnection 24, such as PS1 for the top row shown in FIG. 2. To provide uniform energy per heater resistor 20, the parasitic resistances R_p of the primitive select and common interconnections are carefully balanced as shown and only one resistor 20 is energized at a time per primitive. However, any number of the primitive selects may be enabled concurrently. Each enabled primitive select 24 such as PS1, PS2, etc., thus delivers both power and one of the enable signals to the

REPLACEMENT SHEET

04 JUL 1996

driver circuitry 16. The other enable signal for the driver matrix is an address signal provided by each control interconnection 28, such as A1, A2, etc., only one of which is preferably active at a time. Each control interconnection 28 is tied to all of the switching devices 22 in a matrix column so that all such switching devices are conductive when the interconnection is enabled or "active," i.e., at a voltage level which turns on the switching devices 22. Where a primitive select interconnection 24 and a control interconnection 28 for a heater resistor R_p 20 are both active concurrently, that resistor 20 is energized. Alternatively, each matrix column could be a primitive or other defined group of drivers and each row could be a column or other defined group of drivers tied to a single control interconnection 28. "Matrix" as used herein refers to an electrical, not physical, relationship.

The interconnections for controlling the printhead driver circuitry of FIG. 2 include separate primitive select and primitive common interconnections for each primitive and separate control interconnections for each matrix column. A typical driver matrix comprises an array of 8 primitives and 13 columns, requiring 29 interconnections. Increasing the number of drivers to 300 with a similar matrix would only increase the number of interconnections to 49.

The Advanced Embodiment

FIG. 3 shows an advanced embodiment of printhead driver circuitry 30 for minimizing the number of interconnections 24, 26 and 28. Primitive select interconnection 24 and common interconnection 26 provide constant power to an array 32 of drivers 31. "Array," like matrix, as used herein refers to an electrical, not physical, relationship. At a minimum, one of each interconnections 24 and 26 is required for the entire array of drivers, assuming the parasitic resistances R_p in the array 32 are balanced throughout. Because such balancing may be difficult to achieve in practice, it may

REPLACEMENT SHEET

04 JUL 1996



THIS SHEET HAS BEEN
REPLACED

- 7 -

Substitute sheet - 28 June 1996

be desirable to have the array 32 divided into primitives each with interconnections 24, 26 connected in the manner shown in FIG. 2. Alternatively, an energy control circuit may be incorporated into the driver circuitry 30, as will be discussed.

Control interconnection 28 provides a print command from the printer interface circuitry 10 to the driver circuitry 30. The print command includes an address generating signal such as a clock signal and a print enable signal. These two signals may be carried on separate interconnections 28 or combined using known data compression techniques in a signal on a single interconnection, as will be described. Whichever way the two signals arrive at the printhead 14, they are directed to different components of circuitry 30 for selecting one or more drivers 31 from a driver array 32 have n-by-m drivers.

One of these components is an address generator 34 which receives the print command and in response generates a address signals for the drivers 31 of array 32. The address generator 34 has an input for receiving the address generating signal and a plurality of address lines as outputs for transmitting address signals to the drivers of the array 32. Preferably only one of the address lines is active at one time, although it may be possible to have generator 34 produce concurrent address signals if desired. Each of these lines is interconnected to a row of drivers in the array 32 such that each driver in the row receives the address. The address generator 34 may be a state machine, circular shift register or other equivalent device that can receive an address generating signal and in response generate multiple address signals. FIG. 6 shows a shift register embodiment of such a generator 34 comprising a number of D flip flops 36 connected from output to input. The address generating signal in this example is a clock signal 37 within the print command which is applied to a clock input on each of the flip flops 36. The outputs of the generator 34, A(1),

PLACEMENT SHEET

04 JUL 1996

A(2), ..., A(n) are active individually in sequential order. A reset input may also be provided for receiving an reset signal 38 from the printer. A reset of generator 34 to an initial state may be desired at power up of the printer or other appropriate times in the printing process.

Returning to FIG. 3, another of the components of the driver circuitry 30 for selecting a driver 31 to fire is a print control device such as print enable data register 40. Register 40 receives the print command and in response generates one or more print enable signals. The function of these print enable signals is analogous to the enabling function provided by primitive select interconnections 24, 26 in the embodiment of FIG. 2. Specifically, register 40 converts a serial stream of print enable signals it receives from the printer 12 into a format for applying the print enable signals concurrently to one or more columns of drivers in array 32. FIG. 7 shows one embodiment of the register 40 in the form of a serial-to-parallel shift register comprising a row of connected D flip flops 42. The print command data is applied serially to the D input of the first flip flop and clocked through to the output of the mth flip flop, which corresponds to the mth column in the array 32. The outputs of the flip flops 42 are provided in parallel. A clock signal for clocking the D flip flops 42 may be the same clock signal that forms the address generating signal for address generator 34 or may be a separate signal.

The drivers D_{1,1} through D_{n,n} may be constructed in a number of ways. A preferred design is shown in FIG 4A, where each driver 31 comprises a heater resistor 44, an associated switching device 46 such as a MOSFET in series with the resistor, and a logic gate 48 such as a two-input AND gate connected for controlling the switching device 46. The resistor 44 and switching device 46 are operably connected between a power interconnection 24 and a common interconnection 26. The inputs to the gate 48 are an address signal from the generator 34, such as

REPLACEMENT SHEET

04 JUL 1996

signal Ax (where x indicates the xth row of the array 32), and a print enable signal PEy from register 40 (where y represents the yth column of the array 32). The switching device 46 is driven between conductive and nonconductive states by the presence or absence of these two signals at the logic gate 48. Thus in response to a print command from the printer 12 to fire a particular driver, the switching device 46 energizes the associated heater resistor 44 by allowing current to flow from the power interconnection 24 through the resistor to the common interconnection 26.

Of course, it will be appreciated by those skilled in the art that a number of equivalent devices could be substituted for the components described above. For example, in this particular embodiment, a circuit is completed through the heater resistor 44 when the switching device 46 is switched to a conductive state. Alternative arrangements such as switching the device 46 to a nonconductive state are possible.

Driver Circuitry with Energy Control

The number of power interconnections 24, 26 may be reduced to a minimum if the firing energy per resistor can be equalized without the use of primitives in array 32. In the ideal case, the power interconnections could be reduced to one power interconnection 24 and one common interconnection 26. This arrangement would allow more than one driver to be fired per row in the array 32 of FIG. 3 if desired.

To make this possible, a mechanism for controlling the energy provided to each heater resistor 44 is provided. FIG. 4B shows one example of such a mechanism in the form of an energy control circuit 50. The circuit 50 monitors the voltage across each heater resistor 44 and compares the monitored voltage to a reference voltage. The output of that comparison controls the strength of the drive signal applied to the gate of switching device 46 so that the switch is driven to conduct sufficiently to achieve the desired voltage across

REPLACEMENT SHEET

04 JUL 1996

- 10 -

resistor 44. One form of circuit 50 is illustrated in FIG. 5. An instrument amplifier 52 measures the voltage drop across the resistor 44. The magnitude of this voltage is compared at a comparator 54 to a reference voltage REF that is the same reference voltage for each heater resistor 44 in the array 32. The output signal of the comparator 54 is applied to a level shift circuit 56 that shifts the level of voltage applied to the gate of switching device 46 in an appropriate direction. Circuit 50 and several equivalents are more fully shown and described in U.S. Patent No. 5,083,137, commonly owned by the present assignee and hereby incorporated by reference.

Driver Circuitry with Data Decoding and Compression

FIG. 8 is a partial view of the embodiment in FIG. 3 in which a data converter 58 is placed between the interconnections from the printer 12 and the driver circuitry 30. The data converter 58 decodes an encoded electrical signal and, if the data has also been compressed, uncompresses the data as well. Any of a number of encoding schemes maybe used, including but not limited to pulse code modulation, pulse width modulation, run length limited encoding and time division multiplexing. By using such a scheme, the print command may be carried on a single interconnection or at least fewer interconnections than if no encoding is used. Data converter 58, of conventional design, converts the print command into the print enable signal and address generating signal (or address signal if address generation is not performed on the printhead).

Driver Circuitry with Gray Scale Modulation

The intensity of the ink (multi-color or black) printed by the printer 12 is a function of ink drop volume and drop velocity. This intensity can be scaled by varying the control voltage applied to the gate of switching device 46 (or switching device 22 in FIG. 2.)

this voltage controls the amount of energy delivered to the heater resistor by power interconnections 24 and 26,

REPLACEMENT SHEET

04 JUL 1996

PART OF THIS SHEET HAS BEEN
REPLACEDTHIS SHEET HAS BEEN
REPLACED

Substitute sheet - 28 June 1996

- 11 -

as described above. One approach for providing for such gray scale printing is shown in FIG. 9.

A number of analog voltage levels $GL_1, \dots, GL_n$ are generated by an on- or off-printhead voltage reference and are provided as signal inputs to a selection device such as a multiplexer 60 that connects to the input of each switching device 46. PE.LVL is an m bit bus ($m = \log_2 n$) which is connected to the selection inputs of multiplexer 60 and controls the selection of the analog voltage level in the multiplexer. Ax is an address signal to an enable input of multiplexer 60. This scheme requires a group of m bits of print enable data for each row of drivers in array 32. A particular driver fires when its address signal and its PE.LVL bus are both active. The analog voltage GL selected depends upon the data on the PE.LVL print enable bus.

Row Sub-Multiplexing

Referring to FIG. 10, an alternative approach to reducing the interconnections to the printhead 14 is multiplexing the control interconnections to the drivers in the circuitry 16 of FIG. 2. This approach is called "row sub-multiplexing" (RSM). By multiplexing the control interconnections into a square (or nearly square) array, the number of interconnections is twice the number of columns plus twice the square root of the number of rows. With RSM, the total number of interconnections n when optimized is reduced from $3\sqrt{n}$ to $3\sqrt[3]{n}$.

Although the reduction in interconnections with RSM is not as dramatic as in the advanced embodiment and its variations, RSM has advantages in simplicity and the small number of active devices, e.g., transistors, required for implementation. RSM also permits fabricating the required printhead circuitry using a simple NMOS process. For example, the additional number of active devices required for RSM compared to the driver circuit 16 in FIG. 2 is equal to the number of rows in the matrix. Therefore RSM has only a negligible effect on the size of the driver circuit. In fact, depending on the specific

REPLACEMENT SHEET

04 JUL 1996

THIS SHEET HAS BEEN
REPLACED

- 12 - Substitute sheet - 28 June 1996

layout of the driver circuit, RSM may actually reduce the circuit size because of the reduced number of interconnection pads. If RSM is implemented using resistor-transistor logic (RTL) structures as shown in FIG. 10, a simple NMOS process can be used to fabricate the structures.

FIG. 10 shows a simple example of RSM. Structurally, the multiplexer 70 is located on printhead 14 and comprises groups of X and Y inputs serially connected through resistors R_p 71 and logic gates 72. A control line A_i is connected at one location to a node between each resistor R_p and gate 72 and at another location to a switching device 22 within driver circuitry 16. Each input group has a single X input and multiple paths each through a resistor R_p , gate and Y input as desired. The Y inputs are common to multiple groups. A control line A_i is enabled if the X_i input signal is enabled and the Y_i input signal is disabled.

In RSM operation, the control lines $A_1, \dots, A_i$ to the switching devices 22 are sequentially enabled one at a time. To enable line A_1 for example, inputs X_1 and Y_2 are enabled and inputs X_2 and Y_1 are disabled. In similar fashion, control lines $A_2, \dots, A_i$ are sequentially enabled.

The power consumed by the row multiplexer 70 depends inversely on the resistance of resistors R_p . The resistors must have enough resistance that the power consumed does not contribute to excessive printhead temperature, which can degrade print quality. However, the switching time for turning on the drivers 31 within driver circuitry 16 is proportional to the value of the resistors R_p . The desire for low printhead temperature and fast switching time are thus in conflict. One way of reducing switching time, power consumption and temperature is to increase the number of X inputs and decrease the number of Y inputs. But this option increases both the number of interconnections and the number of active devices from the minimum set forth above.

REPLACEMENT SHEET

04 JUL 1996

This Sheet Has Been Replaced



THIS SHEET HAS BEEN
REPLACED

Substitute sheet - 28 June 1996

13

Having described and illustrated the principles of the invention with reference to a preferred embodiment and several variations thereon, it should be readily apparent to those skilled in the art that the embodiment can be modified without departing from such principles. We recognize that the principles of this invention can be applied to a wide variety of equivalent embodiments. For example, the address signals may come directly from the printer over interconnections rather than being generated within driver circuitry 30, if desired. Components such as logic gates 48 and switching devices 46 may be interchanged with analog or software-based equivalent structure such as look up tables, comparison operations, etc. Therefore, the illustrated embodiments should be considered as an examples only of our preferred forms of the invention and not as limitations on the scope of the invention. We claim as the invention all embodiments of the invention that come within the scope and spirit of the following claims.

This Sheet Has Been Replaced



REPLACEMENT SHEET

04 JUL 1996



THIS SHEET HAS BEEN
REPLACED

Substitute sheet - 28 June 1996

- 14 -

We claim:

1. A thermal inkjet printhead (14) for interconnection to a printer (12), comprising:
a power interconnection (24) for providing constant power to the printhead;
a control interconnection (28) for providing a print command to the printhead;
a plurality of heater resistors (44), each operably connected to the constant power interconnection (24); and
a switching device (46) for selectively energizing each heater resistor (44) with power from the power interconnection,
each switching device (46) responsive to a print command from the control interconnection (28) for energizing the heater resistor (44).

2. The printhead (14) of claim 1 wherein the switching device (46) is interconnected in a circuit (30) including the heater resistor (44), the power interconnection (24) source and a return path (26) to complete the circuit (30), the switching device (46) switchable between a conductive state and a nonconductive state.

3. The printhead (14) of claim 1 including an energy control circuit (50) for controlling the energy provided to the heater resistor (44).

4. The printhead (14) of claim 1 including an address generating device (34) for receiving the print command and in response generating address signals for the switching devices (46).

5. The printhead (14) of claim 1 wherein the print command includes an address generating signal and a print enable signal, the printhead further including:
an address generating device (34) for generating address signals in response to the address generating signal; and

REPLACEMENT SHEET

04 JUL 1996

This Sheet Has Been Replaced





THIS SHEET HAS BEEN
REPLACED

Substitute sheet

REPLACEMENT SHEET

28 04 JUL 1996

- 15 -

a print control device (40) for applying print enable signals to the switching devices (46),

wherein the switching devices (46) are organized into a matrix (32), one matrix group of switching devices (46) receiving a same print signal and another matrix group of switching devices (46) receiving a same address signal.

6. The printhead (14) of claim 1 wherein the print command includes an address generating signal and a print enable signal, the printhead further including:

a data converter (58) for receiving a print command from the printer (12) and converting the print command into a print enable signal and an address generating signal;

an address generating device (34) for generating a pattern of address signals in response to an address generating signal; and

a print control device (40) for applying print enable signals to the switching devices (46).

7. A method of selectively energizing heater resistors (44) on a printhead (14) interconnected to a printer (12), comprising:

providing constant power to the heater resistors (44);

sending an address signal to a first group of heater resistors (44);

sending a print enable signal to a second group of heater resistors (44); and

energizing a heater resistor (44) that receives an address signal and a print enable signal.

8. A thermal inkjet printhead (14) for interconnection to a printer (12), comprising:

a power interconnection (24) for providing power to the printhead;

a control interconnection (28) for providing a print enable signal and an address generating signal to the printhead (14);

REPLACEMENT SHEET

04 JUL 1996



* C L M S *

This Sheet Has Been Replaced



REPLACEMENT SHEET

04 JUL 1996

Substitute sheet - 28 June 1996

- 16 -

a plurality of heater resistors (44), each operably connected to the power interconnection (24);

a switching device (46) for selectively energizing the heater resistor (44) with power from the power interconnection (24);

a register (40) for receiving a print enable signal from a control interconnection (28) and applying the print enable signal to a first group of switching devices (46); and

an address generating device (34) for receiving an address generating signal from a control interconnection (28) and generating an address signal for a second group of switching devices (46),

each switching device (46) responsive to the address signal and a print enable signal for energizing the heater resistor.

9. The printhead (14) of claim 18 wherein the power interconnection (24) provides constant power to the printhead (14).

10. The printhead (14) of claim 18 wherein a single control interconnection (28) provides the address generating signal and the print enable signal.



0 JUL 1996

Substitute sheet - 28 June 1996

1/5

FIG. 1





FIG. 2




04 JUL 1996

Substitute sheet - 28 June 1996

2/5

FIG. 3



04 JUL 1996

Substitute sheet - 28 June 1996

3/5

FIG. 4A




FIG. 4B





FIG. 5



04 JUL 1996

Substitute sheet - 28 June 1996

4/5









FIG. 10



**PRINthead WITH REDUCED INTERCONNECTIONS TO A PRINTER****BACKGROUND OF THE INVENTION**

This invention relates generally to thermal inkjet printing. More particularly, this invention
5 relates to a novel printhead design for increasing the number of inkjet nozzles on the printhead while minimizing the number of electrical interconnections between the printer and printhead. The term "printhead" as used herein includes an ink source as well as an ink drop
10 generating mechanism attached to the source and is also known as a cartridge or pen.

Print quality and throughput are important objectives in the design of thermal inkjet printers. Print quality is a function of, among other things, the
15 distance between the inkjet nozzles on the printhead. Higher print quality produces crisper output and more colors through better dithering. Throughput is a function of the width of the printed swath. The wider the swath, the fewer passes the printhead must^{make} to print a page.

20 Both of these objectives can be met by increasing the number of inkjet nozzles on the printhead. By placing nozzles closer together, the print quality can be improved. By placing more nozzles on the printhead, the width of the printing swath is increased. However, adding
25 nozzles requires adding associated drivers, which comprise heater resistors, control logic and power and control interconnections. These interconnections are flexible wires or equivalent conductors that electrically connect the drivers on the printhead to printhead interface
30 circuitry in the printer. They may be contained in a ribbon cable that connects on one end to control circuitry within the printer and on the other end to driver circuitry on the printhead.

Interconnections are a major source of cost in
35 printer design, and adding them to increase the number of drivers increases the cost. Interconnections also affect the reliability of the printer, with more interconnections increasing the likelihood that the printer will fail.

06 AUG 1999

US-A-5006864 describes a thermal inkjet printhead comprising a plurality of resistive heating elements each associated with a corresponding switch in the form of a bipolar transistor. Power is supplied to the printhead by two power rails, the high voltage rail being connected directly to each resistive heating element, whereas the low voltage power rail is indirectly connected to each of the bipolar transistors via one of several field effect transistors.

10 EP-A-0405574 describes an inkjet recording apparatus incorporating an integrated circuit which is ^{integrally} mounted with the recording head. The recording head comprises an array of resistive heating elements each of which is connected in series with a corresponding bipolar transistor which acts as a switch. Selection signals derived in the integrated circuit are supplied to the bipolar transistors so as to select desired resistive heating elements for energization.

It would be desirable to increase the number of inkjet nozzles on a printhead without increasing the number of interconnections between the printhead and printer.

It would further be desirable to minimise the number of printer connections required per driver on the printhead.

It would further be desirable to reduce the cost or complexity of printer control circuitry by shifting control functions from the printer to the printhead.

SUMMARY OF THE INVENTION

In accordance with a first aspect of the present invention, there is provided a thermal inkjet printhead as defined in Claim 1.

30 In accordance with a second aspect of the present invention, there is provided a method of selectively energizing heater resistors as defined in Claim 7.

Variations on the inventive printhead include multiplexed interconnections, energy control, gray scale modulation and other features described more particularly below.

06 AUG 1999

Substitute sheet - 6 August 1999

The foregoing and other ~~objects~~, features, and advantages of the invention will become more apparent from the following detailed description of several preferred embodiments as shown in the accompanying drawings.

5

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a block diagram showing a conventional printer and printhead and the interconnections between them.

FIG. 2 is a schematic diagram of a conventional driver matrix in the printhead of FIG. 1.

FIG. 3 is a block diagram of printhead driver circuitry according to the invention.

FIGS. 4A and 4B are diagrams of possible drivers for use in the driver circuitry of FIG. 3.

FIG. 5 is a schematic diagram of one embodiment of the energy control circuit shown in the driver design of FIG. 4B.

FIG. 6 is a schematic diagram of one embodiment of the address generating device shown in FIG. 3.

FIG. 7 is a schematic diagram of one embodiment of the print enable register shown in FIG. 3.

FIG. 8 is a block diagram of another embodiment of the printhead driver circuitry that includes a pulse width modulation (PWM) converter.

FIG. 9 is a schematic diagram of another embodiment of printhead driver circuitry that includes gray scale modulation.

~~FIG. 10 is a schematic diagram of a multiplexing scheme for reducing the number of control interconnections between the printer and printhead.~~

DESCRIPTION OF PREFERRED EMBODIMENTS

FIG. 1 shows printhead interface circuitry 10 with an inkjet printer 12 and an IDH inkjet printhead 14. Printing commands are transmitted from the interface circuitry 10, which is conventional in design, to driver circuitry on the printhead 14 through multiple interconnections 18. These interconnections 18 include primitive selects, primitive commons and control

06 AUG 1999

interconnections. The interconnections 18 are operably connected to the driver circuitry on the printhead 14 through various connecting pads for controlling the energizing of heater resistors.

5 The Basic Embodiment

FIG. 2 illustrates a driver matrix (rectangular array) within driver circuitry 16 on the printhead 14 for selecting which drivers to fire in response to print commands from the printer. While the matrix will be
10 described in terms of rows and columns, it should be understood that these terms are not meant to imply physical limitations on the arrangement of drivers within the matrix or on the printhead. Drivers may be arranged in any manner so long as they can be identified in the
15 matrix by two enable signals within the print command. Each driver generally comprises a heater resistor (R_h) 20, a switching device 22, a primitive select 24, a primitive common 26 and a control interconnection 28 (parasitic resistances (R_p) are also shown). The switching device 22
20 is connected in series with the resistor 20 between the primitive select 24 and primitive common 26. The control interconnection 28 is also connected to the switching device 22 for switching the device 22 between a conductive state and a nonconductive state. In the conductive state,
25 the device 22 completes a circuit from the primitive select 24 through the resistor 20 to the primitive common 26 to energize the heater resistor.

Each row of drivers in the matrix is a primitive and may be selectively fired by powering the associated
30 primitive select ("power") interconnection 24, such as PS1 for the top row shown in FIG. 2. To provide uniform energy per heater resistor 20, the parasitic resistances R_p of the primitive select and common interconnections are carefully balanced as shown and only one resistor 20 is
35 energized at a time per primitive. However, any number of the primitive selects may be enabled concurrently. Each enabled primitive select 24 such as PS1, PS2, etc., thus delivers both power and one of the enable signals to the

06 AUG 1999

be desirable to have the array 32 divided into primitives each with interconnections 24, 26 connected in the manner shown in FIG. 2. Alternatively, an energy control circuit may be incorporated into the driver circuitry 30, as will
5 be discussed.

Control interconnection 28 provides a print command from the printer interface circuitry 10 to the driver circuitry 30. The print command includes an address generating signal such as a clock signal and a
10 print enable signal. These two signals ^{are} ~~may be carried on separate interconnections 28 or~~ combined using known data compression techniques in a signal on a single
interconnection, as will be described. ~~Whichever way the~~ ^{The} two signals ~~arrive at the printhead 14, they~~ ^{are} directed
15 to different components of circuitry 30 for selecting one or more drivers 31 from a driver array 32 have n-by-m drivers.

One of these components is an address generator 34 which receives the print command and in response
20 generates ~~a~~ address signals for the drivers 31 of array 32. The address generator 34 has an input for receiving the address generating signal and a plurality of address lines as outputs for transmitting address signals to the drivers of the array 32. Preferably only one of the
25 address lines is active at one time, although it may be possible to have generator 34 produce concurrent address signals if desired. Each of these lines is interconnected to a row of drivers in the array 32 such that each driver in the row receives the address. The address generator 34
30 may be a state machine, circular shift register or other equivalent device that can receive an address generating signal and in response generate multiple address signals. FIG. 6 shows a shift register embodiment of such a generator 34 comprising a number of D flip flops 36
35 connected from output to input. The address generating signal in this example is a clock signal 37 within the print command which is applied to a clock input on each of the flip flops 36. The outputs of the generator 34, A(1),

06 AUG 1999

as described above. One approach for providing for such gray scale printing is shown in FIG. 9.

A number of analog voltage levels $GL_1, \dots, GL_n$ are generated by an on- or off-printhead voltage reference and are provided as signal inputs to a selection device such as a multiplexer 60 that connects to the input of each switching device 46. PE.LVL is an m bit bus ($m = \log_2 n$) which is connected to the selection inputs of multiplexer 60 and controls the selection of the analog voltage level in the multiplexer. Ax is an address signal to an enable input of multiplexer 60. This scheme requires a group of m bits of print enable data for each row of drivers in array 32. A particular driver fires when its address signal and its PE.LVL bus are both active. The analog voltage GL selected depends upon the data on the PE.LVL print enable bus.


Row Sub-Multiplexing

Referring to FIG. 10, an alternative approach to reducing the interconnections to the printhead 14 is multiplexing the control interconnections to the drivers in the circuitry 16 of FIG. 2. This approach is called "row sub-multiplexing" (RSM). By multiplexing the control interconnections into a square (or nearly square) array, the number of interconnections is twice the number of columns plus twice the square root of the number of rows. With RSM, the total number of interconnections n when optimized is reduced from $3\sqrt{n}$ to $3^{\frac{1}{3}}n$.

Although the reduction in interconnections with RSM is not as dramatic as in the advanced embodiment and its variations, RSM has advantages in simplicity and the small number of active devices, e.g., transistors, required for implementation. RSM also permits fabricating the required printhead circuitry using a simple NMOS process. For example, the additional number of active devices required for RSM compared to the driver circuit 16 in FIG. 2 is equal to the number of rows in the matrix. Therefore RSM has only a negligible effect on the size of the driver circuit. In fact, depending on the specific

06 AUG 1999

Having described and illustrated the principles of the invention with reference to a preferred embodiment and several variations thereon, it should be readily apparent to those skilled in the art that the embodiment
5 can be modified without departing from such principles. We recognize that the principles of this invention can be applied to a wide variety of equivalent embodiments. ~~For example, the address signals may come directly from the printer over interconnections rather than being generated~~
10 ~~within driver circuitry 30, if desired.~~ Components such as logic gates 48 and switching devices 46 may be interchanged with analog or software-based equivalent structure such as look up tables, comparison operations, etc. Therefore, the illustrated embodiments should be
15 considered as an examples only of our preferred forms of the invention and not as limitations on the scope of the invention. We claim as the invention all embodiments of the invention that come within the scope and spirit of the following claims.



CLAIMS:

1. A thermal inkjet printhead (14) for interconnection to a printer (12), comprising:

a power interconnection (24) for providing constant power to the printhead (14);

a plurality of heater resistors (44), each operably connected to the constant power interconnection (24);

a plurality of switching devices (46), each-switching device of the plurality of switching devices associated with a respective heater resistor (44), for selectively energizing the heater resistors (44) with power from the power interconnection (24); and

a single control conductor (28) for providing a print command to the printhead (14), the print command including both an address signal (Ax) specifying a first predetermined portion of at least two but fewer than all of the plurality of switching devices (46) and a print enable signal (PEy) specifying a second predetermined portion of at least two but fewer than all of the plurality of switching devices (46), whereby

each of the switching devices (46) energizes its associated heater resistor (44) when both an address signal and a print enable signal are present for a switching device (46) which is a member of both the first portion and the second portion of switching devices (46).

2. The printhead (14) of Claim 1, wherein a switching device (46) is interconnected in a circuit (30) including a heater resistor (44), the power interconnection (24) source and a return path (26) to complete the circuit (30), the switching

06 AUG 1999

device (46) switchable between a conductive state and a nonconductive state.

3. The printhead (14) of Claim 1, including an energy control circuit (50) for controlling the energy provided to each heater resistor (44).

4. The printhead (14) of Claim 1, wherein the address signal within the print command includes an address generating signal and the printhead (14) includes an address generating device (34) for receiving the address generating signal and in response generating address signals for the switching devices (46).

5. The printhead (14) of Claim 1, wherein the print command includes an address generating signal and a print enable signal, the printhead further including:

an address generating device (34) for generating address signals in response to the address generating signal; and

a print control device (40) for applying print enable signals to the switching devices (46),

wherein the switching devices (46) are organized into a matrix (32), one matrix group of switching devices (46) receiving a same print signal and another matrix group of switching devices (46) receiving a same address signal.

6. The printhead (14) of Claim 1, wherein the print command includes an address generating signal and a print enable signal, the printhead further including:

a data converter (58) for receiving a print command from the printer (12) and converting the print command into a print enable signal and an address generating signal;



06 AUG 1999

an address generating device (34) for generating a pattern of address signals in response to an address generating signal; and

a print control device (40) for applying print enable signals to the switching devices (46).

7. A method of selectively energizing heater resistors (44) on a printhead (14) interconnected to a printer (12), comprising:

providing constant power to the printhead (44);

connecting a plurality of heater resistors (44) to the provided constant power (24);

providing a plurality of switching devices (46), each switching device of the plurality of switching devices being associated with a respective heater resistors (44), for selectively energizing the heater resistors (44) with power from the power interconnection; and

coupling a print command to the printhead (14) via a single control conductor (28), the print command including both an address signal (Ax) specifying a first predetermined portion of at least two but fewer than all of the plurality of switching devices (46) and a print enable signal (PEy) specifying a second predetermined portion of at least two but fewer than all of the plurality of switching devices (46), whereby each of the switching devices (46) energizes its associated heater resistor (44) when both an address signal and a print enable signal are present for a switching device (46) which is a member of both the first portion and the second portion of switching devices (46).



* C L M S *