

Description

This invention relates to apparatus for reducing the effect of timing errors in video processing circuitry, and may be used, for example, to reduce the visibility of timing errors in the inset image of a picture in picture (PIP) television display system.

In a PIP system, two images from possibly unrelated sources are displayed simultaneously as one image. The composite image includes a full size primary image and a reduced size secondary image displayed as an inset. The subjective quality of the inset portion of the composite image may be affected by timing errors in either the primary or secondary signals.

The timing errors relevant to the present invention occur when either the primary or secondary signal is a nonstandard signal. As used in this application, the term nonstandard signal means a video signal having a horizontal line period which may vary in width by, for example, 4ns or more from the horizontal line period set by the signal standard to which the video signal nominally conforms (e.g. NTSC, PAL, or SECAM).

To understand how these timing errors may affect the inset image, it is helpful to know how the secondary signal is processed and displayed. In a conventional PIP display system, the secondary signal is sampled at instants determined by a sampling clock signal which, desirably, bears a fixed relationship to the horizontal line scanning frequency of the secondary signal. To aid separation of the luminance and chrominance components of color television signals, the sampling clock signal has a frequency that is a multiple of the chrominance subcarrier frequency which is itself a harmonic of one-half the horizontal line scanning frequency. This sampling clock signal may be developed by a phase locked loop which locks the clock signal to the color reference burst component of the composite video signals.

The secondary signals are separated into their component parts, generally a luminance signal and two color difference signals, and then subsampled both vertically and horizontally to develop signals which represent a reduced-size image. The lines of samples taken during one field of the secondary signal are stored in a memory. These samples are then read from the memory for display using a clock signal which is desirably related to the horizontal line scanning frequency of the primary signal.

When the secondary signal originates from a video tape recorder (VTR), video disk player or home computer, the frequency of the color burst signal may be relatively stable while the frequency of the horizontal line scanning signal may vary significantly from line to line. This variation may be caused by stretching of the tape, defects in the disk, motor speed variations in either the VTR or disk player, or inaccuracies in the frequencies used by the home computer. Since the sampling clock signal is locked to the burst signal, corresponding sampling points on successive lines may be shifted or skewed relative to each other. When these lines of samples are displayed in synchronism with the primary signal, the corresponding samples do not line up vertically. Consequently vertical lines in the inset image may appear jagged. If the timing errors randomly change the period of the horizontal sync signal, or tilted if there is a fixed error in the horizontal sync period. Assuming a 3:1 reduction in the secondary image, a timing difference of 12ns or more in successive horizontal line periods of the secondary signal may produce noticeable skew distortion in the inset image.

Timing errors in the primary signals change the relative time difference between primary horizontal sync pulses, which define the edges of the primary image, and the first samples in lines of the inset image. Primary signal timing errors that cause the periods of successive horizontal sync pulses to vary from the applicable signal standard by 4ns or more may produce noticeable skew distortion in the inset image. This distortion causes the entire inset image to appear jagged or tilted.

To gain a better understanding of skew and the methods which may be used to compensate for it, consider the waveforms shown in FIGURE 1. The waveform A represents a portion of one horizontal line of, e.g. luminance signal, including the horizontal synchronizing pulse (note the waveforms of FIGURE 1 are not drawn to scale). Waveforms B, C and C' represent sampling (system) clock waveforms. The pulses of waveform B are assumed to occur at the points in time that a subcarrier locked clock, locked to a standard signal, would occur. Put another way, if waveform A corresponds to n lines of an image, then waveform B represents the desired sampling (system) clock for each successive line, i.e. without skew. A clock signal having constant skew may also be desirable. In either a zero skew or a constant skew system, the sampling clock pulse r always occurs at the same point in time relative to the HSYNC pulse. This point in time is represented by the sample S2 on waveform A. Waveform C represents a subcarrier locked clock which exhibits a degree of skew. The number of pulses per line period contained in waveform C may not be constant from line-to-line. Generally, the difference in the number of whole clock pulses in a line period can be compensated for in the phase locked loop which generates the horizontal synchronizing signal. The sampling phase error (skew) which is a fractional portion of a clock period, however, may only be corrected by operation on the samples themselves or on the sampling clock signal.

The present invention is embodied in apparatus which compensates for timing errors in a first video signal relative to a second, stored video signal. This apparatus includes circuitry for measuring the time interval between a horizontal synchronizing pulse of the first signal and a pulse of the clock signal which controls the retrieval of the second signal. The apparatus further includes circuitry which changes the timing of the second signal relative to the horizontal sync component of the first signal, to compensate for any variations in the measured time intervals from line-to-line.

One method of correction is to adjust the sample values on a line-by-line basis so that the adjusted samples conform to samples that would be taken by a clock with zero skew or with some constant skew. For example, the sample values generated by the clock signal of waveform C may be adjusted to equal or approximate corresponding sample values that would be generated by the clock signal of waveform B. In the FIGURE 1, clock pulse r' of waveform C is assumed to correspond to clock pulse r of waveform B. Clock pulse r' is advanced in time or skewed by one-half of one clock period, TS , with respect to clock pulse r . Clock pulse r' generates a sample value $S1$. Desirably, clock pulse r' should occur coincident with clock pulse r and generate the sample value $S2$.

Replacing the sample taken coincident with clock pulse r' with a sample having a value approximately equal to $S2$ effectively advances the timing of the signal taken with the sampling clock signal C so that it matches the signal which would have been taken had the zero-skew sampling clock signal B been used. Neglecting the complications of chrominance decoding, an alternative method of skew correction is to adjust the phase of the sampling clock signal on a line-by-line basis so that it approximately matches the phase of the desired clock signal B or some other clock signal which exhibits equal skew from line to line. The waveform C' represents the clock signal C delayed an amount of time substantially equal to the skew. Samples taken with this delayed clock signal approximate samples taken with the desired clock signal, B.

The first skew correction method may be used to correct skew errors in the secondary signal since it does not affect the phase of the sampling clock signal. It is recalled that the phase of this clock signal cannot be changed without affecting the processing of the secondary chrominance signal components. The second skew correction method may be used to compensate for skew errors in the primary signal when the samples representing the separated luminance and color difference signal components of the secondary image are retrieved from the secondary field memory for display.

In the accompanying drawings:

FIGURE 1 is a timing diagram useful in describing skew and methods of skew correction.

FIGURE 2 is a block diagram of a PIP television display system incorporating the present invention.

FIGURE 3 is a block diagram of a digital PIP television display system incorporating the present invention.

FIGURES 4 and 5 are a block diagrams showing skew correction circuitry which may be used in the display devices shown in FIGURES 2 and 3.

FIGURE 6 is a block diagram of alternative skew correcting apparatus which may be used in the display devices shown in FIGURES 2 and 3.

In the drawings, broad arrows represent busses for multiple-bit parallel digital signals and line arrows represent connections carrying analog signals or single bit digital signals. Depending on the processing speed of the devices, compensating delays may be required in certain of the signal paths. One skilled in the art of digital signal processing circuit design would know where such delays would be needed in a particular system.

FIGURE 2 is a block diagram of a PIP display device in which the primary signal is processed using conventional analog apparatus and the secondary signal is processed digitally. This circuitry uses a single clock signal, synchronized to the secondary burst signal, both for sampling and processing the secondary signal and for displaying the secondary image as an inset in the main image.

A source of primary composite video signals 10 applies the primary video signals to a Y/C separation filter 12. Filter 12, which may include conventional low-pass and high-pass filters, separates the composite video signals into primary luminance signals, Y_p , and primary chrominance signals C_p . The primary luminance and chrominance signals are applied to a primary chroma/luma processor 14 which may include, for example, band shaping filters for peaking the high frequency components of the luminance signals to develop a signal Y'_p and a chrominance signal demodulator for deriving the baseband color difference signals $(R-Y)_p$ and $(B-Y)_p$ from the primary chrominance signals, C_p . The signals Y_p , $(R-Y)_p$, and $(B-Y)_p$ are applied to a matrix 16 which combines the signals to develop the color signals R_p , G_p and B_p . These signals are applied to one set of signal input terminals of an analog multiplexer 26, the output of which drives a cathode ray tube (CRT) 28. The color signals R_s , G_s and B_s developed from the secondary signal

are applied to a second set of signal input terminals of the multiplexer 26. These signals are developed by apparatus described below.

A source of secondary composite video signals 50, which may include the tuner, IF amplifier and video detector of a conventional color television receiver, provides secondary composite video signals to an analog-to-digital converter (ADC) 52. ADC 52 samples and digitizes the secondary composite video signals at instants determined by the sampling clock signal CK. A phase-locked-loop (PLL) 56, described below, generates the signal, CK, which has a frequency $4f_c$ substantially equal to four times the chrominance subcarrier frequency, f_c . The signal CK is phase locked to the color synchronizing burst component of the secondary video signals.

ADC 52 provides digitized secondary video signals to a Y/C separation filter 54. Filter 54 may be a conventional digital filter having a clock input terminal coupled to receive the signal CK. Filter 54 may include, for example, an FIR filter which passes the chrominance signal components of composite video signal to the relative exclusion of luminance signal components and a subtractor for subtracting the chrominance signal components from the composite signal to develop luminance signal components.

ADC 52 also provides secondary composite video signals to a deflection processing unit (DPU) 60, which includes sync separator circuitry 58 and skew error measuring circuitry 59. The sync separator circuitry 58 and skew measuring circuitry 59 in the illustrated embodiment are components in a phase-locked-loop which produces a horizontal synchronizing signal, SHS, that is phase-locked to the horizontal synchronizing signal component of the secondary signal. Sync separator circuitry 58 applies the signal SHS and a digital value (HSP) containing an integer part and a fractional part representing the period of the signal SHS in units of one-sixteenth of the sampling clock period ($1/16 T_s$). The sync separator circuitry 58 also develops the vertical synchronization signals, SVS, and a burst gate signal, BG, from the digitized secondary composite video signals. The burst gate signal, BG, and the separated chrominance signals from filter 54 are applied to PLL 56. PLL 56 is, for example, a circuit similar to that described in U.S. Patent US-A-4,291,332 entitled "Phase Locked Circuit" which is hereby incorporated by reference.

The clock signal CK and the secondary horizontal sync signal SHS are applied to the skew measuring circuitry 59. Exemplary skew measuring circuitry 59 accumulates the fractional part of the horizontal skew period values, HSP, provided by the sync separator circuitry 58 to develop a secondary skew signal, SSK. The integer part of the signal SSK is fed back to the sync separator circuitry 58, where it is used in the phase-locked-loop to update the horizontal sync period measurement. The fractional part of the signal SSK is retained in the accumulator of the skew measuring circuitry 59 and applied as skew values to the skew correcting circuitry 62. As used in the present embodiment, the fractional part of the signal SSK represents the time interval between the center of the respective phase locked horizontal sync pulse and the leading edge of the clock pulse which occurs immediately before the center of the respective horizontal sync pulse. This interval is measured with a resolution substantially equal to one-sixteenth of the period of the signal CK. The sync separator circuitry 58 and the skew measuring circuitry 59 can be the type contained in the integrated circuit DPU 2532 manufactured by ITT Intermetall GmbH and which is described at pages 47-72 of the data book "Digit 2000 NTSC Double-scan VLSI Digital TV System" edition 1985/5 of ITT Intermetall, Freiburg, W. Germany.

Exemplary skew error correcting circuitry 62 is shown in FIGURE 4. This circuitry interpolates between successive input samples to provide output samples that are substantially equivalent to the samples which would have been taken synchronous with a sampling clock signal having zero skew. The circuitry shown in FIGURE 4 may be divided into two parts, a linear interpolator and a correction circuit. Luminance samples Y_s are applied to a delay element 410, which delays the samples by one period of the clock signal CK. The delayed samples are applied to a multiplier 412 which scales the samples by a factor K. The factor K may be a value between zero and one and is provided by a read only memory (ROM) 424 in response to the secondary skew signal SSK. Luminance samples Y_s are also applied to a multiplier 414 which scales these undelayed samples by a factor $1-K$, also provided by ROM 424. The samples provided by the multipliers 412 and 414 are summed in adder 416.

The samples provided by adder 416 are linearly interpolated samples. If the frequency components of the sampled signals Y_s are an order of magnitude or more lower than the sampling frequency, the apparent delay of the interpolated samples is given by the product KT_s , where T_s is the period of the sampling clock signal CK. As the frequency components of the sampled signals approach the sampling frequency, however, the amount by which Y_s appears to have been delayed becomes a function of the levels of its higher frequency components as well as of K. The correction circuit, which includes filter 422, multiplier 428 and adder 420 compensates for the frequency induced delay components. Luminance signals Y_s are applied to the filter 422 which has the transfer function $T_{422} = -1 + Z^{-1} + Z^{-2} - Z^{-3}$ expressed in Z transform notation. The samples provided by filter 422 are scaled by a factor C in multiplier 428. The factor C is

provided by ROM 424 in response to the secondary skew signal, SSK. The samples developed by adder 416 are applied to a delay element 418 which compensates for the processing time through filter 422. These delayed samples are then added to the samples from multiplier 428 by an adder 420.

The combination of the linear interpolator and the correcting filter produce signals having an apparent delay of $(1+K)T_s$ where the signals to be delayed have components with frequencies as high as one-third of the frequency of the sampling clock signal. In the NTSC system, for example, where the sampling clock frequency is approximately 14.3 MHz this skew correcting circuit provides uniformly spaced delays for luminance signals which may have frequency components up to 4.2 MHz. TABLE I defines the contents of ROM 424 to achieve delay steps of one-sixteenth of a sampling clock period.

TABLE I

					DELAY	TOTAL
	<u>SSK</u>	<u>K</u>	<u>1-K</u>	<u>C</u>	<u>CHANGE</u>	<u>DELAY</u>
15	15	1/16	15/16	1/32	$T_s/16$	$17T_s/16$
	14	2/16	14/16	1/32	$2T_s/16$	$18T_s/16$
	13	3/16	13/16	2/32	$3T_s/16$	$19T_s/16$
20	12	4/16	12/16	2/32	$4T_s/16$	$20T_s/16$
25	11	5/16	11/16	2/32	$5T_s/16$	$21T_s/16$
	10	6/16	10/16	3/32	$6T_s/16$	$22T_s/16$
	9	7/16	9/16	3/32	$7T_s/16$	$23T_s/16$
30	8	8/16	8/16	3/32	$8T_s/16$	$24T_s/16$
	7	9/16	7/16	3/32	$9T_s/16$	$25T_s/16$
	6	10/16	6/16	3/32	$10T_s/16$	$26T_s/16$
35	5	11/16	5/16	3/32	$11T_s/16$	$27T_s/16$
	4	12/16	4/16	2/32	$12T_s/16$	$28T_s/16$
	3	13/16	3/16	2/32	$13T_s/16$	$29T_s/16$
	2	14/16	2/16	1/32	$14T_s/16$	$30T_s/16$
40	1	15/16	1/16	1/32	$15T_s/16$	$31T_s/16$
	0	1	0	0	T_s	$2T_s$

The samples provided by this skew correcting circuit 62 have apparent delays of between $17T_s/16$ and $2T_s$. The delay is only apparent because the actual timing of the samples has not been changed. The skew correcting circuit 62 adjusts the sample values in each line of secondary luminance signals so they appear to have been generated using a sampling clock signal which had negligible skew.

The chrominance samples provided by Y/C separation filter 54 are applied to delay element 63 which provides a two sample period delay to compensate for the delay through the skew correcting circuitry 62. Because the chrominance signal has a smaller bandwidth than the luminance signal and because the eye is less sensitive to color transitions than to changes in brightness, skew errors in the chrominance signal are not as noticeable as skew errors in the luminance signal. Accordingly, the apparatus shown in FIGURE 1 does not correct skew errors in the chrominance signal. It will be appreciated, however, that delay element 63 may be replaced with a skew correcting circuit similar to circuit element 62.

The luminance samples from skew correcting circuitry 62 and the chrominance samples from delay element 63 are applied to a secondary chroma/luma processor 64. Processor 64 may include, for example, an FIR band shaping filter for peaking the frequency spectrum of the digital luminance signals to provide a

modified secondary luminance signal Y_s' and a digital chrominance demodulator for developing samples which represent the baseband secondary color difference signals $(R-Y)_s$ and $(B-Y)_s$.

The signals y_s' , $(R-Y)_s$ and $(B-Y)_s$ are applied to PIP field memory 68 where they are subsampled and stored under control of the write address generator circuitry 70. Memory 68 may be a conventional random access memory having a sufficient number of storage cells to hold one field of the subsampled secondary signal. This memory may be organized as three separate field memories, one for the luminance signal and one for each of the two color difference signals, or it may be organized as a single field memory with the sampled luminance and color difference signals combined into a single sampled signal. For example, these signals may be combined by alternately concatenating samples of the two color difference signals to samples of the luminance signal.

Data from the secondary chroma/luma processor 64 is written into the field memory 68 under control of the memory address generator circuitry 70. The circuitry 70 develops write address signals, WADDR, and other control signals WCS, as may be needed from the clock signal CK, and the secondary vertical and horizontal sync signals SVS and SHS respectively. The write address generator circuitry 70 operates to subsample the secondary signal in, for example, a three-to-one ratio both vertically and horizontally by providing address values and control signals for the memory 68 at appropriate times.

Samples representing lines of the subsampled secondary image are read from the PIP field memory 68 under control of the read address generator circuitry 24. The signals applied to circuitry 24 are the primary vertical and horizontal sync signals, PVS and PHS respectively, and a skew corrected clock signal CK'. The circuitry 24 may for example, count pulses of the horizontal sync signal, PHS, relative to the vertical sync pulses, PVS, and pulses of the signal CK' relative to the primary horizontal sync pulses to determine when to initiate read operations for the memory 68 and when to switch the multiplexer 26 between providing primary and secondary drive signals to the display device 28. Read address generator 24 provides a read address signal, RADDR, and read control signals RCS, to the field memory 68 and a primary/secondary image selection signal, P/S to the multiplexer 26.

The write address generator circuitry 70, read address generator circuitry 24 and field memory 68 are known per se and, so, are not described in detail. Exemplary circuitry for subsampling, storing, and retrieving the signal which produces the insert image is described in the U.S. Patents US-A-4,249,213 entitled "Picture-in-Picture Television Receiver" and US-A-4,139,880 entitled "Television Receiver Equipped for Simultaneously Showing Several Programs."

The Read address generator 24, it is recalled, operates in synchronism with the skew corrected clock signal CK'. This signal is generated as follows. Primary composite video signals from source 10 are applied to an ADC 17 which is clocked by the signal CK provided by the PLL 56. ADC 17 applies the sampled primary composite video signals to a DPU 20. DPU 20, which includes sync separator 18 and skew measuring circuitry 19 may be identical to the DPU 60 described above. The sync separator 18 develops the primary vertical sync signal, PVS, and the primary horizontal sync signal, PHS, from the primary composite video signals. The signal PHS, the horizontal sync period value HSP, and the clock signal CK are applied to the skew measuring circuitry 19. Circuitry 19 is functionally identical to the skew measuring circuitry 59 described above. It measures the time difference between the center of each pulse of the signal PHS and the leading edge of the immediately preceding pulse of the clock signal CK. The fractional part of the signal, PSK, provided by the skew measuring circuitry 19 is a four bit value indicating the skew for each primary horizontal scan line in units of one-sixteenth of the period of the clock signal CK. The integer part of the signal PSK is applied to the sync separator 18 as set forth above in reference to DPU 60. The fractional part of the signal PSK and the signal CK are applied to the skew correcting circuitry 22. Circuitry 22 may be a programmable delay element similar to that shown in Figure 5.

In Figure 5, the clock signal CK is applied to the input terminal of an inverter I_1 which is the first inverter in a chain of thirty series-connected inverters. The inverter chain is organized as fifteen pairs of inverters, I_1 and I_1' through I_{15} and I_{15}' . The input terminal to the inverter I_1 and the output terminals of all of the pairs, i.e. I_1' , I_2' ... I_{15}' are connected to respectively different data input terminals of the multiplexer 500. The control input port of multiplexer 500 is coupled to receive the fractional part of the primary skew signal, PSK, provided by the skew measuring circuitry 19. Each pair of inverters in the chain has a signal propagation delay of approximately one-sixteenth of the period of clock signal CK so the output terminals of each of the pairs provide clock signals delayed by between one-sixteenth and fifteen-sixteenths of a clock period. The multiplexer 500 is conditioned by the fractional part of the signal PSK to provide, as its output signal CK', the signal CK when PSK is zero, the signal at the output terminal of inverter of I_1' when PSK is one, the signal at the output terminal of inverter I_2' when PSK is two, and so on, providing the signal at the output terminal of inverter I_{15}' when PSK is fifteen. Accordingly, the signal CK' provided by the skew correcting circuitry 22 is a clock signal CK delayed by an amount of time approximately equal to the value

of the fractional part of PSK times one-sixteenth of the period of the signal CK. As set forth above, in reference to Figure 1, this signal is a skew corrected clock signal, which is to say a clock signal aligned with the horizontal sync signal PHS from line-to-line.

The samples provided by the memory 68 in synchronism with the skew corrected clock signal CK' are applied to a digital-to-analog converter (DAC) 72 which is clocked by the skew corrected clock signal CK'. DAC 72 provides analog signals representing the secondary luminance and (R-Y) and (B-Y) color difference signals to the matrix 74. Matrix 74 is a conventional analog matrix which converts secondary luminance and color difference signals into the color signals R_s, G_s, and B_s for application to the multiplexer 26 as set forth above.

The analog multiplexer 26 is controlled by the image selection signal P/S provided by the read address generator 24 to apply either primary or secondary signals to the display device 28 to develop composite PIP images.

FIGURE 6 is a block diagram showing alternative circuitry to correct for skew in the primary signal. This embodiment uses an interpolation scheme which is the same as is used to correct for the skew of the secondary signal. The read address generator circuitry 24' is clocked by the signal CK but is otherwise the same as the circuitry 24 described in reference to FIGURE 2. From the clock signal CK and the primary horizontal and vertical sync signals PHS and PVS, read address generator circuitry 24' develops the read address signal RADDR and the read control signals RCS which control the reading of the subsampled secondary luminance and color difference signals from the PIP field memory 68. The luminance samples, Y_{ss}, are applied to skew correcting circuitry 22' which is responsive to the fractional part of the signal PSK. Circuitry 22' may be identical to the skew correcting circuitry 62 described above in reference to FIGURE 2. Circuitry 22' interpolates between successive ones of the samples Y_{ss} to provide samples having values representing a signal delayed by the skew value. In other words, substantially the same signal as would be represented by the samples read from the memory in synchronism with a skew corrected clock signal. The luminance samples developed by the skew correcting circuitry 22' are applied to a DAC 72'. The (R-Y) and (B-Y) color difference samples provided by the field memory 68' are applied to the DAC 72' via the compensating delay elements 602 and 604 respectively. Delay elements 602 and 604 compensate for processing delay in the skew correcting circuitry 22'. As set forth in reference to the skew correcting circuitry 62, only the luminance signals need skew correction since the eye is less sensitive to changes in color than to changes in brightness. Nonetheless, it is contemplated that the delay elements 602 and 604 may be replaced by skew correcting circuitry similar to the circuitry 22' if skew correction of the color difference samples is found to be desirable. The DAC 72' is clocked by the uncorrected clock signal CK but is otherwise the same as the DAC 72 described with reference to FIGURE 2. DAC 72' provides analog luminance and color difference signals representing the reduced secondary signal to the matrix 74.

FIGURE 3 is a block diagram of an alternative embodiment of the invention in which both the primary and secondary signals are processed digitally. A single clock signal, PCK, which is phase locked to the primary color synchronizing burst signal, is used for both the primary and secondary processing circuitry. Since the secondary signals are sampled by a clock which is not phase locked to the secondary color burst signal, this embodiment of the invention includes circuitry to adjust the phase of the secondary chrominance signals to ensure proper color reproduction.

In the PIP system shown in FIGURE 3, analog composite video signals from a source of primary composite video signals 310 are applied to an ADC 317. ADC 317 is responsive to the primary burst locked clock signal PCK to provide digital samples representing the analog primary video signals. These samples are applied to a Y/C separation filter 312 and to the DPU 320. DPU 320 is, for example, identical to the DPUs 20 and 60 described above. It provides the primary vertical and horizontal synchronization signals, PHS and PVS, a primary burst gate signal, PBG, and a signal, PSK, representing the skew of the clock signal, PCK, relative to the primary horizontal sync signal, PHS, as a proper fraction of the clock period. The Y/C separation filter 312, which may be identical to the filter 54, separates the luminance and chrominance components from the primary composite video signals.

The primary chrominance signals from filter 312 and the burst gate signal PBG from sync separator 318 are applied to the PLL 321. PLL 321, which may contain circuitry identical to that used by the PLL 56, generates the clock signal PCK having a frequency of substantially 4f_c that is phase-locked to the color burst component of the primary signal.

The primary luminance and chrominance signal components are applied to the primary chroma/luma processor 314. Chroma/luma processor 314 provides processed luminance signals and (R-Y) and (B-Y) color difference signals to the DAC 315. DAC 315 converts the digital luminance and color difference signals into analog form and applies the analog signals to an RGB matrix 316. Matrix 316 develops the red, green, and blue color signals which represent the primary image, and applies them to a first set of signal

input terminals of a multiplexer 326. Multiplexer 326, selects between the color signals representing the primary image and color signals representing the secondary image, which are applied to a second set of signal input terminals, to drive the display device 328. Apparatus which generates the color signals for the secondary image and which generates the selection signal, P/S, for the multiplexer 326 is described below.

5 Analog composite video signals from a source of secondary composite video signals 350 are applied to an ADC 352. ADC 352 is responsive to the primary sampling clock signal PCK for providing samples representing secondary composite video signals to the Y/C separation filter 354 and to the DPU 360. DPU 360, for example, is identical to the DPUs 20 and 60 described above. It provides the secondary horizontal and vertical synchronization signals, SHS and SVS respectively, a secondary burst gate signal SBG, and a
10 signal, SSK, representing the skew of the clock signal PCK relative to the secondary horizontal sync signal SHS as a proper fraction of the clock period.

Y/C separation filter 354, separates the secondary composite video samples into a luminance signal component and a chrominance signal component. The luminance signal component and the signal SSK from skew measuring circuitry 359 are applied to skew correcting circuitry 362. The circuitry 362 may be
15 identical to the circuitry described with reference to FIGURE 4. It produces luminance samples having equal skew from line-to-line relative to the secondary horizontal sync signal SHS. These samples are applied to the secondary chroma/luma processor 364. The chrominance samples from filter 354 are applied to the processor 364 via the delay element 363. Delay element 363 compensates for the processing delays incurred by the luminance samples in the skew correction circuitry 362 by delaying the chrominance
20 samples by two sample periods.

The secondary luma/chroma processor 364 processes the luminance signal and demodulates the chrominance signal into two quadrature phase related color difference signals. In this instance, however, the color difference signals provided by the processor 364 may not be (R-Y) and (B-Y) signals. The demodulator in the chroma/luma processor 364 will provide (R-Y) and (B-Y) signals only when the sampling
25 clock signal has a frequency of $4f_c$ and is phase locked to the color burst component of the secondary signal. In this embodiment, the sampling clock signal used to develop the secondary samples is phase locked to the primary color burst component. Since the primary and secondary signals may be from different sources, there may be phase and frequency differences between their respective color burst signals. Consequently, there may be phase errors in the demodulated color difference signals provided by
30 the processor 364 relative to the (R-Y) and (B-Y) phases of the secondary signal. The present embodiment includes chrominance phase error correction circuitry 365 to detect and correct phase errors in the color difference signals provided by processor 364. This circuit is not a part of the present invention. Suitable circuitry 365 may be built by one skilled in the art from the teachings of U.S. Patent US-A-4,558,348, issued December 10, 1985, entitled "Digital Video Signal Processing System Using Asynchronous A-to-D Encod-
35 ing." Briefly, the circuitry 365 converts the two color difference signals into a phase angle signal and an amplitude signal. The phase signal is compared against a reference phase during the secondary burst interval. The difference between the burst phase and the reference phase is used to correct the phase and amplitude signals in a closed loop control system. The corrected phase and amplitude signals are then processed to develop at least two color difference signals (e.g. (R-Y) and (B-Y)).

40 The phase corrected color difference signals provided by the circuitry 365 and the luminance signal provided by processor 364 via compensating delay element 367 are applied to the PIP field memory 368. The PIP field memory 368, memory write address generator circuitry 370 and memory read address generator circuitry 324 may be similar to the respective field memory 68, and memory write and read address generator circuitry 70 and 24 of FIGURE 2. The circuitry 370 and 324 are responsive to the clock
45 signal PCK and skew corrected clock signal PCK' respectively, but otherwise operate identically to the circuitry described above.

The skew corrected clock signal PCK' is developed by the skew correction circuitry 322. Circuitry 322, which may be similar to the circuitry 22, delays the clock signal PCK by the measured skew value times one-sixteenth of the period of PCK, to produce a skew corrected clock signal PCK'. It is contemplated that
50 circuitry configuration similar to that shown in FIGURE 6 may be used, in place of the skew correcting configuration using circuitry 22;322, to correct for the skew of the primary signal.

The samples provided by the PIP field memory 368 under control of the memory output address and timing control circuitry are applied to a DAC 372. DAC 372, synchronous with the skew corrected clock signal PCK', develops analog luminance and (R-Y) and (B-Y) color difference signals representing the
55 secondary image and applies these samples to the matrix 374. Matrix 374 converts these luminance and color difference signals into red, green and blue color signals. These color signals, which represent the secondary image, are applied to the second set of signal input terminals of the analog multiplexer 326 as described above.

Although the embodiments described above use digital processing circuitry and use random access memory for the field store, it is contemplated that similar skew correction circuitry could be used with analog sampled data signals and that analog or digital shift register memories could be used for the field store.

5

Claims

1. A video signal processing system including a source of first video signal having a periodic horizontal line synchronizing signal component, a memory for holding sampled data representing a second video signal, and apparatus for processing said sampled data in synchronism with said first video signal characterized by
 - means (18;318) coupled to said source for developing horizontal synchronizing pulses representing the horizontal line synchronizing signal component of said first video signal;
 - a terminal (CK;PCK) for applying a clock pulse signal wherein the occurrence of clock pulses possibly exhibits varying amounts of skew relative to said horizontal synchronizing pulses;
 - skew measuring means (19;319) coupled to said clock signal terminal and responsive to said horizontal synchronizing pulses for generating a control signal corresponding to the difference in time, as a proper fraction of the period of said clock pulse signal, between the occurrence of one of said horizontal synchronizing pulses and a pulse of said clock signal;
 - means (24;324) coupled to said clock signal terminal, for controlling the reading of the sampled data from said memory; and
 - skew correcting means (22;322) coupled to said clock signal terminal, to said memory (68;368) and to said skew measuring means for effecting a time displacement of the signal represented by the sampled data read from said memory, the magnitude of said time displacement being determined by said control signal.
2. A video signal processing system including a source of first video signal having a horizontal line synchronizing component, a source of second video signal having a horizontal line synchronizing component, and apparatus for processing said second video signal in synchronism with said first video signal characterized by means (18;318) coupled to said source (10;310) of first video signal for developing first horizontal synchronizing pulses representing the horizontal synchronizing component of said first video signal;
 - means (58;358) coupled to said source (50;350) of second video signal for developing second horizontal synchronizing pulses representing the horizontal line synchronizing component of said second video signal;
 - a terminal (CK;PCK) for applying a clock pulse signal, wherein the occurrence of clock pulses possibly exhibits respectively different varying amounts of skew relative to said first and second horizontal sync pulses;
 - means (52;352) coupled to said source of second video signal for developing samples representing said second video signal at instants in time determined by said clock signal;
 - first skew measuring means (59;359) coupled to said clock signal terminal and responsive to said second horizontal synchronizing pulses for generating a first control signal corresponding to the time difference between the occurrence of one of said second horizontal synchronizing pulses and a pulse of said clock pulse signal;
 - first skew correcting means (62;362) responsive to said first control signal and coupled to said sampling means for modifying the values of samples provided thereby to effect a time displacement of the signal represented by said samples, the magnitude of said time displacement being determined by said first control signal; memory means (68;368) coupled to said skew correcting means for storing samples representing said time displaced second signal;
 - second skew measuring means (19;319) responsive to said clock signal and to said first horizontal synchronizing pulses for generating a second control signal corresponding to the time difference between the occurrence of one of said first horizontal synchronizing pulses and a pulse of said clock signal;
 - means (24;324) coupled to said clock signal terminal for controlling the reading of the sampled data from said memory means; and
 - second skew correcting means (22;322) coupled to said clock signal terminal, to said memory and to said second skew measuring means for effecting a time displacement of the signal represented by the sampled data read from said memory, the magnitude of said time displacement being determined



Although the embodiments described above use digital processing circuitry and use random access memory for the field store, it is contemplated that similar skew correction circuitry could be used with analog sampled data signals and that analog or digital shift register memories could be used for the field store.

5

Claims

1. A video signal processing system including a source of first video signal having a periodic horizontal line synchronizing signal component, a memory for holding sampled data representing a second video signal, and apparatus for processing said sampled data in synchronism with said first video signal characterized by
 - means (18;318) coupled to said source for developing horizontal synchronizing pulses representing the horizontal line synchronizing signal component of said first video signal;
 - a terminal (CK;PCK) for applying a clock pulse signal wherein the occurrence of clock pulses possibly exhibits varying amounts of skew relative to said horizontal synchronizing pulses;
 - skew measuring means (19;319) coupled to said clock signal terminal and responsive to said horizontal synchronizing pulses for generating a control signal corresponding to the difference in time, as a proper fraction of the period of said clock pulse signal, between the occurrence of one of said horizontal synchronizing pulses and a pulse of said clock signal;
 - means (24;324) coupled to said clock signal terminal, for controlling the reading of the sampled data from said memory; and
 - skew correcting means (22;322) coupled to said clock signal terminal, to said memory (68;368) and to said skew measuring means for effecting a time displacement of the signal represented by the sampled data read from said memory, the magnitude of said time displacement being determined by said control signal.
2. A video signal processing system including a source of first video signal having a horizontal line synchronizing component, a source of second video signal having a horizontal line synchronizing component, and apparatus for processing said second video signal in synchronism with said first video signal characterized by means (18;318) coupled to said source (10;310) of first video signal for developing first horizontal synchronizing pulses representing the horizontal synchronizing component of said first video signal;
 - means (58;358) coupled to said source (50;350) of second video signal for developing second horizontal synchronizing pulses representing the horizontal line synchronizing component of said second video signal;
 - a terminal (CK;PCK) for applying a clock pulse signal, wherein the occurrence of clock pulses possibly exhibits respectively different varying amounts of skew relative to said first and second horizontal sync pulses;
 - means (52;352) coupled to said source of second video signal for developing samples representing said second video signal at instants in time determined by said clock signal;
 - first skew measuring means (59;359) coupled to said clock signal terminal and responsive to said second horizontal synchronizing pulses for generating a first control signal corresponding to the time difference between the occurrence of one of said second horizontal synchronizing pulses and a pulse of said clock pulse signal;
 - first skew correcting means (62;362) responsive to said first control signal and coupled to said sampling means for modifying the values of samples provided thereby to effect a time displacement of the signal represented by said samples, the magnitude of said time displacement being determined by said first control signal; memory means (68;368) coupled to said skew correcting means for storing samples representing said time displaced second signal;
 - second skew measuring means (19;319) responsive to said clock signal and to said first horizontal synchronizing pulses for generating a second control signal corresponding to the time difference between the occurrence of one of said first horizontal synchronizing pulses and a pulse of said clock signal;
 - means (24;324) coupled to said clock signal terminal for controlling the reading of the sampled data from said memory means; and
 - second skew correcting means (22;322) coupled to said clock signal terminal, to said memory and to said second skew measuring means for effecting a time displacement of the signal represented by the sampled data read from said memory, the magnitude of said time displacement being determined



by said second control signal.

3. A system as set forth in claim 1 or 2 characterized in that said (or, as the case may be, said second) skew correcting means comprises:
 - 6 means (1;500) coupled to said clock signal terminal and responsive to said second control signal for effecting a time displacement of said clock signal to develop a skew corrected clock signal (CK') and
 - means (500) for applying said skew corrected clock (CK') signal to said means for controlling the reading of sampled data from said memory.
- 10 4. A system as set forth in Claim 1 or 2 characterized in that said (or, as the case may be, said second) skew correcting means (19;319) comprises:
 - means (428,420) for generating samples corresponding to the sums of first and second consecutive samples read from said memory and scaled by respective first and second scale factors proportional to said (second) control signal.
- 15 5. A system as set forth in Claim 1 or 2 characterized in that said (or, as the case may be, said second) skew correcting means comprises:
 - 20 means (428) for scaling the values of first and second consecutive samples read from said memory by first and second mutually complementary scale factors proportional to said second control signal; and
 - means (420) for combining the first and second scaled samples to develop samples representing said time displaced signal.
- 25 6. A system as set forth in Claim 2 characterized in that
 - said first skew measuring means (59;359) comprises means for measuring the time interval, as a proper fraction of a period of said clock signal, between a predetermined point on a pulse of said second horizontal line synchronizing signal and a transition of a pulse of said clock signal which is adjacent in time to said predetermined point; and
 - 30 said second skew measuring means (19;319) comprises means for measuring the time interval, as a proper fraction of a period of said clock signal, between a predetermined point on a pulse of said first horizontal line synchronizing signal and a transition of a pulse of said clock signal which is adjacent in time to said predetermined point.
- 35 7. A system as set forth in Claim 6 characterized in that said first skew correcting means (62;362) includes means (428) scaling the values of first and second consecutive samples representing said second signal by a factor proportional to said first control signal and by a factor proportional to the complement of said first control signal respectively and means (420) for adding the first and second scaled samples to develop a first sample representing said time displaced signal.
- 40 8. A picture-in-picture television display system including a source of first video signal having a periodic horizontal line synchronizing signal component and a source of second video signal having a periodic horizontal line synchronizing signal component, and apparatus for processing said second video signal in synchronism with said first video signal characterized by
 - 45 means (64;70;364;370) including a memory (68;368) for processing said second video signal to develop sampled data in said memory representing said second video signal;
 - a terminal (CK;PCK) for applying a clock pulse signal wherein the occurrence of pulses of said clock signal possibly exhibits varying amounts of skew relative to the horizontal synchronizing pulses of said first video signal;
 - 50 skew measuring means (19;319) coupled to said clock signal terminal and responsive to said horizontal synchronizing pulses of said first signal for generating a control signal corresponding to the amount time, as a proper fraction of the period of said clock signal, between the occurrence of one of said horizontal synchronizing pulses and a pulse of said clock signal;
 - skew correcting means (22;322) coupled to said clock signal terminal and responsive to said control signal for effecting a time displacement of said clock signal to develop a skew corrected clock signal;
 - 55 means (24;324) coupled to said skew correcting means and to said memory for extracting the sampled data therefrom in synchronism with said skew corrected clock signal; and



multiplexing means (26;326) coupled to said sampled data extracting means and to said source of first video signal for selectively providing signals from said source of first video signal and from said memory to a display device.

- 5 9. A system as set forth in Claim 2 or 8 characterized in that
 said skew measuring means (19;319) includes means for measuring the time interval between a predetermined point on a pulse of said horizontal line synchronizing signal and a transition of the pulse of said clock signal which occurs immediately prior to said predetermined point; and
 said (or, as the case may be, second skew correcting means (22;322) includes means (I₁-I₁₅, I₁'-I₁₅') for delaying said clock signal by an amount of time approximately equal to said time interval to develop said skew corrected clock signal.
10. A system as set forth in Claim 8 characterized in that said means for processing said second video signal comprises:
 15 means (58;356) coupled to said source of (second) video signal for developing further horizontal synchronizing pulses representing the horizontal line synchronizing signal component of said second video signal;
 means (52;352) to said source of (second) video signal for developing samples representing said second video signal at instants in time determined by said clock signal;
 20 further skew measuring means (59;359) coupled to said clock signal terminal and responsive to said further horizontal synchronizing pulses for generating a further control signal (SSK) corresponding to the amount of time, as a proper fraction of the period of said clock signal, between the occurrence of a further horizontal sync pulse and a pulse of said clock signal;
 further skew correcting means (62;362) coupled to said sample developing means and to said clock
 25 signal terminal and responsive to said further control signal for effecting a time displacement of the signal represented by the samples provided by said sample developing means.
 means (64;364) coupled to said further skew correcting means for applying selected ones of the samples provided thereby to said memory.
- 30 11. A system as set forth in Claim 10, characterized in that
 said second video signal may include a color synchronizing burst signal component (BG;SBG); and
 the clock pulse signal (CK) applied to said clock terminal is synchronized in frequency and phase to said color synchronizing burst signal component (BG;SBG)
- 35 12. A system as set forth in Claim 10, characterized in that
 said first and second video signals include respective first (C_P) and second (C_S) chrominance signal components including respective first (PBG) and second (SBG) color synchronizing burst signal components;
 the clock pulse signal applied to said clock terminal is synchronized in frequency and phase to said
 40 first color synchronizing burst signal component;
 the chrominance signal components of the samples provided by said sample providing means tend to have phase errors relative to the samples which would be provided if the clock signal were locked in frequency and phase to the second color synchronizing burst signal component; and
 means (62;362) coupled to said sample providing means and responsive to said second color
 45 synchronizing burst signal component for substantially correcting said phase errors.

Revendications

- 50 1. Système de traitement de signaux vidéo comprenant une source d'un premier signal vidéo ayant une composante d'un signal de synchronisation horizontale périodique, une mémoire pour contenir la donnée échantillonnée représentant un second signal vidéo et un appareil pour le traitement de ladite donnée échantillonnée en synchronisme avec ledit premier signal vidéo, caractérisé par
 un moyen (18 ; 318) couplé à ladite source pour développer des impulsions de synchronisation horizontale représentant la composante du signal de synchronisation horizontale dudit premier signal vidéo ;
 55 une borne (CK ; PCK) pour l'application d'un signal impulsionnel d'horloge où la présence des impulsions d'horloge présente éventuellement des quantités variables de biais relativement auxdites impulsions de synchronisation horizontale ;



- un moyen de mesure du biais (19 ; 319) couplé à ladite borne de signaux d'horloge et répondant auxdites impulsions de synchronisation horizontale pour produire un signal de commande correspondant à la différence dans le temps, sous la forme d'une fraction appropriée de la période dudit signal impulsif d'horloge, entre la présence de l'une desdites impulsions de synchronisation horizontale et une impulsion dudit signal d'horloge ;
- un moyen (24 ; 324) couplé à ladite borne d'horloge pour contrôler la lecture de la donnée échantillonnée de ladite mémoire ; et
- un moyen de correction du biais (22 ; 322) couplé à ladite borne de signaux d'horloge, à ladite mémoire (68 ; 368) et audit moyen de mesure du biais pour effectuer un déplacement dans le temps du signal représenté par la donnée échantillonnée lue de ladite mémoire, la grandeur dudit déplacement dans le temps étant déterminée par ledit signal de commande.
2. Système de traitement de signaux vidéo comprenant une source d'un premier signal vidéo ayant une composante de synchronisation horizontale, une source d'un second signal vidéo ayant une composante de synchronisation horizontale et un appareil pour le traitement dudit second signal vidéo en synchronisme avec ledit premier signal vidéo, caractérisé par un moyen (18 ; 318) couplé à ladite source (10 ; 310) du premier signal vidéo pour développer des premières impulsions de synchronisation horizontale représentant la composante de synchronisation horizontale dudit premier signal vidéo ;
- un moyen (58 ; 356) couplé à ladite source (50 ; 350) du second signal vidéo pour développer des secondes impulsions de synchronisation horizontale représentant la composante de synchronisation horizontale dudit second signal vidéo ;
- une borne (CK ; PCK) pour appliquer un signal impulsif d'horloge, où la présence des impulsions d'horloge présente éventuellement des quantités respectivement variables et différentes de biais relativement auxdites premières et secondes impulsions de synchronisation horizontale ;
- un moyen (52 ; 352) couplé à ladite source du second signal vidéo pour développer des échantillons représentant ledit second signal vidéo en des instants dans le temps déterminés par ledit signal d'horloge ;
- un premier moyen de mesure du biais (59 ; 359) couplé à ladite borne de signaux d'horloge et répondant auxdites secondes impulsions de synchronisation horizontale pour produire un premier signal de commande correspondant à la différence de temps entre la présence de l'une desdites secondes impulsions de synchronisation horizontale et une impulsion dudit signal impulsif d'horloge ;
- un premier moyen de correction du biais (62 ; 362) répondant audit premier signal de commande et couplé audit moyen d'échantillonnage pour modifier les valeurs des échantillons produits pour ainsi effectuer un déplacement dans le temps du signal représenté par lesdits échantillons, la grandeur dudit déplacement dans le temps étant déterminée par ledit premier signal de commande ; un moyen formant mémoire (68 ; 368) couplé audit moyen de correction du biais pour stocker des échantillons représentant ledit second signal déplacé dans le temps ;
- Un second moyen de mesure du biais (19 ; 319) répondant audit signal d'horloge et auxdites premières impulsions de synchronisation horizontale pour produire un second signal de commande correspondant à la différence dans le temps entre la présence de l'une desdites premières impulsions de synchronisation horizontale et une impulsion dudit signal d'horloge ;
- un moyen (24 ; 324) couplé à ladite borne de signaux d'horloge pour contrôler la lecture de la donnée échantillonnée dudit moyen formant mémoire ; et
- un second moyen de correction du biais (22 ; 322) couplé à ladite borne de signaux d'horloge, à ladite mémoire et audit second moyen de mesure du biais pour effectuer un déplacement dans le temps du signal représenté par la donnée échantillonnée lue de ladite mémoire, la grandeur dudit déplacement dans le temps étant déterminée par ledit second signal de commande.
3. Système selon la revendication 1 ou 2 caractérisé en ce que ledit (ou selon le cas, ledit second) moyen de correction du biais comprend :
- un moyen (11, 500) couplé à ladite borne de signaux d'horloge et répondant audit second signal de commande pour effectuer un déplacement dans le temps dudit signal d'horloge pour développer un signal d'horloge (CK') dont le biais est corrigé ; et
- un moyen (500) pour appliquer ledit signal d'horloge dont le biais est corrigé (CK') audit moyen (24) pour contrôler la lecture de la donnée échantillonnée de ladite mémoire.
4. Système selon la revendication 1 ou 2, caractérisé en ce que ledit (ou selon le cas ledit second) moyen



de correction du biais (19 ; 319) comprend :

un moyen (428, 420) pour produire des échantillons correspondant aux sommes de premier et second échantillons consécutifs lus de ladite mémoire et calibrés par des premier et second facteurs respectifs de calibrage proportionnels audit(second) signal de commande.

5

5. Système selon la revendication 1 ou 2, caractérisé en ce que ledit (ou selon le cas, ledit second) moyen de correction du biais comprend :

un moyen (428) pour calibrer les valeurs des premier et second échantillons consécutifs lus de ladite mémoire par des premier et second facteurs mutuellement complémentaires de calibrage, proportionnels audit second signal de commande ; et

10

un moyen (420) pour combiner les premier et second échantillons calibrés afin de développer des échantillons représentant ledit signal déplacé dans le temps.

6. Système selon la revendication 2, caractérisé en ce que

15

ledit premier moyen de mesure du biais (59 ; 359) comprend un moyen pour mesurer l'intervalle de temps, en tant que fraction d'une période du signal d'horloge, entre un point prédéterminé sur une impulsion dudit second signal de synchronisation horizontale et une transition d'une impulsion dudit signal d'horloge qui est proche dans le temps dudit point prédéterminé ; et

20

ledit second moyen de mesure du biais (19 ; 319) comprend un moyen pour mesurer l'intervalle de temps, en tant que fraction d'une période dudit signal d'horloge, entre un point prédéterminé sur une impulsion dudit premier signal de synchronisation horizontale et une transition d'une impulsion dudit signal d'horloge qui est proche dans le temps dudit point prédéterminé.

7. Système selon la revendication 6, caractérisé en ce que ledit premier moyen de correction du biais (62 ; 362) comprend un moyen (428) pour calibrer les valeurs des premier et second échantillons consécutifs représentant le second signal d'un facteur proportionnel au premier signal de commande et d'un facteur proportionnel au complément du premier signal de commande, respectivement, et un moyen (420) pour ajouter les premier et second échantillons calibrés afin de développer un premier échantillon représentant ledit signal déplacé dans le temps.

25

30

8. Système de visualisation de télévision image dans l'image comprenant une source d'un premier signal vidéo ayant une composante périodique d'un signal de synchronisation horizontale et une source d'un second signal vidéo ayant une composante périodique d'un signal de synchronisation horizontale et un appareil pour le traitement dudit second signal vidéo en synchronisme avec ledit premier signal vidéo, caractérisé par un moyen (64, 70 ; 364, 370) comprenant une mémoire (68 ; 368) pour le traitement dudit second signal vidéo afin de développer une donnée échantillonnée dans ladite mémoire, représentant ledit second signal vidéo ;

35

une borne (CK ; PCK) pour appliquer un signal impulsif d'horloge où la présence des impulsions dudit signal d'horloge présente éventuellement des quantités variables de biais relativement aux impulsions de synchronisation horizontale dudit premier signal vidéo ;

40

un moyen de mesure du biais (19 ; 319) couplé à ladite borne de signaux d'horloge et répondant auxdites impulsions de synchronisation horizontale dudit premier signal pour produire un signal de commande correspondant à la quantité de temps, en tant que fraction de la période dudit signal d'horloge, entre la présence de l'une desdites impulsions de synchronisation horizontale et d'une impulsion dudit signal d'horloge ;

45

un moyen de correction du biais (22 ; 322) couplé à ladite borne de signaux d'horloge et répondant audit signal de commande pour effectuer un déplacement dans le temps dudit signal d'horloge pour développer un signal d'horloge dont le biais est corrigé ;

un moyen (24 ; 324) couplé audit moyen de correction du biais et à ladite mémoire pour en extraire la donnée échantillonnée en synchronisme avec ledit signal d'horloge dont le biais est corrigé ; et

50

un moyen de multiplexage (26 ; 326) couplé audit moyen d'extraction de la donnée échantillonnée et à ladite source du premier signal vidéo pour appliquer sélectivement des signaux de ladite source du premier signal vidéo et de ladite mémoire à un dispositif de visualisation.

55

9. Système selon la revendication 2 ou 8, caractérisé en ce que

ledit moyen de mesure du biais (19 ; 319) comprend un moyen pour mesurer l'intervalle de temps entre un point prédéterminé sur une impulsion dudit signal de synchronisation horizontale et une



transition de l'impulsion dudit signal d'horloge qui se produit immédiatement avant ledit point prédéterminé ; et

ledit (ou selon le cas, ledit second) moyen de correction du biais (22 ; 322) comprend un moyen (11-115 , 11'-115") pour retarder ledit signal d'horloge d'une quantité de temps à peu près égale audit intervalle de temps afin de développer le signal d'horloge dont le biais est corrigé.

10. Système selon la revendication 8, caractérisé en ce que ledit moyen pour le traitement dudit second signal vidéo comprend :

un moyen (58 ; 358) couplé à ladite source du second signal vidéo pour développer d'autres impulsions de synchronisation horizontale représentant la composante du signal de synchronisation horizontale dudit second signal vidéo ;

un moyen (52 ; 352) couplé à ladite source du second signal vidéo pour développer des échantillons représentant ledit signal vidéo en des instants dans le temps, déterminés par ledit signal d'horloge ;

un autre moyen de mesure du biais (59 ; 359) couplé à ladite borne de signaux d'horloge et répondant auxdites autres impulsions de synchronisation horizontale pour produire un autre signal de commande (SSK) correspondant à la quantité de temps, en tant que fraction de la période dudit signal d'horloge, entre la présence d'une autre impulsion de synchronisation horizontale et d'une impulsion dudit signal d'horloge ;

un autre moyen de correction du biais (62 ; 362) couplé audit moyen développant l'échantillon et à ladite borne de signaux d'horloge et répondant audit autre signal de commande pour effectuer un déplacement dans le temps du signal représenté par les échantillons produits par ledit moyen développant les échantillons ;

un moyen (64 ; 364) couplé audit autre moyen de correction du biais pour appliquer des échantillons choisis ainsi produits à ladite mémoire.

11. Système selon la revendication 10, caractérisé en ce que

ledit second signal vidéo peut comprendre une composante d'un signal de salve de synchronisation de couleur (BG ; SBG) ; et

le signal impulsionnel d'horloge (CK) appliqué à ladite borne d'horloge est synchronisé en fréquence et en phase sur ladite composante du signal de salve de synchronisation couleur (BG ; SBG).

12. Système selon la revendication 7, caractérisé en ce que

lesdits premier et second signaux vidéo comprennent des première (C_P) et seconde (C_S) composantes du signal de chrominance comprenant des première et seconde composantes respectives du signal de salve de synchronisation couleur (PBG et SBG) ;

le signal impulsionnel d'horloge appliqué à ladite borne d'horloge est synchronisé en fréquence et en phase sur ladite première composante du signal de salve de synchronisation couleur ;

les composantes du signal de chrominance des échantillons produits par ledit moyen produisant l'échantillon ont tendance à avoir des erreurs de phase relativement aux échantillons qui seraient produits si le signal d'horloge était verrouillé en fréquence et en phase sur la seconde composante du signal de salve de synchronisation couleur ; et

un moyen (62 ; 362) couplé audit moyen produisant l'échantillon et répondant à ladite seconde composante du signal de salve de synchronisation couleur pour corriger sensiblement lesdites erreurs de phase.

Patentansprüche

1. Videosignal-Verarbeitungssystem mit einer Quelle für ein erstes Videosignal, das eine periodische Horizontalsynchronisierkomponente enthält, mit einem Speicher zum Speichern von Abfrageproben, die ein zweites Videosignal darstellen, und mit einer Anordnung zur Verarbeitung der Abfrageproben synchron mit dem ersten Videosignal,

gekennzeichnet durch

eine mit der Quelle gekoppelte Einrichtung (18; 318) zur Erzeugung von Horizontalsynchronisierimpulsen, welche die Horizontalsynchronisierkomponente des ersten Videosignals darstellen;

einen Anschluß (CK; PCX) zum Anlegen eines Taktimpulssignales, bei dem das Auftreten von Taktimpulsen um einen variierenden Betrag bezüglich der Horizontalsynchronisierimpulse verschoben



sein kann;

eine Verschiebungs-Meßeinrichtung (19; 319), die mit dem Taktanschluß gekoppelt ist und auf die Horizontalsynchronisierimpulse anspricht, um ein Steuersignal zu erzeugen, das der Zeitdifferenz, ausgedrückt als Bruchteil der Periode des Taktimpulssignales, zwischen dem Auftreten eines der

Horizontalsynchronisierimpulse und dem Auftreten eines Impulses des Taktimpulssignales entspricht;

eine mit dem Taktsignalanschluß gekoppelte Einrichtung (24; 324) zur Steuerung der Auslesung der Signalproben aus dem Speicher; und

eine Verschiebungs-Korrekturereinrichtung (22; 322), die mit dem Taktsignalanschluß, dem Speicher (68; 368) und mit der Verschiebungs-Meßeinrichtung gekoppelt ist, um eine zeitliche Verschiebung des aus dem Speicher ausgelesenen, durch die Signalproben dargestellten Signales um einen Betrag zu bewirken, der durch das Steuersignal bestimmt ist.

2. Videosignal-Verarbeitungssystem mit einer Quelle für ein erstes Videosignal, das eine periodische Horizontalsynchronisierkomponente enthält, mit einem Speicher zum Speichern von Abfrageproben, die ein zweites Videosignal darstellen, und mit einer Anordnung zur Verarbeitung der Abfrageproben synchron mit dem ersten Videosignal, gekennzeichnet durch

eine mit der Quelle (10; 310) für das erste Videosignal gekoppelte Einrichtung (18; 318) zur Entwicklung von ersten Horizontalsynchronisierimpulsen, welche die Horizontalsynchronisierkomponente des ersten Videosignals darstellen;

eine mit der Quelle (50; 350) für das zweite Videosignal gekoppelte Einrichtung (58; 358) zum Entwickeln von zweiten Horizontalsynchronisierimpulsen, welche die Horizontalzellensynchronisierkomponente des zweiten Videosignales darstellen;

einen Anschluß (CK; PCK) zum Anlegen eines Taktimpulssignales, bei dem das Auftreten von Taktimpulsen um verschiedene Verschiebungsbeträge bezüglich der ersten und der zweiten Horizontalsynchronisierimpulsen verschoben sein kann;

eine mit der Quelle für das zweite Videosignal gekoppelte Einrichtung (52; 352) zum Erzeugen von Abtastproben, welche das zweite Videosignal zu Zeitpunkten, die durch das Taktsignal bestimmt werden, darstellen;

eine erste Verschiebungs-Meßeinrichtung (59; 359), die mit dem Taktsignalanschluß gekoppelt ist und auf die zweiten Horizontalsynchronisierimpulse anspricht, um ein erstes Steuersignal entsprechend der Zeitdifferenz zwischen dem Auftreten eines der zweiten Horizontalsynchronisierimpulse und einem Impuls des Taktimpulssignales zu erzeugen;

eine erste Verschiebungs-Korrekturereinrichtung (62; 362), die auf das erste Steuersignal anspricht und mit der Abtasteinrichtung gekoppelt ist, um die Werte der von dieser gelieferten Abtastproben so zu ändern, daß eine Zeitverschiebung des durch die Proben dargestellten Signals bewirkt wird, wobei der Betrag der Zeitverschiebung durch das erste Steuersignal bestimmt wird;

eine mit der Verschiebungs-Korrekturereinrichtung gekoppelte Speichereinrichtung (68; 368) zum Speichern von Proben, die das zeitlich verschobene zweite Signal darstellen;

eine zweite Verschiebungs-Meßeinrichtung (19; 319) die auf das Taktsignal und die ersten Horizontalsynchronisierimpulse anspricht, um ein zweites Steuersignal entsprechend der Zeitdifferenz zwischen dem Auftreten eines der ersten Horizontalsynchronisierimpulse und einem Impuls des Taktsignals zu erzeugen;

einer Einrichtung (24; 324) die mit dem Taktsignalanschluß gekoppelt ist, um das Auslesen der Abtastwerte aus der Speichereinrichtung zu steuern; und

eine zweite Verschiebungs-Korrekturereinrichtung (22; 322), die mit dem Taktsignalanschluß, dem Speicher und der zweiten Verschiebungs-Meßeinrichtung gekoppelt ist, um eine Zeitverschiebung des durch die aus dem Speicher herausgelesenen Abtastproben repräsentierten Signales um einen Betrag zu bewirken, der durch das zweite Steuersignal bestimmt ist.

3. System nach Anspruch 1 oder 2, dadurch gekennzeichnet, daß die (oder gegebenenfalls die zweite) Verschiebungs-Korrekturereinrichtung

eine Einrichtung (1; 500), die mit dem Taktsignalanschluß gekoppelt ist und auf das zweite Steuersignal anspricht, um eine Zeitverschiebung des Taktsignals zum Erzeugen eines verschiebungskorrigierten Taktsignals (CK') zu bewirken; und

eine Anordnung (500) zum Anlegen des verschiebungskorrigierten Taktsignals (CK') an die Einrichtung zum Steuern des Lesens der Abtastproben aus dem Speicher enthält.



4. System nach Anspruch 1 oder 2, dadurch gekennzeichnet, daß die Verschiebungs-Korrektureinrichtung (19, 319) eine Einrichtung (428, 420) zur Erzeugung von Signalproben, die den Summen einer ersten und einer zweiten, aufeinanderfolgenden, aus dem Speicher ausgelesenen Probe entspricht, die mit einem ersten bzw. zweiten Bemessungsfaktor proportional dem (zweiten) Steuersignal gewichtet sind.
5. System nach Anspruch 1 oder 2, dadurch gekennzeichnet, daß die (oder gegebenenfalls die zweite) Verschiebungs-Korrektureinrichtung
eine Einrichtung (428) zur Gewichtung der Werte jeweils zweier aufeinanderfolgender, aus dem Speicher ausgelesener Proben mit einem ersten bzw. zweiten komplementären Bemessungsfaktor proportional zum zweiten Steuersignal; und
eine Einrichtung (420), welche die beiden gewichteten Proben miteinander kombiniert, um Proben zu entwickeln, die das zeitlich verschobene Signal darstellen, enthält.
6. System nach Anspruch 2, dadurch gekennzeichnet, daß die erste Verschiebungs-Meßeinrichtung (59; 359) eine Einrichtung zum Messen des Zeitintervalls, gerechnet als Bruchteil einer Periode des Taktsignals, zwischen einem vorgegebenen Punkt auf einem Impuls des zweiten Horizontalzeilensynchronisiersignales und einem Übergang eines Pulses des Taktsignales, der dem vorgegebenen Punkt zeitlich benachbart ist, enthält und
die zweite Verschiebungs-Meßeinrichtung (19; 319) eine Einrichtung zum Messen des Zeitintervalls, gerechnet als Bruchteil einer Periode des Taktsignales, zwischen einem vorgegebenen Punkt auf einem Puls des ersten Horizontalzeilensynchronisiersignals und einem Übergang eines Impulses des Taktsignales, der dem vorgegebenen Punkt zeitlich benachbart ist, enthält.
7. System nach Anspruch 6, dadurch gekennzeichnet, daß die erste Verschiebungs-Korrektureinrichtung (62; 362) eine Einrichtung (428) zum Gewichten der Werte einer ersten und einer zweiten aufeinanderfolgenden, das zweite Signal darstellenden Abtastprobe durch einen dem ersten Steuersignal bzw. einem dem Komplement des ersten Steuersignals proportionalen Faktor, und eine Einrichtung (420) zum Addieren der ersten und der zweiten gewichteten Abtastprobe zur Erzeugung einer ersten Abtastprobe, die das zeitlich verschobene Signal darstellt, enthält.
8. Bild-in-Bild-Fernseh wiedergabesystem mit einer Quelle für ein erstes, eine periodische Horizontalzeilensynchronisiersignalkomponente aufweisendes Videosignal, mit einer Quelle für ein zweites, eine periodische Horizontalzeilensynchronisiersignalkomponente aufweisendes Videosignal, und mit einer Einrichtung zum Verarbeiten des zweiten Videosignals synchron mit dem ersten Videosignal, gekennzeichnet durch
eine Einrichtung (64, 70; 364, 370) einschließlich eines Speichers (68; 368) zum Verarbeiten des zweiten Videosignals, um Abtastproben im Speicher zu erzeugen, die das zweite Videosignal darstellen;
einen Anschluß (CK; PCK) zum Zuführen eines Taktimpulssignals, bei dem das Auftreten von Taktsignalimpulsen um variierende Beträge bezüglich der Horizontalsynchronisierimpulse des ersten Videosignals verschoben sein können;
eine Verschiebungs-Meßeinrichtung (19; 319), die mit dem Taktanschluß gekoppelt ist und auf die Horizontalsynchronisierimpulse des ersten Signals anspricht, um ein Steuersignal zu erzeugen, welches dem Zeitbetrag, ausgedrückt als Bruchteil der Periode des Taktsignals, zwischen dem Auftreten eines der Horizontalsynchronisierimpulse und einem Impuls des Taktsignals entspricht;
eine Verschiebungs-Korrektureinrichtung (22; 322), die mit dem Taktsignalanschluß gekoppelt ist und auf das Steuersignal anspricht, um eine zeitliche Verschiebung des Taktsignals zur Entwicklung eines verschiebungskorrigierten Taktsignales zu bewirken;
eine Einrichtung (24; 324), die mit der Verschiebungs-Korrektureinrichtung und dem Speicher gekoppelt ist, um aus diesem die Abtastproben synchron mit dem verschiebungskorrigierten Taktsignal zu extrahieren; und
einer Multiplex-Einrichtung (26; 326) die mit der Abtastproben-Extrahiereinrichtung und der Quelle für das erste Videosignal gekoppelt ist, um wahlweise Signale von der Quelle für das erste Videosignal oder von dem Speicher an eine Wiedergabeeinrichtung zu liefern.
9. System nach Anspruch 2 oder 8, dadurch gekennzeichnet, daß die Verschiebungs-Meßeinrichtung (19; 319) eine Einrichtung zum Messen des Zeitintervalls zwischen einem vorgegebenen Punkt auf einem Impuls des Horizontalzeilensynchronisiersignals und einem Übergang des Impulses des Taktsi-



gnales, der unmittelbar vor dem vorgegebenen Punkt auftritt, enthält und

die (oder gegebenenfalls die zweite) Verschiebungs-Korrekturereinrichtung (22; 322) eine Einrichtung (I_1 - I_{15} , I_1' - I_{15}') zum Verzögern des Taktsignals um einen Zeitbetrag, der ungefähr gleich dem genannten Zeitintervall ist, um das verschiebungskorrigierte Taktsignal zu erzeugen, enthält.

5

10. System nach Anspruch 8, dadurch gekennzeichnet, daß die Einrichtung zum Verarbeiten des zweiten Videosignals enthält:

10

eine Einrichtung (58; 356), die mit der Quelle für das zweite Videosignal gekoppelt ist, um weitere Horizontalsynchronisierimpulse zu erzeugen, die die Horizontalzellensynchronisier-Signalkomponente des zweiten Videosignals darstellen;

eine Einrichtung (52; 352), die mit der Quelle des zweiten Videosignals gekoppelt ist, um Abtastproben zu erzeugen, die das zweite Videosignal zu Zeitpunkten, die durch das Taktsignal bestimmt werden, darstellen;

15

eine weitere Verschiebung-Meßeinrichtung (59, 359), die mit dem Taktsignalanschluß gekoppelt ist und auf die weiteren Horizontalsynchronisierimpulse anspricht, um ein weiteres Steuersignal (SSK) entsprechend dem Zeitbetrag, gerechnet als Bruchteil der Periode des Taktsignals, zwischen dem Auftreten eines weiteren Horizontalsynchronisierimpulses und einem Impuls des Taktsignals zu erzeugen;

20

eine weitere Verschiebungs-Korrekturereinrichtung (62, 362), die mit der die Abtastwerte erzeugenden Einrichtung sowie dem Taktsignalanschluß gekoppelt ist und auf das weitere Steuersignal anspricht, um eine Zeitverschiebung des Signales zu bewirken, welches durch die von der Abtastprobenerzeugungseinrichtung gelieferten Abtastproben dargestellt wird;

eine mit der weiteren Verschiebungs-Korrekturereinrichtung gekoppelte Einrichtung (64, 364) zum Zuführen ausgewählter, von ihr gelieferter Abtastproben zum Speicher.

25

11. System nach Anspruch 10, dadurch gekennzeichnet, daß

das zweite Videosignal eine Farbsynchronisierschwingungszug-Signalkomponente (BG; SBG) enthalten kann und

30

das dem Taktanschluß zugeführte Taktimpulssignal (CH) in Frequenz und Phase mit der Farbsynchronisierschwingungszug-Signalkomponente (BG; SBG) synchronisiert ist.

12. System nach Anspruch 10, dadurch gekennzeichnet, daß

35

das erste und das zweite Videosignal eine entsprechende erste (C_p) und zweite (C_s) Farbart-Signalkomponente einschließlich einer entsprechenden ersten (PBG) bzw. zweiten (SBG) Farbsynchronisierschwingungszug-Signalkomponente enthalten;

das dem Taktanschluß zugeführte Taktimpulssignal in Frequenz und Phase mit der ersten Farbsynchronisierschwingungszug-Signalkomponente synchronisiert ist;

40

die Farbart-Signalkomponenten der Abtastproben, die durch die Abtastprobenerzeugungseinrichtung geliefert werden, zu Phasenfehlern bezüglich der Abtastproben neigen, die erzeugt würden, wenn das Taktsignal in Frequenz und Phase mit der zweiten Farbsynchronisierschwingungszug-Signalkomponente synchronisiert wäre; und

mit der Abtastwerterzeugungseinrichtung eine Einrichtung (62; 362) gekoppelt ist, die auf die zweite Farbsynchronisierschwingungszug-Signalkomponente anspricht, um die genannten Phasenfehler im wesentlichen zu korrigieren.

45

50

55