

POWERED DEVICE

TECHNICAL FIELD

[0001] This application relates to the communications field, and in particular, to a powered device.

BACKGROUND

[0002] A Power over Ethernet (English: Power over Ethernet, PoE) system includes power sourcing equipment (English: power sourcing equipment, PSE) and a powered device (English: powered device, PD). The PSE supplies power to the PD while communicating with the PD through an Ethernet twisted pair. The Ethernet twisted pair includes eight cables numbered 1 to 8. A cable 1 and a cable 2 are paired, a cable 3 and a cable 6 are paired, a cable 4 and a cable 5 are paired, and a cable 7 and a cable 8 are paired. Two paired cables are twisted together. In a widely used 100 M Ethernet, a cable pair 1-2 and a cable pair 3-6 are used for communication, and a cable pair 4-5 and a cable pair 7-8 are idle. Therefore, the cable pair 1-2 and the cable pair 3-6 form a group, and the cable pair 4-5 and the cable pair 7-8 form another group. A data cable pair group (a cable pair 1-2 and a cable pair 3-6) is usually used for early Power over Ethernet supply. Two groups of cable pairs can be used together for new Power over Ethernet supply. FIG. 1 shows a structure of a PD. The PD in FIG. 1 uses a diode full-bridge rectifier circuit.

[0003] A power loss of diodes is large. Therefore, power utilization of the PD is low.

SUMMARY

[0004] This application provides a PD, to improve power utilization of the PD.

[0005] According to a first aspect, a PD is provided. The PD includes an Ethernet port, a rectifier circuit, and a PD circuit. The Ethernet port includes a first contact pair, a second contact pair, a third contact pair, and a fourth contact pair. The first contact pair is configured to connect to a cable pair 1-2 of an Ethernet cable. The second contact pair is configured to connect to a cable pair 3-6 of the Ethernet cable. The third contact pair is configured to connect to a cable pair 4-5 of the Ethernet cable. The fourth contact pair is configured to connect to a cable pair 7-8 of the Ethernet cable. The rectifier circuit includes four metal-oxide semiconductor field-effect transistors

(English: metal-oxide-semiconductor field-effect transistor, MOSFET) and at least four diodes. The four MOSFETs are a first MOSFET, a second MOSFET, a third MOSFET, and a fourth MOSFET. The at least four diodes include a first diode, a second diode, a third diode, and a fourth diode. The first contact pair is connected to an anode of the first diode, and is connected to a first end of the first MOSFET. The second contact pair is connected to a cathode of the second diode, and is connected to a first end of the second MOSFET. The third contact pair is connected to a cathode of the third diode, and is connected to a first end of the third MOSFET. The fourth contact pair is connected to an anode of the fourth diode, and is connected to a first end of the fourth MOSFET. A power input positive electrode of the PD circuit is connected to a cathode of the first diode, is connected to a second end of the second MOSFET, is connected to a second end of the third MOSFET, and is connected to a cathode of the fourth diode. A power input negative electrode of the PD circuit is connected to a second end of the first MOSFET, is connected to an anode of the second diode, is connected to an anode of the third diode, and is connected to a second end of the fourth MOSFET.

[0006] That an electric potential of the contact pair 1-2 is lower than that of the contact pair 3-6 and an electric potential of the contact pair 7-8 is lower than that of the contact pair 4-5 is a most widely used PoE scenario. In the foregoing scenario, the first diode to the fourth diode in the PD are cut off. Therefore, because a current passes through only the MOSFETs but does not pass through the diodes, a loss of the rectifier circuit of the PD is small. Compared with a rectifier circuit in which eight MOSFETs are used, the foregoing structure reduces complexity and costs of the PD when there is a same power loss.

[0007] With reference to the first aspect, in a first implementation of the first aspect, a gate electrode of the first MOSFET is connected to the second contact pair. A gate electrode of the second MOSFET is connected to the first contact pair. A gate electrode of the third MOSFET is connected to the fourth contact pair. A gate electrode of the fourth MOSFET is connected to the third contact pair.

[0008] With reference to the first aspect or the first implementation of the first aspect, in a second implementation of the first aspect, the first MOSFET is an N-type MOSFET. The second MOSFET is a P-type MOSFET. The third MOSFET is a P-type MOSFET. The fourth MOSFET is an N-type MOSFET. When the electric potential of the contact pair 1-2 is lower than that of the contact pair 3-6 and the electric potential of the contact pair 7-8 is lower than that of the contact pair 4-5, the foregoing types of MOSFETs are used without additional drive circuits.

[0009] With reference to the first aspect, the first implementation of the first aspect, or the second implementation of the first aspect, in a third implementation of the first aspect, the first end

of the first MOSFET is a drain electrode of the first MOSFET. The second end of the first MOSFET is a source electrode of the first MOSFET. The first end of the second MOSFET is a drain electrode of the second MOSFET. The second end of the second MOSFET is a source electrode of the second MOSFET. The first end of the third MOSFET is a drain electrode of the third MOSFET. The second end of the third MOSFET is a source electrode of the third MOSFET. The first end of the fourth MOSFET is a drain electrode of the fourth MOSFET. The second end of the fourth MOSFET is a source electrode of the fourth MOSFET.

[0010] With reference to any one of the first aspect or the first to the third implementations of the first aspect, in a fourth implementation of the first aspect, the rectifier circuit further includes a first control circuit and a second control circuit. The gate electrode of the first MOSFET is connected to the second contact pair through the first control circuit. The gate electrode of the fourth MOSFET is connected to the third contact pair through the second control circuit. The first control circuit is configured to: when a value obtained by subtracting an electric potential of the first contact pair from an electric potential of the second contact pair is greater than a first voltage threshold, turn on the first MOSFET; and when the value obtained by subtracting the electric potential of the first contact pair from the electric potential of the second contact pair is less than the first voltage threshold, cut off the first MOSFET. An absolute value of the first voltage threshold is greater than that of a maximum PoE detection voltage and less than or equal to that of a minimum PoE supply voltage. The second control circuit is configured to: when a value obtained by subtracting an electric potential of the fourth contact pair from an electric potential of the third contact pair is greater than a second voltage threshold, turn on the fourth MOSFET; and when the value obtained by subtracting the electric potential of the fourth contact pair from the electric potential of the third contact pair is less than the second voltage threshold, cut off the fourth MOSFET. An absolute value of the second voltage threshold is greater than that of the maximum PoE detection voltage and greater than or equal to that of the minimum PoE supply voltage. For the PD using the structure, a connection between the cable pair 4-5 and a backflow end in the PSE does not cause a detection or classification error.

[0011] With reference to any one of the first aspect or the first to the fourth implementations of the first aspect, in a fifth implementation of the first aspect, the PD is a type-4 PD. If the PD is a type-4 PD, the PSE works as type-4 PSE. The type-4 PSE definitely uses the cable pair 1-2 and the cable pair 7-8 for providing a low electric potential. Therefore, the structure of the PD is particularly suitable for the type-4 PD.

BRIEF DESCRIPTION OF DRAWINGS

[0012] FIG. 1 shows a structure of a PD;

[0013] FIG. 2 shows another structure of a PD;

[0014] FIG. 3 shows a structure of a PD according to an embodiment of the present invention;

5 [0015] FIG. 4 shows another structure of a PD according to an embodiment of the present invention; and

[0016] FIG. 5 shows still another structure of a PD according to an embodiment of the present invention.

DESCRIPTION OF EMBODIMENTS

10 [0017] The following describes the embodiments of the present invention with reference to FIG. 2 to FIG. 5.

[0018] A power loss of a metal-oxide semiconductor field-effect transistor (MOSFET) is lower than that of a diode. Therefore, a MOSFET may be used to replace a diode in FIG. 1. However, a structure of the MOSFET is more complex than that of the diode, and if eight MOSFETs are used to completely replace diodes in FIG. 1, a rectifier circuit of a PD has a complex structure and high costs.

[0019] A compromise method is to use four MOSFETs to replace half of the diodes in FIG. 1. FIG. 2 shows a structure of a PD. As shown in FIG. 2, there are only four MOSFETs in a rectifier circuit of the PD, and therefore costs of the rectifier circuit are lower than that of a full-MOSFET rectifier circuit.

20 [0020] Eight contacts of an Ethernet port of the PD belong to a first contact group and a second contact group. The first contact group includes a contact pair 1-2 and a contact pair 3-6. The second contact group includes a contact pair 4-5 and a contact pair 7-8. The contact pair 1-2 is configured to connect to a cable pair 1-2 of an Ethernet cable. The contact pair 3-6 is configured to connect to a cable pair 3-6 of the Ethernet cable. The contact pair 4-5 is configured to connect to a cable pair 4-5 of the Ethernet cable. The contact pair 7-8 is configured to connect to a cable pair 7-8 of the Ethernet cable. In addition, when PSE uses a first cable pair group for power supply, regardless of which contact pair in the first contact group has a low electric potential, a current flows through a MOSFET and a diode in the rectifier circuit. Similarly, when the PSE uses a second cable pair group for power supply, regardless of which contact pair in the second contact group has a low electric potential, a current flows through a MOSFET and a diode in the rectifier circuit. Therefore, a loss of the rectifier circuit of the PD shown in FIG. 2 is lower than that of the PD shown in FIG. 1.

[0021] However, the loss of the rectifier circuit of the PD shown in FIG. 2 is still higher than that of the full-MOSFET rectifier circuit. If the loss of the rectifier circuit can be decreased under a premise that a quantity of MOSFETs is not increased, the rectifier circuit of the PD can be optimized.

5 **[0022]** PoE requires that a PD can accept power supply of any polarity. PSE is probably a network device. A network device mostly uses a medium dependent interface crossover (English: medium dependent interface crossover, MDI-X) port. PoE power supply polarity of the MDI-X port should satisfy that an electric potential of a cable pair 1-2 is lower than that of a cable pair 3-6. Early Power over Ethernet stipulates that an electric potential of a cable pair 7-8 is lower than that
10 of a cable pair 4-5 in PSE. Although in a new Power over Ethernet system, PSE can provide power supply in which an electric potential of a cable pair 7-8 is higher than that of a cable pair 4-5, but the PSE has not been widely used actually. In addition, a crossover cable (English: crossover cable) also has not been widely used. Therefore, based on a premise that an electric potential of the contact pair 1-2 is lower than that of the contact pair 3-6 and an electric potential of the contact pair 7-8 is
15 lower than that of the contact pair 4-5, the rectifier circuit of the PD may be designed to adapt to a most widely used scenario.

[0023] FIG. 3 shows a structure of a PD according to an embodiment of the present invention. The PD includes an Ethernet port 100, a rectifier circuit 200, and a PD circuit 300. The Ethernet port 100 includes a first contact pair 1-2, a second contact pair 3-6, a third contact pair 4-5, and a
20 fourth contact pair 7-8. The first contact pair 1-2 is configured to connect to a cable pair 1-2 of an Ethernet cable. The second contact pair 3-6 is configured to connect to a cable pair 3-6 of the Ethernet cable. The third contact pair 4-5 is configured to connect to a cable pair 4-5 of the Ethernet cable. The fourth contact pair 7-8 is configured to connect to a cable pair 7-8 of the Ethernet cable.

[0024] The rectifier circuit 200 includes four MOSFETs. That the rectifier circuit 200 includes
25 four MOSFETs means that the quantity of MOSFETs in the rectifier circuit 200 is four. The rectifier circuit 200 further includes at least four diodes. The four MOSFETs are a first MOSFET, a second MOSFET, a third MOSFET, and a fourth MOSFET. The first MOSFET, the second MOSFET, the third MOSFET, and the fourth MOSFET are a MOSFET 1, a MOSFET 2, a MOSFET 3, and a MOSFET 4 in FIG. 3. In FIG. 3, the MOSFET 1 is an N-type MOSFET. The MOSFET 2 is a P-type
30 MOSFET. The MOSFET 3 is a P-type MOSFET. The MOSFET 4 is an N-type MOSFET. In an implementation, an additional drive circuit may be designed for the MOSFET 2 and/or the MOSFET 3, and an N-type MOSFET is used as the MOSFET 2 and/or the MOSFET 3. In an implementation, an additional drive circuit may be designed for the MOSFET 1 and/or the MOSFET 4, and a P-type MOSFET is used as the MOSFET 1 and/or the MOSFET 4.

[0025] The at least four diodes in the rectifier circuit 200 include a first diode, a second diode, a third diode, and a fourth diode. The first diode, the second diode, the third diode, and the fourth diode are a diode 1, a diode 2, a diode 3, and a diode 4 in FIG. 3.

[0026] The PD circuit 300 includes at least one PD chip. The PD chip is configured to implement a PD function in processes such as PoE detection and classification. The PD circuit 300 may further include a direct current-direct current (DC-DC) convertor. The PD circuit may further include PD load. A power input positive electrode of the PD circuit 300 receives a high electric potential, and a power input negative electrode of the PD circuit 300 receives a low electric potential.

[0027] The first contact pair 1-2 is connected to an anode of the diode 1, and is connected to a drain electrode of the MOSFET 1. The second contact pair 3-6 is connected to a cathode of the diode 2, and is connected to a drain electrode of the MOSFET 2. The third contact pair 4-5 is connected to a cathode of the diode 3, and is connected to a drain electrode of the MOSFET 3. The fourth contact pair 7-8 is connected to an anode of the diode 4, and is connected to a drain electrode of the MOSFET 4. In an implementation, a source electrode and a drain electrode of one or more MOSFETs may be exchanged.

[0028] A cathode of the diode 1, a source electrode of the MOSFET 2, a source electrode of the MOSFET 3, and a cathode of the diode 4 are connected to each other, and are connected to the power input positive electrode of the PD circuit 300. A source electrode of the MOSFET 1, an anode of the diode 2, an anode of the diode 3, and a source electrode of the MOSFET 4 are connected to each other, and are connected to the power input negative electrode of the PD circuit 300.

[0029] A gate electrode of the MOSFET 1 is connected to the second contact pair 3-6. A gate electrode of the MOSFET 2 is connected to the first contact pair 1-2. A gate electrode of the MOSFET 3 is connected to the fourth contact pair 7-8. A gate electrode of the MOSFET 4 is connected to the third contact pair 4-5. In other words, in the foregoing structure, a gate electrode of a MOSFET connected to each contact pair is connected to the other contact pair in a same contact group as the contact pair, and a voltage of the gate electrode is controlled by an electric potential of the other contact pair. If a PoE supply voltage is greater than a voltage that the gate electrode of the MOSFET can bear, the gate electrode of the MOSFET is connected to the other contact pair by using a control circuit. The control circuit outputs a suitable electric potential to the gate electrode of the MOSFET based on an electric potential difference between the two contact pairs, to turn on or cut off the MOSFET. In FIG. 3, a connecting point between a gate electrode of a MOSFET connected to a contact pair and the other contact pair in a same contact group as the contact pair is

located between a diode and a MOSFET that are connected to the other contact pair. In FIG. 3, the connecting point between the gate electrode of the MOSFET connected to the contact pair and the other contact pair in the same contact group as the contact pair may alternatively be located between the MOSFET connected to the other contact pair and the PD circuit 300.

5 **[0030]** FIG. 3 shows only a structure of the rectifier circuit in this embodiment of the present invention. In addition to the MOSFETs, some components, for example, a capacitor, a resistor, a diode, a bipolar junction transistor (BJT), and a break-over diode, may be added to the rectifier circuit. The rectifier circuit of the PD in FIG. 3 includes only four MOSFETs, and therefore costs of the rectifier circuit are lower than that of a full-MOSFET rectifier circuit.

10 **[0031]** If an electric potential of the cable pair 1-2 is lower than that of the cable pair 3-6, an electric potential of the first contact pair 1-2 is lower than that of the second contact pair 3-6. Because the MOSFET 1 is an N-type MOSFET, the high electric potential of the second contact pair 3-6 may make an electric potential of the gate electrode of the MOSFET 1 higher than that of the source electrode of the MOSFET 1, so as to turn on the MOSFET 1. Because the MOSFET 2 is
15 a P-type MOSFET, the low electric potential of the first contact pair 1-2 may make an electric potential of the gate electrode of the MOSFET 2 lower than that of the source electrode of the MOSFET 2, so as to turn on the MOSFET 2. In addition, the electric potential of the first contact pair 1-2 is lower than that of the second contact pair 3-6, and therefore the diode 1 and the diode 2 are cut off. A current flows from the second contact pair 3-6 to the first contact pair 1-2 after
20 sequentially passing through the MOSFET 2, the PD circuit 300, and the MOSFET 1.

[0032] If an electric potential of the cable pair 7-8 is lower than that of the cable pair 4-5, an electric potential of the fourth contact pair 7-8 is lower than that of the third contact pair 4-5. Because the MOSFET 4 is an N-type MOSFET, the high electric potential of the third contact pair 4-5 may make an electric potential of the gate electrode of the MOSFET 4 higher than that of the
25 source electrode of the MOSFET 4, so as to turn on the MOSFET 4. Because the MOSFET 3 is a P-type MOSFET, the low electric potential of the fourth contact pair 7-8 may make an electric potential of the gate electrode of the MOSFET 3 lower than that of the source electrode of the MOSFET 3, so as to turn on the MOSFET 3. In addition, the electric potential of the fourth contact pair 7-8 is lower than that of the third contact pair 4-5, and therefore the diode 3 and the diode 4 are
30 cut off. A current flows from the third contact pair 4-5 to the fourth contact pair 7-8 after sequentially passing through the MOSFET 3, the PD circuit 300, and the MOSFET 4.

[0033] Because the current passes through only two MOSFETs but does not pass through a diode, if the electric potential of the cable pair 1-2 is lower than that of the cable pair 3-6, and the electric potential of the cable pair 7-8 is lower than that of the cable pair 4-5, a loss of the rectifier

circuit of the PD shown in FIG. 3 is lower than that of the PD shown in FIG. 2. If the electric potential of the cable pair 1-2 is higher than that of the cable pair 3-6 or the electric potential of the cable pair 7-8 is higher than that of the cable pair 4-5, MOSFETs are cut off, corresponding diodes are turned on, and a current passes through two diodes. Although there is no advantage in terms of a power loss, the PD can still work normally in this scenario.

[0034] If the PD is a type-4 (English: Type 4) PD, it is required that PSE be type-4 PSE. The type-4 PSE definitely uses the cable pair 1-2 and the cable pair 7-8 for providing a low electric potential. Therefore, the structure of the PD is particularly suitable for the type-4 PD.

[0035] If the PSE uses only one cable pair group at a detection or classification stage to send a detection or classification voltage, the PSE should not receive, from another cable pair group, a voltage that is sufficient to affect a detection or classification result. For example, if the PSE provides a negative electric potential by using the cable pair 1-2 and uses the cable pair 3-6 as a backflow cable pair, the MOSFET 1 is turned on. If the cable pair 4-5 and the cable pair 7-8 in the PSE are floating, the PSE does not receive a voltage from a group including the cable pair 4-5 and the cable pair 7-8. However, if the cable pair 4-5 is connected to a backflow end in the PSE, the high electric potential of the cable pair 4-5 makes the MOSFET 4 turned on, and the turned-on MOSFET 4 guides a low electric potential to the cable pair 7-8. Therefore, the PSE receives a voltage from the group including the cable pair 4-5 and the cable pair 7-8. The voltage may be referred to as a reflected voltage. The reflected voltage may cause a detection or classification error.

[0036] Because detection or classification is completed when the PSE supplies power, even if the group including the cable pair 4-5 and the cable pair 7-8 receives the reflected voltage, detection or classification is not affected. The reflected voltage does not damage the PSE. Therefore, a control circuit may be added to a gate electrode of each MOSFET. These control circuits are used for turning on the MOSFETs only when a voltage of a contact group is less than a voltage threshold. The MOSFETs are not turned on when the voltage of the contact group is greater than the voltage threshold. When the voltage of the contact group is equal to the voltage threshold, processing is performed according to one of the foregoing cases. Because a negative electric potential is usually used for power supply in PoE, the voltage threshold is negative. That the voltage of the contact group is less than the voltage threshold means that an absolute value of the voltage of the contact group is greater than that of the voltage threshold. Because a classification error usually does not generate a serious problem, the voltage threshold may be between a maximum PoE detection voltage and a minimum PoE supply voltage. In other words, the absolute value of the voltage threshold is greater than that of the maximum PoE detection voltage and less than or equal to that of the minimum PoE supply voltage. The absolute value of the voltage threshold may alternatively be

greater than that of a maximum PoE classification voltage. Voltage thresholds of the control circuits may be the same or may be different, as long as the values are between the maximum PoE detection voltage and the minimum PoE supply voltage.

[0037] For example, FIG. 4 shows a structure of a PD according to an embodiment of the present invention. In FIG. 4, two resistors that are connected in series between a pair of contacts are used as a control circuit. An MOSFET in FIG. 4 is a power MOSFET (English: power MOSFET).

[0038] A control circuit 210 includes a resistor R1 and a resistor R2. Resistance values of the resistor R1 and the resistor R2 satisfy the following conditions: $R1 \cdot V_D / (R1 + R2) < V_{th1}$, and $R1 \cdot V_{PoE} / (R1 + R2) > V_{th1}$, where V_D is an absolute value of a maximum PoE detection voltage; V_{PoE} is an absolute value of a minimum PoE supply voltage; and V_{th1} is a critical voltage of a MOSFET 1.

[0039] A control circuit 220 includes a resistor R3 and a resistor R4. Resistance values of the resistor R3 and the resistor R4 satisfy the following conditions: $R3 \cdot V_D / (R3 + R4) < V_{th2}$, and $R3 \cdot V_{PoE} / (R3 + R4) > V_{th2}$, where V_{th2} is a critical voltage of a MOSFET 2.

[0040] A control circuit 230 includes a resistor R5 and a resistor R6. Resistance values of the resistor R5 and the resistor R6 satisfy the following conditions: $R5 \cdot V_D / (R5 + R6) < V_{th3}$, and $R5 \cdot V_{PoE} / (R5 + R6) > V_{th3}$, where V_{th3} is a critical voltage of a MOSFET 3.

[0041] A control circuit 240 includes a resistor R7 and a resistor R8. Resistance values of the resistor R7 and the resistor R8 satisfy the following conditions: $R7 \cdot V_D / (R7 + R8) < V_{th4}$, and $R7 \cdot V_{PoE} / (R7 + R8) > V_{th4}$, where V_{th4} is a critical voltage of a MOSFET 4.

[0042] During detection, the MOSFET 1 and the MOSFET 4 are not turned on. However, a power MOSFET usually includes a parasitic body diode (English: body diode). An anode of the body diode is a source electrode of the power MOSFET, and a cathode of the body diode is a drain electrode of the power MOSFET. A detection current may flow through a body diode of the MOSFET 1. A source electrode of the MOSFET 4 is connected to a low electric potential point, and therefore the detection current does not flow through the MOSFET 4. Although a loss is increased because the MOSFET 1 is not turned on, a purpose of detection at a detection stage is detecting an effective PD but not providing power supply, and therefore the loss does not cause a negative effect as long as a detection result is not affected. Similarly, a detection operation on a group including contacts 4, 5, 7, and 8 may also be correctly performed.

[0043] The foregoing requirements on the control circuit 230 and control circuit 240 may alternatively be omitted, because the detection result is not affected even if the MOSFET 2 and the MOSFET 3 are turned on when a contact pair 1-2 receives a detected electric potential. In addition, if a contact pair 3-6 or a contact pair 4-5 receives a low electric potential, a detection current flows

through a diode. Therefore, designs of control circuits of the MOSFET 2 and the MOSFET 3 may be different from designs of control circuits of the MOSFET 1 and the MOSFET 4.

[0044] For another example, FIG. 5 shows another structure of a PD according to an embodiment of the present invention. In FIG. 5, a combination of a resistor and a break-over diode is used as a control circuit. A suitable break-over diode is selected during design of the PD. For example, the break-over diode may be a Zener diode or an avalanche diode. A breakdown voltage of the break-over diode is the foregoing voltage threshold. In this way, only when there is a negative electric potential of a PoE power supply level on a cable pair 1-2 or a cable pair 7-8, a control circuit 210 and a control circuit 240 respectively turn on a MOSFET 1 and a MOSFET 4.

[0045] The control circuit in FIG. 5 includes a resistor, to prevent a MOSFET from being damaged by an excessively high electric potential on a gate electrode. If the MOSFET can bear a maximum PoE power supply voltage (for example, -57 volts (V)), the resistor in the control circuit may be omitted.

[0046] Based on a cause the same as that in the foregoing, although break-over diodes are added to a control circuit 220 and a control circuit 230 in FIG. 5, the two break-over diodes may be omitted.

[0047] FIG. 4 and FIG. 5 show only two possible implementations of a control circuit. The control circuit may further include other components, for example, a capacitor, a diode, and a BJT.

[0048] The foregoing descriptions are merely specific implementations of the present invention, but are not intended to limit the protection scope of the present invention. Any variation or replacement readily figured out by a person skilled in the art within the technical scope disclosed in the present invention shall fall within the protection scope of the present invention. Therefore, the protection scope of the present invention shall be subject to the protection scope of the claims.

CLAIMS

1. A powered device (PD), comprising an Ethernet port, a rectifier circuit, and a PD circuit, wherein

the Ethernet port comprises a first contact pair, a second contact pair, a third contact pair, and a fourth contact pair, wherein the first contact pair is configured to connect to a cable pair 1-2 of an Ethernet cable; the second contact pair is configured to connect to a cable pair 3-6 of the Ethernet cable; the third contact pair is configured to connect to a cable pair 4-5 of the Ethernet cable; and the fourth contact pair is configured to connect to a cable pair 7-8 of the Ethernet cable;

the rectifier circuit comprises four metal-oxide semiconductor field-effect transistors (MOSFET) and at least four diodes, wherein

the four MOSFETs are a first MOSFET, a second MOSFET, a third MOSFET, and a fourth MOSFET;

the at least four diodes comprise a first diode, a second diode, a third diode, and a fourth diode;

the first contact pair is connected to an anode of the first diode, and is connected to a first end of the first MOSFET;

the second contact pair is connected to a cathode of the second diode, and is connected to a first end of the second MOSFET;

the third contact pair is connected to a cathode of the third diode, and is connected to a first end of the third MOSFET;

the fourth contact pair is connected to an anode of the fourth diode, and is connected to a first end of the fourth MOSFET;

a power input positive electrode of the PD circuit is connected to a cathode of the first diode, is connected to a second end of the second MOSFET, is connected to a second end of the third MOSFET, and is connected to a cathode of the fourth diode; and

a power input negative electrode of the PD circuit is connected to a second end of the first MOSFET, is connected to an anode of the second diode, is connected to an anode of the third diode, and is connected to a second end of the fourth MOSFET.

2. The PD according to claim 1, wherein

a gate electrode of the first MOSFET is connected to the second contact pair;

a gate electrode of the second MOSFET is connected to the first contact pair;

a gate electrode of the third MOSFET is connected to the fourth contact pair; and

a gate electrode of the fourth MOSFET is connected to the third contact pair.

3. The PD according to claim 2, wherein the first MOSFET is an N-type MOSFET; the second

MOSFET is a P-type MOSFET; the third MOSFET is a P-type MOSFET; and the fourth MOSFET is an N-type MOSFET.

4. The PD according to claim 3, wherein the first end of the first MOSFET is a drain electrode of the first MOSFET; the second end of the first MOSFET is a source electrode of the first MOSFET; the first end of the second MOSFET is a drain electrode of the second MOSFET; the second end of the second MOSFET is a source electrode of the second MOSFET; the first end of the third MOSFET is a drain electrode of the third MOSFET; the second end of the third MOSFET is a source electrode of the third MOSFET; the first end of the fourth MOSFET is a drain electrode of the fourth MOSFET; and the second end of the fourth MOSFET is a source electrode of the fourth MOSFET.

5. The PD according to claim 4, wherein the rectifier circuit further comprises a first control circuit and a second control circuit;

the gate electrode of the first MOSFET is connected to the second contact pair through the first control circuit;

the gate electrode of the fourth MOSFET is connected to the third contact pair through the second control circuit;

the first control circuit is configured to: when a value obtained by subtracting an electric potential of the first contact pair from an electric potential of the second contact pair is greater than a first voltage threshold, turn on the first MOSFET; and when the value obtained by subtracting the electric potential of the first contact pair from the electric potential of the second contact pair is less than the first voltage threshold, cut off the first MOSFET, wherein an absolute value of the first voltage threshold is greater than that of a maximum Power over Ethernet PoE detection voltage and less than or equal to that of a minimum PoE supply voltage; and

the second control circuit is configured to: when a value obtained by subtracting an electric potential of the fourth contact pair from an electric potential of the third contact pair is greater than a second voltage threshold, turn on the fourth MOSFET; and when the value obtained by subtracting the electric potential of the fourth contact pair from the electric potential of the third contact pair is less than the second voltage threshold, cut off the fourth MOSFET, wherein an absolute value of the second voltage threshold is greater than that of the maximum PoE detection voltage and greater than or equal to the absolute value of the minimum PoE supply voltage.

6. The PD according to any one of claims 1 to 5, wherein the PD is a type-4 PD.