

[0001] METHOD AND APPARATUS FOR SUBCARRIER AND
 ANTENNA SELECTION IN MIMO-OFDM SYSTEM

[0002] FIELD OF INVENTION

[0003] The present invention is related to a wireless communication system. More particularly, the present invention transmits a data stream using multiple antennas in an orthogonal frequency division multiplexing (OFDM) communication system.

[0004] BACKGROUND

[0005] OFDM is a data transmission scheme where data is split into a plurality of smaller streams and each stream is transmitted using a sub-carrier with a smaller bandwidth than the total available transmission bandwidth. Figure 1 shows a graphical representation of orthogonal sub-carriers in OFDM. The efficiency of OFDM depends on choosing these sub-carriers orthogonal to each other. In other words, the sub-carriers do not interfere with each other while each carrying a portion of the total user data.

[0006] OFDM system has advantages over other wireless communication systems. When the user data is split into streams carried by different sub-carriers, the effective data rate on each subcarrier is much smaller. Therefore, the symbol duration is much larger. A large symbol duration can tolerate larger delay spreads. In other words, it is not affected by multipath as severely. Therefore, OFDM symbols can tolerate delay spreads that are typical in other wireless communication systems, and do not require complicated receiver designs to recover from multipath delay.

[0007] As shown in Figure 2, splitting the data stream into multiple parallel transmission streams still keeps the basic user data rate the same. Since each symbol duration increases proportionally, any delay spread is proportionally smaller. In practical implementations, the number of subcarriers is from 16 to 2,048.

[0008] Another advantage of OFDM is that the generation of orthogonal sub-carriers at the transmitter and receiver can be done by using inverse fast

Fourier transform (IFFT) and fast Fourier transform (FFT) engines. Since the IFFT and FFT implementations are well known, OFDM can be implemented easily and does not require complicated receivers.

[0009] Figure 3 is a block diagram of an exemplary OFDM transmitter and receiver. The heart of the transmitter and receiver are IFFT and FFT blocks. IFFT and FFT operations are mathematically almost the same. Therefore, a single computation engine is typically used for both IFFT and FFT operations.

[0010] For the benefits that OFDM provides, (i.e., simpler implementation, resistance to larger delay spreads, and efficient use of the spectrum), OFDM is one of the preferred wireless transmission schemes today. It is used in WLAN air interface such as 802.11a, WMAN such as 802.16, and it is part of many wireless communication standards.

[0011] Multiple-input multiple-output (MIMO) refers to the type of wireless transmission and reception scheme where both a transmitter and a receiver employ more than one antenna. Figure 4 shows such a MIMO transmitter and receiver. A MIMO system takes advantage of the spatial diversity or spatial multiplexing and improves signal-to-noise ratio (SNR) and increases throughput.

[0012] There are primarily two types of MIMO systems. One type of MIMO system maximizes transmission data rate by taking advantage of the parallel transmissions with MIMO. An example of this type of MIMO scheme is the BLAST system. In this type of a system, the data stream is split into multiple parallel streams and sent across the air interface in parallel. Using a successive interference canceller (SIC) type detector, the receiver separates and collects all parallel streams. Therefore, the effective data rate over the air is increased.

[0013] Another type of MIMO system is Space-Time Coding (STC). An STC system provides a much more robust link and therefore can support higher signal constellations. In other words, STC increases the data rate over the air interface by increasing the signaling order, and therefore increasing the effective data rate over the air. An example of STC for a 2X2 MIMO is the so called Alamouti codes.

[0014] One of the techniques for increasing the efficiency of OFDM is "waterpouring" and refers to the way that the transmit power of each sub-carrier in OFDM is selected. Figure 5 shows a typical waterpouring process. The transmitter obtains the channel estimation (step 1), inverts it (step 2), and allocates power to the corresponding sub-carriers starting from the lowest point until the total transmit power is reached (step 3). In order to implement waterpouring, the channel gain information across the transmission band should be known at the transmitter. The receiver may send channel estimation information back to the transmitter in a closed loop manner, or the transmitter can infer the channel from the signals received from the other side.

[0015] Figure 6 shows a block diagram of a prior art MIMO system, such as VBLAST, where data is converted to parallel and transmitted over multiple antennas.

[0016] Figures 7 and 8 show a prior art scheme for controlling transmit power or modulation and coding scheme per antenna basis. In prior art, transmit power or modulation and coding scheme are determined in accordance with average channel gain or other metric. This scheme introduces flexibility by allowing the transmitter to allocate transmit power or modulation and coding scheme differently to different antennas based on channel response seen at the receiver for each transmit antenna.

[0017] Figure 9 is a block diagram of a prior art system for operation in CDMA based systems known as PARC (per antenna rate control). This scheme transmits using the full transmit bandwidth from each antenna, as typical of any CDMA system. The prior art systems only address per antenna rate control, and not well suited for OFDM application since they are not making use of the sub-carrier level resource allocation available in OFDM.

[0018] Figure 10 is a block diagram of another prior art system, called S-PARC (selective per antenna rate control). This scheme transmits using the full transmit bandwidth from each antenna, as typical of any CDMA system.

[0019] Prior art systems are not capable of taking advantage of the subcarrier level resource allocation that OFDM enables. The prior art system

adjusts transmit power for each antenna transmission according to average gain across the band that the receiver sees from each transmit antenna. Therefore, the prior art systems are not suitable for OFDM where sub-carrier level resource control is available.

[0020]

SUMMARY

[0021] The present invention is related to a method and apparatus for radio resources control in an MIMO-OFDM system. Channel metric is calculated for each of a plurality of transmit antennas. Sub-carriers are allocated to each transmit antenna in accordance with the channel metric of each transmit antenna. Signals are transmitted using the allocated sub-carriers at each antenna. Adaptive modulation and coding and transmit power control of each sub-carrier may be further implemented in accordance with the channel metric. Power control may be implemented per antenna basis or per sub-carrier basis. In performing power control, a subset of transmit antennas may be selected and waterpouring may be applied only to the selected antennas. Waterpouring may be based on SNR instead of channel response. With the scheme of sub-carrier level resource control and power control, an additional dimension of flexibility is provided to optimize the system and increase practical throughput and link margin.

[0022]

BRIEF DESCRIPTION OF THE DRAWINGS

[0027] Figure 1 shows a graphical representation of orthogonal sub-carriers in OFDM.

[0028] Figure 2 is an illustration of splitting data streams into multiple parallel transmission streams.

[0029] Figure 3 is a block diagram of an OFDM transmitter and receiver.

[0030] Figure 4 is a block diagram of a prior art MIMO system.

[0031] Figure 5 shows a waterpouring procedure.

[0032] Figure 6 is a block diagram of a prior art MIMO system.

[0033] Figure 7 is a diagram showing prior art method for controlling transmit power in MIMO system.

[0034] Figure 8 is a diagram showing prior art method for adaptive modulation and coding in MIMO system.

[0035] Figure 9 is a block diagram of a transmitter implementing prior art PARC scheme.

[0036] Figure 10 is a block diagram of a transmitter implementing prior art S-PARC scheme.

[0037] Figure 11 is a diagram showing allocation of sub-carriers in accordance with a first embodiment of the present invention.

[0038] Figure 12 is a block diagram of a transmitter in accordance with the first embodiment of the present invention.

[0039] Figure 13 is a diagram showing AMC.

[0040] Figure 14 is a block diagram of a waterfilling variation of the present invention.

[0041] Figure 15 is a block diagram of a transmitter in accordance with another embodiment of the present invention.

[0042] Figure 16 is a diagram showing application of waterpouring technique in accordance with the present invention.

[0043] Figure 17 is a diagram showing application of SNR-based waterpouring technique in accordance with the present invention.

[0044] Figure 18 is a flow diagram of a process for sub-carrier and antenna selection in an MIMO-OFDM communication system in accordance with the present invention.

[0045] DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

[0046] The present invention will be described with reference to the drawing figures wherein like numerals represent like elements throughout.

[0047] Described below are the preferred embodiments of the present invention relating to the use of sub-carrier level resource allocation along with selection of antennas, modulation order, coding scheme, transmit power level, or

the like in order to make full use of the capabilities of OFDM and MIMO.

[0048] The present invention can be implemented both in a wireless transmit/receive unit (WTRU) and a base station. The terminology "WTRU" includes, but is not limited to, a user equipment, a mobile station, a fixed or mobile subscriber unit, a pager, or any other type of device capable of operating in a wireless environment. The terminology "base station" includes, but is not limited to, a Node-B, a site controller, an access point or any other type of interfacing device in a wireless environment.

[0049] Figure 11 is a diagram showing sub-carrier level resource allocation in accordance with a first embodiment of the present invention. Channel metric is calculated for each transmit antenna and sub-carriers are selected and allocated to each transmit antenna in accordance with the channel metric. All, a subset or none of sub-carriers are allocated to each transmit antenna. The set of sub-carriers allocated to each transmit antenna may be distinct from one another if such flexibility is desired or may be the same for simplicity. This gives flexibility to compromise between better link margin versus better throughput and permits more flexibility in resource allocation.

[0050] Since not all MIMO channels behave the same, but some channels are impaired or fade more than the others, and channel response is a time varying behavior and is frequency selective, it is not optimum to transmit all sub-carriers through all antennas. Better overall link quality can be achieved when a set of sub-carriers are transmitted on channels having sufficient quality for a constant average transmit power.

[0051] Figure 12 is a block diagram of a transmitter 100 in accordance with the present invention. The transmitter 100 comprises a plurality of antennas 102, a serial-to-parallel converter 104, a channel estimator 106, a sub-carrier modulation unit 108, and a controller 110. A serial input data is converted to a plurality of parallel data streams. Each data stream is modulated by the sub-carrier modulation unit 108 and forwarded to each transmit antenna 102 for transmission.

[0052] The channel estimator 106 calculates channel metric from measurements or quality indicators for each of transmit antennas 102. The channel metric may be estimated by the transmitter 100 in an open loop manner or may be reported from other communicating entity in a closed loop manner. In an open loop case, the channel estimator 106 performs channel estimation from the received signals, and in a closed loop case, a communication entity that receives communication signals from the transmitter 100 performs channel estimation and reports it back to the transmitter 100.

[0053] Each data stream is modulated by the sub-carrier modulation unit 108 in accordance with output signals from the controller 110. The controller 110 selects all, subset or none of sub-carriers for each transmit antenna 102 in accordance with the channel metric of each antenna 102. For example, if a channel gain is used as a channel metric, the controller 110 selects sub-carriers that exceed a predetermined threshold. A different, same or overlapping set of sub-carriers may be allocated to each antenna.

[0054] Optionally, the transmitter 100 may further perform adaptive modulation and coding (AMC) and power control per transmit antenna. The transmitter 100 includes an AMC unit 112 and/or a gain 114 for each transmit antenna and adjusts modulation order/coding rate and/or transmit power of each transmit antenna (per antenna power control) in accordance with the channel metric of each transmit antenna 102.

[0055] Figure 13 shows a scheme of AMC for each transmit antenna. As shown in Figure 13, a different modulation order or coding rate may be applied to each transmit antenna 102 in accordance with channel metric of each transmit antenna 102. The AMC unit 112 adjusts modulation order and/or coding rate applied to data stream for each transmit antenna 102 in accordance with control signal from the controller 110.

[0056] The transmit power level for each transmit antenna is adjusted at the gain device 114 in accordance with control signal from the controller 110. The transmit power control may be either open loop or closed loop.

[0057] Figure 14 is a block diagram of another embodiment of the present invention. The transmitter 100 further includes a mapper 118 for mapping each data stream to a transmit antenna 102 in addition to the elements of the first embodiment. The mapper 118 selects a transmit antenna 102 and cross-connects each data stream to a transmit antenna 102 in accordance with the control signal from the controller 110.

[0058] In this embodiment, the MIMO scheme selects one or more antennas for transmission based on a metric that is calculated using measurements and quality indicators reported or estimated, and in addition the scheme selects all available subcarriers or a subset of them for transmission. In other words, the scheme selects the combination of best antenna, or a set of antennas, and subcarriers. Note that subsets or subcarriers may be distinct for each antenna if such flexibility is desired or constrained to be the same for simplicity sake. This gives the operator of the system flexibility to compromise between better link margin versus better throughput and permits more flexibility in resource allocation during scheduling. Both open loop or closed loop schemes may be used.

[0059] Not all MIMO channels behave the same, some are impaired or fade more than the others or exhibit unfavorable correlation to other channels. This behavior is a time varying and frequency selective behavior. Therefore, it is not optimum to transmit all subcarriers in all channels. Better link quality can be achieved when a set of subcarriers are transmitted on better quality channels for a constant average transit power within any applicable power spectral density requirements.

[0060] This embodiment recognizes that the quality of each MIMO channel and each OFDM subcarrier (channel) will in general be different and time varying, and that a diversity/capacity advantage can be gained by intelligent usage of those channels. The channel qualities may be signaled to, or estimated by, the transmitter. Complexity and regulations in some implementations may limit the antenna/frequency flexibility.

[0061] In accordance with another embodiment, the transmitter 100 further implements transmit power control for each sub-carrier. Figure 15 is a

block diagram of a transmitter 100 in accordance with a second embodiment of the present invention. The transmitter 100 further comprises a sub-carrier TPC unit 116 for each transmit antenna 102 in addition to the elements of the first embodiment.

[0062] The sub-carrier TPC unit 116 adjusts transmit power level for each sub-carrier in accordance with control signal from the controller 110. Sub-carrier level transmit power control is, preferably, a waterpouring technique, although other techniques may be used. The transmit power level of each sub-carrier is adjusted according to the channel response for each sub-carrier. Therefore, the transmit power level across the transmission band is different for each sub-carriers or groups of sub-carriers.

[0063] The waterpouring algorithm preferably operates across all antennas and all subcarriers and adjusts the transmit power level for each subcarrier. However, this is sometimes not desirable. When a full set of N transmit antennas and M receive antennas are used, the complexity of the receiver is typically proportional to M^4N^4 . In other words, the complexity of the receiver is affected by the number of antennas at the transmitter and the receiver. Moreover, it is often the case that not all antenna signals go through desirable channel conditions.

[0064] Another embodiment of the present invention is an enhancement to the aforementioned waterpouring technique. In accordance with this embodiment, a subset of transmit antenna is selected for transmission and waterpouring is applied only to the selected transmit antenna(s). Figure 16 shows selection of a transmit antenna in accordance with channel response of each transmit antenna. In Figure 16, antennas 102_a, 102_c, 102_d are selected for transmission and antenna 102_b is excluded from transmission. After a subset of antennas, such as antennas 102_a, 102_c, 102_d, is selected, a waterpouring technique, or alternative technique may be applied to the selected transmit antennas.

[0065] The number of transmit antennas 102 is maintained at a reasonable number, (may be predetermined), and keeps the receiver complexity down. At

the same time, by selecting the best antenna combination overall performance is maintained.

[0066] In accordance with another embodiment of the present invention, waterpouring is implemented based on SNR, instead of channel response. This technique considers the impact of the noise level present at each sub-carrier. Typically, the background noise is treated as being white. In other words, the background noise is assumed to be the same level for all sub-carriers. This assumption is typically not correct for unlicensed bands. In unlicensed bands, other transmissions can overlap with part of the sub-carriers in the transmission band and the received signal may be subject to substantially different levels of interference regardless of the channel response. Therefore, SNR can provide a better metric for each sub-carrier or group of sub-carriers, although other interference/noise/signal measurements may be used, such as signal to interference ratio (SIR) or signal to interference noise ratio (SINR). The background noise level can be substantially different for different part of spectrum, and hence the preferred solution may be different than the one that assumes a flat noise spectrum.

[0067] Figure 17 illustrates a scheme of SNR-based waterpouring. Figure 17 shows both channel response and SNR for the OFDM spectrum. Sub-carriers are selected and transmit power is allocated in accordance with the SNR. Compared to Figure 16, which waterpouring is based on channel response, in Figure 17, some of the subcarriers are newly added and some are removed. This embodiment better accommodates and preserves high performance in cases where the background noise level across the spectrum is changing in addition to the channel response.

[0068] Figure 18 is a flow diagram of a process 200 for sub-carrier and antenna selection in an MIMO-OFDM communication system. Channel metric for each of a plurality of transmit antennas is obtained (step 202). Sub-carriers are allocated to each antenna in accordance with the channel metric of each antenna (step 204). Messages are transmitted using the allocated sub-carriers at each antenna (step 206). AMC may be performed per antenna basis, per sub-

carrier or group of sub-carrier basis. Power control may be implemented per antenna basis or per sub-carrier basis. In performing power control per sub-carrier basis, a subset of transmit antennas may be selected and waterpouring may be applied only to the selected antennas. Waterpouring may be based on SNR instead of channel response.

[0069] The elements of Figures 12, 14 and 15 may be implemented using a single integrated circuit (IC), such as an application specific integrated circuit (ASIC), multiple ICs, discrete components or a combination of IC(s) and discrete components.

[0070] Although the features and elements of the present invention are described in the preferred embodiments in particular combinations, each feature or element can be used alone without the other features and elements of the preferred embodiments or in various combinations with or without other features and elements of the present invention.

* * *

CLAIMS

What is claimed is:

1. A method for a multiple input multiple output (MIMO) orthogonal frequency division multiplexing (OFDM) communication system, the method comprising:

obtaining channel metric for each of a plurality of transmit antennas;
allocating sub-carriers to each antenna in accordance with the channel metric of each antenna, wherein a potential allocation of the sub-carriers is not all of the sub-carriers; and
transmitting signals using the allocated sub-carriers at each antenna.

2. The method of claim 1 further comprising the step of performing adaptive modulation and coding (AMC) for each antenna.

3. The method of claim 2 wherein the AMC is performed per antenna basis.

4. The method of claim 3 wherein the AMC is further performed per sub-carrier basis.

5. The method of claim 3 wherein the AMC is performed per a group of sub-carriers basis.

6. The method of claim 1 further comprising the step of applying per-antenna power control of the allocated sub-carriers.

7. The method of claim 1 wherein transmit power of each sub-carrier is adjusted in accordance with the channel metric.

8. The method of claim 7 further comprising the step of selecting a subset of transmit antennas, whereby adjusting transmit power of each sub-carrier only for the selected transmit antennas.

9. The method of claim 8 wherein the number of selected antenna is predetermined.

10. The method of claim 7 wherein the channel metric is a signal-to-noise ration (SNR).

11. The method of claim 7 wherein the channel metric is a channel response.

12. The method of claim 1 further comprising the step of selecting a subset of transmit antennas, whereby allocating sub-carriers only to the selected transmit antennas.

13. The method of claim 1 wherein the channel metric is estimated by a transmitter in an open loop manner.

14. The method of claim 1 wherein the channel metric is reported to the transmitter in a closed loop manner.

15. The method of claim 1 further comprising the step of mapping and cross-connecting data streams to an antenna.

16. A transmitter for transmitting signals in an orthogonal frequency division multiplexing (OFDM) communication system, the transmitter comprising:

a plurality of transmit antennas;

a channel estimator for obtaining channel metric for each of a plurality of transmit antennas; and

a controller for allocating sub-carriers to each antenna in accordance with the channel metric of each antenna, wherein a potential allocation of the sub-carriers is not all of the sub-carriers.

17. The transmitter of claim 16 wherein the controller performs adaptive modulation and coding (AMC) for each antenna.

18. The transmitter of claim 17 wherein the AMC is performed per antenna basis.

19. The transmitter of claim 18 wherein the AMC is performed per sub-carrier basis.

20. The transmitter of claim 17 wherein the AMC is performed per a group of sub-carrier basis.

21. The transmitter of claim 16 wherein the controller performs per-antenna power control of the allocated sub-carriers.

22. The transmitter of claim 16 wherein transmit power of each sub-carrier is adjusted in accordance with the channel metric.

23. The transmitter of claim 22 wherein the controller selects a subset of transmit antennas, whereby transmit power of each sub-carrier is adjusted only for the selected transmit antennas.

24. The transmitter of claim 23 wherein the number of selected transmit antennas is predetermined.

25. The transmitter of claim 22 wherein the channel information is a signal-to-noise ration (SNR).

26. The transmitter of claim 22 wherein the channel information is a channel response.

27. The transmitter of claim 16 wherein the controller selects a subset of transmit antennas, whereby allocates sub-carriers only to the selected transmit antennas.

28. The transmitter of claim 16 wherein the channel information is estimated by a transmitter in an open loop manner.

29. The transmitter of claim 16 wherein the channel information is reported to the transmitter in a closed loop manner.

30. The transmitter of claim 16 further comprising a mapper for mapping and cross-connecting data streams to an antenna.