

Translation**International Patent Application No: PCT/EP2007/007676****Antenna coupler**

5

The invention relates to an antenna coupler for testing a transmitter and/or a receiver device, in particular, a mobile telephone.

- 10 An antenna coupler is used for testing a transmitter and/or a receiver device, in particular, a mobile telephone. The antenna coupler allows a complete final testing of the mobile telephone, because radio properties of the mobile telephone, in particular the antenna efficiency, are tested.
- 15 Moreover, in testing the mobile telephone, a plurality of properties and/or parameters of the mobile telephone are investigated, which can be roughly subdivided into transmitter tests and receiver tests. For example, in the case of a transmitter test, a measurement of the phase
- 20 error, the frequency error, the power and/or the spectrum is implemented. In the case of a reception test, for example, bit-error rates are measured.

- The coupling of the transmitter and/or the receiver device
- 25 is effected via an antenna element provided on the antenna coupler, wherein the coupling factor, which indicates the ratio of the received power relative to the overall transmitted power of the transmitter and/or receiver device, should remain as unchanged as possible in the event of
- 30 changes of position of the transmitter and/or receiver device. An antenna coupler of this kind is known from DE 101 29 408 A1.

- However, the antenna coupler disclosed in DE 101 29 408 A1
- 35 has proved inadequate for testing a transmitter and/or

receiver device with an antenna arrangement, which provides several antennas, operating in a MIMO (multiple-in multiple-out) system, in a Smart-Antenna system or according to an Antenna-Diversity method.

5

The invention is therefore based upon the object of providing an antenna coupler, which is particularly suitable for testing a transmitter and/or receiver device, which has a complex radiation characteristic and/or reception

10 characteristic.

The object named is achieved according to the invention by the features of claim 1. Advantageous further developments form the subject matter of the dependent claims relating

15 back to claim 1.

In order to test a transmitter or receiver device providing a particularly complex radiation characteristic and/or reception characteristic, the antenna coupler comprises

20 several antenna elements, which are arranged on the antenna coupler in such a manner that directions of maximum sensitivity or respectively directions of maximum radiation of the antenna elements of the antenna coupler are orientated differently in space. Furthermore, the antenna
25 coupler provides a holding element for holding the transmitter and/or receiver device. The transmitter or receiver device is designed, in particular, as a mobile telephone.

30 The advantages achieved with the invention are, in particular, that properties of a transmitter and/or of a receiver device, which is operated in a MIMO system and provides an antenna arrangement with several antennas arranged, for example, in linear independence of one
35 another, can be analysed as a complete device (DUT) in a

very reliable manner by means of the antenna coupler according to the invention.

Moreover, the antenna coupler according to the invention is
5 suitable for testing a transmitter and/or receiver device operated in a Smart-Antenna system or according to the Antenna-Diversity method.

Furthermore, the antenna coupler according to the invention
10 is designed for reception and/or transmission of differently-polarised waves and is particularly suitable for testing a transmitter and/or receiver device, which is designed as a mobile telephone or as a blue-tooth device.

15 With a different spatial orientation of the directions of maximum sensitivity of the antenna elements, radiation characteristics of the transmitter, for example, of a MIMO system, can be analysed very accurately for the transmitter test by means of the antenna coupler according to the
20 invention.

For the receiver test, the antenna coupler generates different radiation-diagram configurations by means of different spatial orientation of the directions of maximum
25 radiation of the antenna elements. Through external connection of the antenna coupler, the receiver device can be irradiated simultaneously with beams from several different directions, wherein the different beams can carry the same or different signals. If one beam carries the
30 useful signal and another carries the interference signal, the directionally-selective reception of the useful signal in combination with the directionally-selective suppression of the interference signal can be tested. The differentiation of useful signals from different beams is
35 the essence of a MIMO system and can be represented by this

antenna coupler. That is to say, an antenna coupler of this kind supports not only the very accurate testing of the receiver properties and directional-reception properties; as the last example shows, it is also meaningful for receiver and protocol testing of a MIMO transmitter/receiver.

According to one advantageous development, one or more of the antenna elements are orientated with the direction of maximum sensitivity and/or the direction of maximum radiation facing towards the transmitter and/or receiver device. The antenna elements can expediently be orientated independently of one another. For this purpose, the antenna coupler preferably provides an orientation device.

In one expedient further development, the power transmitted from the antenna elements can be adjusted separately at each antenna element through feeding.

According to one advantageous further development, the antenna elements are each positioned on the antenna coupler at an appropriate spacing distance from the transmitter and/or the receiver device.

Dependent upon the purpose of the test, the spacing distance between the transmitter and/or the receiver device and one or more of the antenna elements of the antenna coupler is $\lambda/4$, (near field) or multiples of λ (distant field), wherein λ corresponds to the wavelength of the wave received or respectively radiated by the respective antenna element.

30

According to one advantageous development, several antenna elements of the antenna coupler are provided on coordinate axes of a coordinate system, wherein the transmitter and/or

receiver device is expediently arranged at the coordinate origin.

According to one advantageous further development, the
5 coordinate axes extend in an orthogonal manner relative to one another, so that the coordinate system is a Cartesian coordinate system.

For a particularly accurate analysis of the radiation
10 characteristic and/or the reception characteristic of the transmitter and/or receiver device, an antenna element is provided respectively both in the positive coordinate-axis direction and also in the negative coordinate-axis direction on the coordinate axes of the coordinate system.

15 According to one advantageous embodiment, the antenna elements of the antenna coupler are disposed at corners of an octahedron, wherein the transmitter and/or receiver device is expediently disposed at the centre point of the
20 octahedron.

According to one advantageous embodiment, the antenna elements of the antenna coupler are designed as rod
antennas, as loop antennas, as Yagi antennas or in a mixed
25 manner as rod antennas, Yagi antennas and loop antennas.

In one expedient further development, the antenna element designed as a loop antenna is substantially of a circular-ring shape and is expediently designed as a substantially-
30 closed loop, wherein a minimum-possible spacing distance is preferably provided between the feedpoint at a feeder end of the loop and a loop end disposed opposite to the feeder end of the loop. The antenna element designed as a loop element expediently comprises an outer conductor and an inner
35 conductor, which is preferably guided outwards from the

outer conductor in the region of the feeder end of the loop and/or in the region of the loop end disposed opposite to the latter and is expediently connected to the outer conductor in an electrically-conductive manner. According to one advantageous embodiment, the antenna element designed as a loop antenna is held by a holder, for example, made of Teflon.

According to one advantageous further development, the circumference of the antenna element designed as a loop antenna corresponds substantially to the mean wavelength λ of the wave radiated and/or received via the antenna element.

The polarisation direction of the waves radiated and/or received by the antenna element designed as a loop antenna is expediently adjustable. For this purpose, the antenna element is preferably mounted in a rotatable manner about a central axis, which is orientated perpendicular to a plane formed by the loop.

In an expedient further development, the antenna element designed as a loop antenna is orientated, with reference to the transmitter and/or the receiver device preferably provided at the coordinate origin of the coordinate system, in such a manner that the central axis of the loop antenna is directed towards the transmitter and/or receiver device.

In an advantageous further development, the connections between the respective antenna elements of the antenna coupler and the external contact of the antenna coupler of the same electrical length, is known to the user.

In order to fix the transmitter and/or receiver device to the holding element, the holding element preferably provides a fastening device.

- 5 Exemplary embodiments of the invention are explained in greater detail below with reference to the drawings. The drawings are as follows:

- Figure 1 shows schematically a longitudinal section
10 through an antenna coupler with antenna elements designed as loop antennas and a transmitter and/or receiver device designed as a mobile telephone;
- 15 Figure 2 shows schematically a plan view of an antenna coupler with antenna elements designed as loop antennas and a transmitter and/or receiver device designed as a mobile telephone;
- 20 Figure 3 shows schematically a plan view of an antenna coupler with antenna elements designed as rod antennas and a transmitter and/or receiver device designed as a mobile telephone; and
- 25 Figure 4 shows schematically a plan view of an antenna coupler with antenna elements designed as Yagi antennas and a transmitter and/or receiver device designed as a mobile telephone.
- 30 Mutually-corresponding components are indicated with identical reference numbers in all the drawings.

Figure 1 shows schematically a longitudinal section through an antenna coupler 2 for testing a mobile telephone 4
35 designed as the transmitter and/or receiver device, which is

held on a holding element 6 and fixed to a fastening device 8. In the exemplary embodiment according to Figure 1, the antenna coupler 2 comprises three antenna elements 91, 92, 93 designed as loop antennas 10, 12, 14.

5

Each loop antenna 10, 12, 14 provides an inner conductor 16, 18, 20 marked in Figure 1 with broken lines and, surrounding the inner conductor 18, 20, 22, an outer conductor 22, 24, 26, which shields the inner conductor 16, 18, 20. The outer
10 conductor 22, 24, 26 encloses the inner conductor 16, 18, 20 in the manner of a cylindrical casing. A dielectric, which is not illustrated in Figure 1, is preferably provided between the inner conductor 16, 18, 20 and the outer
15 conductor 22, 24, 26. The loop antenna 10, 12, 14 is formed substantially as a spatially-closed loop, wherein a minimum possible spacing distance 36, 38 is provided between the feedpoint 28, 30, visible in Figure 1 only on the loop
20 antenna 12, 14, at a feeder end of the loop and a loop end 32, 34 disposed opposite to the latter. At the loop end 32, 34 of the loop antenna 12, 14, the inner conductor 18, 20 projects outwards from the outer conductor 22, 26. The inner conductor 18, 20 is guided in the region of the feedpoint 28, 30 at the feeder end of the loop onto the outer
25 conductor in order to establish an electrical contact between the inner conductor 18, 20 and the outer conductor 24, 26.

The loop antenna 10, 12, 14 is preferably held by a holder not illustrated in Figure 1. By rotation of the loop antenna
30 10, 12, 14 about a central axis 40 disposed perpendicular to a plane formed by the loop of the loop antenna 10, which is marked in Figure 1 only for the loop antenna 10, the polarisation direction of waves radiated from the loop antenna 10, 12, 14 are variable and/or waves of different

polarisation can be detected via the loop antenna 10, 12, 14.

The loop antennas 10, 12, 14 are each coupled to an antenna base 42, which is connected via a signal line 44 to a measurement and control arrangement 46.

In order to achieve an advantageous radiation characteristic and/or reception characteristic, the circumference of the loop antennas 10, 12, 14 corresponds substantially in each case to the mean wavelength λ of the waves, which are radiated or respectively received by the loop antennas 10, 12, 14.

The electrical and magnetic components of an electrical field radiated from an antenna arrangement 50 of the mobile telephone 4 can be measured in a particularly accurate manner with an arrangement of several antenna elements with directions of maximum radiation and/or directions of maximum sensitivity orientated differently in space, which is shown in the exemplary embodiment according to Figure 1 with three antenna elements designed as loop antennas 10, 12, 14.

Moreover, in the case of the antenna elements designed as loop antennas 10, 12, 14, the coupling factor between the loop antennas 10, 12, 14 and the antenna arrangement 50, which provides, for example, several antennas for the realisation of a MIMO system in the mobile telephone, is substantially independent of the precise geometric position of the antenna arrangement 50 relative to the loop antennas 10, 12, 14, so that a spatially-accurate adjustment of the mobile telephone 4 comprising the antenna arrangement 50 on the antenna coupler 2 is not required.

Figure 2 shows a schematic plan view of the antenna coupler 2 in a further exemplary embodiment. Antenna elements designed as loop antennas 10, 12, 14, 52, 54, 56 are arranged substantially at the corners of an octahedron. By way of illustration of the octahedral arrangement of the loop antennas 10, 12, 14, 52, 54, 56, coordinate axes x, y, z of a Cartesian coordinate system are shown by dotted lines in Figure 2. The loop antennas 10, 12, 14, 52, 54, 56 are positioned on the coordinate axes x, y, z in negative and also in positive coordinate-axis direction, wherein the central axes 40 of the loop antennas 10, 12, 14, 52, 54, 56, disposed perpendicular to planes formed by loops of the loop antennas 10, 12, 14, 52, 54, 56, extend along the coordinate axes x, y, z and intersect at a coordinate origin 58, at which the mobile telephone 4 is positioned. In the exemplary embodiment shown in Figure 2, the antenna arrangement of the mobile telephone 4 is designed to be integrated within the latter and is therefore not visible in Figure 2.

Each loop antenna 10, 12, 14, 52, 54, 56 is arranged substantially at a spacing distance $\lambda/4$ relative to the mobile telephone 4. Furthermore, the loop antennas 10, 12, 14, 52, 54, 56 are guided to the antenna base 42 via connecting lines 48, which each provide the same electrical length.

Figure 3 shows a schematic plan view of the antenna coupler 2 with three antenna elements designed, in a further exemplary embodiment, as rod antennas 60, 62, 64 and one transmitter and/or receiver device designed as a mobile telephone 4. The mobile telephone 4 is held in the holding element 6 and contains an integrated antenna arrangement, which is not visible in Figure 3.

The antenna elements designed as rod antennas 60, 62, 64 are orientated with the respective transverse axis of the rod of the rod antenna 60, 62, 64 towards the mobile telephone 4 positioned at the coordinate origin 58, and the directions of maximum radiation, which are indicated with dotted lines in Figure 3, extend along the coordinate axes x, y, z of the Cartesian coordinate system. The spacing distances between the mobile telephone 4, in particular, between the antenna arrangement integrated within the latter, and each rod antenna 60, 62, 64 correspond with one another and are substantially $\lambda/4$ of the mean wavelength of the waves transmitted and/or received by the rod antenna 60, 62, 64.

The rod antennas 60, 62, 64 are guided to the antenna base 42 via connecting lines 48, which each provide the same electrical length.

Figure 4 shows a schematic plan view of the antenna coupler 2 with three antenna elements designed, in a further exemplary embodiment, as Yagi antennas 66, 68, 70 and the transmitter and/or receiver device designed as a mobile telephone 4. The mobile telephone 4 is held in the holding element 6 and contains an integrated antenna arrangement, which is not visible in Figure 4.

As in the case of the exemplary embodiment according to Figure 3, the Yagi antennas 66, 68, 70 in the exemplary embodiment according to Figure 4 are provided on coordinate axes x, y, z of the Cartesian coordinate system with the mobile telephone 4 disposed at the coordinate origin 58 and each provide the same spacing distance relative to the mobile telephone 4. In this context, the main lobes 72, 74, 76 of the Yagi antennas 66, 68, 70 each point in the direction towards the mobile telephone 4.

The Yagi antennas 66, 68, 70 are guided to the antenna base 42 via connecting lines 48, which each provide the same electrical length.

- 5 The invention is not restricted to the exemplary embodiment illustrated, in particular, not the antenna-element arrangements of the antenna coupler shown in the exemplary embodiments and the transmitter and/or receiver device designed as the mobile telephone. Under some circumstances,
- 10 the antenna elements can also be displaceable along the x-, y- or z-axis or may be rotatable about an axis perpendicular to the latter. All of the features described above and presented in the drawings can be combined with one another as required.

Claims

1. Antenna coupler for testing a transmitter and/or
5 receiver device (4), with a holding element (6) for
the transmitter and/or receiver device and with
several antenna elements (91, 92, 93), which are
arranged in such a manner that the directions of
10 maximum radiation or respectively directions of
maximum sensitivity of the antenna elements (91, 92,
93) are orientated differently relative to one another
in space, wherein an orientation of the direction of
maximum radiation and/or the direction of maximum
15 sensitivity for every antenna element (91-93) is
separately adjustable for different radiation-diagram
configurations.
2. Antenna coupler according to claim 1,
characterised in that
20 one or more of the antenna elements are orientated
with directions of maximum sensitivity and/or
directions of maximum radiation in the direction
towards the transmitter and/or receiver device.
- 25 3. Antenna coupler according to any one of claims 1 to 2,
characterised in that
the power radiated from the antenna elements (91-93)
is separately adjustable for each antenna element (91,
92, 93).
- 30 4. Antenna coupler according to any one of claims 1 to 3,
characterised in that
the antenna elements (91-93) can each be positioned at
variable distances relative to the transmitter and/or
35 receiver device (4).

5. Antenna coupler according to any one of claims 1 to 4,
characterised in that
the spacing distance between the respective antenna
5 element (91-93) and the transmitter and/or receiver
device (4) is substantially $\lambda/4$, wherein λ corresponds
to the mean wavelength of the waves received by or
respectively radiated from the antenna element.
- 10 6. Antenna coupler according to any one of claims 1 to 5,
characterised in that,
in each case, one antenna element is disposed on a
coordinate axis (x, y, z) of a coordinate system,
wherein the transmitter and/or receiver device (4) is
15 positioned at a coordinate origin (58) of the
coordinate system of the holding element (6).
7. Antenna coupler according to claim 6,
characterised in that
20 the coordinate axes (x, y, z) are orientated in an
orthogonal manner relative to one another within the
coordinate system.
8. Antenna coupler according to claim 6 or 7,
25 **characterised in that**
an antenna element (10, 52; 12, 54; 14, 56) is
provided on one of the coordinate axes (x, y, z) in
each case in the positive coordinate-axis direction
and/or in the negative coordinate-axis direction.
- 30 9. Antenna coupler according to any one of claims 1 to 8,
characterised in that
the antenna elements are arranged substantially at
corners of an octahedron, wherein the holding element

(6) positions the transmitter and/or receiver device
(4) at the centre point of the octahedron.

10. Antenna coupler according to any one of claims 1 to 9,
5 **characterised in that**
the antenna elements are designed as rod antennas (60, 62, 64) and/or as Yagi antennas (66, 68, 70) and/or as loop antennas (10, 12, 14, 52, 54, 56).
- 10 11. Antenna coupler according to claim 10,
characterised in that
a loop of the antenna element designed as a loop
antenna (10, 12, 14, 52, 54, 56) is formed
substantially in the shape of a circular ring.
- 15 12. Antenna coupler according to claim 11,
characterised in that
a circumference of the loop of the antenna element
designed as a loop antenna (10, 12, 14, 52, 54, 56)
20 corresponds to the mean wavelength λ of the waves
received or respectively radiated via the antenna
element.
13. Antenna coupler according to any one of claims 10 to
25 12,
characterised in that
at least one antenna element designed as a loop
element (10, 12, 14, 52, 54, 56) is mounted in a
rotatable manner about a central axis (40), which is
30 orientated perpendicular to a plane formed by a loop
of the loop antenna, for the adjustment of a
polarisation direction of waves radiated and/or
received via the antenna element.
- 35 14. Antenna coupler according to claim 13,

characterised in that

at least one antenna element designed as a loop antenna (10, 12, 14, 52, 54, 56) is orientated with reference to the transmitter and/or receiver device (4), positioned by the holding element (6) at the coordinate origin (58) of the coordinate system in such a manner that the central axis (40) of the loop antenna (10, 12, 14, 52, 54, 56) extends along one of the coordinate axes (x, y, z) of the coordinate system.

15. Antenna coupler according to any one of claims 1 to 14,

characterised in that

each connecting line (48) between respectively a feedpoint (28, 30) provided on each of the antenna elements and an antenna base (42) of the antenna coupler (2) provides the same electrical length.

16. Antenna coupler according to any one of claims 1 to 15,

characterised in that

the holding element (6) provides a fastening device (8) for fixing the transmitter and/or receiver device.